

Controllable quantum spin precession by Aharonov-Casher phase in conducting ring

Shun-Qing Shen

Department of Physics, The University of Hong Kong,
Pokfulam Road, Hong Kong, China

Zhi-Jian Li

Institute of Physics, Chinese Academy of Sciences, Beijing 100080, China

Zhongshui Ma

State Key Laboratory for Mesoscopic Physics and Department of Physics,
Peking University, Beijing 100871, China

(Dated: June 26, 2003)

Abstract

We investigate quantum spin transport in a structure of conducting ring, embedded in textured electric field, with two leads, and obtain an exact solution for the problem. The spin precession induced by the Aharonov-Casher phase is studied. It is shown that the spin-polarized current and its polarizability can be controlled by the electric field. As a result the polarizability is a function of the geometric phase which originates from the spin-orbital interaction in the ring.

PACS numbers: 72.25.-b, 03.65.Vf

In the recent years spin transport has attracted considerable interests because of its potential applications in semiconductor electronics and quantum computation^{1,2,3}. How to control or to modulate spin polarized current is one of important steps in the investigation of spin coherence in electronic systems. Datta and Das⁴ proposed a spin field-effect transistor (FET), in which spin polarization of charge carriers precesses when the charge carriers transmit through a 2D semiconductor channel between a ferromagnetic spin injector and a ferromagnetic spin collector. It is well known that, in semiconductor heterostructures, the spin-orbit or Rashba interaction makes spin-orbit splitting of the conduction electron energy band. Such splitting produces spin precession while the electrons go through the semiconductor channel. Experimentally, the Rashba coupling can be adjusted by an electric field such that a spin-polarized current injected from the source can be spin-dependently modulated on its way to the drain by an external gate^{5,6}. Other proposals were recently reported^{7,8,9,10,11}. However more sophisticated structures are conceivable where current modulation could arise from the spin interference.

The conventional Aharonov-Bohm (AB) effect is anticipated to modulate the charge current. It was shown that a non-uniform magnetic field may also control the polarization direction of spin current¹². The Aharonov-Casher (AC) effect¹³ originates from the spin-orbit coupling between the moving magnetic polar and the electric field. It is expected to implement the spin current modulation manifested by AC effect. Quantum coherent transport in a structure of the AC ring with two leads was discussed by many authors^{14,15,16,17,18}. It was found that the AC flux can lead to interference phenomena as the AB flux with an observable AC oscillation in the conductance. With an electric field as a parameter, it is expected to study the precession of spin current for interfering electrons manifested by the geometric properties of the ring. In the present paper we establish the connection between quantum spin polarizability and spin precession in the quantum transport in a AC ring, such that it is controllable through the external electric field by means of AC effect. We present an exact solution for the problem and focus on the spin aspect of quantum transport. Assume the ring embeds in a symmetric textured electric field with an arbitrary tilt angle as shown in Fig. 1. In the AC ring, the magnetic moment of charge carriers is influenced by the electric field through the spin-orbit interaction and there is an energy splitting between spin-up and -down electrons. The local spin orientations on the ring are determined by a spin cyclic evolution over the ring. When electrons travel through each arm of the ring,

the wave functions of electrons acquires spin-dependent Aharonov-Anandan (AA) phases¹⁹, which is the geometric part of the AC phase. Without specializing the direction of spin-polarized injection, we calculate the spin-dependent transmission coefficients analytically. In the Landauer framework of ballistic transport²⁰, it is shown that the spin polarized current and its polarizability can be controlled by the electric field via AC phase. Our result shows that the AC ring can act as a tunable spin switch by adjusting the electric field.

In the ring, the one-particle Hamiltonian for non-interacting electrons with a momentum p is given by

$$H = \frac{1}{2m} \left(p - \frac{e}{c} \mathbf{E} \right)^2; \quad (1)$$

where $\mu_B = g \mu_B$ is magnetic moment of charge carrier, μ_B the Bohr magneton, g the gyromagnetic factor, c the velocity of light in vacuum and σ_i ($i = 1, 2, 3$) the Pauli matrices. The linear term of the electric field in the Hamiltonian, $-\frac{e}{c} \mathbf{E} \cdot \mathbf{p}$; represents the spin-orbit coupling and is proportional to the electric field. In the cylindrical coordinate, the textured electric field can be written as $\mathbf{E} = E (\cos \hat{\theta} \sin \hat{\phi} \hat{r} + \sin \hat{\theta} \sin \hat{\phi} \hat{\theta} + \cos \hat{\theta} \hat{z})$. The eigen functions of given Hamiltonian (1) are given by $\psi_{n, \pm} = e^{i n \phi} \begin{pmatrix} \cos \frac{\theta}{2} \\ \sin \frac{\theta}{2} \end{pmatrix} e^{\pm i \phi}$ where

$$+ \begin{pmatrix} \cos \frac{\theta}{2} \\ \sin \frac{\theta}{2} \end{pmatrix} e^{i \phi} \sin \frac{\theta}{2} \quad (2)$$

$$\sin \frac{\theta}{2} e^{i \phi} \cos \frac{\theta}{2} \quad (3)$$

where T stands for the transpose and $\hat{\theta}$ denotes spin up and down along the direction of unit vector $\hat{\theta} = (\sin \theta \cos \phi, \sin \theta \sin \phi, \cos \theta)$: θ is defined by $\tan \theta = \frac{1}{\sqrt{1 + \beta^2}}$ with $\beta = \frac{v}{c} = \frac{E a}{\hbar c}$ and $\phi = \frac{E a}{\hbar c} \cos \theta$. The corresponding eigenvalues are $E_{n, \pm} = \frac{\hbar^2 k^2}{2m a^2} \pm n \frac{\hbar^2 a^2}{2m} \pm 2 \frac{\hbar^2 a^2}{2m} \pm 2 \frac{\hbar^2 a^2}{2m} \pm 2 \frac{\hbar^2 a^2}{2m}$; where n is an integer. $\theta = \frac{E a}{\hbar c} \cos \theta$ ($\phi = \frac{E a}{\hbar c} \sin \theta$) are the AC phases which are acquired while the two spin states evolves in the presence of the electric field³.

Assume that electrons are free electrons in two leads and have the momentum $\hbar k$: The energy is given by $E = \hbar^2 k^2 / 2m$. When an electron is transported along one arm in the clockwise direction from the input intersection A, it acquires an AC phase $\theta_{AC} = 2\pi$ at the output intersection B. And the electron acquires a phase $\theta_{AC} = 2\pi$ in the counter-clockwise direction along the other arm. Thus the total phase changes around the loop is θ_{AC} . In the ring the electric field may change the momenta of the electrons into the same energy as in

the leads in two different spin states, $k_1 = k + \frac{\pi}{2a}$ and $k_2 = k - \frac{\pi}{2a}$; where the subscripts 1;2 denote the clockwise and counter-clockwise direction, respectively. a is the radius of the ring. It is worth to point out that $k_1 - k_2 = \frac{\pi}{a}$ is independent of the momentum of incident particles. This phase difference leads two branches of wave functions to intervene at the output intersection (x ranges from 0 to a in two arms of the ring). The wave function in two arms of the ring can be written as

$$\psi_1 = c_1 e^{ikx} + d_1 e^{-ikx} e^{i\frac{\pi}{2a}x} + \frac{x}{a}; \quad (4)$$

$$\psi_2 = c_2 e^{ikx} + d_2 e^{-ikx} e^{-i\frac{\pi}{2a}x} - \frac{x}{a}; \quad (5)$$

We have assumed that a polarized electron is injected to left electrode from ferromagnetic source and travel in the x direction, and the spin state of the injected electron is $\chi_i = (\cos \theta; \sin \theta)^T e^{ikx}$. For a general considerations the wave functions in the two arms can be expressed in terms of the reflection and transmission of electrons when they transport through the ring in presence of the spin-orbital interaction. The wave functions of the electron in the left and right electrodes are

$$\psi_l = \begin{pmatrix} 0 \\ 1 \end{pmatrix} + \begin{pmatrix} r_l \\ r_r \end{pmatrix} e^{-ikx}; \quad (6)$$

$$\psi_r = \begin{pmatrix} 0 \\ 1 \end{pmatrix} + \begin{pmatrix} t_l \\ t_r \end{pmatrix} e^{ikx}; \quad (7)$$

where r and t are the spin dependent reflection and transmission coefficients, respectively.

In the linear response regime of the Landauer framework²⁰, the quantum mechanical transmission amplitude is related to two-probe conductance. The spin-dependent conductance through the ring is expressed in term of the transmission probability $T = \sum_j |t_j|^2$ as $G = (e^2/h)T$. To calculate the transmission probability through the AC ring, we use the local coordinate system for each circuit such that the x coordinate is taken along the electron current.^{17,21} The origin of each local coordinate is taken at each intersection. The choice of the coordinate origin is trivial because it only affects an extra phase factor on the transmission amplitude. Thus the Grieth's boundary condition²² gives that at each intersection the wave function is continuous and the current density is conserved. After some

tedious algebra, we obtain the transmission coefficient t :

$$t = \frac{i \sin k a \sin \frac{\gamma}{2}}{\sin^2 \frac{\gamma}{2} \cos k a - \frac{i}{2} \sin k a} \begin{matrix} z & z & i j_{k=0} \\ 0 & 1 & \end{matrix}$$

$$= \frac{i \sin k a \sin \frac{\gamma}{2}}{\sin^2 \frac{\gamma}{2} \cos k a - \frac{i}{2} \sin k a} \begin{matrix} \cos (&) \\ \sin (&) \end{matrix} \begin{matrix} A \\ \end{matrix} \quad (8)$$

where $\gamma = \cos \frac{\gamma}{2} z + \sin \frac{\gamma}{2} x$: The corresponding transmission coefficient is given by

$$T = j_z^2 + j_{\#}^2 = \frac{\sin k a \sin \frac{\gamma}{2}}{\sin^2 \frac{\gamma}{2} \cos k a - \frac{i}{2} \sin k a}^2 : \quad (9)$$

The coefficient probability was obtained for two special cases by Choi et al.¹⁷ For instance when $\gamma = \pi/2$; $c_n = d_n = 0$. In this sense only the component of \mathbf{r} remains and there is no spin flip. Our general expression shows that the transmission probability is independent of the incident spin state. Both expressions in Eqs. (8) and (9) are determined by the AC phase, the spin and kinetic state of the incident particles, and the electric field. It is noticed that there is a special case that the transmission coefficients become zero and all incident wave reflects from the ring when $\sin k a = 0$. To illustrate the main physics in the problem, we present some numerical calculation for several physical quantities. For an InAs ring with $a = 1 \text{ nm}$, the Fermi velocity v_F is approximately $3 \times 10^7 \text{ cm s}^{-1}$ and $ka \approx 60^6$. It is interesting that the transmission coefficient is only determined by the decimal part of ka . The number is tunable for k and the size of the ring. Thus in the numerical calculation we take $ka = 60.239$.

Following the Landauer formula, the spin-resolved current is given by $j = V G = V (e^2/h) T$: One of the interesting observations is that

$$j_z = j + j_{\#} = V \frac{e^2}{h} T; \quad (10)$$

which is determined by the AC phase as well as the radius of the ring. It depends on the energy of incident particles, but is independent of the initial spin state. Thus the electric field can modulate the transmission charge current through the AC phase. In Fig. 2, we plot j_z versus the magnitude E and direction angle θ of the electric field. For a specific size a and an incident momentum k , we find that the transmission charge current oscillates with the electric field for an arbitrary θ . From two explicit expressions for t and $t_{\#}$ we observe that, after going through the AC ring the particles evolves from the spin state $(\cos \gamma/2; \sin \gamma/2)$

into a new one $(\cos(\theta); \sin(\theta))$. Thus the spin current along the \hat{z} axis is given by

$$j_s = \frac{e}{h} (j_{\uparrow} - j_{\downarrow}) = V \frac{e}{h} T \cos 2(\theta) : \quad (11)$$

In Fig.3, we plot the polarized spin current versus the electric field magnitude E and direction angle θ : The transmission polarized spin current is controlled by the tilt angle θ as well as the modulation analogous to the transmission charge current.

To see this modulation clear, we introduce a dimensionless polarizability P to describe the polarization degree along the spin S_z axis of the transmitted current through the AC ring, which is defined by

$$P = \frac{j_{\uparrow} - j_{\downarrow}}{j_{\uparrow} + j_{\downarrow}} = \cos 2(\theta) : \quad (12)$$

P is independent of the mass m and momentum $\hbar k$ of the incident charge carriers for a large ka . This is an important advantage for the device application. P is similar to the spin injection rate defined in ferromagnetic/semiconductor/ferromagnetic heterostructures²³, and can be measured experimentally. Thus P is simply determined by θ only. For the incident state ψ_i , the spin polarized tilt angle is 2θ and the polarizability $P = P_0 \cos 2\theta$. We see that the transmitted polarizability is modulated by θ . In the case the transmitted current is just modulated by the AC phase, and is spin-independent. We plot the spin polarizability P versus E and θ in Fig.4 for the case $\phi = 0$. From the definition of P it is equal to ± 1 when the electric field E is very large. It is obvious that the spin polarizability approaches to a constant with increasing of electric field strength for a certain angle. This mechanism is different from Datta and Das's proposal, where is the phase difference of two spin states determines spin precession. In the present paper, the role of phase difference $k_1 - k_2 - a = \frac{\pi}{2}$ of two spin eigenstates between the source and drain just controls the transmission coefficients and does not affect the spin polarizability.

This theory can be applied to a simple device to control the polarized spin current following Datta and Das's proposal. The semiconductor heterostructure is replaced by a conducting ring to connect the source and drain. The gate voltage is applied to control the electric field exerting on the ring as shown in Fig. 1(b). In this case $E = E \hat{z}$, i.e., $\theta = \pi/2$. Assume a spin-up electron ($\sigma = 0$) is injected from ferromagnetic source and passes through the AC ring. The tilt angle is simply written as $\theta = \arctan(E a / \hbar c)$: The polarization direction of

the transmission current can be tuned by the electric field explicitly, i.e.,

$$P = \frac{1}{1 + (Ea/\hbar c)^2} \quad (13)$$

For a large electric field $E \gg \hbar c/a$; $\alpha \approx 2$ and $P \approx 1$: The polarization direction of incident electron with spin up can be flipped into spin down. One of the advantages of the device is either the transmission probability or polarizability of the transmitted current is tunable by the electric field. A similar device was proposed by Nitta et al.¹⁸. Except for the electric field, an magnetic field is also applied to split energy levels in the ring. According to the present theory the electron spin can evolve a tilt angle even in absence of an external magnetic field.

In summary, we have obtained an exact solution for the quantum transport in a AC ring with two leads and shown that the quantum spin transport is modulated by the electric field. The AC phase may control the transmission current, and the spin of electron evolves an tilt angle after passing through the ring. The angle is determined by the electric field and the size of the ring, but independent of the energy of incident particles. Following Datta and Das, we propose that the device of AC ring with two leads can serve as a spin transistor. The spin-resolved current can be well controlled by the voltage gate.

This work was supported by a grant from Research Grant Council of Hong Kong, a CRCG grant of The University of Hong Kong, and the NNSFC-China. One of the authors (SQS) acknowledge Max Planck Institute for Physics of Complex Systems at Dresden, Germany for its support and hospitality, where part of the work was done.

¹ G.A.Prinz, Science 282, 1660 (1998); Physics Today 48 (4), 58 (1995).

² J.M.Kikkawa, Physics Today 52 (6), 33 (1999).

³ S.A.Wolf, D.D.Awschalom, R.A.Buhrmann, J.M.Daughton, S.von Molnar, M.L.Roukes, A.Y.Chtchelkanova, and D.M.Treger, Science 294, 1488 (2001).

⁴ S.Datta and B.Das, Appl.Phys.Lett. 56, 665 (1990).

⁵ J.Nitta, T.Akazaki, H.Takayanagi, and T.Enoki, Phys.Rev.Lett. 78, 1335 (1997).

⁶ D.Grundler, Phys.Rev.Lett. 84, 6074 (2000).

⁷ J.C.Egues, G.Burkard, and D.Loss, Appl.Phys.Lett. 82, 2658 (2003); Phys.Rev.Lett. 89, 176401 (2002).

FIG. 1: (a) A symmetric textured electric field exerted on the AC ring. The arrows indicates the incident, transmitted and reflected current flows. (b) Spin transistor geometry: a AC ring with two leads connecting to ferromagnetic source and drain is sandwiched between two electrodes.

- ⁸ J. Schliemann, J. C. Egues, and D. Loss, Phys. Rev. Lett. 90, 146801 (2003).
- ⁹ X. F. Wang, P. Vasilopoulos, and F. M. Peeters, Appl. Phys. Lett. 80, 1400 (2002); Phys. Rev. B 65, 165217 (2002).
- ¹⁰ A. A. Kiseley and K. W. Kim, Appl. Phys. Lett. 78, 775 (2001).
- ¹¹ A. G. M al'shukov, V. V. Shlyapin, and K. A. Chao, Phys. Rev. B 66, 081311 (2002).
- ¹² D. Frustaglia, M. Henschel, and K. Richter, Phys. Rev. Lett. 87, 256602 (2001).
- ¹³ Y. Aharonov and A. Casher, Phys. Rev. Lett. 53, 319 (1984).
- ¹⁴ H. Mathur and A. D. Stone, Phys. Rev. Lett. 68, 2964 (1992).
- ¹⁵ A. G. Aronov and Y. B. Lyanda-Geller, Phys. Rev. Lett. 70, 343 (1993).
- ¹⁶ Y. S. Yi, T. Z. Qian, and Z. B. Su, Phys. Rev. B, 55, 10631 (1997).
- ¹⁷ T. Choi, S. Y. Cho, C. M. Ryu, and C. K. Kim, Phys. Rev. B 56, 4825 (1997).
- ¹⁸ J. Nitta, F. E. Meier, and H. Takayanagi, Appl. Phys. Lett. 75, 695 (1999).
- ¹⁹ Y. Aharonov and J. Anandan, Phys. Rev. Lett. 58, 1593 (1987).
- ²⁰ R. Landauer, IBM J. Res. Dev. 1, 233 (1957); Phils. Mag. 21, 863 (1970).
- ²¹ J. B. Xia, Phys. Rev. B 45, 3593 (1992).
- ²² S. Gri th, Trans. Faraday Soc. 49, 345 (1953); 49, 650 (1953).
- ²³ M. Johnson, Phys. Rev. B 58, 9635 (1998); M. Johnson and R. H. Silsbee, Phys. Rev. B 37, 5326 (1988).

FIG .2: The charge current j_e with unit $V e^2/h$ varies with respect to the electric field E with unit $\sim \text{eV}/\text{\AA}$ and its direction tilt angle with unit $^\circ$.

FIG .3: The polarized spin current j_s with unit $V e/h$ varies with respect to the electric field E with unit $\sim \text{eV}/\text{\AA}$ and its direction tilt angle with unit $^\circ$.

FIG . 4: The spin polarizability of current P with respect to the electric field E with unit $\sim c/a$ and its direction tilt angle with unit $^\circ$.







