

Modulation of dephasing due to a spin-boson environment?

E. Paladino^a, M. Sassetti^b and G. Falci^a

^a Dipartimento di Metodologie Fisiche e Chimiche (DMFCI), Università di Catania, viale A. Doria 6, 95125 Catania, Italy & MATIS-Istituto Nazionale per la Fisica della Materia, Catania, Italy

^b Dipartimento di Fisica, INFN-Lamia, Università di Genova, Via Dodecaneso 33, 16146 Genova, Italy

Abstract

We study the reduced dynamics of a spin (qubit) coupled to a spin-boson environment in the case of pure dephasing. We derive formal exact expressions which can be cast in terms of exact integro-differential master equations. We present results for a SB environment with ohmic dissipation at finite temperatures. For the special value of the ohmic damping strength $K = 1/2$ the reduced dynamics is found in analytic form. For $K \neq 1/2$ we discuss the possibility of modulating the effect of the SB environment on the qubit. In particular we study the effect of the crossover to a slow environment dynamics, which may be triggered by changing both the temperature and the system-environment coupling.

Key words: Decoherence, quantum statistical methods, quantum computation
PACS: 03.65.Yz, 03.67.Lx

1 Introduction

The possibility of controlling the dynamics of a complex quantum system would open a wide scenario for both fundamental and applied physics. New physical properties emerging at the nanoscale may yield new paradigms for nanoelectronics, an example being quantum information processing [1]. The basic operations of a quantum logic device can be described in its computational space defined by a set of degrees of freedom which can be prepared

? The authors are pleased to dedicate this paper to Uli Weiss 60th birthday
Email address: epaladino@dmfci.unict.it (E. Paladino).

(write) and measured (read) and of course evolve coherently. However the Hilbert space of the device is much larger than the computational space, and effects of the additional degrees of freedom may be relevant for the reduced dynamics we aim to control [2,3]. These environmental degrees of freedom may be "internal" to the device, which is a many-body object, or "external", belonging to the read/write circuitry or to auxiliary devices (buses or other idle or working qubits). They determine loss of coherence, which is ultimately due to the entanglement between system and environment [2].

Much of the effort in the analysis of decoherence in quantum logic devices has been focused on model environments made of many weakly coupled harmonic oscillators [2,4]. The key feature of these linear models is that the effects on the reduced dynamics of the system can be described in terms of simple statistical information on the environment, spectral densities or power spectra, even if a detailed knowledge of its microscopic structure is not known [5-7]. However a slightly more detailed knowledge of the environment dynamics is needed in certain situations, for instance if the environment has memory on the time scale of the system dynamics [8,9].

Bistable impurities located close to a solid state device which produce 1/f noise [10] are a physical realization of an environment with memory. They have been recognized as the major source of decoherence in recent experiments [11] demonstrating quantum coherent dynamics in superconducting devices. Such an environment has been modeled in Ref. [9], with a set of Fano impurities [12] which randomly polarize the device. A peculiar effect of this environment, related to its non linear nature, is that the reduced qubit dynamics shows various qualitatively different regimes depending on the switching rate of the impurities. In particular dephasing due to slow impurities is not described by a single rate and memory effects of the environment enter the qubit dynamics.

The main goal of this work is to discuss a situation where the reduced dynamics of the system is able to probe different regimes of the environment dynamics. To this end we introduce a model which exhibits tunable crossover effects. We take as the environment an impurity described by a spin-boson (SB) model [5,6]. The Hamiltonian is introduced in section 2, where we also discuss applications to physical problems. In section 3 the formal solution for the off-diagonal element $\rho_{01}(t)$ of the RDM is found, in the limit of pure dephasing and ohmic damping in the scaling regime. In section 4 a generalized master equation for $\rho_{01}(t)$ is derived and the analytic structure of the kernels is exploited in section 5 to study the character of the behavior of $\rho_{01}(t)$. Finally in section 6 we sketch a phase diagram for this problem.

2 Model

We study the following Hamiltonian ($\hbar = 1$)

$$H = \frac{\sigma_z}{2} + \frac{E_J}{2} \sigma_x + \frac{V}{2} \sigma_z X + H_{SB}; \quad (1)$$

$$H_{SB} = \frac{S_B}{2} \sigma_z + \frac{1}{2} X^2 + \frac{1}{2} (a^\dagger + a) X; \quad X = \frac{1}{\sqrt{2}} (a^\dagger + a);$$

It describes two spins (\uparrow and \downarrow) coupled to each other by the interaction V . The spin \uparrow is also coupled to a collective coordinate X of a set of otherwise noninteracting harmonic oscillators (operators a^\dagger and a). The Hamiltonian H_{SB} represents a spin-boson model [5,6], which describes a two state system with tunneling amplitude and bias S_B coupled to a set of harmonic oscillators. This set of bosons is characterized by the spectral density of the operator X , given by $G(\omega) = \frac{1}{2} \sum_j \omega_j^2 \delta(\omega - \omega_j)$. The Hamiltonian Eq.(1) is very rich and may model many different physical problems. In this work we will regard \uparrow as describing a qubit coupled with an environment consisting of a bistable impurity (\downarrow) described by the SB model, H_{SB} . We are primarily interested in the reduced dynamics of the qubit, resulting from tracing out all the environmental degrees of freedom, i.e. the harmonic modes and the spin \downarrow . Physically \downarrow may represent a Josephson quantum logic device where external voltage gates and magnetic fields are used to tune the effective charging energy and Josephson coupling E_J [4,13]. The environment may be a charge close to the device undergoing phonon-assisted tunneling between two positions. We will consider an ohmic spectral density $G(\omega)$ [5], i.e. we choose a set of free bosons such that the power spectrum of the collective coordinate X is given by

$$S_X(\omega) = \int_{-\infty}^{\infty} dt \frac{1}{2} \langle X(t)X(0) + X(0)X(t) \rangle e^{i\omega t} =$$

$$= G(\omega) \coth \frac{\hbar\omega}{2} = \frac{2}{\pi} K \int_0^{\omega_c} d\omega' \frac{\omega'}{\omega^2 - \omega'^2} \coth \frac{\hbar\omega'}{2}; \quad (2)$$

where ω_c represents the high frequency cut-off of the harmonic modes. The case of ohmic spectral density is interesting because the SB model has a rich phase diagram resulting in an environment where memory effects may be tuned by the temperature T . We will present results for $K \gg 1$ focusing on nonzero temperatures, $T > T_r = (\hbar\omega_c)^{K/(K-1)}$, where T_r is the renormalized tunneling amplitude in H_{SB} [5]. Physically this regime describes a SB impurity active in producing decoherence for the qubit \uparrow . From a technical point of view this regime requires some care. For instance the dephasing rate for $\hbar\omega_c$ using the standard secular master equation [8,5] in the couplings

(for $\nu_{SB} = \nu = 0$) reads $S_X(\omega_r) = 4$ [5]. For $T > T_r$ it reduces to

$$\chi(T) = K k_B T; \quad (3)$$

this result being valid only if $\chi(T) > T_r$ [8,5]. Thus for large enough temperatures an analysis which goes beyond the standard secular master equation is needed [16,5].

We mention finally other physical problems where the model we study may be relevant. First of all the Hamiltonian Eq.(1) may describe a system of two-qubits (\sim and \sim) subject to gaussian noise, the ohmic case describing the effect of a resistive circuitry. The low temperature regime, which may describe a working two-qubit gate, has been investigated using the standard secular master equation [14]. Instead for temperatures $T > T_r$ our model may describe a working qubit (\sim) coupled with a idle qubit (\sim) not perfectly switched off. Finally the spin may represent a measuring device [15] for the mesoscopic system described by H_{SB} . This picture is an alternative framework for our work, namely the reduced dynamics of \sim provides the result of the measurement on a SB system. If the coupling ν is weak and the dynamics of the SB is fast enough only the power spectrum of the coupling operator ν_z

$$S(\omega) = \int_{-\infty}^{\infty} dt \frac{\nu^2}{2} (\langle \sigma_z(t) \sigma_z(0) \rangle + \langle \sigma_z(0) \sigma_z(t) \rangle i \hbar \omega \langle \sigma_z^2 \rangle) e^{i\omega t} \quad (4)$$

enters the dynamics of \sim , whereas if the SB has a slow dynamics the spin \sim is able to detect also details of the dynamics of \sim which go beyond $S(\omega)$.

3 Formal solution for the reduced density matrix

We consider the pure dephasing regime $E_J = 0$ where $[H; \sigma_z] = 0$, so no relaxation process takes place and dephasing is due to fluctuations of the energy difference of system, i.e. σ_z , eigenstates. Hence the diagonal elements of the reduced density matrix of the qubit in the σ_z basis (populations) are constant, whereas off-diagonal elements (coherences) decay. All the information on the reduced dynamics is included in the coherences. In this section we derive an exact formal expression for the coherence $\rho_{01}(t) = \langle \sigma_0 | \rho(t) | \sigma_1 \rangle$.

We choose a factorized initial density matrix $W(0) = \rho(0) \otimes w_{SB}(0)$, with the spin-boson environment in the general state $w_{SB}(0)$. Product initial states are relevant in quantum computing, one of the main requirements being the possibility to prepare the qubit in well defined initial states. The coherence

$\rho_1(t)$ is thus related to the following correlation function involving the spin-boson variables

$$\rho_1(t) = \rho_1(0) e^{i t T_{SB}} e^{i H_B} e^{i t w_{SB}} \rho_1(0) e^{i H_B} e^{i t T_{SB}} \rho_1(0) e^{i t C_+}(t) \quad (5)$$

where $H_B = H_{SB} - \frac{V}{2} z$. We evaluate the correlator $C_+(t)$ using a functional integral approach. In the derivation we consider a dimensionless continuous "coordinate" q , and specify later to the spin states (\sim). The trace over the environmental degrees of freedom in the coordinate basis $|q\rangle \langle q|$ reads

$$C_+(t) = \int_{-\infty}^{\infty} dq_f \int_{-\infty}^{\infty} dq_i \int_{-\infty}^{\infty} dx_f dx_i dx_i^0 K(q_f; x_f; t; q_i; x_i; 0) h(q_i; x_i) w_{SB}(0) \langle q_i^0; x_i^0 | K_+(q_f; x_f; t; q_i^0; x_i^0; 0) \rangle \quad (6)$$

where we have introduced the compact notation

$$x = \int_{-\infty}^{\infty} dx f(x) g; \quad \int_{-\infty}^{\infty} dx \quad \int_{-\infty}^{\infty} dx : \quad (7)$$

The Feynman propagators K are associated to the two Hamiltonians H and can be expressed as a real-time path integral

$$K(q_f; x_f; t; q_i; x_i; 0) = \int_{-\infty}^{\infty} Dq D^h x \exp i(S_B[q] + S_B[x] + S_{SB}[q; x]) \quad ;$$

with the constraints $q(0) = q_i$, $q(t) = q_f$ and $x(0) = x_i$, $x(t) = x_f$. $S_B[x]$ and $S_{SB}[q; x]$ are the actions corresponding to the free boson and the spin-boson interaction terms in (1) respectively. We now specify to an initial non equilibrium state of the factorized form $w_{SB}(0) = w(0) w$, where the harmonic oscillators start from the thermal equilibrium state w , and $w(0)$ is a general density matrix for the system of coordinate q . Then $C_+(t)$ reads

$$C_+(t) = \int_{-\infty}^{\infty} dq_f \int_{-\infty}^{\infty} dq_i \int_{-\infty}^{\infty} dx_f dx_i dx_i^0 h(q_i; x_i) w_{SB}(0) \langle q_i^0; x_i^0 | J(q_f; q_f; t; q_i; q_i^0; 0) \rangle \quad (8)$$

$$J(q_f; q_f; t; q_i; q_i^0; 0) = \int_{-\infty}^{\infty} Dq D^h q^0 \exp i(S_B[q] - S_+(q^0)) F_{FV}[q; q^0] \quad (9)$$

with the path integration constraints $q(0) = q_i$, $q(t) = q_f$, $q^0(0) = q_i^0$, $q^0(t) = q_f$. The influence of the harmonic modes enters the generalized "propagating function" $J(q_f; q_f; t; q_i; q_i^0; 0)$ via the Feynman-Vernon influence functional

$$F_{FV}[q; q^0] = \exp \int_0^t dt^0 \int_0^{t^0} dt^0 [-\langle t^0 | Q^0(t^0 - t^0) - \langle t^0 | + i \langle t^0 | Q^0(t^0 - t^0) - \langle t^0 |] \quad ; \quad (10)$$

where we have introduced the linear combinations

$$q(t) = [q(t) + q^0(t)]/2; \quad q(t) = [q(t) - q^0(t)]/2;$$

describing respectively propagation along the diagonal of the density matrix and off-diagonal excursions. For a spin these paths are piecewise constant, the time intervals in which the spin is in a diagonal state $\sigma = \pm 1$ are called sojums, while the time intervals spent in an off-diagonal state $\sigma = \pm 1$ are referred to as blips. Depending on the initial condition for the spin, the initial state can be either a sojum or a blip. We now choose for the spin a diagonal initial state in the $|z\rangle$ basis with $\langle \sigma | \hat{I}_z | \sigma \rangle = \frac{1}{2} \hat{I}_z + \frac{1}{2} p(0) \sigma$, where $p(0)$ denotes the initial population difference between the $|z\rangle$ eigenstates. Then all paths that contribute to $C_{\pm}(t)$ in Eq.(8) start out and end up in a sojum state, $q(0) = q^0(0) = q_{\pm} \neq 0$, $q(t) = q^0(t) = q_{\pm} \neq 0$. Thus a general path is characterized by $2m$ transitions at the intermediate times t_j ($t_j = 1; 2; \dots; 2m$) and it is parametrized by

$$\begin{aligned} {}^{(2m)}(t^0) &= \sum_{j=1}^{X^n} [(t^0, t_{j-1}) \quad (t^0, t_j)]; \\ {}^{(2m)}(t^0) &= \sum_{j=0}^{X^n} [(t^0, t_j) \quad (t^0, t_{j+1})]; \end{aligned} \quad (11)$$

where $t_0 = 0$ and $t_{2m+1} = t$. Inserting the path (11) into S_{\pm} in Eq.(9) we get

$$\exp i(S_{\pm}[q] - S_{\pm}[q^0]) = \exp i \sum_{j=0}^{2m} B_m \exp i v_j \sum_{j=0}^{X^n} s_j \quad (12)$$

where $B_m = \exp i \sum_{j=1}^m p_j$ is the usual bias factor which depends only on the blip lengths s_j . Notice that due to the two propagators K_{\pm} which occur in Eq.(6), we get dynamic contributions which depend on the sojum lengths s_j in the spin actions (last term in Eq.(12)).

Substituting the paths (11) into Eq.(10), the influence functional reduces to

$$F_m = G_m H_m; \quad (13)$$

The factor G_m contains all the inter- and intra-blip-interactions,

$$\begin{aligned} G_m &= \exp [\sum_{j=1}^m Q_{2j,2j-1}^0 + \sum_{j=2}^m \sum_{k=1}^{j-1} Q_{2j,2k-1}^0]; \\ s_{jk} &= Q_{2j,2k-1}^0 + Q_{2j-1,2k}^0 - Q_{2j,2k}^0 - Q_{2j-1,2k-1}^0; \end{aligned}$$

the sojourn-blip interactions are captured by the phase factor H_m given by

$$H_m = \exp \left[i \sum_{j=1}^m \sum_{k=0}^{j-1} X_{jk} \right]$$

$$X_{jk} = Q_{2j,2k+1}^{(0)} + Q_{2j-1,2k}^{(0)} - Q_{2j,2k}^{(0)} - Q_{2j-1,2k+1}^{(0)} :$$

The kernels $Q^{(0)}$ and $Q^{(0)}$ are the real and imaginary parts of the second integral of the bath correlation function

$$Q(t) = \int_0^t d! \frac{G(!)^n}{!^2} \coth \frac{!}{2} \left[1 - \cos(!t) + i \sin(!t) \right] :$$

and we have used the notation $Q_{h,i} = Q(t_h - t_i)$.

We proceed considering the important case of an ohmic bath Eq. (2), where the correlator $Q(t)$ in the scaling limit $!_c t \rightarrow 1$, reads

$$Q(t) = 2K \ln \frac{!_c}{\sinh \frac{!}{2}} + i K \operatorname{sgn}(t) : \quad (14)$$

Using the above scaling form each sojourn interacts only with the subsequent blip, so that H_m simplifies to

$$H_m = \exp \left[i K \sum_{k=0}^{m-1} X_{k,k+1} \right] : \quad (15)$$

Taking into account this features, the sum over histories of paths of Eq.(9) is represented by

- (i) the sum over all possible numbers of steps,
- (ii) the time-ordered integrations over the corresponding ip times $ft_j g$,
- (iii) the sum over all possible arrangements of blips $f_j = \pm 1g$ and sojourns $f_j = \pm 1g$.

The correlator $C_+(t)$ becomes

$$C_+(t) = \sum_w e^{i v t} + \sum_w \sum_0^X \frac{!^2}{2} \int_0^{2m Z t} D_{2m} f t_j g \sum_{f_j g}^X G_m B_m \sum_{f_j g^0}^X H_m \exp \left[i \sum_{j=0}^m X_{j,j+1} \right] : \quad (16)$$

where $w = \pm 1$ and $j = 0, 1, \dots, m$ and $\sum_{f_j g^0}^P$ denotes the sum over all paths j subject to the constraints $f_0 = \pm 1$, $f_m = \pm 1$. The first term in Eq.(16) comes from the

path without any transition between the initial and final sojourns, and occurs for $v = 0$. The sum over $f_j g^0$ can be easily performed using the scaling form (14) for H_m , this leads to

$$\sum_{f_j g^0} H_m \exp \left(i v \sum_{j=0}^n s_j \right) = e^{i K - 1} e^{i v (s_0 + s_m)} 2^{m-1} D_m \quad (17)$$

where $D_m = \sum_{j=2}^m \cos(K_j + v s_{j-1})$. Whereas for $v = 0$ the sum over the intermediate sojourns provides a contribution which only depends on the blip states j , because of the coupling the sum over j gives also a dynamic term dependent on the sojourn lengths s_j . Thus we finally get

$$C_+(t) = \sum_w e^{i v t} + \tilde{A}(t) + i \tilde{B}(t) \quad (18)$$

$$\tilde{A}(t) = \frac{1}{2} \sum_w \sum_0^X {}^0A(\cdot; \cdot; t) \quad (19)$$

$$\tilde{B}(t) = \frac{1}{2} \sum_w \sum_0^X {}^0B(\cdot; \cdot; t) \quad (20)$$

where

$$A(\cdot; \cdot; t) = \sum_{m=1}^X \frac{2^{m-1}}{2} \sum_0^t D_{2m} f t_j g e^{i v (s_0 + s_m)} \sum_{f_j g}^X G_m B_m D_m \cos(K) \quad (21)$$

$$B(\cdot; \cdot; t) = \sum_{m=1}^X \frac{2^{m-1}}{2} \sum_0^t D_{2m} f t_j g e^{i v (s_0 + s_m)} \sum_{f_j g}^X {}_1G_m B_m D_m \sin(K) : (22)$$

Eq.(5) with Eqs.(18) – (22) is the exact formal expression for the coherence $\rho_{01}(t)$, valid for Ohmic damping in the scaling regime.

4 Generalized Master Equation

For quantum dissipative systems it is generally useful to formulate the dynamics of the open system by means of appropriate master equations for the reduced density matrix. For the spin-boson problem generalized master equations relating the averages of the spin components have been obtained in Refs. [5,16]. In this section we show that the series expressions for $A(\cdot; \cdot; t)$ and $B(\cdot; \cdot; t)$ given in Eqs.(21,22) can also be cast into the form of exact integro-differential equations.

To this end we have to find the kernels, i.e. the irreducible components in the formal expressions (21,22). Irreducibility of a kernel means that it cannot be cut into uncorrelated pieces at an intermediate sojourn without removing correlations due to the harmonic bath, across this sojourn. Following the lines of Refs.[5,16] we define irreducible in uence functions subtracting from the inter- and intra-blip interaction factors G_m all the reducible components

$$\tilde{G}_n = G_n - \sum_{j=2}^n (1)^j \sum_{m_1 \dots m_j} G_{m_1} \dots G_{m_j} \quad ;$$

where the inner sum is over all positive integers m_j . By inspection of (21,22) we find that the irreducible kernels are

$$K_1(t, t^0) = K_1(t, t^0) + \sum_{n=2}^{\infty} \frac{(-1)^n}{2} \int_{t^0}^t dt_{2n-1} \dots \int_{t^0}^t dt_2 G_n B_n D_n \quad (23)$$

$$K_2(t, t^0) = K_2(t, t^0) + \sum_{n=2}^{\infty} \frac{(-1)^n}{2} \int_{t^0}^t dt_{2n-1} \dots \int_{t^0}^t dt_2 G_n B_n D_n \quad ; \quad (24)$$

where the lowest order contributions do not depend on the coupling v and coincide with the lowest order kernels entering the spin dynamics in the uncoupled case [5,16]

$$K_1(t, t^0) = \cos(K) G_1(t, t^0) \cos[S_B(t, t^0)] \quad (25)$$

$$K_2(t, t^0) = \sin(K) G_1(t, t^0) \sin[S_B(t, t^0)] \quad ; \quad (26)$$

With the above the generalized master equations for $A(\cdot; t)$ and $B(\cdot; t)$ read

$$\begin{aligned} \frac{d}{dt} A = & i \omega_A \int_{t^0}^t dt^0 e^{i \omega_A t^0} + A \int_{t^0}^t dt^0 [K_1(t, t^0) - K_2(t, t^0)] A(t^0) \\ & + i v \int_{t^0}^t dt^0 e^{i \omega_A(t-t^0)} \int_{t^0}^t dt^0 [K_1(t^0, t^0) - K_2(t^0, t^0)] B(t^0) \end{aligned} \quad (27)$$

$$\begin{aligned} \frac{d}{dt} B = & i \omega_B \int_{t^0}^t dt^0 [K_1(t, t^0) B(t^0) - K_2(t, t^0) e^{i \omega_B t^0}] \\ & + i v \int_{t^0}^t dt^0 e^{i \omega_B(t-t^0)} \int_{t^0}^t dt^0 [K_1(t^0, t^0) - K_2(t^0, t^0)] B(t^0) \quad ; \end{aligned} \quad (28)$$

In the absence of coupling, $v = 0$, $A(\omega; 0; t)$ and $B(\omega; 0; t)$ are simply related to the components of the average $\langle h_z \rangle_t$ symmetric and antisymmetric under bias inversion $s_B \rightarrow -s_B$, $\langle h_z \rangle_t = P_s(t) + P_a(t)$, via $A_0(\omega; 0; t) = P_s(t) - 1$ and $B_0(\omega; 0; t) = iP_a(t)$. In this limit Eqs.(27,28), reduce to the master equations satisfied by $P_s(t)$ and $P_a(t)$ [5,16].

Being of convolutive forms the integro-differential equations Eqs.(27,28) are conveniently solved in Laplace space. Performing the sums in Eqs.(19,20) the Laplace transform of the correlator $C_+(\omega, t)$ reads

$$\mathcal{C}_+(\omega) = \frac{1}{D(\omega)} [1 + K_1(\omega) - ivp(0)] \quad (29)$$

$$D(\omega) = \omega^2 + v^2 + K_1(\omega) + ivK_2(\omega); \quad (30)$$

where $K_1(\omega)$, $K_2(\omega)$ are the Laplace transforms of the kernels (23,24) and $p(0)$ comes from the initial condition chosen for the spin \sim .

5 Reduced dynamics at finite temperatures

Solving the pole equation (30) represents a formidable task, so in the following we shall focus on special damping and temperature regimes which are particularly relevant for quantum computing. We shall analyze dephasing at finite temperatures at two special coupling conditions: weak damping $K = 1$ and $K = 1=2$. In the second case the spin-boson model can be mapped onto a Fano Anderson model [12] which is suitable to study dephasing due to bistable actuators producing 1=f noise [9].

We shall adopt an approximate treatment widely used in the spin-boson literature [5,6], the noninteracting-blip approximation (NIBA). In the NIBA, the blip-blip interactions X_{jk} are neglected, and also the sojurn-blip interactions $X_{j,k}$ are disregarded except those of neighbors, $k = j \pm 1$, and they are approximated by $X_{j,j \pm 1} = Q^0(\omega_j)$. Thus the influence functions (13) factorize into the individual blip influence factors, and the irreducible influence functions (23) vanish for $n > 1$. For Ohmic damping in the scaling regime, each blip interacts with the subsequent sojurn only (see Eq.(15)), thus the only approximation involved in the NIBA is the neglect of the blip-blip interactions. This approximation is justified in the regimes of our interest, see ref. [5].

Within the NIBA the series expression for the irreducible kernels (23,24) reduce to the lowest order contributions (25,26). Evaluation of Eqs.(27,28), with these kernels give the reduced dynamics of the qubit in the NIBA. To make things simpler we shall consider the unbiased case $s_B = 0$.

5.1 The case $K = 1=2$

For $K = 1=2$ the Laplace transform of the kernel $K_1(t, t')$ takes the form

$$\lim_{K \rightarrow 1=2} \int_0^\infty dt e^{-st} K_1(t, t') = \frac{2}{2!} \frac{1}{c} F; \quad (30)$$

the zero coming from $\cos(K)$ for $K \rightarrow 1=2$ being compensated from the short distance singularity of the intra-blip interaction $\lim_{t \rightarrow 0} e^{-Q^0(t)} \sim (t_c t)^{2K}$. The pole equation (30) is readily solved and $C_+(t)$ reads

$$C_+(t) = A e^{\frac{1}{2}(1 - \gamma) F t} + (1 - A) e^{\frac{1}{2}(1 + \gamma) F t}; \quad (31)$$

This form is suitable for illustrative purposes since γ and A have a very simple expression [17]

$$\gamma = \frac{2v}{F} \frac{1}{2} \frac{1}{F}; \quad A = \frac{1}{2} \left(1 + i \frac{2v}{F} p(0) \right); \quad (32)$$

The behavior of $C_+(t)$ has been analyzed in Ref. [9] where two qualitatively different regimes for the problem were identified.

Fast environment { If $2v = F \gg 1$ only one of the exponentials appearing in Eq. (31) dominates the long-time behavior and $C_+(t)$ shows a single rate, given by $\frac{1}{2}(1 - \gamma) F \approx \frac{1}{2} F$, the standard Golden Rule result. The decay of $C_+(t)$ at all times, described by $\langle t \rangle = -\ln C_+(t) / C_+(t)$, is well approximated by simulating the SB model with suitable set of harmonic oscillators reproducing the power spectrum $S(\omega)$. In this case the decay is described by $\langle t \rangle \approx \tau_{osc}(t)$ where [3,5]

$$\tau_{osc}(t) = \int_0^\infty d\omega S(\omega) \frac{1 - \cos \omega t}{\omega^2}; \quad (33)$$

Here the power spectrum Eq.(4) is a Lorentzian $S(\omega) = 2v^2 / F (\frac{2}{F} + \omega^2)$, due to the pure relaxation behavior of $\langle z_i \rangle$ for $v = 0$ [5]. Thus in this regime the spin \sim sees the SB environment as an effective set of harmonic oscillators, and no detailed information or memory effects of the environment enters $C_+(t)$.

Slow environment { If $2v = F \ll 1$, $C_+(t)$ is determined by both the exponential terms in Eq. (31). Deviations from the weak coupling result $\tau_{osc}(t)$ are observed, in particular the short times behavior $\tau \sim F^{-1}$ shows memory effects whereas for long times the coupling v does not enter the decay rates,

given by $\gamma_1 = \gamma_F = 2$, but determines the frequency shifts, which reduce to γ_F (see Fig. 5.1 a).




Fig. 1. (a) The real part (solid lines) and the imaginary part (dots) of the rates entering Eq. (31) are plotted for finite temperature $k_B T_{SB} > 0$. (b) The full expression for $\Gamma(t)$ for various $2v = \gamma_F$: deviations from the weak coupling result $\Gamma_{osc}(t)$ (dashed line) are apparent for $\gamma_F < 2v$. Here $p = \tanh[\gamma_{SB} = (2k_B T)] = 0.08$.

We mention that for $K = 1/2$ the same structure Eq. (31) is also found in more general situations, $\gamma_{SB}; E_J \neq 0$ [9,17]. Formulas for A and α are more complicated, for instance Re and Im are both non vanishing in the entire $2v = \gamma_F$ range and a third regime $2v = \gamma_F > 1$ appears (see Fig. 5.1). However the analysis using the expressions (32) remains still valid, and in the following we will identify the different regimes for $K < 1$ from a similar analysis of the poles of $\mathcal{C}_+^{(b)}(\omega)$.

5.2 Weak ohmic damping $K < 1$ and finite temperatures

For weak ohmic damping, $K < 1$ and temperatures $k_B T_b \ll k_B T_c$, where $k_B T_b = \frac{\gamma_F^2}{2} + v^2$, the characteristic fluctuations of the harmonic oscillators in H_{SB} have no memory and $Q(t)$ assumes the Markov form

$$Q(t) = 2K \frac{\gamma_F}{2} + \ln \frac{\gamma_F}{2} + iK \text{sgn}(t) :$$

Using this latter expression the interblip interactions cancel out exactly, thus justifying the NIBA.

In the absence of bias, $\gamma_{SB} = 0$ only the kernel $K_1(\omega)$ is non vanishing, and in the Markov limit it reads $K_1(\omega) = \frac{\gamma_F}{2} [1 + 2\beta(T)]$, where $\beta(T)$ is given by Eq. (3) and we have introduced the temperature dependent tunneling term $T = \gamma_F (2k_B T - \gamma_F)^K$. The correlator $\mathcal{C}_+^{(b)}(\omega)$ is readily found as

$$\begin{aligned} \chi_+(t) &= \frac{[1 + 2(T)] [1 - i\sqrt{v} p(0)] + \frac{2}{T}}{N(t)} \\ N(t) &= (v^2 + \frac{2}{T}) [1 + 2(T)] + \frac{2}{T} \end{aligned} \quad (34)$$

The qualitative behavior of $\chi_+(t)$ is determined by the three poles found by solving the equation $N(t) = 0$.

Low temperatures { At temperatures $T_b = T = T_0$ the poles, in lowest order in $T=T_0$, are given by

$$\omega_0 = \frac{2v^2(T)}{v^2 + \frac{2}{T}} ; \quad \omega_{1=2} = \frac{\frac{2}{T}(T)}{v^2 + \frac{2}{T}} \pm i \sqrt{v^2 + \frac{2}{T}} : \quad (35)$$

The limiting temperature is given by $k_B T_0 = T = (K) v^2 = (2K - T)$ for $v = T = 1$ and by $k_B T_0 = \frac{2}{T} + v^2 = (2K)$ for $v = T = 1$. The behavior of $\chi_+(t)$ depends essentially on $v = T$. If $v = T = 1$ the reduced dynamics shows a single rate, corresponding to the dominant pole $\omega_0 = 2(v = T)^2(T)$. Instead in the opposite regime, $v = T = 1$, the two poles $\omega_{1=2} = \pm i \sqrt{(T = v)^2(T)}$ are dominant. The frequency shifts are given by v as in the slow environment case of section 5.1. Thus for $v = T = 1$ a crossover is expected in the behavior of $\chi_+(t)$.

High temperatures { If $T = T_0$, the leading behavior is given by

$$\omega_0 = 2(T) ; \quad \omega_{1=2} = \frac{\frac{2}{T}}{4(T)} \pm i \frac{1}{2} \sqrt{\frac{4}{4^2(T)}} \sqrt{4v^2} : \quad (36)$$

In this case there is an intermediate temperature regime, $k_B T_0 = k_B T < k_B T_+ = \frac{2}{T} = (4Kv)$, where we may have three real roots. In this regime, which occurs only if $v = T < 1$, the dominant contribution to $\chi_+(t)$ comes again from a single pole, $\omega_1 = 2(v = T)^2(T)$. Instead for temperatures $T > T_+$ the two complex conjugate $\omega_{1=2}$ are the dominant poles. The decay rate displays the Kondo behavior $\frac{2}{T} = [4(T)] / T^{2K-1}$ and does not depend on v . The coupling v enters the frequency shifts, which approach v if the temperature is further increased. Thus in the region $T = T_0$ and $v < T$ we find a crossover which may be triggered by both v and T , the crossover line being given by

$$v = \frac{\frac{2}{T}}{4K - k_B T} : \quad (37)$$

Finally for larger values of $v > T$ the system stays in the regime where

the dominant rates are the two complex conjugate $\gamma_{\pm} = \gamma_0 \pm i\omega_0$ [4] (iv). A gain v does not enter the decay rate but determines the shifts ω_{\pm} .

6 Discussion of the results and conclusions

The analysis of the poles of $\mathcal{C}_+(s)$, Eq.(34) allows to extend the qualitative conclusion for $K = 1/2$ to the regime $K < 1$. In this latter case we find that the dynamics of \sim shows a behavior which reflects the crossover of the SB environment to a slow dynamics regime. For $K < 1$ the SB environment can be modulated by acting on both the coupling v and the temperature. Instead for $K = 1/2$ and $\gamma_{SB} = 0$ the crossover is triggered by the parameter $v = v_F$ only. This is simply due to the fact that for the relatively strong coupling $K = 1/2$, z has a relaxation dynamics at any temperature. Thus at any temperature we may identify the correlation time of the SB environment $\tau_c = \tau_F^{-1}$. The crossover to the slow environment regime occurs when $2v\tau_c = 1$ which marks the limit where the standard master equation approach in the coupling v would break down [8].

To understand the behavior for $K < 1$ we focus on $v = v_T$ and we identify the correlation time τ_c of the SB environment from the dynamics of the SB model for $v = 0$. In this case z displays a crossover from coherent to incoherent dynamics at a temperature $k_B T_c(K) = T_F = K$. Below T_c coherent oscillations at frequency ω_0 are slowly damped with rate given by $\gamma(T) = \gamma_0$ and we may identify $\tau_c = \gamma_0^{-1}$. Thus the SB environment is fast, since $2v\tau_c = 2v = \gamma_0^{-1} < 1$ and $\rho_1(t)$ shows the single rate $\gamma_0 = 2(v = v_T)^2 \gamma(T) = \gamma_0$. If the temperature increases fairly above T_c the dynamics of \sim is incoherent and relaxation occurs, with a slow rate $\gamma_r(T) = \gamma_0^2/2\gamma(T)$ [5] which is identified with τ_c^{-1} . Slow environment effects are then expected to appear in the reduced dynamics of \sim at $2v = \gamma_r(T) = 1$ which is indeed the crossover line Eq.(37).

Finally we point out possible extensions of our analysis. A SB environment with subohmic (superohmic) spectral densities [5] could be treated along the same lines, but since the uncoupled SB dynamics is always slow (fast) we do not expect tunable crossover lines to appear. Our analysis can be easily extended to an environment made of an arbitrary number of SB impurities. In this case $\mathcal{C}_+(t) = \sum_i^Q \mathcal{C}_+^{(i)}(t)$ where $\mathcal{C}_+^{(i)}(t)$ is the individual contribution of the i -th SB impurity. This allows to model a simple environment which produces $1/f$ noise by choosing a suitable distribution [10] of the parameters of the set SB impurities. For instance in Ref. [9], which focuses on $K = 1/2$, the standard distribution $\gamma_0 = \gamma_F$ has been chosen for the relaxation rate of the SB. We notice that for $K = 1/2$ temperature has no effect in the regime we consider. If we allow for impurities with $\gamma_{SB} \neq 0$ the temperature determines at

most how many impurities in the set are active. Instead for a 1=f environment modeled by a set of ohmic SB impurities with $K = 1$ our results show a non trivial behavior as a function of the temperature, which may be relevant for recent observations [18] of temperature-dependent dephasing due to 1=f noise. Finally if $E_J \neq 0$, ϕ_z is not conserved and relaxation occurs. The relaxation rate increases monotonically with E_J . We believe that the physical picture emerging from this work still applies to dephasing (see Ref. [17] for $K = 1=2$) at least for times smaller than the relaxation time.

7 Acknowledgements

The authors are pleased to thank Uli Weiss for the physics they learned and enjoyed from the extremely vivid cooperation with him during the last 15 years.

References

- [1] A. Ekert and A. Jozsa, *Rev. Mod. Phys.* **68**, 733 (1996); *Quantum Computation and Quantum Information Theory*, edited by C. Macchiavello, G. M. Palma, A. Zeilinger, World Scientific (2000). M. Nielsen and I. Chuang *Quantum Computation and Quantum Communication*, Cambridge University Press, (2000). *Experimental implementation of quantum computation*, edited by R. G. Clark, Rinton Press, Princeton (2001).
- [2] W. Zurek, *Physics Today* **44**, 36 (1991).
- [3] G. M. Palma, K. A. Suominen and A. K. Ekert, *Proc. Roy. Soc. London A* **452**, 567 (1996).
- [4] Y. Makhlin, G. Schon and A. Shnirman, *Rev. Mod. Phys.* **73** 357 (2001).
- [5] U. Weiss *Quantum Dissipative Systems* 2nd Ed (World Scientific, Singapore 1999).
- [6] A. Leggett et al., *Rev. Mod. Phys.* **59**, 1 (1987).
- [7] A. O. Caldeira and A. J. Leggett, *Ann. Phys.* **149**, 374 (1983).
- [8] C. Cohen-Tannoudji, J. Dupont-Roc and G. Grynberg *Atom-Photon Interactions*, Wiley-Interscience (1993).
- [9] E. Paladino et. al., *Phys. Rev. Lett.* **88**, 228304 (2002); G. Falci et. al., *Proceedings of the International School Enrico Fermi "Quantum Phenomena of Mesoscopic Systems"*, B. Altshuler and V. Tognetti Eds., IOSBologna (2003).

- [10] M. B. Weissman, *Rev. Mod. Phys.* 60, 537 (1988); A. B. Zorin et al, *Phys. Rev. B* 53, 13682 (1996).
- [11] Y. Nakamura, Yu. A. Pashkin, J. S. Tsai, *Nature* 398, 786 (1999); Y. Nakamura et al, *Phys. Rev. Lett.* 88, 047901 (2002); D. Vion et al, *Science* 296, 886 (2002); Y. Yu et al, *Science* 296, 889 (2002); J. Martinis et al, *Phys. Rev. Lett.* 89, 117901 (2002); J. Friedman et al, *Nature* 406, 43 (2000); I. Chiorescu et al, *Science*, 299, 1869 (2003); Yu. A. Pashkin et al, *Nature* 421, 823 (2003).
- [12] Fano impurities are localized levels occupied by electrons which may tunnel to a band of delocalized states, see G. D. Mahan, *Many-particle physics*, third edition, Kluwer 2000.
- [13] D. A. Averin, *Sol. State Comm.* 105, 659 (1998); J. E. Mooij et al, *Science* 285, 1036 (1999); Y. Makhlin, G. Schon and A. Shnirman, *Nature* 398, 305 (1999); G. Falci et al, *Nature* 407, 355 (2000).
- [14] M. G. Overmire, M. G. Riffoni, G. Schon, *Chem. Phys.* 268, 273 (2001).
- [15] R. Aguado and L. P. Kouwenhoven, *Phys. Rev. Lett.* 84, 1986 (2000); M. H. Devoret and R. J. Schoelkopf, *Nature* 406, 1039 (2000).
- [16] M. G. Riffoni, M. Sassetti and U. Weiss, *Phys. Rev. E* 53, R2033 (1996); M. G. Riffoni, E. Paladino, U. Weiss, *Eur. Phys. J. B* 10, 719 (1999).
- [17] E. Paladino, L. Faoro, G. Falci, *Adv. Solid State Phys.* 43, 747 (2003).
- [18] J. A. Bonetti, D. J. Van Harlingen, M. B. Weissman, *Physica C*, 288 – 389, 343 (2003).