

The origin of flux-flow resistance oscillations in $\text{Bi}_2\text{Sr}_2\text{CaCu}_2\text{O}_{8+y}$: Fiske steps in a single junction?

A. V. Ustinov

Physikalisches Institut III, Universität Erlangen-Nürnberg, D-91058, Erlangen, Germany

N. F. Pedersen

*Oersted-DTU, Section of Electric Power Engineering,
The Technical University of Denmark, DK-2800 Lyngby, Denmark*

(Dated: January 9, 2022)

We propose an alternative explanation to the oscillations of the flux-flow resistance found in several previously published experiments with $\text{Bi}_2\text{Sr}_2\text{CaCu}_2\text{O}_{8+y}$ stacks. It has been argued by the previous authors that the period of the oscillations corresponding to the field needed to add one vortex per two intrinsic Josephson junctions is associated with a moving triangular lattice of vortices (out-of-phase mode), while the period corresponding to one vortex per one junction is due to the square lattice (in-phase mode). In contrast, we show that both type of oscillations may occur in a single-layer Josephson junction and thus the above interpretation is inconsistent.

PACS numbers: 74.50.+r, 74.40.+k, 74.78.Na

Recently, a lot of attention has been focused on the possible use of single crystals of $\text{Bi}_2\text{Sr}_2\text{CaCu}_2\text{O}_{8+y}$ as generators of electromagnetic radiation in the THz range. Promising experiments in that direction were reported by Hirata et al. [1] and shortly thereafter by Kakeya et al. [2] and Hatano et al. [3]. These experiments all showed oscillations in the flux-flow voltage and flux-flow resistance when a large magnetic field (of order several Tesla) was applied parallel to the ab plane in the presence of a small bias current in the c -direction (of order a few percent of the critical current). The observed flux-flow voltage oscillations typically showed two different oscillation periods. At the lowest magnetic fields the period was $\Delta H_T = \Phi_0/(2sL)$ corresponding to one extra flux quantum per *two* layers in the stack. Here Φ_0 is the magnetic flux quantum, s and L are the thickness and the length of the junction, respectively. At higher magnetic fields there was a transition to a period $\Delta H_S = \Phi_0/(sL)$, i.e. corresponding to an extra flux quantum in *every* layer.

These exiting experiments were interpreted both analytically [4] and numerically [5, 6, 7] by several authors. One of the important questions to be answered was whether the flux lattice correspond to a triangular

lattice (anti-phase ordering with possible cancellation of the sum voltage at the junction end) or a square lattice (in-phase ordering leading to a large sum voltage at the junction end). Figure 1 shows schematically a $\text{Bi}_2\text{Sr}_2\text{CaCu}_2\text{O}_{8+y}$ stack with flux ordering in a triangular lattice and square lattice. Obviously, the latter case is highly preferable for applications to THz generation of electromagnetic waves; however simple intuition would suggest triangular ordering since fluxons of same polarity naturally repel each other. An intuitive interpretation of the experimentally observed oscillations in the flux-flow voltage would suggest that an oscillation period ΔH_T corresponds to triangular ordering while a period ΔH_S corresponds to a square lattice. Numerical simulations [5, 6, 7] have shown that both triangular and square lattices are possible, but their relation to regions of ΔH_T oscillations and regions of ΔH_S oscillations is not simple and details are still a matter of debate.

In this paper, we present fairly standard numerical simulations corresponding to the simplest case of a single-layer Josephson junction. Even for this case, where there is no triangular nor square lattice ordering (as our stack consists of only one junction), we find that both the ΔH_T and ΔH_S periods appear much the same way as in experiments and numerical simulations for $\text{Bi}_2\text{Sr}_2\text{CaCu}_2\text{O}_{8+y}$ stacks with many layers and flux lattice ordering. After presenting the numerical simulations we provide a qualitative explanation in terms of the well-known Fiske modes [8].




FIG. 1: Schematic drawing of the triangular lattice (a) corresponding to the out-of-phase fluxon mode and the square lattice (b) associated with the in-phase fluxon mode.

The system under investigation is described by coupled

sine-Gordon equations of the form [9]:

$$\mathbf{S}\mathbf{J} = \frac{\partial^2 \varphi}{\partial x^2}; \quad \mathbf{S} = \begin{pmatrix} 1 & S & & & \\ S & 1 & S & & 0 \\ & \ddots & \ddots & \ddots & \\ & & \ddots & \ddots & \ddots \\ 0 & & & S & 1 & S \\ & & & & S & 1 \end{pmatrix} \quad (1)$$

with

$$J_i \equiv \frac{\partial^2 \varphi_i}{\partial t^2} + \alpha \frac{\partial \varphi_i}{\partial t} + \sin \varphi_i - \gamma. \quad (2)$$

Here $\alpha = (1/R)[\hbar/(2eI_0C)]^{1/2}$ is the dissipation parameter (R , I_0 , and C are the normal resistance, the critical current and the capacitance per unit length, respectively), γ is the current normalized to the critical current I_0 of the individual junctions. The normalized coupling term among the junctions in the stack reads $S = -\lambda_L/[d' \sinh(t/\lambda_L)]$, where $d' = d + 2\lambda_L \coth(t/\lambda_L)$, t is the thickness of one superconducting layer, and λ_L is the London penetration depth [9]. Time t is normalized to the inverse of the Josephson plasma frequency $\omega_p = [2eI_0/(\hbar C_J)]^{1/2}$ and spatial coordinate x is normalized with respect to the Josephson length $\lambda_J = [\hbar/(2e\mu_0 I_0)]^{1/2}$. The magnetic field gives rise to boundary conditions of the form [9]

$$\left. \frac{\partial \varphi_i}{\partial x} \right|_{x=0,\ell} = \frac{H}{\lambda_J I_0} \equiv h. \quad (3)$$

Index $i = 1, \dots, N$ stands here for the junction number in the stack and ℓ is the normalized length of the system.

Figure 2 shows the result of a simulation of the current-voltage characteristics for only one junction in the stack, i.e. $N = 1$. It shows the flux-flow branch of the junction with normalized length $\ell = 40$ and damping constant $\alpha = 0.1$ placed in magnetic field $h = 4$. The characteristics is calculated by rising the bias current γ from zero to 0.85 and then decreasing it back to zero. The voltage V is given in normalized units chosen such that the voltage spacing between neighboring Fiske steps

$$\Delta V = \frac{\Phi_0 \bar{c}}{2L} \quad (4)$$

is equal to unity (here \bar{c} is the Swihart velocity and $L = \ell\lambda_J$ is the physical length of the junction). The current-voltage characteristics displays fine structure due to the Fiske steps, which gather around the flux-flow voltage, also known as Eck peak [10]. The hysteresis in this voltage region is due to the coexistence of several Fiske resonances at a given current γ . Some parts of these Fiske resonances are located inside the hysteresis and are not displayed on the plot.

Using the above junction parameters, we calculated the dependence of the flux-flow resistance on magnetic




FIG. 2: Current-voltage characteristics of a long junction ($N = 1$) with parameters $\ell = 40$, $\alpha = 0.1$, and $h = 4$. Arrows indicate switching between branches for rising and decreasing bias current γ .




FIG. 3: Differential flux-flow resistance $dV/d\gamma$ versus magnetic field h for the single junction ($N = 1$) with $\ell = 40$ and $\alpha = 0.1$ at constant bias current $\gamma = 0.3$.

field. Figure 3 presents the differential flux-flow resistance $dV/d\gamma$ versus magnetic field h at the fixed bias current $\gamma = 0.3$. It clearly shows flux-flow resistance oscillations. In order to relate the period of oscillations with the number of vortices in the junction we show a grid in magnetic field with a period $\Delta h = 2\pi/L\ell$, which approximately corresponds to adding one vortex in the junction. This can be seen from the simple fact that




FIG. 4: Flux-flow resistance V/γ (thick curve) and $dV/d\gamma$ (thin curve) versus magnetic field h for the same junction as in Fig. 3 at a lower bias current $\gamma = 0.2$.

at the critical field $h = 2$ the normalized spacing between vortices penetrated into the junction is equal to π , and their number rises proportionally to h . In Fig. 3 we see that most oscillations have a characteristic period in h corresponding to adding a half flux quantum into the junction, with a tendency of doubling the period at higher fields.

As another illustration, in Fig. 4 we show both static resistance V/γ and differential resistance $dV/d\gamma$ versus magnetic field h for the same junction but at a lower bias current $\gamma = 0.2$. The oscillations of $dV/d\gamma$ (thin curve) have two characteristic periods, which are found at different ranges of magnetic field h . The oscillation period at low fields corresponds to about or less than *half flux quantum*, while at higher fields we find very clear oscillations which account for *one flux quantum* into the junction. The crossover from one regime to another occurs at magnetic field $h \approx 3$. Below this field the differential resistance at $\gamma = 0.2$ is lower as it is determined by the Eck peak (see also Fig. 2) composed of individual Fiske steps. At $h > 3$ the Eck peak shifts to higher

currents and the differential resistance levels at the resistive slope determined by the loss parameter α of the junction. The static junction resistance (upper curve in Fig. 4) also changes in this range but its oscillations are much less pronounced and can only be clearly seen on the magnified scale.

We suggest the following explanation for the two oscillation periods of the flux-flow resistance in a single-barrier Josephson junction. At high enough magnetic field the resistance at a low bias current follows oscillations of the critical current of the junction and thus have a characteristic period of *one flux quantum*. At the same time, the resistance measured at a higher current (or lower field but the same bias current) follows the oscillations due to the Fiske steps, which envelope is associated with the Eck peak (sometimes called as flux-flow or velocity matching step). The matter is that – for a single junction – the Fiske steps induce a variation of the resistance with characteristic period corresponding to *half flux quantum*.

Fiske modes in a Josephson junction [8] are linear cavity type excitations with resonance angular frequencies given by

$$\omega_n = n \frac{2\pi}{\ell}, \quad n = 1, 2, 3, \dots \quad (5)$$

in normalized units. The corresponding wave vectors are

$$k_n = n \frac{\pi}{\ell}. \quad (6)$$

In experiments these Fiske modes are visible as current singularities in the current-voltage curve with a voltage spacing given by Eq. (4). The amplitude of the Fiske steps oscillate with the magnetic field in a typical Bessel function like pattern such that the even numbered steps have maxima together with maxima in the critical current, while maxima in the odd numbered steps correspond to minima in the critical current. Refs. [11, 12] give an approximate analytical form for the current-voltage curve for a single Josephson junction with Fiske steps. The current-voltage characteristics is approximately written as [12]:

$$\gamma(\omega, h) = \alpha\omega + \sum_{-\infty}^{+\infty} \left[\frac{h}{\ell(h^2 - k_n^2)} \sin \frac{h\ell - k_n\ell}{2} \right]^2 \cdot \frac{2\alpha\omega}{(\omega^2 - k_n^2)^2 + \alpha^2\omega^2}. \quad (7)$$

This approximation neglects high-order nonlinearities in the junction and is originally expected [11] to describe

well the case of short junction, i.e. $\ell < 1$. However, the comparison with long junction data made by Cirillo et




FIG. 5: Differential flux-flow resistance $dV/d\gamma$ at constant bias current $\gamma = 0.2$ versus magnetic field h calculated directly from Eq. (7) with parameters $\ell = 40$ and $\alpha = 0.1$. The voltage is multiplied by a factor ℓ/π to make its scale identical to the voltage normalization used in the previous figures.

al. [12] shows that Eq. (7) can approximately account for the shape and for the maximum current modulation of the Fiske singularities in long ($\ell \gg 1$) junctions when the field penetration overcomes Meissner shielding, i.e. at $h > 2$.

The first term in Eq. (7) represents the Ohmic part of the current-voltage characteristics, while the second term gives an infinite series of equidistant resonances. The height of the resonances is modulated by a slowly varying amplitude factor and a fast Fraunhofer amplitude factor [12]. The Fraunhofer factor emphasizes the resonance closest to $\omega = h$ and drops off fast: If $h\ell$ is an even multiple of π , the odd numbered Fiske steps are enhanced and if $h\ell$ is an odd multiple of π , the even numbered Fiske steps survive.

Equation (7) gives the current-voltage curve containing Fiske steps with the magnetic field as a parameter. If we instead assume a fixed bias current γ and vary the magnetic field, Eq. (7) expresses the voltage $V \propto \omega$ oscillations in an implicit form. In order to compare this analytical form with our simulations, we solved Eq. (7) for ω at a given γ numerically. The obtained dependence of the flux-flow resistance $dV/d\gamma$ at constant bias current $\gamma = 0.2$ versus magnetic field h is presented in Fig. 5. The qualitative agreement between Figs. 3 and 4 obtained by full numerical simulation of the perturbed sine-Gordon equation and Fig. 5 emerging from the analytical formula (7) is strikingly good. Figure 5 clearly

displays two characteristic periods of oscillations, namely half flux quantum oscillations at low fields and one flux quantum oscillations which become very explicit at high fields. The intermediate field range shows a complicated beating between two periods.

Thus, odd and even numbered Fiske resonances in the last term in Eq. (7) produce the "magic" half-flux-quantum oscillations corresponding to the magnetic field period $\Delta H_T = \Phi_0/(2sL)$ even in a single Josephson junction. Although we investigated here Fiske steps with $N = 1$, we note that Fiske steps are also present in stacks with $N > 1$ [13]. Thus we are lead to suggest that also for $N > 1$ the flux-flow voltage oscillations have their origin in the Fiske mode excitations.

We conclude that for $\text{Bi}_2\text{Sr}_2\text{CaCu}_2\text{O}_{8+y}$ stacks the flux-flow voltage oscillations with two different periods in a magnetic field have their origin in the Fiske mode excitations. Thus the flux lattice ordering in either triangular or square lattice is not directly related to the two periods of the oscillations. We speculate that Fiske modes also existing in stacks indirectly play a role for the flux lattice formation.

We would like to acknowledge discussions with T. Hatano, S. Kim, A. E. Koshelev, S. Madsen, M. R. Samuelsen, H. B. Wang, and T. Yamashita.

-
- [1] S. Ooi, T. Mochiku, and K. Hirata, Phys. Rev. Lett. **89**, 247002 (2002)
 - [2] I. Kakeya, M. Iwase, T. Yamamoto, and K. Kadowaki, cond-mat/0503498 (2005); I. Kakeya et al. Physica C **378**, 406 (2002)
 - [3] T. Hatano et al., IEEE Trans Appl. Supercond., to be published
 - [4] A.E. Koshelev, Phys. Rev B **66**, 224514 (2002)
 - [5] M. Machida, Phys. Rev. Lett. **90**, 037001 (2003)
 - [6] M. Tachiki, M. Iizuka, K. Minami, S. Tejima, and H. Nakamura, cond-mat/0407052 (2004)
 - [7] N.F. Pedersen and S. Madsen, IEEE Trans Appl. Supercond., to be published
 - [8] M. D. Fiske, Rev. Mod. Phys. **36**, 221 (1964)
 - [9] S. Sakai, P. Bodin, and N.F. Pedersen, J. Appl. Phys. **73**, 2411 (1993)
 - [10] R. E. Eck, D. J. Scalapino and B. N. Taylor, Phys. Rev. Lett. **13**, 15 (1964).
 - [11] I. O. Kulik, Pis'ma Zh. Eksp. Teor. Fiz. **2**, 134 (1965) [Sov. Phys. JETP Lett. **2**, 84 (1965)]; I. O. Kulik, Zh. Tekhn. Fiz. **37** 157 (1967) [Sov. Tech. Phys. **12**, 111 (1967)]
 - [12] M. Cirillo, N. Grønbech-Jensen, M. R. Samuelsen, M. Salerno, and G. V. Rinati, Phys. Rev. B **58**, 12377 (1998)
 - [13] S. Kim, S. Urayama, H. B. Wang, T. Hatano, M. Nagao, S. Kawakami, Y. Takano, and T. Yamashita. Poster Presentation in the conference 'Plasma-2004' Tsukuba, Japan, November 2004