

Lower bounds on the error probability of multiple quantum channel discrimination by the Bures angle and the trace distance

Ryo Ito* and Ryuhei Mori†

School of Computing, Tokyo Institute of Technology, Japan

(Dated: January 13, 2022)

Quantum channel discrimination is a fundamental problem in quantum information science. In this study, we consider general quantum channel discrimination problems, and derive the lower bounds of the error probability. Our lower bounds are based on the triangle inequalities of the Bures angle and the trace distance. As a consequence of the lower bound based on the Bures angle, we prove the optimality of Grover’s search if the number of marked elements is fixed to some integer k . This result generalizes Zalka’s result for $k = 1$. We also present several numerical results in which our lower bounds based on the trace distance outperform recently obtained lower bounds.

I. INTRODUCTION

The quantum channel discrimination problem is a fundamental problem in quantum information science [1–5]. In this study, we consider a general quantum channel discrimination problem, and derive the lower bounds of the error probability.

From Helstrom’s seminar work [6] and Holevo’s subsequent work [7], the error probability of the discrimination of two quantum states ρ and σ is characterized by the trace distance $\frac{1}{2}\|\rho - \sigma\|_1$, which can be computed efficiently. As a consequence, the error probability of the discrimination of two quantum channels Ψ and Φ by algorithms invoking the quantum channel once can be characterized by the maximum of the trace distance, $\max_{\rho} \frac{1}{2}\|\Phi \otimes \text{id}(\rho) - \Psi \otimes \text{id}(\rho)\|_1 =: \frac{1}{2}\|\Phi - \Psi\|_{\diamond}$, which is called the diamond distance. The diamond distance can be computed efficiently as well [8]. On the other hand, if we consider algorithms that use the quantum channel n times, the analysis is more complicated. If we restrict the discrimination algorithms to be non-adaptive, the error probability is characterized by the diamond distance $\frac{1}{2}\|\Phi^{\otimes n} - \Psi^{\otimes n}\|_{\diamond}$. To compute the above diamond distance, we have to solve an optimization problem on exponentially high-dimensional linear space in n . Hence, it is computationally hard to compute the error probability of non-adaptive algorithms with n queries when n is large. Furthermore, for general discrimination algorithms, no simple representation of the error probability has been known even for the discrimination of two quantum channels.

The exact error probability for a fixed number of queries is known if two unitary channels are given with uniform probabilities [3]. In this case, a non-adaptive algorithm achieves the minimum error probability. For general quantum channel discriminations, however, there exists some discrimination problem in which some adaptive algorithm gives a strictly smaller error probability than any non-adaptive algorithms [1].

The well-known Grover’s search problem can be regarded as an instance of a multiple quantum channel discrimination problem if there is exactly one marked element. Grover’s search algorithm solves this problem with $O(\sqrt{N})$ queries, where N is the number of elements. The asymptotic optimality of Grover’s algorithm was shown in [9]. Zalka showed that the error probability of Grover’s algorithm for a fixed number of queries is optimal when there is exactly one marked element [10].

Recently, lower bounds on the error probability of general quantum channel discrimination have been studied [4, 5, 11]. In this study, we consider a quantum channel group discrimination problem, which is a generalization of the quantum channel discrimination problem, and derive the lower bounds of the error probability. On the lines of previous studies [9, 10, 12], the main technique we use to derive the lower bounds is the application of triangle inequalities for some distance measures to series of quantum states. In this work, we use two distance measures, namely, the Bures angle and the trace distance. Our lower bound based on the Bures angle shows the optimality of Grover’s algorithm if the number of marked elements is fixed to some integer k . This result generalizes Zalka’s result for $k = 1$. For the lower bound based on the trace distance, we introduce “weights” of the internal quantum states to tighten the triangle inequality. This yields better lower bounds for some problems considered in [5].

Moreover, we derive another type of lower bound on the error probability of two quantum channel discriminations. Our technique is a natural generalization using the Bures angle of the known technique for unitary channel discrimination [3]. For the discrimination of two amplitude damping channels with damping rates r_0 and r_1 , we obtain a simple analytic lower bound $\frac{1}{2}(1 - \sin(n\Delta(r_0, r_1)))$ if $n\Delta(r_0, r_1) \leq \frac{\pi}{2}$, where $\Delta(r_0, r_1) := \arccos(\sqrt{r_0 r_1} + \sqrt{(1 - r_0)(1 - r_1)})$. This lower bound is better than the known lower bounds [4, 13] for some choices of the damping rates r_0 and r_1 and the number n of queries. We also present several numerical results in which our lower bounds for two quantum channel discrimination based on the trace distance outperform recently obtained lower bounds.

* ito.r.al@m.titech.ac.jp

† mori@c.titech.ac.jp

This paper is organized as follows. Distance measures for quantum states, including the Bures angle and the trace distance, are introduced in Section II. The quantum channel discrimination problem and the quantum channel group discrimination problem are introduced in Section III. The main results in this paper are presented in Section IV. The applications of our lower bounds are described in Section V. The proofs of the main results are presented in Section VI. In Section VII, we show that the lower bounds derived in this paper can be computed efficiently using semidefinite programming (SDP). We conclude the paper in Section VIII.

II. THE TRACE DISTANCE AND THE BURES ANGLE

In this section, we introduce the notion of distance measures for quantum states, and several examples of distance measures, including the trace distance and the Bures angle. Let $\mathsf{L}(A)$ be a set of linear operators on a quantum system A . Let $\mathsf{D}(A)$ be a set of density operators on a quantum system A .

Definition 1 (Distance measure for quantum states). A function

$$D: \{\rho_A \in \mathsf{D}(A), \sigma_A \in \mathsf{D}(A) \mid A: \text{a system}\} \rightarrow [0, \infty)$$

is called a distance function if it satisfies the following conditions.¹

1. (Identity of indiscernibles) For any $\rho_A, \sigma_A \in \mathsf{D}(A)$, $D(\rho_A, \sigma_A) = 0$ if and only if $\rho_A = \sigma_A$.
2. (Symmetry) For any $\rho_A, \sigma_A \in \mathsf{D}(A)$, $D(\rho_A, \sigma_A) = D(\sigma_A, \rho_A)$.
3. (Triangle inequality) For any $\rho_A, \sigma_A, \tau_A \in \mathsf{D}(A)$, $D(\rho_A, \sigma_A) \leq D(\rho_A, \tau_A) + D(\tau_A, \sigma_A)$.
4. (Monotonicity) For any $\rho_A, \sigma_A \in \mathsf{D}(A)$ and any quantum channel $\Psi_{A \rightarrow B}$ from a quantum system A to a quantum system B , $D(\Psi_{A \rightarrow B}(\rho_A), \Psi_{A \rightarrow B}(\sigma_A)) \leq D(\rho_A, \sigma_A)$.

The trace distance is a well-known distance measure for quantum states.

Definition 2 (Trace distance). For a linear operator $L_A \in \mathsf{L}(A)$, the trace norm is defined as $\|L_A\|_1 := \text{Tr} \sqrt{L_A L_A^\dagger}$. For density operators $\rho_A, \sigma_A \in \mathsf{D}(A)$, the trace distance is defined as $D(\rho_A, \sigma_A) = \frac{1}{2} \|\rho_A - \sigma_A\|_1$.

The trace distance has a useful property called the *joint convexity*, which is $D\left(\sum_i p_i \rho_A^{(i)}, \sum_i p_i \sigma_A^{(i)}\right) \leq \sum_i p_i D(\rho_A^{(i)}, \sigma_A^{(i)})$ for any probability distribution $\{p_i\}_i$ and density operators $\{\rho_A^{(i)}\}_i$ and $\{\sigma_A^{(i)}\}_i$.

The fidelity of quantum states is defined as follows.

Definition 3 (Fidelity). For density operators $\rho_A, \sigma_A \in \mathsf{D}(A)$, the fidelity is defined as

$$F(\rho_A, \sigma_A) := \|\sqrt{\rho_A} \sqrt{\sigma_A}\|_1.$$

The Bures angle is defined as follows.

Definition 4 (Bures angle). For density operators $\rho_A, \sigma_A \in \mathsf{D}(A)$, the Bures angle is defined as

$$\mathcal{A}(\rho_A, \sigma_A) := \arccos F(\rho_A, \sigma_A).$$

The Bures angle satisfies the conditions on the distance measure for quantum states [14].

There are several distance measures induced by the fidelity. Indeed, the Bures distance $\mathcal{B}(\rho_A, \sigma_A)$ and the sine distance $\mathcal{C}(\rho_A, \sigma_A)$, defined as

$$\begin{aligned} \mathcal{B}(\rho_A, \sigma_A) &:= \sqrt{2 - 2F(\rho_A, \sigma_A)} \\ \mathcal{C}(\rho_A, \sigma_A) &:= \sqrt{1 - F(\rho_A, \sigma_A)^2}, \end{aligned}$$

satisfy the conditions on the distance measure for quantum states. These distance measures can be naturally represented in terms of the Bures angle. Indeed, for $\theta = \mathcal{A}(\rho_A, \sigma_A)$, it holds $\mathcal{B}(\rho_A, \sigma_A) = 2 \sin(\theta/2)$ and $\mathcal{C}(\rho_A, \sigma_A) = \sin(\theta)$. The triangle inequalities for the Bures distance and the sine distance are obtained from the triangle inequality for the Bures angle (see Appendix A). This fact means that the triangle inequality for the Bures angle gives better bounds than the triangle inequalities for the Bures distance and the sine distance. Hence, in this study, we use the Bures angle, and do not use the Bures distance or the sine distance to derive inequalities.

Although the fidelity-based distances \mathcal{A} , \mathcal{B} , and \mathcal{C} are not jointly convex, the fidelity has a useful property called the joint concavity, which is $F\left(\sum_i p_i \rho_A^{(i)}, \sum_i p_i \sigma_A^{(i)}\right) \geq \sum_i p_i F(\rho_A^{(i)}, \sigma_A^{(i)})$ for any probability distribution $\{p_i\}_i$ and density operators $\{\rho_A^{(i)}\}_i$ and $\{\sigma_A^{(i)}\}_i$.

III. QUANTUM CHANNEL DISCRIMINATION PROBLEMS

Let Ξ and H be finite sets. Let A, B, E, R , and W be finite-dimensional quantum systems. The quantum channel discrimination problem is defined as follows.

Definition 5 (Quantum channel discrimination problem). Let $\{\mathcal{O}_{A \rightarrow B}^\xi\}_{\xi \in \Xi}$ be a finite family of quantum channels and $\{p_\xi\}_{\xi \in \Xi}$ be a probability distribution on

¹ In fact, we only need the triangle inequality and the monotonicity in this paper.

the quantum channels. Assume that one of the quantum channels $\mathcal{O}_{A \rightarrow B}^\xi$ is given as an oracle with probability p_ξ . The given oracle can be used multiple times. “The quantum channel discrimination problem” is the problem of determining the index of the given oracle $\xi \in \Xi$, and is denoted by $\text{QCDP}(\{p_\xi\}, \{\mathcal{O}_{A \rightarrow B}^\xi\})$.

We also consider the quantum channel group discrimination problem, which is a natural generalization of the quantum channel discrimination problem.

Definition 6 (Quantum channel group discrimination problem). Let $\{\mathcal{O}_{A \rightarrow B}^\xi\}_{\xi \in \Xi}$ be a finite family of quantum channels and $\{p_\xi\}_{\xi \in \Xi}$ be a probability distribution on the quantum channels. Let $\{C_\eta \subseteq \Xi\}_{\eta \in H}$ be a family of subsets of Ξ . Assume that one of the quantum channels $\mathcal{O}_{A \rightarrow B}^\xi$ is given in the same way as $\text{QCDP}(\{p_\xi\}, \{\mathcal{O}_{A \rightarrow B}^\xi\})$. “The quantum channel group discrimination problem” is the problem of finding one of the indexes of a subset $\eta \in H$ that satisfies $\xi \in C_\eta$. This problem is denoted by $\text{QCGDP}(\{p_\xi\}, \{\mathcal{O}_{A \rightarrow B}^\xi\}, \{C_\eta\})$.

Note that $\{C_\eta\}_{\eta \in H}$ is not necessarily a partition of Ξ . When there are multiple $\eta \in H$ satisfying $\xi \in C_\eta$, all of them are regarded as correct answers. When there is no $\eta \in H$ satisfying $\xi \in C_\eta$, any η is incorrect answer. The quantum channel discrimination problem can be regarded as the quantum channel group discrimination problem where $H = \Xi$ and $C_\eta = \{\eta\}$ for all $\eta \in H$.

We consider algorithms that solve the quantum channel group discrimination problem. The general algorithm for the quantum channel group discrimination problem is defined as follows.

Definition 7 (Discrimination algorithm). Let R be a working system. Let $\{\Phi_{BR \rightarrow AR}^k\}_{k=1}^n$ be a family of quantum channels, and $\{M_{BR}^\eta\}_{\eta \in H}$ be a positive operator-valued measure (POVM). Then a pair $(\{\Phi_{BR \rightarrow AR}^k\}, \{M_{BR}^\eta\})$ represents the following algorithm for $\text{QCGDP}(\{p_\xi\}, \{\mathcal{O}_{A \rightarrow B}^\xi\}, \{C_\eta\})$.

- 1: Set the initial state $|0\rangle\langle 0|_{BR}$ in a quantum computer.
- 2: **for** $k = 1, 2, \dots, n$ **do**
- 3: Apply the quantum channel $\Phi_{BR \rightarrow AR}^k$.
- 4: Apply the given oracle $\mathcal{O}_{A \rightarrow B}^\xi$.
- 5: **end for**
- 6: Apply a measurement $\{M_{BR}^\eta\}_{\eta \in H}$ to the state and output the observed value $\eta \in H$.

An algorithm succeeds if and only if its output $\eta \in H$ satisfies $\xi \in C_\eta$, where $\xi \in \Xi$ is the index of the given oracle $\mathcal{O}_{A \rightarrow B}^\xi$. The minimum error probability of a QCGDP is then defined as follows.

Definition 8 (The minimum error probability of a QCGDP). Let $(\{\Phi_{BR \rightarrow AR}^k\}, \{M_{BR}^\eta\})$ be an algorithm for $\text{QCGDP}(\{p_\xi\}, \{\mathcal{O}_{A \rightarrow B}^\xi\}, \{C_\eta\})$ with n queries. For each $\xi \in \Xi$, a density operator ρ_{BR}^ξ is defined as

$$\begin{aligned} \rho_{BR}^\xi &:= \mathcal{O}_{A \rightarrow B}^\xi \circ \Phi_{BR \rightarrow AR}^n \circ \mathcal{O}_{A \rightarrow B}^\xi \circ \Phi_{BR \rightarrow AR}^{n-1} \\ &\quad \circ \dots \circ \mathcal{O}_{A \rightarrow B}^\xi \circ \Phi_{BR \rightarrow AR}^1(|0\rangle\langle 0|_{BR}). \end{aligned}$$

The minimum error probability of $\text{QCGDP}(\{p_\xi\}, \{\mathcal{O}_{A \rightarrow B}^\xi\}, \{C_\eta\})$ with n queries is defined as

$$p_{\text{err}}(n) := \min_{\{\Phi_{BR \rightarrow AR}^k\}, \{M_{BR}^\eta\}} \sum_{\xi \in \Xi} p_\xi \sum_{\eta: \xi \notin C_\eta} \text{Tr} \left(M_{BR}^\eta \rho_{BR}^\xi \right).$$

The minimum error probability of $\text{QCDP}(\{p_\xi\}, \{\mathcal{O}_{A \rightarrow B}^\xi\})$ is defined in the same way.

An algorithm that achieves the minimum error probability exists for any QCGDP because the set of algorithms is compact and the error probability is continuous. The main goal of this study is to derive a lower bound of the minimum error probability $p_{\text{err}}(n)$.

The error probability $p_{\text{err}}(0)$ without calling the oracle can be evaluated as follows:

$$\begin{aligned} p_{\text{err}}(0) &= \min_{\{M_{BR}^\eta\}} \sum_{\xi \in \Xi} p_\xi \sum_{\eta: \xi \notin C_\eta} \text{Tr} \left(M_{BR}^\eta |0\rangle\langle 0|_{BR} \right) \\ &= \min_{\{M_{BR}^\eta\}} \sum_{\eta \in H} \text{Tr} \left(M_{BR}^\eta |0\rangle\langle 0|_{BR} \right) \sum_{\xi \notin C_\eta} p_\xi \\ &= \min_{\eta \in H} \left(\sum_{\xi \notin C_\eta} p_\xi \right). \end{aligned}$$

Once the quantum channels $\{\Phi_{BR \rightarrow AR}^k\}_{k=1}^n$ in a discrimination algorithm are fixed, the problem is reduced to the quantum state discrimination problem. The optimal measurement and the error probability of discrimination of two quantum states were known by Helstrom [6] and Holevo [7].

Proposition 1 (Holevo–Helstrom theorem [6, 7, 15]). Let ρ_A^0 and ρ_A^1 be density operators, and let p_0 and p_1 be non-negative real numbers that satisfy $p_0 + p_1 = 1$. For any POVM $\{M_A^0, M_A^1\}$, the following holds:

$$\sum_{\xi \in \{0,1\}} p_\xi \text{Tr} \left(M_A^\xi \rho_A^\xi \right) \leq \frac{1}{2} \left(1 + \|p_0 \rho_A^0 - p_1 \rho_A^1\|_1 \right).$$

Moreover, a POVM $\{M_A^0, M_A^1\}$ exists that satisfies the equality.

From the Holevo–Helstrom theorem, the error probability of discrimination of two quantum channels with a single query is given by the following proposition.

Proposition 2 ([15]). Let $p_{\text{err}}(1)$ be the minimum error probability for $\text{QCDP}(\{p_0, p_1\}, \{\mathcal{O}_{A \rightarrow B}^0, \mathcal{O}_{A \rightarrow B}^1\})$ with one query. The following then holds:

$$\begin{aligned} p_{\text{err}}(1) &= \frac{1}{2} \left(1 - \max_{\rho_{AR} \in \mathcal{D}(A \otimes R)} \left\| p_0 (\mathcal{O}_{A \rightarrow B}^0 \otimes \text{id}_R)(\rho_{AR}) \right. \right. \\ &\quad \left. \left. - p_1 (\mathcal{O}_{A \rightarrow B}^1 \otimes \text{id}_R)(\rho_{AR}) \right\|_1 \right), \end{aligned}$$

where id_R denotes the identity operator on $\mathcal{L}(R)$.

If $\dim(R) \geq \dim(A)$, the maximum of the trace norm is called the diamond norm.

Definition 9 (Diamond norm). Let $\Psi_{A \rightarrow B}$ be a linear operator from $L(A)$ to $L(B)$. The diamond norm of $\Psi_{A \rightarrow B}$ is then defined as

$$\|\Psi_{A \rightarrow B}\|_{\diamond} := \max_{\rho_{AR} \in \mathcal{D}(A \otimes R)} \|(\Psi_{A \rightarrow B} \otimes \text{id}_R)(\rho_{AR})\|_1,$$

for a quantum system R whose dimension is equal to $\dim(A)$.

An algorithm is said to be non-adaptive if it calls the oracle in parallel. In general, the minimum error probability of non-adaptive algorithms with n queries for discriminating two quantum channels is expressed as

$$\frac{1}{2} \left(1 - \left\| p_0 (\mathcal{O}_{A \rightarrow B}^0)^{\otimes n} - p_1 (\mathcal{O}_{A \rightarrow B}^1)^{\otimes n} \right\|_{\diamond} \right),$$

if $\dim(R) \geq \dim(A)^n$. Although the diamond norm $\|\Psi_{A \rightarrow B}\|_{\diamond}$ can be evaluated in polynomial time with respect to the dimensions of A and B via SDP [8], the dimension of $A^{\otimes n}$ is exponentially large, so that SDP does not give an efficient algorithm when n is large. For general adaptive algorithms, no simple formula expressing the minimum error probability is known even for the discrimination of two quantum channels.

IV. MAIN RESULTS

In this paper, we present four theorems on the lower bounds on the minimum error probability $p_{\text{err}}(n)$. The Stinespring representation $O_{A \rightarrow BE}$ of a quantum channel $\mathcal{O}_{A \rightarrow B}$ is a linear isometry from A to $B \otimes E$ satisfying

$$\mathcal{O}_{A \rightarrow B}(\rho_A) = \text{Tr}_E \left(O_{A \rightarrow BE} \rho_A O_{A \rightarrow BE}^{\dagger} \right),$$

for some quantum system E . Let $\mathcal{S}(A)$ be a set of state vectors on a quantum system A . We first show a lower bound of the error probability for QCGDP by using the Bures angle.

Theorem 1. Let $p_{\text{err}}(n)$ be the minimum error probability for QCGDP($\{p_{\xi}\}, \{\mathcal{O}_{A \rightarrow B}^{\xi}\}, \{C_{\eta}\}$) with n queries. For a quantum channel $\Psi_{AR \rightarrow BR}$ and $m \in \{0, 1, \dots, n\}$, $\theta_{\mathcal{A}}(\Psi_{AR \rightarrow BR})$ and θ_m are defined as

$$\begin{aligned} \theta_{\mathcal{A}}(\Psi_{AR \rightarrow BR}) &:= \arccos \min_{|\phi\rangle_{AR} \in \mathcal{S}(AR)} \sum_{\xi \in \Xi} p_{\xi} \\ &F \left(\mathcal{O}_{A \rightarrow B}^{\xi}(|\phi\rangle\langle\phi|_{AR}), \Psi_{AR \rightarrow BR}(|\phi\rangle\langle\phi|_{AR}) \right), \\ \theta_m &:= \arccos \sqrt{p_{\text{err}}(m)}. \end{aligned}$$

The following then holds:

$$p_{\text{err}}(n) \geq \cos^2((n-m)\theta_{\mathcal{A}}(\Psi_{AR \rightarrow BR}) + \theta_m),$$

for an arbitrary $\Psi_{AR \rightarrow BR}$ and m satisfying $(n-m)\theta_{\mathcal{A}}(\Psi_{AR \rightarrow BR}) + \theta_m \in [0, \pi/2]$.

Furthermore, if $\dim(R) \geq \dim(A)$, the following then holds:

$$\begin{aligned} \theta_{\mathcal{A}}(\Psi_{A \rightarrow B} \otimes \text{id}_R) &= \arccos \min_{\sigma_A \in \mathcal{D}(A)} \sum_{\xi \in \Xi} p_{\xi} \\ &\left\| \text{Tr}_B \left(O_{A \rightarrow BE}^{\xi} \sigma_A (V_{A \rightarrow BE})^{\dagger} \right) \right\|_1, \end{aligned}$$

where $O_{A \rightarrow BE}^{\xi}$ denotes the Stinespring representation of $\mathcal{O}_{A \rightarrow B}^{\xi}$ for $\xi \in \Xi$, and $V_{A \rightarrow BE}$ denotes the Stinespring representation of $\Psi_{A \rightarrow B}$.

We next show a lower bound of the error probability for QCGDP by using the trace distance.

Theorem 2. Let $p_{\text{err}}(n)$ be the minimum error probability for QCGDP($\{p_{\xi}\}, \{\mathcal{O}_{A \rightarrow B}^{\xi}\}, \{C_{\eta}\}$) with n queries. Let m and k be integers that satisfy $0 \leq m \leq k \leq n$. Let α_0 and α_1 be non-negative real numbers that satisfy $\alpha_0^{n-k} = \alpha_1^{k-m}$. For a quantum channel $\Psi_{AR \rightarrow BR}$, $\theta_{\diamond}^0(\Psi_{AR \rightarrow BR})$ and $\theta_{\diamond}^1(\Psi_{AR \rightarrow BR})$ are defined as

$$\begin{aligned} \theta_{\diamond}^0(\Psi_{AR \rightarrow BR}) &:= \max_{|\phi\rangle_{AR} \in \mathcal{S}(AR)} \sum_{\xi \in \Xi} p_{\xi} \\ &\frac{1}{2} \left\| (\mathcal{O}_{A \rightarrow B}^{\xi} - \alpha_0 \Psi_{AR \rightarrow BR})(|\phi\rangle\langle\phi|_{AR}) \right\|_1, \\ \theta_{\diamond}^1(\Psi_{AR \rightarrow BR}) &:= \max_{|\phi\rangle_{AR} \in \mathcal{S}(AR)} \sum_{\xi \in \Xi} p_{\xi} \\ &\frac{1}{2} \left\| (\alpha_1 \mathcal{O}_{A \rightarrow B}^{\xi} - \Psi_{AR \rightarrow BR})(|\phi\rangle\langle\phi|_{AR}) \right\|_1. \end{aligned}$$

The following then holds:

$$\begin{aligned} p_{\text{err}}(n) &\geq p_{\text{err}}(m) - \left(\sum_{i=0}^{n-k-1} \alpha_0^i \right) \theta_{\diamond}^0(\Psi_{AR \rightarrow BR}) \\ &\quad - \left(\sum_{i=0}^{k-m-1} \alpha_1^i \right) \theta_{\diamond}^1(\Psi_{AR \rightarrow BR}), \end{aligned}$$

for an arbitrary $\Psi_{AR \rightarrow BR}$, m , α_0 , α_1 , and k .

For the discrimination of two channels, we show another type of lower bound. The following is a lower bound based on the Bures angle.

Theorem 3. Let $p_{\text{err}}(n)$ be the minimum error probability for QCDP($\{p_0, p_1\}, \{\mathcal{O}_{A \rightarrow B}^0, \mathcal{O}_{A \rightarrow B}^1\}$) with n queries. Let $\tau_{\mathcal{A}}$ be

$$\begin{aligned} \tau_{\mathcal{A}} &:= \arccos \\ &\min_{|\phi\rangle_{AR} \in \mathcal{S}(AR)} F \left(\mathcal{O}_{A \rightarrow B}^0(|\phi\rangle\langle\phi|_{AR}), \mathcal{O}_{A \rightarrow B}^1(|\phi\rangle\langle\phi|_{AR}) \right). \end{aligned}$$

The following then holds:

$$p_{\text{err}}(n) \geq \frac{1}{2} \left(1 - \sqrt{1 - 4p_0 p_1 \cos^2(n\tau_{\mathcal{A}})} \right),$$

under the condition $n\tau_A \in [0, \pi/2]$. Furthermore, if both the quantum channels are unitary channels, then a non-adaptive algorithm exists that satisfies the equality.

Furthermore, if $\dim(R) \geq \dim(A)$, the following then holds:

$$\tau_A = \arccos \min_{\sigma_A \in \mathcal{D}(A)} \left\| \text{Tr}_B (O_{A \rightarrow BE}^1 \sigma_A (O_{A \rightarrow BE}^0)^\dagger) \right\|_1,$$

where $O_{A \rightarrow BE}^0$ and $O_{A \rightarrow BE}^1$ denote the Stinespring representations of $\mathcal{O}_{A \rightarrow B}^0$ and $\mathcal{O}_{A \rightarrow B}^1$, respectively.

Finally, we show a lower bound based on the trace distance for the discrimination of two quantum channels.

Theorem 4. Let $p_{\text{err}}(n)$ be the minimum error probability for QCDP($\{p_0, p_1\}, \{\mathcal{O}_{A \rightarrow B}^0, \mathcal{O}_{A \rightarrow B}^1\}$) with n queries. Let $k \in \{0, 1, \dots, n\}$ be an integer. Let α_0 and α_1 be non-negative real numbers that satisfy $p_0 \alpha_0^k = p_1 \alpha_1^{n-k}$. Let τ_\diamond^0 and τ_\diamond^1 be

$$\begin{aligned} \tau_\diamond^0 &:= \max_{|\phi\rangle_{AR}} \left\| (\mathcal{O}_{A \rightarrow B}^0 - \alpha_0 \mathcal{O}_{A \rightarrow B}^1) (|\phi\rangle\langle\phi|_{AR}) \right\|_1, \\ \tau_\diamond^1 &:= \max_{|\phi\rangle_{AR}} \left\| (\alpha_1 \mathcal{O}_{A \rightarrow B}^0 - \mathcal{O}_{A \rightarrow B}^1) (|\phi\rangle\langle\phi|_{AR}) \right\|_1. \end{aligned}$$

The following then holds:

$$p_{\text{err}}(n) \geq \frac{1}{2} \left[1 - p_0 \left(\sum_{i=0}^{k-1} \alpha_0^i \right) \tau_\diamond^0 - p_1 \left(\sum_{i=0}^{n-k-1} \alpha_1^i \right) \tau_\diamond^1 \right],$$

for arbitrary α_0, α_1 and, k .

Furthermore, if $\dim(R) \geq \dim(A)$, the following then holds:

$$\tau_\diamond^0 = \left\| \mathcal{O}_{A \rightarrow B}^0 - \alpha_0 \mathcal{O}_{A \rightarrow B}^1 \right\|_\diamond, \tau_\diamond^1 = \left\| \alpha_1 \mathcal{O}_{A \rightarrow B}^0 - \mathcal{O}_{A \rightarrow B}^1 \right\|_\diamond.$$

The proofs of Theorems 1, 2, 3, and 4 are presented in Section VI.

In Section VII, we show that all optimization problems on quantum states $|\psi\rangle_{AR}$ and σ_A in Theorems 1, 2, 3, and 4 can be written as SDP when $\dim(R) \geq \dim(A)$, so that the lower bounds can be evaluated efficiently.

V. APPLICATIONS

A. Application of Theorem 1: Grover's search problem

We prove the optimality of Grover's algorithm by using Theorem 1. Let A be an $|H|$ -dimensional quantum system, and $\{|\eta\rangle_A\}_{\eta \in H}$ be its computational basis. For some fixed $k \in \{1, 2, \dots, |H|/2\}$, $\Xi := \{\xi \subseteq H \mid |\xi| = k\}$. Let $\{O_A^\xi\}_{\xi \in \Xi}$ be a family of unitary operators defined as $O_A^\xi := I - 2 \sum_{u \in \xi} |u\rangle\langle u|_A$. Let $\{\mathcal{O}_A^\xi\}_{\xi \in \Xi}$ be a family of quantum channels defined as

$$\mathcal{O}_A^\xi(\rho_A) := O_A^\xi \rho_A O_A^{\xi\dagger}.$$

Let $\{C_\eta\}_{\eta \in H}$ be a family of subsets of Ξ defined as $C_\eta := \{\xi \in \Xi \mid \eta \in \xi\}$. The problem QCGDP($\{1/|\Xi|\}, \{\mathcal{O}_A^\xi\}, \{C_\eta\}$) is then called Grover's search problem. The following holds:

$$\begin{aligned} \frac{1}{|\Xi|} \sum_{\xi \in \Xi} O_A^\xi &= \binom{|H|}{k}^{-1} \left[\binom{|H|-1}{k} - \binom{|H|-1}{k-1} \right] I_A \\ &= \left(1 - \frac{2k}{|H|} \right) I_A. \end{aligned}$$

Hence, we obtain

$$\begin{aligned} \theta_A(\text{id}_A) &= \arccos \min_{|\phi\rangle_{AR}} \sum_{\xi \in \Xi} \frac{1}{|\Xi|} F \left(\mathcal{O}_A^\xi (|\phi\rangle\langle\phi|_{AR}), |\phi\rangle\langle\phi|_{AR} \right) \\ &= \arccos \min_{|\phi\rangle_{AR}} \sum_{\xi \in \Xi} \frac{1}{|\Xi|} \left| \langle \phi | O_A^\xi | \phi \rangle_{AR} \right| \\ &\leq \arccos \min_{|\phi\rangle_{AR}} \sum_{\xi \in \Xi} \frac{1}{|\Xi|} \left| \langle \phi | O_A^\xi | \phi \rangle_{AR} \right| \\ &= \arccos \left(1 - \frac{2k}{|H|} \right) \\ &= 2 \arcsin \sqrt{\frac{k}{|H|}}. \end{aligned}$$

Moreover, we obtain

$$\begin{aligned} \theta_0 &= \arccos \sqrt{1 - \max_{\eta \in H} \left(\sum_{\xi \in C_\eta} \frac{1}{|\Xi|} \right)} \\ &= \arcsin \sqrt{\max_{\eta \in H} \left(\sum_{\xi \in C_\eta} \frac{1}{|\Xi|} \right)} \\ &= \arcsin \sqrt{\binom{|H|-1}{k-1} \binom{|H|}{k}^{-1}} \\ &= \arcsin \sqrt{\frac{k}{|H|}}. \end{aligned}$$

Therefore, we obtain the lower bound

$$p_{\text{err}}(n) \geq \cos^2 \left((2n+1) \arcsin \sqrt{\frac{k}{|H|}} \right),$$

from Theorem 1 under the condition $(2n+1) \arcsin(\sqrt{k/|H|}) \in [0, \pi/2]$. This lower bound is achieved by Grover's algorithm [16] if $(2n+1) \arcsin(\sqrt{k/|H|}) \in [0, \pi/2]$ and by a modification of Grover's algorithm [17] otherwise. The lower bound for $k=1$ was obtained by Zalka [10].²

² Zalka wrote: "It seems very plausible that the proof can be extended to oracles with any known number of marked elements." However, no formal proof is known to the best of our knowledge.




FIG. 1. The lower bounds on the channel position finding for amplitude damping channels ($\ell = 3, n = 15, p_\xi = 1/\ell$ ($\xi \in \Xi$), $r_1 = r_0 + 0.01$); \bullet , the bound from Theorem 2; \times , the bound from [5].

B. Application of Theorem 2: Channel position finding for amplitude damping channels

We consider the discrimination of amplitude damping channels to demonstrate the lower bound given by Theorem 2.

Definition 10. The amplitude damping channel $\mathcal{E}_A^r(\rho_A)$ with damping rate $r \in [0, 1]$ is defined by the Stinespring representation

$$U_{A \rightarrow AE}^r := (|0\rangle\langle 0|_A + \sqrt{1-r}|1\rangle\langle 1|_A) \otimes |0\rangle_E \\ + (\sqrt{r}|0\rangle\langle 1|_A) \otimes |1\rangle_E.$$

In the following, we consider the channel position finding problem introduced in [5]. Let $\ell \geq 2$ be an integer. Let A_1, \dots, A_ℓ , and R be two-dimensional quantum systems. Let A' be the composite system of A_1, \dots, A_ℓ , i.e., $A' = \bigotimes_{i=1}^\ell A_i$. Let $\Xi := \{1, \dots, \ell\}$, and $r_0, r_1 \in [0, 1]$. For each $\xi \in \Xi$, a quantum channel $\mathcal{O}_{A'}^\xi$ is defined as

$$\mathcal{O}_{A'}^\xi := \left(\bigotimes_{i=1}^{\xi-1} \mathcal{E}_{A_i}^{r_0} \right) \otimes \mathcal{E}_{A_\xi}^{r_1} \otimes \left(\bigotimes_{i=\xi+1}^\ell \mathcal{E}_{A_i}^{r_0} \right).$$

We consider the channel discrimination problem QCDP($\{1/\ell\}, \{\mathcal{O}_{A'}^\xi\}$) using a working system $R' = R^{\otimes \ell}$. Let k be an integer that satisfies $0 \leq k \leq n$. Let α_0 and α_1 be non-negative real numbers that satisfy $\alpha_0^{n-k} = \alpha_1^k$. We then obtain

$$\left\| \mathcal{O}_{A'}^\xi - \alpha_0 \bigotimes_{i=1}^\ell \mathcal{E}_{A_i}^{r_0} \right\|_\diamond \\ = \left\| \left(\bigotimes_{i=1}^{\xi-1} \mathcal{E}_{A_i}^{r_0} \right) \otimes \left(\mathcal{E}_{A_\xi}^{r_1} - \alpha_0 \mathcal{E}_{A_\xi}^{r_0} \right) \otimes \left(\bigotimes_{i=\xi+1}^\ell \mathcal{E}_{A_i}^{r_0} \right) \right\|_\diamond$$




FIG. 2. The lower bounds on the channel position finding for amplitude damping channels ($\ell = 3, p_\xi = 1/\ell$ ($\xi \in \Xi$), $r_0 = 0.10, r_1 = 0.11$); \blacktriangle , the bound from Theorem 2 where $k = \lfloor n/2 \rfloor$; \bullet , the bound from Theorem 2 where k is optimal; \times , the bound from [5].

$$= \left(\prod_{i=1}^{\xi-1} \left\| \mathcal{E}_{A_i}^{r_0} \right\|_\diamond \right) \left\| \mathcal{E}_{A_\xi}^{r_1} - \alpha_0 \mathcal{E}_{A_\xi}^{r_0} \right\|_\diamond \left(\prod_{i=\xi+1}^\ell \left\| \mathcal{E}_{A_i}^{r_0} \right\|_\diamond \right) \\ = \left\| \mathcal{E}_{A'}^{r_1} - \alpha_0 \mathcal{E}_{A'}^{r_0} \right\|_\diamond.$$

The second equality follows from the multiplicativity of the diamond norm [15]. Hence, $\theta_\diamond^0 \left(\bigotimes_{i=1}^\ell \mathcal{E}_{A_i}^{r_0} \right)$ in Theorem 2 is bounded as

$$\theta_\diamond^0 \left(\bigotimes_{i=1}^\ell \mathcal{E}_{A_i}^{r_0} \right) \\ = \max_{\rho_{A'R'}} \sum_{\xi \in \Xi} \frac{1}{\ell} \cdot \frac{1}{2} \left\| \left(\mathcal{O}_{A'}^\xi - \alpha_0 \bigotimes_{i=1}^\ell \mathcal{E}_{A_i}^{r_0} \right) (\rho_{A'R'}) \right\|_1 \\ \leq \sum_{\xi \in \Xi} \frac{1}{\ell} \cdot \frac{1}{2} \left\| \mathcal{O}_{A'}^\xi - \alpha_0 \bigotimes_{i=1}^\ell \mathcal{E}_{A_i}^{r_0} \right\|_\diamond \\ = \frac{1}{2} \left\| \mathcal{E}_{A'}^{r_1} - \alpha_0 \mathcal{E}_{A'}^{r_0} \right\|_\diamond.$$

Note that $\rho_{A'R'} = (\arg\max_{\rho_{AR}} \|(\mathcal{E}_{A'}^{r_1} - \alpha_0 \mathcal{E}_{A'}^{r_0})(\rho_{AR})\|_1)^{\otimes \ell}$ satisfies the equality. Similarly, we obtain

$$\theta_\diamond^1 \left(\bigotimes_{i=1}^\ell \mathcal{E}_{A_i}^{r_0} \right) = \frac{1}{2} \left\| \alpha_1 \mathcal{E}_{A'}^{r_1} - \mathcal{E}_{A'}^{r_0} \right\|_\diamond.$$

From $p_{\text{err}}(0) = 1 - 1/\ell$, we obtain

$$p_{\text{err}}(n) \geq 1 - \frac{1}{\ell} - \left(\sum_{i=0}^{n-k-1} \frac{\alpha_0^i}{2} \right) \left\| \mathcal{E}_{A'}^{r_1} - \alpha_0 \mathcal{E}_{A'}^{r_0} \right\|_\diamond \\ - \left(\sum_{i=0}^{k-1} \frac{\alpha_1^i}{2} \right) \left\| \alpha_1 \mathcal{E}_{A'}^{r_1} - \mathcal{E}_{A'}^{r_0} \right\|_\diamond.$$

The numerical result for multiple amplitude damping channel discrimination is shown in Figs. 1 and 2. The distribution of the channels is uniform, i.e., $p_\xi = 1/\ell$ ($\xi \in \Xi$). The number of oracles is $\ell = 3$. In Fig. 1, the damping rates of the channels are r_0 and $r_1 = r_0 + 0.01$. The parameters α_0 and α_1 , are optimized to maximize the lower bound. In Fig. 1, the number of queries is $n = 15$. In Fig. 2, the damping rates of the channels are $r_0 = 0.10$ and $r_1 = 0.11$. Compared with a lower bound obtained by Zhuang and Pirandola [5], the lower bound given by Theorem 2 is better for all r_0 in Figs. 1 and for all n in Fig. 2.

C. Application of Theorems 3 and 4: Discrimination of two amplitude damping channels

Next, we derive a lower bound on the error probability of the discrimination of two amplitude damping channels by using Theorem 3. For $\text{QCDP}(\{p_0, p_1\}, \{\mathcal{E}_A^{r_0}, \mathcal{E}_A^{r_1}\})$, we obtain the following bound of τ_A in Theorem 3 with a two-dimensional working system R :

$$\begin{aligned} \tau_A &= \arccos \min_{\sigma_A} \left\| \text{Tr}_A(U_{A \rightarrow AE}^{r_1} \sigma_A (U_{A \rightarrow AE}^{r_0})^\dagger) \right\|_1 \\ &\leq \arccos \min_{\sigma_A} \left| \text{Tr}_{AE}(U_{A \rightarrow AE}^{r_1} \sigma_A (U_{A \rightarrow AE}^{r_0})^\dagger) \right|_1 \\ &= \arccos \min_{\sigma_A} \left| \langle 0 | \sigma_A | 0 \rangle_A \right. \\ &\quad \left. + \left(\sqrt{r_0 r_1} + \sqrt{(1-r_0)(1-r_1)} \right) \langle 1 | \sigma_A | 1 \rangle_A \right| \\ &= \arccos \left(\sqrt{r_0 r_1} + \sqrt{(1-r_0)(1-r_1)} \right). \end{aligned}$$

The inequality follows from the monotonicity of the trace norm (i.e., $\|\cdot\|_1 \geq |\text{Tr}(\cdot)|$). Note that $\sigma_A = |1\rangle\langle 1|_A$ satisfies the equality. Let the Bhattacharyya angle of r_0 and r_1 be $\Delta(r_0, r_1) := \arccos(\sqrt{r_0 r_1} + \sqrt{(1-r_0)(1-r_1)})$. We then obtain

$$p_{\text{err}}(n) \geq \frac{1}{2} \left(1 - \sqrt{1 - 4p_0 p_1 \cos^2(n\Delta(r_0, r_1))} \right)$$

under the condition $n\Delta(r_0, r_1) \in [0, \pi/2]$.

Next, we consider the lower bound obtained from Theorem 4. Let $k \in \{0, 1, \dots, n\}$ be an integer. Let α_0 and α_1 be non-negative real numbers that satisfy $p_0 \alpha_0^k = p_1 \alpha_1^{n-k}$. We then obtain

$$\begin{aligned} p_{\text{err}}(n) &\geq \frac{1}{2} \left[1 - p_0 \left(\sum_{i=0}^{k-1} \alpha_0^i \right) \|\mathcal{E}_A^{r_0} - \alpha_0 \mathcal{E}_A^{r_1}\|_\diamond \right. \\ &\quad \left. - p_1 \left(\sum_{i=0}^{n-k-1} \alpha_1^i \right) \|\alpha_1 \mathcal{E}_A^{r_0} - \mathcal{E}_A^{r_1}\|_\diamond \right]. \end{aligned}$$

The numerical results for two amplitude damping channel discrimination are shown in Figs. 3 and 4. In both the figures, the distribution of the channels is uniform, i.e., $p_0 = p_1 = 1/2$. The parameters α_0 and α_1 are optimized. In Fig. 3, the damping rates of the channels are r_0 and $r_1 = r_0 + 0.01$. The number of queries is




FIG. 3. The lower bounds of two amplitude damping channel discrimination ($p_0 = p_1 = 1/2, r_1 = r_0 + 0.01, n = 90$); continuous line, the bound from Theorem 3; \blacktriangle , the bound from Theorem 4 where $k = \lfloor n/2 \rfloor$; \bullet , the bound from Theorem 4 where k is optimal; $+$, the bound from [13].




FIG. 4. The lower bounds of two amplitude damping channel discrimination ($p_0 = p_1 = 1/2, r_0 = 0.10, r_1 = 0.11$); \blacklozenge , the bound from Theorem 3; \star , the bound from [4]; the other marks are the same as Fig. 3.

$n = 90$. In Fig. 4, the damping rates are $r_0 = 0.10$ and $r_1 = 0.11$. Compared with the lower bounds obtained by Pirandola et al. [4] and Pereira and Pirandola [13] (alternative resource lower bound, which is specific to the amplitude damping channel), the lower bound given by Theorems 3 and 4 are better for some r_0 in Fig. 3, and better for all n in Fig. 4. In Fig. 3, the lower bound from [4] is identically 0.

In the numerical results, we optimized α_0 for given k by the golden-section search because the function empirically has a single maximal point. We optimized k in an exhaustive way under the assumption that the optimum

k^* is non-decreasing with respect to r_0 and n .

VI. PROOFS OF THE THEOREMS

A. Proof of Theorem 1

Let $(\{\Phi_{BR \rightarrow AR}^k\}, \{M_{BR}^\eta\})$ be an algorithm with n queries that achieves the minimum error probability $p_{\text{err}}(n)$ of QCGDP $(\{p_\xi\}, \{\mathcal{O}_{A \rightarrow B}^\xi\}, \{C_\eta\})$. Let W be a two-dimensional quantum system. Quantum channels $\{\mathcal{M}_{BR \rightarrow W}^\xi\}_{\xi \in \Xi}$ are defined as

$$\begin{aligned} \mathcal{M}_{BR \rightarrow W}^\xi(\rho_{BR}) &:= \text{Tr} \left(\sum_{\eta: \xi \in C_\eta} M_{BR}^\eta \rho_{BR} \right) |1\rangle\langle 1|_W \\ &\quad + \text{Tr} \left(\sum_{\eta: \xi \notin C_\eta} M_{BR}^\eta \rho_{BR} \right) |0\rangle\langle 0|_W, \end{aligned}$$

for each $\xi \in \Xi$. Let $\Psi_{AR \rightarrow BR}$ be an arbitrary quantum channel. We define density operators as follows:

$$\begin{aligned} \rho_{BR}^i &:= \begin{cases} |0\rangle\langle 0|_{BR} & (i = 0), \\ \Psi_{AR \rightarrow BR} \circ \Phi_{BR \rightarrow AR}^i(\rho_{BR}^{i-1}) & (1 \leq i \leq n), \end{cases} \\ \rho_{BR}^{k,i,\xi} &:= \begin{cases} \rho_{BR}^i & (0 \leq k = i \leq n), \\ \mathcal{O}_{A \rightarrow B}^\xi \circ \Phi_{BR \rightarrow AR}^i(\rho_{BR}^{k,i-1,\xi}) & (0 \leq k < i \leq n), \end{cases} \\ \sigma_W^i &:= \sum_{\xi \in \Xi} p_\xi \mathcal{M}_{BR \rightarrow W}^\xi(\rho_{BR}^{n-i,n,\xi}) \quad (0 \leq i \leq n). \end{aligned}$$

By applying the triangle inequality for the Bures angle to a sequence of density operators $|1\rangle\langle 1|_W, \sigma_W^n, \sigma_W^{n-1}, \dots, \sigma_W^m, |0\rangle\langle 0|_W$, we obtain the following inequality:

$$\begin{aligned} \frac{\pi}{2} &= \mathcal{A}(|1\rangle\langle 1|_W, |0\rangle\langle 0|_W) \\ &\leq \mathcal{A}(|1\rangle\langle 1|_W, \sigma_W^n) + \sum_{i=m+1}^n \mathcal{A}(\sigma_W^i, \sigma_W^{i-1}) \\ &\quad + \mathcal{A}(\sigma_W^m, |0\rangle\langle 0|_W). \end{aligned}$$

Each term in the above inequality is evaluated as follows. For the first term of the right-hand side, we obtain

$$\begin{aligned} \mathcal{A}(|1\rangle\langle 1|_W, \sigma_W^n) &= \arccos \sqrt{\langle 1 | \sigma_W^n | 1 \rangle_W} \\ &= \arccos \sqrt{\sum_{\xi \in \Xi} p_\xi \sum_{\eta: \xi \in C_\eta} \text{Tr} \left(M_{BR}^\eta \rho_{BR}^{0,n,\xi} \right)} \\ &= \arccos \sqrt{1 - p_{\text{err}}(n)}. \end{aligned}$$

For the second term of the right-hand side, we obtain

$$\begin{aligned} \mathcal{A}(\sigma_W^i, \sigma_W^{i-1}) &= \arccos F \left(\sum_{\xi \in \Xi} p_\xi \mathcal{M}_{BR \rightarrow W}^\xi(\rho_{BR}^{n-i,n,\xi}), \right. \\ &\quad \left. \sum_{\xi \in \Xi} p_\xi \mathcal{M}_{BR \rightarrow W}^\xi(\rho_{BR}^{n-i+1,n,\xi}) \right) \\ &\leq \arccos \left(\sum_{\xi \in \Xi} p_\xi F \left(\mathcal{M}_{BR \rightarrow W}^\xi(\rho_{BR}^{n-i,n,\xi}), \right. \right. \\ &\quad \left. \left. \mathcal{M}_{BR \rightarrow W}^\xi(\rho_{BR}^{n-i+1,n,\xi}) \right) \right) \\ &\leq \arccos \left(\sum_{\xi \in \Xi} p_\xi F \left(\mathcal{O}_{A \rightarrow B}^\xi \circ \Phi_{BR \rightarrow AR}^{n-i+1}(\rho_{BR}^{n-i}), \right. \right. \\ &\quad \left. \left. \Psi_{AR \rightarrow BR} \circ \Phi_{BR \rightarrow AR}^{n-i+1}(\rho_{BR}^{n-i}) \right) \right) \\ &\leq \arccos \min_{\rho_{AR}} \sum_{\xi \in \Xi} p_\xi F \left(\mathcal{O}_{A \rightarrow B}^\xi(\rho_{AR}), \Psi_{AR \rightarrow BR}(\rho_{AR}) \right) \\ &= \arccos \min_{|\phi\rangle_{AR}} \sum_{\xi \in \Xi} p_\xi F \left(\mathcal{O}_{A \rightarrow B}^\xi(|\phi\rangle\langle\phi|_{AR}), \right. \\ &\quad \left. \Psi_{AR \rightarrow BR}(|\phi\rangle\langle\phi|_{AR}) = \theta_{\mathcal{A}}(\Psi_{AR \rightarrow BR}). \right) \end{aligned}$$

The first inequality and the second equality follow from the joint concavity of the fidelity. The second inequality follows from the monotonicity of the fidelity.

For the last term, we obtain

$$\begin{aligned} \mathcal{A}(\sigma_W^m, |0\rangle\langle 0|_W) &= \arccos \sqrt{\langle 0 | \sigma_W^m | 0 \rangle_W} \\ &= \arccos \sqrt{\sum_{\xi \in \Xi} p_\xi \sum_{\eta: \xi \notin C_\eta} \text{Tr} \left(M_{BR}^\eta \rho_{BR}^{n-m,n,\xi} \right)} \\ &\leq \arccos \sqrt{p_{\text{err}}(m)}. \end{aligned}$$

From the above inequalities, we obtain

$$\begin{aligned} \frac{\pi}{2} &\leq \arccos \sqrt{1 - p_{\text{err}}(n)} \\ &\quad + (n - m) \theta_{\mathcal{A}}(\Psi_{AR \rightarrow BR}) + \arccos \sqrt{p_{\text{err}}(m)}. \end{aligned}$$

Therefore, we obtain

$$\begin{aligned} 1 - p_{\text{err}}(n) &\leq \\ &= \cos^2 \left(\frac{\pi}{2} - (n - m) \theta_{\mathcal{A}}(\Psi_{AR \rightarrow BR}) - \arccos \sqrt{p_{\text{err}}(m)} \right) \\ &= \sin^2 \left((n - m) \theta_{\mathcal{A}}(\Psi_{AR \rightarrow BR}) + \theta_m \right), \end{aligned}$$

for $\Psi_{AR \rightarrow BR}$ and m satisfying $(n - m) \theta_{\mathcal{A}}(\Psi_{AR \rightarrow BR}) + \theta_m \in [0, \pi/2]$. Hence, we obtain Theorem 1.

Although $\theta_{\mathcal{A}}$ is represented using the minimum of the concave function, when $\dim(R) \geq \dim(A)$, $\theta_{\mathcal{A}}$ can be represented by the minimum of a convex function.

Lemma 1. Let $\mathcal{O}_{A \rightarrow B}^\xi$ and $\Psi_{A \rightarrow B}$ be quantum channels with the Stinespring representations $O_{A \rightarrow BE}^\xi$ and $V_{A \rightarrow BE}$, respectively. If $\dim(R) \geq \dim(A)$, the following holds:

$$\begin{aligned} & \min_{|\phi\rangle_{AR} \in \mathcal{S}(AR)} \sum_{\xi \in \Xi} p_\xi F \left(\mathcal{O}_{A \rightarrow B}^\xi (|\phi\rangle\langle\phi|_{AR}), \Psi_{A \rightarrow B} (|\phi\rangle\langle\phi|_{AR}) \right) \\ &= \min_{\sigma_A \in \mathcal{D}(A)} \sum_{\xi \in \Xi} p_\xi \left\| \text{Tr}_B \left(O_{A \rightarrow BE}^\xi \sigma_A (V_{A \rightarrow BE})^\dagger \right) \right\|_1. \end{aligned}$$

Proof. First, we introduce the following identity of the fidelity:

$$\begin{aligned} & F \left(\text{Tr}_E (|\psi^0\rangle\langle\psi^0|_{CE}), \text{Tr}_E (|\psi^1\rangle\langle\psi^1|_{CE}) \right) \\ &= \max_{U_E} |\langle\psi^1| U_E |\psi^0\rangle_{CE}| \\ &= \max_{U_E} |\text{Tr}_{CE} (U_E |\psi^0\rangle\langle\psi^1|_{CE})| \\ &= \max_{U_E} |\text{Tr}_E (U_E \text{Tr}_C (|\psi^0\rangle\langle\psi^1|_{CE}))| \\ &= \left\| \text{Tr}_C (|\psi^0\rangle\langle\psi^1|_{CE}) \right\|_1, \end{aligned}$$

where U_E is a unitary operator. The first equality follows from Uhlmann's theorem. The last equality follows from the duality of Schatten p -norm.

Let $|\hat{\phi}\rangle_{AR}$ be a state vector that achieves the minimum on the left-hand side. We then obtain

$$\begin{aligned} & \sum_{\xi \in \Xi} p_\xi F \left(\mathcal{O}_{A \rightarrow B}^\xi (|\hat{\phi}\rangle\langle\hat{\phi}|_{AR}), \Psi_{A \rightarrow B} (|\hat{\phi}\rangle\langle\hat{\phi}|_{AR}) \right) \\ &= \sum_{\xi \in \Xi} p_\xi \left\| \text{Tr}_{BR} \left(O_{A \rightarrow BE}^\xi |\hat{\phi}\rangle\langle\hat{\phi}|_{AR} (V_{A \rightarrow BE})^\dagger \right) \right\|_1 \\ &= \sum_{\xi \in \Xi} p_\xi \left\| \text{Tr}_B \left(O_{A \rightarrow BE}^\xi \text{Tr}_R (|\hat{\phi}\rangle\langle\hat{\phi}|_{AR}) (V_{A \rightarrow BE})^\dagger \right) \right\|_1 \\ &\geq \min_{\sigma_A} \sum_{\xi \in \Xi} p_\xi \left\| \text{Tr}_B \left(O_{A \rightarrow BE}^\xi \sigma_A (V_{A \rightarrow BE})^\dagger \right) \right\|_1. \end{aligned}$$

Next, let $\hat{\sigma}_A$ be a density operator that achieves the minimum on the right-hand side. There exists a purification $|\hat{\phi}\rangle_{AR}$ of $\hat{\sigma}_A$ because $\dim(R) \geq \dim(A)$. Therefore,

$$\begin{aligned} & \sum_{\xi \in \Xi} p_\xi \left\| \text{Tr}_B \left(O_{A \rightarrow BE}^\xi \hat{\sigma}_A (V_{A \rightarrow BE})^\dagger \right) \right\|_1 \\ &= \sum_{\xi \in \Xi} p_\xi \left\| \text{Tr}_B \left(O_{A \rightarrow BE}^\xi \text{Tr}_R (|\hat{\phi}\rangle\langle\hat{\phi}|_{AR}) (V_{A \rightarrow BE})^\dagger \right) \right\|_1 \\ &= \sum_{\xi \in \Xi} p_\xi F \left(\mathcal{O}_{A \rightarrow B}^\xi (|\hat{\phi}\rangle\langle\hat{\phi}|_{AR}), \Psi_{A \rightarrow B} (|\hat{\phi}\rangle\langle\hat{\phi}|_{AR}) \right) \\ &\geq \min_{|\phi\rangle_{AR}} \sum_{\xi \in \Xi} p_\xi F \left(\mathcal{O}_{A \rightarrow B}^\xi (|\phi\rangle\langle\phi|_{AR}), \Psi_{A \rightarrow B} (|\phi\rangle\langle\phi|_{AR}) \right). \end{aligned}$$

□




FIG. 5. Triangle inequality for the Euclidean distance.




FIG. 6. The shortcut method.

B. Proof of Theorem 2

The proof of Theorem 2 is in principle obtained from the proof of Theorem 1 by replacing the Bures angle with the trace distance. Another important trick is the introduction of “weights” of internal quantum states. We refer to this trick as the shortcut method. We first explain the intuition underlying the shortcut method. For pure states $|\psi\rangle\langle\psi|$ and $|\varphi\rangle\langle\varphi|$, the Bures angle and the trace distance are $\arccos |\langle\psi|\varphi\rangle|$ and $\sqrt{1 - |\langle\psi|\varphi\rangle|^2}$, respectively. If $|\psi\rangle$ and $|\varphi\rangle$ are both real vectors, the Bures angle and the trace distance are the angle between vectors $|\psi\rangle$ and $|\varphi\rangle$ and the Euclidean distance between vectors $|\psi\rangle$ and $|\varphi\rangle$ divided by $\sqrt{2}$, respectively. For unit vectors $|\psi_0\rangle$, $|\psi_1\rangle$, and $|\psi_2\rangle$, the triangle inequality for the Euclidean distance is not tight; i.e., $\| |\psi_0\rangle - |\psi_2\rangle \| < \| |\psi_0\rangle - |\psi_1\rangle \| + \| |\psi_1\rangle - |\psi_2\rangle \|$, where $\| \cdot \|$ denotes the Euclidean distance. This fact is depicted in Fig. 5. On the other hand, the triangle inequality for the angle may be saturated. This is the idea of Zalka [10]. To tighten the triangle inequality for the Euclidean distance (the trace distance), we introduce a weight r_1 of a vector $|\psi_1\rangle$. The triangle inequality $\| |\psi_0\rangle - |\psi_2\rangle \| \leq \| |\psi_0\rangle - r_1 |\psi_1\rangle \| + \| r_1 |\psi_1\rangle - |\psi_2\rangle \|$ may then be saturated if we choose $r_1 \in (0, 1]$ appropriately, as in Fig. 5.

Because there are $n - m - 1$ internal quantum states $\sigma_W^{n-1}, \dots, \sigma_W^{m+1}$, we have to determine $n - m - 1$ “weights” r_{n-1}, \dots, r_{m+1} , as in Fig. 6. Because the optimization of $n - m - 1$ parameters is computationally hard if n is large, we only use three parameters $\alpha_0, \alpha_1 \in (0, 1]$, and $k \in \{m, m + 1, \dots, n\}$ such that $\alpha_0^{n-k} = \alpha_1^{k-m}$, and assume that $r_{n-i} = \alpha_0^i$ if $i \leq n - k$ and $r_{m+i} = \alpha_1^i$ if $i \leq k - m - 1$. We then need to optimize only two parameters α_0 and k . Once the parameters are fixed, we can calculate the lower bound in a constant time with respect to the number n of queries.

We now present the proof of Theorem 2. In the same way as for the proof of Theorem 1, we obtain the following inequality:

$$\begin{aligned} 1 &= \frac{1}{2} \left\| |1\rangle\langle 1|_W - |0\rangle\langle 0|_W \right\|_1 \\ &\leq \frac{1}{2} \left\| |1\rangle\langle 1|_W - \sigma_W^n \right\|_1 \\ &\quad + \sum_{i=0}^{n-k-1} \frac{1}{2} \left\| \alpha_0^i \sigma_W^{n-i} - \alpha_0^{i+1} \sigma_W^{n-i-1} \right\|_1 \\ &\quad + \sum_{i=0}^{k-m-1} \frac{1}{2} \left\| \alpha_1^{i+1} \sigma_W^{m+i+1} - \alpha_1^i \sigma_W^{m+i} \right\|_1 \\ &\quad + \frac{1}{2} \left\| \sigma_W^m - |0\rangle\langle 0|_W \right\|_1. \end{aligned}$$

We used the condition $\alpha_0^{n-k} = \alpha_1^{k-m}$ in the above inequality. Each term on the right-hand side is evaluated as follows. For the first term, we obtain

$$\begin{aligned} &\frac{1}{2} \left\| |1\rangle\langle 1|_W - \sigma_W^n \right\|_1 \\ &= \sum_{\xi \in \Xi} p_\xi \sum_{\eta: \xi \notin C_\eta} \text{Tr} \left(M_{BR}^\eta \rho_{BR}^{n-m, n, \xi} \right) \\ &= p_{\text{err}}(n). \end{aligned}$$

For the second term, we obtain

$$\begin{aligned} &\sum_{i=0}^{n-k-1} \frac{1}{2} \left\| \alpha_0^i \sigma_W^{n-i} - \alpha_0^{i+1} \sigma_W^{n-i-1} \right\|_1 \\ &= \sum_{i=0}^{n-k-1} \frac{\alpha_0^i}{2} \left\| \sum_{\xi \in \Xi} p_\xi \mathcal{M}_{BR \rightarrow W}^\xi \left(\rho_{BR}^{i, n, \xi} \right) \right. \\ &\quad \left. - \alpha_0 \sum_{\xi \in \Xi} p_\xi \mathcal{M}_{BR \rightarrow W}^\xi \left(\rho_{BR}^{i+1, n, \xi} \right) \right\|_1 \\ &\leq \sum_{i=0}^{n-k-1} \frac{\alpha_0^i}{2} \sum_{\xi \in \Xi} p_\xi \left\| \mathcal{M}_{BR \rightarrow W}^\xi \left(\rho_{BR}^{i, n, \xi} \right) \right. \\ &\quad \left. - \alpha_0 \mathcal{M}_{BR \rightarrow W}^\xi \left(\rho_{BR}^{i+1, n, \xi} \right) \right\|_1 \end{aligned}$$

$$\begin{aligned} &\leq \sum_{i=0}^{n-k-1} \frac{\alpha_0^i}{2} \sum_{\xi \in \Xi} p_\xi \left\| \mathcal{O}_{A \rightarrow B}^\xi \circ \Phi_{BR \rightarrow AR}^{i+1} \left(\rho_{BR}^i \right) \right. \\ &\quad \left. - \alpha_0 \Psi_{AR \rightarrow BR} \circ \Phi_{BR \rightarrow AR}^{i+1} \left(\rho_{BR}^i \right) \right\|_1 \\ &\leq \sum_{i=0}^{n-k-1} \frac{\alpha_0^i}{2} \max_{\rho_{AR}} \sum_{\xi \in \Xi} p_\xi \left\| \left(\mathcal{O}_{A \rightarrow B}^\xi - \alpha_0 \Psi_{AR \rightarrow BR} \right) \left(\rho_{AR} \right) \right\|_1 \\ &= \sum_{i=0}^{n-k-1} \frac{\alpha_0^i}{2} \max_{|\phi\rangle_{AR}} \sum_{\xi \in \Xi} p_\xi \\ &\quad \left\| \left(\mathcal{O}_{A \rightarrow B}^\xi - \alpha_0 \Psi_{AR \rightarrow BR} \right) \left(|\phi\rangle\langle \phi|_{AR} \right) \right\|_1 \\ &= \sum_{i=0}^{n-k-1} \alpha_0^i \theta_\diamond^0(\Psi_{AR \rightarrow BR}). \end{aligned}$$

The first inequality and the second equality follows from the convexity of the trace distance. The second inequality follows from the monotonicity of the trace norm.

Similarly, we obtain

$$\begin{aligned} &\sum_{i=0}^{k-m-1} \frac{1}{2} \left\| \alpha_1^{i+1} \sigma_W^{m+i+1} - \alpha_1^i \sigma_W^{m+i} \right\|_1 \\ &\leq \sum_{i=0}^{k-m-1} \alpha_1^i \theta_\diamond^1(\Psi_{AR \rightarrow BR}). \end{aligned}$$

For the last term, we obtain

$$\begin{aligned} &\frac{1}{2} \left\| \sigma_W^m - |0\rangle\langle 0|_W \right\|_1 \\ &= \sum_{\xi \in \Xi} p_\xi \sum_{\eta: \xi \in C_\eta} \text{Tr} \left(M_{BR}^\eta \rho_{BR}^{n-m, n, \xi} \right) \\ &\leq 1 - p_{\text{err}}(m). \end{aligned}$$

From the above inequalities, we obtain

$$\begin{aligned} 1 &\leq p_{\text{err}}(n) + \sum_{i=0}^{n-k-1} \alpha_0^i \theta_\diamond^0(\Psi_{AR \rightarrow BR}) \\ &\quad + \sum_{i=0}^{k-m-1} \alpha_1^i \theta_\diamond^1(\Psi_{AR \rightarrow BR}) + 1 - p_{\text{err}}(m). \end{aligned}$$

This proves Theorem 1.

C. Proof of Theorem 3

The Fuchs–van de Graaf inequality $\|\rho_A^0 - \rho_A^1\|_1 \leq 2\sqrt{1 - F(\rho_A^0, \rho_A^1)}$ is useful for bounding the trace distance by the fidelity [18]. The following lemma is a minor generalization of the inequality.

Lemma 2. *Let a_0 and a_1 be non-negative real numbers. Let ρ_A^0 and ρ_A^1 be density operators. The following then holds:*

$$\|a_0 \rho_A^0 - a_1 \rho_A^1\|_1 \leq \sqrt{(a_0 + a_1)^2 - 4a_0 a_1 F(\rho_A^0, \rho_A^1)}.$$

The proof is given in Appendix B.

We prove Theorem 3 by using Proposition 1 and Lemma 2. Let $(\{\Phi_{BR \rightarrow AR}^i\}, \{M_{BR}^0, M_{BR}^1\})$ be an algorithm with n queries that achieves the minimum error probability $p_{\text{err}}(n)$ for QCDP $(\{p_0, p_1\}, \{\mathcal{O}_{A \rightarrow B}^0, \mathcal{O}_{A \rightarrow B}^1\})$. We define density operators as follows:

$$\rho_{BR}^{k,i} := \begin{cases} |0\rangle\langle 0|_{BR} & (k = i = 0), \\ \mathcal{O}_{A \rightarrow B}^1 \circ \Phi_{BR \rightarrow AR}^i(\rho_{BR}^{i-1, i-1}) & (1 \leq k = i < n), \\ \mathcal{O}_{A \rightarrow B}^0 \circ \Phi_{BR \rightarrow AR}^i(\rho_{BR}^{k, i-1}) & (0 \leq k < i \leq n). \end{cases}$$

We then obtain

$$\begin{aligned} & \mathcal{A}(\rho_{BR}^{0,n}, \rho_{BR}^{n,n}) \\ & \leq \sum_{i=0}^{n-1} \mathcal{A}(\rho_{BR}^{i,n}, \rho_{BR}^{i+1,n}) \\ & \leq \sum_{i=0}^{n-1} \mathcal{A}\left(\mathcal{O}_{A \rightarrow B}^0 \circ \Phi_{BR \rightarrow AR}^{i+1}(\rho_{BR}^{i,i}), \right. \\ & \quad \left. \mathcal{O}_{A \rightarrow B}^1 \circ \Phi_{BR \rightarrow AR}^{i+1}(\rho_{BR}^{i,i})\right) \\ & \leq \sum_{i=0}^{n-1} \arccos \min_{|\phi\rangle_{AR}} F(\mathcal{O}_{A \rightarrow B}^0(|\phi\rangle\langle\phi|_{AR}), \mathcal{O}_{A \rightarrow B}^1(|\phi\rangle\langle\phi|_{AR})) \\ & = n\tau_{\mathcal{A}}. \end{aligned}$$

The first inequality follows from the triangle inequality for the Bures angle. The second inequality follows from the monotonicity of the fidelity. The third inequality follows from the joint concavity of the fidelity. Hence, we obtain $F(\rho_{BR}^{0,n}, \rho_{BR}^{n,n}) \geq \cos(n\tau_{\mathcal{A}})$ under the condition $n\tau_{\mathcal{A}} \in [0, \pi/2]$. Therefore, we obtain

$$\begin{aligned} 1 - p_{\text{err}}(n) &= p_0 \text{Tr}(M_{BR}^0 \rho_{BR}^{0,n}) + p_1 \text{Tr}(M_{BR}^1 \rho_{BR}^{n,n}) \\ &= \frac{1}{2} \left(1 + \left\|p_0 \rho_{BR}^{0,n} - p_1 \rho_{BR}^{n,n}\right\|_1\right) \\ &\leq \frac{1}{2} \left(1 + \sqrt{1 - 4p_0 p_1 F(\rho_{BR}^{0,n}, \rho_{BR}^{n,n})^2}\right) \\ &\leq \frac{1}{2} \left(1 + \sqrt{1 - 4p_0 p_1 \cos^2(n\tau_{\mathcal{A}})}\right). \end{aligned}$$

The second equality follows from Proposition 1. The first inequality follows from Lemma 2. Hence, we obtain Theorem 3.

Kawachi et al. characterized the exact minimum error probability when the two quantum channels are both unitary channels, and the distribution of the oracle is uniform (i.e., $p_0 = p_1 = 0.5$) in [3]. Their lower bound can be reproduced from Theorem 3. The minimum error probability is represented by using the *covering angle*.

Definition 11 (Covering angle). Let $\arg_{\geq 0}(z) := \min\{\varphi \geq 0 \mid z = |z| \exp(i\varphi)\}$ for a complex number z . Let $\theta_1, \theta_2, \dots, \theta_n$ be real numbers and $\Theta :=$

$\{\exp(i\theta_1), \dots, \exp(i\theta_n)\}$. The covering angle θ_{cover} of Θ is defined as

$$\theta_{\text{cover}} := \min_{k \in \{1, \dots, n\}} \max_{\ell \in \{1, \dots, n\}} \arg_{\geq 0}(\exp(i(\theta_\ell - \theta_k))).$$

From Theorem 3 and an algorithm in [3], we obtain the following corollary.

Corollary 1. Let O_A^0, O_A^1 be unitary operators. Let $\mathcal{O}_A^0, \mathcal{O}_A^1$ be quantum channels that satisfy $\mathcal{O}_A^\xi(\rho_A) = O_A^\xi \rho_A O_A^{\xi\dagger}$ ($\xi \in \{0, 1\}$). Let $p_{\text{err}}(n)$ be the minimum error probability for QCDP $(\{p_0, p_1\}, \{\mathcal{O}_A^0, \mathcal{O}_A^1\})$ with n queries. Let θ_{cover} be the covering angle of the set of eigenvalues of an operator $O_A^{0\dagger} O_A^1$. The following then holds:

$$p_{\text{err}}(n) = \frac{1}{2} \left(1 - \sqrt{1 - 4p_0 p_1 \cos^2 \frac{n\theta_{\text{cover}}}{2}}\right),$$

under the condition $n\theta_{\text{cover}}/2 \in [0, \pi/2]$.

The lower bound is obtained from Lemma 2 and Theorem 3 with $\tau_{\mathcal{A}} = \theta_{\text{cover}}/2$ (see [3] for the details). The upper bound is obtained from Lemma 2 and the explicit non-adaptive algorithm in [3].

D. Proof of Theorem 4

In the same way as for the proof of Theorem 3, we obtain the following inequality:

$$\begin{aligned} & \left\|p_0 \rho_{BR}^{0,n} - p_1 \rho_{BR}^{n,n}\right\|_1 \\ & \leq \sum_{i=0}^{k-1} \left\|p_0 \alpha_0^i \rho_{BR}^{i,n} - p_0 \alpha_0^{i+1} \rho_{BR}^{i+1,n}\right\|_1 \\ & \quad + \sum_{i=0}^{n-k-1} \left\|p_1 \alpha_1^{i+1} \rho_{BR}^{n-i-1,n} - p_1 \alpha_1^i \rho_{BR}^{n-i,n}\right\|_1. \end{aligned}$$

We used the condition $p_0 \alpha_0^k = p_1 \alpha_1^{n-k}$ in the above inequality. For the first term of the right-hand side, we obtain

$$\begin{aligned} & \sum_{i=0}^{k-1} \left\|p_0 \alpha_0^i \rho_{BR}^{i,n} - p_0 \alpha_0^{i+1} \rho_{BR}^{i+1,n}\right\|_1 \\ & \leq \sum_{i=0}^{k-1} p_0 \alpha_0^i \left\|\mathcal{O}_{A \rightarrow B}^0 \circ \Phi_{BR \rightarrow AR}^{i+1}(\rho_{BR}^{i,i})\right. \\ & \quad \left. - \alpha_0 \mathcal{O}_{A \rightarrow B}^1 \circ \Phi_{BR \rightarrow AR}^{i+1}(\rho_{BR}^{i,i})\right\|_1 \\ & \leq \sum_{i=0}^{k-1} p_0 \alpha_0^i \max_{\rho_{AR}} \left\|(\mathcal{O}_{A \rightarrow B}^0 - \alpha_0 \mathcal{O}_{A \rightarrow B}^1)(\rho_{AR})\right\|_1 \\ & = \sum_{i=0}^{n-1} p_0 \alpha_0^i \max_{|\phi\rangle_{AR}} \left\|(\mathcal{O}_{A \rightarrow B}^0 - \alpha_0 \mathcal{O}_{A \rightarrow B}^1)(|\phi\rangle\langle\phi|_{AR})\right\|_1 \\ & = \sum_{i=0}^{n-1} p_0 \alpha_0^i \tau_{\diamond}^0. \end{aligned}$$

The first inequality follows from the monotonicity of the trace norm. The first equality follows from the convexity of the trace distance.

Similarly, we obtain

$$\sum_{i=0}^{n-k-1} \left\| p_1 \alpha_1^{i+1} \rho_{BR}^{n-i-1, n} - p_1 \alpha_1^i \rho_{BR}^{n-i, n} \right\|_1 \leq \sum_{i=0}^{n-k-1} p_1 \alpha_1^i \tau_\diamond^1.$$

Therefore, we obtain

$$\begin{aligned} & 1 - p_{\text{err}}(n) \\ &= p_0 \text{Tr} \left(M_{BR}^0 \rho_{BR}^{0, n} \right) + p_1 \text{Tr} \left(M_{BR}^1 \rho_{BR}^{n, n} \right) \\ &= \frac{1}{2} \left(1 + \left\| p_0 \rho_{BR}^{0, n} - p_1 \rho_{BR}^{n, n} \right\|_1 \right) \\ &\leq \frac{1}{2} \left(1 + \sum_{i=0}^{n-1} p_0 \alpha_0^i \tau_\diamond^0 + \sum_{i=0}^{n-k-1} p_1 \alpha_1^i \tau_\diamond^1 \right). \end{aligned}$$

The second equality follows from Proposition 1. This proves Theorem 4.

VII. OPTIMIZATION BY SEMIDEFINITE PROGRAMMING

In this section, we show that if $\dim(R) \geq \dim(A)$, all optimization problems in Theorems 1, 2, 3, and 4 can be written as SDPs, so that the evaluation will be efficient. The minimization of the trace norm $\|\text{Tr}_B(O_{A \rightarrow BE}^1 \sigma_A (O_{A \rightarrow BE}^0)^\dagger)\|_1$ in Theorem 3 can be formalized as the following SDP [19]:

$$\begin{aligned} & \min_{X_E, Y_E, Z_E, \sigma_A} : \frac{1}{2} \text{Tr}(Y_E) + \frac{1}{2} \text{Tr}(Z_E) \\ & \text{subject to: } \begin{cases} \begin{bmatrix} Y_E & X_E \\ X_E^\dagger & Z_E \end{bmatrix} \succeq 0 \\ X_E = \text{Tr}_B \left(O_{A \rightarrow BE}^1 \sigma_A (O_{A \rightarrow BE}^0)^\dagger \right) \\ \sigma_A \succeq 0, \quad \text{Tr}(\sigma_A) = 1. \end{cases} \end{aligned}$$

Similarly, the minimization of the average of the trace norms $\sum_{\xi \in \Xi} p_\xi \|\text{Tr}_B(O_{A \rightarrow BE}^\xi \sigma_A (V_{A \rightarrow BE})^\dagger)\|_1$ in Theorem 1 can be formalized as the following SDP:

$$\begin{aligned} & \min_{X_E^\xi, Y_E^\xi, Z_E^\xi, \sigma_A} : \frac{1}{2} \sum_{\xi \in \Xi} p_\xi \text{Tr} \left(Y_E^\xi + Z_E^\xi \right) \\ & \text{subject to: } \begin{cases} \begin{bmatrix} Y_E^\xi & X_E^\xi \\ (X_E^\xi)^\dagger & Z_E^\xi \end{bmatrix} \succeq 0 \quad (\forall \xi \in \Xi) \\ X_E^\xi = \text{Tr}_B \left(O_{A \rightarrow BE}^\xi \sigma_A (V_{A \rightarrow BE})^\dagger \right) (\forall \xi \in \Xi) \\ \sigma_A \succeq 0, \quad \text{Tr}(\sigma_A) = 1. \end{cases} \end{aligned}$$

For Theorems 2 and 4, we use Watrous's SDP [8, 15]. For the maximization problem in $\|\mathcal{O}_{A \rightarrow B}^0 - \alpha \mathcal{O}_{A \rightarrow B}^1\|_\diamond$, let $S_{A \rightarrow BE}$ and $T_{A \rightarrow BE}$ be linear maps defined by

$$(\mathcal{O}_{A \rightarrow B}^0 - \alpha \mathcal{O}_{A \rightarrow B}^1)(\rho_A) = \text{Tr}_E \left(S_{A \rightarrow BE} \rho_A T_{A \rightarrow BE}^\dagger \right).$$

It is known that $\|\mathcal{O}_{A \rightarrow B}^0 - \alpha \mathcal{O}_{A \rightarrow B}^1\|_\diamond$ in Theorem 4 is a solution of the following SDP [8, 15]:

$$\begin{aligned} & \max_{X_E, Y_E, Z_E, \sigma_A} : \frac{1}{2} \text{Tr}(X_E) + \frac{1}{2} \text{Tr}(X_E^\dagger) \\ & \text{subject to: } \begin{cases} \begin{bmatrix} Y_E & X_E \\ X_E^\dagger & Z_E \end{bmatrix} \succeq 0 \\ Y_E = \text{Tr}_B \left(S_{A \rightarrow BE} \sigma_A S_{A \rightarrow BE}^\dagger \right) \\ Z_E = \text{Tr}_B \left(T_{A \rightarrow BE} \sigma_A T_{A \rightarrow BE}^\dagger \right) \\ \sigma_A \succeq 0, \quad \text{Tr}(\sigma_A) = 1. \end{cases} \end{aligned}$$

Similarly, for Theorem 2,

$$\max_{|\phi\rangle_{AR}} \sum_{\xi \in \Xi} p_\xi \frac{1}{2} \left\| (\mathcal{O}_{A \rightarrow B}^\xi - \alpha \Psi_{A \rightarrow B} \otimes \text{id}_R)(|\phi\rangle\langle\phi|_{AR}) \right\|_1$$

can be represented as a solution of SDP. For $\xi \in \Xi$, let $S_{A \rightarrow BE}^\xi$ and $T_{A \rightarrow BE}^\xi$ be linear maps defined by

$$(\mathcal{O}_{A \rightarrow B}^\xi - \alpha \Psi_{A \rightarrow B})(\rho_A) = \text{Tr}_E \left(S_{A \rightarrow BE}^\xi \rho_A \left(T_{A \rightarrow BE}^\xi \right)^\dagger \right).$$

Similarly to the above case, $2\theta_\diamond^\alpha(\Psi_{A \rightarrow B} \otimes \text{id}_R)$ is a solution of the following SDP:

$$\begin{aligned} & \max_{X_E^\xi, Y_E^\xi, Z_E^\xi, \sigma_A} : \frac{1}{2} \sum_{\xi \in \Xi} p_\xi \text{Tr} \left(X_E^\xi + (X_E^\xi)^\dagger \right) \\ & \text{subject to: } \begin{cases} \begin{bmatrix} Y_E^\xi & X_E^\xi \\ (X_E^\xi)^\dagger & Z_E^\xi \end{bmatrix} \succeq 0 \quad (\xi \in \Xi) \\ Y_E^\xi = \text{Tr}_B \left(S_{A \rightarrow BE}^\xi \sigma_A \left(S_{A \rightarrow BE}^\xi \right)^\dagger \right) (\xi \in \Xi) \\ Z_E^\xi = \text{Tr}_B \left(T_{A \rightarrow BE}^\xi \sigma_A \left(T_{A \rightarrow BE}^\xi \right)^\dagger \right) (\xi \in \Xi) \\ \sigma_A \succeq 0, \quad \text{Tr}(\sigma_A) = 1. \end{cases} \end{aligned}$$

VIII. CONCLUDING REMARKS

In this study, we derive lower bounds on the error probability of quantum channel group discrimination on the basis of the triangle inequalities for the Bures angle and the trace distance.

The minimum of the fidelity in Theorem 3

$$\min_{|\phi\rangle_{AR} \in \mathcal{S}(AR)} F \left(\mathcal{O}_{A \rightarrow B}^0(|\phi\rangle\langle\phi|_{AR}), \mathcal{O}_{A \rightarrow B}^1(|\phi\rangle\langle\phi|_{AR}) \right)$$

is referred to as the stabilized process fidelity in [20].

In the lower bounds in Theorems 2 and 4, we restricted the sequence of weights to a geometric sequence. Obviously, this restriction makes the lower bounds suboptimal because in the simplest case in Fig. 6, the sequence of the weights for the state vectors is

1, $\frac{\cos \theta}{\cos(2\theta/n)}$, $\frac{\cos \theta}{\cos(2\theta/(n-2))}$, \dots , where θ is half the angle between the first vector and the last vector. We choose geometric sequences just for the efficiency of evaluation of the lower bounds. For small n , we may treat each weight as an independent parameter. By optimizing these weights, we would obtain better lower bounds. Hence, there is a trade-off between the efficiency and the accuracy of the lower bounds based on the trace distance.

The optimization of quantum channel $\Psi_{AR \rightarrow BR}$ in Theorems 1 and 2 is an interesting open problem. Even on the restriction $\Psi_{AR \rightarrow BR} = \Psi_{A \rightarrow B} \otimes \text{id}_R$, we do not have a method to optimize the quantum channel $\Psi_{A \rightarrow B}$.

In this work, we used the Bures angle and the trace distance as distance measures for quantum states. It would be interesting to investigate if other distance measures exist that yield tighter and/or efficiently computable lower bounds.

ACKNOWLEDGMENTS

This work was supported by JST PRESTO Grant Number JPMJPR1867 and JSPS KAKENHI Grant Numbers JP17K17711, JP18H04090, JP20H04138, and JP20H05966. We would like to thank Editage (www.editage.com) for English language editing.

Appendix A: Triangle inequalities for the Bures distance and the sine distance

In this appendix, we show the triangle inequalities for the Bures distance and the sine distance from the triangle inequality for the Bures angle. For arbitrary quantum states $\rho_A, \sigma_A, \tau_A \in \mathcal{D}(A)$, the Bures angle satisfies the triangle inequality

$$\mathcal{A}(\rho_A, \sigma_A) \leq \mathcal{A}(\rho_A, \tau_A) + \mathcal{A}(\tau_A, \sigma_A).$$

Then,

$$\begin{aligned} \mathcal{B}(\rho_A, \sigma_A) &= 2 \sin \left(\frac{\mathcal{A}(\rho_A, \sigma_A)}{2} \right) \\ &\leq 2 \sin \left(\frac{\mathcal{A}(\rho_A, \tau_A) + \mathcal{A}(\tau_A, \sigma_A)}{2} \right) \end{aligned}$$

because the sine function is monotonically increasing in $[0, \pi/2]$. From the trigonometric addition formula,

$$\begin{aligned} &2 \sin \left(\frac{\mathcal{A}(\rho_A, \tau_A) + \mathcal{A}(\tau_A, \sigma_A)}{2} \right) \\ &= 2 \sin \left(\frac{\mathcal{A}(\rho_A, \tau_A)}{2} \right) \cos \left(\frac{\mathcal{A}(\tau_A, \sigma_A)}{2} \right) \\ &\quad + 2 \sin \left(\frac{\mathcal{A}(\tau_A, \sigma_A)}{2} \right) \cos \left(\frac{\mathcal{A}(\rho_A, \tau_A)}{2} \right) \\ &\leq 2 \sin \left(\frac{\mathcal{A}(\rho_A, \tau_A)}{2} \right) + 2 \sin \left(\frac{\mathcal{A}(\tau_A, \sigma_A)}{2} \right). \end{aligned}$$

This proves the triangle inequality for the Bures distance.

The triangle inequality for the sine distance

$$\sin(\mathcal{A}(\rho_A, \sigma_A)) \leq \sin(\mathcal{A}(\rho_A, \tau_A)) + \sin(\mathcal{A}(\tau_A, \sigma_A))$$

can be obtained in the same way if $\mathcal{A}(\rho_A, \tau_A) + \mathcal{A}(\tau_A, \sigma_A) \leq \frac{\pi}{2}$. If $\mathcal{A}(\rho_A, \tau_A) + \mathcal{A}(\tau_A, \sigma_A) > \frac{\pi}{2}$, the triangle inequality is obtained from

$$\begin{aligned} &\sin(\mathcal{A}(\rho_A, \tau_A)) + \sin(\mathcal{A}(\tau_A, \sigma_A)) \\ &\geq \frac{2}{\pi} (\mathcal{A}(\rho_A, \tau_A) + \mathcal{A}(\tau_A, \sigma_A)) > 1. \end{aligned}$$

Appendix B: Proof of Lemma 2

The following proof is a generalization of the proof of Fuchs–van de Graaf inequality in [15]. From Uhlmann's theorem, there exist pure states $|\phi^0\rangle_{AR}, |\phi^1\rangle_{AR}$ satisfying the equalities $\text{Tr}_R(|\phi^0\rangle\langle\phi^0|_{AR}) = \rho_A^0$, $\text{Tr}_R(|\phi^1\rangle\langle\phi^1|_{AR}) = \rho_A^1$, and $|\langle\phi^0|\phi^1\rangle_{AR}| = F(\rho_A^0, \rho_A^1)$. Therefore, we obtain

$$\begin{aligned} &\|a_0\rho_A^0 - a_1\rho_A^1\|_1 \\ &= \|a_0\text{Tr}_R(|\phi^0\rangle\langle\phi^0|_{AR}) - a_1\text{Tr}_R(|\phi^1\rangle\langle\phi^1|_{AR})\|_1 \\ &\leq \|a_0|\phi^0\rangle\langle\phi^0|_{AR} - a_1|\phi^1\rangle\langle\phi^1|_{AR}\|_1 \\ &= \sqrt{(a_0 + a_1)^2 - 4a_0a_1|\langle\phi^0|\phi^1\rangle_{AR}|^2} \\ &= \sqrt{(a_0 + a_1)^2 - 4a_0a_1F(\rho_A^0, \rho_A^1)^2}. \end{aligned}$$

The inequality follows from the monotonicity of the trace norm.

-
- [1] A. Harrow, A. Hassidim, D. Leung, and J. Watrous, Phys. Rev. A **81**, 032339 (2010).
[2] R. Duan, Y. Feng, and M. Ying, Phys. Rev. Lett. **103**, 210501 (2009).
[3] A. Kawachi, K. Kawano, F. Le Gall, and S. Tamaki, IE-ICE Trans. Inf. & Syst. **102**, 483 (2019).
[4] S. Pirandola, R. Laurenza, C. Lupo, and J. L. Pereira, NPJ Quantum Inf. **5**, 1 (2019).
[5] Q. Zhuang and S. Pirandola, Phys. Rev. Lett. **125**, 080505 (2020).
[6] C. W. Helstrom, Inf. Control. **10**, 254 (1967).
[7] A. S. Holevo, Tr. Mosk. Mat. Obs. **26**, 133 (1972).
[8] J. Watrous, Chic. J. Theoret. Comput. Sci. **2013** (2013).
[9] C. H. Bennett, E. Bernstein, G. Brassard, and U. Vazirani, SIAM J. Comput. **26**, 1510 (1997).
[10] C. Zalka, Phys. Rev. A **60**, 2746 (1999).

- [11] K. Nakahira and K. Kato, Phys. Rev. Lett. **126**, 200502 (2021).
- [12] M. Boyer, G. Brassard, P. Høyer, and A. Tapp, Fortschr. Phys. **46**, 493 (1998).
- [13] J. L. Pereira and S. Pirandola, Phys. Rev. A **103**, 022610 (2021).
- [14] M. A. Nielsen and I. L. Chuang, *Quantum Computation and Quantum Information: 10th Anniversary Edition* (Cambridge University Press, 2010).
- [15] J. Watrous, *The Theory of Quantum Information* (Cambridge University Press, 2018).
- [16] L. K. Grover, in *Proceedings of the Twenty-Eighth Annual ACM Symposium on Theory of Computing*, edited by G. L. Miller (Association for Computing Machinery, New York, 1996) p. 212.
- [17] G. Brassard, P. Høyer, M. Mosca, and A. Tapp, Contemp. Math. **305**, 53 (2002).
- [18] C. A. Fuchs and J. van de Graaf, IEEE Trans. Inf. Theory **45**, 1216 (1999).
- [19] M. Fazel, H. Hindi, and S. P. Boyd, in *Proceedings of the 2001 American Control Conference. (Cat. No. 01CH37148)*, Vol. 6, edited by B. H. Krogh (IEEE, 2001) pp. 4734–4739.
- [20] A. Gilchrist, N. K. Langford, and M. A. Nielsen, Phys. Rev. A **71**, 062310 (2005).