

Convergence of Batch Asynchronous Stochastic Approximation With Applications to Reinforcement Learning

Rajeeva L. Karandikar and M. Vidyasagar *

September 9, 2021

Abstract

The stochastic approximation (SA) algorithm is a widely used probabilistic method for finding a solution to an equation of the form $\mathbf{f}(\boldsymbol{\theta}) = \mathbf{0}$ where $\mathbf{f} : \mathbb{R}^d \rightarrow \mathbb{R}^d$, when only noisy measurements of $\mathbf{f}(\cdot)$ are available. In the literature to date, one can make a distinction between “synchronous” updating, whereby the entire vector of the current guess $\boldsymbol{\theta}_t$ is updated at each time, and “asynchronous” updating, whereby only one component of $\boldsymbol{\theta}_t$ is updated. In convex and nonconvex optimization, there is also the notion of “batch” updating, whereby some but not all components of $\boldsymbol{\theta}_t$ are updated at each time t . In addition, there is also a distinction between using a “local” clock versus a “global” clock. In the literature to date, convergence proofs when a local clock is used make the assumption that the measurement noise is an i.i.d sequence, an assumption that does not hold in Reinforcement Learning (RL).

In this note, we provide a general theory of convergence for batch asynchronous stochastic approximation (BASA), that works whether the updates use a local clock or a global clock, for the case where the measurement noises form a martingale difference sequence. This is the most general result to date and encompasses all others.

1 Introduction

The stochastic approximation algorithm is a widely used probabilistic method for finding a solution to an equation of the form $\mathbf{f}(\boldsymbol{\theta}) = \mathbf{0}$ where $\mathbf{f} : \mathbb{R}^d \rightarrow \mathbb{R}^d$, when only noisy measurements of $\mathbf{f}(\cdot)$ are available. This method was first introduced in [3] for the case where $d = 1$. Subsequent research has extended the approach to the multi-dimensional case ($d > 1$). In this case, one can make two distinctions. The first distinction is between **synchronous** updating, whereby at each time t *every component* of the current guess $\boldsymbol{\theta}_t$, versus updating *only one component* at each time t . The latter is referred to as **asynchronous stochastic approximation**, a term apparently first introduced in [4]. The second distinction is between using a “local” clock versus using a “global” clock to determine the step size at each update. In this distinction, if one chooses the step size at time t to equal a constant α_t , then this would be called a global clock. In contrast, if the step size equals $\alpha_{N(i)}$, where $N(i)$ is the number of times that the i -th coordinate of $\boldsymbol{\theta}_t$ has been updated earlier, then this would be called a local clock. It appears that this distinction was first introduced in [1].

In the literature to date, the convergence of the iterates $\{\boldsymbol{\theta}_t\}$ to a solution of $\mathbf{f}(\boldsymbol{\theta}) = \mathbf{0}$ is established under various conditions. In [4], the author assumes that the function \mathbf{f} either satisfies

*RLK is Professor Emeritus at the Chennai Mathematical Institute. MV is SERB National Science Chair and Distinguished Professor, Indian Institute of Technology Hyderabad, Kandi, Talangana 502284, INDIA. Emails: rlk@cmi.ac.in, m.vidyasagar@iith.ac.in. This research is supported by the Science and Engineering Research Board (SERB), India.

a monotonicity condition, or else is a global contraction with respect to the ℓ_∞ -norm. The updating rule in [4] uses a global clock. In [1], the updating rule uses a local clock. However, the price paid for this is that the measurement noise sequence is assumed to be zero-mean i.i.d. In contrast, most papers on stochastic approximation require the noise only to be a martingale difference sequence, and not necessarily zero-mean i.i.d. In recent times, with the use of probabilistic methods for convex and nonconvex optimization, an “intermediate” variant has been studied, which goes under the name “batch stochastic gradient descent.” Among other things, in this approach, more than one but not all d components of θ_t are updated at each time t . There is relatively little theory to cover this situation.

In this paper, we present a unified theory for batch asynchronous stochastic approximation (BASA). For the moment, we do not incorporate delays in the measurements, as in [4, 1]. However, this is an easy extension, and we intend to include this extension in the next version of the paper. We also plan to use BASA as a unifying theme to explain various widely used algorithms in Reinforcement Learning (RL), such as Temporal Difference ($TD(0)$), and Q -learning.

2 Convergence of Asynchronous Stochastic Approximation

In this section, we state and prove the main result on the convergence of asynchronous stochastic approximation. We permit the use of both global as well as local clocks. In contrast with [1], we permit the noise sequence to be a martingale difference sequence, which need not be i.i.d. The proof is somewhat simpler than that in [4], though it broadly follows the same lines. Also, we permit “batch” updating, whereby, at each time instant, more than one component can be updated. This is not permitted in either of the above papers.

Throughout we consider vectors $\theta_t \in \mathbb{R}^d$ where d is fixed. We use $\theta_{t,i}$ to denote the i -th component of θ , which belongs to \mathbb{R} . $\|\theta\|_\infty$ is the ℓ_∞ -norm of θ . For $s \leq t$, θ_s^t denotes $(\theta_s, \dots, \theta_t)$. Note that

$$\|\theta_s^t\|_\infty = \max_{s \leq \tau \leq t} \|\theta_\tau\|_\infty.$$

We use \mathbb{N} for the set of natural numbers plus zero, so that $\mathbb{N} = \{0, 1, \dots\}$. If $\{\mathcal{F}_t\}$ is a filtration with $t \in \mathbb{N}$ (that is, an increasing sequence of σ -algebras, then $\mathcal{M}(\mathcal{F}_t)$ denotes the set of functions that are measurable with respect to \mathcal{F}_t . The symbol $[d]$ denotes the set $\{1, \dots, d\}$.

The objective is to compute the fixed point of a map $\mathbf{g} : \mathbb{R}^d \rightarrow \mathbb{R}^d$ which is a contraction in the ℓ_∞ -norm. The results of Gladyshev [2] do not apply to this case. (They apply only when \mathbf{g} is a contraction with respect to the ℓ_2 -norm, which is in general not true in problems of RL.)

The proof is divided into two parts. In the first, it is shown that iterations using a very general updating rule are bounded almost surely. This result would appear to be of independent interest; it is referred to as “stability” by some authors. Then this result is applied to show convergence of the iterations to a fixed point of a contractive map. In contrast with both [4] and [1], for the moment we do not permit delayed information. This will be done in the next version of the paper.

For the first theorem on almost sure boundedness, we set up the problem as follows: We consider a function $\mathbf{h} : \mathbb{N} \times (\mathbb{R}^d)^\mathbb{N} \rightarrow (\mathbb{R}^d)^\mathbb{N}$, and say that it is **nonanticipative** if, for each $t \in \mathbb{N}$,

$$\theta_0^\infty, \phi_0^\infty \in (\mathbb{R}^d)^\mathbb{N}, \theta_0^t = \phi_0^t \implies \mathbf{h}(\tau, \theta_0^\infty) = \mathbf{h}(\tau, \phi_0^\infty), 0 \leq \tau \leq t.$$

Note that such functions are also referred to as “causal” in control and system theory. There are also d distinct “update processes” $\{\nu_{t,i}\}_{t \geq 0}$ for each $i \in [d]$. Finally, there is a “step size” sequence $\{\beta_t\}_{t \geq 0}$, which for convenience we take to be deterministic, though this is not essential. Also, it is assumed that $\beta_t \in (0, 1)$ for all t .

The “core” stochastic processes are the parameter sequence $\{\boldsymbol{\theta}_t\}_{t \geq 0}$, and the noise sequence $\{\boldsymbol{\xi}_t\}_{t \geq 1}$. Note the mismatch in the initial values of t . Often it is assumed that $\boldsymbol{\theta}_0$ is deterministic, but this is not essential. We define the filtration

$$\mathcal{F}_0 = \sigma(\boldsymbol{\theta}_0), \mathcal{F}_t = \sigma(\boldsymbol{\theta}_0^t, \boldsymbol{\xi}_1^t) \text{ for } t \geq 1,$$

where $\sigma(\cdot)$ denotes the σ -algebra generated by the random variables inside the parentheses.

Now we can begin to state the problem set-up.

- (U1). The update processes $\nu_{t,i} \in \mathcal{M}(\mathcal{F}_t)$ for all $t \geq 0, i \in [d]$.
- (U2.) The update processes satisfy the conditions that $\nu_{0,i}$ equals either 0 or 1, and that $\nu_{t,i}$ equals either $\nu_{t-1,i}$ or $\nu_{t-1,i} + 1$. In other words, the process can only increment by at most one at each time instant t , for each index i . This automatically guarantees that $\nu_{t,i} \leq t$ for all $i \in [d]$.
- (S1). For “batch asynchronous updating” with a “global clock,” the step size $\alpha_{t,i}$ for each index i is defined as

$$\alpha_{t,i} = \begin{cases} \beta_t & \text{if } \nu_{t,i} = \nu_{t-1,i} + 1, \\ 0, & \text{if } \nu_{t,i} = \nu_{t-1,i}. \end{cases} \quad (1)$$

Therefore $\alpha_{t,i}$ equals β_t for those indices i that get incremented at time t , and zero for other indices.

- (S2.) For “batch asynchronous updating” with a “local clock,” the step size $\alpha_{t,i}$ for each index i is defined as

$$\alpha_{t,i} = \begin{cases} \beta_{\nu_{t,i}} & \text{if } \nu_{t,i} = \nu_{t-1,i} + 1, \\ 0, & \text{if } \nu_{t,i} = \nu_{t-1,i}. \end{cases} \quad (2)$$

Note that, with a local clock, we can also write

$$\alpha_{t,i} = \nu_{0,i} + \sum_{\tau=1}^t I_{\{\nu_{\tau,i} = \nu_{\tau-1,i} + 1\}}, \quad (3)$$

where I denotes the indicator function: It equals 1 if the subscripted statement is true, and equals 0 otherwise. Note that with a global clock, the step size for each index that has a nonzero $\alpha_{t,i}$ is the same, namely β_t . However, with a local clock, this is not necessarily true.

With this set-up, we can define the basic asynchronous iteration scheme.

$$\theta_{t+1,i} = \theta_{t,i} + \alpha_{t,i}(\eta_{t,i} - \theta_{t,i} + \xi_{t+1,i}), i \in [d], t \geq 0, \quad (4)$$

where

$$\boldsymbol{\eta}_t = \mathbf{h}(t, \boldsymbol{\theta}_0^t). \quad (5)$$

Note that in our view it makes no sense to define

$$\eta_{t,i} = h_i(\nu_{t,i}, \boldsymbol{\theta}_0^{\nu_{t,i}}).$$

We cannot think of any application for such an updating rule.

The question under study in the first part of the paper is the almost sure boundedness of the iterations $\{\boldsymbol{\theta}_t\}$. For this purpose we introduce a few assumptions.

(A1.) There exist constants $\gamma < 1$ and $c_0 \geq 0$ such that

$$\|\mathbf{h}(t, \boldsymbol{\theta}_0^t) - \mathbf{h}(t, \boldsymbol{\phi}_0^t)\|_\infty \leq \gamma \|\boldsymbol{\theta}_0^t - \boldsymbol{\phi}_0^t\|_\infty, \forall \boldsymbol{\theta}, \boldsymbol{\phi} \in (\mathbb{R}^d)^\mathbb{N}, t \geq 0, \quad (6)$$

$$\|\mathbf{h}(t, \mathbf{0})\|_\infty \leq c_0, \forall t \geq 0. \quad (7)$$

Note that in (9), we use the generic symbol $\mathbf{0}$ to denote a vector with all zero components, whose dimension is determined by the context. If we choose any $\rho \in (\gamma, 1)$ and define

$$c_1 := \frac{c_0}{\rho - \gamma}, \quad (8)$$

then it is easy to verify that

$$\|\mathbf{h}(t, \boldsymbol{\theta}_0^t)\|_\infty \leq \rho \max\{c_1, \|\boldsymbol{\theta}_0^t\|_\infty\}, \forall \boldsymbol{\theta}, t. \quad (9)$$

(A2.) The step sizes $\alpha_{t,i}$ satisfy the analogs of the Robbins-Monro conditions of [3], namely

$$\sum_{t=0}^{\infty} \alpha_{t,i} = \infty \text{ a.s.}, \forall i \in [d], \quad (10)$$

$$\sum_{t=0}^{\infty} \alpha_{t,i}^2 < \infty \text{ a.s.}, \forall i \in [d]. \quad (11)$$

Note that if $\sum_{t=0}^{\infty} \beta_t^2 < \infty$, then the square-summability of the $\alpha_{t,i}$ is automatic. However, the divergence of the summation of $\alpha_{t,i}$ requires additional conditions on both the step sizes β_t and the update processes $\nu_{t,i}$.

(A3.) The noise process $\{\boldsymbol{\xi}_t\}$ satisfies the following:

$$E(\xi_{t+1,i} | \mathcal{F}_t) = 0, \forall t \geq 0, i \in [d], \quad (12)$$

$$E(\xi_{t+1}^2 | \mathcal{F}_t) \leq c_2(1 + \|\boldsymbol{\theta}_t\|_2^2), \quad (13)$$

for some constant c_2 .

Now we can state the result on the almost sure boundedness of the iterates.

Theorem 1. *With the set up above, and subject to assumptions (A1), (A2) and (A3), we have that the sequence $\{\boldsymbol{\theta}_t\}$ is bounded almost surely.*

Next, we state a result on convergence. For this purpose, we significantly reduce the generality of the function $\mathbf{h}(\cdot)$.

Theorem 2. *Suppose that, in addition to the conditions of Theorem 1, we have that the function $\mathbf{h}(\cdot)$ is defined by*

$$\mathbf{h}(t, \boldsymbol{\theta}_0^t) = \mathbf{g}(\boldsymbol{\theta}_t),$$

where the function $\mathbf{g} : \mathbb{R}^d \rightarrow \mathbb{R}^d$ satisfies

$$|g_i(\boldsymbol{\theta}) - g_i(\boldsymbol{\phi})| \leq \gamma \|\boldsymbol{\theta} - \boldsymbol{\phi}\|_\infty, \forall i \in [d], \forall \boldsymbol{\theta}, \boldsymbol{\phi} \in \mathbb{R}^d,$$

for some constant $g < 1$.¹ Let $\boldsymbol{\theta}^*$ denote the unique fixed point of the map \mathbf{g} . Then $\boldsymbol{\theta}_t \rightarrow \boldsymbol{\theta}^*$ almost surely as $t \rightarrow \infty$.

¹In other words, the function \mathbf{g} is a contraction with respect to the ℓ_∞ -norm.

Now we prove the two theorems. The proof of Theorem 1 is very long and involves several auxiliary lemmas. Before proceeding to the lemmas, a matter of notation is cleared up. Throughout we are dealing with stochastic processes. So in principle we should be writing, for instance, $\theta_t(\omega)$, where ω is the element of the probability space that captures the randomness. We do not do this in the interests of brevity, but the presence of the argument ω is implicit throughout.

Lemma 1. *Define a real-valued stochastic process $\{U_i(0; t)\}_{t \geq 0}$ by*

$$U_i(0; t + 1) = (1 - \alpha_{t,i})U_i(0; t) + \alpha_{t,i}\xi_{t+1,i}, \quad (14)$$

where $U_i(0, 0) \in \mathcal{F}_0$, $\{\alpha_{t,i}\}$ satisfy (10) and (11), and $\{\xi_t\}$ satisfies (12) and (13). Then $U_i(0; t) \rightarrow 0$ almost surely as $t \rightarrow \infty$.

This lemma is a ready consequence of the main result in [2]. Note that (14) attempts to find a fixed-point of the function $f(U) = -U$, and that $Uf(U) < 0$ whenever $U \neq 0$. Now apply the theorem for $U = U_i$.

Lemma 2. *Define a doubly-indexed real-valued stochastic process $W_i(\tau; t)$ by*

$$W_i(t_0; t + 1) = (1 - \alpha_{t,i})W_i(t_0, t) + \alpha_{t,i}\xi_{t+1,i}, \quad (15)$$

where $W_i(t_0, t_0) = 0$, $\{\alpha_{t,i}\}$ satisfy (10) and (11), and $\{\xi_t\}$ satisfies (12) and (13). Then, for each $\delta > 0$, there exists a t_0 such that $|W_i(s; t)| \leq \delta$, for all $t_0 \leq s \leq t$.

Proof. It is easy to prove using induction that $W_i(s; t)$ satisfies the recursion

$$U_i(0; t) = \left[\prod_{r=s}^{t-1} (1 - \alpha_{r,i}) \right] U_i(0; s) + W_i(s; t), \quad 0 \leq s \leq t.$$

Note that the product in the square brackets is no larger than one. Hence

$$|W_i(s; t)| \leq |U_i(0; t)| + |U_i(0; s)|.$$

Now, given $\delta > 0$, choose a t_0 such that $|U_i(0; t)| \leq \delta/2$ whenever $t \geq t_0$. Then choosing $t_0 \leq s \leq t$ and applying the triangle inequality leads to the desired conclusion. \square

Now we come to the proof of Theorem 1.

For $t \geq 0$, define

$$\Gamma_t := \max\{\|\theta_0^t\|_\infty, c_1\}, \quad (16)$$

where $c_1 = (\rho - \gamma)/c_0$ as before. With this definition, it follows from (9) and (5) that

$$\|\eta_t\|_\infty \leq \rho\Gamma_t, \quad \forall t. \quad (17)$$

Next, choose any $\epsilon \in (0, 1)$ such that $\rho(1 + \epsilon) < 1$.² Now we define a sequence of constants recursively. Let $\Lambda_0 = \Gamma_0$, and define

$$\Lambda_{t+1} = \begin{cases} \Lambda_t, & \text{if } \Gamma_{t+1} \leq \Lambda_t(1 + \epsilon), \\ \Gamma_{t+1} & \text{if } \Gamma_{t+1} > \Lambda_t(1 + \epsilon). \end{cases} \quad (18)$$

²In the proof of Theorem 1, it is sufficient that $\rho(1 + \epsilon) \leq 1$. However, in the proof of Theorem 2, we require that $\rho(1 + \epsilon) < 1$. To avoid proliferating symbols, we use the same ϵ in both proofs.

Define $\lambda_t = 1/\Lambda_t$. Then it is clear that $\{\Lambda_t\}$ is a nondecreasing sequence, starting at $\Gamma_0 = \|\boldsymbol{\theta}_0\|_\infty$. Consequently, $\{\lambda_t\}$ is a bounded, nonnegative, nonincreasing sequence. Further, $\lambda_t \Gamma_t \leq 1 + \epsilon$ for all t . Moreover, either $\Lambda_{t+1} = \Lambda_t$, or else $\Lambda_{t+1} > \Lambda_t(1 + \epsilon)$. Hence, saying that $\Lambda_{t+1} > \Lambda_t$ is the same as saying that $\Lambda_{t+1} > \Lambda_t(1 + \epsilon)$. Let us refer to this as an ‘‘updating’’ of Λ_t at time $t + 1$.

Next, observe that

$$\Gamma_t = \max\{\|\boldsymbol{\theta}_t\|_\infty, \Gamma_{t-1}\}. \quad (19)$$

It is a ready consequence of (18) that $\Gamma_t \leq \Lambda_t(1 + \epsilon)$ for all t , whence $\|\boldsymbol{\theta}_t\|_\infty \lambda_t \leq 1 + \epsilon$ for all t . Moreover, if Λ is updated at time t , then

$$\Gamma_t > \Lambda_{t-1}(1 + \epsilon) \geq \Gamma_{t-1}.$$

This, coupled with (19), shows that $\|\boldsymbol{\theta}_t\|_\infty = \Gamma_t = \Lambda_t$. Hence $\|\boldsymbol{\theta}_t\|_\infty \lambda_t = 1$ at any time where Λ is updated (and at other times $\|\boldsymbol{\theta}_t\|_\infty \lambda_t \leq 1 + \epsilon$). In the same vein, if $\lambda_t \|\boldsymbol{\theta}_{t+1}\|_\infty \leq 1 + \epsilon$, or equivalently $\|\boldsymbol{\theta}_{t+1}\|_\infty \leq \Lambda_t(1 + \epsilon)$, then (19) implies that $\Gamma_{t+1} \leq \Lambda_t(1 + \epsilon)$, and there is no update at time t .

Now we make the following claim: If $\{\boldsymbol{\theta}_t\}$ is unbounded, then Λ_t is updated infinitely often (i.e., for infinitely many values of t). To establish the claim, suppose $\{\boldsymbol{\theta}_t\}$ is unbounded, and let T be arbitrary. It is shown that there exists a $\tau \geq T$ such that $\Lambda_\tau > \Lambda_{\tau-1}(1 + \epsilon)$, i.e., that Λ gets updated at time τ . Since this argument can again be repeated, it would show that Λ_t gets updated infinitely often if $\{\boldsymbol{\theta}_t\}$ is unbounded, establishing the claim. We prove the existence of such a τ as follows. Since $\{\boldsymbol{\theta}_t\}$ is unbounded, there exists a $t > T$ such that $\|\boldsymbol{\theta}_t\|_\infty > \Lambda_T(1 + \epsilon)$. If there already exists a τ between T and $t - 1$ such that Λ gets updated at time τ , then we are done. So suppose this is not the case, i.e., that

$$\Lambda_T = \Lambda_{T+1} = \cdots = \Lambda_{t-2} = \Lambda_{t-1}.$$

This implies in particular that Λ is not updated at time $t - 1$, i.e., that

$$\Gamma_{t-1} \leq \Lambda_{t-2}(1 + \epsilon) = \Lambda_{t-1}(1 + \epsilon) = \Lambda_T(1 + \epsilon).$$

On the other hand, by assumption $\|\boldsymbol{\theta}_t\|_\infty > \Lambda_T(1 + \epsilon)$. Therefore

$$\Gamma_t = \|\boldsymbol{\theta}_t\|_\infty > \Lambda_{t-1}(1 + \epsilon).$$

Therefore Λ is updated at time t , i.e.,

$$\Lambda_t = \Gamma_t = \|\boldsymbol{\theta}_t\|_\infty > \Lambda_{t-1}(1 + \epsilon).$$

Hence we can take $\tau = t$.

The contrapositive of the claim just proven is the following: If there is a time T such that Λ is *not updated* after time T , then $\{\boldsymbol{\theta}_t\}$ is bounded. From the above discussion, a sufficient condition for this is the following: If there exists a T such that

$$\|\boldsymbol{\theta}_{t+1}\|_\infty \lambda_t \leq 1 + \epsilon, \quad \forall t \geq T, \quad (20)$$

then Λ is not updated after time t , and as a result, $\{\boldsymbol{\theta}_t\}$ is bounded. So henceforth our efforts are focused on establishing (20).

Now we derive a ‘‘closed form’’ expression for $\lambda_T \theta_{T+1,i}$. Towards this end, observe the following: A closed form solution to the recursion

$$a_{t+1} = (1 - x_t)a_t + b_t \quad (21)$$

is given by

$$a_{T+1} = \left[\prod_{r=s}^T (1 - x_r) \right] a_s + \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - x_r) \right] b_t, \quad (22)$$

for every $0 \leq s \leq T$. The proof by induction is easy and is left to the reader. Observe that

$$\begin{aligned} \lambda_{T+1} \theta_{T+1,i} &= \theta_{T+1,i}(\lambda_{T+1} - \lambda_T) + \theta_{T+1,i} \lambda_T \\ &= \theta_{T+1,i}(\lambda_{T+1} - \lambda_T) + [(1 - \alpha_{T,i})\theta_{T,i} + \alpha_{T,i}v_{T,i}] \lambda_T, \end{aligned} \quad (23)$$

where we use the shorthand

$$v_{T,i} = \eta_{T,i} + \xi_{T+1,i}.$$

Now we partition $\lambda_{T+1} \theta_{T+1,i}$ as $F_{T+1,i} + G_{T+1,i}$, and find recursive formulas for F and G such that (23) holds. Thus we must have

$$F_{T+1,i} + G_{T+1,i} = (1 - \alpha_{T,i})(F_{T,i} + G_{T,i}) + \theta_{T+1,i}(\lambda_{T+1} - \lambda_T) + \alpha_{T,i}v_{T,i}\lambda_T.$$

This equation holds if

$$\begin{aligned} F_{T+1,i} &= (1 - \alpha_{T,i})F_{T,i} + \theta_{T+1,i}(\lambda_{T+1}, \\ G_{T+1,i} &= (1 - \alpha_{T,i})G_{T,i} + \alpha_{T,i}v_{T,i}\lambda_T. \end{aligned} \quad (24)$$

The solutions to (24) follow readily from (22), and are

$$F_{T+1,i} = \left[\prod_{r=s}^T (1 - \alpha_{r,i}) \right] F_s + \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_{r,i}) \right] (\theta_{t+1,i})(\lambda_{t+1} - \lambda_t), \quad (25)$$

$$G_{T+1,i} = \left[\prod_{r=s}^T (1 - \alpha_{r,i}) \right] G_s + \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_{r,i}) \right] \alpha_{t,i} \lambda_t v_{t,i}. \quad (26)$$

Adding these two equations, noting that $F_s + G_s = \lambda_s \theta_{s,i}$, and expanding $v_{t,i}$ as $\eta_{t,i} + \xi_{t+1,i}$ gives

$$\begin{aligned} \lambda_{T+1} \theta_{T+1}^i &= \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \theta_{t+1}^i (\lambda_{t+1} - \lambda_t) \\ &+ \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \alpha_t^i (\lambda_t \eta_t^i + \lambda_t \xi_{t+1}^i) + \left[\prod_{r=s}^T (1 - \alpha_r^i) \right] \lambda_s \theta_s^i. \end{aligned} \quad (27)$$

Next, let us expand the right side of (27) as

$$\begin{aligned} \lambda_{T+1} \theta_{T+1}^i &= \theta_{T+1,i}(\lambda_{T+1} - \lambda_T) + \sum_{t=s}^{T-1} \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \theta_{t+1}^i (\lambda_{t+1} - \lambda_t) + \left[\prod_{r=s}^T (1 - \alpha_r^i) \right] \lambda_s \theta_s^i \\ &+ \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \alpha_t^i \lambda_t \eta_t^i + \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \alpha_t^i \lambda_t \xi_{t+1}^i. \end{aligned} \quad (28)$$

Cancelling the common term $\lambda_{T+1}\theta_{T+1,i}$ and moving $\lambda_T\theta_{T+1,i}$ to the left side gives the desired expression, namely

$$\lambda_T\theta_{T+1,i} = A_i(s, T) + B_i(s, T) + C_i(s, T) + D_i(s, T), \quad (29)$$

where for $0 \leq s < T$

$$A_i(s, T) = \sum_{t=s}^{T-1} \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \theta_{t+1}^i (\lambda_{t+1} - \lambda_t) \quad (30)$$

$$B_i(s, T) = \left[\prod_{r=s}^T (1 - \alpha_r^i) \right] \lambda_s \theta_s^i \quad (31)$$

$$C_i(s, T) = \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \alpha_t^i \lambda_t \eta_t^i \quad (32)$$

$$D_i(s, T) = \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \alpha_t^i \lambda_t \xi_{t+1}^i. \quad (33)$$

Now we carry on with the proof of Theorem 1. First, we find an upper bound for $C_i(s, T)$. Observe that, because $\eta(\cdot)$ is a contraction with constant ρ , and $\rho(1 + \epsilon) \leq 1$, we get from (18) that $\Gamma_{t+1} \leq \Lambda_t(1 + \epsilon)$, or $\Gamma_t \lambda_t \leq 1 + \epsilon$. Since $\|\theta_0^t\|_\infty \leq \Gamma_t$, all this implies that

$$\lambda_t \|\eta_t\|_\infty \leq \lambda_t \rho \Gamma_t (1 + \epsilon) \leq 1, \quad \forall t,$$

by the manner in which ϵ is chosen. Substituting this into (32) gives

$$|C_i(s, T)| \leq \sum_{t=s}^T \left| \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \alpha_t^i \lambda_t \eta_t^i \right| \quad (34)$$

$$\begin{aligned} &\leq \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \alpha_t^i \\ &= \left(1 - \prod_{r=s}^T (1 - \alpha_r^i) \right) \end{aligned} \quad (35)$$

Next, we derive a recursion for $D_i(s, T)$.

$$\begin{aligned} D_i(s, T) &= \sum_{t=s}^T \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \alpha_t^i \lambda_t \xi_{t+1}^i \\ &= \alpha_{T,i} \lambda_T \xi_{T+1,i} + \sum_{t=s}^{T-1} \left[\prod_{r=t+1}^T (1 - \alpha_r^i) \right] \alpha_t^i \lambda_t \xi_{t+1}^i \\ &= \alpha_{T,i} \lambda_T \xi_{T+1,i} + (1 - \alpha_{T,i}) \sum_{t=s}^{T-1} \left[\prod_{r=t+1}^{T-1} (1 - \alpha_r^i) \right] \alpha_t^i \lambda_t \xi_{t+1}^i \\ &= \alpha_{T,i} \lambda_T \xi_{T+1,i} + (1 - \alpha_{T,i}) D_i(s, T-1). \end{aligned} \quad (36)$$

The next lemma is a direct consequence of Lemma 1.

Lemma 3. Define a stochastic process $\{M_i(0, t)\}_{t \geq 0}$ by the recursion

$$M_i(0, t + 1) = (1 - \alpha_{t,i})\lambda_t M_i(0, t) + \alpha_{t,i}\lambda_t \xi_{t+1,i},$$

with the initial condition $M_i(0, 0) = 0$. Then $M_i(0, t) \rightarrow 0$ almost surely as $t \rightarrow \infty$.

The proof follows readily from Lemma 1 by replacing $\xi_{t+1,i}$ by $\lambda_t \xi_{t+1,i}$, and observing that $\lambda_t \xi_{t+1,i}$ satisfies the analogs of (12) and (13), because $\lambda_t \in \mathcal{M}(\mathcal{F}_t)$ for all t and is bounded.

Lemma 4. For every $\delta > 0$, there exists a t_0 such that the solution $D_i(s, T)$ of the recursion (36) with the initial condition $D_i(s, s - 1) = 0$ satisfies $|D_i(s, T)| \leq \delta$ for all $t_0 \leq s \leq T$.

The proof follows readily from Lemma 2 with minor changes.

We continue with the proof of Theorem 1. Choose a t_0 such that

$$|D_i(s, T)| \leq \epsilon/2, \quad \forall t_0 \leq s \leq T. \quad (37)$$

If Λ is not updated at any time after t_0 , then it follows from earlier discussion that $\{\theta_t\}$ is bounded. Otherwise, define s to be any time after $t_0 + 1$ at which Λ is updated. Thus $\|\theta_s\|_\infty \lambda_s = 1$ due to the updating. Next, suppose that, for some $T \geq s$, we have that

$$\|\theta_t\|_\infty \lambda_t \leq 1 + \epsilon, \quad \forall s \leq t \leq T. \quad (38)$$

Then it is shown that

$$\|\theta_{T+1}\|_\infty \lambda_{T+1} \leq 1 + \epsilon.$$

The proof is by induction on T . Note that (38) holds with $T = s$ to start the induction. Now (38) implies that Λ is not updated between times s and T , so that $\lambda_s = \lambda_t = \lambda_T$ for $s \leq t \leq T$. Hence it follows from (30) that $A(s, T) = 0$. Next, (31) gives

$$|B(s, T)| \leq \prod_{r=s}^T (1 - \alpha_{r,i}) \lambda_s \|\theta_s\|_\infty \leq \prod_{r=s}^T (1 - \alpha_{r,i}).$$

Combining this bound with (35) gives

$$|B_i(s, T) + C_i(s, T)| \leq |B_i(s, T)| + |C_i(s, T)| \leq 1.$$

Finally, from Lemma 4, we have that $|D_i(s, T)| \leq \epsilon$. Combining all these shows that

$$|\lambda_{T+1} \theta_{T+1,i}| \leq 1 + \epsilon \quad \forall i \in [d], \quad \text{or} \quad \lambda_{T+1} \|\theta_{T+1}\|_\infty \leq 1 + \epsilon.$$

This completes the inductive step and proves the theorem.

Now we come to the proof of Theorem 2. We study is the common situation where

$$\mathbf{h}(t, \theta_0^t) = \mathbf{g}(\theta_t),$$

where $\mathbf{g} : \mathbb{R}^d \rightarrow \mathbb{R}^d$ is a contraction with respect to the ℓ_∞ -norm. In other words, there exists a $\gamma < 1$ such that

$$|g_i(\theta) - g_i(\phi)| \leq \gamma \|\theta - \phi\|_\infty, \quad \forall i \in [d], \quad \forall \theta, \phi \in \mathbb{R}^d.$$

In addition, define $c_0 = \|\mathbf{g}(\mathbf{0})\|_\infty$. This notation is consistent with (6) and (9). These hypotheses imply that there is a unique fixed point $\theta^* \in \mathbb{R}^d$ of $\mathbf{g}(\cdot)$. Theorem 2 states that $\theta_t \rightarrow \theta^*$ almost surely as $t \rightarrow \infty$.

For notational convenience, it is assumed that $\boldsymbol{\theta}^* = \mathbf{0}$. The modifications required to handle the case where $\boldsymbol{\theta}^* \neq \mathbf{0}$ are obvious, and can be incorporated at the expense of more messy notation. If $\boldsymbol{\theta}^* = \mathbf{0}$, then $\mathbf{g}(\mathbf{0}) = \mathbf{0}$ so that $c_0 = 0$. Hence we can take $c_1 = 0$, $\rho \in (\gamma, 1)$, and (??) becomes

$$\|h(t, \boldsymbol{\theta}_0^t)\|_\infty \leq \rho \|\boldsymbol{\theta}_t\|_\infty \leq \rho \|\boldsymbol{\theta}_0^t\|_\infty, \|\boldsymbol{\eta}_t\|_\infty \leq \rho \|\boldsymbol{\theta}_t\|_\infty.$$

Let $\Omega_0 \subseteq \Omega$ be the subset of Ω such that $U_i(0, t)(\omega) \rightarrow 0$ as $t \rightarrow \infty$, for all $i \in [d]$. So for each $\omega \in \Omega_0$, there exists a bound $H_0 = H_0(\omega)$ such that

$$\|\boldsymbol{\theta}_0^\infty(\omega)\|_\infty \leq H_0(\omega), \text{ or } |\theta_{t,i}(\omega)| \leq H_0(\omega), \forall i \in [d], \forall t \geq 0.$$

Hereafter we suppress the dependence of ω . Now choose $\epsilon \in (0, 1)$ such that $\rho(1 + \epsilon) < 1$. Note that in the proof of Theorem 1, we required only that $\rho(1 + \epsilon) \leq 1$. For such a choice of ϵ , Theorem 1 continues to apply. Therefore $\|\boldsymbol{\theta}_0^\infty\|_\infty \leq H_0$. Now define $H_{k+1} = \rho(1 + \epsilon)H_k$ for each $k \geq 0$. Then clearly $H_k \rightarrow 0$ as $k \rightarrow \infty$.

Now we show that there exists a sequence of times $\{t_k\}$ such that $\|\boldsymbol{\theta}_{t_k}^\infty\|_\infty \leq H_k$, for each k . This is enough to show that $\boldsymbol{\theta}_t(\omega) \rightarrow \mathbf{0}$ for all $\omega \in \Omega_0$, which is the claimed almost sure convergence to the fixed point of \mathbf{g} . The proof of this claim is by induction. It is shown that *if* there exists a t_k such that $\|\boldsymbol{\theta}_{t_k}^\infty\|_\infty \leq H_k$, then there exists a t_{k+1} such that $\|\boldsymbol{\theta}_{t_{k+1}}^\infty\|_\infty \leq H_{k+1}$. The statement holds for $k = 0$ – take $t_0 = 0$ because H_0 is a bound on $\|\boldsymbol{\theta}_0^\infty\|_\infty$. To prove the inductive step, suppose that $\|\boldsymbol{\theta}_{t_k}^\infty\|_\infty \leq H_k$. Choose a $\tau_k \geq t_0$ such that the solution to (15) satisfies

$$|W_i(\tau_k; t)| \leq \frac{\rho\epsilon}{2} H_k, \forall i \in [d], \forall t \geq \tau_k. \quad (39)$$

Define a sequence $\{Y_{t,i}\}$ by

$$Y_{t+1,i} = (1 - \alpha_{t,i})Y_{t,i} + \alpha_{t,i}\rho H_k, Y_{\tau_k,i} = H_k, i \in [d], t \geq \tau_k. \quad (40)$$

Then clearly $Y_{t,i} \rightarrow \rho H_k$ as $t \rightarrow \infty$ for each $i \in [d]$. Now it is claimed that

$$-Y_{t,i} + W_i(\tau_k; t) \leq \theta_{t,i} \leq Y_{t,i} + W_i(\tau_k; t), \forall i \in [d], t \geq \tau_k. \quad (41)$$

The proof of (41) is also by induction on t . The bound (41) holds for $t = \tau_k$ because $W_i(\tau_k; \tau_k) = 0$, and the inductive assumption on k , which implies that

$$|\theta_{\tau_k,i}| \leq \|\boldsymbol{\theta}_{\tau_k}^\infty\|_\infty \leq \|\boldsymbol{\theta}_{t_k}^\infty\|_\infty \leq H_k = Y_{\tau_k,i}.$$

Now note that if (41) holds for a specific value of k , then for $t \geq \tau_k$ we have

$$\begin{aligned} \theta_{t+1,i} &= (1 - \alpha_{t,i})\theta_{t,i} + \alpha_{t,i}\eta_{t,i} + \alpha_{t,i}\xi_{t+1,i} \\ &\leq (1 - \alpha_{t,i})\theta_{t,i} + \alpha_{t,i}\rho H_k + \alpha_{t,i}\xi_{t+1,i} \\ &\leq (1 - \alpha_{t,i})[Y_{t,i} + W_i(\tau_k; t)] + \alpha_{t,i}\xi_{t+1,i} \\ &= (1 - \alpha_{t,i})Y_{t,i} + \alpha_{t,i}\rho H_k + (1 - \alpha_{t,i})W_i(\tau_k; t) + \alpha_{t,i}\xi_{t+1,i} \\ &= Y_{t+1,i} + W_{t+1,i}. \end{aligned}$$

This proves the upper bound in (41) for $t + 1$. So the inductive step is established, showing that the upper bound in (41) is true for all $t \geq \tau_k$. Now note that $Y_{t,i} \rightarrow \rho H_k$ as $t \rightarrow \infty$. Hence there exists a $t'_{k+1} \geq \tau_k$ such that

$$Y_{t,i} \leq \rho H_k + \frac{\rho\epsilon}{2} = \rho \left(1 + \frac{\epsilon}{2}\right) H_k, \forall t \geq t'_{k+1}.$$

This, combined with (39) shows that

$$Y_{t,i} + W_i(\tau_k; t) \leq \rho(1 + \epsilon)H_k = H_{k+1}, \quad \forall t \geq t'_{k+1}.$$

Hence

$$\theta_{t,i} \leq H_{k+1} \quad \forall i \in [d], t \geq t'_{k+1}.$$

A parallel argument gives a lower bound: There exists a t''_{k+1} such that

$$-H_{k+1} \leq \theta_{t,i} \quad \forall i \in [d], t \geq t''_{k+1}.$$

If we define $t_{k+1} = \max\{t'_{k+1}, t''_{k+1}\}$, then

$$|\theta_{t,i}| \leq H_{k+1} \quad \forall i \in [d], t \geq t_{k+1}.$$

This establishes the inductive step for k and completes the proof.

References

- [1] V. S. Borkar. Asynchronous stochastic approximations. *SIAM Journal on Control and Optimization*, 36(3):840–851, 1998.
- [2] E. G. Gladyshev. On stochastic approximation. *Theory of Probability and Its Applications*, X(2):275–278, 1965.
- [3] Herbert Robbins and Sutton Monro. A stochastic approximation method. *Annals of Mathematical Statistics*, 22(3):400–407, 1951.
- [4] John N. Tsitsiklis. Asynchronous stochastic approximation and q-learning. *Machine Learning*, 16:185–202, 1994.