

# Convolution and Correlation Theorems for Wigner-Ville Distribution Associated with the Quaternion Offset Linear Canonical Transform

Convolution and Correlation Theorems for WVD Associated with the QOLCT

M. YOUNUS BHAT · AAMIR H. DAR

Received: date / Accepted: date

**Abstract** The quaternion offset linear canonical transform(QOLCT) has gained much popularity in recent years because of its applications in many areas, including color image and signal processing. At the same time the applications of Wigner-Ville distribution (WVD) in signal analysis and image processing can not be excluded. In this paper we investigate the Winger-Ville Distribution associated with quaternion offset linear canonical transform (WVD-QOLCT). Firstly, we propose the definition of the WVD-QOLCT, and then several important properties of newly defined WVD-QOLCT, such as nonlinearity, bounded, reconstruction formula, orthogonality relation and Plancherel formula are derived. Secondly a novel canonical convolution operator and a related correlation operator for WVD-QOLCT are proposed. Moreover, based on the proposed operators, the corresponding generalized convolution, correlation theorems are studied. We also show that the convolution and correlation theorems of the QWVD and WVD-QLCT can be looked as a special case of our achieved results.

**Keywords** Quaternion algebra · Offset linear canonical transform · Quaternion offset linear canonical transform · Wigner-Ville distribution · Convolution · Correlation · Modulation

**Mathematics Subject Classification (2010)** 11R52 · 42C40 · 42C30 · 43A30.

M. YOUNUS BHAT  
Department of Mathematical Sciences, Islamic University of Science and Technology Awantipora, Pulwama, Jammu and Kashmir 192122, India. E-mail: gyounusg@gmail.com

AAMIR H. DAR  
Department of Mathematical Sciences, Islamic University of Science and Technology Awantipora, Pulwama, Jammu and Kashmir 192122, India.

## 1 Introduction

In the time-frequency signal analysis the classical Wigner-Ville distribution (WVD) or Wigner-Ville transform (WVT) has an important role to play. Eugene Wigner introduced the concept WVD while making his calculation of the quantum corrections. later on it was J. Ville who derived it independently as a quadratic representation of the local time-frequency energy of a signal in 1948. Many important properties of WVT has been studied by many authors. On replacing the kernel of the classical Fourier transform (FT) with the kernel of the LCT in the WVD domain, this transform can be extended to the domain of linear canonical transform [3]-[6], [13]-[19].

On the other hand the quaternion Fourier transform (QFT) is of the interest in the present era. Many important properties like shift, modulation, convolution, correlation, differentiation, energy conservation, uncertainty principle of QFT have been found. Many generalized transforms are closely related to the QFTs, for example, the quaternion wavelet transform, fractional quaternion Fourier transform, quaternion linear canonical transform, and quaternionic windowed Fourier transform. Based on the QFTs, one also may extend the WVD to the quaternion algebra while enjoying similar properties as in the classical case. Many authors generalized the classical WVD to quaternion algebra, which they called as the quaternion Wigner-Ville distribution (QWVD). For more details we refer to [1], [2], [7]-[12].

The linear canonical transform (LCT) with four parameters  $(a, b, c, d)$  has been generalized to a six parameter transform  $(a, b, c, d, u_0, w_0)$  known as offset linear canonical transform (OLCT). Due to the time shifting  $u_0$  and frequency modulation parameters, the OLCT has gained more flexibility over classical LCT. Hence

has found wide applications in image and signal processing. On the other side the convolution has some applications in various areas of Mathematics like linear algebra, numerical analysis and signal processing. Where as Correlation like convolution is an another important tool n signal processing, optics and detection applications. In the domains of LCT, WVD and OLCT the convolution and correlation operations have been studied [7]-[10].

The quaternion offset linear canonical transform (QOLCT) has gained much popularity in recent years because of its applications in many areas, including colour image and signal processing. At the same time the applications of Wigner-Ville distribution (WVD) in signal analysis and image processing can not be excluded. Motivated by QOLCT and WVD, we in this paper we investigate the Winger-Ville Distribution associated with quaternion offset linear canonical transform (WVD-QOLCT). Firstly, we propose the definition of the WVD-QOLCT, and then several important properties of newly defined WVD-QOLCT, such as nonlinearity, bounded, reconstruction formula, orthogonality relation and Plancherel formula are derived. Secondly a novel canonical convolution operator and a related correlation operator for WVD-QOLCT are proposed. Moreover, based on the proposed operators, the corresponding generalized convolution, correlation theorems are studied. We also show that the convolution and correlation theorems of the QWVD and WVD-QLCT can be looked as a special case of our achieved results.

The paper is organised as follows. In Section 2, we provide the definition of Wigner-Ville distribution associated with the quaternionic offset linear canonical transform (WVD-QOLCT). Then we will investigate several basic properties of the WVD-QOLCT which are important for signal representation in signal processing. In Section 3 we first define the convolution and correlation for the QOLCT. We then establish the new convolution and correlation for the WVD-QOLCT. We also show that the convolution theorems of the QWVD and WVD-QLCT can be looked as a special case of our achieved results I

## 2 Winger-ville Distribution associated with Quaternion Offset Linear Canonical Transform(WVD-QOLCT)

Since in practice most natural signals are non-stationary. In order to study a non-stationary signals the Wigner-Ville distribution has become a suite tool for the analysis of the non stationary signals. In this section,we are going to give the definition of Wigner-Ville distribution

associated with the quaternionic offset linear canonical transform (WVD-QOLCT),then we will investigate several basic properties of the WVD-QOLCT which are important for signal representation in signal processing.

**Definition 1** Let  $A_i = \begin{bmatrix} a_i & b_i & | & r_i \\ c_s & d_i & | & s_i \end{bmatrix}$ , be a matrix parameter such that  $a_s, b_i, c_i, d_i, r_i, s_i \in \mathbf{R}$  and  $a_i d_i - b_i c_i = 1$ , for  $i = 1, 2$ . The Wigner-Ville distribution associated with the two-sided quaternionic offset linear canonical transform (WVD-QOLCT) of signals  $f, g \in L^2(\mathbf{R}^2, \mathbf{H})$ , is given by

$$\mathcal{W}_{f,g}^{A_1, A_2}(t, u) = \begin{cases} \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) f(t + \frac{n}{2}) \overline{g(t - \frac{n}{2})} \\ K_{A_2}^j(n_2, u_2) dn, \\ b_1, b_2 \neq 0, \\ \sqrt{d_1} e^{i(\frac{c_1 d_1}{2}(u_1 - r_1)^2 + u_1 r_1)} \\ f(t_1 + \frac{d_1(u_1 - r_1)}{2}, t_2 + \frac{n_2}{2}) \\ \overline{g}(t_1 - \frac{d_1(u_1 - r_1)}{2}, t_2 - \frac{n_2}{2}) \\ K_{A_2}^j(n_2, u_2), \\ b_1 = 0, b_2 \neq 0; \\ \sqrt{d_2} K_{A_1}^i(n_1, u_1) \\ f(t_1 + \frac{n_1}{2}, t_2 + \frac{d_2(u_2 - r_2)}{2}) \\ \overline{g}(t_1 - \frac{n_1}{2}, t_2 - \frac{d_2(u_2 - r_2)}{2}) \\ e^{j(\frac{c_2 d_2}{2}(u_2 - r_2)^2 + u_2 r_2)}, \\ b_1 \neq 0, b_2 = 0; \\ \sqrt{d_1 d_2} e^{i(\frac{c_1 d_1}{2}(u_1 - r_1)^2 + u_1 r_1)} \\ f(t_1 + \frac{d_1(u_1 - r_1)}{2}, t_2 + \frac{d_2(u_2 - r_2)}{2}) \\ \overline{g}(t_1 - \frac{d_1(u_1 - r_1)}{2}, t_2 - \frac{d_2(u_2 - r_2)}{2}) \\ e^{j(\frac{c_2 d_2}{2}(u_2 - r_2)^2 + u_2 r_2)}, \\ b_1 = b_2 = 0. \end{cases} \quad (1)$$

where  $t = (t_1, t_2), u = (u_1, u_2), n = (n_1, n_2)$  and  $K_{A_1}^i(n_1, u_1)$  and  $K_{A_2}^j(n_2, u_2)$  are the quaternion kernels.

*Note 1* If  $f = g$  then  $\mathcal{W}_{f,f}^{A_1, A_2}(t, u)$  we call it the Auto WVD-QOLCT. Otherwise is called Cross WVD-QOLCT

Without loss of generality we will deal with the case  $b_i \neq 0, i = 1, 2$ , as in other cases proposed transform reduces to a chirp multiplications. Thus for any  $f, g \in L^2(\mathbf{R}^2, \mathbf{H})$  we have

$$\begin{aligned} \mathcal{W}_{f,g}^{A_1, A_2}(t, u) &= \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) f(t + \frac{n}{2}) \overline{g(t - \frac{n}{2})} K_{A_2}^j(n_2, u_2) dn \\ &= \mathcal{O}_{A_1, A_2}^{i,j} \left\{ f\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} \right\} \\ &= \mathcal{O}_{A_1, A_2}^{i,j} \{h_{f,g}(t, n)\}. \end{aligned} \quad (2)$$

Where  $h_{f,g}(t, n) = f\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)}$  is known as quaternion correlation product. Applying the inverse QOLCT

to (2), we get

$$\{h_{f,g}(t, n)\} = \{\mathcal{O}_{A_1, A_2}^{i,j}\}^{-1} \{\mathcal{W}_{f,g}^{A_1, A_2}(t, u)\}$$

which implies

$$\begin{aligned} f\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} &= \{\mathcal{O}_{A_1, A_2}^{i,j}\}^{-1} \{\mathcal{W}_{f,g}^{A_1, A_2}(t, u)\} \\ &= \int_{\mathbf{R}^2} K_{A_1}^{-i}(t_1, u_1) \mathcal{W}_{f,g}^{A_1, A_2}(t, u) \\ &\quad K_{A_2}^{-j}(t_2, u_2) dw. \end{aligned} \quad (3)$$

Now, we discuss several basic properties of the WVD-QOLCT given by (1). These properties play important roles in signal representation.

**Theorem 1 (Boundedness)** *Let  $f, g \in L^2(\mathbf{R}^2, \mathbf{H})$ . Then*

$$|\mathcal{W}_{f,g}^{A_1, A_2}(t, u)| \leq \frac{2}{\pi\sqrt{b_1 b_2}} \|f\|_{L^2(\mathbf{R}^2, H)} \|g\|_{L^2(\mathbf{R}^2, H)} \quad (4)$$

*Proof* By the virtue of Cauchy-Schwarz inequality in quaternion domain, we have

$$\begin{aligned} &|\mathcal{W}_{f,g}^{A_1, A_2}(t, u)|^2 \\ &= \left| \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) f\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} K_{A_2}^j(n_2, u_2) dn \right|^2 \\ &\leq \left( \int_{\mathbf{R}^2} \left| K_{A_1}^i(n_1, u_1) f\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} K_{A_2}^j(n_2, u_2) \right| dn \right)^2 \\ &= \left( \frac{1}{\sqrt{4\pi^2 |b_1 b_2|}} \int_{\mathbf{R}^2} \left| f\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} \right| dn \right)^2 \\ &\leq \frac{1}{4\pi^2 |b_1 b_2|} \left( \int_{\mathbf{R}^2} |f\left(t + \frac{n}{2}\right)|^2 dn \right) \left( \int_{\mathbf{R}^2} \left| \overline{g\left(t - \frac{n}{2}\right)} \right|^2 ds \right) \\ &= \frac{1}{4\pi^2 |b_1 b_2|} \left( 4 \int_{\mathbf{R}^2} |f(w)|^2 dw \right) \left( 4 \int_{\mathbf{R}^2} |\overline{g(y)}|^2 dy \right) \\ &= \frac{4}{\pi^2 |b_1 b_2|} \|f\|_{L^2(\mathbf{R}^2, H)}^2 \|g\|_{L^2(\mathbf{R}^2, H)}^2 \end{aligned}$$

where applying the change of variables  $w = t + \frac{n}{2}$  and  $y = t - \frac{n}{2}$  in the last second step. Then we have

$$|\mathcal{W}_{f,g}^{A_1, A_2}(t, u)| \leq \frac{2}{\pi\sqrt{|b_1 b_2|}} \|f\|_{L^2(\mathbf{R}^2, H)} \|g\|_{L^2(\mathbf{R}^2, H)}$$

which completes the proof of Theorem.

**Theorem 2 (Nonlinearity)** *Let  $f$  and  $g$  be two quaternion functions in  $L^2(\mathbf{R}^2, \mathbf{H})$ . Then*

$$\mathcal{W}_{f+g}^{A_1, A_2} = \mathcal{W}_{f,f}^{A_1, A_2} + \mathcal{W}_{f,g}^{A_1, A_2} + \mathcal{W}_{g,f}^{A_1, A_2} + \mathcal{W}_{g,g}^{A_1, A_2} \quad (5)$$

*Proof* By definition 1 we have

$$\begin{aligned} &\mathcal{W}_{f+g}^{A_1, A_2}(t, u) \\ &= \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) \left[ f\left(t + \frac{n}{2}\right) + g\left(t + \frac{n}{2}\right) \right] \\ &\quad \overline{\left[ f\left(t - \frac{n}{2}\right) + g\left(t - \frac{n}{2}\right) \right]} K_{A_2}^j(n_2, u_2) dn \\ &= \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) \left[ f\left(t + \frac{n}{2}\right) \overline{f\left(t - \frac{n}{2}\right)} \right. \\ &\quad \left. + f\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} \right. \\ &\quad \left. + g\left(t + \frac{n}{2}\right) \overline{f\left(t - \frac{n}{2}\right)} + g\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} \right] K_{A_2}^j(n_2, u_2) dn \\ &= \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) f\left(t + \frac{n}{2}\right) \overline{f\left(t - \frac{n}{2}\right)} K_{A_2}^j(n_2, u_2) dn \\ &\quad + \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) f\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} K_{A_2}^j(n_2, u_2) dn \\ &\quad + \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) g\left(t + \frac{n}{2}\right) \overline{f\left(t - \frac{n}{2}\right)} K_{A_2}^j(n_2, u_2) dn \\ &\quad + \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) g\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} K_{A_2}^j(n_2, u_2) dn \\ &= \mathcal{W}_{f,f}^{A_1, A_2} + \mathcal{W}_{f,g}^{A_1, A_2} + \mathcal{W}_{g,f}^{A_1, A_2} + \mathcal{W}_{g,g}^{A_1, A_2} \end{aligned}$$

which completes the proof of Theorem.

Note the properties like Shift, Modulation, Dilation are similar to the classical QOLCT so we avoided them.

**Theorem 3 (Reconstruction formula).** *For  $f, g \in L^2(\mathbf{R}^2, \mathbf{H})$  where  $g$  does not vanish at 0. We get the following inversion formula of the WVD-QOLCT:*

$$f(t) = \frac{1}{g(0)} \int_{\mathbf{R}^2} K_{A_1}^{-i}(u_1, n_1) \mathcal{W}_{f,g}^{A_1, A_2}\left(\frac{t}{2}, u\right) K_{A_2}^{-j}(u_2, n_2) du \quad (6)$$

*Proof* By (3), we have

$$\{h_{f,g}(t, n)\} = \{\mathcal{O}_{A_1, A_2}^{i,j}\}^{-1} \{\mathcal{W}_{f,g}^{A_1, A_2}(t, u)\}$$

which implies

$$\begin{aligned} &f\left(t + \frac{n}{2}\right) \overline{g\left(t - \frac{n}{2}\right)} \\ &= \int_{\mathbf{R}^2} K_{A_1}^{-i}(t_1, u_1) \mathcal{W}_{f,g}^{A_1, A_2}(t, u) K_{A_2}^{-j}(t_2, u_2) dw, \end{aligned}$$

Now let  $t = \frac{n}{2}$  and taking change of variable  $w = 2t$ , we get

$$f(w) = \frac{1}{g(0)} \int_{\mathbf{R}^2} K_{A_1}^{-i}(u_1, n_1) \mathcal{W}_{f,g}^{A_1, A_2}\left(\frac{w}{2}, u\right) K_{A_2}^{-j}(u_2, n_2) du$$

which completes the proof of Theorem.

**Theorem 4 (Orthogonality relation).** *If  $f_1, f_2, g_1, g_2 \in L^2(\mathbf{R}^2, \mathbf{H})$  which completes the proof theorem.*

*$L^2(\mathbf{R}^2, \mathbf{H})$  are quaternion-valued signals. Then*

$$\langle \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u), \mathcal{W}_{f_2, g_2}^{A_1, A_2}(t, u) \rangle = [\langle f_1, f_2 \rangle \langle g_2, g_1 \rangle]_{\mathbf{H}} \quad (7)$$

*Proof* By the definition of Winger-ville distribution associated with quaternion OLCT and inner product relation we have

$$\begin{aligned} & \langle \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u), \mathcal{W}_{f_2, g_2}^{A_1, A_2}(t, u) \rangle \\ &= \int_{\mathbf{R}^4} \left[ \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u) \overline{\mathcal{W}_{f_2, g_2}^{A_1, A_2}(t, u)} \right]_{\mathbf{H}} dudt \\ &= \int_{\mathbf{R}^4} \left[ \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u) \right. \\ & \quad \left. \overline{\int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) f_2 \left( t + \frac{n}{2} \right) g_2 \left( t - \frac{n}{2} \right)} \right. \\ & \quad \left. \overline{K_{A_2}^j(n_2, u_2) dn} \right]_{\mathbf{H}} dudt \\ &= \int_{\mathbf{R}^6} \left[ \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u) K_{A_2}^{-j}(n_2, u_2) g_2 \left( t - \frac{n}{2} \right) \right. \\ & \quad \left. \overline{f_2 \left( t + \frac{n}{2} \right) K_{A_1}^{-i}(n_1, u_1)} \right]_{\mathbf{H}} dudtdn \\ &= \int_{\mathbf{R}^6} \left[ K_{A_1}^{-i}(n_1, u_1) \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u) K_{A_2}^{-j}(n_2, u_2) \right. \\ & \quad \left. g_2 \left( t - \frac{n}{2} \right) \overline{f_2 \left( t + \frac{n}{2} \right)} \right]_{\mathbf{H}} dudtdn \\ &= \int_{\mathbf{R}^4} \left[ \int_{\mathbf{R}^2} K_{A_1}^{-i}(n_1, u_1) \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u) K_{A_2}^{-j}(n_2, u_2) du \right. \\ & \quad \left. g_2 \left( t - \frac{n}{2} \right) \overline{f_2 \left( t + \frac{n}{2} \right)} \right]_{\mathbf{H}} dtdn \end{aligned} \quad (8)$$

Because

$$\overline{K_{A_1}^i(n_1, u_1)} = K_{A_1}^{-i}(u_1, n_1) = K_{A_1^{-1}}^i(u_1, n_1)$$

$$\overline{K_{A_2}^j(n_2, u_2)} = K_{A_2}^{-j}(n_2, u_2) = K_{A_2^{-1}}^j(u_2, n_2)$$

Now by using (3) in (8), we have

$$\begin{aligned} & \langle \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u), \mathcal{W}_{f_2, g_2}^{A_1, A_2}(t, u) \rangle \\ &= \int_{\mathbf{R}^4} \left[ \int_{\mathbf{R}^2} K_{A_1^{-1}}^i(u_1, n_1) \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u) K_{A_2^{-1}}^j(u_2, n_2) du \right. \\ & \quad \left. g_2 \left( t - \frac{n}{2} \right) \overline{f_2 \left( t + \frac{n}{2} \right)} \right]_{\mathbf{H}} dtdn \\ &= \int_{\mathbf{R}^4} \left[ f_1 \left( t + \frac{n}{2} \right) \overline{g_1 \left( t - \frac{n}{2} \right)} g_2 \left( t - \frac{n}{2} \right) \overline{f_2 \left( t + \frac{n}{2} \right)} \right]_{\mathbf{H}} dtdn \end{aligned}$$

Using the change of variables  $t + \frac{n}{2} = \omega$ , and  $t - \frac{n}{2} = \xi$  the equation becomes

$$\begin{aligned} & \langle \mathcal{W}_{f_1, g_1}^{A_1, A_2}(t, u), \mathcal{W}_{f_2, g_2}^{A_1, A_2}(t, u) \rangle \\ &= \int_{\mathbf{R}^4} \left[ f_1(\omega) \overline{g_1(\xi)} g_2(\xi) \overline{f_2(\omega)} \right]_{\mathbf{H}} d\omega d\xi \\ &= \left[ \int_{\mathbf{R}^2} f_1(\omega) \overline{f_2(\omega)} d\omega \int_{\mathbf{R}^2} g_2(\xi) \overline{g_1(\xi)} d\xi \right]_{\mathbf{H}} \\ &= [\langle f_1, f_2 \rangle \langle g_2, g_1 \rangle]_{\mathbf{H}} \end{aligned}$$

### Consequences of Theorem 4.

1. If  $g_1 = g_2 = g$ , then

$$\langle \mathcal{W}_{f_1, g}^{A_1, A_2}(t, u), \mathcal{W}_{f_2, g}^{A_1, A_2}(w, u) \rangle = \|g\|_{L^2(\mathbf{R}^2)}^2 \langle f_1, f_2 \rangle \quad (9)$$

2. If  $f_1 = f_2 = f$ , then

$$\langle \mathcal{W}_{f, g_1}^{A_1, A_2}(t, u), \mathcal{W}_{f, g_2}^{A_1, A_2}(w, u) \rangle = \|f\|_{L^2(\mathbf{R}^2)}^2 \langle g_1, g_2 \rangle. \quad (10)$$

3. If  $f_1 = f_2 = f$  and  $g_1 = g_2 = g$ , then

$$\begin{aligned} & \langle \mathcal{W}_{f, g}^{A_1, A_2}(t, u), \mathcal{W}_{f, g}^{A_1, A_2}(w, u) \rangle \\ &= \int_{\mathbf{R}^2} \int_{\mathbf{R}^2} |\mathcal{W}_{f, g}^{A_1, A_2}(t, u)|^2 dudt \\ &= \|f\|_{L^2(\mathbf{R}^2)}^2 \|g\|_{L^2(\mathbf{R}^2)}^2 \end{aligned} \quad (11)$$

### Theorem 5 (Plancherel's theorem for

**WVD-QOLCT).** *For  $f, g \in L^2(\mathbf{R}^2, \mathbf{H})$ , we have the equality*

$$\begin{aligned} & \int_{\mathbf{R}^2} \int_{\mathbf{R}^2} |\mathcal{W}_{f, g}^{A_1, A_2}(t, u)|^2 dudt \\ &= \|\mathcal{W}_{f, g}^{A_1, A_2}\|_{L^2(\mathbf{R}^2, \mathbf{H})}^2 \\ &= \|f\|_{L^2(\mathbf{R}^2, \mathbf{H})}^2 \|g\|_{L^2(\mathbf{R}^2, \mathbf{H})}^2 \end{aligned} \quad (12)$$

*Proof* If we look at (11), the proof of the theorem follows.

Now we move forward towards our main section that is convolution and correlation theorems for winger-ville distribution associated with quaternion offset linear canonical transform.

### 3 Convolution and Correlation theorem for WVD-QOLCT

The convolution and correlation are fundamental signal processing algorithms in the theory of linear time-invariant (LTI) systems. In engineering, they have been widely used for various template matchings. In the following we first define the convolution and correlation for the QOLCT. They are extensions of the convolution definition from the OLCT (see [16]) to the QOLCT domain. We then establish the new convolution and correlation for the WVD-QOLCT. We also show that the convolution theorems of the QWVD and WVD-QOLCT can be looked as a special case of our achieved results.

**Definition 2** For any two quaternion functions  $f, g \in L^2(\mathbf{R}^2, \mathbf{H})$ , we define the convolution operator of the QOLCT as

$$(f \star g)(t) = \int_{\mathbf{R}^2} \Psi(z_1, t_1) f(z) g(t - z) \Psi(z_2, t_2) dz \quad (13)$$

Where  $\Psi(z_1, t_1)$  and  $\Psi(z_2, t_2)$  are known as weight functions.

We assume

$$\Psi(z_1, t_1) = e^{-i\frac{a_1}{b_1}2z_1(t_1-z_1)}$$

and

$$\Psi(z_2, t_2) = e^{-j\frac{a_2}{b_2}2z_2(t_2-z_2)} \quad (14)$$

As a consequence of the above definition, we get the following important theorem.

**Theorem 6** (WVD-QOLCT Convolution). *For any two quaternion functions  $f, g \in L^2(\mathbf{R}^2, \mathbf{H})$ , the following result holds*

$$\begin{aligned} & \mathcal{W}_{f \star g}^{A_1, A_2}(t, u) \\ &= \sqrt{2\pi b_1 i} e^{\frac{-i}{2b_1}[d_1(u_1^2+r_1^2)-2u_1(d_1r_1-b_1s_1)]} \\ & \times \left\{ \int_{\mathbf{R}^2} e^{-i\frac{a_1}{b_1}(4w_1(t_1-w_1))} \mathcal{W}_{f, f}^{A_1, A_2}(w, u) \mathcal{W}_{g, g}^{A_1, A_2}(t-w, u) \right. \\ & \left. e^{-j\frac{a_2}{b_2}(4w_2(t_2-w_2))} dw \right\} \\ & \times \sqrt{2\pi b_2 j} e^{\frac{-j}{2b_2}[d_2(u_2^2+r_2^2)-2u_2(d_2r_2-b_2s_2)]} \end{aligned} \quad (15)$$

*Proof* Applying the definition of the WVD-QOLCT we have

$$\begin{aligned} \mathcal{W}_{f \star g}^{A_1, A_2}(t, u) &= \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) \left[ (f \star g)\left(t + \frac{n}{2}\right) \right] \\ & \left[ \bar{f} \star \bar{g}\left(t - \frac{n}{2}\right) \right] K_{A_2}^j(n_2, u_2) dn \end{aligned} \quad (16)$$

Now using Definition 2 in (16) we have

$$\begin{aligned} & \mathcal{W}_{f \star g}^{A_1, A_2}(t, u) \\ &= \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) \left\{ \int_{\mathbf{R}^2} \Psi_1\left(z_1, t_1 + \frac{n_1}{2}\right) f(z) \right. \\ & \quad g\left(t + \frac{n}{2} - z\right) \Psi_2\left(z_2, t_2 + \frac{n_2}{2}\right) dz \\ & \quad \times \int_{\mathbf{R}^2} \Psi_1\left(\gamma_1, t_1 - \frac{n_1}{2}\right) \overline{f(\gamma)g\left(t - \frac{n}{2} - \gamma\right)} \\ & \quad \left. \Psi_2\left(\gamma_2, t_2 - \frac{n_2}{2}\right) d\gamma \right\} K_{A_2}^j(n_2, u_2) dn \\ &= \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) \left\{ \int_{\mathbf{R}^2} e^{-i\frac{a_1}{b_1}2z_1\left(\left(t_1 + \frac{n_1}{2}\right) - z_1\right)} f(z) \right. \\ & \quad g\left(t + \frac{n}{2} - z\right) e^{-j\frac{a_2}{b_2}2z_2\left(\left(t_2 + \frac{n_2}{2}\right) - z_2\right)} dz \\ & \quad \times \int_{\mathbf{R}^2} e^{-i\frac{a_1}{b_1}2\gamma_1\left(\left(t_1 - \frac{n_1}{2}\right) - \gamma_1\right)} \overline{f(\gamma)g\left(t - \frac{n}{2} - \gamma\right)} \\ & \quad \left. e^{-j\frac{a_2}{b_2}2\gamma_2\left(\left(t_2 - \frac{n_2}{2}\right) - \gamma_2\right)} d\gamma \right\} K_{A_2}^j(n_2, u_2) dn \end{aligned} \quad (17)$$

For simplicity let us denote

$$\begin{aligned} K_{A_1}^i(t_1, u_1) &= K_{A_1}^i e^{\frac{i}{2b_1}[a_1t_1^2+2t_1(r_1-u_1)-2u_1(d_1r_1-b_1s_1)+d_1u_1^2]}, \\ K_{A_1}^i &= \frac{1}{\sqrt{2\pi b_1 i}} e^{i\frac{d_1}{2b_1}r_1^2} \end{aligned} \quad (18)$$

and

$$\begin{aligned} K_{A_2}^j(t_2, u_2) &= K_{A_2}^j e^{\frac{j}{2b_2}[a_2t_2^2+2t_2(r_2-u_2)-2u_2(d_2r_2-b_2s_2)+d_2u_2^2]}, \\ K_{A_2}^j &= \frac{1}{\sqrt{2\pi b_2 j}} e^{j\frac{d_2}{2b_2}r_2^2} \end{aligned} \quad (19)$$

Now using (18) and (19) in (17), we have

$$\begin{aligned} & \mathcal{W}_{f \star g}^{A_1, A_2}(t, u) \\ &= \int_{\mathbf{R}^6} K_{A_1}^i e^{\frac{i}{2b_1}[a_1n_1^2+2n_1(r_1-u_1)-2u_1(d_1r_1-b_1s_1)+d_1u_1^2]} \\ & e^{-i\frac{a_1}{b_1}2z_1\left(\left(t_1 + \frac{n_1}{2}\right) - z_1\right)} \\ & \times f(z)g\left(t + \frac{n}{2} - z\right) e^{-j\frac{a_2}{b_2}2z_2\left(\left(t_2 + \frac{n_2}{2}\right) - z_2\right)} \\ & e^{-i\frac{a_1}{b_1}2\gamma_1\left(\left(t_1 - \frac{n_1}{2}\right) - \gamma_1\right)} \\ & \times \overline{f(\gamma)g\left(t - \frac{n}{2} - \gamma\right)} e^{-j\frac{a_2}{b_2}2\gamma_2\left(\left(t_2 - \frac{n_2}{2}\right) - \gamma_2\right)} \\ & \times K_{A_2}^j e^{\frac{j}{2b_2}[a_2n_2^2+2n_2(r_2-u_2)-2u_2(d_2r_2-b_2s_2)+d_2u_2^2]} dz d\gamma dn \end{aligned}$$

Setting  $z_i = w_i + \frac{p_i}{2}$ ,  $\gamma_i = w_i - \frac{p_i}{2}$ ,  $i = 1, 2$  we get

$$\begin{aligned} & \mathcal{W}_{f \star g}^{A_1, A_2}(t, u) \\ &= \int_{\mathbf{R}^6} K_{A_1}^i e^{\frac{i}{2b_1}[a_1n_1^2+2n_1(r_1-u_1)-2u_1(d_1r_1-b_1s_1)+d_1u_1^2]} \\ & e^{-i\frac{a_1}{b_1}2\left(w_1 + \frac{p_1}{2}\right)\left(\left(t_1 + \frac{n_1}{2}\right) - \left(w_1 + \frac{p_1}{2}\right)\right)} \\ & \times f\left(w + \frac{p}{2}\right) g\left(t + \frac{n}{2} - \left(w + \frac{p}{2}\right)\right) \\ & e^{-j\frac{a_2}{b_2}2\left(w_2 + \frac{p_2}{2}\right)\left(\left(t_2 + \frac{n_2}{2}\right) - \left(w_2 + \frac{p_2}{2}\right)\right)} \\ & \times e^{-i\frac{a_1}{b_1}2\left(w_1 - \frac{p_1}{2}\right)\left(\left(t_1 - \frac{n_1}{2}\right) - \left(w_1 - \frac{p_1}{2}\right)\right)} \\ & \times \overline{f\left(w - \frac{p}{2}\right) g\left(t - \frac{n}{2} - \left(w - \frac{p}{2}\right)\right)} \\ & \times e^{-j\frac{a_2}{b_2}2\left(w_2 - \frac{p_2}{2}\right)\left(\left(t_2 - \frac{n_2}{2}\right) - \left(w_2 - \frac{p_2}{2}\right)\right)} \\ & \times K_{A_2}^j e^{\frac{j}{2b_2}[a_2n_2^2+2n_2(r_2-u_2)-2u_2(d_2r_2-b_2s_2)+d_2u_2^2]} dp dq dw \end{aligned}$$

and  $n_i = p_i + q_i$ ,  $i = 1, 2$  we obtain

$$\begin{aligned} & \mathcal{W}_{f \star g}^{A_1, A_2}(t, u) \\ &= \int_{\mathbf{R}^6} K_{A_1}^i e^{\frac{i}{2b_1}[a_1(p_1+q_1)^2+2(p_1+q_1)(r_1-u_1)-2u_1(d_1r_1-b_1s_1)+d_1u_1^2]} \\ & e^{-i\frac{a_1}{b_1}(4w_1(t_1-w_1))} e^{-i\frac{a_1}{b_1}p_1q_1} \\ & \times f\left(w + \frac{p}{2}\right) \overline{f\left(w - \frac{p}{2}\right)} g\left(t - w + \frac{q}{2}\right) \overline{g\left(t - w - \frac{q}{2}\right)} \\ & e^{-j\frac{a_2}{b_2}(4w_2(t_2-w_2))} e^{-j\frac{a_2}{b_2}p_2q_2} \\ & \times K_{A_2}^j e^{\frac{j}{2b_2}[a_2n_2^2+2n_2(r_2-u_2)-2u_2(d_2r_2-b_2s_2)+d_2u_2^2]} dp dq dw \\ &= \int_{\mathbf{R}^2} \left\{ \int_{\mathbf{R}^2} K_{A_1}^i e^{\frac{i}{2b_1}[a_1p_1^2+2p_1(r_1-u_1)-2u_1(d_1r_1-b_1s_1)+d_1u_1^2]} \right. \\ & \left. f\left(w + \frac{p}{2}\right) \overline{f\left(w - \frac{p}{2}\right)} \right. \\ & \left. \times K_{A_2}^j e^{\frac{j}{2b_2}[a_2p_2^2+2p_2(r_2-u_2)-2u_2(d_2r_2-b_2s_2)+d_2u_2^2]} dp \right\} \end{aligned}$$

$$\begin{aligned} & \times \int_{\mathbf{R}^2} e^{\frac{i}{2b_1}[a_1q_1^2-2q_1(r_1-u_1)]} g\left(t-w+\frac{q}{2}\right) \\ & \times g\left(t-w-\frac{q}{2}\right) e^{\frac{j}{2b_2}[a_2q_2^2-2q_2(r_2-u_2)]} dq \Big\} \\ & \times e^{-i\frac{a_1}{b_1}(4w_1(t_1-w_1))} e^{-j\frac{a_2}{b_2}(4w_2(t_2-w_2))} dw \end{aligned} \quad (20)$$

Now multiply (20) both sides by  $K_{A_1}^i e^{\frac{i}{2b_1}[d_1u_1^2-2u_1(d_1r_1-b_1s_1)]}$  and  $K_{A_2}^j e^{\frac{j}{2b_2}[d_2u_2^2-2u_2(d_2r_2-b_2s_2)]}$ , we get

$$\begin{aligned} & K_{A_1}^i e^{\frac{i}{2b_1}[d_1u_1^2-2u_1(d_1r_1-b_1s_1)]} \\ & K_{A_2}^j e^{\frac{j}{2b_2}[d_2u_2^2-2u_2(d_2r_2-b_2s_2)]} \mathcal{W}_{f \star g}^{A_1, A_2}(t, u) \\ & = \int_{\mathbf{R}^2} e^{-i\frac{a_1}{b_1}(4w_1(t_1-w_1))} \mathcal{W}_{f, f}^{A_1, A_2}(w, u) \\ & \mathcal{W}_{g, g}^{A_1, A_2}(t-w, u) e^{-j\frac{a_2}{b_2}(4w_2(t_2-w_2))} dw \end{aligned} \quad (21)$$

Now using (18) and (19) in (21) we get,

$$\begin{aligned} & \mathcal{W}_{f \star g}^{A_1, A_2}(t, u) \\ & = \sqrt{2\pi b_1 i} e^{\frac{-i}{2b_1}[d_1(u_1^2+r_1^2)-2u_1(d_1r_1-b_1s_1)]} \\ & \times \left\{ \int_{\mathbf{R}^2} e^{-i\frac{a_1}{b_1}(4w_1(t_1-w_1))} \mathcal{W}_{f, f}^{A_1, A_2}(w, u) \mathcal{W}_{g, g}^{A_1, A_2}(t-w, u) \right. \\ & \left. e^{-j\frac{a_2}{b_2}(4w_2(t_2-w_2))} dw \right\} \\ & \times \sqrt{2\pi b_2 j} e^{\frac{-j}{2b_2}[d_2(u_2^2+r_2^2)-2u_2(d_2r_2-b_2s_2)]} \end{aligned}$$

which completes the proof of theorem.

### Consequences of theorem 6.

1. Changing parameter  $A_i = \begin{bmatrix} a_i & b_i & | & r_i \\ c_i & d_i & | & s_i \end{bmatrix}, i = 1, 2$  to

$A_i = \begin{bmatrix} a_i & b_i & | & 0 \\ c_i & d_i & | & 0 \end{bmatrix}, i = 1, 2$ , then the Theorem 4 reduces to convolution theorem of the WVD-QLCT as follows:

$$\begin{aligned} & \mathcal{W}_{f \star g}^{A_1, A_2}(t, u) \\ & = \sqrt{2\pi b_1 i} e^{\frac{-i}{2b_1}d_1u_1^2} \sqrt{2\pi b_2 j} e^{\frac{-j}{2b_2}d_2u_2^2} \\ & \times \left\{ \int_{\mathbf{R}^2} e^{-i\frac{a_1}{b_1}(4w_1(t_1-w_1))} \mathcal{W}_{f, f}^{A_1, A_2}(w, u) \mathcal{W}_{g, g}^{A_1, A_2}(t-w, u) \right. \\ & \left. e^{-j\frac{a_2}{b_2}(4w_2(t_2-w_2))} dw \right\} \end{aligned}$$

where  $\mathcal{W}_{f, f}^{A_1, A_2}$  and  $\mathcal{W}_{g, g}^{A_1, A_2}$  is the WVD in the QLCT domain of a signal  $f$  and  $g$ , respectively.

2. Changing parameter  $A_i = \begin{bmatrix} a_i & b_i & | & r_i \\ c_i & d_i & | & s_i \end{bmatrix}, i = 1, 2$

to  $A_i = \begin{bmatrix} 0 & 1 & | & 0 \\ -1 & 0 & | & 0 \end{bmatrix}, i = 1, 2$ , then the Theorem 4 reduces to convolution theorem of the WVD in Quaternion Domain as follows:

$$\mathcal{W}_{f \star g}(t, u) = \sqrt{2\pi i} \left\{ \int_{\mathbf{R}^2} \mathcal{W}_{f, f}^{i, j}(w, u) \mathcal{W}_{g, g}^{i, j}(t-w, u) dw \right\} \sqrt{2\pi j} \quad (23)$$

where  $\mathcal{W}_{f, f}^{i, j}$  and  $\mathcal{W}_{g, g}^{i, j}$  is the WVD in the Quaternion domain of a signal  $f$  and  $g$ , respectively.

Next, we will derive the correlation theorem in the WVD-QOLCT. Let us define the correlation for the QOLCT.

**Definition 3** For any two quaternion functions  $f, g \in L^2(\mathbf{R}^2, \mathbf{H})$ , we define the correlation operator of the QOLCT as

$$(f \circ g)(t) = \int_{\mathbf{R}^2} e^{i\frac{a_1}{b_1}2z_1(z_1+t_1)} \overline{f(z)} g(z+t) e^{j\frac{a_2}{b_2}2z_2(z_2+t_2)} dz \quad (24)$$

Now, we reap a consequence of the above definition .

**Theorem 7 (WVD-QOLCT Correlation).** For any two quaternion functions  $f, g \in L^2(\mathbf{R}^2, \mathbf{H})$ , the following result holds

$$\begin{aligned} & \mathcal{W}_{f \circ g}^{A_1, A_2}(t, u) \\ & = \sqrt{2\pi b_1 i} e^{\frac{-i}{2b_1}[d_1(u_1^2+r_1^2)+2u_1(d_1r_1-b_1s_1)]} \\ & \times \left\{ \int_{\mathbf{R}^2} e^{i\frac{a_1}{b_1}(4w_1(t_1+w_1))} \mathcal{W}_{f, f}^{A_1, A_2}(w, -u) \right. \\ & \left. \mathcal{W}_{g, g}^{A_1, A_2}(t+w, u) e^{j\frac{a_2}{b_2}(4w_2(t_2+w_2))} dw \right\} \\ & \times \sqrt{2\pi b_2 j} e^{\frac{-j}{2b_2}[d_2(u_2^2+r_2^2)+2u_2(d_2r_2-b_2s_2)]} \end{aligned} \quad (25)$$

*Proof* Applying the definition of the WVD-QOLCT we have

$$\begin{aligned} & \mathcal{W}_{f \circ g}^{A_1, A_2}(t, u) \\ & = \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) \left[ (f \circ g)(t + \frac{n}{2}) \right] \\ & \left[ \overline{f} \circ \overline{g}(t - \frac{n}{2}) \right] K_{A_2}^j(n_2, u_2) dn \end{aligned} \quad (26)$$

Now using definition 3 in (26) we have

$$\begin{aligned} & \mathcal{W}_{f \circ g}^{A_1, A_2}(t, u) \\ & = \int_{\mathbf{R}^2} K_{A_1}^i(n_1, u_1) \left\{ \int_{\mathbf{R}^2} e^{i\frac{a_1}{b_1}2z_1(z_1+(t_1+\frac{n_1}{2}))} \overline{f(z)} \right. \\ & \left. g(z+t+\frac{n}{2}) e^{j\frac{a_2}{b_2}2z_2(z_2+(t_2+\frac{n_2}{2}))} dz \right. \\ & \times \int_{\mathbf{R}^2} e^{i\frac{a_1}{b_1}2\gamma_1(\gamma_1+(t_1-\frac{n_1}{2}))} \overline{f(\gamma)} \overline{g(\gamma+(t-\frac{n}{2}))} \\ & \left. e^{j\frac{a_2}{b_2}2\gamma_2(\gamma_2+(t_2-\frac{n_2}{2}))} d\gamma \right\} K_{A_2}^j(n_2, u_2) dn \end{aligned} \quad (27)$$

Now with the help of (18) and (19), we have from (27)

$$\begin{aligned} & \mathcal{W}_{f \circ g}^{A_1, A_2}(t, u) \\ & = \int_{\mathbf{R}^6} K_{A_1}^i e^{\frac{i}{2b_1}[a_1n_1^2+2n_1(r_1-u_1)-2u_1(d_1r_1-b_1s_1)+d_1u_1^2]} \\ & e^{i\frac{a_1}{b_1}2z_1(z_1+(t_1+\frac{n_1}{2}))} \\ & \times \overline{f(z)} g(z+(t+\frac{n}{2})) e^{j\frac{a_2}{b_2}2z_2(z_2+(t_2+\frac{n_2}{2}))} e^{i\frac{a_1}{b_1}2\gamma_1(\gamma_1+(t_1-\frac{n_1}{2}))} \\ & \times \overline{f(\gamma)} g(\gamma+(t-\frac{n}{2})) e^{j\frac{a_2}{b_2}2\gamma_2(\gamma_2+(t_2-\frac{n_2}{2}))} \\ & \times K_{A_2}^j e^{\frac{j}{2b_2}[a_2n_2^2+2n_2(r_2-u_2)-2u_2(d_2r_2-b_2s_2)+d_2u_2^2]} dz d\gamma dn \end{aligned}$$

Setting  $z_i = w_i + \frac{p_i}{2}$ ,  $\gamma_i = w_i - \frac{p_i}{2}$ ,  $i = 1, 2$ , we get

$$\begin{aligned} & \mathcal{W}_{f \circ g}^{A_1, A_2}(t, u) \\ &= \int_{\mathbf{R}^6} K_{A_1}^i e^{\frac{i}{2b_1}[a_1 n_1^2 + 2n_1(r_1 - u_1) - 2u_1(d_1 r_1 - b_1 s_1) + d_1 u_1^2]} \\ & e^{i \frac{a_1}{b_1} 2(w_1 + \frac{p_1}{2})((t_1 + \frac{n_1}{2}) + (w_1 + \frac{p_1}{2}))} \\ & \times \overline{f\left(w + \frac{p}{2}\right) g\left(t + \frac{n}{2} + \left(w + \frac{p}{2}\right)\right)} \\ & e^{j \frac{a_2}{b_2} 2(w_2 + \frac{p_2}{2})((t_2 + \frac{n_2}{2}) + (w_2 + \frac{p_2}{2}))} \\ & \times e^{i \frac{a_1}{b_1} 2(w_1 - \frac{p_1}{2})((t_1 - \frac{n_1}{2}) + (w_1 - \frac{p_1}{2}))} f\left(w - \frac{p}{2}\right) \\ & \overline{g\left(t - \frac{n}{2} + \left(w - \frac{p}{2}\right)\right)} \\ & \times e^{j \frac{a_2}{b_2} 2(w_2 - \frac{p_2}{2})((t_2 - \frac{n_2}{2}) + (w_2 - \frac{p_2}{2}))} K_{A_2}^j \\ & e^{\frac{j}{2b_2}[a_2 n_2^2 + 2n_2(r_2 - u_2) - 2u_2(d_2 r_2 - b_2 s_2) + d_2 u_2^2]} dpdqdw \quad (28) \end{aligned}$$

Now put  $n_i = q_i - p_i$ ,  $i = 1, 2$  and on following the same procedure as followed in previous Theorem 6, we have from (28)

$$\begin{aligned} & \mathcal{W}_{f \circ g}^{A_1, A_2}(t, u) \\ &= \int_{\mathbf{R}^2} \left[ \int_{\mathbf{R}^2} e^{\frac{i}{2b_1}[a_1 p_1^2 - 2p_1(r_1 - u_1)]} \overline{f\left(w + \frac{p}{2}\right) f\left(w - \frac{p}{2}\right)} \right. \\ & \left. e^{\frac{j}{2b_2}[a_2 p_2^2 - 2p_2(r_2 - u_2)]} dp \right] \\ & \times \left[ \int_{\mathbf{R}^2} K_{A_1}^i e^{\frac{i}{2b_1}[a_1 q_1^2 + 2q_1(r_1 - u_1) - 2u_1(d_1 r_1 - b_1 s_1) + d_1 u_1^2]} \right. \\ & \times g\left(t + w + \frac{q}{2}\right) \overline{g\left(t + w - \frac{q}{2}\right)} \\ & \times K_{A_2}^j e^{\frac{j}{2b_2}[a_2 q_2^2 + 2q_2(r_2 - u_2) - 2u_2(d_2 r_2 - b_2 s_2) + d_2 u_2^2]} dq \left. \right] \\ & \times e^{i \frac{a_1}{b_1}(4w_1(t_1 + w_1))} e^{j \frac{a_2}{b_2}(4w_2(t_2 + w_2))} dw \quad (29) \end{aligned}$$

On multiplying (29) both sides by

$K_{A_1}^i e^{\frac{i}{2b_1}[d_1 u_1^2 - 2u_1(d_1 r_1 - b_1 s_1) + 4p_1(r_1 - u_1)]}$  and  $K_{A_2}^j e^{\frac{j}{2b_2}[d_2 u_2^2 - 2u_2(d_2 r_2 - b_2 s_2) + 4p_2(r_2 - u_2)]}$ , we get

$$\begin{aligned} & K_{A_1}^i e^{\frac{i}{2b_1}[d_1 u_1^2 - 2u_1(d_1 r_1 - b_1 s_1) + 4p_1(r_1 - u_1)]} \\ & K_{A_2}^j e^{\frac{j}{2b_2}[d_2 u_2^2 - 2u_2(d_2 r_2 - b_2 s_2) + 4p_2(r_2 - u_2)]} \mathcal{W}_{f \circ g}^{A_1, A_2}(t, u) \\ &= \int_{\mathbf{R}^2} e^{-i \frac{a_1}{b_1}(4w_1(t_1 - w_1))} \mathcal{W}_{f, f}^{A_1, A_2}(w, u) \\ & \mathcal{W}_{g, g}^{A_1, A_2}(t - w, u) e^{-j \frac{a_2}{b_2}(4w_2(t_2 - w_2))} dw \quad (30) \end{aligned}$$

Now using (18) and (19) in (30) we obtain,

$$\begin{aligned} & \mathcal{W}_{f * g}^{A_1, A_2}(t, u) \\ &= \sqrt{2\pi b_1 i} e^{\frac{-i}{2b_1}[d_1(u_1^2 + r_1^2) + 2u_1(d_1 r_1 - b_1 s_1)]} \\ & \times \left\{ \int_{\mathbf{R}^2} e^{i \frac{a_1}{b_1}(4w_1(t_1 + w_1))} \mathcal{W}_{f, f}^{A_1, A_2}(w, -u) \mathcal{W}_{g, g}^{A_1, A_2}(t + w, u) \right. \\ & \left. \times e^{j \frac{a_2}{b_2}(4w_2(t_2 + w_2))} dw \right\} \sqrt{2\pi b_2 j} e^{\frac{-j}{2b_2}[d_2(u_2^2 + r_2^2) + 2u_2(d_2 r_2 - b_2 s_2)]} \end{aligned}$$

which completes the proof of theorem.

## Consequences of Theorem 7.

1. Changing parameter  $A_i = \begin{bmatrix} a_i & b_i & | & r_i \\ c_i & d_i & | & s_i \end{bmatrix}$ ,  $i = 1, 2$  to

$A_i = \begin{bmatrix} a_i & b_i & | & 0 \\ c_i & d_i & | & 0 \end{bmatrix}$ ,  $i = 1, 2$ , then the Theorem 7 reduces to correlation theorem of the WVD-QLCT as follows:

$$\begin{aligned} & \mathcal{W}_{f \circ g}^{A_1, A_2}(t, u) \\ &= \sqrt{2\pi b_1 i} e^{\frac{-i}{2b_1} d_1 u_1^2} \sqrt{2\pi b_2 j} e^{\frac{-j}{2b_2} d_2 u_2^2} \\ & \times \left\{ \int_{\mathbf{R}^2} e^{i \frac{a_1}{b_1}(4w_1(t_1 + w_1))} \mathcal{W}_{f, f}^{A_1, A_2}(w, -u) \right. \\ & \left. \mathcal{W}_{g, g}^{A_1, A_2}(t + w, u) e^{j \frac{a_2}{b_2}(4w_2(t_2 + w_2))} dw \right\} \end{aligned}$$

where  $\mathcal{W}_{f, f}^{A_1, A_2}$  and  $\mathcal{W}_{g, g}^{A_1, A_2}$  is the WVD in the QLCT domain of a signal  $f$  and  $g$ , respectively.

2. Changing parameter  $A_i = \begin{bmatrix} a_i & b_i & | & r_i \\ c_i & d_i & | & s_i \end{bmatrix}$ ,  $i = 1, 2$  to

$A_i = \begin{bmatrix} 0 & 1 & | & 0 \\ -1 & 0 & | & 0 \end{bmatrix}$ ,  $i = 1, 2$ , then the Theorem 4.4 reduces to correlation theorem of the WVD in Quaternion Domain as follows:

$$\mathcal{W}_{f \circ g}(t, u) = \sqrt{2\pi i} \left\{ \int_{\mathbf{R}^2} \mathcal{W}_{f, f}^{i, j}(w, -u) \mathcal{W}_{g, g}^{i, j}(t + w, u) dw \right\} \sqrt{2\pi j}$$

where  $\mathcal{W}_{f, f}^{i, j}$  and  $\mathcal{W}_{g, g}^{i, j}$  is the WVD in the Quaternion domain of a signal  $f$  and  $g$ , respectively.

**Acknowledgements** This work is supported by the UGC-BSR Research Start Up Grant(No. F.30-498/2019(BSR)) provided by UGC, Govt. of India.

## Conflict of interest

The authors declare that they have no conflict of interest.

## References

1. M. Bahri, R. Ashino, and R. Vaillancourt, *Convolution theorems for quaternion Fourier transform: properties and applications*, Abst. Appl Anal. 2013, Article ID 162769.
2. M. Bahri, E. S. M. Hitzer, A. Hayashi, and R. Ashino, *An uncertainty principle for quaternion Fourier transform*, Comps. Maths with Appl., 56( 9) 2398–2410(2008).
3. M. Bahri, *Correlation theorem for Wigner-Ville distribution*, Far East J. Math. Sci. 80(1) 123– 133(2013) .
4. R. F. Bai, B. Z. Li, and Q. Y. Cheng, *Wigner-Ville distribution associated with the linear canonical transform*, J. Appl. Maths, 2012, Article ID 740161.
5. L. Debnath, B. V. Shankara, and N. Rao, *On new two-dimensional Wigner-Ville nonlinear integral transforms and their basic properties*, Int. Trans. Sp. Funct. , 21(3) 165–174(2010).
6. W. B. Gao and B. Z. Li, *Convolution and correlation theorems for the windowed offset linear canonical transform* arxiv: 1905.01835v2 [math.GM](2019)
7. X. Guanlei, W. Xiaotong, X. Xiaogang, *Uncertainty inequalities for linear canonical transform*. IET Signal Process. 3(5) 392–402 (2009)
8. Y. El Haoui S. and S. Fahlaoui , *Generalized Uncertainty Principles associated with the Quaternionic Offset Linear Canonical Transform*, <https://arxiv.org/abs/1807.04068v1>.
9. E. M. S. Hitzer, *Quaternion Fourier transform on quaternion fields and generalizations*, Adv. Appl. Clifford Algs , 17(3) 497–517(2007) .
10. H. Y. Huo, W. C. Sun, L. Xiao, *Uncertainty principles associated with the offset linear canonical transform* Mathl. Methods Appl. Scis. 42(2) 466-474(2019) .
11. K. I. Kou, Jian-YuOu, J. Morais, *On uncertainty principle for quaternionic linear canonical transform*, Abstr. Appl. Anal.,2013 (Article ID 725952) (2013) 14pp
12. K. I. Kou, J. Morais and Y. Zhang, *Generalized prolate spheroidal wave functions for offset linear canonical transform in clifford analysis*, Mathematical Methods in the Applied Sciences 36 (9) 1028-1041(2013).
13. Y. G. Li, B. Z Li and H. F. Sun, *Uncertainty principle for Wigner-Ville distribution associated with the linear canonical transform*, Abstr. Appl. Anal., 2014, Article ID 470459.
14. Y.E. Song, X.Y. Zhang, C.H. Shang, H.X. Bu, X.Y. Wang, *The Wigner-Ville distribution based on the linear canonical transform and its applications for QFM signal parameters estimation*, J. App. Maths (2014) 8 pages.
15. D. Urynbassarova, B. Z. Li, and R. Tao, *The Wigner-Ville distribution in the linear canonical transform domain*, IAENG Int. J. Appl. Maths. 46 (4) 559-563(2016).
16. D. Urynbassarova, B.Zhao, R.Tao, *Convolution and Correlation Theorems for Wigner-Ville Distribution Associated with the Offset Linear Canonical Transform*. Int. J. Light Elect. Optics <http://dx.doi.org/10.1016/j.ijleo.2017.08.099>
17. D. Wei, Q. Ran, and Y. Li, *A convolution and correlation theorem for the linear canonical transform and its application*, Circuits Syst. Signal Process., 31(1) 301–312(2012).
18. D. Wei, Q. Ran, and Y. Li, *New convolution theorem for the linear canonical transform and its translation invariance property*, Optik., 123(16) 1478–1481(2012).
19. Z. C. Zhang, *Sampling theorem for the short-time linear canonical transform and its applications*. Signal Proces. 113138-146( 2015) .