

On the Sample Complexity of Decentralized Linear Quadratic Regulator with Partially Nested Information Structure

Lintao Ye* Zhu Hao† Vijay Gupta*

October 15, 2021

Abstract

We study the problem of control policy design for decentralized state-feedback linear quadratic control with a partially nested information structure, when the system model is unknown. We propose a model-based learning solution, which consists of two steps. First, we estimate the unknown system model from a single system trajectory of finite length, using least squares estimation. Next, based on the estimated system model, we design a control policy that satisfies the desired information structure. We show that the suboptimality gap between our control policy and the optimal decentralized control policy (designed using accurate knowledge of the system model) scales linearly with the estimation error of the system model. Using this result, we provide an end-to-end sample complexity result for learning decentralized controllers for a linear quadratic control problem with a partially nested information structure.

1 Introduction

In large-scale control systems, the control policy is often required to be decentralized, where different controllers may only use partial state information, when designing their local control policies. For example, a given controller may only receive a subset of the global state measurements (e.g., [35]), and there may be a delay in receiving the measurements (e.g., [25]). In general, finding a globally optimal control policy under information constraints is NP-hard, even if the system model is known at the controllers [39, 31, 6]. This has led to a large literature on identifying tractable subclasses of the problem. For instance, if the information structure describing the decentralized control problem is partially nested [21], the optimal solution to the state-feedback linear quadratic control problem can be solved efficiently using dynamic programming [26]. Other conditions, such as quadratic invariance [32, 33], have also been identified as tractable subclasses of the problem.

However, the classical work in this field assumes the knowledge of the system model at the controllers. In this work, we are interested in the situation when the system model is not known a priori [23]. In such a case, the existing algorithms do not apply. Moreover, it is not clear whether subclasses such as problems with partially nested information patterns or where quadratic invariance is satisfied are any more tractable than the general decentralized control problem in this case.

In this paper, we consider a decentralized infinite-horizon state-feedback Linear Quadratic Regulator (LQR) control problem with a partially nested information structure [35, 26] and assume that the controllers do not have access to the system model. We use a model-based learning approach, where we first identify the system model, and then use it to design a control policy that satisfies the prescribed information constraints. Using this approach, we provide an end-to-end sample complexity result, which relates the number of data samples used for estimating the system model to the performance of the control policy. The performance of the control policy is characterized by the gap between the infinite-horizon LQR cost of our control policy and that of the optimal control policy for the partially nested information structure when the system model is known a priori, as obtained in [26].

*Department of Electrical Engineering at the University of Notre Dame, Notre Dame, IN, USA; lye2@nd.edu, vgupta2@nd.edu.

†Department of Electrical and Computer Engineering at the University of Texas at Austin, Austin, TX, USA; haozhu@utexas.edu.

Related Work

Solving optimal control problems without prior system model knowledge has received much attention recently. One of the most studied problems is the centralized LQR problem. For this problem, two broad classes of methods have been studied, i.e., model-based learning [1, 29, 12], and model-free learning [16, 40, 28, 20]. In the model-based learning approach, a system model is first estimated from observed system trajectories using some system identification method. A control policy can then be obtained based on the estimated system model. In the model-free learning approach, the objective function in the LQR problem is first viewed as a function of the control policies. Based on zeroth-order optimization methods (e.g., [19, 30]), the optimal solution can then be obtained using gradient descent, where the gradient of the objective function is estimated from the data samples from system trajectories. Moreover, the model-based learning approach has also been studied for the centralized linear quadratic Gaussian control problem [42]. In general, compared to model-free learning, model-based learning tends to require less data samples in order to achieve a policy of equivalent performance [38].

Most of the previous works on model-based learning for centralized LQR build on recent advances in non-asymptotic analyses for system identification of linear dynamical systems with full state observations (e.g., [13, 36, 34]). Such non-asymptotic analyses (i.e., sample complexity results) relate the estimation error of the system matrices to the number of samples used for system identification. In particular, it was shown in [36] that when using a single system trajectory, the least squares approach for system identification achieves the optimal sample complexity up to logarithmic factors. In this paper, we utilize a similar least squares approach for estimating the system matrices from a single system trajectory. Although the system matrices in our problem are structured, as dictated by the interconnections among the subsystems, we leverage the results in [2, 10] to provide a non-asymptotic analysis of the resulting estimation error.

There are few results on solving decentralized linear quadratic control problems with information constraints, when the system model is unknown. In [18], the authors studied a decentralized output-feedback linear quadratic control problem, under the assumption that the quadratic invariance condition is satisfied. The authors proposed a model-free approach and provided a sample complexity analysis. They focused on a finite-horizon setting, since gradient-based optimization methods may not converge to the optimal controller for infinite-horizon decentralized linear quadratic control problems with information constraints, even when the system model is known [17, 7]. In [27], the authors proposed a consensus-based model-free learning algorithm for multi-agent decentralized LQR over an infinite horizon, where each agent (i.e., controller) has access to a subset of the global state without delay. They showed that their algorithm converges to a control policy that is a stationary point of the objective function in the LQR problem. In [15], the authors studied model-based learning for LQR with subspace constraints on the closed-loop responses. However, those constraints may not lead to controllers that satisfy the information constraints that we consider in this paper (e.g., [41]).

There is also a line of research on online adaptive control for centralized LQR with unknown system models, using either model-based learning [1, 11, 10], or model-free learning [3, 8]. The goal there is to adaptively design a control policy in an online manner when new data samples from the system trajectory become available, and bound the corresponding regret.

Contributions

We propose a two-step model-based approach to learning decentralized LQR with a partially nested information structure. First, we use a least squares approach for estimating the system model from a single system trajectory. We analyze the resulting estimation error and provide a sample complexity result. Next, based on the estimated system model, we design a control policy that satisfies the prescribed information constraints. We analyze the performance guarantees of the control policy, and show that the suboptimality gap between our control policy and the optimal decentralized control policy (designed based on accurate knowledge of the system model) scales linearly with the estimation error of the system model. Combining the above results, we provide an end-to-end sample complexity result for learning decentralized LQR with a partially nested information structure. Despite the existence of the information constraint and the fact that the optimal controller is a linear dynamic controller, our sample complexity result matches with that of learning centralized LQR without any information constraints [12].

2 Preliminaries and Problem Formulation

2.1 Notation and Terminology

The sets of integers and real numbers are denoted as \mathbb{Z} and \mathbb{R} , respectively. The set of integers (resp., real numbers) that are greater than or equal to $a \in \mathbb{R}$ is denoted as $\mathbb{Z}_{\geq a}$ (resp., $\mathbb{R}_{\geq a}$). For a real number a , let $\lceil a \rceil$ be the smallest integer that is greater than or equal to a . The space of m -dimensional real vectors is denoted by \mathbb{R}^m , and the space of $m \times n$ real matrices is denoted by $\mathbb{R}^{m \times n}$. For a matrix $P \in \mathbb{R}^{n \times n}$, let P^\top , $\text{Tr}(P)$, and $\{\sigma_i(P) : i \in \{1, \dots, n\}\}$ be its transpose, trace, and set of singular values, respectively. Without loss of generality, let the singular values of P be ordered as $\sigma_1(P) \geq \dots \geq \sigma_n(P)$. Let $\|\cdot\|$ denote the ℓ_2 norm, i.e., $\|P\| = \sigma_1(P)$ for a matrix $P \in \mathbb{R}^{n \times n}$, and $\|x\| = \sqrt{x^\top x}$ for a vector $x \in \mathbb{R}^n$. Let $\|P\|_F = \sqrt{\text{Tr}(PP^\top)}$ denote the Frobenius norm of $P \in \mathbb{R}^{n \times m}$. A positive semidefinite matrix P is denoted by $P \succeq 0$, and $P \succeq Q$ if and only if $P - Q \succeq 0$. Let \mathbb{S}_+^n (resp., \mathbb{S}_{++}^n) denote the set of $n \times n$ positive semidefinite (resp., positive definite) matrices. Let I denote an identity matrix whose dimension can be inferred from the context. Given any integer $n \geq 1$, we define $[n] = \{1, \dots, n\}$. The cardinality of a finite set \mathcal{A} is denoted by $|\mathcal{A}|$.

2.2 Solution to Decentralized LQR with Sparsity and Delay Constraints

In this section, we sketch the method developed in [26, 35], which presents the optimal solution to a decentralized LQR problem with a *partially nested* information structure, when the system model is known a priori. First, let us consider a *directed* graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$ with $\mathcal{V} = [p]$, and assume that $\mathcal{G}(\mathcal{V}, \mathcal{A})$ does not have self loops, where $p \in \mathbb{Z}_{\geq 1}$. Next, given the directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$, we associate each edge in \mathcal{A} with a delay of either 0 or 1.¹ If there is an edge from node j to i in $\mathcal{G}(\mathcal{V}, \mathcal{A})$, we denote the corresponding edge as (j, i) or $j \rightarrow i$. Then, we define the delay matrix corresponding to $\mathcal{G}(\mathcal{V}, \mathcal{A})$ as $D \in \mathbb{R}^{p \times p}$ such that: (i) If $i \neq j$ and there is a directed path from j to i in $\mathcal{G}(\mathcal{V}, \mathcal{A})$, then D_{ij} is equal to the sum of delays along the directed path from node j to node i with the smallest accumulative delay; (ii) If $i \neq j$ and there is no directed path from j to i in $\mathcal{G}(\mathcal{V}, \mathcal{A})$, then $D_{ij} = +\infty$; (iii) $D_{ii} = 0$ for all $i \in \mathcal{V}$. At each node $i \in \mathcal{V}$, we consider a discrete-time linear time-invariant (LTI) system given by

$$x_i(t+1) = \left(\sum_{\substack{j \in \mathcal{V} \\ D_{ij} \leq 1}} A_{ij} x_j(t) + B_{ij} u_j(t) \right) + w_i(t) \quad \forall i \in \mathcal{V}, \quad (1)$$

where $A_{ij} \in \mathbb{R}^{n_i \times n_j}$, $B_{ij} \in \mathbb{R}^{n_i \times m_j}$, and $w_i(t) \in \mathbb{R}^{n_i}$ is a white Gaussian noise process with $w_i(t) \sim \mathcal{N}(0, \sigma_w^2 I)$ for all $t \in \mathbb{Z}_{\geq 0}$, where $\sigma_w \in \mathbb{R}_{>0}$.² For simplicity, we assume throughout this paper that $n_i \geq m_i$ for all $i \in \mathcal{V}$. We see from Eq. (1) that each node $i \in \mathcal{V}$ can be associated with state $x_i(t) \in \mathbb{R}^{n_i}$ of an LTI system, and $u_i(t) \in \mathbb{R}^{m_i}$ is the control input corresponding to node $i \in \mathcal{V}$. Letting $n = \sum_{i \in \mathcal{V}} n_i$ and $m = \sum_{i \in \mathcal{V}} m_i$, and defining $x(t) = [x_1(t)^\top \dots x_p(t)^\top]^\top$, $u(t) = [u_1(t)^\top \dots u_p(t)^\top]^\top$ and $w(t) = [w_1(t)^\top \dots w_p(t)^\top]^\top$, we can compactly write Eq. (1) into the following matrix form:

$$x(t+1) = Ax(t) + Bu(t) + w(t), \quad (2)$$

where the (i, j) th block of $A \in \mathbb{R}^{n \times n}$ (resp., $B \in \mathbb{R}^{n \times m}$), i.e., A_{ij} (resp., B_{ij}), satisfies $A_{ij} = 0$ (resp., $B_{ij} = 0$), if $D_{ij} > 1$. We assume that $w_i(t_1)$ and $w_j(t_2)$ are independent for all $i, j \in \mathcal{V}$ with $i \neq j$ and for all $t_1, t_2 \in \mathbb{Z}_{\geq 0}$. In other words, $w(t)$ is a white Gaussian noise process with $w(t) \sim \mathcal{N}(0, \sigma_w^2 I)$ for all $t \in \mathbb{Z}_{\geq 0}$. For simplicity, we assume that $x(0) = 0$ throughout this paper.³

Now, denoting

$$\mathcal{N}_i = \{j \in \mathcal{V} : D_{ij} \leq 1\}, \quad (3)$$

we can also rewrite Eq. (1) as

$$x_i(t+1) = A_i x_{\mathcal{N}_i}(t) + B_i u_{\mathcal{N}_i}(t) + w_i(t) \quad \forall i \in \mathcal{V}, \quad (4)$$

¹The framework described in this paper can also be used to handle $\mathcal{G}(\mathcal{V}, \mathcal{A})$ with larger delays; see [26] for a detailed discussion.

²The analysis can be extended to the case when $w_i(t)$ is a zero-mean white Gaussian noise process with covariance $W \in \mathbb{S}_{++}^{n_i}$. In that case, our analysis will depend on $\max_{i \in \mathcal{V}} \sigma_1(W_i)$ and $\min_{i \in \mathcal{V}} \sigma_n(W_i)$.

³The analysis can be extended to the case when $x(0)$ is given by a zero-mean Gaussian distribution, as one may view $x(0)$ as $w(-1)$.

where $A_i \triangleq [A_{ij_1} \ \cdots \ A_{ij_{|\mathcal{N}_i|}}]$, $B_i \triangleq [B_{ij_1} \ \cdots \ B_{ij_{|\mathcal{N}_i|}}]$, $x_{\mathcal{N}_i}(t) \triangleq [x_{j_1}(t) \ \cdots \ x_{j_{|\mathcal{N}_i|}}(t)]^\top$, and $u_{\mathcal{N}_i}(t) \triangleq [u_{j_1}(t) \ \cdots \ u_{j_{|\mathcal{N}_i|}}(t)]^\top$, with $\mathcal{N}_i = \{j_1, \dots, j_{|\mathcal{N}_i|}\}$. We note from Eq. (1) that if there does not exist a directed path with a 0 or 1 accumulative delay from node j to node i in $\mathcal{G}(\mathcal{V}, \mathcal{A})$, then the state $x_j(t)$ corresponding to node j does not directly affect the state $x_i(t+1)$ corresponding to node i . Also note that as argued in [26], we assume that there is no directed cycle with zero accumulative delay; otherwise, one can first collapse all the nodes in such a directed cycle into a single node, and equivalently consider the resulting directed graph in the framework described above.

Next, we consider designing the control input $u(t)$ for the LTI system in Eq. (2). We focus on *state-feedback* control, i.e., we can view $u(t)$ as a policy that maps the states of the LTI system to a control input. Moreover, we require that $u(t)$ satisfy a certain information structure according to the directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$ and the delay matrix $D \in \mathbb{R}^{p \times p}$, described above. Specifically, considering any $i \in \mathcal{V}$ and any $t \in \mathbb{Z}_{\geq 0}$, and noting that the controller corresponding to node $i \in \mathcal{V}$ provides the control input $u_i(t) \in \mathbb{R}^{m_i}$, the state information that is available to the controller $i \in \mathcal{V}$ is given by

$$\mathcal{I}_i(t) = \{x_j(k) : j \in \mathcal{V}_i, 0 \leq k \leq t - D_{ij}\}, \quad (5)$$

where $\mathcal{V}_i \triangleq \{j \in \mathcal{V} : D_{ij} \neq +\infty\}$. In other words, the control policy $u_i(t)$ maps the states contained in $\mathcal{I}_i(t)$ to a control input. In the sequel, we also call $\mathcal{I}_i(t)$ the *information set* of controller $i \in \mathcal{V}$ at time $t \in \mathbb{Z}_{\geq 0}$. Now, based on the information set $\mathcal{I}_i(t)$, we further define $\mathcal{S}(\mathcal{I}_i(t))$ to be the set that consists of all the policies that map the states in $\mathcal{I}_i(t)$ to a control input at node i . The goal is then to solve the following constrained optimization problem:

$$\begin{aligned} \min_{u(0), u(1), \dots} \lim_{T \rightarrow \infty} \mathbb{E} \left[\frac{1}{T} \sum_{t=0}^{T-1} (x(t)^\top Q x(t) + u(t)^\top R u(t)) \right] \\ \text{s.t. } x(t+1) = Ax(t) + Bu(t) + w(t), \\ u_i(t) \in \mathcal{S}(\mathcal{I}_i(t)) \quad \forall i \in \mathcal{V}, \forall t \in \mathbb{Z}_{\geq 0}, \end{aligned} \quad (6)$$

where $Q \in \mathbb{S}_+^m$ and $R \in \mathbb{S}_+^n$ are the cost matrices, the expectation is taken with respect to $w(t)$ for all $t \in \mathbb{Z}_{\geq 0}$, and $x(0) = 0$. Under the block structure of the system matrices A and B described above, and the information set given by Eq. (5), [26] shows that problem (6) is partially nested [21].

In order to present the solution to (6) given in, e.g., [26], we need to construct an information graph $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ (see [26] for more details). Considering any directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$ with $\mathcal{V} = [p]$, and the delay matrix $D \in \mathbb{R}^{p \times p}$ as we described above, let us first define $s_j(k)$ to be the set of nodes in $\mathcal{G}(\mathcal{V}, \mathcal{A})$ that are reachable from node j within k time steps, i.e., $s_j(k) = \{i \in \mathcal{V} : D_{ij} \leq k\}$. The information graph $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ is then constructed as

$$\begin{aligned} \mathcal{U} &= \{s_j(k) : k \geq 0, j \in \mathcal{V}\}, \\ \mathcal{H} &= \{(s_j(k), s_j(k+1)) : k \geq 0, j \in \mathcal{V}\}. \end{aligned} \quad (7)$$

Thus, we see from (7) that each node $s \in \mathcal{U}$ corresponds to a set of nodes from $\mathcal{V} = [p]$ in the original directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$. Using a similar notation to that for the graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$, if there is an edge from s to r in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, we denote the edge as $s \rightarrow r$. Additionally, considering any $s_i(0) \in \mathcal{U}$, we write $w_i \rightarrow s_i(0)$ to indicate the fact that the noise $w_i(t)$ is injected to node $i \in \mathcal{V}$ at time $t \in \mathbb{Z}_{\geq 0}$.⁴ From the above construction of the information graph $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, one can show that the following properties hold.

Lemma 1. [26, Proposition 1] *Given a directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$ with $\mathcal{V} = [p]$, the information graph $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ constructed in (7) satisfies the following: (i) For every $r \in \mathcal{U}$, there is a unique $s \in \mathcal{U}$ such that $(r, s) \in \mathcal{H}$, i.e., $r \rightarrow s$; (ii) every path in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ ends at a node with a self loop; and (iii) $n \leq |\mathcal{U}| \leq p^2 - p + 1$.*

Remark 1. *One can see from the construction of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ and Lemma 1 that $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ is a forest, i.e., a set of disconnected directed trees, where each directed tree in the forest is oriented to a node with a self loop in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$. Specifically, $s_i(0)$ for all $i \in \mathcal{V}$ are the leaf nodes in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, and the nodes with self loop are root nodes in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$.*

⁴Note that we have assumed that there is no directed cycle with zero accumulative delay in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$. Hence, one can show that for any $s_i(0) \in \mathcal{U}$, w_i is the only noise term such that $w_i \rightarrow s_i(0)$.

Throughout this paper, we assume that the elements in $\mathcal{V} = [p]$ are ordered in an increasing manner, and that the elements in s are also ordered in an increasing manner for all $s \in \mathcal{U}$. Now, for any $s, r \in \mathcal{U}$, we use A_{sr} (or $A_{s,r}$) to denote the submatrix of A that corresponds to the nodes in s and r . For example, $A_{\{1\},\{1,2\}} = \begin{bmatrix} A_{11} & A_{12} \end{bmatrix}$. In the sequel, we will also use similar notations to denote submatrices of B , Q , R and the identity matrix I . We will make the following standard assumptions (see, e.g., [26]).

Assumption 1. For any $s \in \mathcal{U}$ that has a self loop, the pair (A_{ss}, B_{ss}) is stabilizable and the pair (A_{ss}, C_{ss}) is detectable, where $Q_{ss} = C_{ss}^\top C_{ss}$.

Leveraging the partial nestedness of (6), the authors in [26] obtained the optimal solution to (6), which we summarize in the following lemma.

Lemma 2. [26, Corollary 4] Consider the problem given in (6), and let $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ be the associated information graph. Suppose Assumption 1 holds. For all $r \in \mathcal{U}$, define matrices P_r and K_r recursively as

$$K_r = -(R_{rr} + B_{sr}^\top P_s B_{sr})^{-1} B_{sr}^\top P_s A_{sr}, \quad (8)$$

$$P_r = Q_{rr} + K_r^\top R_{rr} K_r + (A_{sr} + B_{sr} K_r)^\top P_s (A_{sr} + B_{sr} K_r), \quad (9)$$

where for each $r \in \mathcal{U}$, $s \in \mathcal{U}$ is the unique node such that $r \rightarrow s$. In particular, for any $s \in \mathcal{U}$ that has a self loop, the matrix P_s is the unique positive semidefinite solution to the Riccati equation given by Eq. (9), and the matrix $A_{ss} + B_{ss} K_s$ is stable. The optimal solution to (6) is then given by

$$\zeta_s(t+1) = \sum_{r \rightarrow s} (A_{sr} + B_{sr} K_r) \zeta_r(t) + \sum_{w_i \rightarrow s} I_{s,\{i\}} w_i(t), \quad (10)$$

and

$$u_i^*(t) = \sum_{r \ni i} I_{\{i\},r} K_r \zeta_r(t), \quad (11)$$

for all $t \in \mathbb{Z}_{\geq 0}$, where $\zeta_s(t)$ is an internal state initialized with $\zeta_s(0) = \sum_{w_i \rightarrow s} I_{s,\{i\}} x_i(0) = 0$ for all $s \in \mathcal{U}$. The corresponding optimal cost of (6), denoted as J_* , is given by

$$J_* = \sigma_w^2 \sum_{\substack{i \in \mathcal{V} \\ w_i \rightarrow s}} \text{Tr}(I_{\{i\},s} P_s I_{s,\{i\}}). \quad (12)$$

Remark 2. Obtaining the optimal policy $u_i^*(t)$, for any $i \in \mathcal{V}$, given by Lemma 2 requires global knowledge of the system matrices A and B , the cost matrices Q and R , and the directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$ with the associated delay matrix D . Moreover, $u^*(t)$ given in Lemma 2 is not a static state-feedback controller, but a linear dynamic controller based on the internal states $\zeta_r(\cdot)$ for all $r \in \mathcal{U}$. For any controller $i \in \mathcal{V}$ and for any $t \in \mathbb{Z}_{\geq 0}$, the authors in [26] proposed an algorithm to determine $\zeta_r(t)$ for all $r \in \mathcal{U}$ such that $i \in r$, and thus $u_i^*(t)$, using only the memory maintained by the algorithm, the state information contained in the information set $\mathcal{I}_i(t)$ defined in Eq. (5), and the global information described above.

2.3 Problem Formulation and Summary of Results

We now formally introduce the problem that we will study in this paper. We consider the scenario where the system matrices A and B are unknown. However, we assume that the directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$ and the associated delay matrix D are known. Similarly to, e.g., [12, 42], we consider the scenario where we can first conduct experiments in order to estimate the unknown system matrices A and B . Specifically, starting from the initial state $x(0) = 0$, we evolve the system given in Eq. (2) for $N \in \mathbb{Z}_{\geq 1}$ time steps using a given control input sequence $\{u(0), u(1), \dots, u(N-1)\}$, and collect the resulting state sequence $\{x(1), x(2), \dots, x(N)\}$. Based on $\{u(0), \dots, u(N-1)\}$ and $\{x(0), \dots, x(N)\}$, we use a least squares approach to obtain estimates of the system matrices A and B , denoted as \hat{A} and \hat{B} , respectively. Using the obtained \hat{A} and \hat{B} , the goal is still to solve (6). Since the true system matrices A and B are unknown, it may no longer be possible to solve (6) optimally, using the methods introduced in Section 2.2. Thus, we aim to provide a solution to (6) using \hat{A} and \hat{B} , and characterize its performance (i.e., suboptimality) guarantees.

In the rest of this paper, we first analyze the estimation error of \hat{A} and \hat{B} obtained from the procedure described above. In particular, we show in Section 3 that the estimation errors $\|\hat{A} - A\|$ and $\|\hat{B} - B\|$ scale as $\tilde{O}(1/\sqrt{N})$ with high probability.⁵ Next, in Section 4, we design a control policy $\hat{u}(\cdot)$, based on \hat{A} and \hat{B} , which satisfies the information constraints given in (6). Supposing $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$, where $\varepsilon \in \mathbb{R}_{>0}$, and denoting the cost of (6) corresponding to $\hat{u}(\cdot)$ as \hat{J} , we show in Section 5.2 that

$$\hat{J} - J_\star \leq C\varepsilon,$$

as long as $\varepsilon \leq C_0$, where J_\star is the optimal cost of (6) given by (12), and C and C_0 are constants that explicitly depend on the problem parameters of (6). Finally, combining the above results together, we show in Section 5.3 that with high probability and for large enough N , the following end-to-end sample complexity of learning decentralized LQR with the partially nested information structure holds:

$$\hat{J} - J_\star = \tilde{O}\left(\frac{1}{\sqrt{N}}\right).$$

3 System Identification Using Least Squares

As we described in Section 2.3, we use a least squares approach to estimate the system matrices $A \in \mathbb{R}^{n \times n}$ and $B \in \mathbb{R}^{n \times m}$, based on a single system trajectory consisting of the control input sequence $\{u(0), \dots, u(N-1)\}$ and the system state sequence $\{x(0), \dots, x(N)\}$, where $x(0) = 0$ and $N \in \mathbb{Z}_{\geq 1}$. Here, we draw the inputs $u(0), \dots, u(N-1)$ independently from a Gaussian distribution $\mathcal{N}(0, \sigma_u^2 I)$, where $\sigma_u \in \mathbb{R}_{>0}$. In other words, we let $u(t) \stackrel{\text{i.i.d.}}{\sim} \mathcal{N}(0, \sigma_u^2 I)$ for all $t \in \{0, \dots, N-1\}$. Moreover, we assume that the input $u(t)$ and the disturbance $w(t)$ are independent for all $t \in \{0, \dots, N-1\}$. Note that we consider the scenario where the estimation of A and B is performed in a centralized manner. In the following, we present the least squares approach to estimate A and B , and characterize the corresponding estimation error.

3.1 Least Squares Estimation of System Matrices

Let us denote

$$\Theta = [A \quad B] \text{ and } z(t) = [x(t)^\top \quad u(t)^\top]^\top, \quad (13)$$

where $\Theta \in \mathbb{R}^{n \times (n+m)}$ and $z(t) \in \mathbb{R}^{n+m}$. Given the sequences $\{z(0), \dots, z(N-1)\}$ and $\{x(1), \dots, x(N)\}$, we use the regularized least squares to obtain an estimate of Θ , denoted as $\hat{\Theta}(N)$, i.e.,

$$\hat{\Theta}(N) = \arg \min_{Y \in \mathbb{R}^{n \times (n+m)}} \left\{ \lambda \|Y\|_F^2 + \sum_{t=0}^{N-1} \|x(t+1) - Yz(t)\|^2 \right\}, \quad (14)$$

where $\lambda \in \mathbb{R}_{>0}$ is the regularization parameter. We summarize the above least squares approach in Algorithm 1.

Algorithm 1 Least Squares Estimation of A and B

Input: parameter $\lambda > 0$ and time horizon length N

- 1: Initialize $x(0) = 0$
 - 2: **for** $t = 0, \dots, N-1$ **do**
 - 3: Play $u(t) \stackrel{\text{i.i.d.}}{\sim} \mathcal{N}(0, \sigma_u^2 I)$
 - 4: Obtain $\hat{\Theta}(N)$ using (14)
 - 5: Extract \hat{A} and \hat{B} from $\hat{\Theta}(N)$
-

⁵Throughout this paper, we let $\tilde{O}(\cdot)$ hide logarithmic factors in N .

3.2 Least Squares Estimation Error

In order to characterize the estimation error of $\hat{\Theta}(N)$ given by (14), we will use the following result from [10], which is a consequence of Theorem 1 in [2].

Lemma 3. [10, Lemma 6] *For any $t \in \mathbb{Z}_{\geq 1}$, let $V(t) = \lambda I + \sum_{k=0}^{t-1} z(k)z(k)^\top$ and $\Delta(t) = \Theta - \hat{\Theta}(t)$, where Θ and $z(k)$ are given in (13), $\hat{\Theta}(t)$ is given by (14), and $\lambda \in \mathbb{R}_{>0}$. Then, for any $\delta_\Theta > 0$, the following hold with probability at least $1 - \delta_\Theta$:*

$$\text{Tr}(\Delta(t)^\top V(t) \Delta(t)) \leq 4\sigma_w^2 n \log \left(\frac{n_i \det(V(t))}{\delta_\Theta \det(\lambda I)} \right) + 2\lambda \|\Theta\|_F^2, \quad \forall t \in \mathbb{Z}_{\geq 0}.$$

For any $\delta > 0$, we now introduce the following probabilistic events that will be useful in our analysis later:

$$\begin{aligned} \mathcal{E}_w &= \left\{ \max_{0 \leq t \leq N-1} \|w(t)\| \leq \sigma_w \sqrt{5n \log \frac{4N}{\delta}} \right\}, \\ \mathcal{E}_u &= \left\{ \max_{0 \leq t \leq N-1} \|u(t)\| \leq \sigma_u \sqrt{5m \log \frac{4N}{\delta}} \right\}, \\ \mathcal{E}_\Theta &= \left\{ \text{Tr}(\Delta(N)^\top V(N) \Delta(N)) \leq 4\sigma_w^2 n \log \left(\frac{4n \det(V(N))}{\delta \det(\lambda I)} \right) + 2\lambda \|\Theta\|_F^2 \right\}, \\ \mathcal{E}_z &= \left\{ \sum_{t=0}^{N-1} z(t)z(t)^\top \succeq \frac{(N-1)\underline{\sigma}^2}{40} I \right\}, \end{aligned} \tag{15}$$

where $\underline{\sigma} \triangleq \min\{\sigma_w, \sigma_u\}$. Denoting

$$\mathcal{E} = \mathcal{E}_w \cap \mathcal{E}_v \cap \mathcal{E}_\Theta \cap \mathcal{E}_z, \tag{16}$$

we have the following result; the proof is included in the Appendix A.

Lemma 4. *For any $\delta > 0$ and for any $N \geq 200(n+m) \log \frac{48}{\delta}$, it holds that $\mathbb{P}(\mathcal{E}) \geq 1 - \delta$.*

For the analysis in the rest of this paper, we will make the following assumption, which is also made in related literature (see e.g., [24, 37, 42]).

Assumption 2. *The system matrix $A \in \mathbb{R}^{n \times n}$ is stable, and $\|A^k\| \leq \kappa_0 \gamma_0^k$ for all $k \in \mathbb{Z}_{\geq 0}$, where $\kappa_0 \geq 1$ and $\rho(A) < \gamma_0 < 1$.*

Note that for any stable matrix A , we have from the Gelfand formula (e.g., [22]) that there always exist $\kappa_0 \in \mathbb{R}_{\geq 1}$ and $\gamma_0 \in \mathbb{R}$ with $\rho(A) < \gamma_0 < 1$ such that $\|A^k\| \leq \kappa_0 \gamma_0^k$ for all $k \in \mathbb{Z}_{\geq 0}$. We then have the following results; the proofs are included in the Appendix A.

Lemma 5. *Suppose Assumption 2 holds. On the event \mathcal{E} defined in Eq. (16),*

$$\|z(t)\| \leq \frac{5\kappa_0}{1-\gamma_0} \bar{\sigma} \sqrt{(\|B\|^2 m + m + n) \log \frac{4N}{\delta}}, \tag{17}$$

for all $t \in \{0, \dots, N-1\}$, where $N \geq 1$, $\bar{\sigma} = \max\{\sigma_w, \sigma_u\}$, γ_0 and κ_0 are given in Assumption 2, and $z(t) = [x(t)^\top \ u(t)^\top]^\top$ with $x(t) \in \mathbb{R}^n$ and $w(t) \in \mathbb{R}^m$ to be the state and input of the system in Eq. (2), respectively, corresponding to Algorithm 1.

Proposition 1. *Suppose Assumption 2 holds, and $\|A\| \leq \vartheta$ and $\|B\| \leq \vartheta$, where $\vartheta \in \mathbb{R}_{>0}$. Consider any $\delta > 0$. Let the input parameters to Algorithm 1 satisfy $N \geq 200(n+m) \log \frac{48}{\delta}$ and $\frac{\underline{\sigma}^2}{40} \leq \lambda \leq z_b$, where $\underline{\sigma} = \min\{\sigma_w, \sigma_u\}$, and*

$$z_b = \frac{5\kappa_0}{1-\gamma_0} \bar{\sigma} \sqrt{(\|B\|^2 m + m + n) \log \frac{4N}{\delta}},$$

where κ_0 and γ_0 are given in Assumption 2, and $\bar{\sigma} = \max\{\sigma_w, \sigma_u\}$. Then, with probability at least $1 - \delta$, it holds that $\|\hat{A} - A\| \leq \varepsilon_0$ and $\|\hat{B} - B\| \leq \varepsilon_0$, where \hat{A} and \hat{B} are returned by Algorithm 1, and

$$\varepsilon_0 = 4\sqrt{\frac{10}{N\bar{\sigma}^2} \left(2n\sigma_w^2(n+m) \log \frac{N+1}{\delta} + \lambda n\vartheta^2 \right)}.$$

While considering the problem of learning centralized LQR without any information constraints, the authors in [12] proposed to obtain \hat{A} and \hat{B} from multiple system trajectories using least squares, where each trajectory starts from $x(0) = 0$. They showed that $\|\hat{A} - A\| = \mathcal{O}(1/\sqrt{N_r})$ and $\|\hat{B} - B\| = \mathcal{O}(1/\sqrt{N_r})$, where $N_r \in \mathbb{Z}_{\geq 1}$ is the number of system trajectories. In contrast, we estimate A and B from a single system trajectory, and achieve $\|\hat{A} - A\| = \tilde{\mathcal{O}}(1/\sqrt{N})$ and $\|\hat{B} - B\| = \tilde{\mathcal{O}}(1/\sqrt{N})$. Note that we do not leverage the block structure (i.e., sparsity pattern) of A and B described in Section 2.2, when we obtain \hat{A} and \hat{B} . Therefore, the sparsity pattern of \hat{A} and \hat{B} may potentially be inconsistent with that of A and B . Nonetheless, such a potential inconsistency does not play any role in our analysis later. In our analysis, we only leverage the fact that the estimation error corresponding to submatrices in \hat{A} (resp., \hat{B}) will be upper bounded by $\|\hat{A} - A\|$ (resp., $\|\hat{B} - B\|$). We remark that one may also use system identification schemes and the associated sample complexity analysis dedicated to sparse system matrices (e.g., [14]). Under some extra assumptions (e.g., [14]), one may then obtain \hat{A} and \hat{B} that have the same sparsity pattern as A and B , and remove the logarithmic factor in N in ε_0 defined in Proposition 1.

4 Control Policy Design

While the estimation of A and B is performed in a centralized manner as we discussed in Section 3.1, we assume that each controller $i \in \mathcal{V}$ receives the estimates \hat{A} and \hat{B} after we conduct the system identification step described in Algorithm 1. Given the matrices \hat{A} , \hat{B} , Q , and R , and the directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$ ($\mathcal{V} = [p]$) with the delay matrix D , in this section we design a control policy for each controller $i \in \mathcal{V}$, while satisfying the information constraints described in Section 2.2. To this end, we leverage the structure of the optimal policy $u^*(\cdot)$ given in Lemma 2 (when A and B are known). Note that the optimal policy $u^*(\cdot)$ cannot be applied to our scenario, since only \hat{A} and \hat{B} are available.

First, given the directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$ with $\mathcal{V} = [p]$ and the delay matrix D , we construct the information graph $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ given by (7). Recall from Remark 1 that $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ is a forest that contains a set of disconnected directed trees. We then let \mathcal{L} denote the set of all the leaf nodes in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, i.e.,

$$\mathcal{L} = \{s_i(0) \in \mathcal{U} : i \in \mathcal{V}\}. \quad (18)$$

Moreover, for any $s \in \mathcal{U}$, we denote

$$\mathcal{L}_s = \{v \in \mathcal{L} : v \rightsquigarrow s\}, \quad (19)$$

where we write $v \rightsquigarrow s$ if and only if there is a unique directed path from node v to node s in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$. In other words, \mathcal{L}_s is the set of leaf nodes in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ that can reach s . Moreover, for any $v, s \in \mathcal{U}$ such that $v \rightsquigarrow s$, we let l_{vs} denote the length of the unique directed path from v to s in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$; we let $l_{vs} = 0$ if $v = s$.

Next, in order to leverage the structure of the optimal policy $u^*(\cdot)$ given in Eqs. (8)-(11), we substitute (submatrices of) \hat{A} and \hat{B} into the right-hand sides of Eqs. (8)-(9), and obtain \hat{K}_r and \hat{P}_r for all $r \in \mathcal{U}$. Specifically, for all $r \in \mathcal{U}$, we obtain \hat{K}_r , and \hat{P}_r recursively as

$$\hat{K}_r = -(R_{rr} + \hat{B}_{sr}^\top \hat{P}_s \hat{B}_{sr})^{-1} \hat{B}_{sr}^\top \hat{P}_s \hat{A}_{sr}, \quad (20)$$

$$\hat{P}_r = Q_{rr} + \hat{K}_r^\top R_{rr} \hat{K}_r + (\hat{A}_{sr} + \hat{B}_{sr} \hat{K}_r)^\top \hat{P}_s (\hat{A}_{sr} + \hat{B}_{sr} \hat{K}_r), \quad (21)$$

where for each $r \in \mathcal{U}$, we let $s \in \mathcal{U}$ be the unique node such that $r \rightarrow s$, and \hat{A}_{sr} (resp., \hat{B}_{sr}) is a submatrix of \hat{A} (resp., \hat{B}) obtained in the same manner as A_{sr} (resp., B_{sr}) described before. Similarly to Eq. (10), we then use \hat{K}_r for all $r \in \mathcal{U}$ together with \hat{A} and \hat{B} to maintain an (estimated) internal state $\hat{\zeta}_r(t)$ for all $r \in \mathcal{U}$ and for all $t \in \{0, \dots, T-1\}$, which, via a similar form to Eq. (11), will lead to our control policy,

denoted as $\hat{u}_i(t)$, for all $i \in \mathcal{V}$ and for all $t \in \{0, \dots, T-1\}$. Specifically, for all $i \in \mathcal{V}$ in parallel, we propose Algorithm 2 to compute the control policy

$$\hat{u}_i(t) = \sum_{r \ni i} I_{\{i\},r} \hat{K}_r \hat{\zeta}_r(t) \quad \forall t \in \{0, \dots, T-1\}. \quad (22)$$

Algorithm 2 Control policy design for node $i \in \mathcal{V}$

Input: estimates \hat{A} and \hat{B} , cost matrices Q and R , directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$ with $\mathcal{V} = [p]$ and delay matrix D , time horizon length T

- 1: Construct the information graph $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ from (7)
 - 2: Obtain \hat{K}_s for all $s \in \mathcal{U}$ from Eq. (8)
 - 3: Initialize $\mathcal{M}_i \leftarrow \bar{\mathcal{M}}_i$
 - 4: **for** $t = 0, \dots, T-1$ **do**
 - 5: **for** $s \in \mathcal{L}(\mathcal{T}_i)$ **do**
 - 6: Find $s_j(0) \in \mathcal{U}$ s.t. $j \in \mathcal{V}$ and $s_j(0) = s$
 - 7: Obtain $\hat{w}_j(t - D_{ij} - 1)$ from Eq. (28)
 - 8: Obtain $\hat{\zeta}_s(t - D_{ij})$ from Eq. (27)
 - 9: $\mathcal{M}_i \leftarrow \mathcal{M}_i \cup \{\hat{\zeta}_s(t - D_{ij})\}$
 - 10: **for** $s \in \mathcal{R}(\mathcal{T}_i)$ **do**
 - 11: Obtain $\hat{\zeta}_s(t - D_{\max})$ from Eq. (27)
 - 12: $\mathcal{M}_i \leftarrow \mathcal{M}_i \cup \{\hat{\zeta}_s(t - D_{\max})\}$
 - 13: Play $\hat{u}_i(t) = \sum_{r \ni i} I_{\{i\},r} \hat{K}_r \hat{\zeta}_r(t)$
 - 14: $\mathcal{M}_i \leftarrow \mathcal{M}_i \setminus (\{\hat{\zeta}_s(t - 2D_{\max} - 1) : s \in \mathcal{L}(\mathcal{T}_i)\} \cup \{\hat{\zeta}_s(t - D_{\max} - 1) : s \in \mathcal{R}(\mathcal{T}_i)\})$
-

We now describe the notations used in Algorithm 2 and hereafter. Let us consider any $i \in \mathcal{V}$. In Algorithm 2, we let \mathcal{T}_i denote the set of disconnected directed trees in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ such that the root node of any tree in \mathcal{T}_i contains i . Slightly abusing the notation, we also let \mathcal{T}_i denote the set of nodes of all the trees in \mathcal{T}_i . Moreover, we denote

$$\mathcal{L}(\mathcal{T}_i) = \mathcal{T}_i \cap \mathcal{L}, \quad (23)$$

where \mathcal{L} is defined in Eq. (18), i.e., $\mathcal{L}(\mathcal{T}_i)$ is the set of leaf nodes of all the trees in \mathcal{T}_i . Letting $\mathcal{R} \subseteq \mathcal{U}$ be the set of root nodes in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, we denote

$$\mathcal{R}(\mathcal{T}_i) = \mathcal{T}_i \cap \mathcal{R}, \quad (24)$$

where we recall from Lemma 1 that any root node in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ has a self loop. Note that if any node $s \in \mathcal{T}_i$ is a leaf node with a self loop (i.e., s is an isolated node in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$), we only include s in $\mathcal{L}(\mathcal{T}_i)$ (i.e., $s \in \mathcal{L}(\mathcal{T}_i)$) but $s \notin \mathcal{R}(\mathcal{T}_i)$.

Remark 3. For any $s, r \in \mathcal{L}(\mathcal{T}_i)$, let $j_1, j_2 \in \mathcal{V}$ be such that $s_{j_1}(0) = s$ and $s_{j_2}(0) = r$. In Algorithm 2, we assume that the elements in $\mathcal{L}(\mathcal{T}_i)$ are already ordered such that if $D_{ij_1} > D_{ij_2}$, then s comes before r in $\mathcal{L}(\mathcal{T}_i)$. We then let the for loop in lines 5-9 in Algorithm 2 iterate over the elements in $\mathcal{L}(\mathcal{T}_i)$ according to the above order.

Furthermore, we denote

$$D_{\max} = \max_{\substack{i, j \in \mathcal{V} \\ j \rightsquigarrow i}} D_{ij}, \quad (25)$$

where we write $j \rightsquigarrow i$ if and only if there is a directed path from node j to node i in $\mathcal{G}(\mathcal{V}, \mathcal{A})$, and recall that D_{ij} is the sum of delays along the directed path from j to i with the smallest accumulative delay. Finally, the memory \mathcal{M}_i of Algorithm 2 is initialized as $\mathcal{M}_i = \bar{\mathcal{M}}_i$ with

$$\bar{\mathcal{M}}_i = \{\hat{\zeta}_s(k) : k \in \{-2D_{\max} - 1, \dots, -D_{ij} - 1\}, s \in \mathcal{L}(\mathcal{T}_i), j \in \mathcal{V}, s_j(0) = s\} \cup \{\hat{\zeta}_s(-D_{\max} - 1) : s \in \mathcal{R}(\mathcal{T}_i)\}, \quad (26)$$

where we initialize $\hat{\zeta}_s(k) = 0$ for all $\hat{\zeta}_s(k) \in \bar{\mathcal{M}}_i$.

Remark 4. Recall that each edge in $\mathcal{G}(\mathcal{V}, \mathcal{A})$ is associated with a delay of either 0 or 1. Considering the scenario with only sparsity constraints (e.g., [35]), i.e., all the edges in $\mathcal{G}(\mathcal{V}, \mathcal{A})$ have a zero delay, we see that $D_{ij} = 0$ for all $i, j \in \mathcal{V}$ such that $j \rightsquigarrow i$, which implies via Eq. (25) that $D_{\max} = 0$.

For any $r \ni i$, the dynamics of the internal state $\hat{\zeta}_r(t)$ is given by

$$\hat{\zeta}_r(t+1) = \sum_{v \rightarrow r} (\hat{A}_{rv} + \hat{B}_{rv} \hat{K}_v) \hat{\zeta}_v(t) + \sum_{w_j \rightarrow r} I_{r, \{j\}} \hat{w}_j(t), \quad (27)$$

where $\hat{w}_j(t)$ is an estimate of the disturbance $w_j(t)$ in Eq. (4) obtained as

$$\hat{w}_j(t) = \begin{cases} 0 & \text{if } t < -1, \\ x_j(0) & \text{if } t = -1, \\ x_j(t+1) - \hat{A}_j x_{\mathcal{N}_j}(t) - \hat{B}_j \hat{u}_{\mathcal{N}_j}(t) & \text{if } t \geq 0, \end{cases} \quad (28)$$

where we replace A_j and B_j with the estimates \hat{A}_j and \hat{B}_j in Eq. (4), respectively, and $\hat{u}_{\mathcal{N}_j}(t)$ is the vector that collects $\hat{u}_{j_1}(t)$ for all $j_1 \in \mathcal{N}_j$, with \mathcal{N}_j defined in Eq. (3). We note from Eqs. (27)-(28) that $\hat{\zeta}_r(0) = \sum_{w_j \rightarrow r} I_{r, \{j\}} x_j(0)$, where $x(0) = 0$ as we assumed previously.

Observation 1. From the structure of the information graph $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ defined in (7), the following hold:

- (a) If r is not a leaf node in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, Eq. (27) reduces to $\hat{\zeta}_r(t+1) = \sum_{v \rightarrow r} (\hat{A}_{rv} + \hat{B}_{rv} \hat{K}_v) \hat{\zeta}_v(t)$.
- (b) If r is a leaf node in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ that is not isolated, Eq. (27) reduces to $\hat{\zeta}_r(t+1) = \sum_{w_j \rightarrow r} I_{r, \{j\}} \hat{w}_j(t)$.
- (c) If r is an isolated node in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, Eq. (27) reduces to $\hat{\zeta}_r(t+1) = (\hat{A}_{rr} + \hat{B}_{rr} \hat{K}_r) \hat{\zeta}_r(t) + \sum_{w_j \rightarrow r} I_{r, \{j\}} \hat{w}_j(t)$.

We will show that in each iteration $t \in \{0, \dots, T-1\}$ of the for loop in lines 4-14 of Algorithm 2, the internal states $\hat{\zeta}_r(t)$ for all $r \in \mathcal{U}$ such that $i \in r$ (i.e., for all $r \ni i$) can be determined using Eq. (27) and the current memory \mathcal{M}_i of the algorithm. As we will see, Algorithm 2 maintains, in its current memory \mathcal{M}_i , the internal states (with potential time delays) for a certain subset of nodes in \mathcal{U} , via the recursion in Eq. (27). Given those internal states, $\hat{\zeta}_r(t)$ for all $r \ni i$ can be determined using Eq. (27). Moreover, the memory \mathcal{M}_i of Algorithm 2 is recursively updated in the for loop in lines 4-14 of the algorithm. Formally, we have the following result for Algorithm 2; the proof can be found in the Appendix B.

Proposition 2. Suppose that any controller $i \in \mathcal{V}$ at any time step $t \in \mathbb{Z}_{\geq 0}$ has access to the states in $\tilde{\mathcal{I}}_i(t)$ defined as

$$\tilde{\mathcal{I}}_i(t) = \{x_j(t - D_{ij} - 1), x_j(t - D_{ij}) : j \in \mathcal{V}_i\} \subseteq \mathcal{I}_i(t), \quad (29)$$

where $\mathcal{V}_i = \{j \in \mathcal{V} : D_{ij} \neq +\infty\}$, and $\mathcal{I}_i(t)$ is defined in Eq. (5). Then, the following properties hold for Algorithm 2:

- (a) The memory \mathcal{M}_i of Algorithm 2 can be recursively updated such that at the beginning of any iteration $t \in \{0, \dots, T-1\}$ of the for loop in lines 4-14 of the algorithm,

$$\mathcal{M}_i = \left\{ \hat{\zeta}_s(k) : k \in \{t - 2D_{\max} - 1, \dots, t - D_{ij} - 1\}, s \in \mathcal{L}(\mathcal{T}_i), j \in \mathcal{V}, s_j(0) = s \right\} \cup \left\{ \hat{\zeta}_s(t - D_{\max} - 1) : s \in \mathcal{R}(\mathcal{T}_i) \right\}. \quad (30)$$

- (b) The control input $\hat{u}_i(t)$ in line 13 can be determined using Eq. (27) and the states in the memory \mathcal{M}_i after line 12 (and before line 14) in any iteration $t \in \{0, \dots, T-1\}$ of the for loop in lines 4-14 of Algorithm 2.

Since $|\mathcal{L}(\mathcal{T}_i)| \leq p$ and $|\mathcal{R}(\mathcal{T}_i)| \leq p$, one can show via the definition of Algorithm 2 that the number of the states in the memory \mathcal{M}_i of Algorithm 2 is always upper bounded by $(2D_{\max} + 2)p + 2p$, where we note that D_{\max} defined in Eq. (25) satisfies $D_{\max} \leq p$, and p is the number of nodes in the directed graph $\mathcal{G}(\mathcal{V}, \mathcal{A})$. Moreover, one can check that Algorithm 2 can be implemented in polynomial time.

It is worth noting that the control policy $\hat{u}_i(\cdot)$ for all $i \in \mathcal{U}$ that we proposed in Eq. (22) is related to the certainty equivalent approach (e.g., [4]) that has been used for learning centralized LQR without any information constraints on the controllers (e.g., [12, 29, 9]). It is known that the optimal solution to classic centralized LQR (i.e., problem (6) without the information constraints) is given by a static state-feedback

controller $u^*(t) = Kx(t)$, where K can be obtained from the solution to the Ricatti equation corresponding to A , B , Q and R (e.g., [5]). The corresponding certainty equivalent controller simply takes the form $\hat{u}(t) = \hat{K}x(t)$, where \hat{K} is obtained from the solution to the Ricatti equation corresponding to \hat{A} , \hat{B} , Q and R , with \hat{A} and \hat{B} to be the estimates of A and B , respectively. While we also leverage the structure of the optimal control policy $u^*(\cdot)$ given in Eq. (11), we cannot simply replace K_r with \hat{K}_r for all $r \in \mathcal{U}$ in Eq. (11), where \hat{K}_r is given by the Ricatti equations in Eqs. (20)-(21). As we argued in Remark 2, this is because $u^*(\cdot)$ is not a static state-feedback controller, but a linear dynamic controller based on the internal states $\zeta_r(\cdot)$ for all $r \in \mathcal{U}$, where the dynamics of $\zeta_r(\cdot)$ given by Eq. (10) also depends on A and B . Thus, the control policy $\hat{u}_i(\cdot)$ that we proposed in Eq. (22) is a linear dynamic controller based on \hat{K}_r and the estimated internal states $\hat{\zeta}_r(\cdot)$ for all $r \in \mathcal{U}$, where the dynamics of $\hat{\zeta}_r(\cdot)$ given by Eq. (27) depends on \hat{A} and \hat{B} . Such a more complicated form of $\hat{u}_i(\cdot)$ also creates several challenges when we analyze the corresponding suboptimality guarantees in the next section.

Finally, we remark that Algorithm 2 is not the unique way to implement the control policy $\hat{u}_i(\cdot)$ given in Eq. (22), under the information constraints on each controller $i \in \mathcal{V}$.

5 Suboptimality Guarantees

In this section, we characterize the suboptimality guarantees of the control policy $\hat{u}(\cdot)$ proposed in Section 4. To begin with, in order to explicitly distinguish the states of the system in Eq. (2) corresponding to the control policies $u^*(\cdot)$ and $\hat{u}(\cdot)$ given by Eqs. (11) and (22), respectively, we let $\hat{x}(t)$ denote the state of the system in Eq. (2) corresponding to the control policy $\hat{u}(\cdot)$ given by Eq. (22), for $t \in \mathbb{Z}_{\geq 0}$, i.e.,

$$\hat{x}(t+1) = A\hat{x}(t) + B\hat{u}(t) + w(t), \quad (31)$$

where we note from Eq. (22) that $\hat{u}(t) = \sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \hat{K}_s \hat{\zeta}_s(t)$ with \hat{K}_s and $\hat{\zeta}_s(t)$ given by Eqs. (20) and (27), respectively, for all $s \in \mathcal{U}$. We let $x(t)$ denote the state of the system in Eq. (2) corresponding to the optimal control policy $u^*(t)$ given by Eq. (11), for $t \in \mathbb{Z}_{\geq 0}$, i.e.,

$$x(t+1) = Ax(t) + Bu^*(t) + w(t), \quad (32)$$

where $u^*(t) = \sum_{s \in \mathcal{U}} I_{\mathcal{V},s} K_s \zeta_s(t)$ with K_s and $\zeta_s(t)$ given by Eqs. (8) and (10), respectively, for all $s \in \mathcal{U}$. In Eqs. (31)-(32), we set $\hat{x}(0) = x(0) = 0$. Moreover, for our analysis in the sequel, we introduce another control policy $\tilde{u}(t)$ given by

$$\tilde{u}_i(t) = \sum_{s \ni i} I_{\{i\},s} \hat{K}_s \tilde{\zeta}_s(t) \quad \forall i \in \mathcal{V}, \quad (33)$$

for $t \in \mathbb{Z}_{\geq 0}$, where for any $s \in \mathcal{U}$, \hat{K}_s is given by Eq. (20), and $\tilde{\zeta}_s(t)$ is given by

$$\tilde{\zeta}_s(t+1) = \sum_{r \rightarrow s} (A_{sr} + B_{sr} \hat{K}_r) \tilde{\zeta}_r(t) + \sum_{w_i \rightarrow s} I_{s,\{i\}} w_i(t), \quad (34)$$

with $\tilde{\zeta}_s(0) = \sum_{w_i \rightarrow s} I_{s,\{i\}} x_i(0) = 0$. We then let $\tilde{x}(t)$ denote the state of the system in Eq. (2) corresponding to $\tilde{u}_i(\cdot)$, for $t \in \mathbb{Z}_{\geq 0}$, i.e.,

$$\tilde{x}(t+1) = A\tilde{x}(t) + B\tilde{u}(t) + w(t), \quad (35)$$

where $\tilde{u}(t) = \sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \hat{K}_s \tilde{\zeta}_s(t)$ from Eq. (33), and we set $\tilde{x}(0) = x(0) = 0$. We then have the following result; the proof follows directly from Lemma 14 in [26] and is thus omitted.

Lemma 6. *For any $t \in \mathbb{Z}_{\geq 0}$, the following hold: (a) $\mathbb{E}[\tilde{\zeta}_s(t)] = 0$, for all $s \in \mathcal{U}$; (b) $\tilde{x}(t) = \sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \tilde{\zeta}_s(t)$; (c) $\tilde{\zeta}_{s_1}(t)$ and $\tilde{\zeta}_{s_2}(t)$ are independent for all $s_1, s_2 \in \mathcal{U}$ with $s_1 \neq s_2$.*

Using the above notations, the cost of the optimization problem in (6) corresponding to the control policy $\hat{u}(\cdot)$ (i.e., \hat{J}) can be written as

$$\hat{J} = \limsup_{T \rightarrow \infty} \mathbb{E} \left[\frac{1}{T} \sum_{t=0}^{T-1} (\hat{x}(t)^\top Q \hat{x}(t) + \hat{u}(t)^\top R \hat{u}(t)) \right], \quad (36)$$

where we use \limsup instead of \lim since the limit may not exist. Furthermore, we let \tilde{J} denote the cost of the optimization problem in (6) corresponding to the control policy $\tilde{u}(\cdot)$ given in Eq. (33),⁶

$$\tilde{J} = \lim_{T \rightarrow \infty} \mathbb{E} \left[\frac{1}{T} \sum_{t=0}^{T-1} (\tilde{x}(t)^\top Q \tilde{x}(t) + \tilde{u}(t)^\top R \tilde{u}(t)) \right]. \quad (37)$$

Now, we recall from Lemma 2 that for any $s \in \mathcal{U}$ that has a self loop, the matrix $A_{ss} + B_{ss}K_s$ is stable, where K_s is given by Eq. (8). We then have from the Gelfand formula that for any $s \in \mathcal{U}$ that has a self loop, there exist $\kappa_s \in \mathbb{R}_{\geq 1}$ and $\gamma_s \in \mathbb{R}$ with $\rho(A_{ss} + B_{ss}K_s) < \gamma_s < 1$ such that $\|(A_{ss} + B_{ss}K_s)^k\| \leq \kappa_s \gamma_s^k$ for all $k \in \mathbb{Z}_{\geq 0}$. For notational simplicity, let us denote

$$\gamma = \max \left\{ \max_{s \in \mathcal{R}} \gamma_s, \gamma_0 \right\}, \quad \kappa = \max \left\{ \max_{s \in \mathcal{R}} \kappa_s, \kappa_0 \right\}, \quad (38)$$

where $\mathcal{R} \subseteq \mathcal{U}$ denotes the set of root nodes in \mathcal{U} , and $\kappa_0 \in \mathbb{R}_{\geq 1}$ and $\gamma_0 \in \mathbb{R}$ with $\rho(A) < \gamma_0 < 1$ are given in Assumption 2. Thus, we see from Assumption 2 and our above arguments that $\|(A_{ss} + B_{ss}K_s)^k\| \leq \kappa \gamma^k$ for all $s \in \mathcal{R}$ and for all $k \in \mathbb{Z}_{\geq 0}$, and $\|A^k\| \leq \kappa \gamma^k$ for all $k \in \mathbb{Z}_{\geq 0}$, where $\kappa \in \mathbb{R}_{\geq 1}$ and $0 < \gamma < 1$. Moreover, we denote

$$\begin{aligned} \Gamma &= \max \left\{ \|A\|, \|B\|, \max_{s \in \mathcal{U}} \|P_s\|, \max_{s \in \mathcal{U}} \|K_s\| \right\}, \\ \tilde{\Gamma} &= \Gamma + 1. \end{aligned} \quad (39)$$

For our analysis in this section, we will make the following assumption; similar assumptions can be found in, e.g., [10, 29, 12].

Assumption 3. *The cost matrices R and Q in (6) satisfy that $\sigma_n(R) \geq 1$ and $\sigma_m(Q) \geq 1$.*

Note that the above assumption is not more restrictive than assuming that R and Q are positive definite. Specifically, supposing $R \succ 0$ and $Q \succ 0$, one can assume without loss of generality that $\sigma_n(R) \geq 1$ and $\sigma_m(Q) \geq 1$. This is because one can check that scaling the objective function in (6) by a positive constant does not change K_r in the optimal solution to (6) provided in Lemma 2, for any $r \in \mathcal{U}$.

5.1 Perturbation Bounds on Solutions to Ricatti Equations

Supposing $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$ with $\varepsilon \in \mathbb{R}_{>0}$, in this subsection we aim to provide upper bounds on the perturbations $\|\hat{P}_r - P_r\|$ and $\|\hat{K}_r - K_r\|$ for all $r \in \mathcal{U}$, where P_r (resp., \hat{P}_r) is given by Eq. (9) (resp., Eq. (21)), and K_r (resp., \hat{K}_r) is given by Eq. (8) (resp., Eq. (20)). We note from Lemma 2 that for any $r \in \mathcal{U}$ that has a self loop, Eq. (9) (resp., Eq. (21)) reduces to a discrete Ricatti equation in P_r (resp., \hat{P}_r). The following results characterize the bounds on $\|\hat{P}_r - P_r\|$ and $\|\hat{K}_r - K_r\|$, for all $r \in \mathcal{U}$; the proofs can be found in the Appendix C.

Lemma 7. *Suppose Assumptions 1 and 3 hold, and $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$, where $\varepsilon \in \mathbb{R}_{>0}$. Then, for any $r \in \mathcal{U}$ that has a self loop, the following hold:*

$$\|\hat{P}_r - P_r\| \leq 6 \frac{\kappa^2}{1 - \gamma^2} \tilde{\Gamma}^5 (1 + \sigma_1(R^{-1})) \varepsilon \leq \frac{1}{6}, \quad (40)$$

$$\|\hat{K}_r - K_r\| \leq 18 \frac{\kappa^2}{1 - \gamma^2} \tilde{\Gamma}^8 (1 + \sigma_1(R^{-1})) \varepsilon \leq 1, \quad (41)$$

and

$$\|(A_{rr} + B_{rr}\hat{K}_r)^k\| \leq \kappa \left(\frac{\gamma + 1}{2} \right)^k, \quad \forall k \geq 0, \quad (42)$$

under the assumption that

$$\varepsilon \leq \frac{1}{768} \frac{(1 - \gamma^2)^2}{\kappa^4} \tilde{\Gamma}^{-11} (1 + \sigma_1(R^{-1}))^{-2}, \quad (43)$$

where P_r (resp., \hat{P}_r) is given by Eq. (9) (resp., Eq. (21)), K_r (resp., \hat{K}_r) is given by Eq. (8) (resp., (20)), γ and κ are defined in (38), and $\tilde{\Gamma}$ is defined in (39).

⁶We will show in Proposition 3 that the limit in Eq. (37) exists.

Lemma 8. Suppose Assumptions 1 and 3 hold, and $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$, where $\varepsilon \in \mathbb{R}_{>0}$. Then, for any $r \in \mathcal{U}$ that does not have a self loop, the following hold:

$$\|\hat{K}_r - K_r\| \leq 18 \frac{\kappa^2}{1 - \gamma^2} \tilde{\Gamma}^8 (1 + \sigma_1(R^{-1})) (20\tilde{\Gamma}^9 \sigma_1(R))^{l_{rs} - 1} \varepsilon \leq 1, \quad (44)$$

and

$$\|\hat{P}_r - P_r\| \leq 6 \frac{\kappa^2}{1 - \gamma^2} \tilde{\Gamma}^5 (1 + \sigma_1(R^{-1})) (20\tilde{\Gamma}^9 \sigma_1(R))^{l_{rs}} \varepsilon \leq \frac{1}{6}, \quad (45)$$

under the assumption that

$$\varepsilon \leq \frac{1}{768} \frac{(1 - \gamma^2)^2}{\kappa^4} \tilde{\Gamma}^{-11} (1 + \sigma_1(R^{-1}))^{-2} (20\tilde{\Gamma}^9 \sigma_1(R))^{-D_{\max}}, \quad (46)$$

where K_r (resp., \hat{K}_r) is given by Eq.(8) (resp., Eq. (20)), P_r (resp., \hat{P}_r) is given by Eq. (9) (resp., Eq. (21)), $\tilde{\Gamma}$ is defined in (39), κ and γ are defined in (38), l_{rs} is the length of the unique directed path from node r to node s in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ with $s \in \mathcal{U}$ to be the unique root node that is reachable from r , and D_{\max} is defined in Eq. (25).

5.2 Perturbation Bounds on Costs

Suppose $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$, where $\varepsilon \in \mathbb{R}_{>0}$. In this subsection, we aim to provide an upper bound on $\hat{J} - J_*$, where J_* and \hat{J} are given by Eqs. (12) and (36), respectively. To this end, we first provide upper bounds on $\tilde{J} - J_*$ and $\hat{J} - \tilde{J}$, where \tilde{J} is given by Eq. (37), which will lead to the upper bound on $\hat{J} - J_*$. We start with the following results; all the proofs omitted in this subsection can be found in the Appendix D.

Lemma 9. Suppose Assumptions 1 and 3 hold, and $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$, where $\varepsilon \in \mathbb{R}_{>0}$ satisfies (46). Then, for any $s \in \mathcal{U}$,

$$\lim_{t \rightarrow \infty} \mathbb{E} \left[\tilde{\zeta}_s(t) \tilde{\zeta}_s(t)^\top \right] \preceq \frac{4p\sigma_w^2 \tilde{\Gamma}^{4D_{\max}} \kappa^2}{1 - \gamma^2} I, \quad (47)$$

where $p = |\mathcal{V}|$, κ and γ are defined in (38), $\tilde{\Gamma}$ is defined in (39), and D_{\max} is defined in Eq. (25).

For our analysis in the sequel, we further define \tilde{P}_r recursively, for all $r \in \mathcal{U}$, as

$$\tilde{P}_r = Q_{rr} + \hat{K}_r^\top R_{rr} \hat{K}_r + (A_{sr} + B_{sr} \hat{K}_r)^\top \tilde{P}_s (A_{sr} + B_{sr} \hat{K}_r), \quad (48)$$

where \hat{K}_r is given by Eq. (20), and $s \in \mathcal{U}$ is the unique node such that $r \rightarrow s$. We then have the following result, which gives an upper bound on $\tilde{J} - J_*$.

Proposition 3. Suppose Assumption 1 and 3 hold, and $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$, where $\varepsilon \in \mathbb{R}_{>0}$ satisfies (46). It holds that

$$\tilde{J} = \sigma_w^2 \sum_{\substack{i \in \mathcal{V} \\ w_i \rightarrow s}} \text{Tr}(I_{\{i\}, s} \tilde{P}_s I_{s, \{i\}}), \quad (49)$$

where \tilde{J} is defined in Eq. (37). Moreover, consider the optimal cost J_* given by Eq. (12). For any $\varphi \in \mathbb{R}_{>0}$,

$$\tilde{J} - J_* \leq \frac{72\kappa^4 \sigma_w^2 n p q}{(1 - \gamma^2)^2} \tilde{\Gamma}^{4D_{\max} + 8} (\Gamma^3 + \sigma_1(R)) (1 + \sigma_1(R^{-1})) (20\tilde{\Gamma}^9 \sigma_1(R))^{D_{\max}} \varepsilon + \varphi,$$

where κ and γ are defined in (38), $p = |\mathcal{V}|$ and $q = |\mathcal{U}|$, D_{\max} is defined in Eq. (25), and Γ and $\tilde{\Gamma}$ are defined in (39).

Next, we aim to provide an upper bound on $\hat{J} - \tilde{J}$. We first prove the following result.

Lemma 10. Suppose Assumptions 1 and 3 hold, and $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$, where ε satisfies (46). Then, for any $s \in \mathcal{U}$ and for any $t \in \mathbb{Z}_{\geq 0}$,

$$\mathbb{E} \left[\|\tilde{\zeta}_s(t)\|^2 \right] \leq \frac{4np\sigma_w^2 \tilde{\Gamma}^{4D_{\max}} \kappa^2}{1 - \gamma^2}, \quad (50)$$

where $\tilde{\zeta}_s(t)$ is given in Eq. (34), $p = |\mathcal{V}|$, κ and γ are defined in (38), $\tilde{\Gamma}$ is defined in (39), and D_{\max} is defined in Eq. (25). Moreover, for any $t \in \mathbb{Z}_{\geq 0}$,

$$\mathbb{E} \left[\|\tilde{x}(t)\|^2 \right] \leq \frac{4npq^2 \sigma_w^2 \tilde{\Gamma}^{4D_{\max}} \kappa^2}{1 - \gamma^2}, \quad (51)$$

and

$$\mathbb{E} \left[\|\tilde{u}(t)\|^2 \right] \leq \frac{4npq^2 \sigma_w^2 \tilde{\Gamma}^{4D_{\max}+2} \kappa^2}{1 - \gamma^2}, \quad (52)$$

where $\tilde{x}(t)$ and $\tilde{u}(t)$ are given by Eqs. (35) and (33), respectively, and $q = |\mathcal{U}|$.

For notational simplicity in the sequel, let us denote

$$\begin{aligned} \zeta_b &= \sqrt{\frac{4np\sigma_w^2 \tilde{\Gamma}^{4D_{\max}} \kappa^2}{1 - \gamma^2}}, \\ \bar{\varepsilon} &= \frac{(1 - \gamma)^3}{768\kappa^4 pq} (\tilde{\Gamma} + 1)^{-2} \tilde{\Gamma}^{-9} (1 + \sigma_1(R^{-1}))^{-2} (20(\tilde{\Gamma} + 1)^2 \tilde{\Gamma}^7 \sigma_1(R))^{-D_{\max}}. \end{aligned} \quad (53)$$

We then have the following results.

Lemma 11. Suppose Assumptions 1-3 hold, and $\|\hat{A} - A\| \leq \bar{\varepsilon}$ and $\|\hat{B} - B\| \leq \bar{\varepsilon}$, where $\bar{\varepsilon}$ is defined in (53). Then, for all $t \in \mathbb{Z}_{\geq 0}$,

$$\mathbb{E} \left[\|\hat{u}(t) - \tilde{u}(t)\|^2 \right] \leq \left(\frac{58\kappa^2 (\tilde{\Gamma} + 1)^{2D_{\max}+3} p^2 q^2}{(1 - \gamma)^2} \zeta_b \bar{\varepsilon} \right)^2, \quad (54)$$

and

$$\mathbb{E} \left[\|\hat{x}(t) - \tilde{x}(t)\|^2 \right] \leq \left(\frac{58\kappa^3 \Gamma (\tilde{\Gamma} + 1)^{2D_{\max}+3} p^2 q^2}{(1 - \gamma)^3} \zeta_b \bar{\varepsilon} \right)^2, \quad (55)$$

where $\hat{u}(t)$ (resp., $\tilde{u}(t)$) is given by Eq. (22) (resp., Eq. (33)), $\hat{x}(t)$ (resp., $\tilde{x}(t)$) is given by Eq. (31) (resp., Eq. (35)), Γ and $\tilde{\Gamma}$ are defined in (39), κ and γ are defined in (38), $p = |\mathcal{V}|$ and $q = |\mathcal{U}|$, D_{\max} is defined in Eq. (25), and ζ_b is defined in (53).

Corollary 1. Suppose Assumptions 1-3 hold. and $\|\hat{A} - A\| \leq \bar{\varepsilon}$ and $\|\hat{B} - B\| \leq \bar{\varepsilon}$, where $\bar{\varepsilon}$ is defined in (53). Then, for all $t \in \mathbb{Z}_{\geq 0}$,

$$\mathbb{E} \left[\|\hat{x}(t)\|^2 \right] \leq \left(\frac{58\kappa^3 \Gamma (\tilde{\Gamma} + 1)^{2D_{\max}+3} p^2 q^2}{(1 - \gamma)^3} \zeta_b \bar{\varepsilon} + q \zeta_b \right)^2, \quad (56)$$

and

$$\mathbb{E} \left[\|\hat{u}(t)\|^2 \right] \leq \left(\frac{58\kappa^2 (\tilde{\Gamma} + 1)^{2D_{\max}+3} p^2 q^2}{(1 - \gamma)^2} \zeta_b \bar{\varepsilon} + q \tilde{\Gamma} \zeta_b \right)^2, \quad (57)$$

where $\hat{u}(t)$ is given by Eq. (22), $\hat{x}(t)$ is given by Eq. (31), Γ and $\tilde{\Gamma}$ are defined in (39), κ and γ are defined in (38), $p = |\mathcal{V}|$ and $q = |\mathcal{U}|$, D_{\max} is defined in Eq. (25), and ζ_b is given by (53).

Proof. Note that

$$\begin{aligned} \sqrt{\mathbb{E} \left[\|\hat{x}(t)\|^2 \right]} &= \sqrt{\mathbb{E} \left[\|\hat{x}(t) - \tilde{x}(t) + \tilde{x}(t)\|^2 \right]} \\ &\leq \sqrt{\mathbb{E} \left[\|\hat{x}(t) - \tilde{x}(t)\|^2 \right]} + \sqrt{\mathbb{E} \left[\|\tilde{x}(t)\|^2 \right]}, \end{aligned}$$

where the inequality follows from Lemma 14. The proof of (56) now follows directly from Lemmas 10-11. Similarly, we can prove (57). \blacksquare

Proposition 4. *Suppose Assumptions 1-3 hold, and $\|\hat{A} - A\| \leq \bar{\varepsilon}$ and $\|\hat{B} - B\| \leq \bar{\varepsilon}$, where $\bar{\varepsilon}$ is defined in Eq. (53). Then, for \hat{J} and \tilde{J} defined in Eqs. (36) and (37), respectively,*

$$\hat{J} - \tilde{J} \leq 696 \frac{\kappa^6 \sigma_w^2 n p^4 q^3}{(1-\gamma)^4 (1-\gamma^2)} \tilde{\Gamma}^{4D_{\max}+2} (\tilde{\Gamma} + 1)^{2D_{\max}+3} (\sigma_1(Q) + \sigma_1(R)) \bar{\varepsilon}, \quad (58)$$

where κ and γ are defined in (38), $p = |\mathcal{V}|$ and $q = |\mathcal{U}|$, $\tilde{\Gamma}$ is defined in (39), and D_{\max} is defined in Eq. (25).

Suppose $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$ with $\varepsilon \in \mathbb{R}_{>0}$. We see from the results in Propositions 3-4 that $\hat{J} - J_\star \leq C\varepsilon$, if $\varepsilon \leq C_0$, where C and C_0 are constants that depend on the problem parameters.

5.3 Sample Complexity Result

We are now in place to present the sample complexity result for learning decentralized LQR with the partially nested information structure described in Section 2.2.

Theorem 1. *Suppose Assumptions 1-3 hold, and Algorithm 1 is used to obtain \hat{A} and \hat{B} . Moreover, suppose $\|A\| \leq \vartheta$ and $\|B\| \leq \vartheta$, where $\vartheta \in \mathbb{R}_{>0}$, and $D_{\max} \leq D$, where D_{\max} is defined in Eq. (25) and D is a universal constant. Consider any $\delta > 0$. Let the input parameters to Algorithm 1 satisfy $N \geq \frac{\alpha}{\bar{\varepsilon}}$ and $0 < \lambda \leq z_b$, where*

$$z_b = \frac{5\kappa_0}{1-\gamma_0} \bar{\sigma} \sqrt{(\|B\|^2 m + m + n) \log \frac{4N}{\delta}},$$

and

$$\alpha = \frac{160}{\underline{\sigma}^2} \left(2n\sigma_w^2(n+m) \log \frac{N+1}{\delta} + \lambda n \vartheta^2 \right),$$

where κ_0 and γ_0 are given in Assumption 2, $\underline{\sigma} = \min\{\sigma_w, \sigma_u\}$, $\bar{\sigma} = \max\{\sigma_w, \sigma_u\}$, and $\bar{\varepsilon}$ is defined in (53). Then, with probability at least $1 - \delta$,

$$\hat{J} - J_\star \leq C_1 \frac{\kappa^6 \sigma_w^2 n p^4 q^3}{(1-\gamma^2)^2} \tilde{\Gamma}^{11D+5} (\tilde{\Gamma} + 1)^{2D+3} \times (\Gamma^3 + \sigma_1(R) + \sigma_1(Q)) \sigma_1(R)^D \sqrt{\frac{\alpha}{N}}, \quad (59)$$

where \hat{J} and J_\star are given in Eqs. (36) and (12), respectively, C_1 is a universal constant, κ and γ are defined in (38), and Γ and $\tilde{\Gamma}$ are defined in (39), $p = |\mathcal{V}|$, and $q = |\mathcal{U}|$.

Proof. Note that the results in Propositions 3-4 hold, if $\|\hat{A} - A\| \leq \bar{\varepsilon}$ and $\|\hat{B} - B\| \leq \bar{\varepsilon}$ with $\bar{\varepsilon}$ given in (53). Thus, letting $N \geq \frac{\alpha}{\bar{\varepsilon}}$ and $0 < \lambda \leq z_b$, one can first check that $N \geq 200(n+m) \log \frac{4\delta}{\delta}$, and then obtain from Proposition 1 that with probability at least $1 - \delta$, \hat{A} and \hat{B} returned by Algorithm 1 satisfy that $\|\hat{A} - A\| \leq \bar{\varepsilon}$ and $\|\hat{B} - B\| \leq \bar{\varepsilon}$. Now, noting that $D_{\max} \leq D$, where D is a universal constant, and setting $\varphi = 1/\sqrt{N}$ in Proposition 3, one can then show via Propositions 3-4 that (59) holds with probability at least $1 - \delta$. ■

Thus, we have shown a $\tilde{\mathcal{O}}(1/\sqrt{N})$ end-to-end sample complexity result for learning decentralized LQR with the partially nested information structure. In other words, we relate the number of data samples used for estimating the system model to the performance of the control policy proposed in Section 4. Note that our result in Theorem 1 matches with the $\mathcal{O}(1/\sqrt{N})$ sample complexity result (up to logarithm factors in N) provided in [12] for learning centralized LQR without any information constraints. Also note that the sample complexity for learning centralized LQR has been improved to $\mathcal{O}(1/N)$ in [29]. Specifically, the authors in [29] showed that the gap between the cost \hat{J} corresponding to the control policy they proposed and the optimal cost J_\star is upper bounded by $\mathcal{O}(\varepsilon^2)$, where $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$, if ε is sufficiently small. Due to the additional challenges introduced by the information constraints on the controllers (see our discussions at the end of Section 4), we leave investigating the possibility of improving our sample complexity result in Theorem 1 for future work.

6 Conclusion

We considered the problem of control policy design for decentralized state-feedback linear quadratic control with a partially nested information structure, when the system model is unknown. We took a model-based learning approach consisting of two steps. First, we estimated the unknown system model from a single system trajectory of finite length, using least squares estimation. Next, we designed a control policy based on the estimated system model, which satisfies the desired information constraints. We showed that the suboptimality gap between our control policy and the optimal decentralized control policy (designed using accurate knowledge of the system model) scales linearly with the estimation error of the system model. Combining the above results, we provided an end-to-end sample complexity of learning decentralized controllers for state-feedback linear quadratic control with a partially nested information structure.

References

- [1] Y. Abbasi-Yadkori and C. Szepesvári. Regret bounds for the adaptive control of linear quadratic systems. In *Proc. Conference on Learning Theory*, pages 1–26, 2011.
- [2] Y. Abbasi-Yadkori, D. Pál, and C. Szepesvári. Improved algorithms for linear stochastic bandits. In *Proc. Advances in neural information processing systems*, volume 24, pages 2312–2320, 2011.
- [3] Y. Abbasi-Yadkori, P. Bartlett, K. Bhatia, N. Lazic, C. Szepesvari, and G. Weisz. Politex: Regret bounds for policy iteration using expert prediction. In *Proc. International Conference on Machine Learning*, pages 3692–3702, 2019.
- [4] K. J. Åström and B. Wittenmark. *Adaptive Control*. Courier Corporation, 2008.
- [5] D. P. Bertsekas. *Dynamic programming and optimal control: Vol. 2 4th Edition*. Athena Scientific, 2017.
- [6] V. D. Blondel and J. N. Tsitsiklis. A survey of computational complexity results in systems and control. *Automatica*, 36(9):1249–1274, 2000.
- [7] J. Bu, A. Mesbahi, M. Fazel, and M. Mesbahi. LQR through the lens of first order methods: Discrete-time case. *arXiv preprint arXiv:1907.08921*, 2019.
- [8] A. Cassel and T. Koren. Online policy gradient for model free learning of linear quadratic regulators with \sqrt{T} regret. *arXiv preprint arXiv:2102.12608*, 2021.
- [9] A. Cassel, A. Cohen, and T. Koren. Logarithmic regret for learning linear quadratic regulators efficiently. In *Proc. International Conference on Machine Learning*, pages 1328–1337, 2020.
- [10] A. Cohen, T. Koren, and Y. Mansour. Learning linear-quadratic regulators efficiently with only \sqrt{T} regret. In *Proc. International Conference on Machine Learning*, pages 1300–1309, 2019.
- [11] S. Dean, H. Mania, N. Matni, B. Recht, and S. Tu. Regret bounds for robust adaptive control of the linear quadratic regulator. In *Proc. International Conference on Neural Information Processing Systems*, pages 4192–4201, 2018.
- [12] S. Dean, H. Mania, N. Matni, B. Recht, and S. Tu. On the sample complexity of the linear quadratic regulator. *Foundations of Computational Mathematics*, 20(4):633–679, 2020.
- [13] M. K. S. Faradonbeh, A. Tewari, and G. Michailidis. Finite time identification in unstable linear systems. *Automatica*, 96:342–353, 2018.
- [14] S. Fattahi, N. Matni, and S. Sojoudi. Learning sparse dynamical systems from a single sample trajectory. In *Proc. IEEE Conference on Decision and Control*, pages 2682–2689, 2019.
- [15] S. Fattahi, N. Matni, and S. Sojoudi. Efficient learning of distributed linear-quadratic control policies. *SIAM Journal on Control and Optimization*, 58(5):2927–2951, 2020.

- [16] M. Fazel, R. Ge, S. Kakade, and M. Mesbahi. Global convergence of policy gradient methods for the linear quadratic regulator. In *Proc. International Conference on Machine Learning*, pages 1467–1476, 2018.
- [17] H. Feng and J. Lavaei. On the exponential number of connected components for the feasible set of optimal decentralized control problems. In *Proc. American Control Conference*, pages 1430–1437, 2019.
- [18] L. Furieri, Y. Zheng, and M. Kamgarpour. Learning the globally optimal distributed LQ regulator. In *Proc. Learning for Dynamics and Control Conference*, pages 287–297, 2020.
- [19] S. Ghadimi and G. Lan. Stochastic first-and zeroth-order methods for nonconvex stochastic programming. *SIAM Journal on Optimization*, 23(4):2341–2368, 2013.
- [20] B. Gravell, P. M. Esfahani, and T. H. Summers. Learning optimal controllers for linear systems with multiplicative noise via policy gradient. *IEEE Transactions on Automatic Control*, 2020.
- [21] Y.-C. Ho et al. Team decision theory and information structures in optimal control problems—part i. *IEEE Transactions on Automatic control*, 17(1):15–22, 1972.
- [22] R. A. Horn and C. R. Johnson. *Matrix analysis*. Cambridge university press, 2012.
- [23] Z.-S. Hou and Z. Wang. From model-based control to data-driven control: Survey, classification and perspective. *Information Sciences*, 235:3–35, 2013.
- [24] S. Lale, K. Azizzadenesheli, B. Hassibi, and A. Anandkumar. Logarithmic regret bound in partially observable linear dynamical systems. *arXiv preprint arXiv:2003.11227*, 2020.
- [25] A. Lamperski and J. C. Doyle. Dynamic programming solutions for decentralized state-feedback LQG problems with communication delays. In *Proc. American Control Conference*, pages 6322–6327, 2012.
- [26] A. Lamperski and L. Lessard. Optimal decentralized state-feedback control with sparsity and delays. *Automatica*, 58:143–151, 2015.
- [27] Y. Li, Y. Tang, R. Zhang, and N. Li. Distributed reinforcement learning for decentralized linear quadratic control: A derivative-free policy optimization approach. *arXiv preprint arXiv:1912.09135*, 2019.
- [28] D. Malik, A. Pananjady, K. Bhatia, K. Khamaru, P. L. Bartlett, and M. J. Wainwright. Derivative-free methods for policy optimization: Guarantees for linear quadratic systems. *Journal of Machine Learning Research*, 21(21):1–51, 2020.
- [29] H. Mania, S. Tu, and B. Recht. Certainty equivalence is efficient for linear quadratic control. In *Proc. International Conference on Neural Information Processing Systems*, pages 10154–10164, 2019.
- [30] Y. Nesterov and V. Spokoiny. Random gradient-free minimization of convex functions. *Foundations of Computational Mathematics*, 17(2):527–566, 2017.
- [31] C. H. Papadimitriou and J. Tsitsiklis. Intractable problems in control theory. *SIAM Journal on Control and Optimization*, 24(4):639–654, 1986.
- [32] M. Rotkowitz and S. Lall. A characterization of convex problems in decentralized control. *IEEE Transactions on Automatic Control*, 50(12):1984–1996, 2005.
- [33] M. C. Rotkowitz and N. C. Martins. On the nearest quadratically invariant information constraint. *IEEE Transactions on Automatic Control*, 57(5):1314–1319, 2011.
- [34] T. Sarkar and A. Rakhlin. Near optimal finite time identification of arbitrary linear dynamical systems. In *Proc. International Conference on Machine Learning*, pages 5610–5618, 2019.
- [35] P. Shah and P. A. Parrilo. \mathcal{H}_2 -optimal decentralized control over posets: A state-space solution for state-feedback. *IEEE Transactions on Automatic Control*, 58(12):3084–3096, 2013.

- [36] M. Simchowitz, H. Mania, S. Tu, M. I. Jordan, and B. Recht. Learning without mixing: Towards a sharp analysis of linear system identification. In *Proc. Conference On Learning Theory*, pages 439–473, 2018.
- [37] M. Simchowitz, K. Singh, and E. Hazan. Improper learning for non-stochastic control. In *Proc. Conference on Learning Theory*, pages 3320–3436, 2020.
- [38] S. Tu and B. Recht. The gap between model-based and model-free methods on the linear quadratic regulator: An asymptotic viewpoint. In *Proc. Conference on Learning Theory*, pages 3036–3083, 2019.
- [39] H. S. Witsenhausen. A counterexample in stochastic optimum control. *SIAM Journal on Control*, 6(1): 131–147, 1968.
- [40] K. Zhang, B. Hu, and T. Basar. Policy optimization for \mathcal{H}_2 linear control with \mathcal{H}_∞ robustness guarantee: Implicit regularization and global convergence. In *Proc. Learning for Dynamics and Control Conference*, pages 179–190, 2020.
- [41] Y. Zheng, L. Furieri, A. Papachristodoulou, N. Li, and M. Kamgarpour. On the equivalence of Youla, system-level, and input–output parameterizations. *IEEE Transactions on Automatic Control*, 66(1): 413–420, 2020.
- [42] Y. Zheng, L. Furieri, M. Kamgarpour, and N. Li. Sample complexity of linear quadratic gaussian (LQG) control for output feedback systems. In *Proc. Learning for Dynamics and Control Conference*, pages 559–570, 2021.

Appendix

A Proofs for Least Squares Estimation of System Matrices

A.1 Proof of Lemma 4

First, let us consider \mathcal{E}_w . We can apply Lemma 12 with $\delta_w = \frac{\delta}{4}$ and obtain that $\mathbb{P}(\mathcal{E}_w) \geq 1 - \frac{\delta}{4}$. Similarly, recalling from Algorithm 1 that $u(t) \stackrel{\text{i.i.d.}}{\sim} \mathcal{N}(0, \sigma_u^2 I)$ for all $t \in \{0, \dots, N-1\}$, we have from Lemma 12 that $\mathbb{P}(\mathcal{E}_u) \geq 1 - \frac{\delta}{4}$. Next, let us consider \mathcal{E}_Θ . Applying Lemma 3 with $\delta_\Theta = \frac{\delta}{4}$, we obtain $\mathbb{P}(\mathcal{E}_\Theta) \geq 1 - \frac{\delta}{4}$.

Finally, let us consider \mathcal{E}_z . Consider the sequence of random vectors $\{z(t)\}_{t \geq 0}$ and the filtration $\{\mathcal{F}_t\}_{t \geq 0}$, where $z(t) \in \mathbb{R}^{n+m}$ is defined in (13), and $\mathcal{F}_t = \sigma(x(0), u(0), \dots, x(t), u(t))$ for all $t \in \mathbb{Z}_{\geq 0}$. For any $t \in \{1, \dots, N-1\}$, we note from Eq. (2) that $x(t)$ is conditionally Gaussian on $x(t-1)$ and $u(t-1)$, with

$$\mathbb{E}[x(t)x(t)^\top | \mathcal{F}_{t-1}] \succeq \mathbb{E}[w(t-1)w(t-1)^\top] = \sigma_w^2 I.$$

Note again from Algorithm 1 that $u(t) \stackrel{\text{i.i.d.}}{\sim} \mathcal{N}(0, \sigma_u^2 I)$ for all $t \in \{0, \dots, N-1\}$, and that $u(t)$ is assumed to be independent of $w(t)$ for all $t \in \{0, \dots, N-1\}$. We then see that $z(t)$ is also conditionally Gaussian on $x(t-1)$ and $u(t-1)$, with

$$\begin{aligned} \mathbb{E}[z(t)z(t)^\top | \mathcal{F}_{t-1}] &= \begin{bmatrix} \mathbb{E}[x(t)x(t)^\top | \mathcal{F}_{t-1}] & 0 \\ 0 & \mathbb{E}[u(t)u(t)^\top] \end{bmatrix} \\ &= \begin{bmatrix} \mathbb{E}[x(t)x(t)^\top | \mathcal{F}_{t-1}] & 0 \\ 0 & \sigma_u^2 I \end{bmatrix} \succeq \underline{\sigma}^2 I. \end{aligned}$$

Now, we can apply Lemma 13 with $\{z(t)\}_{t \geq 0}$ and $\{\mathcal{F}_t\}_{t \geq 0}$ described above, and let $\delta_z = \frac{\delta}{4p}$. Since $N \geq 200(n+m) \log \frac{48}{\delta}$, we have from Lemma 13 that $\sum_{t=0}^{N-1} z(t)z(t)^\top \succeq \frac{(N-1)\underline{\sigma}^2}{40} I$ holds with probability at least $1 - \frac{\delta}{4}$. Combining the above arguments together and applying a union bound over the events \mathcal{E}_w , \mathcal{E}_ψ , \mathcal{E}_Θ and \mathcal{E}_z , we complete the proof of the lemma. \blacksquare

A.2 Proof of Lemma 5

First, considering any $t \in \{0, \dots, N-1\}$, we denote $\psi(t) = Bu(t) + w(t)$. We see from (15) that

$$\begin{aligned} \|\psi(k)\| &\leq \|B\|\sigma_u\sqrt{5m\log\frac{4N}{\delta}} + \sigma_w\sqrt{5n\log\frac{4N}{\delta}} \\ &\leq \bar{\sigma}(\sqrt{m\|B\|^2} + \sqrt{n})\sqrt{5\log\frac{4N}{\delta}} \\ &\leq \bar{\sigma}\sqrt{10(m\|B\|^2 + n)\log\frac{4N}{\delta}}. \end{aligned}$$

Next, for any $t \in \{1, \dots, N-1\}$, we see from Eq. (2) that

$$x(t) = A^t x(0) + \sum_{k=0}^{t-1} A^{t-1-k} \psi(k),$$

where recall that we assumed previously that $x(0) = 0$. Since A is stable from Assumption 2, we know that $\|A^k\| \leq \kappa_0 \gamma_0^k$ for all $k \in \mathbb{Z}_{\geq 0}$, where $\kappa_0 \geq 1$ and $\rho(A) < \gamma_0 < 1$. It now follows from the above arguments that

$$\|x(t)\| \leq \frac{\kappa_0}{1-\gamma_0} \bar{\sigma} \sqrt{10(m\|B\|^2 + n)\log\frac{4N}{\delta}},$$

for all $t \in \{0, \dots, N-1\}$. Noting that $\|z(t)\| \leq \|x(t)\| + \|u(t)\|$, we then have

$$\begin{aligned} \|z(t)\| &\leq \frac{\kappa_0}{1-\gamma_0} \bar{\sigma} \sqrt{10(m\|B\|^2 + n)\log\frac{4N}{\delta}} + \sigma_u \sqrt{5m\log\frac{4N}{\delta}} \\ &\leq \frac{5\kappa_0}{1-\gamma_0} \bar{\sigma} \sqrt{(\|B\|^2 m + m + n)\log\frac{4N}{\delta}}, \end{aligned}$$

for all $t \in \{0, \dots, N-1\}$. ■

A.3 Proof of Proposition 1

First, we see from Eq. (15) that on the event \mathcal{E} defined in Eq. (16), the following holds:

$$\text{Tr}(\Delta(N)^\top V(N) \Delta(N)) \leq 4\sigma_w^2 n \log\left(\frac{4n \det(V(N))}{\delta \det(\lambda I)}\right) + 4\lambda n \vartheta^2, \quad (60)$$

where recall that $V(N) = \lambda I + \sum_{t=0}^{N-1} z(t)z(t)^\top$ and $\Delta(N) = \Theta - \hat{\Theta}(N)$, and where Θ and $z(t)$ are defined in (13), and $\hat{\Theta}(N)$ is given by (14). To obtain (60), we also use the fact that $\|\Theta\|^2 \leq \|A\|^2 + \|B\|^2 \leq 2\vartheta^2$, which implies via $\Theta \in \mathbb{R}^{n \times (n+m)}$ that $\|\Theta\|_F^2 \leq 2n\vartheta^2$. Moreover, we have from Eq. (15) that on the event \mathcal{E} , the following holds:

$$V(N) \succeq \lambda I + \frac{(N-1)\underline{\sigma}^2}{40} I \succeq \frac{N\underline{\sigma}^2}{40} I.$$

Combining the above arguments together, one can show that

$$\|\Delta(N)\|^2 \leq \frac{160}{N\underline{\sigma}} \left(n\sigma_w^2 \log\left(\frac{4n \det(V(N))}{\delta \det(\lambda I)}\right) + \lambda n \vartheta^2 \right).$$

Noting from Lemma 5 that $\|z(t)\| \leq z_b$ for all $t \in \{0, \dots, N-1\}$, one can use similar arguments to those for Lemma 37 in [9], and show that

$$\log \frac{\det(V(N))}{\det(\lambda I)} \leq (n+m) \log\left(N + \frac{\lambda}{z_b}\right) \leq (n+m) \log(N+1).$$

Noting that $N \geq 200(n+m) \log \frac{48}{\delta}$, we have $N \geq 4n$. It then follows that

$$\begin{aligned} \|\Delta(N)\|^2 &\leq \frac{160}{N\sigma^2} \left(n\sigma_w^2 \log \frac{N}{\delta} + n\sigma_w^2(n+m) \log(N+1) + \lambda n\vartheta^2 \right) \\ &\leq \frac{160}{N\sigma^2} \left(2n\sigma_w^2(n+m) \log \frac{N+1}{\delta} + \lambda n\vartheta^2 \right). \end{aligned}$$

Noting that Algorithm 1 extracts \hat{A} and \hat{B} from $\hat{\Theta}(N)$, i.e., $\hat{\Theta}(N) = [\hat{A} \ \hat{B}]$, one can show that $\|\hat{A} - A\| \leq \|\hat{\Theta}(N) - \Theta\|$ and $\|\hat{B} - B\| \leq \|\hat{\Theta}(N) - \Theta\|$. Finally, since we know from Lemma 4 that $\mathbb{P}(\mathcal{E}) \geq 1 - \delta$, we conclude that $\|\hat{A} - A\| \leq \varepsilon_0$ and $\|\hat{B} - B\| \leq \varepsilon_0$ hold with probability at least $1 - \delta$. \blacksquare

B Proof for Algorithm 2

B.1 Proof of Proposition 2

To prove part (a), we use an induction on $t = 0, \dots, T-1$. For the base case $t = 0$, we see directly from line 4 in Algorithm 2 and Eq. (26) that \mathcal{M}_i satisfies Eq. (30) (with $t = 0$) at the beginning of iteration 0 of the for loop in lines 4-14 of the algorithm. For the induction step, consider any $t \in \{0, \dots, T-1\}$ and suppose the memory \mathcal{M}_i satisfies Eq. (30) at the beginning of iteration t of the for loop in lines 4-14 of the algorithm.

To proceed, let us consider any $s \in \mathcal{L}(\mathcal{T}_i)$ with $j \in \mathcal{V}$ and $s_j(0) = s$ in the for loop in lines 5-9 of Algorithm 2, where $\mathcal{L}(\mathcal{T}_i)$ is defined in Eq. (23). We will show that $\hat{w}_j(t - D_{ij} - 1)$ in line 7, and thus $\hat{\zeta}_s(t - D_{ij})$ in line 8, can be determined using Eq. (27) and the current memory \mathcal{M}_i of Algorithm 2. As suggested by the first two cases in Eq. (28), we can focus on the case when $t - D_{ij} > 0$ (otherwise, $\hat{\zeta}_s(t - D_{ij})$ can be directly determined). We then note from the third case in Eq. (28) that in order to determine $\hat{w}_j(t - D_{ij} - 1)$, we need to know $x_j(t - D_{ij})$, and $x_{j_1}(t - D_{ij} - 1)$ and $u_{j_1}(t - D_{ij} - 1)$ for all $j_1 \in \mathcal{N}_j$, where \mathcal{N}_j is defined in Eq. (3). Also noting that $D_{ij_1} \leq D_{ij} + 1$ for all $j_1 \in \mathcal{N}_j$, we see that $x_j(t - D_{ij}) \in \tilde{\mathcal{I}}_i(t)$, and $x_{j_1}(t - D_{ij} - 1) \in \tilde{\mathcal{I}}_i(t)$ for all $j_1 \in \mathcal{N}_j$, where $\tilde{\mathcal{I}}_i(t)$ is defined in Eq. (29). Now, considering any $j_1 \in \mathcal{N}_j$, we note from Eq. (22) that $\hat{u}_{j_1}(t - D_{ij} - 1) = \sum_{r \ni j_1} I_{\{j_1\}, r} \hat{K}_r \hat{\zeta}_r(t - D_{ij} - 1)$. Thus, in order to determine $\hat{u}_{j_1}(t - D_{ij} - 1)$, it suffices to determine $\hat{\zeta}_r(t - D_{ij} - 1)$ for all $r \in \mathcal{U}$ such that $j_1 \in r$ (i.e., for all $r \ni j_1$). Note that $j_1 \rightsquigarrow i$, i.e., there exists a directed path from node j_1 to node i in $\mathcal{G}(\mathcal{V}, \mathcal{A})$. Moreover, noting the definition of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ given by (7) with its properties discussed in Lemma 1 and Remark 1, and noting the way we defined the set \mathcal{T}_i , one can show that for any $r \ni j_1$, it holds that $r \in \mathcal{T}_i$. Next, considering any $r \ni j_1$, we recall from Eq. (19) that \mathcal{L}_r denotes the set of leaf nodes that can reach r in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, i.e., $\mathcal{L}_r = \{v \in \mathcal{L} : v \rightsquigarrow r\} = \{v \in \mathcal{L}(\mathcal{T}_i) : v \rightsquigarrow r\}$, where the second equality again follows from the properties of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ and the definition of $\mathcal{L}(\mathcal{T}_i)$ in Eq. (23). Now, we split our arguments into two cases: r is a root node in \mathcal{T}_i (i.e., r has a self loop), and r does not have a self loop.

First, suppose r has a self loop. For the case when r is a leaf node in \mathcal{T}_i (i.e., r is an isolated node in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ and $r \in \mathcal{L}(\mathcal{T}_i)$), we see that $\hat{\zeta}_r(k) \in \mathcal{M}_i$ with \mathcal{M}_i given by Eq. (30), for all $k \in \{k - 2D_{\max} - 1, \dots, k - D_{ij_r} - 1\}$, where $j_r \in \mathcal{V}$ and $s_{j_r}(0) = r$. Noting from the definition of \mathcal{T}_i that $i, j_r \in r$, we have from the construction of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ in Eq. (7) that $j_r \rightarrow i$ in $\mathcal{G}(\mathcal{V}, \mathcal{A})$ with $D_{ij_r} = 0$. It follows that $\hat{\zeta}_r(t - D_{ij} - 1) \in \mathcal{M}_i$ with \mathcal{M}_i given by Eq. (30). Thus, we focus on the case when r is not a leaf node in \mathcal{T}_i , i.e., $r \in \mathcal{R}(\mathcal{T}_i)$. We now see from Eq. (27) that given $\hat{\zeta}_r(t - D_{ij} - 2)$, and $\hat{\zeta}_{r'}(t - D_{ij} - 2)$ for all r' such that $r' \rightarrow r$ (with $r \neq r'$) in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, the state $\hat{\zeta}_r(t - D_{ij} - 1)$ can be determined. Let us consider any r' such that $r' \rightarrow r$ (with $r' \neq r$) in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, and denote $\mathcal{L}_{r'} = \{v' \in \mathcal{L}(\mathcal{T}_i) : v' \rightsquigarrow r'\}$, where we note that $\mathcal{L}_{r'} \subseteq \mathcal{L}_r$. For any $k \in \mathbb{Z}$, one can recursively apply Eq. (27) to show that given $\hat{\zeta}_{v'}(k - l_{v'r'})$ for all $v' \in \mathcal{L}_{r'}$, the state $\hat{\zeta}_{r'}(k)$ can be determined, where $l_{v'r'}$ is the length of the (unique) directed path from v' to r' in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$. Further considering any $v' \in \mathcal{L}_{r'}$, and noting that $v' \in \mathcal{L}(\mathcal{T}_i)$, we have that $\hat{\zeta}_{v'}(k) \in \mathcal{M}_i$ for all $k \in \{t - 2D_{\max} - 1, \dots, t - D_{ij_{v'}} - 1\}$ with $j_{v'} \in \mathcal{V}$ and $s_{j_{v'}}(0) = v'$, where \mathcal{M}_i is given by Eq. (30). Recalling again the definition of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ in (7), and noting that $v' \in \mathcal{L}_{r'}$, $j_{v'} \in v'$, $j_1 \in r$, and $r' \rightarrow r$ in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, one can show that

$$D_{j_1 j_{v'}} \leq l_{v'r'} + 1 \leq D_{\max}. \quad (61)$$

We further split our arguments into $D_{ij_{v'}} \leq D_{ij}$ and $D_{ij_{v'}} \geq D_{ij} + 1$. First, supposing $D_{ij_{v'}} \leq D_{ij}$, we have

$$\begin{aligned} t - 2D_{\max} - 1 &\leq t - D_{\max} - l_{v'r'} - 1 \\ t - D_{ij_{v'}} - 1 &\geq t - D_{ij} - l_{v'r'} - 2. \end{aligned} \quad (62)$$

Second, suppose $D_{ij_{v'}} \geq D_{ij} + 1$. Recall from Remark 3 that we let the for loop in lines 5-9 of Algorithm 2 iterate over the elements in $\mathcal{L}(\mathcal{T}_i)$ according to a certain order of the elements in $\mathcal{L}(\mathcal{T}_i)$. We then see from the inequality $D_{ij_{v'}} \geq D_{ij} + 1$ that $s_{j_{v'}}(0) \in \mathcal{L}(\mathcal{T}_i)$ (with $j_{v'} \in \mathcal{V}$ and $s_{j_{v'}}(0) = v'$) has already been considered by the for loop in lines 5-9 in Algorithm 2, i.e., the states $\hat{\zeta}_{v'}(k)$ for all $k \in \{t - 2D_{\max} - 1, \dots, t - D_{ij_{v'}}\}$ are in the current memory of Algorithm 2, denoted as \mathcal{M}'_i , when we consider the $s \in \mathcal{L}(\mathcal{T}_i)$ with $j \in \mathcal{V}$ and $s_j(0) = s$ in the for loop in lines 5-9 of the algorithm. Moreover, we have from the above arguments that $j_{v'} \rightsquigarrow j_1 \rightsquigarrow i$ in $\mathcal{G}(\mathcal{V}, \mathcal{A})$, i.e., there is a directed path from node $j_{v'}$ to node i that goes through node j_1 in $\mathcal{G}(\mathcal{V}, \mathcal{A})$. It then follows that

$$D_{ij_{v'}} \leq D_{ij_1} + D_{j_1 j_{v'}} \leq D_{ij} + D_{jj_1} + D_{j_1 j_{v'}}, \quad (63)$$

where $D_{jj_1} \in \{0, 1\}$. Combining (61) and (63), we obtain

$$\begin{aligned} t - 2D_{\max} - 1 &\leq t - D_{\max} - l_{v'r'} - 1 \\ t - D_{ij_{v'}} &\geq t - D_{ij} - l_{v'r'} - 2. \end{aligned} \quad (64)$$

It then follows from (62) and (64) and our arguments above that the states $\hat{\zeta}_{v'}(k)$ for all $k \in \{t - D_{\max} - l_{v'r'} - 1, \dots, t - D_{ij} - l_{v'r'} - 2\}$ are in the current memory \mathcal{M}'_i described above, for all $v' \in \mathcal{L}_{r'}$. Combining the above arguments together, we have that $\hat{\zeta}_{r'}(k)$ can be determined from Eq. (27) and the current memory \mathcal{M}'_i , for all $k \in \{t - D_{\max} - 1, \dots, t - D_{ij} - 2\}$ and for all r' such that $r' \rightarrow r$ (with $r \neq r'$) in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$. Moreover, recalling that $r \in \mathcal{R}(\mathcal{T}_i)$ as we argued above, we see from Eq. (30) that $\hat{\zeta}_r(t - D_{\max} - 1) \in \mathcal{M}'_i$. One can now apply Eq. (27) multiple times to show that $\hat{\zeta}_r(k)$ can be determined from the current memory \mathcal{M}'_i described above, for all $k \in \{t - D_{\max}, \dots, t - D_{ij} - 1\}$.

Next, suppose r does not have a self loop. Similarly to our arguments above, we first consider the case when r is a leaf node in \mathcal{T}_i , i.e., $r \in \mathcal{L}(\mathcal{T}_i)$. We see that $\hat{\zeta}_r(t - D_{ij_r} - 1) \in \mathcal{M}_i$, where $j_r \in \mathcal{V}$ with $s_{j_r}(0) = r$, and \mathcal{M}_i is defined in Eq. (30). Since $j_1, j_r \in r$, we have from the construction of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ in (7) that $j_r \rightarrow j_1$ in $\mathcal{G}(\mathcal{V}, \mathcal{A})$ with $D_{j_1 j_r} = 0$. Noting that $j_1 \rightsquigarrow i$ in $\hat{\mathcal{G}}(\mathcal{V}, \mathcal{A})$ as we argued above, we then have the following:

$$D_{ij_r} \leq D_{ij} + D_{jj_1} + D_{j_1 j_r} = D_{ij} + D_{jj_1}, \quad (65)$$

where $D_{jj_1} \in \{0, 1\}$. Now, supposing $D_{ij_r} \leq D_{ij}$, we see directly see from Eq. (30) that $\hat{\zeta}_r(t - D_{ij} - 1) \in \mathcal{M}_i$ holds. Supposing $D_{ij_r} \geq D_{ij} + 1$, we see from (65) that $D_{ij_r} = D_{ij} + 1$. Using similar arguments to those above for the case when r has a self loop (particularly, the order of the elements in $\mathcal{L}(\mathcal{T}_i)$ over which the for loop in lines 5-9 of Algorithm 2 iterates), one can show that the states $\hat{\zeta}_r(k)$ for all $k \in \{t - 2D_{\max} - 1, \dots, t - D_{ij_r}\}$ have been added to the current memory of Algorithm 2, denoted as \mathcal{M}''_i , when we consider the $s \in \mathcal{L}(\mathcal{T}_i)$ with $j \in \mathcal{V}$ and $s_j(0) = s$ in the for loop in lines 5-9 of the algorithm. It follows that $\hat{\zeta}_r(t - D_{ij} - 1) \in \mathcal{M}''_i$. Then, we consider the case when r is not a leaf node in \mathcal{T}_i . We see from Eq. (27) that given $\hat{\zeta}_{r'}(t - D_{ij} - 2)$ for all r' such that $r' \rightarrow r$ (with $r \neq r'$) in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, the state $\hat{\zeta}_r(t - D_{ij} - 1)$ can be determined. The remaining arguments then follow directly from those above for the case when r has a self loop.

In summary, we have shown that $\hat{\zeta}_r(t - D_{ij} - 1)$ can be determined from Eq. (27) and the current memory of Algorithm 2, for all $r \ni j_1$, for all $j_1 \in \mathcal{N}_j$, and for all $s \in \mathcal{L}(\mathcal{T}_i)$ with $j \in \mathcal{V}$ and $s_j(0) = s$. It then follows from our arguments above that $\hat{w}_j(t - D_{ij} - 1)$ in line 7 of Algorithm 2, and thus $\hat{\zeta}_s(t - D_{ij})$ in line 8 of Algorithm 2, can be determined using Eq. (27) and the current memory of Algorithm 2, for all $s \in \mathcal{L}(\mathcal{T}_i)$ with $j \in \mathcal{V}$ and $s_j(0) = s$. In other words, we have shown that $\hat{\zeta}_s(t - D_{ij})$ can be added to the memory of Algorithm 2 in line 9, for all $s \in \mathcal{L}(\mathcal{T}_i)$ with $j \in \mathcal{V}$ and $s_j(0) = s$.

Now, let us consider any $s \in \mathcal{R}(\mathcal{T}_i)$ with $\mathcal{R}(\mathcal{T}_i)$ defined in Eq. (24). We will show that $\hat{\zeta}_r(t - D_{\max} - 1)$ can be determined using Eq. (27) and the states in \mathcal{M}_i given by Eq. (30), for all r such that $r \rightarrow s$ in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$. Note from our definition of $\mathcal{R}(\mathcal{T}_i)$ in Eq. (24) that s is not a leaf node. Following similar arguments to those above, let us consider any r such that $r \rightarrow s$ (with $r \neq s$) in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, and denote

$\mathcal{L}_r = \{v \in \mathcal{L}(\mathcal{T}_i) : v \rightsquigarrow r\}$. Further considering any $v \in \mathcal{L}_r$, and noting that $v \in \mathcal{L}(\mathcal{T}_i)$, we have that $\hat{\zeta}_v(k) \in \mathcal{M}_i$ for all $k \in \{t - 2D_{\max} - 1, \dots, t - D_{ij_v} - 1\}$, where \mathcal{M}_i is given by Eq. (30), and $j_v \in \mathcal{V}$ with $s_{j_v}(0) = v$. Similarly to Eq. (61), we have that $l_{vr} \leq D_{\max}$, which implies that $t - 2D_{\max} - 1 \leq t - D_{\max} - l_{vr} - 1$. Therefore, we see that $\hat{\zeta}_v(t - D_{\max} - l_{vr} - 1) \in \mathcal{M}_i$ with \mathcal{M}_i given by Eq. (30), for all $v \in \mathcal{L}_r$. Using similar arguments to those above, one can now recursively apply Eq. (27) to show that $\hat{\zeta}_r(t - D_{\max} - 1)$ can be determined from \mathcal{M}_i given by Eq. (30), for all r such that $r \rightarrow s$ (with $r \neq s$). Since $\hat{\zeta}_s(t - D_{\max} - 1) \in \mathcal{M}_i$, we see from Eq. (27) that $\hat{\zeta}_s(t - D_{\max})$ can be determined from \mathcal{M}_i given by Eq. (30). Thus, we have shown that $\hat{\zeta}_s(t - D_{\max})$ can be added to the memory of Algorithm 2 in line 12, for all $s \in \mathcal{R}(\mathcal{T}_i)$.

Combining all the above arguments together and noting line 14 in Algorithm 2, we see that at the beginning of iteration $(t + 1)$ of the for loop in lines 4-14 of Algorithm 2, the memory \mathcal{M}_i of the algorithm satisfies

$$\mathcal{M}_i = \{\hat{\zeta}_s(k) : k \in \{t - 2D_{\max}, \dots, t - D_{ij}\}, s \in \mathcal{L}(\mathcal{T}_i), j \in \mathcal{V}, s_j(0) = s\} \cup \{\hat{\zeta}_s(t - D_{\max}) : s \in \mathcal{R}(\mathcal{T}_i)\}. \quad (66)$$

This completes the induction step for the proof of Eq. (30), and thus completes the proof of part (a).

We then prove part (b). Consider any $t \in \{0, 1, \dots, T - 1\}$. In order to prove part (b), it suffices for us to show that $\hat{\zeta}_r(t)$ for all $r \ni i$ can be determined using Eq. (27) and the memory \mathcal{M}_i after line 12 (and before line 14) in iteration t of the for loop in lines 4-14 of Algorithm 2, which is given by

$$\begin{aligned} \mathcal{M}_i = \{ & \hat{\zeta}_s(k) : k \in \{t - 2D_{\max} - 1, \dots, t - D_{ij}\}, s \in \mathcal{L}(\mathcal{T}_i), j \in \mathcal{V}, s_j(0) = s\} \\ & \cup \{\hat{\zeta}_s(k) : k \in \{t - D_{\max} - 1, t - D_{\max}\}, s \in \mathcal{R}(\mathcal{T}_i)\}. \end{aligned} \quad (67)$$

Considering any $r \ni i$, one can show via the definition of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ in (7) and the definition of \mathcal{T}_i that $r \in \mathcal{T}_i$. Again, we split our arguments into two cases: r has a self loop, and r does not have a self loop.

First, suppose r has a self loop. For the case when $r \in \mathcal{L}(\mathcal{T}_i)$ (i.e., r is an isolated node in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$), we see that $\hat{\zeta}_r(t - D_{ij_r}) \in \mathcal{M}_i$ with \mathcal{M}_i given by Eq. (67), where $j_r \in \mathcal{V}$ with $s_{j_r}(0) = r$. Noting that $i, j_r \in r$, we see from the definitions of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ in (7) that $j_r \rightarrow i$ in $\mathcal{G}(\mathcal{A}, \mathcal{V})$ with $D_{ij_r} = 0$. It follows that $\hat{\zeta}_r(t) \in \mathcal{M}_i$ with \mathcal{M}_i given by Eq. (67). Thus, we focus on the case when r is not a leaf node, i.e., $r \in \mathcal{R}(\mathcal{T}_i)$. We see from Eq. (27) that given $\hat{\zeta}_r(t - 1)$, and $\hat{\zeta}_{r'}(t - 1)$ for all $r' \rightarrow r$ (with $r' \neq r$) in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, the state $\hat{\zeta}_r(t)$ can be determined. Again, let us consider any r' such that $r' \rightarrow r$ in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, and denote $\mathcal{L}_{r'} = \{v' \in \mathcal{L}(\mathcal{T}_i) : v' \rightsquigarrow r'\}$. Further considering any $v' \in \mathcal{L}_{r'}$, and noting that $v' \in \mathcal{L}(\mathcal{T}_i)$, we have that $\hat{\zeta}_{v'}(k) \in \mathcal{M}_i$ with \mathcal{M}_i given by Eq. (67), for all $k \in \{t - 2D_{\max} - 1, \dots, t - D_{ij_{v'}}\}$, where $j_{v'} \in \mathcal{V}$ and $s_{j_{v'}}(0) = v'$. Similarly to (61), we have that $D_{ij_{v'}} \leq l_{v'r'} + 1 \leq D_{\max}$, which implies that

$$\begin{aligned} t - 2D_{\max} - 1 & \leq t - D_{\max} - l_{v'r'} - 1 \\ t - D_{ij_{v'}} & \geq t - l_{v'r'} - 1. \end{aligned} \quad (68)$$

It then follows from (68) that $\hat{\zeta}_{v'}(k) \in \mathcal{M}_i$ with \mathcal{M}_i given by Eq. (67), for all $k \in \{t - D_{\max} - l_{v'r'} - 1, \dots, t - l_{v'r'} - 1\}$, and for all $v' \in \mathcal{L}_{r'}$. Using similar arguments to those before, one can recursively use Eq. (27) to show that $\hat{\zeta}_{r'}(k)$ can be determined from \mathcal{M}_i given by Eq. (67), for all $k \in \{t - D_{\max} - 1, \dots, t - 1\}$. Moreover, recalling that $r \in \mathcal{R}(\mathcal{T}_i)$ as we argued above, we see that $\hat{\zeta}_r(t - D_{\max} - 1) \in \mathcal{M}_i$ with \mathcal{M}_i given by Eq. (67). One can then apply Eq. (27) multiple times and show that $\hat{\zeta}_r(t)$ can be determined from \mathcal{M}_i given by Eq. (67). Next, suppose r does not have a self loop. Using similar arguments to those above for the case when r has a self loop, one can show that $\hat{\zeta}_r(t)$ can be determined using Eq. (27) and the current memory \mathcal{M}_i given in Eq. (67).

Combining the above arguments together, we conclude that for any $t \in \{0, 1, \dots, T - 1\}$, the control input $\hat{u}_i(t)$ in line 13 can be determined using Eq. (27) and the memory \mathcal{M}_i given by Eq. (67). This completes the proof of part (b). \blacksquare

C Proofs for Perturbation Bounds on Solutions to Riccati Equations

C.1 Proof of Lemma 7

Consider any $r \in \mathcal{U}$ that has a self loop. To show that (40) holds under the assumption on ε given in (43), we use Proposition 2 in [29]. Specifically, since $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$ hold, one can show that $\|\hat{A}_{rr} - A_{rr}\| \leq \varepsilon$ and $\|\hat{B}_{rr} - B_{rr}\| \leq \varepsilon$ hold, for all $r \in \mathcal{U}$. Similarly, noting that $\|A_{rr}\| \leq \|A\|$ and $\|B_{rr}\| \leq \|B\|$ hold, for all $r \in \mathcal{U}$, one can show that $\|A_{rr} + B_{rr}K_r\| \leq \tilde{\Gamma}^2$. Moreover, note that $1 \leq \sigma_n(R) \leq \sigma_{n_r}(R_{rr}) \leq \sigma_1(R_{rr}) \leq \sigma_1(R)$ and $1 \leq \sigma_m(Q) \leq \sigma_{m_r}(Q_{rr}) \leq \sigma_1(Q_{rr}) \leq \sigma_1(Q)$ from Assumption 3, where $n_r \triangleq \sum_{i \in r} n_i$ and $m_r \triangleq \sum_{i \in r} m_i$. Recalling the definitions of κ , γ and Γ , the proof of (40) under the assumption on ε given in (43) now follows from Proposition 2 in [29].

Next, let denote

$$f(\varepsilon) = 6 \frac{\kappa^2}{1 - \gamma^2} \tilde{\Gamma}^5 (1 + \sigma_1(R^{-1})) \varepsilon,$$

and note that $\|P_r\| \leq \Gamma$. Moreover, we see from Eq. (20) that

$$\hat{K}_r = -(R_{rr} + \hat{B}_{rr}^\top \hat{P}_r \hat{B}_{rr})^{-1} \hat{B}_{rr}^\top \hat{P}_r \hat{A}_{rr},$$

where $\|\hat{A}_{rr} - A_{rr}\| \leq \varepsilon$ and $\|\hat{B}_{rr} - B_{rr}\| \leq \varepsilon$. We have

$$\|\hat{B}_{rr}^\top \hat{P}_r \hat{B}_{rr} - B_{rr}^\top P_r B_{rr}\| \leq \|\hat{B}_{rr}^\top \hat{P}_r \hat{B}_{rr} - B_{rr}^\top \hat{P}_r \hat{B}_{rr}\| + \|\hat{B}_{rr}^\top \hat{P}_r \hat{B}_{rr} - B_{rr}^\top P_r \hat{B}_{rr}\| + \|B_{rr}^\top P_r \hat{B}_{rr} - B_{rr}^\top P_r B_{rr}\|,$$

which implies that

$$\|\hat{B}_{rr}^\top \hat{P}_r \hat{B}_{rr} - B_{rr}^\top P_r B_{rr}\| \leq \|\hat{P}_r\| \|\hat{B}_{rr}\| \varepsilon + \|B_{rr}\| \|\hat{B}_{rr}\| f(\varepsilon) + \|B_{rr}\| \|P_r\| \varepsilon.$$

Noting that $\varepsilon \leq f(\varepsilon) \leq \frac{1}{6}$ and recalling the definition of Γ given in (39), we have

$$\|\hat{B}_{rr}^\top \hat{P}_r \hat{B}_{rr} - B_{rr}^\top P_r B_{rr}\| \leq 3\tilde{\Gamma}^2 f(\varepsilon).$$

Similarly, one can show that

$$\|\hat{B}_{rr}^\top \hat{P}_r \hat{A}_{rr} - B_{rr}^\top P_r A_{rr}\| \leq 3\tilde{\Gamma}^2 f(\varepsilon).$$

Now, following similar arguments to those in the proof of Lemma 2 in [29], one can show that

$$\|\hat{K}_r - K_r\| \leq 3\tilde{\Gamma}^3 f(\varepsilon) \leq 1,$$

where the second inequality follows from the assumption on ε given in (43). ■

C.2 Proof of Lemma 8

First, let us consider any $r \in \mathcal{U}$ such that $l_{rs} = 1$, i.e., $r \rightarrow s$. Since s is the unique root node that is reachable from r , we see from Lemma 1 and Remark 1 that s has a self loop. Noting that $\sigma_1(R) \geq 1$ from Assumption 3, and that $\tilde{\Gamma} \geq 1$, we see that any ε satisfying (46) also satisfies (43). Thus, we have from (40) in Lemma 7 that

$$\|\hat{P}_s - P_s\| \leq f(\varepsilon) \leq \frac{1}{6},$$

where

$$f(\varepsilon) = 6 \frac{\kappa^2}{1 - \gamma^2} \tilde{\Gamma}^5 (1 + \sigma_1(R^{-1})) \varepsilon,$$

and we note that $\|P_s\| \leq \Gamma$. Moreover, we see from Eq. (20) that

$$\hat{K}_r = -(R_{rr} + \hat{B}_{sr}^\top \hat{P}_s \hat{B}_{sr})^{-1} \hat{B}_{sr}^\top \hat{P}_s \hat{A}_{sr},$$

where $\|\hat{A}_{sr} - A_{sr}\| \leq \varepsilon$ and $\|\hat{B}_{sr} - B_{sr}\| \leq \varepsilon$ (since $\|\hat{A} - A\| \leq \varepsilon$ and $\|\hat{B} - B\| \leq \varepsilon$). Now, using similar arguments to those in the proof of Lemma 7, one can also show that

$$\|\hat{B}_{sr}^\top \hat{P}_s \hat{B}_{sr} - B_{sr}^\top P_s B_{sr}\| \leq 3\tilde{\Gamma}^2 f(\varepsilon),$$

and

$$\|\hat{B}_{sr}^\top \hat{P}_s \hat{A}_{sr} - B_{sr}^\top P_s A_{sr}\| \leq 3\tilde{\Gamma}^2 f(\varepsilon).$$

Using similar arguments to those in the proof of Lemma 2 in [29], one can now show that

$$\|\hat{K}_r - K_r\| \leq 3\tilde{\Gamma}^3 f(\varepsilon) \leq 1, \quad (69)$$

where the second inequality follows from the assumption on ε given in (46), and we note that $\|K_r\| \leq \Gamma$. Hence, we have shown that (44) holds for $l_{rs} = 1$

To prove Eq. (45) for $l_{rs} = 1$, we first recall the expressions for P_r and \hat{P}_r given in Eqs. (9) and (21), respectively. Using similar arguments to those above, we have

$$\begin{aligned} & \|\hat{A}_{sr} + \hat{B}_{sr} \hat{K}_r - A_{sr} - B_{sr} K_r\| \\ & \leq \|\hat{A}_{sr} - A_{sr}\| + \|\hat{B}_{sr} \hat{K}_r - B_{sr} \hat{K}_r\| + \|B_{sr} \hat{K}_r - B_{sr} K_r\| \\ & \leq \varepsilon + (\Gamma + 1)\varepsilon + \Gamma 3\tilde{\Gamma}^3 f(\varepsilon) \leq 4\tilde{\Gamma}^4 f(\varepsilon), \end{aligned} \quad (70)$$

where the first inequality in (70) follows from (69) and the definition of Γ given in (39). To obtain the second inequality in (70), we first note from Eq. (9) that $P_r \succeq Q_{rr} \succeq \sigma_m(Q)I \succeq I$, where the last inequality follows from Assumption 3. We then have from (39) that $\Gamma \geq \|P_r\| \geq 1$, which further implies that $\tilde{\Gamma} + 1 \leq \tilde{\Gamma}^4$. It follows that the second inequality in (70) holds. To proceed, denoting $\hat{L}_{sr} = \hat{A}_{sr} + \hat{B}_{sr} \hat{K}_r$ and $L_{sr} = A_{sr} + B_{sr} K_r$, we have from Eqs. (9) and (21) that

$$\|\hat{P}_r - P_r\| \leq \|\hat{K}_r^\top R_{rr} \hat{K}_r - K_r^\top R_{rr} K_r\| + \|\hat{L}_{sr}^\top \hat{P}_s \hat{L}_{sr} - L_{sr}^\top P_s L_{sr}\|, \quad (71)$$

where we note that $\|L_{sr}\| \leq \tilde{\Gamma}^2$. From the above arguments, we have the following:

$$\begin{aligned} \|\hat{K}_r^\top R_{rr} \hat{K}_r - K_r^\top R_{rr} K_r\| & \leq \|\hat{K}_r^\top R_{rr} \hat{K}_r - K_r^\top R_{rr} \hat{K}_r\| + \|K_r^\top R_{rr} \hat{K}_r - K_r^\top R_{rr} K_r\| \\ & \leq 3\tilde{\Gamma}^3 f(\varepsilon) \sigma_1(R) (\Gamma + 3\tilde{\Gamma}^3 f(\varepsilon)) + \Gamma \sigma_1(R) 3\tilde{\Gamma}^3 f(\varepsilon) \\ & \leq 6\tilde{\Gamma}^4 \sigma_1(R) f(\varepsilon) + 9\tilde{\Gamma}^6 \sigma_1(R) f(\varepsilon)^2, \end{aligned}$$

and

$$\begin{aligned} & \|\hat{L}_{sr}^\top \hat{P}_s \hat{L}_{sr} - L_{sr}^\top P_s L_{sr}\| \\ & \leq \|\hat{L}_{sr}^\top \hat{P}_s \hat{L}_{sr} - L_{sr}^\top \hat{P}_s \hat{L}_{sr}\| + \|L_{sr}^\top \hat{P}_s \hat{L}_{sr} - L_{sr}^\top P_s L_{sr}\| + \|L_{sr}^\top P_s \hat{L}_{sr} - L_{sr}^\top P_s L_{sr}\| \\ & \leq 4\tilde{\Gamma}^4 f(\varepsilon) (\Gamma + 1) (\tilde{\Gamma}^2 + 4\tilde{\Gamma}^4 f(\varepsilon)) + \tilde{\Gamma}^2 f(\varepsilon) (\tilde{\Gamma}^2 + 4\tilde{\Gamma}^4 f(\varepsilon)) + \tilde{\Gamma}^2 \Gamma 4\tilde{\Gamma}^4 f(\varepsilon) \\ & \leq 4\tilde{\Gamma}^7 f(\varepsilon) + 16\tilde{\Gamma}^9 f(\varepsilon)^2 + \tilde{\Gamma}^4 f(\varepsilon) + 4\tilde{\Gamma}^6 f(\varepsilon)^2 + 4\tilde{\Gamma}^7 f(\varepsilon). \end{aligned}$$

Noting that $f(\varepsilon) \leq \frac{1}{6}$, one can now obtain from (71) that

$$\|\hat{P}_r - P_r\| \leq 20\tilde{\Gamma}^9 \sigma_1(R) f(\varepsilon) \leq \frac{1}{6}, \quad (72)$$

where the second inequality again follows from the assumption on ε given in (46).

Next, let us consider any $r \in \mathcal{U}$ such that $l_{sr} = 2$ (where $s \in \mathcal{U}$ is the unique root node that is reachable from r), and denote the unique directed path from r to s in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ as $r \rightarrow r_1 \rightarrow s$. We see that $r_1 \in \mathcal{U}$ satisfies (69) and (72). Repeating the above arguments for obtaining (69) and (72) one more time, one can show that

$$\|\hat{K}_r - K_r\| \leq 3\tilde{\Gamma}^3 20\tilde{\Gamma}^9 \sigma_1(R) f(\varepsilon) \leq 1,$$

and

$$\|\hat{P}_r - P_r\| \leq (20\tilde{\Gamma}^9 \sigma_1(R))^2 f(\varepsilon) \leq \frac{1}{6},$$

where we use again the assumption on ε given by (46). Further repeating the above arguments, and noting from Eq. (25) and the definition of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ in (7) that $l_{sr} \leq D_{\max}$ for all $s, r \in \mathcal{U}$, one can show that (44)-(45) hold, for all $r \in \mathcal{U}$ without a self loop, under the assumption on ε given in (46). \blacksquare

D Proofs for Perturbation Bounds on Costs

D.1 Proof of Lemma 9

First, let us consider any $s \in \mathcal{U}$ that has a self loop. Noting the construction of the information graph $\hat{\mathcal{G}} = (\mathcal{U}, \mathcal{H})$ given in (7), one can show that Eq. (34) can be rewritten as

$$\tilde{\zeta}_s(t+1) = (A_{ss} + B_{ss}\hat{K}_s)\tilde{\zeta}_s(t) + \sum_{v \in \mathcal{L}_s} H(v, s) \sum_{w_j \rightarrow v} I_{v, \{j\}} w_j(t - l_{vs}), \quad (73)$$

where $\mathcal{L}_s = \{v \in \mathcal{L} : v \rightsquigarrow s\}$ is the set of leaf nodes in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ that can reach s , l_{vs} is the length of the (unique) directed path from node v to node s in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ with $l_{vs} = 0$ if $v = s$, and

$$H(v, s) \triangleq (A_{sr_1} + B_{sr_1}\hat{K}_{r_1}) \cdots (A_{r_{l_{vs}-1}v} + B_{r_{l_{vs}-1}v}\hat{K}_v),$$

with $H(v, s) = I$ if $v = s$, where \hat{K}_r is given by Eq. (8) for all $r \in \mathcal{U}$, and $v, r_{l_{vs}-1}, \dots, r_1, s$ are the nodes along the directed path from v to s in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$. Recalling from Eq. (34) that $\tilde{\zeta}_s(0) = \sum_{w_i \rightarrow s} I_{s, \{i\}} x_i(0) = 0$, in Eq. (73) we set $w_j(t - l_{vs}) = 0$ if $t - l_{vs} < 0$. Now, under the assumption on ε given in Eq. (46), we see from (44) in Lemma 8 that $\|\hat{K}_r\| \leq \tilde{\Gamma}$, which implies that $\|A_{sr} + B_{sr}\hat{K}_r\| \leq \tilde{\Gamma}^2$, for all $r \in \mathcal{U}$ with $r \neq s$. Noting that $l_{vs} \leq D_{\max}$ from the construction of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$, we have $\|H(v, s)\| \leq \tilde{\Gamma}^{2D_{\max}}$, for all $v \in \mathcal{L}_s$. Considering any $t \in \mathbb{Z}_{\geq 0}$ and denoting

$$\eta_s(t) = \sum_{v \in \mathcal{L}_s} H(v, s) \sum_{w_j \rightarrow v} I_{v, \{j\}} w_j(t - l_{vs}), \quad (74)$$

we have

$$\mathbb{E}[\eta_s(t)\eta_s(t)^\top] = \mathbb{E}\left[\sum_{v \in \mathcal{L}_s} \sum_{w_j \rightarrow v} H(v, s) I_{v, \{j\}} w_j(t - l_{vs}) w_j(t - l_{vs})^\top I_{\{j\}, v} H(v, s)^\top\right],$$

where we use the fact from $w(t) \sim \mathcal{N}(0, \sigma_w^2 I)$ that $w_{j_1}(t)$ and $w_{j_2}(t)$ are independent for all $j_1, j_2 \in \mathcal{V}$ with $j_1 \neq j_2$, and the fact that for any $v \in \mathcal{U}$ with $s_j(0) = v$, w_j is the only noise term such that $w_j \rightarrow v$ (see Footnote 2). Moreover, we see that $\eta_s(t_1)$ and $\eta_s(t_2)$ are independent for all $t_1, t_2 \in \mathbb{Z}_{\geq 0}$ with $t_1 \neq t_2$, and that $\eta_s(t)$ is independent of $\tilde{\zeta}_s(t)$ for all $t \in \mathbb{Z}_{\geq 0}$. Now, considering any $k \in \mathbb{Z}_{\geq 0}$ such that $k - l_{vs} \geq 0$ for all $v \in \mathcal{L}_s$, and noting that $w(t) \sim \mathcal{N}(0, \sigma_w^2 I)$ for all $t \in \mathbb{Z}_{\geq 0}$, we have

$$\mathbb{E}[\eta_s(k)\eta_s(k)^\top] = \sigma_w^2 \sum_{v \in \mathcal{L}_s} \sum_{w_j \rightarrow v} H(v, s) I_{v, \{j\}} I_{\{j\}, v} H(v, s)^\top. \quad (75)$$

Let us denote the right-hand side of Eq. (75) as \bar{W}_s , and denote

$$\tilde{L}_{ss} = A_{ss} + B_{ss}\hat{K}_s.$$

Fixing any $\tau \in \mathbb{Z}_{\geq 1}$ such that $\tau - l_{vs} \geq 0$ for all $v \in \mathcal{L}_s$, and considering any $t \geq \tau$, one can then unroll Eq. (73) and show that

$$\mathbb{E}[\tilde{\zeta}_s(t)\tilde{\zeta}_s(t)^\top] = \tilde{L}_{ss}^{t-\tau} \mathbb{E}[\tilde{\zeta}_s(\tau)\tilde{\zeta}_s(\tau)^\top] (\tilde{L}_{ss}^\top)^{t-\tau} + \sum_{k=0}^{t-\tau-1} L_{ss}^k \bar{W}_s (\tilde{L}_{ss}^\top)^k. \quad (76)$$

Under the assumption on ε given in (46), one can obtain from Lemma 7 that $\|\tilde{L}_{ss}^k\| \leq \kappa(\frac{\gamma+1}{2})^k$ for all $k \geq 0$, where $0 < \frac{\gamma+1}{2} < 1$, which implies that \tilde{L}_{ss} is stable. It follows that

$$\begin{aligned} \lim_{t \rightarrow \infty} \mathbb{E}[\tilde{\zeta}_s(t)\tilde{\zeta}_s(t)^\top] &= \lim_{t \rightarrow \infty} \sum_{k=0}^{t-\tau-1} L_{ss}^k \bar{W}_s (\tilde{L}_{ss}^\top)^k \\ &\preceq \|\bar{W}_s\| \lim_{t \rightarrow \infty} \sum_{k=0}^{k-0-1} \|\tilde{L}_{ss}^k\| \|(\tilde{L}_{ss}^\top)^k\| I \\ &\preceq \frac{4\|\bar{W}_s\|\kappa^2}{1-\gamma^2} I. \end{aligned}$$

Noting that $|\mathcal{L}_s| \leq p$ from the definition of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ given in (7), and that for any $v \in \mathcal{U}$ with $s_j(0) = v$, w_j is the only noise term such that $w_j \rightarrow v$, as we argued above, we have from Eq. (75) that

$$\|\bar{W}_s\| \leq \sigma_w^2 p \max_{v \in \mathcal{L}_s} \|H(v, s)\|^2 \leq \sigma_w^2 p \tilde{\Gamma}^{4D_{\max}},$$

where the second inequality follows from the fact that $\|H(v, s)\| \leq \tilde{\Gamma}^{2D_{\max}}$ as we argued above. It then follows that (47) holds.

Next, let us consider any $s \in \mathcal{U}$ that does not have a self loop. Similarly to Eq. (73), one can rewrite Eq. (34) as

$$\tilde{\zeta}_s(t+1) = \sum_{v \in \mathcal{L}_s} H(v, s) \sum_{w_j \rightarrow v} I_{v, \{j\}} w_j(t - l_{vs}).$$

Using similar arguments to those above, one can show that (47) also holds. \blacksquare

D.2 Proof of Proposition 3

First, since ε satisfies (46) (and thus (43)), we have from (42) in Lemma 8 that $A_{ss} + B_{ss}\hat{K}_s$ is stable for any $s \in \mathcal{U}$ that has a self loop. Now, using similar arguments to those for the proofs of Theorem 2 and Corollary 4 in [26], and leveraging Lemma 6 and Eqs. (33)-(34), (20) and (48), one can show that Eq. (49) holds. To proceed, for any $t \in \mathbb{Z}_{\geq 0}$ and for any $T \geq t$ and, we set $T' = T + \lceil \frac{\varphi}{J_\star} T \rceil$, and define

$$J_T(\tilde{x}(t)) = \mathbb{E} \left[\sum_{k=t}^{T'-1} (x(k)^\top Q x(k) + u^\star(k)^\top R u^\star(k)) \right], \quad (77)$$

where $u^\star(k) = \sum_{s \in \mathcal{U}} I_{\mathcal{V}, s} K_s \zeta_s(k)$ is the optimal control policy given by Eq. (11), for all $i \in \mathcal{V}$ and for all $k \geq t$, and where K_r and $\zeta_r(k)$ are given by Eqs. (8) and (10), respectively, for all $r \in \mathcal{U}$. Moreover, on the right-hand side of Eq. (77), we set $x(t) = \tilde{x}(t)$, where $\tilde{x}(t)$ given by Eq. (35) is the state after applying the control policy $\tilde{u}(k)$ in Eq. (33) for $k \in \{0, \dots, t-1\}$. Noting that $\tilde{x}(0) = x(0)$ as we discussed at the beginning of Section 5, and that $T + \frac{\varphi}{J_\star} T \leq T' \leq T + \frac{\varphi}{J_\star} T + 1$, we see that

$$\begin{aligned} \lim_{T \rightarrow \infty} \frac{1}{T} J_T(\tilde{x}(0)) &= \lim_{T \rightarrow \infty} \left(\frac{T'}{T} \frac{1}{T'} J_T(\tilde{x}(0)) \right) \\ &= \lim_{T \rightarrow \infty} \frac{T'}{T} \left(\lim_{T \rightarrow \infty} \frac{1}{T'} J_T(\tilde{x}(0)) \right) \\ &\leq \left(1 + \frac{\varphi}{J_\star} \right) J_\star = J_\star + \varphi, \end{aligned}$$

where we use the fact that $\lim_{T \rightarrow \infty} \frac{1}{T'} J_T(\tilde{x}(0)) = J_\star$.

Recalling the definition of \tilde{J} in Eq. (37), we denote $\tilde{c}(t) = \tilde{x}(t)^\top Q \tilde{x}(t) + \tilde{u}(t)^\top R \tilde{u}(t)$. We then have the following:

$$\begin{aligned} \tilde{J} &= \lim_{T \rightarrow \infty} \frac{1}{T} \mathbb{E} \left[\sum_{t=0}^{T-1} \tilde{c}(t) \right] \\ &= \lim_{T \rightarrow \infty} \frac{1}{T} \left(\mathbb{E} \left[\sum_{t=0}^{T-1} (\tilde{c}(t) - J_T(\tilde{x}(t))) + \sum_{t=0}^{T-1} J_T(\tilde{x}(t)) \right] \right) \\ &= \lim_{T \rightarrow \infty} \frac{1}{T} \left(\mathbb{E} \left[\sum_{t=0}^{T-2} (\tilde{c}(t) - J_T(\tilde{x}(t))) + \sum_{t=0}^{T-2} J_T(\tilde{x}(t+1)) + J_T(\tilde{x}(0)) \right] \right) \\ &= \lim_{T \rightarrow \infty} \frac{1}{T} \left(\mathbb{E} \left[\sum_{t=0}^{T-2} (\tilde{c}(t) + J_T(\tilde{x}(t+1)) - J_T(\tilde{x}(t))) + J_T(\tilde{x}(0)) \right] \right). \end{aligned}$$

Using similar arguments to those for the proof of Theorem 2 in [26], one can show that

$$J_T(\tilde{x}(t+1)) - J_T(\tilde{x}(t)) = \mathbb{E} \left[\sum_{r \in \mathcal{U}} \tilde{\zeta}_r(t+1)^\top P_r(t+1) \tilde{\zeta}_r(t+1) \right] \\ - \mathbb{E} \left[\sum_{r \in \mathcal{U}} \tilde{\zeta}_r(t)^\top P_r(t) \tilde{\zeta}_r(t) \right] - \sigma_w^2 \sum_{\substack{i \in \mathcal{V} \\ w_i \rightarrow r}} \text{Tr}(I_{\{i\},r} P_r(t+1) I_{r,\{i\}}), \quad (78)$$

where $\tilde{\zeta}_r(k) = \sum_{w_i \rightarrow r} I_{r,\{i\}} \tilde{x}_i(k)$ for $k \in \{t, t+1\}$. To obtain $P_r(t)$ for all $t \in \{0, \dots, T\}$ and for all $r \in \mathcal{U}$ in Eq. (78), we use the following recursion:

$$P_r(k) = Q_{rr} + K_r^\top R_{rr} K_r + (A_{sr} + B_{sr} K_r)^\top P_s(k+1) (A_{sr} + B_{sr} K_r), \quad (79)$$

initialized with $P_r(T') = 0$ for all $r \in \mathcal{U}$, where $T' = T + \lceil \frac{\varphi}{J_\star} T \rceil$, and for each $r \in \mathcal{U}$, we let $s \in \mathcal{U}$ be the unique node such that $r \rightarrow s$, and K_r is given by Eq. (8) for all $r \in \mathcal{U}$. Combining the above arguments together, we obtain the following:

$$\tilde{J} - J_\star = \lim_{T \rightarrow \infty} \frac{1}{T} \mathbb{E} \left[\sum_{t=0}^{T-1} \left(\tilde{c}(t) + \sum_{r \in \mathcal{U}} \tilde{\zeta}_r(t+1)^\top P_r(t+1) \tilde{\zeta}_r(t+1) - \sum_{r \in \mathcal{U}} \tilde{\zeta}_r(t)^\top P_r(t) \tilde{\zeta}_r(t) \right. \right. \\ \left. \left. - \sigma_w^2 \sum_{\substack{i \in \mathcal{V} \\ w_i \rightarrow r}} \text{Tr}(I_{\{i\},r} P_r(t+1) I_{r,\{i\}}) \right) \right] + \lim_{T \rightarrow \infty} \frac{1}{T} J_T(\tilde{x}(0)) - J_\star$$

$$\leq \lim_{T \rightarrow \infty} \frac{1}{T} \mathbb{E} \left[\sum_{t=0}^{T-1} \sum_{r \in \mathcal{U}} \left(\tilde{\zeta}_r(t)^\top (Q_{rr} + \hat{K}_r^\top R_{rr} \hat{K}_r) \tilde{\zeta}_r(t) + \tilde{\zeta}_r(t+1)^\top P_r(t+1) \tilde{\zeta}_r(t+1) \right. \right. \\ \left. \left. - \tilde{\zeta}_r(t)^\top P_r(t) \tilde{\zeta}_r(t) - \sigma_w^2 \sum_{\substack{i \in \mathcal{V} \\ w_i \rightarrow r}} \text{Tr}(I_{\{i\},r} P_r(t+1) I_{r,\{i\}}) \right) \right] + \varphi \quad (80)$$

$$= \lim_{T \rightarrow \infty} \frac{1}{T} \mathbb{E} \left[\sum_{t=0}^{T-1} \sum_{r \in \mathcal{U}} \left(\tilde{\zeta}_r(t)^\top (Q_{rr} + \hat{K}_r^\top R_{rr} \hat{K}_r - P_r(t)) \tilde{\zeta}_r(t) \right. \right. \\ \left. \left. + \sum_{v \rightarrow r} \tilde{\zeta}_v^\top(t) (A_{rv} + B_{rv} \hat{K}_v)^\top P_r(t+1) (A_{rv} + B_{rv} \hat{K}_v) \tilde{\zeta}_v(t) \right) \right] + \varphi \quad (81)$$

$$= \lim_{T \rightarrow \infty} \frac{1}{T} \mathbb{E} \left[\sum_{t=0}^{T-1} \sum_{r \in \mathcal{U}} \left(\tilde{\zeta}_r(t)^\top (Q_{rr} + \hat{K}_r^\top R_{rr} \hat{K}_r - P_r(t)) \tilde{\zeta}_r(t) \right. \right. \\ \left. \left. + \tilde{\zeta}_r^\top(t) ((A_{sr} + B_{sr} \hat{K}_r)^\top P_s(t+1) (A_{sr} + B_{sr} \hat{K}_r)) \tilde{\zeta}_r(t) \right) \right] + \varphi, \quad (82)$$

where for each $r \in \mathcal{U}$ in Eq. (82), we let $s \in \mathcal{U}$ be the unique node such that $r \rightarrow s$. To obtain Eq. (80), we note from Lemma 6 that $\tilde{x}(t) = \sum_{r \in \mathcal{U}} I_{\mathcal{V},r} \tilde{\zeta}_r(t)$ for all $t \in \mathbb{Z}_{\geq 0}$, where $\mathbb{E}[\tilde{\zeta}_r(t)] = 0$ for all $r \in \mathcal{U}$, and $\tilde{\zeta}_{r_1}(t)$ and $\tilde{\zeta}_{r_2}(t)$ are independent for all $r_1, r_2 \in \mathcal{U}$ with $r_1 \neq r_2$. Moreover, we note from Eq. (33) that $\tilde{u}(t) = \sum_{r \in \mathcal{U}} I_{\mathcal{V},s} \hat{K}_r \tilde{\zeta}_r(t)$ for all $t \in \mathbb{Z}_{\geq 0}$, where \hat{K}_r is given by Eq. (20). Combining the above arguments together, and recalling that $\tilde{c}_t = \tilde{x}(t)^\top Q \tilde{x}(t) + \tilde{u}(t)^\top R \tilde{u}(t)$, we obtain Eq. (80). To obtain Eq. (81), we first apply Eq. (34) and notice $w(t) \sim \mathcal{N}(0, \sigma_w^2 I)$. Next, we use the facts that the information graph $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ defined in (7) is a tree (see Lemma 1 and Remark 1), and that $\tilde{\zeta}_{r_1}(t)$ and $\tilde{\zeta}_{r_2}(t)$ are independent for all $r_1, r_2 \in \mathcal{U}$ with $r_1 \neq r_2$ and for all $t \in \mathbb{Z}_{\geq 0}$, as we argued above. To obtain Eq. (82), we leverage again the tree structure of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$.

Now, leveraging the recursion in Eq. (79), and using similar arguments to those for the proof of Lemma 12 in [16], one can show via (82) that

$$\tilde{J} - J_\star \leq \lim_{T \rightarrow \infty} \frac{1}{T} \mathbb{E} \left[\sum_{t=0}^{T-1} \sum_{r \in \mathcal{U}} \left(\tilde{\zeta}_r(t)^\top (\hat{K}_r - K_r)^\top (R_{rr} + B_{sr}^\top P_s(t+1) B_{sr}) (\hat{K}_r - K_r) \tilde{\zeta}_r(t) \right. \right. \\ \left. \left. + 2 \tilde{\zeta}_r(t)^\top (\hat{K}_r - K_r)^\top ((R_{rr} + B_{sr}^\top P_s(t+1) B_{sr}) K_r + B_{sr}^\top P_s(t+1) A_{sr}) \tilde{\zeta}_r(t) \right) \right] + \varphi.$$

Recall from Lemma 2 that $A_{ss} + B_{ss}K_s$ is stable for any $s \in \mathcal{U}$ that has a self loop. Using similar arguments to those for the proof of Corollary 4 in [26], one can show via Eq. (79) that $P_r(t) \rightarrow P_r$ as $T \rightarrow \infty$, for all $t \in \{0, \dots, T\}$ and for all $r \in \mathcal{U}$, where P_r is given by Eq. (9). It then follows that

$$\begin{aligned}
\tilde{J} - J_\star &\leq \lim_{T \rightarrow \infty} \frac{1}{T} \mathbb{E} \left[\sum_{t=0}^{T-1} \sum_{r \in \mathcal{U}} \left(\tilde{\zeta}_r(t)^\top (\hat{K}_r - K_r)^\top (R_{rr} + B_{sr}^\top P_s B_{sr}) (\hat{K}_r - K_r) \tilde{\zeta}_r(t) \right. \right. \\
&\quad \left. \left. + 2\tilde{\zeta}_r(t)^\top (\hat{K}_r - K_r)^\top ((R_{rr} + B_{sr}^\top P_s B_{sr}) K_r + B_{sr}^\top P_s A_{sr}) \tilde{\zeta}_r(t) \right) \right] + \varphi \\
&= \lim_{T \rightarrow \infty} \frac{1}{T} \mathbb{E} \left[\sum_{t=0}^{T-1} \sum_{r \in \mathcal{U}} \left(\tilde{\zeta}_r(t)^\top (\hat{K}_r - K_r)^\top (R_{rr} + B_{sr}^\top P_s B_{sr}) (\hat{K}_r - K_r) \tilde{\zeta}_r(t) \right) + \varphi \right] \\
&= \text{Tr} \left(\sum_{r \in \mathcal{U}} (\hat{K}_r - K_r)^\top (R_{rr} + B_{sr}^\top P_s B_{sr}) (\hat{K}_r - K_r) \lim_{t \rightarrow \infty} \mathbb{E} \left[\tilde{\zeta}_r(t) \tilde{\zeta}_r(t)^\top \right] \right) + \varphi, \tag{83}
\end{aligned}$$

where the equality follows from Eq. (8), and the second equality follows from the fact that the limit $\lim_{t \rightarrow \infty} \mathbb{E} [\tilde{\zeta}_r(t) \tilde{\zeta}_r(t)^\top]$ exists, for all $r \in \mathcal{U}$, as we argued in the proof of Lemma 9.

Finally, substituting (47) in Lemma 9 into the right-hand side of (83), we obtain

$$\begin{aligned}
\tilde{J} - J_\star &\leq \frac{4p\sigma_w^2 \tilde{\Gamma}^{4D_{\max}} \kappa^2}{1 - \gamma^2} \text{Tr} \left(\sum_{r \in \mathcal{U}} (K_r - \hat{K}_r)^\top (R_{rr} + B_{sr}^\top P_s B_{sr}) (K_r - \hat{K}_r) \right) + \varphi \\
&\leq \frac{4p\sigma_w^2 \tilde{\Gamma}^{4D_{\max}} \kappa^2}{1 - \gamma^2} (\Gamma^3 + \sigma_1(R)) \text{Tr} \left(\sum_{r \in \mathcal{U}} (K_r - \hat{K}_r)^\top (K_r - \hat{K}_r) \right) + \varphi \\
&\leq \frac{4p\sigma_w^2 \tilde{\Gamma}^{4D_{\max}} \kappa^2}{1 - \gamma^2} (\Gamma^3 + \sigma_1(R)) \sum_{r \in \mathcal{U}} \min\{m_r, n_r\} \|K_r - \hat{K}_r\|^2 + \varphi \\
&\leq \frac{72\kappa^4 \sigma_w^2 p q n}{(1 - \gamma^2)^2} \tilde{\Gamma}^{4D_{\max}+8} (\Gamma^3 + \sigma_1(R)) (1 + \sigma_1(R^{-1})) (20\tilde{\Gamma}^9 \sigma_1(R))^{D_{\max}} \varepsilon + \varphi, \tag{84}
\end{aligned}$$

where the third inequality follows from the fact that $K_r, \hat{K}_r \in \mathbb{R}^{n_r \times m_r}$ for all $r \in \mathcal{U}$, with $n_r \triangleq \sum_{i \in r} n_i$ and $m_r \triangleq \sum_{i \in r} m_i$. To obtain (84), we first note that ε is assumed to satisfy (46) (and thus (43)). Recalling $|\mathcal{U}| = q$, and $n_i \geq m_i$ for all $i \in \mathcal{V}$ as we assumed previously, we then obtain (84) from Lemmas 7-8, where we also use the fact that $\|\hat{K}_r - K_r\| \leq 1$ for all $r \in \mathcal{U}$. \blacksquare

D.3 Proof of Lemma 10

First, considering any $s \in \mathcal{U}$ and any $t \in \mathbb{Z}_{\geq 0}$, we have

$$\begin{aligned}
\mathbb{E} \left[\|\tilde{\zeta}_s(t)\|^2 \right] &= \mathbb{E} \left[\tilde{\zeta}_s(t)^\top \tilde{\zeta}_s(t) \right] = \mathbb{E} \left[\text{Tr} \left(\tilde{\zeta}_s(t) \tilde{\zeta}_s(t)^\top \right) \right] = \text{Tr} \left(\mathbb{E} \left[\tilde{\zeta}_s(t) \tilde{\zeta}_s(t)^\top \right] \right) \\
&\leq n\sigma_1 \left(\mathbb{E} \left[\tilde{\zeta}_s(t) \tilde{\zeta}_s(t)^\top \right] \right).
\end{aligned}$$

Following similar arguments to those in the proof of Lemma 9 (particularly Eq. (76)), one can show that

$$\mathbb{E} \left[\tilde{\zeta}_s(t) \tilde{\zeta}_s(t)^\top \right] \preceq \tilde{L}_{ss}^t \mathbb{E} \left[\tilde{\zeta}_s(0) \tilde{\zeta}_s(0)^\top \right] (\tilde{L}_{ss}^\top)^t + \sigma_w^2 p \tilde{\Gamma}^{4D_{\max}} \sum_{k=0}^{t-1} L_{ss}^k (\tilde{L}_{ss}^\top)^k,$$

where $\tilde{L}_{ss} = A_{ss} + B_{ss} \hat{K}_s$, and $\tilde{\zeta}_s(0) = \sum_{w_i \rightarrow s} I_{s, \{i\}} x_i(0) = 0$. Since ε satisfies (46) and thus (43), we see from Lemma 7 that $\|\tilde{L}_{ss}^k\| \leq \kappa \left(\frac{\gamma+1}{2}\right)^k$ for all $k \in \mathbb{Z}_{\geq 0}$. It now follows that

$$\begin{aligned}
\mathbb{E} \left[\tilde{\zeta}_s(t) \tilde{\zeta}_s(t)^\top \right] &\preceq \sigma_w^2 p \kappa^2 \tilde{\Gamma}^{4D_{\max}} \sum_{k=0}^t \left(\frac{\gamma+1}{2} \right)^{2k} I \\
&\preceq \frac{4\sigma_w^2 p \kappa^2 \tilde{\Gamma}^{4D_{\max}}}{1 - \gamma^2} I.
\end{aligned}$$

Combining the above arguments together, we obtain (50).

Next, recalling from Lemma 6 that $\tilde{x}(t) = \sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \tilde{\zeta}_s(t)$ for all $t \in \mathbb{Z}_{\geq 0}$, we then have

$$\begin{aligned} \mathbb{E}[\|\tilde{x}(t)\|^2] &= \mathbb{E}\left[\left(\sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \tilde{\zeta}_s(t)\right)^\top \left(\sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \tilde{\zeta}_s(t)\right)\right] \\ &\leq \left(\sum_{s \in \mathcal{U}} \sqrt{\mathbb{E}\left[\tilde{\zeta}_s(t)^\top I_{s,\mathcal{V}} I_{\mathcal{V},s} \tilde{\zeta}_s(t)\right]}\right)^2 \\ &\leq \left(\sum_{s \in \mathcal{U}} \sqrt{\mathbb{E}\left[\|\tilde{\zeta}_s(t)\|^2\right]}\right)^2 \\ &\leq \frac{4npq^2 \sigma_w^2 \tilde{\Gamma}^{4D_{\max}} \kappa^2}{1 - \gamma^2}, \end{aligned}$$

where the first inequality follows from Lemma 14, and the last inequality follows from the fact that $|\mathcal{U}| = q$. This completes the proof of (51).

Finally, we note from Eq. (33) that $\tilde{u}(t) = \sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \hat{K}_s(t) \tilde{\zeta}_s(t)$. Moreover, since ε satisfies (46) (and thus (43)), we know from Lemmas 7-8 that $\|\hat{K}_s - K_s\| \leq 1$ for all $s \in \mathcal{U}$, which implies via the definition of Γ given in (39) that $\|\hat{K}_s\| \leq \tilde{\Gamma}$ for all $s \in \mathcal{U}$. Now, using similar arguments to those above, we can show that (52) holds. \blacksquare

D.4 Proof of Lemma 11

For notational simplicity in this proof, we denote

$$\begin{aligned} \delta_h &= p(\tilde{\Gamma} + 1)^{2D_{\max}-1}, \quad \beta = \tilde{\Gamma}^{2D_{\max}}, \\ \Lambda_1 &= q\tilde{\Gamma} \left(\frac{2\kappa p(\beta + 1)}{1 - \gamma} + \frac{32\kappa^2 p(\tilde{\Gamma} + 1)}{(1 - \gamma)^2} \right) \left(1 + \frac{\kappa\Gamma}{1 - \gamma} \right), \end{aligned}$$

and

$$\Lambda_2 = \frac{2pq\tilde{\Gamma}\kappa}{1 - \gamma} ((\beta + 1)q(\tilde{\Gamma} + 1) + \delta_h)\zeta_b + \frac{16\kappa^2 pq\tilde{\Gamma}(\tilde{\Gamma} + 1)}{(1 - \gamma)^2} (2q(\tilde{\Gamma} + 1) + 2)\zeta_b.$$

We first prove (54). Based on the above notations, we can show that

$$\begin{aligned} \Lambda_2 &= \left(\frac{2\kappa pq^2}{1 - \gamma} \tilde{\Gamma}(\tilde{\Gamma} + 1)(\beta + 1) + \frac{32\kappa^2 pq^2}{(1 - \gamma)^2} \tilde{\Gamma}(\tilde{\Gamma} + 1)^2 \right) \zeta_b + \left(\frac{2\kappa pq}{1 - \gamma} \tilde{\Gamma} \delta_h + \frac{32\kappa^2 pq}{(1 - \gamma)^2} \tilde{\Gamma}(\tilde{\Gamma} + 1) \right) \zeta_b \\ &\leq \frac{34\kappa^2 pq^2}{(1 - \gamma)^2} (\tilde{\Gamma} + 1)^2 \tilde{\Gamma}^{2D_{\max}+1} \zeta_b + \frac{18\kappa^2 p^2 q}{(1 - \gamma)^2} (\tilde{\Gamma} + 1)^{2D_{\max}+3} \zeta_b \\ &\leq \frac{52\kappa^2 p^2 q^2}{(1 - \gamma)^2} (\tilde{\Gamma} + 1)^{2D_{\max}+3} \zeta_b, \end{aligned}$$

where the first inequality follows from the facts that $\frac{\kappa}{1 - \gamma} > 1$, and that $\beta + 1 \leq \tilde{\Gamma}^{2D_{\max}+1}$ since $\tilde{\Gamma} = \Gamma + 1 \geq 2$ (see our arguments in the proof of Lemma 8). We then have

$$1.1\Lambda_2 \leq \frac{58\kappa^2 (\tilde{\Gamma} + 1)^{2D_{\max}+3} p^2 q^2}{(1 - \gamma)^2} \zeta_b. \quad (85)$$

Thus, in order to show that (54) holds for all $t \in \mathbb{Z}_{\geq 0}$, it suffices to show that $\mathbb{E}[\|u(t) - \tilde{u}(t)\|^2] \leq (1.1\Lambda_2 \varepsilon)^2$ holds for all $t \in \mathbb{Z}_{\geq 0}$. To this end, we prove via an induction on $t = 0, 1, \dots$. For any $t \in \mathbb{Z}_{\geq 0}$, we recall from Eqs. (22) and (33) that $\hat{u}_i(t) = \sum_{r \ni i} I_{\{i\},r} \hat{K}_r \hat{\zeta}_r(t)$ and $\tilde{u}_i(t) = \sum_{r \ni i} I_{\{i\},r} \hat{K}_r \tilde{\zeta}_r(t)$, respectively, for all $i \in \mathcal{V}$, where $\hat{\zeta}_r(t)$ and $\tilde{\zeta}_r(t)$ are given by Eqs. (27) and (34), respectively, and \hat{K}_r is given by Eq. (20), for all $r \in \mathcal{U}$. As we argued before, in Eqs. (27) and (34) we have $\hat{\zeta}_r(0) = \tilde{\zeta}_r(0) = \sum_{w_i \rightarrow r} I_{r,\{i\}} x_i(0)$ for all $r \in \mathcal{U}$. Hence, we have $\hat{u}(0) = \tilde{u}(0)$, which implies that (54) holds for $t = 0$, completing the proof of the base step of the induction.

For the induction step, suppose $\mathbb{E}[\|\hat{u}(k) - \tilde{u}(k)\|^2] \leq (1.1\Lambda_2\bar{\varepsilon})^2$ holds for all $k \in \{0, \dots, t\}$. Now, considering any $k \in \{0, \dots, t\}$, we can unroll the expressions of $\hat{x}(k)$ and $\tilde{x}(k)$ given by Eqs. (31) and (35), respectively, and obtain

$$\hat{x}(k) = A^{k-0}\hat{x}(0) + \sum_{k'=0}^{k-1} A^{k-k'-1}(B\hat{u}(k') + w(k')),$$

and

$$\tilde{x}(k) = A^{k-0}\tilde{x}(0) + \sum_{k'=0}^{k-1} A^{k-k'-1}(B\tilde{u}(k') + w(k')),$$

where we note that $\hat{x}(0) = \tilde{x}(0) = x(0)$. It then follows that

$$\begin{aligned} \sqrt{\mathbb{E}[\|\hat{x}(k) - \tilde{x}(k)\|^2]} &\leq \sum_{k'=0}^{k-1} \sqrt{\mathbb{E}[\|A^{k-k'-1}B(\hat{u}(k') - \tilde{u}(k'))\|^2]} \\ &\leq \sum_{k'=0}^{k-1} \sqrt{\mathbb{E}[\|A^{k-k'-1}\|^2 \|B\|^2 \|\hat{u}(k') - \tilde{u}(k')\|^2]} \\ &\leq \|B\| \sum_{k'=0}^{k-1} \|A^{k-k'-1}\| \sqrt{\mathbb{E}[\|\hat{u}(k') - \tilde{u}(k')\|^2]} \\ &\leq \Gamma 1.1\Lambda_2\bar{\varepsilon} \sum_{k'=0}^{k-1} \|A^{k-k'-1}\| \leq 1.1\Gamma\Lambda_2\bar{\varepsilon} \frac{\kappa}{1-\gamma}, \end{aligned} \quad (86)$$

where the first inequality follows from Lemma 14. To obtain the first inequality in (86), we use the induction hypothesis. To obtain the second inequality in (86), we use the fact that $\|A^{k'}\| \leq \kappa\gamma^{k'}$ (with $0 < \gamma < 1$), for all $k' \in \mathbb{Z}_{\geq 0}$, from Assumption 2. Recalling from our arguments in Section 4 (particularly, Eq. (28)), one can show that

$$\hat{w}(k) = \hat{x}(k+1) - \hat{A}\hat{x}(k) - \hat{B}\hat{u}(k),$$

where $\hat{w}(k) = [\hat{w}_1(k)^\top \ \dots \ \hat{w}_p(k)^\top]^\top$ is an estimate of $w(k)$ in Eq. (2). From Eq. (31), we see that

$$w(k) = \hat{x}(k+1) - A\hat{x}(k) - B\hat{u}(k).$$

It follows that

$$\begin{aligned} \|\hat{w}(k) - w(k)\| &\leq \|\hat{A} - A\|\|\hat{x}(k)\| + \|\hat{B} - B\|\|\hat{u}(k)\| \\ &\leq (\|\hat{x}(k)\| + \|\hat{u}(k)\|)\bar{\varepsilon}. \end{aligned}$$

Recall from Lemma 10 that $\mathbb{E}[\|\hat{x}(k)\|^2] \leq q^2\zeta_b^2$ and $\mathbb{E}[\|\tilde{u}(k)\|^2] \leq q^2\tilde{\Gamma}^2\zeta_b^2$, for all $k \in \mathbb{Z}_{\geq 0}$. We then obtain

$$\begin{aligned} \mathbb{E}[\|\hat{x}(k)\|^2] &= \mathbb{E}[\|\hat{x}(k) - \tilde{x}[k] + \tilde{x}[k]\|^2] \\ &\leq \left(\sqrt{\mathbb{E}[\|\hat{x}(k) - \tilde{x}(k)\|^2]} + \sqrt{\mathbb{E}[\|\tilde{x}[k]\|^2]} \right)^2 \\ &\leq \left(\frac{1.1\Gamma\Lambda_2\kappa}{1-\gamma}\bar{\varepsilon} + q\zeta_b \right)^2, \end{aligned}$$

where the first inequality follows again from Lemma 14, and the second inequality uses (86). Similarly, we have

$$\begin{aligned} \mathbb{E}[\|\hat{u}(k)\|^2] &= \mathbb{E}[\|\hat{u}(k) - \tilde{u}[k] + \tilde{u}[k]\|^2] \\ &\leq \left(\sqrt{\mathbb{E}[\|\hat{u}(k) - \tilde{u}(k)\|^2]} + \sqrt{\mathbb{E}[\|\tilde{u}[k]\|^2]} \right)^2 \\ &\leq (1.1\Lambda_2\bar{\varepsilon} + q\tilde{\Gamma}\zeta_b)^2. \end{aligned}$$

It then follows that

$$\begin{aligned}
\mathbb{E}\left[\|\hat{w}(k) - w(k)\|^2\right] &= \mathbb{E}\left[\|(\hat{A} - A)\hat{x}(k) + (\hat{B} - B)\hat{u}(k)\|^2\right] \\
&\leq \left(\sqrt{\mathbb{E}\left[\|(\hat{A} - A)\hat{x}(k)\|^2\right]} + \sqrt{\mathbb{E}\left[\|(\hat{B} - B)\hat{u}(k)\|^2\right]}\right)^2 \\
&\leq \left(\sqrt{\mathbb{E}\left[\|\hat{x}(k)\|^2\right]} + \sqrt{\mathbb{E}\left[\|\hat{u}(k)\|^2\right]}\right)^2 \bar{\varepsilon}^2 \\
&\leq (q(\tilde{\Gamma} + 1)\zeta_b + \frac{1.1\Gamma\Lambda_2\kappa}{1-\gamma}\bar{\varepsilon} + 1.1\Lambda_2)^2 \bar{\varepsilon}^2,
\end{aligned}$$

where the first inequality again follows from Lemma 14, and the second inequality follows from $\|\hat{A} - A\| \leq \bar{\varepsilon}$ and $\|\hat{B} - B\| \leq \bar{\varepsilon}$. Denoting

$$\delta_w = q(\tilde{\Gamma} + 1)\zeta_b + \frac{1.1\Gamma\Lambda_2\kappa}{1-\gamma}\bar{\varepsilon} + 1.1\Lambda_2\bar{\varepsilon}, \quad (87)$$

we have

$$\mathbb{E}\left[\|\hat{w}(k) - w(k)\|^2\right] \leq \delta_w^2 \bar{\varepsilon}^2 \quad \forall k \in \{0, \dots, t\}. \quad (88)$$

Moreover, note that

$$\begin{aligned}
\mathbb{E}\left[\|w(k)\|^2\right] &= \mathbb{E}\left[\text{Tr}(w(k)w(k)^\top)\right] = \text{Tr}\left(\mathbb{E}\left[w(k)w(k)^\top\right]\right) \\
&= n\sigma_w^2 \leq \zeta_b^2 \quad \forall k \in \mathbb{Z}_{\geq 0}.
\end{aligned} \quad (89)$$

To proceed, let us consider any $s \in \mathcal{U}$ that has a self loop. Recalling the arguments in the proof of Lemmas 9, we can rewrite Eq. (34) as

$$\tilde{\zeta}_s(t+1) = (A_{ss} + B_{ss}\hat{K}_s)\tilde{\zeta}_s(t) + \eta_s(t), \quad (90)$$

with

$$\eta_s(t) = \sum_{v \in \mathcal{L}_s} H(v, s) \sum_{w_j \rightarrow v} I_{v, \{j\}} w_j(t - l_{vs}), \quad (91)$$

where $\mathcal{L}_s = \{v \in \mathcal{L} : v \rightsquigarrow s\}$ is the set of leaf nodes in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ that can reach s , l_{vs} is the length of the (unique) directed path from node v to node s in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ with $l_{vs} = 0$ if $v = s$, and

$$H(v, s) = (A_{sr_1} + B_{sr_1}\hat{K}_{r_1}) \cdots (A_{r_{l_{vs}-1}v} + B_{r_{l_{vs}-1}v}\hat{K}_v),$$

with $H(v, s) = I$ if $v = s$, where $v, r_{l_{vs}-1}, \dots, r_1, s$ are the nodes along the directed path from v to s in $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$. We also recall from the arguments in the proof of Lemma 9 that $\|H(v, s)\| \leq \beta$ for all $v \in \mathcal{L}_s$. We then see from (75) in the proof of Lemma 9 and the definition of ζ_b in (53) that

$$\begin{aligned}
\mathbb{E}\left[\|\eta_s(k)\|^2\right] &= \mathbb{E}\left[\text{Tr}(\eta_s(k)\eta_s(k)^\top)\right] = \text{Tr}\left(\mathbb{E}\left[\eta_s(k)\eta_s(k)^\top\right]\right) \\
&\leq \sigma_w^2 np\beta^2 \leq \zeta_b^2 \quad \forall k \in \mathbb{Z}_{\geq 0}.
\end{aligned} \quad (92)$$

Similarly, one can rewrite Eq. (27) as

$$\hat{\zeta}_s(t+1) = (\hat{A}_{ss} + \hat{B}_{ss}\hat{K}_s)\hat{\zeta}_s(t) + \hat{\eta}_s(t), \quad (93)$$

where

$$\hat{\eta}_s(t) = \sum_{v \in \mathcal{L}_s} \hat{H}(v, s) \sum_{w_j \rightarrow v} I_{v, \{j\}} \hat{w}_j(t - l_{vs}), \quad (94)$$

where

$$\hat{H}(v, s) = (\hat{A}_{sr_1} + \hat{B}_{sr_1}\hat{K}_{r_1}) \cdots (\hat{A}_{r_{l_{vs}-1}v} + \hat{B}_{r_{l_{vs}-1}v}\hat{K}_v),$$

with $\hat{H}(v, s) = I$ if $v = s$. Note that for any $v \in \mathcal{L}_s$ and for any $w_j \rightarrow v$ in Eqs. (91) and (94), we set $\hat{w}_j(k - l_{vs}) = w_j(k - l_{vs}) = 0$ if $k < l_{vs}$. One can check that $\bar{\varepsilon}$ satisfies (43) and (46). We then have from

Lemmas 7-8 that $\|\hat{K}_r\| \leq \Gamma + 1 = \tilde{\Gamma}$ for all $r \in \mathcal{U}$. It follows that $\|\hat{A}_{sr} + \hat{B}_{sr}\hat{K}_r\| \leq (\tilde{\Gamma} + 1)^2$ for all $r \in \mathcal{U}$ with $r \neq s$. Noting from the construction of $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ in (7) that $l_{vs} \leq D_{\max} \leq p$ for all $v \in \mathcal{L}_s$, one can now show that

$$\|H(v, s) - \hat{H}(v, s)\| \leq \delta_h \bar{\varepsilon}. \quad (95)$$

which also implies that

$$\|\hat{H}(v, s)\| \leq \delta_h \bar{\varepsilon} + \beta, \quad (96)$$

for all $v \in \mathcal{L}_s$. For any $k \in \{0, \dots, t\}$, we then have from the above arguments that

$$\begin{aligned} & \sqrt{\mathbb{E} \left[\|\eta_s(k) - \hat{\eta}_s(k)\|^2 \right]} \\ &= \left(\mathbb{E} \left[\left\| \sum_{v \in \mathcal{L}_s} \sum_{w_j \rightarrow v} (H(v, s) I_{v, \{j\}} w_j(k - l_{vs}) - \hat{H}(v, s) I_{v, \{j\}} \hat{w}_j(k - l_{vs})) \right\|^2 \right] \right)^{\frac{1}{2}} \\ &\leq \sum_{v \in \mathcal{L}_s} \sum_{w_j \rightarrow v} \left(\sqrt{\mathbb{E} \left[\|(H(v, s) - \hat{H}(v, s)) w_j(k - l_{vs})\|^2 \right]} + \sqrt{\mathbb{E} \left[\|\hat{H}(v, s) (w_j(k - l_{vs}) - \hat{w}_j(k - l_{vs}))\|^2 \right]} \right) \\ &\leq p(\delta_h \zeta_b \bar{\varepsilon} + (\delta_h \bar{\varepsilon} + \beta) \delta_w \bar{\varepsilon}), \end{aligned} \quad (97)$$

where the first inequality follows from Lemma 14. To obtain (97), we first note (88)-(89) and (95)-(96). We then use the fact that $|\mathcal{L}_s| \leq p$ from the definition of the information graph $\hat{\mathcal{G}}(\mathcal{U}, \mathcal{H})$ given by (7), and the fact that for any $v \in \mathcal{U}$ with $s_j(0) = v$, w_j is the only noise term such that $w_j \rightarrow v$ (see Footnote 2). From (92) and (97), we also obtain

$$\begin{aligned} \sqrt{\mathbb{E} \left[\|\hat{\eta}_s(k)\|^2 \right]} &= \sqrt{\mathbb{E} \left[\|\hat{\eta}_s(k) - \eta_s(k) + \eta_s(k)\|^2 \right]} \\ &\leq \sqrt{\mathbb{E} \left[\|\hat{\eta}_s(k) - \eta_s(k)\|^2 \right]} + \sqrt{\mathbb{E} \left[\|\eta_s(k)\|^2 \right]} \\ &\leq p(\delta_h \zeta_b \bar{\varepsilon} + (\delta_h \bar{\varepsilon} + \beta) \delta_w \bar{\varepsilon}) + \zeta_b, \end{aligned} \quad (98)$$

where the first inequality follows from Lemma 14.

Now, let us denote $\tilde{L}_{ss} = A_{ss} + B_{ss}\hat{K}_s$ and $\hat{L}_{ss} = \hat{A}_{ss} + \hat{B}_{ss}\hat{K}_s$. Recalling that $\hat{\zeta}_s(0) = \tilde{\zeta}_s(0) = \sum_{w_i \rightarrow s} I_{s, \{i\}} x_i(0)$, where $x(0) = 0$ as we assumed before, one can unroll Eqs. (90) and (93), and show that

$$\hat{\zeta}_s(t+1) - \tilde{\zeta}_s(t+1) = \sum_{k=0}^t (\hat{L}_{ss}^{t-k} \hat{\eta}_s(k) - \tilde{L}_{ss}^{t-k} \tilde{\eta}_s(k)). \quad (99)$$

Since $\|\hat{A} - A\| \leq \bar{\varepsilon}$ and $\|\hat{B} - B\| \leq \bar{\varepsilon}$, where $\bar{\varepsilon}$ satisfies (43), as we argued above, we have from Lemma 7 that

$$\|\tilde{L}_{ss}^k\| \leq \kappa \left(\frac{\gamma + 1}{2} \right)^k \quad \forall k \in \mathbb{Z}_{\geq 0}, \quad (100)$$

where $\kappa \in \mathbb{R}_{\geq 1}$ and $\gamma \in \mathbb{R}$, with $0 < \gamma < 1$. Moreover, since $\|\hat{L}_{ss} - \tilde{L}_{ss}\| = \|\hat{A}_{ss} - A_{ss} + \hat{K}_s(\hat{B}_{ss} - B_{ss})\| \leq (\tilde{\Gamma} + 1)\bar{\varepsilon}$, we have from Lemma 15 that

$$\begin{aligned} \|\hat{L}_{ss}^k - \tilde{L}_{ss}^k\| &\leq k\kappa^2 \left(\kappa(\tilde{\Gamma} + 1)\bar{\varepsilon} + \frac{\gamma + 1}{2} \right)^{k-1} (\tilde{\Gamma} + 1)\bar{\varepsilon} \\ &\leq k\kappa^2 \left(\frac{\gamma + 3}{4} \right)^{k-1} (\tilde{\Gamma} + 1)\bar{\varepsilon} \quad \forall k \in \mathbb{Z}_{\geq 0}, \end{aligned} \quad (101)$$

where (101) follows from the choice of $\bar{\varepsilon}$ in (53). Now, considering any term in the summation on the

right-hand side of (99), we have

$$\begin{aligned}
& \sqrt{\mathbb{E} \left[\|\hat{L}_{ss}^{t-k} \hat{\eta}_s(k) - \tilde{L}_{ss}^{t-k} \tilde{\eta}_s(k)\|^2 \right]} \\
& \leq \sqrt{\mathbb{E} \left[\|\hat{L}_{ss}^{t-k} - \tilde{L}_{ss}^{t-k}\| \|\hat{\eta}_s(k)\|^2 \right]} + \sqrt{\mathbb{E} \left[\|\tilde{L}_{ss}^{t-k}(\hat{\eta}_s(k) - \eta_s(k))\|^2 \right]} \\
& \leq (t-k) \kappa^2 \left(\frac{\gamma+3}{4} \right)^{t-k-1} (\tilde{\Gamma}+1) \bar{\varepsilon} (p(\delta_w \delta_h \bar{\varepsilon} + \delta_h \zeta_b + \delta_w \beta) \bar{\varepsilon} + \zeta_b) + \kappa \left(\frac{\gamma+1}{2} \right)^{t-k} p(\delta_w \delta_h \bar{\varepsilon} + \delta_h \zeta_b + \delta_w \beta) \bar{\varepsilon} \\
& \leq (t-k) \kappa^2 \left(\frac{\gamma+3}{4} \right)^{t-k-1} (\tilde{\Gamma}+1) p(2\delta_w + 2\zeta_b) \bar{\varepsilon} + \kappa \left(\frac{\gamma+1}{2} \right)^{t-k} p((\beta+1)\delta_w + \delta_h \zeta_b) \bar{\varepsilon}, \tag{102}
\end{aligned}$$

where the first inequality follows from Lemma 14, and the second inequality uses the upper bounds provided in (97)-(98) and (100)-(101). Moreover, one can show that $\bar{\varepsilon}$ defined in (53) satisfies that $\delta_h \bar{\varepsilon} \leq 1$ and $\beta \bar{\varepsilon} \leq 1$, which, via algebraic manipulations, yield (102). We then see from (99) that

$$\begin{aligned}
& \sqrt{\mathbb{E} \left[\|\hat{\zeta}_s(t+1) - \tilde{\zeta}_s(t+1)\|^2 \right]} \\
& \leq \sum_{k=0}^t \sqrt{\mathbb{E} \left[\|\hat{L}_{ss}^{t-k} \hat{\eta}_s(k) - \tilde{L}_{ss}^{t-k} \tilde{\eta}_s(k)\|^2 \right]} \\
& \leq \left(\kappa p((\beta+1)\delta_w + \delta_h \zeta_b) \bar{\varepsilon} \sum_{k=0}^t \left(\frac{\gamma+1}{2} \right)^{t-k} \right) + \kappa^2 (\tilde{\Gamma}+1) p(2\delta_w + 2\zeta_b) \bar{\varepsilon} \sum_{k=0}^t (t-k) \left(\frac{\gamma+3}{4} \right)^{t-k-1} \\
& \leq \frac{2\kappa p}{1-\gamma} ((\beta+1)\delta_w + \delta_h \zeta_b) \bar{\varepsilon} + \frac{16\kappa^2 (\tilde{\Gamma}+1) p}{(1-\gamma)^2} (2\delta_w + 2\zeta_b) \bar{\varepsilon}, \tag{103}
\end{aligned}$$

where the first inequality follows from Lemma 14, and (103) follows from standard formulas for series. Now, substituting Eq. (87) into the right-hand side of (103), one can show that

$$\sqrt{\mathbb{E} \left[\|\hat{\zeta}_s(t+1) - \tilde{\zeta}_s(t+1)\|^2 \right]} \leq \frac{1}{q\tilde{\Gamma}} (\Lambda_1(1.1\Lambda_2\bar{\varepsilon}) + \Lambda_2) \bar{\varepsilon}, \tag{104}$$

where we note that $\Lambda_1 > 0$ and $\Lambda_2 > 0$ by their definitions.

Next, considering any $s \in \mathcal{U}$ that does not have a self loop, we have from the arguments in the proof of Lemma 9 that Eq. (34) can be rewritten as $\tilde{\zeta}_s(t+1) = \eta_s(t)$, where $\eta_s(t)$ is defined in Eq. (91). Similarly, Eq. (27) can be rewritten as $\hat{\zeta}_s(t+1) = \hat{\eta}_s(t)$, where $\hat{\eta}_s(t)$ is defined in Eq. (94). Using similar arguments to those above, one can then show that (104) also holds.

Further recalling Eqs. (22) and (33), we know that $\hat{u}(t+1) = \sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \hat{K}_s \hat{\zeta}(t+1)$ and $\tilde{u}(t+1) = \sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \tilde{K}_s \tilde{\zeta}(t+1)$, which imply that

$$\begin{aligned}
\sqrt{\mathbb{E} \left[\|\hat{u}(t+1) - \tilde{u}(t+1)\|^2 \right]} &= \sqrt{\mathbb{E} \left[\left\| \sum_{s \in \mathcal{U}} I_{\mathcal{V},s} \hat{K}_s (\hat{\zeta}_s(t+1) - \tilde{\zeta}_s(t+1)) \right\|^2 \right]} \\
&\leq \sum_{s \in \mathcal{U}} \sqrt{\mathbb{E} \left[\left\| I_{\mathcal{V},s} \hat{K}_s (\hat{\zeta}_s(t+1) - \tilde{\zeta}_s(t+1)) \right\|^2 \right]} \\
&\leq \tilde{\Gamma} \sum_{s \in \mathcal{U}} \sqrt{\mathbb{E} \left[\|\hat{\zeta}_s(t+1) - \tilde{\zeta}_s(t+1)\|^2 \right]} \\
&\leq (\Lambda_1(1.1\Lambda_2\bar{\varepsilon}) + \Lambda_2) \bar{\varepsilon},
\end{aligned}$$

where the first inequality follows from Lemma 14, the second inequality follows from $\|\hat{K}_s\| \leq \tilde{\Gamma}$ for all $s \in \mathcal{U}$, as we argued above, and the last inequality follows from (104) and the fact that $|\mathcal{U}| = q$. Moreover, we can

show that

$$\begin{aligned}\Lambda_1 &\leq q\tilde{\Gamma} \frac{34\kappa^2 p}{(1-\gamma)^2} (\tilde{\Gamma}+1)(\beta+1) \frac{\tilde{\Gamma}\kappa}{1-\gamma} \\ &\leq \frac{34\kappa^2 pq}{(1-\gamma)^3} (\tilde{\Gamma}+1) \tilde{\Gamma}^{2D_{\max}+3},\end{aligned}$$

where the first inequality follows from the fact that $\frac{\kappa}{1-\gamma} > 1$, and the second inequality follows from the fact that $\beta+1 \leq \tilde{\Gamma}^{2D_{\max}+1}$ as we argued above. One can then show that $\bar{\varepsilon}$ given in (53) satisfies that $0 < \bar{\varepsilon} \leq \frac{1}{11\Lambda_1}$, which implies that $0 < \bar{\varepsilon} < \frac{1}{11\Lambda_1}$. Thus, we obtain the following:

$$\begin{aligned}1.1\Lambda_1\bar{\varepsilon} + 1 &\leq 1.1 \\ \Leftrightarrow 1.1\Lambda_1\Lambda_2\bar{\varepsilon} + \Lambda_2 &\leq 1.1\Lambda_2 \\ \Leftrightarrow \Lambda_1(1.1\Lambda_2\bar{\varepsilon})\bar{\varepsilon} + \Lambda_2\bar{\varepsilon} &\leq 1.1\Lambda_2\bar{\varepsilon}.\end{aligned}$$

It follows that

$$\sqrt{\mathbb{E}\left[\|\hat{u}(t+1) - \tilde{u}(t+1)\|^2\right]} \leq 1.1\Lambda_2\bar{\varepsilon},$$

which completes the induction step, i.e., we have shown that $\sqrt{\mathbb{E}\left[\|\hat{u}(k) - \tilde{u}(k)\|^2\right]} \leq 1.1\Lambda_2\bar{\varepsilon}$ holds for all $k \in \{0, \dots, t+1\}$.

Next, using similar arguments to those for (86), we have $\sqrt{\mathbb{E}\left[\|\hat{x}(t) - \tilde{x}(t)\|^2\right]} \leq \frac{1.1\Gamma\Lambda_2\kappa}{1-\gamma}\bar{\varepsilon}$ for all $t \in \mathbb{Z}_{\geq 0}$. It then follows from (85) that (55) holds for all $t \in \mathbb{Z}_{\geq 0}$. \blacksquare

D.5 Proof of Proposition 4

For notational simplicity in this proof, we denote

$$\Lambda = \frac{58\kappa^2(\tilde{\Gamma}+1)^{2D_{\max}+3}p^2q^2}{(1-\gamma)^2}. \quad (105)$$

For all $t \in \mathbb{Z}_{\geq 0}$, we then see from Lemma 11 that

$$\mathbb{E}\left[\|\hat{u}(t) - \tilde{u}(t)\|^2\right] \leq (\Lambda\zeta_b\bar{\varepsilon})^2,$$

and

$$\mathbb{E}\left[\|\hat{x}(t) - \tilde{x}(t)\|^2\right] \leq \left(\frac{\kappa\Gamma}{1-\gamma}\Lambda\zeta_b\bar{\varepsilon}\right)^2,$$

where $\hat{u}(k)$ (resp., $\tilde{u}(k)$) is given by Eq. (22) (resp., Eq. (33)), $\hat{x}(k)$ (resp., $\tilde{x}(k)$) is given by Eq. (31) (resp., Eq. (35)), and ζ_b is defined in Eq. (53). Similarly, we see from Corollary 1 that

$$\mathbb{E}\left[\|\hat{x}(t)\|^2\right] \leq \left(\frac{\kappa\Gamma}{1-\gamma}\Lambda\zeta_b\bar{\varepsilon} + q\zeta_b\right)^2,$$

and

$$\mathbb{E}\left[\|\hat{u}(t)\|^2\right] \leq (\Lambda\zeta_b\bar{\varepsilon} + q\tilde{\Gamma}\zeta_b)^2,$$

for all $t \in \mathbb{Z}_{\geq 0}$.

To proceed, we have the following:

$$\begin{aligned}\hat{J} - \tilde{J} &= \limsup_{T \rightarrow \infty} \mathbb{E}\left[\frac{1}{T} \sum_{t=0}^{T-1} (\hat{x}(t)^\top Q \hat{x}(t) + \hat{u}(t)^\top R \hat{u}(t))\right] - \lim_{T \rightarrow \infty} \mathbb{E}\left[\frac{1}{T} \sum_{t=0}^{T-1} (\tilde{x}(t)^\top Q \tilde{x}(t) + \tilde{u}(t)^\top R \tilde{u}(t))\right] \\ &= \limsup_{T \rightarrow \infty} \mathbb{E}\left[\frac{1}{T} \sum_{t=0}^{T-1} (\hat{x}(t)^\top Q \hat{x}(t) - \tilde{x}(t)^\top Q \tilde{x}(t) + \hat{u}(t)^\top R \hat{u}(t) - \tilde{u}(t)^\top R \tilde{u}(t))\right].\end{aligned} \quad (106)$$

Now, considering any term in the summation on the right-hand side of Eq. (106), and dropping the dependency on t for notational simplicity, we have the following:

$$\begin{aligned}
& \mathbb{E} \left[\hat{x}^\top Q \hat{x} - \tilde{x}^\top Q \tilde{x} \right] \\
&= \mathbb{E} \left[\hat{x}^\top Q (\hat{x} - \tilde{x}) + (\hat{x} - \tilde{x})^\top Q \tilde{x} \right] \\
&\leq \mathbb{E} \left[\|Q \hat{x}\| \|\hat{x} - \tilde{x}\| \right] + \mathbb{E} \left[\|\hat{x} - \tilde{x}\| \|Q \tilde{x}\| \right] \\
&\leq \sqrt{\mathbb{E} \left[\|Q \hat{x}\|^2 \right] \mathbb{E} \left[\|\hat{x} - \tilde{x}\|^2 \right]} + \sqrt{\mathbb{E} \left[\|\hat{x} - \tilde{x}\|^2 \right] \mathbb{E} \left[\|Q \tilde{x}\|^2 \right]} \\
&\leq \sigma_1(Q) \left(\frac{\kappa \Gamma \Lambda \zeta_b}{1-\gamma} \bar{\varepsilon} + q \zeta_b \right) \frac{\kappa \Gamma \Lambda \zeta_b}{1-\gamma} \bar{\varepsilon} + \sigma_1(Q) \frac{\kappa \Gamma \Lambda \zeta_b}{1-\gamma} \bar{\varepsilon} q \zeta_b \\
&= \sigma_1(Q) \left(\frac{\kappa \Gamma \Lambda \zeta_b}{1-\gamma} \bar{\varepsilon} + 2q \zeta_b \right) \frac{\kappa \Gamma \Lambda \zeta_b}{1-\gamma} \bar{\varepsilon}, \tag{107}
\end{aligned}$$

where the first two inequalities follow from the Cauchy-Schwartz inequality, and the third inequality follows from the upper bounds on $\mathbb{E}[\|\hat{x}\|^2]$, $\mathbb{E}[\|\hat{x} - \tilde{x}\|^2]$, and $\mathbb{E}[\|\tilde{x}\|^2]$ given above and in Lemma 10. Similarly, we have

$$\begin{aligned}
& \mathbb{E} \left[\hat{u}^\top R \hat{u} - \tilde{u}^\top R \tilde{u} \right] \\
&\leq \sqrt{\mathbb{E} \left[\|R \hat{u}\|^2 \right] \mathbb{E} \left[\|\hat{u} - \tilde{u}\|^2 \right]} + \sqrt{\mathbb{E} \left[\|\hat{u} - \tilde{u}\|^2 \right] \mathbb{E} \left[\|R \tilde{u}\|^2 \right]} \\
&\leq \sigma_1(R) (\Lambda \zeta_b \bar{\varepsilon} + q \tilde{\Gamma} \zeta_b) \Lambda \zeta_b \bar{\varepsilon} + \sigma_1(R) \Lambda \zeta_b \bar{\varepsilon} q \tilde{\Gamma} \zeta_b \\
&= \sigma_1(R) (\Lambda \zeta_b \bar{\varepsilon} + 2q \tilde{\Gamma} \zeta_b) \Lambda \zeta_b \bar{\varepsilon}, \tag{108}
\end{aligned}$$

where the second inequality follows from the upper bounds on $\mathbb{E}[\|\hat{u}\|^2]$, $\mathbb{E}[\|\hat{u} - \tilde{u}\|^2]$, and $\mathbb{E}[\|\tilde{u}\|^2]$ given above and in Lemma 10. Combining (107) and (108) together, we obtain from Eq. (106) that

$$\begin{aligned}
\hat{J} - \tilde{J} &\leq \sigma_1(Q) \left(\frac{\kappa \Gamma \Lambda \zeta_b}{1-\gamma} \bar{\varepsilon} + 2q \zeta_b \right) \frac{\kappa \Gamma \Lambda \zeta_b}{1-\gamma} \bar{\varepsilon} + \sigma_1(R) (\Lambda \zeta_b \bar{\varepsilon} + 2q \tilde{\Gamma} \zeta_b) \Lambda \zeta_b \bar{\varepsilon} \\
&\leq \left(\frac{\kappa \tilde{\Gamma} \zeta_b}{1-\gamma} \right)^2 (\Lambda^2 \bar{\varepsilon} + 2q \Lambda) (\sigma_1(Q) + \sigma_1(R)) \bar{\varepsilon} \\
&\leq \left(\frac{\kappa \tilde{\Gamma} \zeta_b}{1-\gamma} \right)^2 3 \Lambda p q (\sigma_1(Q) + \sigma_1(R)) \bar{\varepsilon}, \tag{109}
\end{aligned}$$

where the second inequality follows from the fact that $\frac{\kappa \tilde{\Gamma}}{1-\gamma} \geq 1$. To obtain (109), one can show that $\Lambda^2 \bar{\varepsilon} \leq \Lambda p q$. Finally substituting the expressions for ζ_b and Λ given in (53) and (105), respectively, we obtain from (109) that (58) holds. \blacksquare

E Auxiliary Lemmas

Lemma 12. [9, Lemma 34] *Let $w(t) \in \mathbb{R}^n$ be a Gaussian random vector with distribution $\mathcal{N}(0, \sigma_w^2 I)$, for all $t \in \{0, \dots, N-1\}$, where $\sigma_w \in \mathbb{R}_{\geq 0}$. Then for any $N \geq 2$ and for any $\delta_w > 0$, the following holds with probability at least $1 - \delta_w$:*

$$\max_{0 \leq t \leq N-1} \|w(t)\| \leq \sigma \sqrt{5n \log \frac{N}{\delta_w}}.$$

Lemma 13. [9, Lemma 36] *Let $\{z(t)\}_{t \geq 0}$ be a sequence of random vectors that is adapted to a filtration $\{\mathcal{F}_t\}_{t \geq 0}$, where $z(t) \in \mathbb{R}^d$ for all $t \in \mathbb{Z}_{\geq 0}$. Suppose $z(t)$ is conditionally Gaussian on \mathcal{F}_{t-1} with $\mathbb{E}[z(t)z(t)^\top | \mathcal{F}_{t-1}] \geq \sigma_z^2 I$, for all $t \in \mathbb{Z}_{\geq 1}$, where $\sigma_z \in \mathbb{R}_{> 0}$. Then, for any $\delta_z \in \mathbb{R}_{> 0}$ and for any $t \geq 200d \log \frac{12}{\delta_z}$, the following holds with probability at least $1 - \delta_z$:*

$$\sum_{k=0}^{t-1} z(k)z(k)^\top \succeq \frac{(t-1)\sigma_z^2}{40} I.$$

Lemma 14. Let X_1, \dots, X_t be a sequence of random vectors, where $t \in \mathbb{Z}_{\geq 1}$. Then,

$$\mathbb{E}\left[\left(\sum_{k=1}^t X_k\right)^\top \left(\sum_{k=1}^t X_k\right)\right] \leq \left(\sum_{k=1}^t \sqrt{\mathbb{E}\left[\|X_k\|^2\right]}\right)^2.$$

Proof. We have the following:

$$\begin{aligned} \mathbb{E}\left[\left(\sum_{k=1}^t X_k\right)^\top \left(\sum_{k=1}^t X_k\right)\right] &= \sum_{k=1}^t \mathbb{E}\left[\|X_k\|^2\right] + 2 \sum_{k_1=1}^t \sum_{\substack{k_2=1 \\ k_2 \neq k_1}}^t \mathbb{E}\left[X_{k_1}^\top X_{k_2}\right] \\ &\leq \sum_{k=1}^t \mathbb{E}\left[\|X_k\|^2\right] + 2 \sum_{k_1=1}^t \sum_{\substack{k_2=1 \\ k_2 \neq k_1}}^t \mathbb{E}\left[\|X_{k_1}\| \|X_{k_2}\|\right] \\ &\leq \sum_{k=1}^t \mathbb{E}\left[\|X_k\|^2\right] + 2 \sum_{k_1=1}^t \sum_{\substack{k_2=1 \\ k_2 \neq k_1}}^t \sqrt{\mathbb{E}\left[\|X_{k_1}\|^2\right]} \sqrt{\mathbb{E}\left[\|X_{k_2}\|^2\right]} \\ &= \left(\sum_{k=1}^t \sqrt{\mathbb{E}\left[\|X_k\|^2\right]}\right)^2, \end{aligned}$$

where the first and second inequalities follow from the Cauchy-Schwarz inequality. ■

Lemma 15. [29, Lemma 5] Consider any matrix $M \in \mathbb{R}^{n \times n}$ and any matrix $\Delta \in \mathbb{R}^{n \times n}$. Let $\kappa_M \in \mathbb{R}_{\geq 1}$ and $\gamma_M \in \mathbb{R}_{>0}$ be such that $\gamma_M > \rho(M)$, and $\|M^k\| \leq \kappa_M \gamma_M^k$ for all $k \in \mathbb{Z}_{\geq 0}$. Then, for all $k \in \mathbb{Z}_{\geq 0}$,

$$\|(M + \Delta)^k - M^k\| \leq k \kappa_M^2 (\kappa_M \|\Delta\| + \gamma_M)^{k-1} \|\Delta\|.$$