

# Quantum Regularized Least Squares

Shantanav Chakraborty\*

Aditya Morolia<sup>†</sup>

Anurudh Peduri<sup>‡</sup>

July 4, 2022

## Abstract

Linear regression is a widely used technique to fit linear models and finds widespread applications across different areas such as machine learning and statistics. In most real-world scenarios, however, linear regression problems are often *ill-posed* or the underlying model suffers from *overfitting*, leading to erroneous or trivial solutions. This is often dealt with by adding extra constraints, known as regularization. In this paper, we use the frameworks of block-encoding and quantum singular value transformation (QSVT) to design the first quantum algorithms for quantum least squares with general  $\ell_2$ -regularization. These include regularized versions of quantum ordinary least squares, quantum weighted least squares, and quantum generalized least squares. Our quantum algorithms substantially improve upon prior results on *quantum ridge regression* (polynomial improvement in the condition number and an exponential improvement in accuracy), which is a particular case of our result.

To this end, we assume approximate block-encodings of the underlying matrices as input and use robust QSVT algorithms for various linear algebra operations. In particular, we develop a variable-time quantum algorithm for matrix inversion using QSVT, where we use quantum eigenvalue discrimination as a subroutine instead of gapped phase estimation. This ensures that substantially fewer ancilla qubits are required for this procedure than prior results. Owing to the generality of the block-encoding framework, our algorithms are applicable to a variety of input models and can also be seen as improved and generalized versions of prior results on standard (non-regularized) quantum least squares algorithms.

---

\*CSTAR and CQST, IIIT Hyderabad, Telangana - 500032 (India). [shchakra@iiit.ac.in](mailto:shchakra@iiit.ac.in)

<sup>†</sup>CCNSB and CQST, IIIT Hyderabad, Telangana - 500032 (India). [aditya.morolia@research.iiit.ac.in](mailto:aditya.morolia@research.iiit.ac.in)

<sup>‡</sup>CSTAR, IIIT Hyderabad, Telangana - 500032 (India). [anurudh.peduri@research.iiit.ac.in](mailto:anurudh.peduri@research.iiit.ac.in)

# Contents

<b>1</b>	<b>Introduction</b>	<b>3</b>
1.1	Linear regression with $\ell_2$ -regularization . . . . .	4
1.2	Prior work . . . . .	5
1.3	Our contributions . . . . .	6
<b>2</b>	<b>Preliminaries</b>	<b>8</b>
2.1	Notation . . . . .	8
2.2	Quantum Input Models . . . . .	9
2.2.1	Quantum Data Structure Input Model . . . . .	10
2.2.2	Sparse Access Input Model . . . . .	11
2.3	Quantum Singular Value Transformation . . . . .	12
2.4	Variable Time Amplitude Amplification . . . . .	13
<b>3</b>	<b>Algorithmic Primitives</b>	<b>14</b>
3.1	Arithmetic with Block-Encoded Matrices . . . . .	16
3.2	Robust Quantum Eigenvalue Discrimination . . . . .	18
3.3	Variable-Time Quantum Algorithm for Matrix Inversion using QSVT . . . . .	21
3.4	Positive and Negative Powers of Matrices using QSVT . . . . .	25
<b>4</b>	<b>Quantum Least Squares with General <math>\ell_2</math>-Regularization</b>	<b>28</b>
4.1	Quantum Ordinary Least Squares . . . . .	28
4.2	Quantum Weighted And Generalized Least Squares . . . . .	33
4.2.1	Quantum Extended Least Squares . . . . .	34
4.2.2	Quantum Weighted Least Squares . . . . .	37
4.2.3	Quantum Generalized Least Squares . . . . .	39
4.2.4	Improved Quantum Weighted Least Squares Algorithms . . . . .	42
<b>5</b>	<b>Future Directions</b>	<b>45</b>
<b>A</b>	<b>Algorithmic Primitives</b>	<b>48</b>
A.1	Arithmetic with Block-Encoded Matrices . . . . .	50

# 1 Introduction

The problem of fitting a theoretical model to a large set of experimental data appears across various fields ranging from the natural sciences to machine learning and statistics [Mur12]. Linear regression is one of the most widely used procedures for achieving this. By assuming that, for the underlying model, there exists a linear relationship between a dependent variable and one or more explanatory variables, linear regression constructs the best linear fit to the series of data points. Usually, it does so while minimizing the sum of squared errors - known as the least squares method.

In other words, suppose that we are given  $N$  data points  $\{(a_i, b_i)\}_{i=1}^N$  where  $\forall i : a_i \in \mathbb{R}^d, \forall i : b_i \in \mathbb{R}$ . The assumption is that each  $b_i$  is linearly dependent on  $a_i$  up to some random noise of mean 0. Suppose  $A$  is the data matrix of dimension  $N \times d$ , such that its  $i^{\text{th}}$  row is the vector  $a_i$  and  $b \in \mathbb{R}^N$  such that  $b = (b_1, \dots, b_N)^T$ . Then the procedure, known as ordinary least squares, obtains a vector  $x \in \mathbb{R}^d$  that minimizes the objective function  $\|Ax - b\|_2^2$ . This problem has a closed-form solution given by  $x = (A^T A)^{-1} A^T b = A^+ b$ , where  $A^+$  denotes the Moore-Penrose inverse of the matrix  $A$ . Thus computationally, finding the best fit by linear regression reduces to finding the pseudoinverse of a matrix that represents the data, a task that is expensive for classical machines for large data sets.

In practice, however, least squares regression runs into problems such as *overfitting*. For instance, the solution might fit most data points, even those corresponding to random noise. Furthermore, the linear regression problem may also be *ill-posed*, for instance, when the number of variables exceeds the number of data points rendering it impossible to fit the data. These issues come up frequently with linear regression models and result in erroneous or trivial solutions. Furthermore, another frequent occurrence is that the data matrix  $A$  has linearly dependent columns. In this scenario, the matrix  $A^T A$  is not full rank and therefore is not invertible.

Regularization is a widely used technique to remedy these problems, not just for linear regression but for inverse problems in general [EHN96]. In the context of linear regression, broadly, this involves adding a penalty term to the objective function, which constrains the solution of the regression problem. For instance, in the case of  $\ell_2$ -regularization, the objective is to obtain  $x$  that minimizes

$$\|Ax - b\|_2^2 + \lambda \|Lx\|_2^2 \quad (1)$$

where  $L$  is an appropriately chosen penalty matrix (or regularization matrix) of dimension  $N \times d$  and  $\lambda > 0$  is the regularization parameter, an appropriately chosen constant. This regularization technique is known as *general  $\ell_2$ -regularization* or *Tikhonov regularization* in the literature [Hem75, HH93, Bis95, GHO99, vW15]. It is a generalization of *ridge regression* which corresponds to the case when  $L$  is the identity matrix [HK00, Mar70, Vin78]. The closed-form solution of the general  $\ell_2$ -regularized ordinary least squares problem is given by

$$x = (A^T A + \lambda L^T L)^{-1} A^T b. \quad (2)$$

A straightforward observation is that even when  $A^T A$  is singular, regularization ensures that the condition number (ratio of the maximum and the minimum singular values) of the resulting matrix is finite and therefore  $A^T A + \lambda L^T L$  is invertible.

In this paper, we develop quantum algorithms for linear regression with general  $\ell_2$ -regularization. If the optimal solution is  $x = (x_1, \dots, x_d)^T$ , then our quantum algorithm outputs a quantum state that is  $\delta$ -close to  $|x\rangle = \sum_{j=1}^d x_j |j\rangle / \|x\|$ , assuming access to the matrices  $A, L$ , and the quantum state  $|b\rangle$  via general quantum input models.

In several practical scenarios, depending on the underlying theoretical model, generalizations of the ordinary least squares (OLS) technique are more useful to fit the data. For instance, certain samples may be of more importance (and therefore have more weight) than the others, in which case weighted least squares (WLS) is preferred. Generalized least squares (GLS) is used when the underlying samples obtained are correlated. These techniques also suffer from the issues commonplace with OLS, warranting the need for regularization [vW15]. Consequently, we also design algorithms for quantum WLS with general  $\ell_2$ -regularization and quantum GLS with general  $\ell_2$ -regularization.

**Organization of the paper:** In the remainder of [Section 1](#), we formally describe  $\ell_2$ -regularized versions of OLS, WLS, and GLS ([Section 1.1](#)), discuss prior and related work ([Section 1.2](#)), and outline our contributions and results ([Section 1.3](#)). In [Section 2](#), we briefly outline the framework of block-encoding and quantum input models that are particular instances of it ([Section 2.2](#)). We also briefly introduce quantum singular value transformation (QSVT) ([Section 2.3](#)) and variable time amplitude amplification (VTAA) ([Section 2.4](#)). Following this, in [Section 3](#), we develop several algorithmic primitives involving arithmetic of block-encodings ([Section 3.1](#)), quantum eigenvalue discrimination ([Section 3.2](#)) and quantum linear algebra using QSVT ([Section 3.3](#)). These are the technical building blocks for designing our quantum regularized regression algorithms. Using these algorithmic primitives, we design quantum algorithms for the quantum least squares with  $\ell_2$ -regularization in [Section 4](#). Finally, we conclude by discussing some possible future directions in [Section 5](#).

## 1.1 Linear regression with $\ell_2$ -regularization

Suppose we are given data points  $\{(a_i, b_i)\}_{i=1}^N$ , where  $\forall i : a_i \in \mathbb{R}^d, \forall i : b_i \in \mathbb{R}$  such that  $(a_i, b_i) \sim_{i.i.d} \mathcal{D}$ , i.e. they are sampled i.i.d. from some unknown distribution  $\mathcal{D}$ , assumed to be linear. We want to find a vector  $x \in \mathbb{R}^d$  such that the inner product  $x^T a_j$  is a good predictor for the target  $b_j$  for some unknown  $a_j$ . This can be done by minimizing the total squared loss over the given data points,

$$\mathcal{L}_O := \sum_j (x^T a_j - b_j)^2, \quad (3)$$

leading to the ordinary least squares (OLS) optimization problem. The task then is to find  $x \in \mathbb{R}^d$  that minimizes  $\|Ax - b\|_2^2$ , where  $A$  is the  $N \times d$  data matrix such that the  $i^{\text{th}}$  row of  $A$  is  $a_i$ , and the  $i^{\text{th}}$  element of the vector  $b$  is  $b_i$ . Assuming that  $A^T A$  is non-singular, the optimal  $x$  satisfies

$$x = (A^T A)^{-1} A^T b = A^+ b, \quad (4)$$

which corresponds to solving a linear system of equations.

Suppose that out of the samples present in the data, we have higher confidence in some of them than others. In such a scenario, the  $i^{\text{th}}$  observation can be assigned a weight  $w_i \in \mathbb{R}$ . This leads to a generalization of the OLS problem to *weighted least squares* (WLS). In order to obtain the best linear fit, the task is now to minimize the weighted version of the loss

$$\mathcal{L}_W := \sum_j w_j (x^T a_j - b_j)^2. \quad (5)$$

As before, assuming  $A^T W A$  is non-singular, the above loss function has the following closed-form solution

$$x = (A^T W A)^{-1} A^T W b, \quad (6)$$

where  $W$  is a diagonal matrix with  $w_i$  being the  $i^{\text{th}}$  diagonal element.

There can arise scenarios where there exists some correlation between any two samples. For *generalized least squares* (GLS), the presumed correlations between pairs of samples are given in a symmetric, non-singular covariance matrix  $\Omega$ . This objective is to find the vector  $x$  that minimizes

$$\mathcal{L}_\Omega := \sum_{i,j} (\Omega^{-1})_{i,j} (x^T a_i - b_i)(x^T a_j - b_j). \quad (7)$$

Similarly, the closed form solution for GLS is given by

$$x = (A^T \Omega^{-1} A)^{-1} A^T \Omega^{-1} b. \quad (8)$$

As mentioned previously, in several practical scenarios, the linear regression problem may be *ill-posed* or suffer from *overfitting*. Furthermore, the data may be such that some of the columns of the matrix  $A$  are linearly dependent. This shrinks the rank of  $A$ , and consequently of the matrix  $A^T A$ , rendering it singular and therefore non-invertible. Recall that the closed-form solution of OLS exists only if  $A^T A$  is non-singular, which is no longer the case. Such scenarios arise even for WLS and GLS problems [vW15].

In such cases, one resorts to *regularization* to deal with them. Let  $\mathcal{L}$  be the loss function to be minimized for the underlying least squares problem (such as OLS, WLS, or GLS). Then general  $\ell_2$ -regularization (*Tikhonov regularization*) involves an additional penalty term so that the objective now is to find the vector  $x \in \mathbb{R}^d$  that minimizes

$$\mathcal{L} + \lambda \|Lx\|_2^2. \quad (9)$$

Here  $\lambda$ , known as the regularization parameter, is a positive constant that controls the size of the vector  $x$ , while  $L$  is known as the penalty matrix (or regularization matrix) that defines a (semi)norm on the solution through which the size is measured. The solution to the Tikhonov regularization problem also has a closed-form solution. For example, in the OLS problem, when  $\mathcal{L} = \mathcal{L}_O$ , we have that

$$x = (A^T A + \lambda L^T L)^{-1} A^T b. \quad (10)$$

It is worth noting that when  $L = I$ , the  $\ell_2$ -regularized OLS problem is known as *ridge regression*. For the unregularized OLS problem, the singular values of  $A$ ,  $\sigma_j$  are mapped to  $1/\sigma_j$ . Immediately, one sees that adding the regularization term transforms a singular value  $\sigma_j$  to  $\sigma_j/(\sigma_j^2 + \lambda\gamma_j^2)$ , where  $\gamma_j$  is the singular value of  $L$ . Thus the penalty term due to  $\ell_2$ -regularization, results in a shrinkage of the singular values. This implies that even in the scenario where  $A$  has linearly dependent columns (some  $\sigma_j = 0$ ) and  $(A^T A)^{-1}$  does not exist, the inverse  $(A^T A + \lambda L^T L)^{-1}$  is well defined for  $\lambda > 0$ .

The penalty matrix  $L$  allows for penalizing each regression parameter differently and leads to joint shrinkage among the elements of  $x$ . It also determines the rate and direction of shrinkage. In the special case of ridge regression, as  $L = I$ , the penalty shrinks each element of  $x$  equally along the unit vectors  $e_j$ .

Closed-form expressions can also be obtained for the WLS and the GLS problem ( $\mathcal{L} = \mathcal{L}_W, \mathcal{L}_\Omega$  respectively), and finding the optimal solution  $x$  reduces to solving a linear system. The quantum version of these algorithms output a quantum state that is  $\epsilon$ -close  $|x\rangle = \sum_j x_j |j\rangle / \|x\|$ .

Throughout this work, while designing our quantum algorithms, we shall assume access (via a block-encoding) to the matrices  $A$ ,  $W$ ,  $\Omega$ , and  $L$  and knowledge of the parameter  $\lambda$ . Classically, however, the regularization matrix  $L$  and the optimal parameter  $\lambda$  are obtained via several heuristic techniques [HH93, GHO99, vW15].

## 1.2 Prior work

Quantum algorithms for (unregularized) linear regression was first developed by Wiebe et al. [WBL12], wherein the authors made use of the HHL algorithm for solving a linear system of equations [HHL09]. Their algorithm assumes query access to a sparse matrix  $A$  (*sparse-access-model*) and to a procedure to prepare  $|b\rangle = \sum_i b_i |i\rangle$ . They first prepare a quantum state proportional to  $A^T |b\rangle$ , and then use the HHL algorithm to apply the operator  $(A^T A)^{-1}$  to it. Overall the algorithm runs in a time scaling as  $\kappa_A^6$  (the condition number of  $A$ ) and inverse polynomial in the accuracy  $\delta$ . Subsequent results have considered the problem of obtaining classical outputs for linear regression. For instance, in Ref. [Wan17],  $A^+$  is directly applied to the quantum state  $|b\rangle$ , followed by amplitude estimation to obtain the entries of  $x$ . On the other hand, Ref. [SSP16] used the techniques of quantum principal component analysis in [LMR14] to predict a new data point for the regression problem. These algorithms also work in the *sparse access model* and run in a time that scales as  $\text{poly}(\kappa, 1/\delta)$ . Kerenidis and Prakash [KP20] provided a quantum algorithm for the WLS problem wherein they used a classical data structure to store the entries of  $A$  and  $W$ . Furthermore, they assumed QRAM access to this data structure [Pra14, KP17]

that would allow the preparation of quantum states proportional to the entries of  $A$  and  $W$  efficiently. They showed that in this input model (*quantum data structure model*), an iterative quantum linear systems algorithm can prepare  $|x\rangle$  in time  $\tilde{O}(\mu\kappa^3/\delta)$ , where  $\kappa$  is the condition number of the matrix  $A^T\sqrt{W}$  while  $\mu = \left\|\sqrt{W}A\right\|_F$ . Chakraborty et al. [CGJ19] applied the framework of block-encoding along with (controlled) Hamiltonian simulation of Low and Chuang [LC19] to design improved quantum algorithms for solving linear systems. Quantum algorithms developed in the block-encoding framework are applicable to a wide variety of input models, including the sparse access model and the quantum data structure model of [KP20]. They applied their quantum linear systems solver to develop quantum algorithms for quantum weighted least squares and generalized least squares. Their quantum algorithm for WLS has a complexity that is in  $\tilde{O}(\alpha\kappa\text{polylog}(Nd/\delta))$ , where  $\alpha = s$ , the sparsity of the matrix  $A^T\sqrt{W}$  in the sparse access model while  $\alpha = \left\|\sqrt{W}A\right\|_F$ , for the quantum data structure input model. For GLS, their quantum algorithm outputs  $|x\rangle$  in cost  $\tilde{O}(\kappa_A\kappa_\Omega(\alpha_A + \alpha_\Omega\kappa_\Omega)\text{polylog}(1/\delta))$ , where  $\kappa_A$  and  $\kappa_\Omega$  are the condition numbers of  $A$  and  $\Omega$  respectively while  $\alpha_A$  and  $\alpha_\Omega$  are parameters that depend on how the matrices  $A$  and  $\Omega$  are accessed in the underlying input model.

While quantum linear regression algorithms have been designed and subsequently improved over the years, quantum algorithms for regularized least squares have not been developed extensively. Yu et al. [YGW21] developed a quantum algorithm for *ridge regression* in the sparse access model using the LMR scheme [LMR14] for Hamiltonian simulation and quantum phase estimation, which they then used to determine the optimal value of the parameter  $\lambda$ . Their algorithm to output  $|x\rangle$  has a cubic dependence on both  $\kappa$  and  $1/\delta$ . They use this as a subroutine to determine a good value of  $\lambda$ . A few other works [SX20, CYGL22] have considered the quantum ridge regression problem in the sparse access model, all of which can be implemented with  $\text{poly}(\kappa, 1/\delta)$  cost.

Recently, Chen and de Wolf designed quantum algorithms for lasso ( $\ell_1$ -regularization) and ridge regressions from the perspective of empirical loss minimization [CdW21]. For both lasso and ridge, their quantum algorithms output a classical vector  $\tilde{x}$  whose loss (mean squared error) is  $\delta$ -close to the minimum achievable loss. In this context, they prove a quantum lower bound of  $\Omega(d/\delta)$  for ridge regression which indicates that in their setting, the dependence on  $d$  cannot be improved on a quantum computer (the classical lower bound is also linear in  $d$  and there exists a matching upper bound). Note that  $\tilde{x}$  is not necessarily close to the optimal solution  $x$  of the corresponding least squares problem, even though their respective loss values are. Moreover, their result (of outputting a classical vector  $\tilde{x}$ ) is incomparable to our objective of obtaining a quantum state encoding the optimal solution to the regularized regression problem.

Finally, Gilyén et al. obtained a “dequantized” classical algorithm for ridge regression assuming norm squared access to input data similar to the quantum data structure input model [GST20]. Furthermore, similar to the quantum setting where the output is the quantum state  $|x\rangle = \sum_j x_j |j\rangle / \|x\|$  instead of  $x$  itself, their algorithm obtains samples from the distribution  $x_j^2 / \|x\|^2$ . For the regularization parameter  $\lambda = O(\|A\|\|A\|_F)$ , the running time of their algorithm is in  $\tilde{O}(\kappa^{12}r_A^3/\delta^4)$ , where  $r_A$  is the rank of  $A$ . Their result (and several prior results) does not have a polynomial dependence on the dimension of  $A$  and therefore rules out the possibility of generic exponential quantum speedup (except in  $\delta$ ) in the quantum data structure input model.

### 1.3 Our contributions

In this work, we design the first quantum algorithms for OLS, WLS, and GLS with general  $\ell_2$ -regularization. We assume that the relevant matrices are provided as input in the *block-encoding* model and use the Quantum Singular Value Transformation (QSVT) framework introduced by Gilyén et al [GSLW19]. The block-encoding model assumes that an operator (close to)  $A/\alpha$  is encoded in the top-left block of some unitary  $U_A$ . The parameter  $\alpha$  takes specific values depending on the underlying input model. On the other hand, QSVT allows us to implement nearly arbitrary polynomial transformations to a block of a unitary matrix using a series of parameterized, projector-controlled rotations

(quantum signal processing [LC17b]). Our results utilize both these frameworks.

More precisely, given approximate block-encodings of the data matrix  $A$  and the regularizing matrix  $L$ , and a unitary procedure to prepare the state  $|b\rangle$ , our quantum algorithms output a quantum state that is  $\delta$ -close to  $|x\rangle$ , the quantum state proportional to the  $\ell_2$ -regularized ordinary least squares (or weighted least squares or generalized least squares problem). We briefly summarize the query complexities of our results in Table 1.

For the OLS problem with general  $\ell_2$ -regularization (Section 4.2, Theorem 35), we design a quantum algorithm which given an  $(\alpha_A, a_A, \varepsilon_A)$ -block-encoding of  $A$  (implemented in cost  $T_A$ ), an  $(\alpha_L, a_L, \varepsilon_L)$ -block-encoding of  $L$  (implemented in cost  $T_L$ ), a parameter  $\lambda > 0$ , and a procedure to prepare  $|b\rangle$  (in cost  $T_b$ ), outputs a quantum state which is  $\delta$ -close to  $|x\rangle$ . The algorithm has a cost

$$\mathcal{O}\left(\kappa \log \kappa \left(\frac{\alpha_A + \sqrt{\lambda} \alpha_L}{\sqrt{\|A^T A + \lambda L^T L\|}} (T_A + T_L) \log\left(\frac{\kappa}{\delta}\right) + T_b\right)\right),$$

where  $\kappa$  can be thought of as the *effective condition number* and is related to the condition numbers of the matrices  $A$  and  $L$  ( $\kappa_A$  and  $\kappa_L$ , respectively). More precisely, it is defined as

$$\kappa = \kappa_A \kappa_L \sqrt{\frac{\|A\|^2 + \lambda \|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|L\|^2}}$$

Here  $\kappa < \kappa_A$ , where  $\kappa_A$  is the condition number of  $A$ . For instance, when  $\kappa_A$  is very large, we have  $\kappa = \mathcal{O}(\kappa_L)$ . The parameters  $\alpha_A$  and  $\alpha_L$  take specific values depending on the underlying input model. For the sparse access input model,  $\alpha_A = s_A$  and  $\alpha_L = s_L$ , the respective sparsities of the matrices  $A$  and  $L$ . On the other hand for the quantum data structure input model,  $\alpha_A = \|A\|_F$  and  $\alpha_L = \|L\|_F$ . Consequently the complexity of *Quantum Ridge Regression* can be obtained by substitute  $L = I$  in the aforementioned complexity as

$$\mathcal{O}\left(\kappa \log \kappa \left(\frac{\alpha_A}{\|A\| + \sqrt{\lambda}} \log\left(\frac{\kappa}{\delta}\right) T_A + T_b\right)\right),$$

by noting that the block-encoding of  $I$  is trivial while the norm and condition number of the identity matrix is one. For this problem of *quantum ridge regression*, our quantum algorithms are substantially better than prior results [SX20, YGW21, CYGL22], exhibiting a polynomial improvement in  $\kappa$  and an exponential improvement in  $1/\delta$ .

For the  $\ell_2$ -regularized GLS problem (Section 4, Theorem 43), we design a quantum algorithm that along with approximate block-encodings of  $A$  and  $L$ , takes as input an  $(\alpha_\Omega, a_\Omega, \varepsilon_\Omega)$  - block encoding of the matrix  $\Omega$  (implementable at a cost of  $T_\Omega$ ) to output a state  $\delta$ -close to  $|x\rangle$  at a cost of

$$\mathcal{O}\left(\kappa \log \kappa \left(r \left(\frac{\alpha_A}{\|A\|} T_A + \frac{\alpha_L}{\|L\|} T_L + \frac{\alpha_\Omega \kappa_\Omega^{3/2}}{\|\Omega\|} T_\Omega \log\left(\frac{\kappa_\Omega}{\sqrt{\|\Omega\|}}\right)\right) \log^3\left(\frac{\kappa r}{\delta}\right) + \sqrt{\kappa_\Omega} T_b\right)\right).$$

Here  $r$  is a parameter that is a ratio of the spectral norms of the matrices  $A$ ,  $\Omega$  and  $L$  and is a constant whenever the norms are. On the other hand, the expression for the effective condition number  $\kappa$  is defined as

$$\kappa = \kappa_A \kappa_L \sqrt{\frac{\kappa_\Omega \|A\|^2 + \lambda \|\Omega\| \|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|\Omega\| \|L\|^2}}.$$

The WLS problem is a special case of GLS, wherein the matrix  $\Omega$  is diagonal. However, we show that better complexities for the  $\ell_2$ -regularized WLS problem can be obtained if we assume QRAM access to the diagonal entries of  $W$  (Section 4, Theorem 48 and Theorem 49).

Table 1 summarizes the complexities of our algorithms for quantum linear regression with general  $\ell_2$ -regularization. For better exposition, here we assume that  $\|A\|, \|L\|, \|\Omega\|$  and  $\lambda = \Theta(1)$ . For the general expression of the complexities, we refer the readers to Section 4.

Problem	Unregularized	$\ell_2$ -Regularized
Quantum OLS	$\tilde{O}(\alpha_A \kappa_A \log(1/\delta))$	$\tilde{O}((\alpha_A + \alpha_L) \kappa \log(1/\delta))$
Quantum GLS	$\tilde{O}((\alpha_A + \alpha_\Omega \kappa_\Omega^{1.5}) \kappa_A \log^3(1/\delta))$	$\tilde{O}((\alpha_A + \alpha_L + \alpha_\Omega \kappa_\Omega^{1.5}) \kappa \log^3(1/\delta))$

Table 1: Complexity of quantum linear regression algorithms with and without general  $\ell_2$ -regularization. All of these algorithms require only  $\Theta(\log \kappa)$  additional qubits.

In order to derive our results, we take advantage of the ability to efficiently perform arithmetic operations on block-encoded matrices, as outlined in [Section 3](#). Along with this, we use QSVT to perform linear algebraic operations on block-encoded matrices. To this end, adapt the results in Refs. [\[GSLW19, MRTC21\]](#) to our setting. One of our contributions is that we work with robust versions of many of these algorithms. In prior work, QSVT is often applied to block-encoded matrices, assuming perfect block-encoding. For the quantum algorithms in this paper, we rigorously obtain the precision  $\varepsilon$  required to obtain a  $\delta$ -approximation of the desired output state.

For instance, a key ingredient of our algorithm for regularized least squares is to make use of QSVT to obtain  $A^+$ , given an  $\varepsilon$ -approximate block-encoding of  $A$ . In order to obtain a (near) optimal dependence on the condition number of  $A$  by applying variable-time amplitude amplification (VTAA) [\[Amb12\]](#), we recast the standard QSVT algorithm as a variable stopping-time quantum algorithm. Using QSVT instead of controlled Hamiltonian simulation ensures that the variable-time quantum procedure to prepare  $A^+ |x\rangle$  has a slightly better running time (by a log factor) and considerably fewer additional qubits than Refs. [\[CKS17, CGJ19\]](#).

Furthermore, for the variable time matrix inversion algorithm, a crucial requirement is the application of the inversion procedure to the portion of the input state that is spanned by singular values larger than a certain threshold. In order to achieve this, prior results have made use of *Gapped Phase Estimation* (GPE), which is a simple variant of the standard phase estimation procedure that decides whether the eigenvalue of an operator is above or below a certain threshold [\[Amb12, CKS17, CGJ19\]](#). However, GPE requires extra registers that store the estimates of the phases, which are never used for variable-time amplitude amplification. In this work, instead of GPE, we make use of a robust version of *quantum eigenvalue discrimination* (QEVD) using QSVT, which decides whether the eigenvalue of a matrix is above or below a certain threshold without storing the eigenvalue estimates [\[GSLW19, MRTC21\]](#). This further reduces the number of additional qubits required for our variable time by a factor of  $O(\log^2(\kappa/\delta))$  as compared to prior results [\[CKS17, CGJ19\]](#). We show that in order to implement  $A^+$ , the precision required in the block-encoding of  $A$  is determined in turn by the precision in the QEVD procedure. Consequently, this also implies that in our framework, quantum algorithms for (unregularized) least squares (which are special cases of our result) have better complexities than those of Ref. [\[CGJ19\]](#).

## 2 Preliminaries

This section introduces the quantum singular value transformation (QSVT) and block-encoding frameworks, which are used to design the algorithm for quantum regression.

### 2.1 Notation

For a matrix  $A \in \mathbb{R}^{N \times d}$ ,  $A_{i,\cdot}$  denotes the  $i^{\text{th}}$  row of  $A$ , and  $\|A_{i,\cdot}\|$  denotes the vector norm of  $A_{i,\cdot}$ .  $s_r^A$  and  $s_c^A$  denote the row and column sparsity of the matrix, which is the maximum number of non-zero entries in any row and any column respectively.



**Singular Value Decomposition.** The decomposition  $A = W\Sigma V^\dagger$ , where  $W$  and  $V$  are unitary and  $\Sigma$  is a diagonal matrix, represents the *singular value decomposition* (SVD) of  $A$ . All matrices can be decomposed in this form. The diagonal entries of  $\Sigma$ , usually denoted by  $\sigma(A) = \{\sigma_j\}$ , is the multiset of all *singular values* of  $A$ , which are real and non-negative.  $\sigma_{\max}$  and  $\sigma_{\min}$  denote the maximum and minimum singular values of  $A$ .  $r(A) = \text{rank}(A)$  is the number of non-zero singular values of  $A$ . The columns of  $W$ ,  $V$  (denoted by  $\{|w_j\rangle\}$  and  $\{|v_j\rangle\}$ ) are the left and right *singular vectors* of  $A$ . Thus  $A = \sum_j^r \sigma_j |w_j\rangle\langle v_j|$ . The singular vectors of  $A$  can be computed as the positive square roots of the eigenvalues of  $A^T A$  (which is Hermitian, and therefore has real eigenvalues.)

**Condition Number.**  $\kappa_A$  denotes (an upper bound on) the condition number of  $A$ , defined as the ratio of the maximum and minimum singular values of  $A$ ,

$$\kappa_A \geq \frac{\sigma_{\max}(A)}{\sigma_{\min}(A)}.$$

**Norm.** Unless otherwise specified,  $\|A\|$  denotes the spectral norm of  $A$ , while  $\|A\|_F$  denotes the Frobenius norm of  $A$ , defined as

$$\|A\| := \max_{x \neq 0} \frac{\|Ax\|}{\|x\|} = \sigma_{\max}(A)$$

$$\|A\|_F := \sqrt{\sum_{j=1}^r \sigma_j^2}$$

Unless otherwise specified, when  $A$  is assumed to be normalized, it is with respect to the spectral norm.

**Soft-O Complexity.** Finally, we use  $f = \tilde{\mathcal{O}}(g)$  to denote  $f = \mathcal{O}(g \cdot \text{polylog}(g))$ .

**Controlled Unitaries.** If  $U$  is a  $s$ -qubit unitary, then  $C-U$  is a  $(s+1)$ -qubit unitary defined by

$$C-U = |0\rangle\langle 0| \otimes I_s + |1\rangle\langle 1| \otimes U$$

## 2.2 Quantum Input Models

The complexities of quantum algorithms often depend on how the input data is accessed. For instance, in quantum algorithms for linear algebra (involving matrix operations), it is often assumed that there exists a black-box that returns the positions of the non-zero entries of the underlying matrix when queried. The algorithmic running time is expressed in terms of the number of queries made to this black-box. Such an input model, known as the *Sparse Access Model*, helps design efficient quantum algorithms whenever the underlying matrices are sparse. Various other input models exist, and quantum algorithms are typically designed and optimized for specific input models.

Kerenidis and Prakash [KP17] introduced a different input model, known as the *quantum data structure model*, which is more conducive for designing quantum machine learning algorithms. In this model, the input data (e.g: entries of matrices) arrive online and are stored in a classical data structure (often referred to as the KP-tree in the literature), which can be queried in superposition by using a QRAM. This facilitates efficiently preparing quantum states corresponding to the rows of the underlying matrix, that can then be used for performing several matrix operations. Subsequently, several quantum-inspired classical algorithms have also been developed following the breakthrough result of Tang [Tan19]. Such classical algorithms have the same underlying assumptions as the quantum algorithms designed in the data structure input model and are only polynomially slower provided the underlying matrix is low rank.

In this work, we will consider the framework of *block-encoding*, wherein it is assumed that the input matrix  $A$  (up to some sub-normalization) is stored in the left block of some unitary. The advantage of the block-encoding framework, which was introduced in a series of works [LC19, LC17b, CGJ19, GSLW19], is that it can be applied to a wide variety of input models. For instance, it can be shown that both the sparse access input model as well as the quantum data structure input model are specific instances of block-encoded matrices [CGJ19, GSLW19]. Here we formally define the framework of block-encoding and also express the sparse access model as well as the quantum data structure model as block-encodings. We refer the reader to [CGJ19, GSLW19] for proofs.

**Definition 1** (Block Encoding, restated from [GSLW19]). *Suppose that  $A$  is an  $s$ -qubit operator,  $\alpha, \varepsilon \in \mathbb{R}^+$  and  $a \in \mathbb{N}$ , then we say that the  $(s + a)$ -qubit unitary  $U_A$  is an  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$ , if*

$$\|A - \alpha(\langle 0|^{\otimes a} \otimes I)U_A(|0\rangle^{\otimes a} \otimes I)\| \leq \varepsilon. \quad (11)$$

Let  $|\psi\rangle$  be an  $s$ -qubit quantum state. Then applying  $U_A$  to  $|\psi\rangle|0\rangle^{\otimes a}$  outputs a quantum state that is  $\frac{\varepsilon}{\alpha}$ -close to

$$\frac{A}{\alpha}|\psi\rangle|0\rangle^{\otimes a} + |\Phi^\perp\rangle,$$

where  $(I_s \otimes |0\rangle^{\otimes a} \langle 0|^{\otimes a})|\Phi^\perp\rangle = 0$ . Equivalently, suppose  $\tilde{A} := \alpha(\langle 0|^{\otimes a} \otimes I_s)U_A(|0\rangle^{\otimes a} \otimes I_s)$  denotes the actual matrix that is block-encoded into  $U_A$ , then  $\|A - \tilde{A}\| \leq \varepsilon$ .

In the subsequent sections, we provide an outline of the quantum data structure model and the sparse access model which are particular instances of the block encoding framework.

### 2.2.1 Quantum Data Structure Input Model

Kerenidis and Prakash introduced a quantum accessible classical data structure which has proven to be quite useful for designing several quantum algorithms for linear algebra [KP17]. The classical data structure stores entries of matrices or vectors and can be queried in superposition using a QRAM (quantum random access memory). We directly state the following theorem from therein.

**Theorem 2** (Implementing quantum operators using an efficient data structure, [Pra14, KP17]). *Let  $A \in \mathbb{R}^{N \times d}$ , and  $w$  be the number of non-zero entries of  $A$ . Then there exists a data structure of size  $\mathcal{O}(w \log^2(dN))$  that given the matrix elements  $(i, j, a_{ij})$ , stores them at a cost of  $\mathcal{O}(\log(dN))$  operations per element. Once all the non-zero entries of  $A$  have been stored in the data structure, there exist quantum algorithms that are  $\varepsilon$ -approximations to the following maps:*

$$U : |i\rangle|0\rangle \mapsto \frac{1}{\|A_{i,\cdot}\|} \sum_{j=1}^d a_{i,j} |i, j\rangle = |\psi_i\rangle,$$

$$V : |0\rangle|j\rangle \mapsto \frac{1}{\|A\|_F} \sum_{i=1}^N \|A_{i,\cdot}\| |i, j\rangle = |\phi_j\rangle$$

where  $\|A_{i,\cdot}\|$  is the norm of the  $i^{\text{th}}$  row of  $A$  and the second register of  $|\psi_i\rangle$  is the quantum state corresponding to the  $i^{\text{th}}$  row of  $A$ . These operations can be applied at a cost of  $\mathcal{O}(\text{polylog}(Nd/\varepsilon))$ .

It was identified in Ref. [CGJ19] that if a matrix  $A$  is stored in this quantum accessible data structure, there exists an efficiently implementable block-encoding of  $A$ . We restate their result here.

**Lemma 3** (Implementing block encodings from quantum data structures, [CGJ19]). *Let the entries of the matrix  $A \in \mathbb{R}^{N \times d}$  be stored in a quantum accessible data structure, then there exist unitaries  $U_R, U_L$  that can be implemented at a cost of  $\mathcal{O}(\text{polylog}(dN/\varepsilon))$  such that  $U_R^\dagger U_L$  is a  $(\|A\|_F, \lceil \log(d + N) \rceil, \varepsilon)$ -block-encoding of  $A$ .*

*Proof.* The unitaries  $U_R$  and  $U_L$  can be implemented via  $U$  and  $V$  in the previous lemma. Let  $U_R = U$  and  $U_L = V.\text{SWAP}$ . Then for  $s = \lceil \log(d + N) \rceil$  we have

$$U_R : |i\rangle |0^s\rangle \rightarrow |\psi_i\rangle,$$

and

$$U_L : |j\rangle |0^s\rangle \rightarrow |\phi_j\rangle,$$

So we have that the top left block of  $U_R^\dagger U_L$  is given by

$$\sum_{i=1}^N \sum_{j=1}^d \langle \psi_i | \phi_j \rangle |i, 0\rangle \langle j, 0|$$

Now

$$\begin{aligned} \langle \psi_i | \phi_j \rangle &= \sum_{k=1}^d \sum_{\ell=1}^N \frac{a_{ik}}{\|A_{i,\cdot}\|} \cdot \frac{\|A_{\ell}\|}{\|A\|_F} \underbrace{\langle i, k | \ell, j \rangle}_{:=\delta_{i,\ell} \delta_{k,j}} \\ &= \frac{a_{ij}}{\|A\|_F}. \end{aligned}$$

Moreover since only  $\varepsilon$ -approximations of  $U$  and  $V$  can be implemented we have that  $U_R^\dagger U_L$  is a  $(\|A\|_F, \lceil \log(n + d) \rceil, \varepsilon)$  block encoding of  $A$  implementable with the same cost as  $U$  and  $V$ .  $\square$

In Ref. [KP20] argued that in certain scenarios, storing the entries of  $A^{(p)}, (A^{1-p})^\dagger$  might be useful as compared to storing  $A$ , for some  $p \in [0, 1]$ . In such cases, the quantum data structure is a  $(\mu_p, \lceil \log(N + d) \rceil, \varepsilon)$  block encoding of  $A$ , where  $\mu_p(A) = \sqrt{s_{2p}(A) \cdot s_{2(1-p)}(A^T)}$  such that  $s_p(A) := \max_j \|A_{j,\cdot}\|_q^q$ . Throughout the work, whenever our results are expressed in the quantum data structure input model, we shall state our complexity in terms of  $\mu_A$ . When the entries of  $A$  are directly stored in the data structure,  $\mu_A = \|A\|_F$ . Although, we will not state it explicitly each time, our results also hold when fractional powers of  $A$  are stored in the database and simply substituting  $\mu_A = \mu_p(A)$ , yields the required complexity.

## 2.2.2 Sparse Access Input Model

The sparse access input model considers that the input matrix  $A \in \mathbb{R}^{N \times d}$  has row sparsity  $s_r$  and column sparsity  $s_c$ . Furthermore, it assumes that the entries of  $A$  can be queried via an oracle as

$$O_A : |i\rangle |j\rangle |0\rangle^{\otimes b} \mapsto |i\rangle |j\rangle |a_{ij}\rangle \quad \forall i \in [N], j \in [d],$$

and the indices of the non-zero elements of each row and column can be queried via the following oracles:

$$\begin{aligned} O_r : |i\rangle |j\rangle &\mapsto |i\rangle |r_{ij}\rangle \quad \forall i \in [N], k \in [s_r], \\ O_c : |i\rangle |j\rangle &\mapsto |c_{ij}\rangle |j\rangle \quad \forall i \in [d], k \in [s_c] \end{aligned}$$

where  $r_{ij}$  is the  $j^{\text{th}}$  non-zero entry of the  $i^{\text{th}}$  row of  $A$  and  $c_{ij}$  is the  $i^{\text{th}}$  non-zero entry of the  $j^{\text{th}}$  column of  $A$ . Gilyén et al. [GSLW19] showed that a block encoding of a sparse  $A$  can be efficiently prepared by using these three oracles. We restate their lemma below.

**Lemma 4** (Constructing a block-encoding from sparse-access to matrices, [GSLW19]). *Let  $A \in \mathbb{R}^{N \times d}$  be an  $s_r, s_c$  row, column sparse matrix given as a sparse access input. Then for all  $\varepsilon \in (0, 1)$ , we can implement a  $(\sqrt{s_c s_r}, \text{polylog}(Nd/\varepsilon), \varepsilon)$ -block-encoding of  $A$  with  $\mathcal{O}(1)$  queries to  $O_r, O_c, O_A$  and  $\text{polylog}(Nd/\varepsilon)$  elementary quantum gates.*

Throughout the paper, we shall assume input matrices are accessible via approximate block-encodings. This also allows us to write down the complexities of our quantum algorithms in this general framework. Additionally, we state the complexities in both the sparse access input model as well as the quantum accessible data structure input model as particular cases.

### 2.3 Quantum Singular Value Transformation

In a seminal work, Gilyén et al. presented a framework to apply an arbitrary polynomial function to the singular values of a matrix, known as Quantum Singular Value Transformation (QSVT) [GSLW19]. QSVT is quite general: many quantum algorithms can be recast to this framework, and for several problems, better quantum algorithms can be obtained [GSLW19, MRTC21]. In particular, QSVT has been extremely useful in obtaining optimal quantum algorithms for linear algebra. For instance, using QSVT, given the block-encoding of a matrix  $A$ , one could obtain  $A^{-c}$  with  $c \in [0, \infty)$  with optimal complexity and by using fewer additional qubits than prior art. This section briefly describes this framework, which is a generalization of Quantum Signal Processing (QSP) [LC19, LC17b, LYC16]. The reader may refer to [MRTC21] for a more pedagogical overview of these techniques.

QSP is a quantum algorithm to apply a  $d$ -degree bounded polynomial transformation with parity  $d \bmod 2$  to an arbitrary quantum subsystem, using a quantum circuit  $U_\Phi$  consisting of only controlled single qubit rotations. This is achieved by interleaving a *signal rotation operator*  $W$  (which is an  $x$ -rotation by some fixed angle  $\theta$ ) and a *signal processing operator*  $S_\phi$  (which is a  $z$ -rotation by a variable angle  $\phi \in [0, 2\pi]$ ). In this formulation, the signal rotation operator is defined as

$$W(x) := \begin{pmatrix} x & i\sqrt{1-x^2} \\ i\sqrt{1-x^2} & x \end{pmatrix}, \quad (12)$$

which is an  $x$ -rotation by angle  $\theta = -2 \arccos(x)$ , and the signal processing operator is defined as

$$S_\phi := e^{i\phi Z}, \quad (13)$$

which is a  $z$ -rotation by an angle  $-2\phi$ . Interestingly, sandwiching them together for some  $\Phi := (\phi_0, \phi_1, \dots, \phi_d) \in \mathbb{R}^{d+1}$ , as shown in Equation 14, gives us a matrix whose elements are polynomial transformations of  $x$ ,

$$U_\Phi := e^{i\phi_0 Z} \prod_{j=1}^{j=d} \left( W(x) e^{i\phi_j Z} \right) \quad (14)$$

$$= \begin{pmatrix} P(x) & iQ(x)\sqrt{1-x^2} \\ iQ^*(x)\sqrt{1-x^2} & P^*(x) \end{pmatrix}, \quad (15)$$

such that

1.  $\deg P \leq d$ ;  $\deg Q \leq d - 1$ ,
2.  $P(x)$  has a parity  $d \bmod 2$ ,
3.  $|P(x)|^2 + (1 - x^2)|Q(x)|^2 = 1 \quad \forall x \in [-1, 1]$ .

Following the application of the quantum circuit  $U_\Phi$  for an appropriate  $\Phi$ , one can project into the top left block of  $U_\Phi$  to recover the polynomial  $\langle 0 | U_\Phi | 0 \rangle = P(x)$ . Projecting to other basis allows the ability to perform more interesting polynomial transformations, which can be linear combinations of  $P(x)$ ,  $Q(x)$ , and their complex conjugates. For example, projecting to  $\{|+\rangle, |-\rangle\}$  basis gives us

$$\langle + | U_\Phi | + \rangle = \Re(P(x)) + i\Re(Q(x))\sqrt{1-x^2}. \quad (16)$$

This procedure can be naturally generalized to apply a similar polynomial transformation to each singular value of an arbitrary block of a unitary matrix. Suppose we have access to a matrix  $A$ , which is block encoded into some unitary  $U_A$ , and can be accessed by projectors  $\Pi, \tilde{\Pi}$  as  $A := \tilde{\Pi}U_A\Pi$ . The singular value decomposition of  $A$  is given as

$$A := W\Sigma V^\dagger = \sum_j \sigma_j |v_j\rangle \langle w_j|, \quad (17)$$

where  $W, V$  are unitary matrices,  $\Sigma$  is a diagonal matrix whose  $j^{\text{th}}$  diagonal entry is  $\sigma_j$  (the singular values of  $A$ ), and  $|v_j\rangle, |w_j\rangle$  are the corresponding left and right singular vectors respectively.

Then one can interleave  $U_A$  and  $U_A^\dagger$  with a *projector controlled phase shift* operator,  $\Pi_\phi := e^{i\phi(2\Pi-I)}, \tilde{\Pi}_\phi := e^{i\phi(2\tilde{\Pi}-I)}$ , for a parameter  $\phi$ . For a given phase angle sequence  $\Phi \in \mathbb{R}^d$ , the QSVT sequence is given as

$$U_\Phi = \begin{cases} \tilde{\Pi}_{\phi_1} U_A \left[ \prod_{k=1}^{(d-1)/2} \Pi_{\phi_{2k}} U_A^\dagger \tilde{\Pi}_{\phi_{2k+1}} U_A \right] & d \text{ is odd} \\ \left[ \prod_{k=1}^{d/2} \Pi_{\phi_{2k-1}} U_A^\dagger \tilde{\Pi}_{\phi_{2k}} U_A \right] & d \text{ is even,} \end{cases} \quad (18)$$

where  $\phi_i$  is the  $i^{\text{th}}$  element of  $\Phi$ . Now projecting to  $\Pi, \tilde{\Pi}$  gives us the polynomial transformation of  $A$  as

$$P^{SV}(A) = \begin{cases} \tilde{\Pi}U_\Phi\Pi & d \text{ is odd} \\ \Pi U_\Phi \Pi & d \text{ is even,} \end{cases} \quad (19)$$

where  $P^{SV}(A)$  is the polynomial transformation of the matrix  $A$  defined as

$$P^{SV}(A) := \begin{cases} \sum_j P(\sigma_j) |w_j\rangle \langle v_j| & P \text{ is odd} \\ \sum_j P(\sigma_j) |v_j\rangle \langle v_j| & P \text{ is even,} \end{cases} \quad (20)$$

This gives us an extremely powerful primitive to design novel quantum algorithms, some of which we shall be using in subsequent sections.

## 2.4 Variable Time Amplitude Amplification

Ambainis [Amb12] defined the notion of a *variable-stopping-time quantum algorithm* and formulated the technique of *Variable Time Amplitude Amplification* (VTAA), a tool that can be used to amplify the success probability of a variable-stopping-time quantum algorithm to a constant by taking advantage of the fact that computation on some parts of an algorithm can complete earlier than on other parts. The key idea here is to look at a quantum algorithm  $\mathcal{A}$  acting on a state  $|\psi\rangle$  as a combination of  $m$  quantum sub-algorithms  $\mathcal{A} = \mathcal{A}_m \cdot \mathcal{A}_{m-1} \cdot \dots \cdot \mathcal{A}_1$ , each acting on  $|\psi\rangle$  conditioned on some ancilla flag being set. Formally, a variable stopping time algorithm is defined as follows

**Definition 5** (Variable-stopping-time Algorithm, [Amb12]). *A quantum algorithm  $\mathcal{A}$  acting on  $\mathcal{H}$  that can be written as  $m$  quantum sub-algorithms,  $\mathcal{A} = \mathcal{A}_m \cdot \mathcal{A}_{m-1} \cdot \dots \cdot \mathcal{A}_1$  is called a variable stopping time algorithm if  $\mathcal{H} = \mathcal{H}_C \otimes \mathcal{H}_A$ , where  $\mathcal{H}_C = \otimes_{i=1}^m \mathcal{H}_{C_i}$  with  $\mathcal{H}_{C_i} = \text{span}(|0\rangle, |1\rangle)$ , and each unitary  $\mathcal{A}_j$  acts on  $\mathcal{H}_{C_j} \otimes \mathcal{H}_A$  controlled on the first  $j-1$  qubits  $|0\rangle^{\otimes j-1} \in \otimes_{i=1}^{j-1} \mathcal{H}_{C_i}$  being in the all zero state.*

Here  $\mathcal{H}_{C_i}$  is a single qubit clock register. In VTAA,  $\mathcal{H}_A$  has a flag space consisting of a single qubit to indicate success,  $\mathcal{H}_A = \mathcal{H}_F \otimes \mathcal{H}_W$ . Here  $\mathcal{H}_F = \text{Span}(|g\rangle, |b\rangle)$  flags the good and bad parts of the run. Furthermore, for  $1 \leq i \leq m$ , define the stopping times  $t_i$  such that  $t_1 < t_2 < \dots < t_m = T_{\max}$ , such that the algorithm  $\mathcal{A}_j \mathcal{A}_{j-1} \dots \mathcal{A}_1$  having (gate/query) complexity  $t_i$  halts with probability

$$p_j = \left\| \Pi_{C_j} \mathcal{A}_j \mathcal{A}_{j-1} \dots \mathcal{A}_1 |0\rangle_{\mathcal{H}} \right\|^2,$$

where  $|0\rangle_{\mathcal{H}} \in \mathcal{H}$  is the all zero quantum state and  $\Pi_{C_j}$  is the projector onto  $|1\rangle$  in  $\mathcal{H}_{C_j}$ . From this one can define the average stopping time of the algorithm  $\mathcal{A}$  defined as

$$\|T\|_2 = \sqrt{\sum_{j=1}^m p_j t_j^2}.$$

For a variable stopping time algorithm if the average stopping time  $\|T\|_2$  is less than the maximum stopping time  $T_{\max}$ , VTAA can amplify the success probability ( $p_{\text{succ}}$ ) much faster than standard amplitude amplification. In this framework, the success probability of  $\mathcal{A}$  is given by

$$p_{\text{succ}} = \|\Pi_F \mathcal{A}_m \mathcal{A}_{m-1} \cdots \mathcal{A}_1 |0\rangle_{\mathcal{H}}\|^2$$

While standard amplitude amplification requires time scaling as  $\mathcal{O}(T_{\max}/\sqrt{p_{\text{succ}}})$ , the complexity of VTAA is more involved. Following [CGJ19], we define the complexity of VTAA as follows.

**Lemma 6** (Efficient variable time amplitude amplification [CGJ19]). *Let  $U$  be a state preparation unitary such that  $U |0\rangle^{\otimes k} = \sqrt{p_{\text{prep}}} |0\rangle |\psi_0\rangle + \sqrt{1-p_{\text{prep}}} |1\rangle |\psi_1\rangle$  that has a query complexity  $T_U$ . And let  $\mathcal{A} = \mathcal{A}_m \mathcal{A}_{m-1} \cdots \mathcal{A}_1$  be a variable stopping time quantum algorithm that we want to apply to the state  $|\psi_0\rangle$ , with the following known bounds:  $p_{\text{prep}} \geq p'_{\text{prep}}$  and  $p_{\text{succ}} \geq p'_{\text{succ}}$ . Define  $T'_{\max} := 2T_{\max}/t_1$  and*

$$Q := \left( T_{\max} + \frac{T_U + k}{\sqrt{p_{\text{prep}}}} \right) \sqrt{\log(T'_{\max})} + \frac{\left( \|T\|_2 + \frac{T_U + k}{\sqrt{p_{\text{prep}}}} \right) \log(T'_{\max})}{\sqrt{p_{\text{succ}}}}.$$

*Then with success probability  $\geq 1 - \delta$ , we can create a variable-stopping time algorithm  $\mathcal{A}'$  that prepares the state  $a |0\rangle \mathcal{A}' |\psi_0\rangle + \sqrt{1-a^2} |1\rangle |\psi_{\text{garbage}}\rangle$ , such that  $a = \Theta(1)$  is a constant and  $\mathcal{A}'$  has the complexity  $\mathcal{O}(Q)$ .*

One cannot simply replace standard amplitude amplification with VTAA to boost the success probability of a quantum algorithm. A crucial task would be to recast the underlying algorithm in the VTAA framework. We will be applying VTAA to the quantum algorithm for matrix inversion by QSVT. So, first of all, in order to apply VTAA to the algorithm must be first recast into a variable-time stopping algorithm so that VTAA can be applied.

Originally, Ambainis [Amb12] used VTAA to improve the running time of the HHL algorithm from  $\mathcal{O}(\kappa^2 \log N)$  to  $\mathcal{O}(\kappa \log^3 \kappa \log N)$ . Childs et al. [CKS17] designed a quantum linear systems algorithm with a polylogarithmic dependence on the accuracy. Additionally, they recast their algorithm into a framework where VTAA could be applied to obtain a linear dependence on  $\kappa$ . Later Chakraborty et al. [CGJ19] modified Ambainis' VTAA algorithm to perform variable time amplitude estimation.

In this work, to design quantum algorithms for  $\ell_2$ -regularized linear regression, we use a quantum algorithm for matrix inversion by QSVT. We recast this algorithm in the framework of VTAA to achieve nearly linear dependence in  $\kappa$  (the condition number of the matrix to be inverted). QSVT instead of controlled Hamiltonian simulation improves the complexity of the overall matrix inversion algorithm (using QSVT and VTAA) by a log factor and reduces the number of additional qubits substantially. Furthermore, we replace a quantum gapped phase estimation procedure with a more efficient quantum eigenvalue discrimination algorithm using QSVT. This further reduces the number of additional qubits by  $O(\log^2(\kappa/\delta))$  than in Refs. [CKS17, CGJ19], where  $\kappa$  is the condition number of the underlying matrix and  $\delta$  is the desired accuracy. The details of a variable stopping time quantum algorithm for matrix inversion by QSVT is laid out in Section 3.3.

### 3 Algorithmic Primitives

This section introduces the building blocks of our quantum algorithms for quantum linear regression with general  $\ell_2$ -regularization. As mentioned previously, we work in the block-encoding framework.

We develop robust quantum algorithms for arithmetic operations, inversion, and positive and negative powers of matrices using quantum singular value transformation, assuming that we have access to approximate block-encodings of these matrices. While some of these results were previously derived assuming perfect block-encodings [GSLW19, CGJ19], we calculate the precision required in the input block-encodings to output a block-encoding or quantum state arbitrarily close to the target.

Given a  $(\alpha, a, \varepsilon)$ -block-encoding of a matrix  $A$ , we can efficiently amplify the sub-normalization factor from  $\alpha$  to a constant and obtain an amplified block-encoding of  $A$ . For our quantum algorithms in Sec. 4, we show working with pre-amplified block-encodings often yields better complexities. We state the following lemma which was proven in Ref. [LC17a]:

**Lemma 7** (Uniform Block Amplification of Contractions, [LC17a]). *Let  $A \in \mathbb{R}^{N \times d}$  such that  $\|A\| \leq 1$ . If  $\alpha \geq 1$  and  $U$  is a  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$  that can be implemented at a cost of  $T_U$ , then there is a  $(\sqrt{2}, a + 1, \varepsilon + \gamma)$ -block-encoding of  $A$  that can be implemented at a cost of  $\mathcal{O}(\alpha T_U \log(1/\gamma))$ .*

**Corollary 8** (Uniform Block Amplification). *Let  $A \in \mathbb{R}^{N \times d}$  and  $\delta \in (0, 1]$ . Suppose  $U$  is a  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$ , such that  $\varepsilon \leq \frac{\delta}{2}$ , that can be implemented at a cost of  $T_U$ . Then a  $(\sqrt{2}\|A\|, a + 1, \delta)$ -block-encoding of  $A$  can be implemented at a cost of  $\mathcal{O}\left(\frac{\alpha T_U}{\|A\|} \log(\|A\|/\delta)\right)$ .*

We now obtain the complexity of applying a block-encoded matrix to a quantum state, which is a generalization of a lemma proven in Ref. [CGJ19].

**Lemma 9** (Applying a Block-encoded Matrix on a Quantum State). *Let  $A$  be an  $s$ -qubit operator such that its singular values lie in  $[\|A\|/\kappa, \|A\|]$ . Also let  $\delta \in (0, 1)$ , and  $U_A$  be an  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$ , such that*

$$\varepsilon \leq \frac{\delta \|A\|}{2\kappa},$$

*that can be implemented in time  $T_A$ . Furthermore, suppose  $|b\rangle$  be an  $s$ -qubit quantum state that can be prepared in time  $T_b$ . Then we can prepare a state that is  $\delta$ -close to  $\frac{A|b\rangle}{\|A|b\rangle\|}$  with success probability  $\Omega(1)$  at a cost of*

$$\mathcal{O}\left(\frac{\alpha\kappa}{\|A\|}(T_A + T_b)\right)$$

**Corollary 10** (Applying a pre-amplified Block-encoded Matrix on a Quantum State). *Let  $A$  be an  $s$ -qubit operator such that its singular values lie in  $[\|A\|/\kappa, \|A\|]$ . Also let  $\delta \in (0, 1)$ , and  $U_A$  be an  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$ , such that*

$$\varepsilon \leq \frac{\delta \|A\|}{4\kappa},$$

*that can be implemented in time  $T_A$ . Furthermore, suppose  $|b\rangle$  be an  $s$ -qubit quantum state that can be prepared in time  $T_b$ . Then we can prepare a state that is  $\delta$ -close to  $\frac{A|b\rangle}{\|A|b\rangle\|}$  with success probability  $\Omega(1)$  at a cost of*

$$\mathcal{O}\left(\frac{\alpha\kappa}{\|A\|} \log\left(\frac{\kappa}{\delta}\right) T_A + \kappa T_b\right)$$

Now, it may happen that the  $U_b$  prepares a quantum state that is only  $\varepsilon$ -close to the desired state  $|b\rangle$ . In such cases, we have the following lemma

**Lemma 11** (Robustness of state preparation). *Let  $A$  be an  $s$ -qubit operator such that its singular values lie in  $[\frac{\|A\|}{\kappa}, \|A\|]$ . Suppose  $|b'\rangle$  is a quantum state that is  $\varepsilon/2\kappa$ -close to  $|b\rangle$  and  $|\psi\rangle$  is a quantum state that is  $\varepsilon/2$ -close to  $A|b'\rangle/\|A|b'\rangle\|$ . Then we have that  $|\psi\rangle$  is  $\varepsilon$ -close to  $A|b\rangle/\|A|b\rangle\|$ .*

The proofs for [Corollary 8](#), [Lemma 9](#), [Corollary 10](#), and [Lemma 11](#) can be found in [Appendix A](#).

### 3.1 Arithmetic with Block-Encoded Matrices

The block-encoding framework embeds a matrix on the top left block of a larger unitary  $U$ . It has been demonstrated framework allows us to obtain sums, products, linear combinations of block-encoded matrices. This is particularly useful for solving linear algebra problems in general. Here, we state some of the arithmetic operations on block-encoded matrices that we shall be using in order to design the quantum algorithms of [Section 4](#) and tailor existing results to our requirements.

First we prove a slightly more general form of linear combination of unitaries in the block-encoding framework, presented in [\[GSLW19\]](#). To do this we assume that we are given optimal state preparation pairs, defined as follows.

**Lemma 12** (Optimal State Preparation Unitary). *Let  $m \in \mathbb{Z}^+$ ,  $\eta \in \mathbb{R}_+^m$ , and  $s = \lceil \log m \rceil$ . Then there exists an  $s$ -qubit unitary  $P$  – called a  $\eta$  state-preparation unitary – such that  $P|0\rangle$  is proportional to  $\sum_j \sqrt{\eta_j} |j\rangle$*

**Lemma 13** (Linear Combination of Block Encoded Matrices). *For each  $j \in \{0, \dots, m-1\}$ , let  $A_j$  be an  $s$ -qubit operator, and  $y_j \in \mathbb{R}^+$ . Let  $U_j$  be a  $(\alpha_j, a_j, \varepsilon_j)$ -block-encoding of  $A_j$ , implemented in time  $T_j$ . Define the matrix  $A = \sum_j y_j A_j$ , and the vector  $\eta \in \mathbb{R}^m$  s.t.  $\eta_j = y_j \alpha_j$ . Let  $U_\eta$  be a  $\eta$  state-preparation unitary, implemented in time  $T_\eta$ . Then we can implement a*

$$\left( \sum_j y_j \alpha_j, \max_j(a_j) + s, \sum_j y_j \varepsilon_j \right)$$

*block-encoding of  $A$  at a cost of  $\mathcal{O}(\sum_j T_j + T_\eta)$ .*

The proof is similar to the one in Ref. [\[GSLW19\]](#), with some improvements to the bounds. The detailed proof can be found in [Appendix A](#). We now specialize the above lemma for the case where we need a linear combination of just two unitaries. This is the case used in this work, and we obtain a better error scaling for this by giving an explicit state preparation unitary.

**Corollary 14** (Linear Combination of Two Block Encoded Matrices). *For  $j \in \{0, 1\}$ , let  $A_j$  be an  $s$ -qubit operator and  $y_j \in \mathbb{R}^+$ . Let  $U_j$  be a  $(\alpha_j, a_j, \varepsilon_j)$ -block-encoding of  $A_j$ , implemented in time  $T_j$ . Then we can implement a  $(y_0 \alpha_0 + y_1 \alpha_1, 1 + \max(a_0, a_1), y_0 \varepsilon_0 + y_1 \varepsilon_1)$  encoding of  $y_0 A_0 + y_1 A_1$  in time  $\mathcal{O}(T_0 + T_1)$ .*

*Proof.* Let  $\alpha = y_0 \alpha_0 + y_1 \alpha_1$  and  $P = \frac{1}{\sqrt{\alpha}} \begin{pmatrix} \sqrt{y_0 \alpha_0} & -\sqrt{y_1 \alpha_1} \\ \sqrt{y_1 \alpha_1} & \sqrt{y_0 \alpha_0} \end{pmatrix}$ . By [Lemma 12](#), we have that  $P$  is an  $\{y_0 \alpha_0, y_1 \alpha_1\}$  state preparation unitary. Invoking [Lemma 13](#) with  $P$ , we get the required unitary.  $\square$

Given block-encodings of two matrices  $A$  and  $B$ , it is easy to obtain a block-encoding of  $AB$ .

**Lemma 15** (Product of Block Encodings, [\[GSLW19\]](#)). *If  $U_A$  is an  $(\alpha, a, \delta)$ -block-encoding of an  $s$ -qubit operator  $A$  implemented in time  $T_A$ , and  $U_B$  is a  $(\beta, b, \varepsilon)$ -block-encoding of an  $s$ -qubit operator  $B$  implemented in time  $T_B$ , then  $(I^{\otimes b} \otimes U_A)(I^{\otimes a} \otimes U_B)$  is an  $(\alpha\beta, a + b, \alpha\varepsilon + \beta\delta)$ -block-encoding of  $AB$  implemented at a cost of  $\mathcal{O}(T_A + T_B)$ .*

Directly applying [Lemma 15](#) results in a block-encoding of  $\frac{AB}{\alpha\beta}$ . If  $\alpha$  and  $\beta$  are large, then the sub-normalization factor  $\alpha\beta$  might incur an undesirable overhead to the cost of the algorithm that uses it. In many cases, the complexity of obtaining products of block-encodings can be improved if we first amplify the block-encodings (using [Lemma 8](#)) and then apply [Lemma 15](#). We prove the following lemma:



**Lemma 16** (Product of Amplified Block-Encodings). *Let  $\delta \in (0, 1]$ . If  $U_A$  is an  $(\alpha_A, a_A, \varepsilon_A)$ -block-encoding of an  $s$ -qubit operator  $A$  implemented in time  $T_A$ , and  $U_B$  is a  $(\alpha_B, a_B, \varepsilon_B)$ -block-encoding of an  $s$ -qubit operator  $B$  implemented in time  $T_B$ , such that  $\varepsilon_A \leq \frac{\delta}{4\sqrt{2}\|B\|}$  and  $\varepsilon_B \leq \frac{\delta}{4\sqrt{2}\|A\|}$ . Then we can implement a  $(2\|A\|\|B\|, a_A + a_B + 2, \delta)$ -block-encoding of  $AB$  implemented at a cost of*

$$\mathcal{O}\left(\left(\frac{\alpha_A}{\|A\|}T_A + \frac{\alpha_B}{\|B\|}T_B\right) \log\left(\frac{\|A\|\|B\|}{\delta}\right)\right).$$

*Proof.* Using [Corollary 8](#) for some  $\delta_A \geq 2\varepsilon_A$  we get a  $(\sqrt{2}\|A\|, a_A + 1, \delta_A)$ -block-encoding of  $A$  at a cost of

$$\mathcal{O}\left(\frac{\alpha_A T_A}{\|A\|} \log(\|A\|/\delta_A)\right).$$

Similarly for some  $\delta_B \geq 2\varepsilon_B$  we get a  $(\sqrt{2}\|B\|, a_B + 1, \delta_B)$ -block-encoding of  $B$  at a cost of

$$\mathcal{O}\left(\frac{\alpha_B T_B}{\|B\|} \log(\|B\|/\delta_B)\right).$$

Now using [Lemma 15](#) we get a  $(2, a_A + a_B + 2, \sqrt{2}(\|A\|\delta_B + \|B\|\delta_A))$ -block-encoding of  $AB$ . We can choose  $\delta_A = \frac{\delta}{2\sqrt{2}\|B\|}$  and  $\delta_B = \frac{\delta}{2\sqrt{2}\|A\|}$  which bounds the final block-encoding error by  $\delta$ .  $\square$

Observe that although we assumed that  $A$  and  $B$  are  $s$ -qubit operators, this is without loss of generality. For any any two matrices of dimension  $N \times d$ , where  $N$  and  $d$  and  $d \times K$ , such that  $N, d, K \leq 2^s$  we can always pad them with rows of zero entries. This leaves the matrix product unaltered.

Next we show how to find the block encoding of tensor product of matrices from their block encodings. This procedure will be useful in creating the dilated matrices required for regularization. The proof can be found in [Appendix A](#).

**Lemma 17** (Tensor Product of Block Encoded Matrices). *Let  $U_1$  and  $U_2$  be  $(\alpha, a, \varepsilon_1)$  and  $(\beta, b, \varepsilon_2)$ -block-encodings of  $A_1$  and  $A_2$ ,  $s$  and  $t$ -qubit operators, implemented in time  $T_1$  and  $T_2$  respectively. Define  $S := \prod_{i=1}^s \text{SWAP}_{a+b+i}^{\alpha+i}$ . Then,  $S(U_1 \otimes U_2)S^\dagger$  is an  $(\alpha\beta, a + b, \alpha\varepsilon_2 + \beta\varepsilon_1 + \varepsilon_1\varepsilon_2)$  block-encoding of  $A_1 \otimes A_2$ , implemented at a cost of  $\mathcal{O}(T_1 + T_2)$ .*

We will now use [Lemma 17](#) to augment one matrix into another, given their approximate block-encodings.

**Lemma 18** (Block-encoding of augmented matrix). *If  $U_A$  is an  $(\alpha_A, a_A, \varepsilon_A)$ -block encoding of an  $s$ -qubit operator  $A$  that can be implemented in time  $T_A$  and  $U_B$  is an  $(\alpha_B, a_B, \varepsilon_B)$ -block encoding of an  $s$ -qubit operator  $B$  that can be implemented in time  $T_B$ , then we can implement an  $(\alpha_A + \alpha_B, \max(a_A, a_B) + 2, \varepsilon_A + \varepsilon_B)$ -block-encoding of*

$$A_B = \begin{pmatrix} A & 0 \\ B & 0 \end{pmatrix}$$

at a cost of  $\mathcal{O}(T_A + T_B)$ .

*Proof.* Let  $M_A = \begin{pmatrix} 1 & 0 \\ 0 & 0 \end{pmatrix}$ . Then the SWAP gate is a  $(1, 1, 0)$  block encoding of  $M_A$ . By [Lemma 17](#), we

can implement  $U'_A$ , an  $(\alpha_A, a_A + 1, \varepsilon_A)$ -block-encoding of their tensor product  $M_A \otimes A = \begin{pmatrix} A & 0 \\ 0 & 0 \end{pmatrix}$  at a

cost of  $\mathcal{O}(T_A)$ . Similarly, Let  $M_B = \begin{pmatrix} 0 & 0 \\ 1 & 0 \end{pmatrix}$ . Then  $(I \otimes X) \cdot \text{SWAP}$  is a  $(1, 1, 0)$ -block-encoding of  $M_B$ .

Similarly [Lemma 17](#), we can implement  $U'_B$ , an  $(\alpha_B, a_B + 1, \varepsilon_B)$ -block-encoding of  $M_B \otimes B = \begin{pmatrix} 0 & 0 \\ B & 0 \end{pmatrix}$

at a cost of  $\mathcal{O}(T_B)$ . We add them by using [Corollary 14](#) on  $U'_A$  and  $U'_B$ , to implement  $U_{AB}$ , an

$(\alpha_A + \alpha_B, 2 + \max(a_A, a_B), \varepsilon_A + \varepsilon_B)$ -block-encoding of  $A_B = \begin{pmatrix} A & 0 \\ B & 0 \end{pmatrix}$ . This can be implemented at a

cost of  $\mathcal{O}(T_A + T_B)$ .  $\square$

**Lemma 19** (Block-Encoding of a dilated matrix). *If  $U_A$  is an  $(\alpha, a, \varepsilon)$ -block-encoding of an  $s$ -qubit operator  $A$  implemented in time  $T_A$ , then there is a  $(\alpha, a, \varepsilon)$ -block-encoding of an  $s + 1$ -qubit operator  $\bar{A} := \begin{pmatrix} 0 & A \\ A^\dagger & 0 \end{pmatrix}$ , that can be prepared at a cost of  $\mathcal{O}(T_A)$ .*

*Proof.* By adding an additional qubit, we can implement a controlled unitary  $C-U_A$  that acts on  $(a + s + 1)$  qubits such that controlled on the  $(a + 1)^{\text{th}}$  qubit, it implements  $U_A$  on the first  $a$  and the last  $s$  qubits. Let,

$$V = C-U_A^\dagger(X \otimes I)C-U_A = |0\rangle\langle 1| \otimes U_A + |1\rangle\langle 0| \otimes U_A^\dagger,$$

Then  $\text{SWAP}_{a,1}V$  is an  $(\alpha, a, \varepsilon)$ -block encoding of  $\bar{A}$ . Here  $\text{SWAP}_{a,1}$  is a sequence of SWAP gates that swaps the entire  $a$ -qubit register,  $|0\rangle^{\otimes a}$  with the single qubit control register, one qubit at a time.  $\square$

When using a dilated matrix  $\bar{A}$ , we must also extend the input state to  $|\bar{b}\rangle = |0\rangle|b\rangle$ . This just increases the number of input qubits by 1, but keeps the rest of the behaviour identical to the non-dilated setting.

### 3.2 Robust Quantum Eigenvalue Discrimination

The problem of deciding whether the eigenvalues of a Hamiltonian lie above or below a certain threshold, known as *eigenvalue discrimination*, finds widespread applications. For instance, the problem of determining whether the ground energy of a generic local Hamiltonian is  $< \lambda_a$  or  $> \lambda_b$  is known to be QMA-Complete [KKR06]. Nevertheless, quantum eigenvalue discrimination has been useful in preparing ground states of Hamiltonians. Generally, a variant of quantum phase estimation, which effectively performs a projection onto the eigenbasis of the underlying Hamiltonian is used to perform eigenvalue discrimination [GTC19]. Recently, it has been shown that QSVT can be used to approximate a projection onto the eigenspace of an operator by implementing a polynomial approximation of the *sign function* [LT20a]. This was then used to design improved quantum algorithms for ground state preparation. In our work, we will use this procedure to develop a more space-efficient variable stopping time matrix inversion algorithm in Section 3.3.

Given a threshold eigenvalue  $c$ , the *sign function* is defined as follows

$$\text{sign}(x - c) = \begin{cases} -1 & x < c \\ 0 & x = c \\ 1 & x > c. \end{cases} \quad (21)$$

Low and Chuang [LC17a] showed that there exists a polynomial approximation to  $\text{sign}(x - c)$  (based on its approximation of the *erf function*). We use the result of Ref. [MRTC21], where such a polynomial of even parity was considered.

**Lemma 20** (Polynomial approximation to the sign function [LC17a, Low17, MRTC21]). *Suppose  $\varepsilon \in (0, 1)$ ,  $\Delta \in (0, 1)$  and  $c \in (0, 1)$ . Then there exists an efficiently computable polynomial  $P_{\varepsilon, \Delta, c}(x)$  of degree  $l = \mathcal{O}(\frac{1}{\Delta} \log(1/\varepsilon))$  and of even parity such that*

1.  $\forall x \in [0, 1], |P_{\varepsilon, \Delta, c}(x)| \leq 1$
2.  $\forall x \in [0, 1] \setminus (c - \frac{\Delta}{2}, c + \frac{\Delta}{2}) : |P_{\varepsilon, \Delta, c}(x) - \text{sign}(c - x)| \leq \varepsilon$

Therefore, given a Hermitian matrix  $A$  with eigenvalues between  $[0, 1]$ , we can use QSVT to implement  $P_{\varepsilon, \Delta, c}(A)$  which correctly distinguishes between eigenvalues of  $A$  that are less than  $c - \Delta/2$  and those that are greater than  $c + \Delta/2$ .

For our purposes, we shall consider that we are given  $U_A$ , which is an  $(\alpha, a, \varepsilon)$  block-encoding of a Hermitian matrix  $A$ . Our goal would be to determine whether a certain eigenvalue  $\lambda$  satisfies  $0 \leq \lambda \leq \phi$

or  $2\phi \leq \lambda \leq 1$ . Since  $U_A$  (approximately) implements  $A/\alpha$ , the task can be rephrased as distinguishing whether an eigenvalue of  $A/\alpha$  is in  $[0, \phi/\alpha]$  or in  $[2\phi/\alpha, 1]$ .

For this task, we develop a robust version of the quantum eigenvalue discrimination problem which indicates the precision  $\varepsilon$  required to commit an error that is upper bounded by at most  $\delta$ . In order to bound the error, we first state a general lemma on the robustness of QSVT from [GSLW19]:

**Lemma 21** (Robustness of Quantum Singular Value Transformation, [GSLW19]). *Let  $P \in \mathbb{C}[x]$  be a polynomial of degree  $n$ . Let  $A, \tilde{A} \in \mathbb{C}^{N \times d}$  be matrices of spectral norm at most 1, such that*

$$\|A - \tilde{A}\| + \left\| \frac{A + \tilde{A}}{2} \right\|^2 \leq 1.$$

Then,

$$\|P^{SV}(A) - P^{SV}(\tilde{A})\| \leq n \sqrt{\frac{2}{1 - \left\| \frac{A + \tilde{A}}{2} \right\|^2}} \|A - \tilde{A}\|.$$

We shall use this result to show how errors propagate in the quantum eigenvalue discrimination problem. For the eigenvalue discrimination problem, we have the following theorem:

**Theorem 22** (Quantum Eigenvalue Discrimination using QSVT). *Suppose  $A$  is a Hermitian matrix such that its eigenvalues are in  $[0, 1]$  and  $|\lambda\rangle$  is an eigenvector of  $A$  with eigenvalue  $\lambda$ . Furthermore, let  $\phi, \delta \in (0, \frac{1}{2})$ . Suppose that for some  $\varepsilon$  satisfying*

$$\varepsilon \leq \frac{\phi^2 \delta}{8\alpha \log^2(2/\delta)}$$

*we have access to  $U_A$ , an  $(\alpha, a, \varepsilon)$ -block-encoding of a Hermitian matrix  $A$  implemented in time  $T_A$ . Then there exists a quantum algorithm  $QEVD(\phi, \delta)$  that implements the following transformation*

$$|0\rangle_C |\lambda\rangle_I \mapsto (\beta_0 |0\rangle_C + \beta_1 |1\rangle_C) |\lambda\rangle_I,$$

such that

- $\lambda \in [0, \phi] \implies |\beta_1| \leq \delta$
- $\lambda \in [2\phi, 1] \implies |\beta_0| \leq \delta$ .

This algorithm has a cost of

$$\mathcal{O}\left(\frac{\alpha}{\phi} \log\left(\frac{1}{\delta}\right) T_A\right)$$

*Proof.* Set  $c = \frac{3\phi}{2}, \Delta = \frac{\phi}{\alpha}$  and  $\varepsilon' = \frac{\delta}{2}$ . We assume  $U_A$  is an  $(\alpha, a, \varepsilon)$ -block encoding of some operator  $\tilde{A}$ , such that  $\|A - \tilde{A}\| \leq \varepsilon$ .

Apply the operator  $P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\tilde{A}/\alpha)$  using QSVT, controlled on an ancillary qubit in the  $|+\rangle$  state to  $|0\rangle_C |\lambda\rangle$ . Let us call this procedure  $W$ . That is,

$$W := (H \otimes I) \left( C - P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\tilde{A}/\alpha) \right) (H \otimes I),$$

that  $W$  acts as

$$W : |0\rangle |\lambda\rangle \mapsto \frac{1}{2} \left( \left(1 + P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\tilde{\lambda}/\alpha)\right) |0\rangle + \left(1 - P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\tilde{\lambda}/\alpha)\right) |1\rangle \right) |\lambda\rangle$$

From Lemma 20, the degree of the polynomial is  $\mathcal{O}\left(\frac{1}{\Delta} \log\left(\frac{1}{\varepsilon'}\right)\right)$ , and as many queries to  $U_A$  and  $U_A^\dagger$  are made. The error in this procedure can be computed as:

$$\begin{aligned}
& \left\| \text{sign}(c/\alpha - \lambda/\alpha) - P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\tilde{\lambda}/\alpha) \right\| \\
&= \left\| \text{sign}(c/\alpha - \lambda/\alpha) - P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\lambda/\alpha) + P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\lambda/\alpha) - P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\tilde{\lambda}/\alpha) \right\| \\
&\leq \underbrace{\left\| \text{sign}(c/\alpha - \lambda/\alpha) - P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\lambda/\alpha) \right\|}_{\leq \varepsilon'} + \left\| P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\lambda/\alpha) - P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\tilde{\lambda}/\alpha) \right\| \\
&\leq \varepsilon' + \frac{1}{\Delta} \log\left(\frac{1}{\varepsilon'}\right) \sqrt{\frac{2\varepsilon}{\alpha}} \quad [\text{By Lemma 21}] \\
&\leq \frac{\delta}{2} + \frac{\delta}{2} \quad \left[ \text{As } \varepsilon \leq \frac{\phi^2 \delta}{8\alpha \log^2(2/\delta)} \right] \\
&\leq \delta
\end{aligned}$$

Now depending on where  $\lambda$  lies, we have the following two cases:

**Case 1:**  $\lambda > \lambda_{\text{th}} + \frac{\phi}{2} = 2\phi$ . Observe that for this case,

$$P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\lambda/\alpha) \in [-1 - \delta, -1 + \delta].$$

Thus,  $|\beta_0| \leq \frac{\delta}{2}$ .

**Case 2:**  $\lambda \leq \lambda_{\text{th}} - \frac{\phi}{2} = \phi$ . Observe that for this case,

$$P_{\varepsilon', \Delta, \frac{\varepsilon}{\alpha}}(\lambda/\alpha) \in [1 - \delta, 1 + \delta].$$

Thus,  $|\beta_1| \leq \frac{\delta}{2}$ . □

When  $\phi \leq \lambda \leq 2\phi$ , the polynomial no longer approximates the sign function but rather is an approximation of the erf function. The algorithm  $\text{QEVD}(\phi, \delta)$  outputs a quantum state that is close to  $(\beta_0|0\rangle + \beta_1|1\rangle)|\lambda\rangle$ , for some non-zero  $\beta_0$  and  $\beta_1$ . By linearity, this algorithm also works when the input is a general superposition state instead of an eigenstate  $|\lambda\rangle$ .

Although [Theorem 22](#) assumes that  $A$  is Hermitian, this is without loss of generality. For any  $A \in \mathbb{R}^{N \times d}$ , we can construct the dilated matrix  $\bar{A} \in \mathbb{R}^{(N+d) \times (N+d)}$  by adding an extra qubit such that  $\bar{A} = |0\rangle\langle 1| \otimes A^T + |1\rangle\langle 0| \otimes A$ . Note that given an  $(\alpha, a, \varepsilon)$ -block encoding of  $A$ , from [Lemma 19](#), we can construct an  $(\alpha, a, \varepsilon)$  block encoding of  $\bar{A}$  that can be implemented at the same cost as  $A$ . The input state can be transformed accordingly.

Furthermore, if  $A$  has negative eigenvalues, it is possible to appropriately shift and rescale  $A$  such that they are in  $[0, 1]$ . For instance if the eigenvalues of  $A$  are in  $[-\|A\|, -\|A\|/\kappa] \cup [\|A\|/\kappa, \|A\|]$ , then for any  $\mu \geq \|A\|$ , the matrix  $(A + \mu I)/(2\mu)$  which can be implemented by linear combination of unitaries with cost  $\Theta(T_A)$ . Consequently, while implementing this algorithm, we shall consider any general  $A \in \mathbb{R}^{N \times d}$ , assuming that these transformations have already been made.

In [Section 3.3](#), we develop a variable stopping time quantum algorithm for matrix inversion using QSVT. In order to recast the usual matrix inversion to the VTAA framework, we need to be able to apply this algorithm to specific ranges of the eigenvalues of the matrix. This is achieved by applying a controlled QEVD algorithm, to determine whether the input eigenstate corresponds to an eigenvalue less than (or greater than) a certain threshold. Based on the outcome of controlled QEVD, the standard inversion algorithm is applied. These two steps correspond to sub-algorithms  $\mathcal{A}_j$  of the VTAA framework.

In prior works such as Refs. [[Amb12](#), [CKS17](#), [CGJ19](#)], gapped phase estimation (GPE) was used to implement this. GPE requires an additional register of  $\mathcal{O}(\log(\kappa) \log(1/\delta))$  qubits to store the estimated phases. For the whole VTAA procedure,  $\log \kappa$  such registers are needed. As a result, substituting GPE with QEVD, we save  $\mathcal{O}(\log^2(\kappa/\delta))$  qubits.

### 3.3 Variable-Time Quantum Algorithm for Matrix Inversion using QSVT

Matrix inversion by QSVT applies a polynomial approximation of  $f(x) = 1/x$ , satisfying the constraints laid out in [Section 2.3](#). Here, we make use of the result of [\[MRTC21\]](#) to implement  $A^+$ . We adapt their result to the scenario where we have an approximate block-encoding of  $A$  as input. Finally, we convert this to a variable stopping time quantum algorithm and apply VTAA to obtain a linear dependence on the condition number of  $A$ .

**Lemma 23** (Matrix Inversion polynomial, [\[MRTC21\]](#)). *Given  $\kappa \geq 1, \varepsilon \in \mathbb{R}^+$ , there exists a polynomial  $P_{\varepsilon, \kappa}^{MI}$  of degree  $\mathcal{O}(\kappa \log(\kappa/\varepsilon))$ , which is an  $\frac{\varepsilon}{2\kappa}$  approximation of the function  $f(x) = \frac{1}{2\kappa x}$  in the range  $\mathcal{D} := [\frac{1}{\kappa}, 1]$ . Also in this range  $P_{\varepsilon, \kappa}^{MI}$  is bounded from above by 1, i.e.  $\forall x \in \mathcal{D} : |P_{\varepsilon, \kappa}^{MI}(x)| \leq 1$ .*

**Theorem 24** (Inverting Normalized Matrices using QSVT). *Let  $A$  be a normalized matrix with singular values in the range  $[1/\kappa_A, 1]$  for some  $\kappa_A \geq 1$ . Let  $\delta \in (0, 1]$ . For some  $\varepsilon \leq \frac{\delta}{2\kappa_A^2}$ , let  $U_A$  be an  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$ , implemented in time  $T_A$ . Then we can implement a  $(2\kappa_A, a + 1, \delta)$ -block-encoding of  $A^+$  at a cost of*

$$\mathcal{O}\left(\kappa_A \alpha \log\left(\frac{\kappa_A}{\delta}\right) T_A\right)$$

*Proof.* We use the matrix inversion polynomial defined in [Lemma 23](#),  $P_{\phi, \kappa}^{MI}$  for this task, with  $\kappa = \kappa_A \alpha$  and an appropriate  $\phi$ . Suppose that the corresponding procedure produces a  $(\beta, a + 1, \delta)$ -block-encoding of  $A^+$ . The number of ancillae is increased by one because of the additional qubit required for the QSVT procedure.  $\beta$  and the error can be computed as follows: Let  $A' = \alpha (|0\rangle^{\otimes a} \otimes I) U_A (|0\rangle^{\otimes a} \otimes I)$ . From [Definition 1](#) we have  $\|A - A'\| \leq \varepsilon$ . From the mean value theorem and Lipschitz continuity condition, it follows that  $\|A^+ - A'^+\| \leq \varepsilon \kappa_A^2$ .

$$\begin{aligned} \left\| A^+ - \beta P_{\phi, \kappa}^{MI} \left( \frac{A'}{\alpha} \right) \right\| &= \left\| A^+ - A'^+ + A'^+ - \beta P_{\phi, \kappa}^{MI} \left( \frac{A'}{\alpha} \right) \right\| \\ &\leq \|A^+ - A'^+\| + \left\| A'^+ - \beta P_{\phi, \kappa}^{MI} \left( \frac{A'}{\alpha} \right) \right\| \\ &\leq \varepsilon \kappa_A^2 + \underbrace{\left\| \frac{2\kappa (A'/\alpha)^+}{\alpha} - \beta P_{\phi, \kappa}^{MI} \left( \frac{A'}{\alpha} \right) \right\|}_{=: e} \end{aligned}$$

From [Lemma 23](#) it follows that  $P_{\phi, \kappa}^{MI}$  is  $\phi/2\kappa$  close to  $f(x) = 1/2\kappa x$ . If we pick  $\beta = \frac{2\kappa}{\alpha}$ , it follows that

$$e = \frac{2\kappa}{\alpha} \left\| f \left( \frac{A'}{\alpha} \right) - P_{\phi, \kappa}^{MI} \left( \frac{A'}{\alpha} \right) \right\| \leq \frac{2\kappa}{\alpha} \frac{\phi}{2\kappa} = \frac{\phi}{\alpha}$$

Pick  $\phi = \frac{\alpha\delta}{2}$ . This implies  $e = \frac{\delta}{2}$ . Also,  $\varepsilon \kappa_A^2 \leq \frac{\delta}{2}$  by assumption. Thus, the error is bounded by  $\delta$  from above.  $\square$

As a corollary, suppose that the input matrix is not normalized (i.e.  $\|A\| \neq 1$ ). We can still use the above procedure with some tweaks.

**Corollary 25** (Matrix Inversion using QSVT). *Let  $A \in \mathbb{R}^{N \times d}$  be a matrix with singular values in the range  $\left[ \frac{\|A\|}{\kappa_A}, \|A\| \right]$  for some  $\kappa_A \geq 1$ . Let  $\delta \in (0, 1]$ . Let  $U_A$  be an  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$  implemented in time  $T_A$ , such that*

$$\varepsilon \leq \frac{\delta \|A\|^2}{2\kappa_A^2}$$

*Then we can implement a  $(2\kappa_A/\|A\|, a + 1, \delta)$ -block-encoding of  $A^+$  at a cost of*

$$\mathcal{O}\left(\frac{\kappa_A \alpha}{\|A\|} \log\left(\frac{\kappa_A}{\delta \|A\|}\right) T_A\right). \quad (22)$$

*Proof.* We can interpret  $U_A$  it as a  $\left(\frac{\alpha}{\|A\|}, a, \frac{\varepsilon}{\|A\|}\right)$ -block-encoding of  $A' := \frac{A}{\|A\|}$ . This implies  $\|A'\| = 1$  and  $\sigma(A') \in \left[\frac{1}{\kappa_A}, 1\right]$ . Invoking [Theorem 24](#) using the matrix  $A'$ , with  $U_A$  and  $\kappa_A$ , we get a  $(2\kappa_A, a + 1, 2\varepsilon\kappa_A^2/\|A\|)$ -block-encoding of  $A'^+$  implemented at a cost of

$$\mathcal{O}\left(\frac{\kappa_A\alpha}{\|A\|} \log\left(\frac{\kappa_A}{\delta\|A\|}\right) T_A\right).$$

Now, we have  $A'^+ = \left(\frac{A}{\|A\|}\right)^+ = \|A\|A^+$ , and so the block-encoding we obtained can be reinterpreted as a  $(2\kappa_A/\|A\|, a + 1, 2\varepsilon\kappa_A^2/\|A\|^2)$ -block-encoding of  $A^+$ .  $\square$

Next, we design a map  $W(\gamma, \delta)$  that uses QSVT to invert the singular values of a matrix if they belong to a particular domain. This helps us recast the usual matrix inversion algorithm as a variable-stopping-time algorithm and will be a key subroutine for boosting the success probability of this algorithm using VTAA. This procedure was also used in Refs. [\[CKS17, CGJ19\]](#) for the quantum linear systems algorithms.

**Theorem 26** (Efficient inversion of block-encoded matrix). *Let  $A$  be a normalized matrix with singular values in the range  $[1/\kappa, 1]$ , for some  $\kappa \geq 1$ . Let  $\delta \in (0, 1]$ ;  $0 < \gamma \leq 1$ . Let  $U_A$  be an  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$  implemented in time  $T_A$ , such that  $\varepsilon \leq \delta\gamma^2/2$ . Then for any quantum state  $|b\rangle$  that is spanned by the singular vectors of  $A$  corresponding to the singular values in the range  $[\gamma, 1]$ , there exists a unitary  $W(\gamma, \delta)$  that implements*

$$W(\gamma, \delta) : |0\rangle_F |0\rangle_Q |b\rangle_I \mapsto \frac{1}{a_{\max}} |1\rangle_F |0\rangle_Q f(A) |b\rangle_I + |0\rangle_F |\perp\rangle_{QI} \quad (23)$$

where  $a_{\max} = \mathcal{O}(\kappa_A)$  is a constant independent of  $\gamma$ ,  $|\perp\rangle_{QI}$  is an unnormalized quantum state orthogonal to  $|0\rangle_Q$  and  $\|f(A)|b\rangle - A^+|b\rangle\| \leq \delta$ . Here  $F$  is the flag register of 1 qubit,  $Q$  is the ancilla register of  $\alpha$  qubits, and  $I$  is the input register of  $\log N$  qubits. This unitary has a cost

$$\mathcal{O}\left(\frac{\alpha}{\gamma} \log\left(\frac{1}{\gamma\delta}\right) T_A\right) \quad (24)$$

*Proof.* Since we only need to invert the singular values in a particular range, we can use the procedure in [Theorem 24](#) with  $\kappa_A$  modified to the restricted range. That gives us the description of a quantum circuit  $\widetilde{W}(\gamma, \delta)$  that can implement the following map

$$\widetilde{W}(\gamma, \delta) : |b\rangle_I |0\rangle_Q \mapsto \frac{\gamma}{2} f(A) |b\rangle_I |0\rangle_Q + |\perp\rangle_{QI}, \quad (25)$$

where  $|\perp\rangle$  is an unnormalized state with no component along  $|0\rangle_Q$ . This has the same cost as [Equation 24](#). Here  $\|f(A)|\psi\rangle - A^+|\psi\rangle\| \leq \delta$  whenever  $|\psi\rangle$  is a unit vector in the span of the singular vectors of  $A$  corresponding to the singular values in  $[\gamma, 1]$ . This follows from the sub-multiplicativity property of the matrix-vector product.

Next, we must transform the amplitude of the good part of the state to  $\Theta(\kappa)$ , independent of  $\gamma$ . To achieve this, we will have to flag it with an ancillary qubit to use a controlled rotation to modify the amplitude. Thus we add a single qubit  $|0\rangle_F$  register and flip this register controlled on register  $Q$  being in the state  $|0\rangle$  (the good part). This gives us the transformation

$$\widetilde{W}'(\gamma, \delta) : |0\rangle_F |b\rangle_I |0\rangle_Q \mapsto \frac{\gamma}{2} |1\rangle_F f(A) |b\rangle_I |0\rangle_Q + |0\rangle_F |\perp\rangle_{QI} \quad (26)$$

Then we use a controlled rotation to replace the amplitude  $\gamma/2$  with some constant  $a_{\max}^{-1}$  which is independent of  $\gamma$ , which is achieved by introducing the relevant phase to the flag space

$$|1\rangle_F \mapsto \frac{2}{\gamma a_{\max}} |1\rangle_F + \sqrt{1 - \frac{4}{\gamma^2 a_{\max}^2}} |0\rangle_F. \quad (27)$$

This gives us the desired  $W(\gamma, \delta)$  as in [Equation 23](#).  $\square$

Given such a unitary  $W(\gamma, \delta)$ , Ref. [CGJ19] laid out a procedure for a variable time quantum algorithm  $\mathcal{A}$  that takes as input the block encoding of an  $N \times d$  matrix  $A$ , and a state preparation procedure  $U_b : |0\rangle^{\otimes n} \mapsto |b\rangle$ , and outputs a quantum state that is a bounded distance away from  $A^+ |b\rangle / \|A^+ |b\rangle\|$ . In order to determine the branches of the algorithm on which to apply VTAA at a particular iteration, [CKS17, CGJ19, Amb12] use the technique of gapped phase estimation, which given a unitary  $U$ , a threshold  $\phi$  and one of its eigenstate  $|\lambda\rangle$ , decides if the corresponding eigenvalue is a bounded distance below the threshold, or a bounded distance above it. In this work we replace gapped phase estimation with the QEVD algorithm (Theorem 22), which allows for saving on  $\mathcal{O}(\log^2(\kappa/\delta))$  qubits.

**The Variable time Algorithm:** This algorithm will be a sequence of  $m$  sub-algorithms  $\mathcal{A} = \mathcal{A}_m \cdot \mathcal{A}_{m-1} \cdot \dots \cdot \mathcal{A}_1$ , where  $m = \lceil \log \kappa \rceil + 1$ . The overall algorithm acts on the following registers:

- $m$  single qubit clock registers  $C_i : i \in [m]$ .
- An input register  $I$ , initialized to  $|0\rangle^{\otimes s}$ .
- Ancillary register space  $Q$  for the block encoding of  $A$ , initialized to  $|0\rangle^{\otimes a}$ .
- A single qubit flag register  $|0\rangle_F$  used to flag success of the algorithm.

Once we have prepared the above state space, we use the state preparation procedure to prepare the state  $|b\rangle$ . Now we can define how each  $\mathcal{A}_j$  acts on the state space. Let  $\varepsilon' = \frac{\delta}{a_{\max} m}$ . Then the action of  $\mathcal{A}_j$  can be broken down into two parts:

1. If  $C_{j-1} \dots C_1$  is in state  $|0\rangle^{\otimes(j-1)}$ , apply QEVD( $2^{-j}, \varepsilon'$ ), (Theorem 22) to the state  $|b\rangle$ . The output is to be written to the clock register  $C_j$ .
2. If the state of  $C_j$  is now  $|1\rangle$ , apply  $W(2^{-j}, \varepsilon')$  to  $I \otimes F \otimes Q$ .

Additionally, we would also need algorithms  $\mathcal{A}' = \mathcal{A}'_m \cdot \dots \cdot \mathcal{A}'_1$  which are similar to  $\mathcal{A}$ , except that in Step 2, it implements  $W'$  which sets the flag register to 1. That is,

$$W' |b\rangle_I |0\rangle_F |0\rangle_Q = |b\rangle_I |1\rangle_F |0\rangle_Q.$$

Now we are in a position to define the variable time quantum linear systems algorithm using QSVT.

**Theorem 27** (Variable Time Quantum Linear Systems Algorithm Using QSVT). *Let  $\varepsilon, \delta > 0$ . Suppose  $A$  is a normalized  $N \times d$  matrix with its singular values between  $[1/\kappa, 1]$ . Suppose that for*

$$\varepsilon \leq \frac{\delta}{32\alpha\kappa^3 \log^3(2\kappa/\delta)},$$

*we have access to  $U_A$  which is an  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$ , implemented with cost  $T_A$ . Furthermore, suppose there exists a procedure to prepare the state  $|b\rangle$  which is spanned by the left singular vectors of  $A$ . Then there exists a variable time quantum algorithm that outputs a state that is  $\delta$ -close  $\frac{A^+ |b\rangle}{\|A^+ |b\rangle\|}$  at a cost of*

$$\mathcal{O}\left(\kappa \left(\alpha T_A \log\left(\frac{\kappa}{\delta}\right) + T_b\right) \log \kappa\right) \quad (28)$$

*using  $\mathcal{O}(\log \kappa)$  additional qubits.*

*Proof.* The correctness of the algorithm is similar to that of Refs. [CKS17, CGJ19], except here we use QEVD instead of gapped phase estimation. The upper bound in the precision  $\varepsilon$ , follows from Theorem 22, which determines the precision in block-encoding of  $A$  needed to implement QEVD with precision  $\varepsilon'$ . Here we will describe the overall complexity of this algorithm and refer the readers to Refs. [CKS17, CGJ19] for details on its correctness.

According to [Lemma 6](#), we need  $T_{\max}$  (the maximum time any of the sub-algorithms  $\mathcal{A}_j$  take),  $\|T\|_2^2$  (the  $\ell_2$ -averaged stopping time of the sub-algorithms), and  $\sqrt{p_{\text{succ}}}$  (the square root of the success probability.)

Now each sub-algorithm consists of two steps, implementing QEVD with precision  $2^{-j}$  and error  $\varepsilon' = \frac{\delta}{ma_{\max}}$ , followed by  $W(2^{-j}, \varepsilon')$ .

From [Theorem 22](#), the first step costs

$$\mathcal{O}\left(\alpha T_A 2^j \log\left(\frac{1}{\varepsilon'}\right)\right), \quad (29)$$

and the cost of implementing  $W(2^{-j}, \varepsilon')$  is as described in [Equation 24](#). Thus the overall cost of  $\mathcal{A}_j$ , which is the sum of these two costs, turns out to be

$$\mathcal{O}\left(\alpha T_A 2^j \log\left(\frac{2^j}{\varepsilon'}\right)\right) \quad (30)$$

Note that the time  $t_j$  required to implement  $\mathcal{A}_j \dots \mathcal{A}_1$  is also the same as [Equation 30](#). Also,

$$\begin{aligned} T_{\max} &= \max_j t_j \\ &= \max_j \mathcal{O}\left(\alpha T_A 2^j \log\left(\frac{2^j}{\varepsilon'}\right)\right) \\ &= \mathcal{O}\left(\alpha T_A \kappa \log\left(\frac{\kappa}{\varepsilon'}\right)\right) \\ &= \mathcal{O}\left(\alpha T_A \kappa \log\left(\frac{\kappa \log(\kappa)}{\delta}\right)\right). \end{aligned}$$

The  $\|T\|_2^2$  is dependent on the probability that  $\mathcal{A}$  stops at the  $j^{\text{th}}$  step. This is given by  $p_j = \left\| \Pi_{C_j} \mathcal{A}_j \dots \mathcal{A}_1 |\psi\rangle_I |0\rangle_{CFPQ} \right\|^2$ , where  $\Pi_{C_j}$  is the projector on  $|1\rangle_{C_j}$ , the  $j^{\text{th}}$  clock register. From this,  $\|T\|_2^2$  can be calculated as

$$\begin{aligned} \|T\|_2^2 &= \sum_j p_j t_j^2 \\ &= \sum_j \left\| \Pi_{C_j} \mathcal{A}_j \dots \mathcal{A}_1 |\psi\rangle_I |0\rangle_{CFPQ} \right\|^2 t_j^2 \\ &= \sum_k |c_k|^2 \sum_j \left( \left\| \Pi_{C_j} \mathcal{A}_j \dots \mathcal{A}_1 |v_k\rangle_I |0\rangle_{CFPQ} \right\|^2 t_j^2 \right) \\ &= \mathcal{O}\left(\alpha^2 T_A^2 \sum_k \log^2\left(\frac{1}{\sigma_k \varepsilon'}\right) \frac{|c_k|^2}{\sigma_k^2}\right) \end{aligned}$$

This tells us that

$$\|T\|_2 = \mathcal{O}\left(\alpha T_A \log\left(\frac{\kappa \log \kappa}{\delta}\right) \sqrt{\sum_k \frac{|c_k|^2}{\sigma_k^2}}\right). \quad (31)$$

Next we calculate the success probability.

$$\sqrt{p_{\text{succ}}} = \left\| \Pi_F \frac{A^{-1}}{\alpha_{\max}} |b\rangle_I |\phi\rangle_{CFPQ} \right\| + \mathcal{O}(m\varepsilon')$$



$$\begin{aligned}
&= \frac{1}{\alpha_{\max}} \sqrt{\sum_j \frac{|c_j|^2}{\sigma_j^2}} + \mathcal{O}\left(\frac{\delta}{\alpha_{\max}}\right) \\
&= \Omega\left(\frac{1}{\kappa} \sqrt{\sum_j \frac{|c_j|^2}{\sigma_j^2}}\right)
\end{aligned}$$

Given these we can use [Lemma 6](#) to write the final complexity of matrix inversion with VTAA as follows.

$$\begin{aligned}
&T_{\max} + T_b + \frac{(\|T\|_2 + T_b) \log(T'_{\max})}{\sqrt{p_{\text{succ}}}} \\
&= \mathcal{O}\left(\kappa \log \kappa \left(\alpha T_A \log\left(\frac{\kappa}{\delta}\right) + T_b\right)\right)
\end{aligned}$$

□

The overall complexity is better by a log factor and requires  $\mathcal{O}(\log^2(\kappa/\delta))$  fewer additional qubits as compared to the variable time algorithms in Refs. [\[CKS17, CGJ19\]](#).

### 3.4 Positive and Negative Powers of Matrices using QSVT

Given an approximate block encoding of a matrix  $A$ , in this section we will consider the problem of preparing a block encoding of  $A^c$  and  $A^{-c}$ , where  $c \in (0, 1)$ . These procedures will be used to develop algorithms for  $\ell_2$ -regularized versions of WLS and GLS. We will directly use the results of [\[GSLW19\]](#).

**Lemma 28** (Polynomial approximations of positive power function, [\[GSLW19\]](#)). *Let  $\Delta, \varepsilon \in (0, \frac{1}{2}]$ ,  $c \in (0, 1]$  and let  $f(x) := \frac{1}{2}x^c$ , then there exist even/odd polynomials  $P, P' \in \mathbb{R}[x]$ , such that  $\|P - f\|_{[\Delta, 1]} \leq \varepsilon$ ,  $\|P\|_{[-1, 1]} \leq 1$  and similarly  $\|P' - f\|_{[\Delta, 1]} \leq \varepsilon$ ,  $\|P'\|_{[-1, 1]} \leq 1$ , moreover the degree of the polynomials are  $\mathcal{O}(\frac{1}{\Delta} \log(\frac{1}{\varepsilon}))$*

**Theorem 29** (Positive fractional powers of a Normalized Matrix Using QSVT). *Let  $c \in (0, 1)$  be a constant, and  $\delta \in (0, 1]$ . Let  $A$  be a matrix with singular values in  $[1/\kappa, 1]$ , and  $U_A$  be a  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$  implemented in time  $T_A$ , such that  $\varepsilon \leq \frac{\delta}{2c\kappa^{1-c}}$ . Then we can construct a  $(2\alpha^c, a + 1, \delta)$ -block-encoding of  $A^c$  at a cost  $\mathcal{O}(\alpha\kappa \log(\alpha/\delta) T_A)$ .*

*Proof.* Let  $A'$  be the scaled encoded block in  $U_A$ , which gives us  $\|A - A'\| \leq \varepsilon$ . It follows from Lipschitz continuity condition and the mean value theorem that

$$\|A^c - A'^c\| \leq c\varepsilon\kappa^{1-c}$$

Let  $\gamma \in (0, \frac{1}{2}]$ . From [Lemma 28](#), there exists a polynomial  $P(x)$  of degree  $\mathcal{O}(\alpha\kappa \log(1/\gamma))$  which is  $\gamma$  close to  $f(x) = \frac{1}{2}x^c$  in the domain  $[1/(\alpha\kappa), 1]$ . Assume that the final unitary is a  $(\eta, a + 1, \delta)$  block-encoding of  $A^c$ . We can compute  $\eta$  and  $\delta$  as:

$$\begin{aligned}
\left\|A^c - \eta P\left(\frac{A'}{\alpha}\right)\right\| &= \left\|A^c - A'^c + A'^c - \eta P\left(\frac{A'}{\alpha}\right)\right\| \\
&\leq \|A^c - A'^c\| + \left\|A'^c - \eta P\left(\frac{A'}{\alpha}\right)\right\| \\
&\leq c\varepsilon\kappa^{1-c} + \left\|2\alpha^c f\left(\frac{A'}{\alpha}\right) - \eta P\left(\frac{A'}{\alpha}\right)\right\| \\
&\leq c\varepsilon\kappa^{1-c} + 2\alpha^c \left\|f\left(\frac{A'}{\alpha}\right) - P\left(\frac{A'}{\alpha}\right)\right\| \quad (\text{fixing } \eta = 2\alpha^c)
\end{aligned}$$

$$\begin{aligned}
&\leq c\varepsilon\kappa^{1-c} + 2\alpha^c\gamma \\
&\leq \delta \quad (\text{fixing } \gamma = \delta/(4\alpha^c))
\end{aligned}$$

This concludes the proof.  $\square$

So for any general matrix  $A$  with singular values between  $[\|A\|/\kappa, \|A\|]$  we can extend the above result to the following corollary.

**Corollary 30** (Positive fractional powers of a Matrix using QSVT). *Let  $c \in (0, 1)$  be a constant. Let  $A$  be a matrix with condition number  $\kappa$ . Let  $U_A$  be a  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$  implemented in time  $T_A$ , such that*

$$\varepsilon \leq \frac{\delta\|A\|^{1-c}}{2c\kappa^{1-c}}$$

Then we can construct a  $(2\alpha^c, a + 1, \delta)$ -block-encoding of  $A^c$  at a cost

$$\mathcal{O}\left(\frac{\alpha\kappa}{\|A\|} \log\left(\frac{\alpha}{\delta}\right) T_A\right)$$

*Proof.* We can interpret  $U_A$  as a  $(\alpha/\|A\|, a, \varepsilon/\|A\|)$ -block-encoding of  $A' = A/\|A\|$ . And as  $A'$  is normalized, invoking [Theorem 29](#) gives us  $U_c$ , a

$$\left(\frac{2\alpha^c}{\|A\|^c}, a + 1, \frac{2c\varepsilon\kappa^{1-c}}{\|A\|}\right)$$

block-encoding of  $A'^c$ , at a cost of

$$\mathcal{O}\left(\frac{\alpha\kappa}{\|A\|} \log\left(\frac{\alpha}{\gamma\|A\|}\right) T_A\right)$$

As  $A^c = \|A\|^c A'^c$ , we can interpret the unitary  $U_c$  as a

$$\left(2\alpha^c, a + 1, \frac{2c\varepsilon\kappa^{1-c}}{\|A\|^{1-c}}\right)$$

-block-encoding of  $A^c$ .  $\square$

Similarly, we can implement negative powers of block encodings.

**Lemma 31** (Polynomial approximations of negative power functions, [\[GSLW19\]](#)). *Let  $\varepsilon, \delta \in (0, \frac{1}{2}]$ ,  $c > 0$  and let  $f(x) := \frac{\delta^c}{2}x^{-c}$ , then there exist even/odd polynomials  $P_{c,\varepsilon,\delta}, P'_{c,\varepsilon,\delta} \in \mathbb{R}[x]$  such that  $\|P_{c,\varepsilon,\delta} - f\|_{[\delta,1]} \leq \varepsilon$ ,  $\|P_{c,\varepsilon,\delta}\|_{[-1,1]} \leq 1$  and  $\|P'_{c,\varepsilon,\delta} - f\|_{[\delta,1]} \leq \varepsilon$ ,  $\|P'_{c,\varepsilon,\delta}\|_{[-1,1]} \leq 1$ . Moreover the degree of the polynomials are  $\mathcal{O}\left(\frac{\max(1,c)}{\delta} \log\left(\frac{1}{\varepsilon}\right)\right)$ .*

**Theorem 32** (Negative fractional powers of a normalized matrix using QSVT). *Let  $c \in (0, 1)$  be some constant and  $\delta \in (0, 1]$  Let  $A$  be a normalized matrix with condition number  $\kappa \geq 2$ , and singular values in the range  $[1/\kappa, 1]$ . Let  $U_A$  be a  $(\alpha, a, \varepsilon)$ -block-encoding of a matrix  $A$ , implemented in time  $T_A$  such that*

$$\varepsilon \leq \frac{\delta}{2c\kappa^{c+1}}$$

. Then we can construct a  $(2\kappa^c, a + 1, \delta)$ -block-encoding of  $A^{-c}$  at a cost of

$$\mathcal{O}\left(\alpha\kappa \log\left(\frac{\kappa}{\delta}\right) T_A\right)$$

*Proof.* Let  $\gamma, \varphi \in (0, \frac{1}{2}]$ . Consider the polynomial in [Lemma 31](#),  $P = P_{c, \gamma, \varphi}$ . This has degree  $\mathcal{O}\left(\frac{1}{\varphi} \log \frac{1}{\gamma}\right)$ , and is  $\gamma$ -close to  $f(x) = \varphi^c x^{-c}/2$ . Let  $A'$  be the scaled encoded block in  $U_A$ , which gives us  $\|A - A'\| \leq \varepsilon$ . It follows from Lipschitz continuity condition and the mean value theorem that

$$\|A^{-c} - A'^{-c}\| \leq c\varepsilon\kappa^{c+1}$$

Say the final unitary is a  $(\eta, a + 1, \delta)$ -block-encoding of  $A^{-c}$ . we can compute  $\eta$  and  $\delta$  as:

$$\begin{aligned} \left\| A^{-c} - \eta P\left(\frac{A'}{\alpha}\right) \right\| &= \left\| A^{-c} - A'^{-c} + A'^{-c} - \eta P\left(\frac{A'}{\alpha}\right) \right\| \\ &\leq \|A^{-c} - A'^{-c}\| + \left\| A'^{-c} - \eta P\left(\frac{A'}{\alpha}\right) \right\| \\ &\leq c\varepsilon\kappa^{c+1} + \left\| \frac{2}{\alpha^c \varphi^c} f\left(\frac{A'}{\alpha}\right) - \eta P\left(\frac{A'}{\alpha}\right) \right\| \\ &\leq c\varepsilon\kappa^{c+1} + \frac{2}{\alpha^c \varphi^c} \left\| f\left(\frac{A'}{\alpha}\right) - P\left(\frac{A'}{\alpha}\right) \right\| \quad (\text{fixing } \eta = 2(\alpha\varphi)^{-c}) \\ &\leq c\varepsilon\kappa^{c+1} + \frac{2\gamma}{\alpha^c \varphi^c} \end{aligned}$$

As  $\alpha \geq \|A\| = 1$  and  $\kappa \geq 2$ , we can choose  $\varphi = (\alpha\kappa)^{-1}$ . And choosing  $\gamma = \delta/(4\kappa^c)$ , we can bound the error with  $\delta$ ,

$$\left\| A^{-c} - \eta P\left(\frac{A'}{\alpha}\right) \right\| \leq \delta \quad (32)$$

Finally, we have  $\eta = 2\kappa^c$ , and the degree of the polynomial as  $\mathcal{O}(\alpha\kappa \log(\kappa/\delta))$ .  $\square$

Similar to the positive powers case, for any general matrix  $A$  with singular values between  $[\|A\|/\kappa, \|A\|]$  we can extend the above result to the following corollary.

**Corollary 33** (Negative fractional powers of a matrix using QSVT). *Let  $c \in (0, 1)$  be some constant. Let  $A$  be a matrix with condition number  $\kappa \geq 2$ , whose singular values lie in  $[\frac{\|A\|}{\kappa}, \|A\|]$ . Let  $U_A$  be a  $(\alpha, a, \varepsilon)$ -block-encoding of a matrix  $A$ , implemented in time  $T_A$  such that*

$$\varepsilon \leq \frac{\delta \|A\|^{c+1}}{2c\kappa^{c+1}}$$

*Then we can implement a  $(2\kappa^c/\|A\|^c, a + 1, \delta)$ -block-encoding of  $A^{-c}$  at a cost of*

$$\mathcal{O}\left(\frac{\alpha\kappa}{\|A\|} \log\left(\frac{\kappa}{\delta\|A\|}\right) T_A\right) \quad (33)$$

*Proof.* We can interpret  $U$  as a  $(\alpha/\|A\|, a, \varepsilon/\|A\|)$ -block-encoding of  $A' = A/\|A\|$ . And as  $A'$  is normalized, by invoking [Theorem 32](#), we get  $U_c$ , a  $(2\kappa^c, a + 1, 2c\varepsilon\kappa^{c+1}/\|A\|)$ -block-encoding of  $A'^{-c}$ , with complexity

$$\mathcal{O}\left(\frac{\alpha\kappa}{\|A\|} \log\left(\frac{\|A\|}{2c\varepsilon\kappa^c}\right) T_A\right).$$

As  $A'^{-c} = \|A\|^c A^{-c}$ , we can interpret the unitary  $U_c$  as a

$$\left(\frac{2\kappa^c}{\|A\|^c}, a + 1, \frac{2c\varepsilon\kappa^{c+1}}{\|A\|^{c+1}}\right)$$

block-encoding of  $A^{-c}$ .  $\square$

Having discussed the necessary algorithmic primitives, we are now in a position to design quantum algorithms for linear regression with general  $\ell_2$ -regularization. We will first deal with ordinary least squares followed by weighted and generalized least squares.

## 4 Quantum Least Squares with General $\ell_2$ -Regularization

In this section, we derive the main results of our paper, namely quantum algorithms for quantum ordinary least squares (OLS), quantum weighted least squares (WLS) and quantum generalized least squares (GLS) with  $\ell_2$ -regularization.

### 4.1 Quantum Ordinary Least Squares

Given  $N$  data points  $\{a_i, b_i\}_{i=1}^N$  such that  $a_i \in \mathbb{R}^d$  and  $b_i \in \mathbb{R}$ , the objective of linear regression is to find  $x \in \mathbb{R}^d$  that minimizes the loss function

$$\mathcal{L}_O = \sum_{j=1}^N (x^T a_j - b_j)^2. \quad (34)$$

Consider the  $N \times d$  matrix  $A$  (known as the data matrix) such that the  $i^{\text{th}}$  row of  $A$  is the vector  $a_i$  transposed and the column vector  $b = (b_1 \cdots b_N)^T$ . Then, the solution to the OLS problem is given by  $x = (A^T A)^{-1} A^T b = A^+ b$ .

For the  $\ell_2$ -regularized version of the OLS problem, a penalty term is added to its objective function. This has the effect of shrinking the singular values of  $A$ . This helps overcome problems such as rank deficiency and *overfitting* for the OLS problem. The loss function to be minimized is of the form

$$\|Ax - b\|_2^2 + \|Lx\|_2^2, \quad (35)$$

where  $L$  is the  $N \times d$  penalty matrix and  $\lambda > 0$  is the optimal regularizing parameter. The solution  $x \in \mathbb{R}^d$  satisfies

$$x = (A^T A + \lambda L^T L)^{-1} A^T b. \quad (36)$$

Therefore, for quantum ordinary least squares with general  $\ell_2$ -regularization, we assume that we have access to approximate block-encodings of the data matrix  $A$ ,  $L$  and a procedure to prepare the quantum state  $|b\rangle = \sum_{j=1}^N b_j |j\rangle / \|b\|$ . Our algorithm outputs a quantum state that is close to

$$|x\rangle = \frac{(A^T A + \lambda L^T L)^{-1} A^T |b\rangle}{\|(A^T A + \lambda L^T L)^{-1} A^T |b\rangle\|}. \quad (37)$$

In order to implement a quantum algorithm that implements this, a straightforward approach would be the following: We first construct block-encodings of  $A^T A$  and  $L^T L$ , given block encodings of  $A$  and  $L$ , respectively (Using [Lemma 15](#)). We could then implement a block-encoding of  $A^T A + \lambda L^T L$  using these block encodings (By [Lemma 13](#)). On the other hand, we could also prepare a quantum state proportional to  $A^T |b\rangle$  by using the block-encoding for  $A$  and the unitary preparing  $|b\rangle$ . Finally, using the block encoding of  $A^T A + \lambda L^T L$ , we could implement a block-encoding of  $(A^T A + \lambda L^T L)^{-1}$  (using [Corollary 25](#)) and apply it to the state  $A^T |b\rangle$ . Although this procedure would output a quantum state close to  $|x\rangle$ , it is not efficient. It is easy to see that the inverse of  $A^T A + \lambda L^T L$ , would be implemented with a complexity that has a quadratic dependence on the condition numbers of  $A$  and  $L$ . This would be undesirable as it would perform worse than the unregularized quantum least squares algorithm, where one is able to implement  $A^+$  directly. However, it is possible to design a quantum algorithm that performs significantly better than this.

The first observation is that it is possible to recast this problem as finding the pseudoinverse of some augmented matrix. Given the data matrix  $A \in \mathbb{R}^{N \times d}$ , the regularizing matrix  $L \in \mathbb{R}^{N \times d}$ , let us define the following augmented matrix

$$A_L := \begin{pmatrix} A & 0 \\ \sqrt{\lambda} L & 0 \end{pmatrix}. \quad (38)$$

It is easy to see that the top left block of  $A_L^\dagger = (A^T A + \lambda L^T L)^{-1} A^T$ , which is the required linear transformation to be applied to  $b$ . Consequently, our strategy would be to implement a block-encoding of  $A_L$ , given block-encodings of  $A$  and  $L$ . Following this, we use matrix inversion by QSVT to implement  $A_L^\dagger |b\rangle |0\rangle$ . The first register is then left in the quantum state given in [Equation 37](#).

Before this we obtain the ratio between the maximum and minimum non-zero singular value of the matrix  $A_L$  via the following lemma:

**Lemma 34** (Condition number and Spectral Norm of  $A_L$ ). *Let the data matrix  $A$  and the penalty matrix  $L$  have spectral norms  $\|A\|$  and  $\|L\|$  respectively. Furthermore, suppose their condition numbers be upper bounded by  $\kappa_A$  and  $\kappa_L$ . Then the ratio between the maximum and minimum (non-zero) singular value of  $A_L$  is upper bounded by*

$$\kappa = \kappa_A \kappa_L \sqrt{\frac{\|A\|^2 + \lambda \|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|L\|^2}}$$

We can also bound the spectral norm as

$$\|A_L\| \leq \|A\| + \sqrt{\lambda} \|L\|$$

*Proof.* To bound the spectral norm and condition number of  $A_L$ , consider the eigenvalues of the following matrix:

$$A_L^T A_L = \begin{pmatrix} A^T A + \lambda L^T L & 0 \\ 0 & 0 \end{pmatrix}$$

This implies that the non-zero eigenvalues of  $A_L^T A_L$  are the same as those of  $A^T A + \lambda L^T L$ . Therefore, using Triangle inequality, the spectral norm of  $A_L$  can be upper-bounded as follows:

$$\begin{aligned} \|A_L\| &= \sqrt{\|A_L^T A_L\|} \\ &= \sqrt{\|A^T A + \lambda L^T L\|} \\ &\leq \sqrt{\|A^T A\| + \lambda \|L^T L\|} \\ &= \sqrt{\|A\|^2 + \lambda \|L\|^2} \\ &\leq \|A\| + \sqrt{\lambda} \|L\| \end{aligned}$$

Also, we have that the minimum singular value of  $A$ ,  $\sigma_{\min}(A) = \|A\|/\kappa_A$  and the minimum singular value of  $L$ ,  $\sigma_{\min}(L) = \|L\|/\kappa_L$ . So by Weyl's inequality, the minimum non-zero singular value of  $A_L$  is lower bounded by

$$\begin{aligned} \sigma_{\min}(A_L) &\geq \sqrt{\sigma_{\min}(A)^2 + \lambda \sigma_{\min}(L)^2} \\ &= \sqrt{\frac{\|A\|^2}{\kappa_A^2} + \lambda \frac{\|L\|^2}{\kappa_L^2}} \end{aligned}$$

Thus,

$$\frac{\sigma_{\max}(A_L)}{\sigma_{\min}(A_L)} \leq \kappa = \kappa_A \kappa_L \sqrt{\frac{\|A\|^2 + \lambda \|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|L\|^2}}.$$

□

It might be possible that  $|b\rangle$  does not belong to the row space of  $(A^T A + \lambda L^T L)^{-1} A^T$  which is equivalent to saying  $|b\rangle |0\rangle$  may not lie in  $\text{row}(A_L^\dagger)$ . However, it is reasonable to expect that the initial hypothesis of the underlying model being close to linear is correct. That is, we expect  $|b\rangle$  to have a good overlap with  $\text{row}(A_L^\dagger) = \text{col}(A_L)$ . The quantity that quantifies how far the model is from being

linear is the so called *normalized residual sum of squares*. For  $\ell_2$ -regularized ordinary least squares, this is given by

$$\mathcal{S}_O = \frac{\|(I - \Pi_{\text{col}(A_L)})|b\rangle|0\rangle\|^2}{\||b\rangle\|^2} = 1 - \|\Pi_{\text{col}(A_L)}|b\rangle|0\rangle\|^2. \quad (39)$$

If the underlying data can indeed be fit by a linear function,  $\mathcal{S}_O$  will be low. Subsequently, we assume that  $\mathcal{S}_O = 1 - \|\Pi_{\text{col}(A_L)}|b\rangle|0\rangle\|^2 \leq \gamma < 1/2$ . This in turn implies that  $\|\Pi_{\text{col}(A_L)}|b\rangle|0\rangle\|^2 = \Omega(1)$ , implying that the data can be reasonably fit by a linear model.<sup>i</sup>

Now we are in a position to present our quantum algorithm for the quantum least squares problem with general  $\ell_2$ -regularization. We also present an improved quantum algorithm for the closely related quantum ridge regression, which is a special case of the former.

**Theorem 35** (Quantum Ordinary Least Squares with General  $\ell_2$ -Regularization). *Let  $A, L \in \mathbb{R}^{N \times d}$  be the data and penalty matrices with condition numbers  $\kappa_A$  and  $\kappa_L$  respectively, and  $\lambda \in \mathbb{R}^+$  be the regression parameter. Let  $U_A$  be a  $(\alpha_A, a_A, \varepsilon_A)$ -block-encoding of  $A$  implemented in time  $T_A$  and  $U_L$  be a  $(\alpha_L, a_L, \varepsilon_L)$ -block-encoding of  $L$  implemented in time  $T_L$ . Furthermore, suppose  $U_b$  be a unitary that prepares  $|b\rangle$  in time  $T_b$ . Define*

$$\kappa := \kappa_A \kappa_L \sqrt{\frac{\|A\|^2 + \lambda\|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|L\|^2}}.$$

Then for any  $\delta \in (0, 1)$  such that

$$\varepsilon_A + \sqrt{\lambda}\varepsilon_L \leq \frac{\delta \|A^T A + \lambda L^T L\|}{32 \left( \alpha_A + \sqrt{\lambda}\alpha_L \right) \kappa^3 \log^3(2\kappa/\delta)} \quad (40)$$

we can prepare a state that is  $\delta$ -close to

$$\frac{(A^T A + \lambda L^T L)^{-1} A^T |b\rangle}{\|(A^T A + \lambda L^T L)^{-1} A^T |b\rangle\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O}\left(\kappa \log \kappa \left(\frac{\alpha_A + \sqrt{\lambda}\alpha_L}{\sqrt{\|A^T A + \lambda L^T L\|}} \log\left(\frac{\kappa}{\delta}\right) (T_A + T_L) + T_b\right)\right) \quad (41)$$

using only  $\mathcal{O}(\log \kappa)$  additional qubits.

*Proof.* We invoke [Lemma 18](#), to obtain a unitary  $U$ , which is a  $(\alpha_A + \sqrt{\lambda}\alpha_L, \max(a_A, a_L) + 2, \varepsilon_A + \sqrt{\lambda}\varepsilon_L)$ -block-encoding of the matrix  $A_L$ , implemented at a cost of  $\mathcal{O}(T_A + T_L)$ . Although in [Lemma 18](#)  $A$  and  $L$  are considered to be  $s$ -qubit operators, this is without loss of generality. For  $N \times d$  matrices, such that  $N, d \leq 2^s$ , we can pad them with zero entries. Padding  $A$  and  $L$  with zeros may result in the augmented matrix  $A_L$  having some zero rows between  $A$  and  $L$ . However, this is also not an issue as we are only interested in the top left block of  $A_L^\dagger$  which remains unaffected.

Note that  $U$  can be reinterpreted as a  $\left(\frac{\alpha_A + \sqrt{\lambda}\alpha_L}{\|A_L\|}, \max(a_A, a_L) + 2, \frac{\varepsilon_A + \sqrt{\lambda}\varepsilon_L}{\|A_L\|}\right)$ -block-encoding of the normalized matrix  $A_L/\|A_L\|$ . Furthermore, we can prepare the quantum state  $|b\rangle|0\rangle$  in time  $T_b$ . Now by using [Theorem 27](#) with  $U$  and an appropriately chosen  $\delta$  specified above, we obtain a quantum state that is  $\delta$ -close to

$$\frac{(A^T A + \lambda L^T L)^{-1} A^T |b\rangle}{\|(A^T A + \lambda L^T L)^{-1} A^T |b\rangle\|}$$

in the first register. □

<sup>i</sup>Our results also hold if we assume that  $\mathcal{S}_O \leq \gamma$  for some  $\gamma \in (0, 1)$ . That is,  $\|\Pi_{\text{col}(A_L)}\| \geq 1 - \gamma$ . In such a scenario our complexity to prepare  $A_L^\dagger |b, 0\rangle / \|A_L^\dagger |b, 0\rangle\|$  is rescaled by  $1/\sqrt{1 - \gamma}$ .

At this stage, it is worth considering how  $\ell_2$ -regularization can potentially improve the complexity of quantum ordinary least squares. Consider the following two scenarios (i) where the input data is such that  $A$  has a very high condition number ( $\kappa_A$ ) and (ii) when the input data is such that two or more columns are linearly dependent, resulting in  $A^T A$  being singular. For ease of exposition, let us deal with these cases assuming  $\|A\| = \|L\| = 1$ .

(i) When  $\kappa_A$  is large (say  $\text{poly}(N, d)$ ), the ordinary least squares algorithm would run in a time proportional to  $\tilde{\mathcal{O}}(\alpha_A \kappa_A)$  (assuming  $T_A$  and  $T_b$  are small). Now consider any penalty matrix  $L$  for which  $\kappa_L \ll \kappa_A$ . Then  $\ell_2$ -regularized regression problem has an effective condition number

$$\kappa = \kappa_L \sqrt{1 + \lambda} \left( \lambda + \frac{\kappa_L^2}{\kappa_A^2} \right)^{-1/2}$$

Typically in most practical scenarios,  $\lambda$  is a small constant. In this regime, we have that  $\kappa = \mathcal{O}(\kappa_L)$  and so the  $\ell_2$ -regularized OLS problem runs in complexity  $\tilde{\mathcal{O}}(\kappa_L(\alpha_A + \alpha_L))$  which can be polynomially better than its unregularized counterpart.

(ii) In the second case, as  $A^T A$  is singular, and so OLS cannot be applied altogether as  $\kappa_A \rightarrow \infty$ . The  $\ell_2$ -regularized OLS problem on the other hand has an effective condition number  $\kappa = \mathcal{O}(\kappa_L)$  and would still have the same complexity as in case (i).

Quantum ridge regression follows directly from [Theorem 35](#) by substituting  $L = I$ . We state it formally via the following corollary.

**Corollary 36** (Quantum Ridge Regression). *Let  $A$  be a matrix of dimension  $N \times d$  with condition number  $\kappa_A$  and  $\lambda \in \mathbb{R}^+$  be the regression parameter. Let  $U_A$  be a  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$  implemented in time  $T_A$ . Let  $U_b$  be a unitary that prepares  $|b\rangle$  in time  $T_b$ . If*

$$\kappa = \kappa_A \sqrt{\frac{\|A\|^2 + \lambda}{\|A\|^2 + \lambda \kappa_A^2}}$$

then for any  $\delta$  such that

$$\varepsilon \leq \frac{\delta \|A^T A + \lambda I\|}{32 (\alpha + \sqrt{\lambda}) \kappa^3 \log^3(\kappa/\delta)}$$

we can prepare a state  $\delta$ -close to

$$\frac{(A^T A + \lambda I)^{-1} A^T |b\rangle}{\|(A^T A + \lambda I)^{-1} A^T |b\rangle\|}$$

at a cost of

$$\mathcal{O}\left(\kappa \log \kappa \left(\frac{\alpha}{\|A\| + \sqrt{\lambda}} \log\left(\frac{\kappa}{\delta}\right) T_A + T_b\right)\right) \quad (42)$$

with probability  $\Theta(1)$  using only  $\mathcal{O}(\log \kappa)$  additional qubits.

*Proof.* The identity matrix  $I$  is a trivial  $(1, 0, 0)$ -block-encoding of itself, and  $\kappa_I = 1$ . We invoke [Theorem 35](#) with  $L = I$  to obtain the solution. We can further simplify the complexity expression by using the identity  $\sqrt{\|A^T A + \lambda I\|} = \|A\| + \sqrt{\lambda}$ , because  $A$  and  $I$  are simultaneously diagonalizable.  $\square$

Being in the block-encoding framework allows us to express the complexity of our quantum algorithm in specific input models such as the *quantum data structure input model* and the *sparse access model*. We express these complexities via the following corollaries.

**Corollary 37** (Quantum Ordinary Least Squares with  $\ell_2$ -Regularization in the Quantum Data Structure Input Model). *Let  $\lambda \in \mathbb{R}^+$ . Let  $A, L \in \mathbb{R}^{N \times d}$  with condition numbers  $\kappa_A, \kappa_L$  respectively. Let*

$$\kappa = \kappa_A \kappa_L \sqrt{\frac{\|A\|^2 + \lambda \|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|L\|^2}}$$

Let  $b \in \mathbb{R}^N$ . Suppose that  $A$ ,  $L$  and  $b$  are stored in a quantum accessible data structure. Then for any  $\delta > 0$  there exists a quantum algorithm to prepare a quantum state  $\delta$ -close to

$$\frac{(A^T A + \lambda L^T L)^{-1} A^T |b\rangle}{\|(A^T A + \lambda L^T L)^{-1} A^T |b\rangle\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O}\left(\kappa \left(\frac{\mu_A + \sqrt{\lambda}\mu_L}{\sqrt{\|A^T A + \lambda L^T L\|}}\right) \text{polylog}\left(\frac{Nd\kappa}{\delta}, \lambda\right)\right). \quad (43)$$

*Proof.* Since  $b$  is stored in the data structure, for some  $\varepsilon_b > 0$ , we can prepare the state  $|b'\rangle$  that is  $\varepsilon_b$ -close to  $|b\rangle = \sum_i b_i |i\rangle / \|b\|$  using  $T_b = \mathcal{O}(\text{polylog}(Nd/\varepsilon_b))$  queries to the data structure (see [Section 2.2.1](#).) Similarly, for some parameter  $\varepsilon > 0$ , we can construct a  $(\mu_A, \lceil \log(d+N) \rceil, \varepsilon)$ -block-encoding of  $A$  using  $T_A = \mathcal{O}(\text{polylog}(Nd/\varepsilon))$  queries to the data structure and a  $(\mu_L, \lceil \log(d+N) \rceil, \varepsilon)$ -block-encoding of  $L$  using  $T_L = \mathcal{O}(\text{polylog}(Nd/\varepsilon))$  queries.

We invoke [Theorem 35](#) with a precision of  $\delta/2$  by setting

$$\varepsilon = \frac{\delta \|A^T A + \lambda L^T L\|}{64(1 + \sqrt{\lambda})(\mu_A + \sqrt{\lambda}\mu_L)\kappa^3 \log^3(4\kappa/\delta)}$$

This gives us a state that is  $\delta/2$ -close to

$$\frac{(A^T A + \lambda L^T L)^{-1} A^T |b'\rangle}{\|(A^T A + \lambda L^T L)^{-1} A^T |b'\rangle\|}$$

We can rewrite the construction complexity for  $A$  and  $L$  using the following bound

$$\log\left(\frac{1}{\varepsilon}\right) = \mathcal{O}\left(\text{polylog}\left(\kappa, \mu_A, \mu_L, \frac{1}{\delta}\right)\right)$$

To compute the final precision as  $\delta$ , we use [Lemma 11](#) by choosing  $\varepsilon_b = \frac{\delta}{2\kappa}$ .  $\square$

In the previous corollary  $\mu_A = \|A\|_F$  and  $\mu_L = \|L\|_F$  when the matrix  $A$  and  $L$  are stored in the data structure. Similarly,  $\mu_A = \mu_p(A)$  and  $\mu_L = \mu_p(L)$  when the matrices  $A^{(p)}$ ,  $A^{(1-p)}$  and  $L^{(p)}$ ,  $L^{(1-p)}$  are stored in the data structure.

Now we discuss the complexity of quantum ordinary least squares with  $\ell_2$ -regularization in the *sparse access input model*. We call a matrix  $M$  as  $(s_r, s_c)$  row-column sparse if it has a row sparsity  $s_r$  and column sparsity  $s_c$ .

**Corollary 38** (Quantum Ordinary least squares with  $\ell_2$ -regularization in the sparse access model). *Let  $A \in \mathbb{R}^{N \times d}$  be  $(s_r^A, s_c^A)$  row-column sparse, and similarly, let  $L \in \mathbb{R}^{N \times d}$  be  $(s_r^L, s_c^L)$  row-column sparse, with condition numbers  $\kappa_A$  and  $\kappa_L$  respectively. Let  $\lambda \in \mathbb{R}^+$  and*

$$\kappa = \kappa_A \kappa_L \sqrt{\frac{\|A\|^2 + \lambda \|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|L\|^2}},$$

*Let  $\delta > 0$ . Suppose there exists a unitary that prepares  $|b\rangle$  at a cost of  $\mathcal{O}(\text{polylog}(Nd/\delta))$ . Then there is a quantum algorithm to prepare a quantum state that is  $\delta$ -close to*

$$\frac{(A^T A + \lambda L^T L)^{-1} A^T |b\rangle}{\|(A^T A + \lambda L^T L)^{-1} A^T |b\rangle\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O}\left(\kappa \left(\frac{\sqrt{s_r^A s_c^A} + \sqrt{\lambda s_r^L s_c^L}}{\sqrt{\|A^T A + \lambda L^T L\|}}\right) \text{polylog}\left(\frac{Nd\kappa}{\delta}, \lambda\right)\right). \quad (44)$$

*Proof.* The proof is similar to [Corollary 37](#) but with  $\alpha_A = \sqrt{s_r^A s_c^A}$  and  $\alpha_L = \sqrt{s_r^L s_c^L}$ .  $\square$



## 4.2 Quantum Weighted And Generalized Least Squares

This technique of working with an augmented matrix will also hold for the other variants of ordinary least squares. In this section, we begin by briefly describing these variants before moving on to designing quantum algorithms for the corresponding problems.

**Weighted Least Squares:** For the WLS problem, each observation  $\{a_i, b_i\}$  is assigned some weight  $w_i \in \mathbb{R}^+$  and the objective function to be minimized is of the form

$$\mathcal{L}_W := \sum_j w_j (x^T a_j - b_j)^2. \quad (45)$$

If  $W \in \mathbb{R}^{N \times N}$  is the diagonal matrix with  $w_i$  being the  $i^{\text{th}}$  diagonal entry, then the optimal  $x$  satisfies

$$x = (A^T W A)^{-1} A^T W b. \quad (46)$$

The  $\ell_2$ -regularized version of WLS satisfies

$$x = (A^T W A + \lambda L^T L)^{-1} A^T W b \quad (47)$$

Our quantum algorithm outputs a state that is close to

$$|x\rangle = \frac{(A^T W A + \lambda L^T L)^{-1} A^T W |b\rangle}{\|(A^T W A + \lambda L^T L)^{-1} A^T W |b\rangle\|} \quad (48)$$

given approximate block-encodings of  $A$ ,  $W$  and  $L$ .

Much like [Equation 38](#), finding the optimal solution reduces to finding the pseudo inverse of an augmented matrix  $A_L$  given by

$$A_L := \begin{pmatrix} \sqrt{W} A & 0 \\ \sqrt{\lambda} L & 0 \end{pmatrix}.$$

The top left block of  $A_L^\dagger = (A^T W A + \lambda L^T L)^{-1} A^T \sqrt{W}$ , which is the required linear transformation to be applied to the vector  $y = \sqrt{W} b$ . The ratio between the minimum and maximum singular values of  $A_L$ ,  $\kappa$ , can be obtained analogously to [Lemma 34](#).

For the  $\ell_2$ -regularized WLS problem, *normalized residual sum of squares* is given by

$$\mathcal{S}_W = \frac{\|(I - \Pi_{\text{col}(A_L)}) |y\rangle |0\rangle\|^2}{\||y\rangle\|^2} = 1 - \|\Pi_{\text{col}(A_L)} |y\rangle |0\rangle\|^2. \quad (49)$$

Subsequently, we assume that  $\mathcal{S}_W = 1 - \|\Pi_{\text{col}(A_L)} |y\rangle |0\rangle\|^2 \leq \gamma < 1/2$ . This in turn implies that  $\|\Pi_{\text{col}(A_L)} |y\rangle |0\rangle\|^2 = \Omega(1)$ , implying that the data can be reasonably fit by a linear model.

**Generalized Least Squares.** Similarly, we can extend this to GLS problem, where there the input data may be correlated. These correlations are given by the non-singular covariance matrix  $\Omega \in \mathbb{R}^{N \times N}$ . The WLS problem is a special case of the GLS problem, corresponding to when  $\Omega$  is a diagonal matrix.

The objective function to be minimized is

$$\mathcal{L}_\Omega := \sum_{i,j} (\Omega^{-1})_{ij} (x^T a_i - b_i)(x^T a_j - b_j). \quad (50)$$

The optimal  $x \in \mathbb{R}^d$  satisfies

$$x = (A^T \Omega^{-1} A)^{-1} A^T \Omega^{-1} b \quad (51)$$

Similarly, the  $\ell_2$ -regularized GLS solver outputs  $x$  such that

$$x = (A^T \Omega^{-1} A + \lambda L^T L)^{-1} A^T \Omega^{-1} b. \quad (52)$$

So, given approximate block-encodings of  $A$ ,  $\Omega$  and  $L$  a quantum GLS solver outputs a quantum state close to

$$|x\rangle = \frac{(A^T \Omega^{-1} A + \lambda L^T L) A^T \Omega^{-1} |b\rangle}{\|(A^T \Omega^{-1} A + \lambda L^T L) A^T \Omega^{-1} |b\rangle\|} \quad (53)$$

The augmented matrix  $A_L$  is defined as

$$A_L := \begin{pmatrix} \Omega^{-1/2} A & 0 \\ \sqrt{\lambda} L & 0 \end{pmatrix}.$$

Then top left block of  $A_L^+$  to the vector  $y = \Omega^{-1/2} b$  yields the optimal  $x$ . Thus the quantum GLS problem with  $\ell_2$ -regularization first prepares  $\Omega^{-1/2} |b\rangle |0\rangle$  and then uses the matrix inversion algorithm by QSVT to implement  $A_L^+ \Omega^{-1/2} |b\rangle |0\rangle$ . Analogous to OLS and WLS, we assume that the normalized residual sum of squares  $\mathcal{S}_\Omega \leq \gamma < 1/2$ .

From both the aforementioned descriptions of the  $\ell_2$ -regularized versions of WLS and GLS, it is clear that given block encodings of  $A$ ,  $L$  and  $W$  (or analogously,  $\Omega$ ) the approach needed to tackle the quantum versions of these problems would be similar. This is what motivates us to define what we call *extended least squares*.

**Extended Least Squares.** We can encapsulate both these cases by using a matrix  $B \in \mathbb{R}^{N \times N}$ , and writing the solution as

$$x = (A^T B^2 A + \lambda L^T L)^{-1} A^T B^2 b = ((BA)^T (BA) + \lambda L^T L)^{-1} (BA)^T B b$$

We call this method *Extended Least Squares*. For WLS we have  $B = \sqrt{W}$  and for GLS we have  $B = \Omega^{-1/2}$ . To solve this, we invoke the Quantum OLS solver from [Theorem 35](#) with a data matrix  $BA$ , penalty matrix  $L$ , regression parameter  $\lambda$ , and input state  $\frac{B|b\rangle}{\|B|b\rangle\|}$ .

In the next section, we solve the *quantum extended least squares problem*, wherein given approximate block-encodings of  $A$ ,  $L$  and  $B$ , a value of  $\lambda$  and a procedure to prepare  $|b\rangle$ , we obtain a quantum state that is  $\delta$ -close to  $|x\rangle$ . This makes it substantially easier for us to obtain the complexities of the  $\ell_2$ -regularized WLS and GLS by just substituting  $B = \sqrt{W}$  and  $B = \Omega^{-1/2}$ , respectively.

#### 4.2.1 Quantum Extended Least Squares

Our strategy to solve the quantum extended least squares problem is the following: given approximate block-encodings of  $A$ ,  $B$  we first obtain a block-encoding of their product  $AB$ . In order to avoid, products of the block-encoding sub-normalization factors (which increases the complexity substantially), we first amplify the block-encodings of  $A$  and  $B$  respectively (using [Corollary 8](#)) and then apply [Lemma 16](#).

We can then use this block-encoding of  $AB$  and the block-encoding of  $L$ , to obtain a block-encoding of the augmented matrix  $A_L$  (using [Lemma 18](#)). Also, using the block-encoding of  $B$  and the procedure to obtain  $|b\rangle$  to prepare a state that is close to  $|y\rangle = B|b\rangle / \|B|b\rangle\|$ .

Finally, we apply the variable time matrix inversion algorithm ([Theorem 27](#)) to implement a state close to

$$\frac{A_L^+ |y\rangle |0\rangle}{\|A_L^+ |y\rangle |0\rangle\|}$$

and read out the first register. We formally derive the complexity via the following lemma:

**Theorem 39** (Quantum Extended Least Squares with General  $\ell_2$ -Regularization). *Let  $A, L \in \mathbb{R}^{N \times d}$  and  $B \in \mathbb{R}^{N \times N}$  with condition numbers  $\kappa_A, \kappa_L, \kappa_B$  respectively. Define  $\|A_L\|$ ,  $r$  and  $\kappa$  as*

$$\|A_L\| = \sqrt{\|A^T B^2 A + \lambda L^T L\|},$$

$$r = \frac{2\|A\|\|B\| + \sqrt{2\lambda}\|L\|}{\|A_L\|},$$

$$\kappa = \kappa_A \kappa_B \kappa_L \sqrt{\frac{\|A\|^2 \|B\|^2 + \lambda \|L\|^2}{\kappa_L^2 \|A\|^2 \|B\|^2 + \lambda \kappa_A^2 \kappa_B^2 \|L\|^2}}.$$

Let  $\delta > 0$  be the error parameter. For some  $\varepsilon_A$  such that

$$\varepsilon_A \leq \frac{\delta \|A_L\|}{256\sqrt{2}\|B\|r\kappa^3 \log^3(4\kappa/\delta)}$$

we have access to  $U_A$ , an  $(\alpha_A, a_A, \varepsilon_A)$ -block-encoding of  $A$  implemented in time  $T_A$ . For some  $\varepsilon_L$  such that

$$\varepsilon_L \leq \frac{\delta \|A_L\|}{256\sqrt{\lambda}r\kappa^3 \log^3(4\kappa/\delta)}$$

we have access to  $U_L$ , an  $(\alpha_L, a_L, \varepsilon_L)$ -block-encoding of  $L$  implemented in time  $T_L$ . For some  $\varepsilon_B$  such that

$$\varepsilon_B \leq \frac{\delta}{8\kappa} \min\left(\frac{\|B\|}{\kappa_B}, \frac{\|A_L\|}{32\sqrt{2}\|A\|r\kappa^2 \log^3(4\kappa/\delta)}\right)$$

we have access to  $U_B$ , an  $(\alpha_B, a_B, \varepsilon_B)$ -block-encoding of  $B$  implemented in time  $T_B$ . Let  $U_b$  be a unitary that prepares the state  $|b\rangle$  in time  $T_b$ .

Then we can prepare the quantum state that is  $\delta$ -close to

$$\frac{(A^T B^2 A + \lambda L^T L)^{-1} A^T B^2 |b\rangle}{\|(A^T B^2 A + \lambda L^T L)^{-1} A^T B^2 |b\rangle\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O}\left(\kappa \log \kappa \left(r \left(\frac{\alpha_A}{\|A\|} T_A + \frac{\alpha_L}{\|L\|} T_L + \frac{\alpha_B \kappa_B}{\|B\|} T_B\right) \log^2\left(\frac{\kappa}{\delta} \frac{r}{\|A_L\|}\right) + \kappa_B T_b\right)\right), \quad (54)$$

using only  $\mathcal{O}(\log \kappa)$  additional qubits.

*Proof.* To solve this version of the problem, we first need to prepare a block-encoding of  $BA$  and the quantum state  $\frac{|B|b\rangle}{\|B|b\rangle\|}$ .

Using [Lemma 16](#) with precision  $\delta_A$  satisfying  $\delta_A \geq 2\sqrt{2} \max(\|B\|\varepsilon_A, \|A\|\varepsilon_B)$ , we get a  $(2\|A\|\|B\|, a_A + a_B + 2, \delta_A)$ -block-encoding of  $A' := BA$  at a cost

$$T_{A'} := \mathcal{O}\left(\left(\frac{\alpha_A}{\|A\|} T_A + \frac{\alpha_B}{\|B\|} T_B\right) \log\left(\frac{\|A\|\|B\|}{\delta_A}\right)\right).$$

To prepare  $\frac{|B|b\rangle}{\|B|b\rangle\|}$ , we first pre-amplify  $U_B$ . Choose some  $\varepsilon_b \geq 4\varepsilon_B \kappa_B / \|B\|$ . Using [Corollary 10](#) on  $|b\rangle$  for some precision  $\varepsilon_b \geq 4\varepsilon_B \kappa_B / \|B\|$ , we can prepare a state that is  $\varepsilon_b$ -close to  $|b'\rangle := \frac{|B|b\rangle}{\|B|b\rangle\|}$  with constant success probability at a cost of

$$T_{b'} := \mathcal{O}\left(\frac{\alpha_B \kappa_B}{\|B\|} \log\left(\frac{\kappa}{\varepsilon_b}\right) T_B + \kappa_B T_b\right)$$

We could invoke OLS directly using the above two, but that ends up with a product of  $\alpha$  terms in the complexity. We want to avoid this, because in most common cases  $\alpha$ -s for block-encodings are quite large. So we also pre-amplify  $U_L$  using [Corollary 8](#): For any  $\delta_L \geq 2\varepsilon_L$  we get a  $(\sqrt{2}\|L\|, a_L + 1, \delta_L)$ -encoding of  $L$  at a cost of

$$T_{L'} := \mathcal{O}\left(\frac{\alpha_L}{\|L\|} T_L \log\left(\frac{\|L\|}{\delta_L}\right)\right).$$

Now we can invoke [Theorem 35](#) with the above block-encodings for  $BA$  and  $L$ , the state  $|b'\rangle$ , and an appropriately chosen precision  $\delta_b$  such that

$$\begin{aligned}\delta_A + \sqrt{\lambda}\delta_L &= \frac{\delta_b \|A^T B^2 A + \lambda L^T L\|}{32 \left( 2\|A\|\|B\| + \sqrt{2\lambda}\|L\| \right) \kappa^3 \log^3(2\kappa/\delta_b)} \\ &= \frac{\delta_b \|A_L\|}{32r\kappa^3 \log^3(2\kappa/\delta_b)}\end{aligned}$$

to get a state  $\delta_b$ -close to  $|\psi\rangle := \frac{A_L^+ |b'\rangle}{\|A_L^+ |b'\rangle\|}$ , where  $A_L^+ = (A^T B^2 A + \lambda L^T L)^{-1} A^T B$ . This procedure has a time complexity of

$$\mathcal{O}\left(\kappa \log \kappa \left(r \log\left(\frac{\kappa}{\delta_b}\right) (T_{A'} + T_{L'}) + T_{b'}\right)\right) \quad (55)$$

We can compute the error between  $|\psi\rangle$  and the expected state by using [Lemma 11](#). For the final error to be  $\delta$ , we have to choose  $\varepsilon_b = \delta/2\kappa$  and  $\delta_b = \delta/2$ . To propagate the error backwards, we choose  $\delta_A = \sqrt{\lambda}\delta_L$ , which gives us the above bounds on the input block-encodings.

$$\begin{aligned}\delta_A = \sqrt{\lambda}\delta_L &= \frac{\delta \|A_L\|}{128r\kappa^3 \log^3(4\kappa/\delta)} \\ \log\left(\frac{1}{\delta_A}\right) &= \log\left(\frac{128r\kappa^3 \log^3(4\kappa/\delta)}{\delta \|A_L\|}\right) = \mathcal{O}\left(\log\left(\frac{r}{\|A_L\|} \frac{\kappa}{\delta}\right)\right) \\ \log\left(\frac{1}{\delta_L}\right) &= \mathcal{O}\left(\log\left(\frac{r\lambda}{\|A_L\|} \frac{\kappa}{\delta}\right)\right)\end{aligned}$$

As  $U_B$  is used twice, we get two separate bounds for  $\varepsilon_B$ . From the state preparation, we have:

$$\varepsilon_B \leq \frac{\varepsilon_b \|B\|}{4\kappa_B} \leq \frac{\delta \|B\|}{8\kappa\kappa_B}$$

And from the product of block-encodings, we have:

$$\varepsilon_B \leq \frac{\delta_A}{2\sqrt{2}\|A\|}$$

Similarly we get bounds on  $\varepsilon_A$  and  $\varepsilon_L$ :

$$\begin{aligned}\varepsilon_A &\leq \frac{\delta_A}{2\sqrt{2}\|B\|} \\ \varepsilon_L &\leq \frac{\delta_L}{2} = \frac{\delta_A}{2\sqrt{\lambda}}\end{aligned}$$

Now let us inspect the query complexities of each input procedure —  $U_A$ ,  $U_L$ ,  $U_B$  and  $U_b$  — in [Equation 55](#). When calculating the contribution for a given input unitary, we set the corresponding  $T$  value to 1, and the rest to 0.

$$\begin{aligned}Q_A &= \mathcal{O}\left(\kappa \log \kappa \left(r \log\left(\frac{\kappa}{\delta_b}\right) T_{A'}\right)\right) \\ &= \mathcal{O}\left(\kappa \log \kappa \left(r \log\left(\frac{\kappa}{\delta_b}\right) \left(\frac{\alpha_A}{\|A\|} \log\left(\frac{\|A\|\|B\|}{\delta_A}\right)\right)\right)\right) \\ &= \mathcal{O}\left(\kappa \log \kappa r \frac{\alpha_A}{\|A\|} \log^2\left(\kappa, \frac{1}{\delta_b}, \frac{1}{\delta_A}, \|A\|, \|B\|\right)\right) \\ &= \mathcal{O}\left(\kappa \log \kappa r \frac{\alpha_A}{\|A\|} \log^2\left(\frac{\kappa}{\delta}, \frac{r}{\|A_L\|}, \|A\|, \|B\|\right)\right)\end{aligned}$$

$$\begin{aligned}
Q_L &= \mathcal{O}\left(\kappa \log \kappa \left(r \log \left(\frac{\kappa}{\delta_b}\right) T_{L'}\right)\right) \\
&= \mathcal{O}\left(\kappa \log \kappa \left(r \log \left(\frac{\kappa}{\delta_b}\right) \left(\frac{\alpha_L}{\|L\|} \log \left(\frac{\|L\|}{\delta_L}\right)\right)\right)\right) \\
&= \mathcal{O}\left(\kappa \log \kappa r \frac{\alpha_L}{\|L\|} \log^2 \left(\kappa, \frac{1}{\delta_b}, \frac{1}{\delta_L}, \|L\|\right)\right) \\
&= \mathcal{O}\left(\kappa \log \kappa r \frac{\alpha_L}{\|L\|} \log^2 \left(\frac{\kappa}{\delta}, \frac{r}{\|A_L\|}, \lambda, \|L\|\right)\right)
\end{aligned}$$

$$\begin{aligned}
Q_B &= \mathcal{O}\left(\kappa \log \kappa \left(r \log \left(\frac{\kappa}{\delta_b}\right) T_{A'} + T_{b'}\right)\right) \\
&= \mathcal{O}\left(\kappa \log \kappa \left(r \log \left(\frac{\kappa}{\delta_b}\right) \frac{\alpha_B}{\|B\|} \log \left(\frac{\|A\|\|B\|}{\delta_A}\right) + \frac{\alpha_B \kappa_B}{\|B\|} \log \left(\frac{\kappa}{\varepsilon_b}\right)\right)\right) \\
&= \mathcal{O}\left(\kappa \log \kappa r \frac{\alpha_B \kappa_B}{\|B\|} \log^2 \left(\kappa, \frac{1}{\delta_b}, \frac{1}{\delta_A}, \frac{1}{\varepsilon_b}, \|A\|, \|B\|\right)\right) \\
&= \mathcal{O}\left(\kappa \log \kappa r \frac{\alpha_B \kappa_B}{\|B\|} \log^2 \left(\frac{\kappa}{\delta}, \frac{r}{\|A_L\|}, \|A\|, \|B\|\right)\right)
\end{aligned}$$

$$Q_b = \mathcal{O}(\kappa \log \kappa T_{b'}) = \mathcal{O}(\kappa \log \kappa \cdot \kappa_B)$$

Finally, as  $r$  contains  $\|A\|, \|B\|, \lambda, \|L\|$ , we can drop the latter terms inside the log factors. Plugging in all the individual terms, we get the final time complexity as

$$\begin{aligned}
&\mathcal{O}(Q_A T_A + Q_B T_B + Q_L T_L + Q_b T_b) \\
&= \mathcal{O}\left(\kappa \log \kappa \left(r \log^2 \left(\frac{\kappa}{\delta} \frac{r}{\|A_L\|}\right) \left(\frac{\alpha_A}{\|A\|} T_A + \frac{\alpha_L}{\|L\|} T_L + \frac{\alpha_B \kappa_B}{\|B\|} T_B\right) + \kappa_B T_b\right)\right)
\end{aligned}$$

□

The parameter  $r$  in the expression of the complexity of extended least squares is a ratio of norms. In the scenario where  $\|A\|, \|B\|$  and  $\|L\|$  are constants,  $r = \frac{2+\sqrt{2\lambda}}{\sqrt{1+\lambda}} = \Theta(1)$ , for any  $\lambda = \Theta(1)$ .

#### 4.2.2 Quantum Weighted Least Squares

In this section, we derive the complexity of the  $\ell_2$ -regularized WLS problem as a special case of quantum extended least squares problem. We assume that we have block-encoded access to a diagonal weight matrix  $W \in \mathbb{R}^{N \times N}$ . The smallest and largest singular values of  $W$  are  $w_{\min}$  and  $w_{\max}$  respectively. This implies that  $\|W\| = w_{\max}$  and  $\kappa_W = w_{\max}/w_{\min}$ .

**Corollary 40** (Preparing  $\sqrt{W}$ ). *Let  $W \in \mathbb{R}^{N \times N}$  be a matrix with largest and smallest singular values  $w_{\max}, w_{\min}$  respectively. Let  $U_W$  be an  $(\alpha_W, a_W, \varepsilon_W)$ -block-encoding of  $W$ , implemented in time  $T_W$ . For any  $\delta \geq \varepsilon_W/\sqrt{w_{\min}}$ , we can prepare a  $(2\sqrt{\alpha_W}, a_W + 1, \delta)$ -block-encoding of  $\sqrt{W}$  at a cost of*

$$\mathcal{O}\left(\frac{\alpha_W}{w_{\min}} \log \left(\frac{\alpha_W}{\delta}\right) T_W\right) \quad (56)$$

*Proof.* We can prepare the required unitary by invoking [Corollary 30](#) on  $U_W$  with  $c = 1/2$  and an error of  $\delta$ . □

**Theorem 41** (Quantum Weighted Least Squares with General  $\ell_2$ -regularization). *Let  $A, L \in \mathbb{R}^{N \times d}$  be the data and penalty matrix, with condition numbers  $\kappa_A, \kappa_L$  respectively. Let  $W \in \mathbb{R}^{N \times N}$  be the diagonal weight matrix, with largest and smallest singular values  $w_{\max}, w_{\min}$  respectively. Define  $\|A_L\|$ ,  $r$  and  $\kappa$  as*

$$\|A_L\| = \sqrt{\|A^T W A + \lambda L^T L\|},$$

$$r = \frac{2\sqrt{w_{\max}}\|A\| + \sqrt{2\lambda}\|L\|}{\|A_L\|},$$

$$\kappa = \kappa_A \kappa_L \sqrt{\frac{w_{\max}\|A\|^2 + \lambda\|L\|^2}{w_{\min}\kappa_L^2\|A\|^2 + \lambda\kappa_A^2\|L\|^2}}.$$

Let  $\delta > 0$  be the error parameter. For some  $\varepsilon_A$  such that

$$\varepsilon_A \leq \frac{\delta\|A_L\|}{256\sqrt{2}w_{\max}r\kappa^3 \log^3(4\kappa/\delta)}$$

we have access to  $U_A$ , an  $(\alpha_A, a_A, \varepsilon_A)$ -block-encoding of  $A$  implemented in time  $T_A$ . For some  $\varepsilon_L$  such that

$$\varepsilon_L \leq \frac{\delta\|A_L\|}{256\sqrt{\lambda}r\kappa^3 \log^3(4\kappa/\delta)}$$

we have access to  $U_L$ , an  $(\alpha_L, a_L, \varepsilon_L)$ -block-encoding of  $L$  implemented in time  $T_L$ . For some  $\varepsilon_W$  such that

$$\varepsilon_W \leq \frac{\delta w_{\min}}{8\kappa} \min\left(1, \frac{\|A_L\|}{32\sqrt{2}w_{\min}\|A\|r\kappa^2 \log^3(4\kappa/\delta)}\right)$$

we have access to  $U_W$ , an  $(\alpha_W, a_W, \varepsilon_W)$ -block-encoding of  $W$  implemented in time  $T_W$ . Let  $U_b$  be a unitary that prepares the state  $|b\rangle$  in time  $T_b$ .

Then we can prepare the quantum state that is  $\delta$ -close to

$$\frac{(A^T W A + \lambda L^T L)^{-1} A^T W |b\rangle}{\|(A^T W A + \lambda L^T L)^{-1} A^T W |b\rangle\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O}\left(\kappa \log \kappa \left\{ r \left( \frac{\alpha_A}{\|A\|} T_A + \frac{\alpha_L}{\|L\|} T_L + \left( \frac{\alpha_W}{w_{\min}} \right)^{3/2} T_W \log \left( \frac{\alpha_W}{w_{\min}} \right) \right) \log^3 \left( \frac{\kappa}{\delta} \frac{r}{\|A_L\|} \right) + \sqrt{\frac{w_{\max}}{w_{\min}}} T_b \right\}, \right) \quad (57)$$

using only  $\mathcal{O}(\log \kappa)$  additional qubits.

*Proof.* We first prepare the block encoding of  $\sqrt{W}$ . Invoking [Corollary 40](#) with  $\varepsilon_B \geq \varepsilon_W / \sqrt{w_{\min}}$ , we have a  $(2\sqrt{\alpha_W}, a_W + 1, \varepsilon_B)$ -block-encoding of  $B := \sqrt{W}$ , at a cost of

$$T_B := \mathcal{O}\left(\frac{\alpha_W}{w_{\min}} \log\left(\frac{\alpha_W}{\varepsilon_B}\right) T_W\right).$$

This implies that  $\|B\| = \sqrt{w_{\max}}$  and  $\kappa_B = \sqrt{w_{\max}/w_{\min}}$ .

We can now invoke [Theorem 39](#) with an appropriate  $\delta$  to prepare the required state. We get the required lower bound on  $\delta$  by choosing  $\varepsilon_B$  as

$$\varepsilon_B = \frac{\delta}{8\kappa} \min\left(\sqrt{w_{\min}}, \frac{\|A_L\|}{32\sqrt{2}\|A\|r\kappa^2 \log^3(4\kappa/\delta)}\right)$$

This implies that

$$\begin{aligned} \log\left(\frac{1}{\varepsilon_B}\right) &= \log\left(\frac{8\kappa}{\delta} \max\left(\frac{1}{\sqrt{w_{\min}}}, \frac{32\sqrt{2}\|A\|r\kappa^2 \log^3(4\kappa/\delta)}{\|A_L\|}\right)\right) \\ &= \mathcal{O}\left(\log\left(\frac{\kappa r\|A\|}{\delta\sqrt{w_{\min}}\|A_L\|}\right)\right) \\ &= \mathcal{O}\left(\log\left(\frac{\kappa}{\delta} \frac{r}{w_{\min}\|A_L\|}\right)\right) \end{aligned}$$

□

**Theorem 41** assumes block-encoding access to  $W$ ,  $A$  and  $L$ . Just as in **Corollary 37**, the algorithm can still be used if we are given access to them via an efficient data structure that can be accessed in superposition. For example, if they are stored in the data structure described by [KP17] and are accessed via a QRAM,  $T_{A,W,L}$  are  $\text{polylog}(Nd/\varepsilon)$ . However,  $W$  is a diagonal matrix and one can assume that the entries of  $W$  can be directly accessed via a QRAM. We will show in **Section 4.2.4**, that this assumption improves the complexity of the quantum WLS problem with general  $\ell_2$ -regularization. However, first we shall deal with the quantum GLS problem as a particular case of quantum extended least squares.

### 4.2.3 Quantum Generalized Least Squares

In this section, we assume that we have block-encoded access to the correlation matrix  $\Omega \in \mathbb{R}^{N \times N}$ , with condition number  $\kappa_\Omega$ . We begin by preparing a block encoding of  $\Omega^{-1/2}$ , given an approximate block-encoding of  $\Omega$ .

**Corollary 42** (Preparing  $\Omega^{-1/2}$ ). *Let  $\Omega \in \mathbb{R}^{N \times N}$  be a matrix with largest and smallest singular values  $w_{max}, w_{min}$  respectively. Let  $U_\Omega$  be an  $(\alpha_\Omega, a_\Omega, \varepsilon_\Omega)$ -block-encoding of  $\Omega$ , implemented in time  $T_\Omega$ . For any  $\delta$  such that*

$$\delta \geq \frac{\varepsilon_\Omega \kappa_\Omega^{3/2}}{\|\Omega\|^{3/2}}$$

*we can prepare a  $(2\sqrt{\kappa_\Omega/\|\Omega\|}, a_\Omega + 1, \delta)$ -block-encoding of  $\Omega^{-1/2}$  at a cost of*

$$\mathcal{O}\left(\frac{\alpha_\Omega \kappa_\Omega}{\|\Omega\|} \log\left(\frac{\kappa_\Omega}{\delta \|\Omega\|}\right) T_\Omega\right)$$

*Moreover, the condition number of  $\Omega^{-1/2}$  is bounded by  $\sqrt{\kappa_\Omega}$ .*

*Proof.* We can prepare the required unitary by invoking **Corollary 33** on  $U_\Omega$  with  $c = 1/2$  and an error of  $\delta$ .  $\square$

We will now use this lemma in conjunction with **Theorem 39** to develop quantum algorithms for GLS with general  $\ell_2$ -regularization.

**Theorem 43** (Quantum Generalized Least Squares with General  $\ell_2$ -regularization). *Let  $A, L \in \mathbb{R}^{N \times d}$  be the data and penalty matrices with condition numbers  $\kappa_A, \kappa_L$  respectively. and  $\Omega \in \mathbb{R}^{N \times N}$  be the covariance matrix with condition number  $\kappa_\Omega$ . Define  $\|A_L\|$ ,  $r$  and  $\kappa$  as*

$$\begin{aligned} \|A_L\| &= \sqrt{\|A^T \Omega^{-1} A + \lambda L^T L\|}, \\ r &= \frac{2\|A\| \sqrt{\kappa_\Omega/\|\Omega\|} + \sqrt{2\lambda}\|L\|}{\|A_L\|}, \\ \kappa &= \kappa_A \kappa_L \sqrt{\frac{\kappa_\Omega \|A\|^2 + \lambda \|\Omega\| \|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|\Omega\| \|L\|^2}}. \end{aligned}$$

*Let  $\delta > 0$  be the error parameter. For some  $\varepsilon_A$  such that*

$$\varepsilon_A \leq \frac{\delta \|A_L\| \sqrt{\|\Omega\|}}{256 \sqrt{2\kappa_\Omega} r \kappa^3 \log^3(4\kappa/\delta)}$$

*we have access to  $U_A$ , an  $(\alpha_A, a_A, \varepsilon_A)$ -block-encoding of  $A$  implemented in time  $T_A$ . For some  $\varepsilon_L$  such that*

$$\varepsilon_L \leq \frac{\delta \|A_L\|}{256 \sqrt{\lambda} r \kappa^3 \log^3(4\kappa/\delta)}$$

we have access to  $U_L$ , an  $(\alpha_L, a_L, \varepsilon_L)$ -block-encoding of  $L$  implemented in time  $T_L$ . For some  $\varepsilon_\Omega$  such that

$$\varepsilon_\Omega \leq \frac{\delta}{8\kappa} \left( \frac{\|\Omega\|}{\kappa_\Omega} \right)^{3/2} \min \left( \frac{1}{\sqrt{\|\Omega\|}}, \frac{\|A_L\|}{32\sqrt{2}\|A\|r\kappa^2 \log^3(4\kappa/\delta)} \right)$$

we have access to  $U_\Omega$ , an  $(\alpha_\Omega, a_\Omega, \varepsilon_\Omega)$ -block-encoding of  $\Omega$  implemented in time  $T_\Omega$ . Let  $U_b$  be a unitary that prepares the state  $|b\rangle$  in time  $T_b$ .

Then we can prepare the quantum state that is  $\delta$ -close to

$$\frac{(A^T \Omega^{-1} A + \lambda L^T L)^{-1} A^T \Omega^{-1} |b\rangle}{\left\| (A^T \Omega^{-1} A + \lambda L^T L)^{-1} A^T \Omega^{-1} |b\rangle \right\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O} \left( \kappa \log \kappa \left( r \left( \frac{\alpha_A}{\|A\|} T_A + \frac{\alpha_L}{\|L\|} T_L + \frac{\alpha_\Omega \kappa_\Omega^{3/2}}{\|\Omega\|} T_\Omega \log \left( \frac{\kappa_\Omega}{\sqrt{\|\Omega\|}} \right) \right) \log^3 \left( \frac{\kappa}{\delta} \frac{r}{\|A_L\|} \right) + \sqrt{\kappa_\Omega} T_b \right) \right), \quad (58)$$

using only  $\mathcal{O}(\log \kappa)$  additional qubits.

*Proof.* The proof is similar in spirit to [Theorem 41](#), but with  $W$  replaced by  $\Omega^{-1}$ . We first prepare the block encoding of  $\Omega^{-1/2}$  by invoking [Corollary 42](#) with an appropriate precision  $\varepsilon_B \geq \varepsilon_\Omega (\kappa_\Omega / \|\Omega\|)^{3/2}$ . We get a  $(2\sqrt{\kappa_\Omega / \|\Omega\|}, a_\Omega + 1, \varepsilon_B)$ -block-encoding of  $B := \Omega^{-1/2}$  at a cost of

$$T_B := \mathcal{O} \left( \frac{\alpha_\Omega \kappa_\Omega}{\|\Omega\|} \log \left( \frac{\kappa_\Omega}{\varepsilon_B \|\Omega\|} \right) T_\Omega \right).$$

This implies that  $\|B\| = \sqrt{\kappa_\Omega / \|\Omega\|}$  and  $\kappa_B = \sqrt{\kappa_\Omega}$ .

We can now invoke [Theorem 39](#) with an appropriate  $\delta$  to prepare the required state. We get the required lower bound on  $\delta$  by choosing  $\varepsilon_B$  as

$$\varepsilon_B = \frac{\delta}{8\kappa} \min \left( \frac{1}{\sqrt{\|\Omega\|}}, \frac{\|A_L\|}{32\sqrt{2}\|A\|r\kappa^2 \log^3(4\kappa/\delta)} \right)$$

This implies that

$$\begin{aligned} \log \left( \frac{\kappa_\Omega}{\varepsilon_B \|\Omega\|} \right) &= \log \left( \frac{8\kappa\kappa_\Omega}{\delta\|\Omega\|} \max \left( \sqrt{\|\Omega\|}, \frac{32\sqrt{2}\|A\|r\kappa^2 \log^3(4\kappa/\delta)}{\|A_L\|} \right) \right) \\ &= \mathcal{O} \left( \log \left( \frac{\kappa}{\delta} \frac{r}{\|A_L\|} \frac{\kappa_\Omega}{\sqrt{\|\Omega\|}} \right) \right) \end{aligned}$$

□

One immediate observation is that for the special case of the (unregularized) quantum GLS problem (when  $L = 0$  and  $\lambda = 0$ ), our algorithm has a slightly better complexity than [\[CGJ19\]](#) and requires fewer additional qubits.

Now, we will state the complexities of this algorithm in specific input models, namely the quantum data structure model and the sparse-access input model.

**Corollary 44** (Quantum Generalized Least Squares with General  $\ell_2$ -Regularization in the Quantum Data Structure Model). *Let  $A, L \in \mathbb{R}^{N \times d}$  be the data and penalty matrices with condition numbers  $\kappa_A, \kappa_L$  respectively. and  $\Omega \in \mathbb{R}^{N \times N}$  be the covariance matrix with condition number  $\kappa_\Omega$ . Let the matrices  $A, L, \Omega$  and the vector  $b$  be stored in a quantum accessible data structure. Define  $\|A_L\|$ ,  $r$  and  $\kappa$  as*

$$\|A_L\| = \sqrt{\|A^T \Omega^{-1} A + \lambda L^T L\|},$$



$$r = \frac{2\|A\|\sqrt{\kappa_\Omega/\|\Omega\|} + \sqrt{2\lambda}\|L\|}{\|A_L\|},$$

$$\kappa = \kappa_A \kappa_L \sqrt{\frac{\kappa_\Omega \|A\|^2 + \lambda \|\Omega\| \|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|\Omega\| \|L\|^2}}.$$

Then for any  $\delta > 0$ , we can prepare the quantum state that is  $\delta$ -close to

$$\frac{(A^T \Omega^{-1} A + \lambda L^T L)^{-1} A^T \Omega^{-1} |b\rangle}{\|(A^T \Omega^{-1} A + \lambda L^T L)^{-1} A^T \Omega^{-1} |b\rangle\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O}\left(\kappa r \left(\frac{\mu_A}{\|A\|} + \frac{\mu_L}{\|L\|} + \frac{\mu_\Omega \kappa_\Omega^{3/2}}{\|\Omega\|}\right) \text{polylog}\left(\frac{Nd\kappa}{\delta}\right)\right). \quad (59)$$

*Proof.* The proof is very similar to [Corollary 37](#) with the extra input of  $\Omega$ . We can use the data structure to prepare the block-encodings for  $A, L, \Omega$  and the state  $|b\rangle$ , with precisions  $\varepsilon_A, \varepsilon_L, \varepsilon_\Omega, \varepsilon_b$  respectively. We invoke [Theorem 43](#) with a precision of  $\delta_b$ , and choose the above  $\varepsilon$  terms to be equal to their corresponding upper-bounds. And finally we use [Lemma 11](#) with  $\varepsilon_b = \delta/2\kappa$  and  $\delta_b = \delta/2$  to get the final error as  $\delta$ .  $\square$

Now,  $\mu_A = \|A\|_F$  (similarly for  $\mu_L$  and  $\mu_\Omega$ ). As  $\|A\|_F \leq \sqrt{r(A)}\|A\|$ , where  $r(A)$  is the rank of  $A$ , we have that the complexity of [Corollary 44](#) can be re-expressed as

$$\mathcal{O}\left(\kappa r \left(\sqrt{r(A)} + \sqrt{r(L)} + \sqrt{r(\Omega)} \kappa_\Omega^{3/2}\right) \text{polylog}\left(\frac{Nd\kappa}{\delta}\right)\right). \quad (60)$$

**Corollary 45** (Quantum Generalized Least Squares with General  $\ell_2$ -Regularization in the Sparse Access Model). *Let  $A \in \mathbb{R}^{N \times d}$  be a  $(s_r^A, s_c^A)$  row-column sparse data matrix. Let  $L \in \mathbb{R}^{N \times d}$  be a  $(s_r^L, s_c^L)$  row-column sparse penalty matrix. Let  $\Omega \in \mathbb{R}^{N \times N}$  be a  $(s_r^\Omega, s_c^\Omega)$  row-column sparse covariance matrix. Suppose we have a procedure to prepare  $|b\rangle$  in  $\mathcal{O}(\text{polylog}(N))$ . Define  $\|A_L\|$ ,  $r$  and  $\kappa$  as*

$$\|A_L\| = \sqrt{\|A^T \Omega^{-1} A + \lambda L^T L\|},$$

$$r = \frac{2\|A\|\sqrt{\kappa_\Omega/\|\Omega\|} + \sqrt{2\lambda}\|L\|}{\|A_L\|},$$

$$\kappa = \kappa_A \kappa_L \sqrt{\frac{\kappa_\Omega \|A\|^2 + \lambda \|\Omega\| \|L\|^2}{\kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|\Omega\| \|L\|^2}}.$$

Then for any  $\delta > 0$ , we can prepare the quantum state that is  $\delta$ -close to

$$\frac{(A^T \Omega^{-1} A + \lambda L^T L)^{-1} A^T \Omega^{-1} |b\rangle}{\|(A^T \Omega^{-1} A + \lambda L^T L)^{-1} A^T \Omega^{-1} |b\rangle\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O}\left(\kappa r \left(\frac{\sqrt{s_r^A s_c^A}}{\|A\|} + \frac{\sqrt{s_r^L s_c^L}}{\|L\|} + \frac{\sqrt{s_r^\Omega s_c^\Omega} \kappa_\Omega^3}{\|\Omega\|}\right) \text{polylog}\left(\frac{Nd\kappa}{\delta}\right)\right). \quad (61)$$

*Proof.* The algorithm is similar to [Corollary 44](#), but with  $\alpha_A = \sqrt{s_r^A s_c^A}$ ,  $\alpha_L = \sqrt{s_r^L s_c^L}$ , and  $\alpha_\Omega = \sqrt{s_r^\Omega s_c^\Omega}$ .  $\square$

#### 4.2.4 Improved Quantum Weighted Least Squares Algorithms

In this section, we can advantage of the fact that the matrix  $W$  is diagonal, and use controlled rotations to directly implement a block encoding of  $\sqrt{W}A$  and a state preparation procedure for the state  $\sqrt{W}|b\rangle$ . These can then be used in conjunction with [Theorem 39](#) to solve QWLS. This gives us an algorithm with a better complexity as compared to when using the data structure access to prepare a block encoding of  $W$ ,  $A$  and  $L$ . The below lemmas show how to prepare the block-encoding of  $\sqrt{W}A$  and the state  $\frac{\sqrt{W}|b\rangle}{\|\sqrt{W}|b\rangle\|}$ .

**Lemma 46** (Efficiently preparing  $\sqrt{W}A$  in the Quantum Data Structure Model). *Let  $W \in \mathbb{R}^{N \times N}$  such that  $W = \text{diag}(w_1, w_2 \dots w_N)$  and  $w_{\max} := \max_i w_i$ , and  $A \in \mathbb{R}^{N \times d}$  be stored in an efficient data structure that can be accessed in superposition. Then for any  $\delta > 0$  there exists a*

$$(\sqrt{w_{\max}}\|A\|_F, \lceil \log(N+d) \rceil, \delta)$$

block-encoding of  $\sqrt{W}A$  that can be implemented at the cost  $\mathcal{O}(\text{polylog}(Nd/\delta))$ .

*Proof.*  $\forall j \in [N]$ , define

$$|\psi_j\rangle := \sqrt{\frac{w_j}{w_{\max}}} |j\rangle \frac{1}{\|A_{j,\cdot}\|} \sum_{k \in [d]} A_{j,k} |k\rangle.$$

Similarly,  $\forall k \in [d]$ , define

$$|\phi_k\rangle := \frac{1}{\|A\|_F} \left( \sum_{j \in [N]} \|A_{j,\cdot}\| |j\rangle \right) |k\rangle.$$

Observe that  $\forall j \in [N], k \in [d]$ ,

$$\langle \psi_j | \phi_k \rangle = \sqrt{\frac{w_j}{w_{\max}}} \frac{A_{j,k}}{\|A\|_F} = \frac{\langle j | \sqrt{W}A |k\rangle}{\sqrt{w_{\max}}\|A\|_F}.$$

Given quantum data structure accesses to  $W$  and  $A$ , once can construct quantum circuits  $W_R$  and  $W_L$  similar to  $U_L$  and  $U_R$  from [Lemma 3](#) that prepare  $|\phi_k\rangle$  and  $|\psi_j\rangle$  above.  $|\phi_k\rangle$  can be prepared just as in [Lemma 3](#), while  $|\psi_j\rangle$  can be prepared using controlled rotations on the state  $|\frac{w_j}{w_{\max}}\rangle$  (which can be constructed from the QRAM access to  $W$ ) after adding an ancilla qubit and the QRAM access to  $A$ . Thus,  $W_R^\dagger W_L$  is the required block encoding, which according to [Theorem 2](#) can be implemented using  $\text{polylog}(Nd/\delta)$  queries.  $\square$

**Lemma 47** (Efficiently preparing  $\sqrt{W}|b\rangle$  in the Quantum Data Structure Model). *Let  $b \in \mathbb{R}^N$  and  $W \in \mathbb{R}^{N \times N}$ . Suppose that  $b$  and  $W$  are stored in an efficient, quantum accessible data structures such that we have a state preparation procedure that acts as*

$$\begin{aligned} U_W &: |j\rangle |0\rangle \mapsto |j\rangle |w_j\rangle, \\ U_b &: |0\rangle \mapsto \sum_j \frac{b_j}{\|b\|} |j\rangle. \end{aligned}$$

Then for any  $\delta > 0$  we can prepare the quantum state that is  $\delta$ -close to  $\frac{\sqrt{W}|b\rangle}{\|\sqrt{W}|b\rangle\|}$  with constant success probability and at a cost of  $\mathcal{O}\left(\sqrt{\frac{w_{\max}}{w_{\min}}} \text{polylog}\left(\frac{N}{\delta}\right)\right)$ .

*Proof.* Use  $U_b$  to prepare the state

$$|b\rangle = \frac{1}{\|b\|} \sum_j b_j |j\rangle$$

in time  $\text{polylog}(N)$ . Then, apply the following transformation

$$\begin{aligned} |j\rangle |0\rangle |0\rangle &\mapsto |j\rangle |w_j\rangle |0\rangle \\ &\mapsto |j\rangle |w_j\rangle \left( \sqrt{\frac{w_j}{w_{\max}}} |0\rangle + \sqrt{1 - \frac{w_j}{w_{\max}}} |1\rangle \right) \\ &\mapsto |j\rangle |0\rangle \left( \sqrt{\frac{w_j}{w_{\max}}} |0\rangle + \sqrt{1 - \frac{w_j}{w_{\max}}} |1\rangle \right) \end{aligned}$$

which can again be applied using some controlled rotations, a square root circuit and  $U_W$ . This gives us the state (ignoring some blank registers)

$$\sum_j \left( \sqrt{\frac{w_j}{w_{\max}}} |0\rangle + \sqrt{1 - \frac{w_j}{w_{\max}}} |1\rangle \right) \frac{b_j}{\|b\|} |j\rangle. \quad (62)$$

The probability for the ancilla to be in  $|0\rangle$  state is

$$\Omega \left( \frac{w_{\min}}{w_{\max}} \right).$$

Thus performing  $\mathcal{O}\left(\sqrt{\frac{w_{\max}}{w_{\min}}}\right)$  rounds of amplitude amplification on  $|0\rangle$  gives us a constant probability of observing  $|0\rangle$ , and therefore obtaining the desired state  $\frac{\sqrt{W}|b\rangle}{\|\sqrt{W}|b\rangle\|}$ .  $\square$

Using the above two theorems, and the quantum extended least squares solver ([Theorem 39](#)), we can solve the quantum weighted least squares problem with a better complexity.

**Theorem 48** (Quantum Weighted Least Squares with General  $\ell_2$ -Regularization in the Quantum Data Structure Model). *Let  $A, L \in \mathbb{R}^{N \times d}$  with condition numbers  $\kappa_A, \kappa_L$  respectively be stored in an efficient quantum accessible data structure. Let  $W \in \mathbb{R}^{N \times N}$  be a diagonal matrix with largest and smallest singular values  $w_{\max}, w_{\min}$  respectively, which is also stored in an efficient quantum accessible data structure. Let  $b \in \mathbb{R}^N$  be a vector that can be accessed similarly. Define  $\|A_L\|$ ,  $\alpha$  and  $\kappa$  as*

$$\begin{aligned} \|A_L\| &:= \sqrt{\|A^T W A + \lambda L^T L\|}, \\ \alpha &:= \sqrt{w_{\max}} \|A\|_F + \sqrt{\lambda} \|L\|_F, \\ \kappa &:= \kappa_A \kappa_L \sqrt{\frac{w_{\max} \|A\|^2 + \lambda \|L\|^2}{w_{\min} \kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|L\|^2}} \end{aligned}$$

Then for any  $\delta > 0$  we can prepare a quantum state that is  $\delta$ -close to

$$\frac{(A^T W A + \lambda L^T L)^{-1} A^T W |b\rangle}{\|(A^T W A + \lambda L^T L)^{-1} A^T W |b\rangle\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O}\left(\kappa \left( \frac{\alpha}{\|A_L\|} + \sqrt{\frac{w_{\max}}{w_{\min}}} \right) \text{polylog}\left(\frac{Nd\kappa}{\delta}\right)\right). \quad (63)$$

*Proof.* The proof is similar in spirit to [Theorem 39](#). Choose some precision parameter  $\varepsilon > 0$  for accessing the data structure. Given accesses to  $W$  and  $A$ , we can use [Lemma 46](#) for some  $\varepsilon > 0$  to prepare a  $(\sqrt{w_{\max}} \|A\|_F, \lceil \log(N+d) \rceil, \varepsilon)$ -block-encoding of  $\sqrt{W}A$ , using  $T_A := \mathcal{O}(\text{polylog}(Nd/\varepsilon))$  queries to the data structure.

Similarly, [Lemma 3](#) allows us to build a  $(\|L\|_F, \lceil \log(N+d) \rceil, \varepsilon)$ -block-encoding of  $L$  using  $T_L := \mathcal{O}(\text{polylog}(Nd/\varepsilon))$  queries to the data structure.

Next, using [Lemma 47](#), for any  $\varepsilon_b > 0$ , we can prepare a state  $\varepsilon_b$ -close to  $|b'\rangle := \frac{\sqrt{W}|b\rangle}{\|\sqrt{W}|b\rangle\|}$ . This procedure requires  $T_b := \mathcal{O}\left(\sqrt{\frac{w_{\max}}{w_{\min}}}\text{polylog}(N/\varepsilon)\right)$  queries to the data structure.

Now we can invoke the OLS solver in [Theorem 35](#) with a precision of  $\delta_b$ , by passing  $\sqrt{W}A$  as the data matrix and  $\frac{\sqrt{W}|b\rangle}{\|\sqrt{W}|b\rangle\|}$  as the input state.

In order for the input block-encoding precision to satisfy the bound in [Equation 40](#), we choose  $\varepsilon$  to be

$$\varepsilon = \frac{\delta_b \|A_L\|^2}{64 \left(1 + \sqrt{\lambda}\right) \left(\sqrt{w_{\max}} \|A\|_F + \sqrt{\lambda} \|L\|_F\right) \kappa^3 \log^3(2\kappa/\delta_b)}$$

Finally, for the output state to be  $\delta$ -close to the required state, we choose  $\delta_b = \delta/2$  and  $\varepsilon_b = \delta/2\kappa$  to use the robustness result from [Lemma 11](#). This gives us

$$\begin{aligned} \log\left(\frac{1}{\varepsilon}\right) &= \log\left(\frac{64 \left(1 + \sqrt{\lambda}\right) \left(\sqrt{w_{\max}} \|A\|_F + \sqrt{\lambda} \|L\|_F\right) \kappa^3 \log^3(2\kappa/\delta_b)}{\delta_b \|A_L\|^2}\right) \\ &= \mathcal{O}\left(\text{polylog}\left(\frac{\kappa}{\delta}, \frac{\alpha}{\|A_L\|}\right)\right) \end{aligned}$$

Now we can substitute the cost of the individual components in the equation

$$\mathcal{O}\left(\kappa \log \kappa \left(\frac{\alpha}{\|A_L\|} (T_A + T_L) \log\left(\frac{\kappa}{\delta}\right) + T_b\right)\right),$$

to obtain the final complexity.  $\square$

Now, if instead of a quantum accessible data structure, the entries were stored such that we had a sparse access to them (defined in [Section 2.2.2](#)) we could use the superpositional queries to construct a block encoding similar to that in [Lemma 46](#) and a quantum state similar to [Lemma 47](#), with the same query complexities. Thus we have an algorithm similar to [Theorem 48](#) in the sparse access model as well. We directly state the complexity of our algorithm in this model.

**Theorem 49** (Quantum Weighted Least Squares with General  $\ell_2$ -Regularization in the Sparse Access Model). *Let  $A, L \in \mathbb{R}^{N \times d}$  with condition numbers  $\kappa_A, \kappa_L$  respectively be matrices that we have sparse access to. Let the row and column sparsities of  $A$  be  $s_r^A$  and  $s_c^A$  respectively. Similarly, let the row and column sparsities of  $L$  be  $s_r^L$  and  $s_c^L$ , respectively. Furthermore, let  $W \in \mathbb{R}^{N \times N}$  be a diagonal matrix with largest and smallest singular values  $w_{\max}, w_{\min}$  respectively, to which we also have sparse access. Let  $b \in \mathbb{R}^N$  be a vector that can be accessed similarly. Define  $\|A_L\|$ ,  $\alpha$  and  $\kappa$  as*

$$\begin{aligned} \|A_L\| &:= \sqrt{\|A^T W A + \lambda L^T L\|}, \\ \alpha &:= \sqrt{w_{\max} s_c^A s_r^A} + \sqrt{\lambda s_c^L s_r^L}, \\ \kappa &:= \kappa_A \kappa_L \sqrt{\frac{w_{\max} \|A\|^2 + \lambda \|L\|^2}{w_{\min} \kappa_L^2 \|A\|^2 + \lambda \kappa_A^2 \|L\|^2}} \end{aligned}$$

Then for any  $\delta > 0$  we can prepare a quantum state that is  $\delta$ -close to

$$\frac{(A^T W A + \lambda L^T L)^{-1} A^T W |b\rangle}{\|(A^T W A + \lambda L^T L)^{-1} A^T W |b\rangle\|}$$

with probability  $\Theta(1)$ , at a cost of

$$\mathcal{O}\left(\kappa \left(\frac{\alpha}{\|A_L\|} + \sqrt{\frac{w_{\max}}{w_{\min}}}\right) \text{polylog}\left(\frac{Nd\kappa}{\delta}\right)\right). \quad (64)$$

## 5 Future Directions

Our algorithms for quantum linear regression with general  $\ell_2$ -regularization made use of QSVT to implement various several matrix operations. However, it is possible to use QSVT directly to obtain the solution to *quantum ridge regression*. This requires computing a polynomial approximation for the transformation  $\sigma \mapsto \sigma/(\sigma^2 + \lambda)$ , to be applied on the singular values of  $A$ , which lie between  $[1/\kappa_A, 1]$ . However, it is not clear how to extend this while considering general  $\ell_2$ -regularization which involves obtaining polynomial approximations to directly implement transformations of the form  $\sigma \mapsto \sigma/(\sigma^2 + \lambda\tilde{\sigma}^2)$ , where  $\tilde{\sigma}$  is a singular value of the penalty matrix  $L$ . A monomial is no longer sufficient to approximate this quantum singular value transformation. It would be interesting to explore whether newly developed ideas of M-QSVT [RC22] can be used to implement such transformations directly with improved complexity.

While developing quantum machine learning algorithms, it is important to point out the caveats, even at the risk of being repetitive [Aar15]. Our quantum algorithms output a quantum state  $|x\rangle$  whose amplitudes encode the solution of the classical (regularized) linear regression problem. While given access to the data matrix and the penalty matrix, we achieve an exponential advantage over classical algorithms, this advantage is not generic. If similar assumptions ( $\ell_2$ -sample and query access) are provided to a classical device, Gilyén et al. developed a quantum algorithm [GST20] for ridge regression (building upon [CGL<sup>+</sup>20]) which has a running time in  $\mathcal{O}(\text{poly}(\kappa, \text{rank}(A), 1/\delta))$ . This implies that any quantum algorithm for this problem can be at most polynomially faster in  $\kappa$ . One might posit that similar quantum-inspired classical algorithms for general  $\ell_2$ -regression can also be developed.

Another future direction of research would be to recast our algorithms in the framework of adiabatic quantum computing (AQC) following the works of [LT20b, AL22]. Quantum algorithms for linear systems in this framework have the advantage that a linear dependence on  $\kappa$  can be obtained without using complicated subroutines like variable-time amplitude amplification. The strategy is to implement these problems in the AQC model and then use time-dependent Hamiltonian simulation [LW18] to obtain their complexities in the circuit model. One caveat is that, so far, time-dependent Hamiltonian simulation algorithms have only been developed in the sparse-access model and therefore the advantage of the generality of the block-encoding framework is lost.

In the future, it would also be interesting to explore other quantum algorithms for machine learning such as principal component regression and linear support vector machines [RML14] using QSVT. Finally, following the results of [CdW21], it would be interesting to investigate techniques for quantum machine learning that do not require the quantum linear systems algorithm as a subroutine.

## Acknowledgements

SC thanks András Gilyén, Stacey Jeffery and Jérémie Roland for useful discussions. SC is funded by the Faculty Seed Grant, IIT Hyderabad.

## References

- [Aar15] Scott Aaronson. Read the fine print. *Nature Physics*, 11(4):291–293, Apr 2015. doi:[10.1038/nphys3272](https://doi.org/10.1038/nphys3272).
- [AL22] Dong An and Lin Lin. Quantum linear system solver based on time-optimal adiabatic quantum computing and quantum approximate optimization algorithm. *ACM Transactions on Quantum Computing*, 3(2), mar 2022. doi:[10.1145/3498331](https://doi.org/10.1145/3498331).
- [Amb12] Andris Ambainis. Variable time amplitude amplification and quantum algorithms for linear algebra problems. In Christoph Dürr and Thomas Wilke, editors, *29th International Symposium on Theoretical Aspects of Computer Science (STACS 2012)*, volume 14 of

- Leibniz International Proceedings in Informatics (LIPIcs), pages 636–647, Dagstuhl, Germany, 2012. Schloss Dagstuhl–Leibniz-Zentrum fuer Informatik. doi:[10.4230/LIPIcs.STACS.2012.636](https://doi.org/10.4230/LIPIcs.STACS.2012.636).
- [Bis95] Chris M. Bishop. Training with noise is equivalent to tikhonov regularization. *Neural Computation*, 7(1):108–116, 1995. doi:[10.1162/neco.1995.7.1.108](https://doi.org/10.1162/neco.1995.7.1.108).
- [CdW21] Yanlin Chen and Ronald de Wolf. Quantum algorithms and lower bounds for linear regression with norm constraints. *arXiv preprint*, 2021. doi:[10.48550/ARXIV.2110.13086](https://doi.org/10.48550/ARXIV.2110.13086).
- [CGJ19] Shantanav Chakraborty, András Gilyén, and Stacey Jeffery. The Power of Block-Encoded Matrix Powers: Improved Regression Techniques via Faster Hamiltonian Simulation. In Christel Baier, Ioannis Chatzigiannakis, Paola Flocchini, and Stefano Leonardi, editors, *46th International Colloquium on Automata, Languages, and Programming (ICALP 2019)*, volume 132 of Leibniz International Proceedings in Informatics (LIPIcs), pages 33:1–33:14, Dagstuhl, Germany, 2019. Schloss Dagstuhl–Leibniz-Zentrum fuer Informatik. doi:[10.4230/LIPIcs.ICALP.2019.33](https://doi.org/10.4230/LIPIcs.ICALP.2019.33).
- [CGL<sup>+</sup>20] Nai-Hui Chia, András Gilyén, Tongyang Li, Han-Hsuan Lin, Ewin Tang, and Chunhao Wang. Sampling-Based Sublinear Low-Rank Matrix Arithmetic Framework for Dequantizing Quantum Machine Learning, page 387–400. Association for Computing Machinery, New York, NY, USA, 2020. URL: <https://doi.org/10.1145/3357713.3384314>.
- [CKS17] Andrew M. Childs, Robin Kothari, and Rolando D. Somma. Quantum algorithm for systems of linear equations with exponentially improved dependence on precision. *SIAM Journal on Computing*, 46(6):1920–1950, Jan 2017. doi:[10.1137/16M1087072](https://doi.org/10.1137/16M1087072).
- [CYGL22] Menghan Chen, Chaohua Yu, Gongde Guo, and Song Lin. Faster quantum ridge regression algorithm for prediction. *International Journal of Machine Learning and Cybernetics*, Apr 2022. doi:[10.1007/s13042-022-01526-6](https://doi.org/10.1007/s13042-022-01526-6).
- [EHN96] H.W. Engl, M. Hanke, and A. Neubauer. *Regularization of Inverse Problems*. Mathematics and Its Applications. Springer Netherlands, 1996. URL: <https://link.springer.com/book/9780792341574>.
- [GHO99] Gene H. Golub, Per Christian Hansen, and Dianne P. O’Leary. Tikhonov regularization and total least squares. *SIAM Journal on Matrix Analysis and Applications*, 21(1):185–194, 1999. doi:[10.1137/S0895479897326432](https://doi.org/10.1137/S0895479897326432).
- [GSLW19] András Gilyén, Yuan Su, Guang Hao Low, and Nathan Wiebe. Quantum singular value transformation and beyond: Exponential improvements for quantum matrix arithmetics. In *Proceedings of the 51st Annual ACM SIGACT Symposium on Theory of Computing, STOC 2019*, page 193–204, New York, NY, USA, 2019. Association for Computing Machinery. doi:[10.1145/3313276.3316366](https://doi.org/10.1145/3313276.3316366).
- [GST20] András Gilyén, Zhao Song, and Ewin Tang. An improved quantum-inspired algorithm for linear regression, 2020. doi:[10.48550/ARXIV.2009.07268](https://doi.org/10.48550/ARXIV.2009.07268).
- [GTC19] Yimin Ge, Jordi Tura, and J. Ignacio Cirac. Faster ground state preparation and high-precision ground energy estimation with fewer qubits. *Journal of Mathematical Physics*, 60(2):022202, 2019. doi:[10.1063/1.5027484](https://doi.org/10.1063/1.5027484).
- [Hem75] William J. Hemmerle. An explicit solution for generalized ridge regression. *Technometrics*, 17(3):309–314, 1975. URL: <http://www.jstor.org/stable/1268066>.
- [HH93] Martin Hanke and Per Christian Hansen. Regularization methods for large-scale problems. *Surv. Math. Ind.*, 3(4):253–315, 1993.

- [HHL09] Aram W. Harrow, Avinatan Hassidim, and Seth Lloyd. Quantum algorithm for linear systems of equations. *Physical Review Letters*, 103(15), Oct 2009. doi:10.1103/physrevlett.103.150502.
- [HK00] Arthur E. Hoerl and Robert W. Kennard. Ridge regression: Biased estimation for nonorthogonal problems. *Technometrics*, 42(1):80–86, 2000. URL: <http://www.jstor.org/stable/1271436>.
- [KKR06] Julia Kempe, Alexei Kitaev, and Oded Regev. The complexity of the local hamiltonian problem. *SIAM Journal on Computing*, 35(5):1070–1097, 2006. doi:10.1137/S0097539704445226.
- [KP17] Iordanis Kerenidis and Anupam Prakash. Quantum Recommendation Systems. In *8th Innovations in Theoretical Computer Science Conference (ITCS 2017)*, volume 67 of *Leibniz International Proceedings in Informatics (LIPIcs)*, pages 49:1–49:21, Dagstuhl, Germany, 2017. Schloss Dagstuhl–Leibniz-Zentrum fuer Informatik. doi:10.4230/LIPIcs.ITCS.2017.49.
- [KP20] Iordanis Kerenidis and Anupam Prakash. Quantum gradient descent for linear systems and least squares. *Phys. Rev. A*, 101:022316, Feb 2020. doi:10.1103/PhysRevA.101.022316.
- [LC17a] Guang Hao Low and Isaac L Chuang. Hamiltonian simulation by uniform spectral amplification. *arXiv:1707.05391*, 2017. doi:10.48550/ARXIV.1707.05391.
- [LC17b] Guang Hao Low and Isaac L. Chuang. Optimal hamiltonian simulation by quantum signal processing. *Phys. Rev. Lett.*, 118:010501, Jan 2017. doi:10.1103/PhysRevLett.118.010501.
- [LC19] Guang Hao Low and Isaac L. Chuang. Hamiltonian simulation by qubitization. *Quantum*, 3:163, Jul 2019. doi:10.22331/q-2019-07-12-163.
- [LMR14] Seth Lloyd, Masoud Mohseni, and Patrick Rebentrost. Quantum principal component analysis. *Nature Physics*, 10(9):631–633, Sep 2014. doi:10.1038/nphys3029.
- [Low17] Guang Hao Low. *Quantum signal processing by single-qubit dynamics*. PhD thesis, Massachusetts Institute of Technology, 2017. URL: <http://hdl.handle.net/1721.1/115025>.
- [LT20a] Lin Lin and Yu Tong. Near-optimal ground state preparation. *Quantum*, 4:372, December 2020. doi:10.22331/q-2020-12-14-372.
- [LT20b] Lin Lin and Yu Tong. Optimal polynomial based quantum eigenstate filtering with application to solving quantum linear systems. *Quantum*, 4:361, November 2020. doi:10.22331/q-2020-11-11-361.
- [LW18] Guang Hao Low and Nathan Wiebe. Hamiltonian simulation in the interaction picture. *arXiv preprint*, 2018. doi:10.48550/arXiv.1805.00675.
- [LYC16] Guang Hao Low, Theodore J. Yoder, and Isaac L. Chuang. Methodology of resonant equiangular composite quantum gates. *Phys. Rev. X*, 6:041067, Dec 2016. doi:10.1103/PhysRevX.6.041067.
- [Mar70] Donald W. Marquardt. Generalized inverses, ridge regression, biased linear estimation, and nonlinear estimation. *Technometrics*, 12(3):591–612, 1970. URL: <http://www.jstor.org/stable/1267205>.
- [MRTC21] John M. Martyn, Zane M. Rossi, Andrew K. Tan, and Isaac L. Chuang. Grand unification of quantum algorithms. *PRX Quantum*, 2:040203, Dec 2021. doi:10.1103/PRXQuantum.2.040203.

- [Mur12] Kevin P Murphy. Machine learning: a probabilistic perspective. MIT press, 2012. URL: <https://mitpress.mit.edu/books/machine-learning-1>.
- [Pra14] Anupam Prakash. Quantum Algorithms for Linear Algebra and Machine Learning. PhD thesis, EECS Department, University of California, Berkeley, Dec 2014. URL: <http://www2.eecs.berkeley.edu/Pubs/TechRpts/2014/EECS-2014-211.html>.
- [RC22] Zane M. Rossi and Isaac L. Chuang. Multivariable quantum signal processing (m-qsp): prophecies of the two-headed oracle. arXiv preprint, 2022. doi:10.48550/ARXIV.2205.06261.
- [RML14] Patrick Rebentrost, Masoud Mohseni, and Seth Lloyd. Quantum support vector machine for big data classification. Phys. Rev. Lett., 113:130503, Sep 2014. doi:10.1103/PhysRevLett.113.130503.
- [SSP16] Maria Schuld, Ilya Sinayskiy, and Francesco Petruccione. Prediction by linear regression on a quantum computer. Phys. Rev. A, 94:022342, Aug 2016. doi:10.1103/PhysRevA.94.022342.
- [SX20] Changpeng Shao and Hua Xiang. Quantum regularized least squares solver with parameter estimate. Quantum Information Processing, 19(4):113, Feb 2020. doi:10.1007/s11128-020-2615-9.
- [Tan19] Ewin Tang. A quantum-inspired classical algorithm for recommendation systems. In Proceedings of the 51st Annual ACM SIGACT Symposium on Theory of Computing, STOC 2019, page 217–228, New York, NY, USA, 2019. Association for Computing Machinery. doi:10.1145/3313276.3316310.
- [Vin78] Hrishikesh D. Vinod. A survey of ridge regression and related techniques for improvements over ordinary least squares. The Review of Economics and Statistics, 60(1):121–131, 1978. URL: <http://www.jstor.org/stable/1924340>.
- [vW15] Wessel N. van Wieringen. Lecture notes on ridge regression, 2015. doi:10.48550/ARXIV.1509.09169.
- [Wan17] Guoming Wang. Quantum algorithm for linear regression. Phys. Rev. A, 96:012335, Jul 2017. doi:10.1103/PhysRevA.96.012335.
- [WBL12] Nathan Wiebe, Daniel Braun, and Seth Lloyd. Quantum algorithm for data fitting. Phys. Rev. Lett., 109:050505, Aug 2012. doi:10.1103/PhysRevLett.109.050505.
- [YGW21] Chao-Hua Yu, Fei Gao, and Qiao-Yan Wen. An improved quantum algorithm for ridge regression. IEEE Transactions on Knowledge and Data Engineering, 33(3):858–866, 2021. doi:10.1109/TKDE.2019.2937491.

## A Algorithmic Primitives

This appendix contains detailed proofs for certain lemmas and corollaries in [Section 3](#), for completeness. These proofs are not necessary to understand the techniques and results of the paper, but may help the reader develop a better intuition for the methods used.

**Corollary 8** (Uniform Block Amplification). *Let  $A \in \mathbb{R}^{N \times d}$  and  $\delta \in (0, 1]$ . Suppose  $U$  is a  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$ , such that  $\varepsilon \leq \frac{\delta}{2}$ , that can be implemented at a cost of  $T_U$ . Then a  $(\sqrt{2}\|A\|, a+1, \delta)$ -block-encoding of  $A$  can be implemented at a cost of  $\mathcal{O}\left(\frac{\alpha T_U}{\|A\|} \log(\|A\|/\delta)\right)$ .*



*Proof.* We can re-interpret  $U$  as a  $(\alpha/\|A\|, a, \varepsilon/\|A\|)$ -block-encoding of  $A/\|A\|$ . Invoking [Lemma 7](#) with  $\gamma = \frac{\delta}{2\|A\|}$ , we get  $U'$ , a  $(\sqrt{2}, a+1, \varepsilon/\|A\| + \frac{\delta}{2\|A\|})$ -block-encoding of  $A/\|A\|$ , implemented at a cost of  $\mathcal{O}\left(\frac{\alpha}{\|A\|} T_U \log(\|A\|/\delta)\right)$  which is a  $(\sqrt{2}\|A\|, a+1, \delta)$ -block-encoding of  $A$ .  $\square$

**Lemma 9** (Applying a Block-encoded Matrix on a Quantum State). *Let  $A$  be an  $s$ -qubit operator such that its singular values lie in  $[\|A\|/\kappa, \|A\|]$ . Also let  $\delta \in (0, 1)$ , and  $U_A$  be an  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$ , such that*

$$\varepsilon \leq \frac{\delta\|A\|}{2\kappa},$$

*that can be implemented in time  $T_A$ . Furthermore, suppose  $|b\rangle$  be an  $s$ -qubit quantum state that can be prepared in time  $T_b$ . Then we can prepare a state that is  $\delta$ -close to  $\frac{A|b\rangle}{\|A|b\rangle}$  with success probability  $\Omega(1)$  at a cost of*

$$\mathcal{O}\left(\frac{\alpha\kappa}{\|A\|}(T_A + T_b)\right)$$

*Proof.* The proof is similar to Lemma 24 of [\[CGJ19\]](#). We have  $\|A|b\rangle\| \geq \frac{\|A\|}{\kappa}$ . By applying  $U_A$  to  $|0\rangle|b\rangle$  (implementable at a cost of  $T_A + T_b$ ), followed by  $\frac{\alpha\kappa}{\|A\|}$ -rounds of amplitude amplification (conditioned on having  $|0\rangle$  in the first register), we obtain a quantum state that within  $\delta$  of  $|0\rangle \otimes \frac{A|b\rangle}{\|A|b\rangle}$ .  $\square$

**Corollary 10** (Applying a pre-amplified Block-encoded Matrix on a Quantum State). *Let  $A$  be an  $s$ -qubit operator such that its singular values lie in  $[\|A\|/\kappa, \|A\|]$ . Also let  $\delta \in (0, 1)$ , and  $U_A$  be an  $(\alpha, a, \varepsilon)$ -block-encoding of  $A$ , such that*

$$\varepsilon \leq \frac{\delta\|A\|}{4\kappa},$$

*that can be implemented in time  $T_A$ . Furthermore, suppose  $|b\rangle$  be an  $s$ -qubit quantum state that can be prepared in time  $T_b$ . Then we can prepare a state that is  $\delta$ -close to  $\frac{A|b\rangle}{\|A|b\rangle}$  with success probability  $\Omega(1)$  at a cost of*

$$\mathcal{O}\left(\frac{\alpha\kappa}{\|A\|} \log\left(\frac{\kappa}{\delta}\right) T_A + \kappa T_b\right)$$

*Proof.* We first pre-amplify the unitary using [Corollary 8](#) with some  $\gamma \geq 2\varepsilon$ . We get a  $(\sqrt{2}\|A\|, a+1, \gamma)$ -block-encoding of  $A$  implemented at a cost of

$$T_{A'} := \mathcal{O}\left(\frac{\alpha T_A}{\|A\|} \log\left(\frac{\|A\|}{\gamma}\right)\right)$$

Now we invoke [Lemma 9](#) with  $\delta = \frac{2\kappa\gamma}{\|A\|}$  and the above unitary to prepare the state, which has a time complexity of

$$\mathcal{O}(\kappa(T_{A'} + T_b)) = \mathcal{O}\left(\frac{\alpha\kappa}{\|A\|} \log\left(\frac{\kappa}{\delta}\right) T_A + \kappa T_b\right)$$

$\square$

**Lemma 11** (Robustness of state preparation). *Let  $A$  be an  $s$ -qubit operator such that its singular values lie in  $[\frac{\|A\|}{\kappa}, \|A\|]$ . Suppose  $|b'\rangle$  is a quantum state that is  $\varepsilon/2\kappa$ -close to  $|b\rangle$  and  $|\psi\rangle$  is a quantum state that is  $\varepsilon/2$ -close to  $A|b'\rangle/\|A|b'\rangle$ . Then we have that  $|\psi\rangle$  is  $\varepsilon$ -close to  $A|b\rangle/\|A|b\rangle$ .*

*Proof.* We know that

$$\| |b\rangle - |b'\rangle \| \leq \frac{\varepsilon}{2\kappa}$$

and

$$\left\| |\psi\rangle - \frac{A|b'\rangle}{\|A|b'\rangle} \right\| \leq \frac{\varepsilon}{2}$$

For small enough  $\varepsilon \ll \kappa$ , we can assume that  $\|A|b\rangle\| \approx \|A|b'\rangle\|$ .

We can derive the final error as

$$\begin{aligned}
\left\| |\psi\rangle - \frac{A|b\rangle}{\|A|b\rangle\|} \right\| &= \left\| |\psi\rangle - \frac{A|b\rangle - A|b'\rangle + A|b'\rangle}{\|A|b\rangle\|} \right\| \\
&= \left\| |\psi\rangle - \frac{A|b'\rangle}{\|A|b\rangle\|} + \frac{A|b'\rangle - A|b\rangle}{\|A|b\rangle\|} \right\| \\
&\leq \left\| |\psi\rangle - \frac{A|b'\rangle}{\|A|b'\rangle\|} \right\| + \left\| \frac{A|b'\rangle - A|b\rangle}{\|A|b\rangle\|} \right\| \\
&\leq \frac{\varepsilon}{2} + \frac{\|A\| \| |b\rangle - |b'\rangle \|}{\|A|b\rangle\|} \\
&\leq \frac{\varepsilon}{2} + \frac{\varepsilon}{2} \\
&= \varepsilon
\end{aligned}$$

□

## A.1 Arithmetic with Block-Encoded Matrices

**Lemma 13** (Linear Combination of Block Encoded Matrices). *For each  $j \in \{0, \dots, m-1\}$ , let  $A_j$  be an  $s$ -qubit operator, and  $y_j \in \mathbb{R}^+$ . Let  $U_j$  be a  $(\alpha_j, a_j, \varepsilon_j)$ -block-encoding of  $A_j$ , implemented in time  $T_j$ . Define the matrix  $A = \sum_j y_j A_j$ , and the vector  $\eta \in \mathbb{R}^m$  s.t.  $\eta_j = y_j \alpha_j$ . Let  $U_\eta$  be a  $\eta$  state-preparation unitary, implemented in time  $T_\eta$ . Then we can implement a*

$$\left( \sum_j y_j \alpha_j, \max_j(a_j) + s, \sum_j y_j \varepsilon_j \right)$$

block-encoding of  $A$  at a cost of  $\mathcal{O}(\sum_j T_j + T_\eta)$ .

*Proof.* Let  $a = \max_j(a_j) + s$  and  $\alpha = \sum_j y_j \alpha_j$ . For each  $j \in \{0, \dots, m-1\}$ , construct the extended unitary  $U'_j$  by padding ancillas to  $U_j$ , i.e.  $U'_j = I_{a-s-a_j} \otimes U_j$ . Note that  $U'_j$  is a  $(\alpha_j, a-s, \varepsilon_j)$ -block-encoding of  $A_j$ . Let  $B_j = (\langle 0|^{a_j} \otimes I_s) U_j (|0\rangle^{a_j} \otimes I_s)$  denote the top left block of  $U_j$  and  $U'_j$ , and observe that  $\|A_j - \alpha_j B_j\| \leq \varepsilon_j$ . We also construct  $P$  — an  $\eta$  state-preparation unitary s.t.  $P|0\rangle = \sum_j \sqrt{y_j \alpha_j} |j\rangle$  — by invoking [Lemma 12](#).

Consider the unitary  $W = (P^\dagger \otimes I_{a-1} \otimes I_s) (\sum_j |j\rangle\langle j| \otimes U'_j) (P \otimes I_{a-1} \otimes I_s)$ . This is a  $(\alpha, a, \varepsilon)$ -block-encoding of  $A = \sum_j y_j A_j$ , where  $\varepsilon$  is computed as:

$$\begin{aligned}
\|A - \alpha(\langle 0|^a \otimes I_s) W (|0\rangle^a \otimes I_s)\| &= \left\| \sum_{j=0}^{m-1} y_j A_j - \alpha(\langle 0|^a \otimes I_s) W (|0\rangle^a \otimes I_s) \right\| \\
&= \left\| \sum_j y_j A_j - \alpha(\langle 0|^a \otimes I_s) \left( \sum_j P^\dagger |j\rangle\langle j| P \otimes U'_j \right) (|0\rangle^a \otimes I_s) \right\| \\
&= \left\| \sum_j y_j A_j - \alpha \sum_j \langle 0| P^\dagger |j\rangle\langle j| P |0\rangle \otimes B_j \right\| \\
&= \left\| \sum_j \left( y_j A_j - \alpha \langle 0| P^\dagger |j\rangle\langle j| P |0\rangle B_j \right) \right\|
\end{aligned}$$

$$\begin{aligned}
&= \left\| \sum_j \left( y_j A_j - \alpha \left( \frac{y_j \alpha_j}{\alpha} \right) B_j \right) \right\| \\
&\leq \sum_j y_j \|A_j - \alpha_j B_j\| \\
&\leq \sum_j y_j \varepsilon_j = \varepsilon
\end{aligned}$$

□

**Lemma 17** (Tensor Product of Block Encoded Matrices). *Let  $U_1$  and  $U_2$  be  $(\alpha, a, \varepsilon_1)$  and  $(\beta, b, \varepsilon_2)$ -block-encodings of  $A_1$  and  $A_2$ ,  $s$  and  $t$ -qubit operators, implemented in time  $T_1$  and  $T_2$  respectively. Define  $S := \Pi_{i=1}^s \text{SWAP}_{a+b+i}^{a+i}$ . Then,  $S(U_1 \otimes U_2)S^\dagger$  is an  $(\alpha\beta, a+b, \alpha\varepsilon_2 + \beta\varepsilon_1 + \varepsilon_1\varepsilon_2)$  block-encoding of  $A_1 \otimes A_2$ , implemented at a cost of  $\mathcal{O}(T_1 + T_2)$ .*

*Proof.* From the property of Kronecker products  $(A \otimes B)(C \otimes D) = (AC) \otimes (BD)$ . For  $j \in \{1, 2\}$  let  $\tilde{A}_j = (\langle 0|^{\otimes a_j} \otimes I_s) U_j (|0\rangle^{\otimes a_j} \otimes I_s)$ . Then it follows that

$$\left( \langle 0|^{\otimes a} \otimes I_s \otimes \langle 0|^{\otimes b} \otimes I_t \right) (U_1 \otimes U_2) \left( |0\rangle^{\otimes a} \otimes I_s \otimes |0\rangle^{\otimes b} \otimes I_t \right) = \tilde{A}_1 \otimes \tilde{A}_2 \quad (65)$$

Therefore  $\tilde{A}_1 \otimes \tilde{A}_2$  is block-encoded in  $U_1 \otimes U_2$  as a non-principal block-encoding, and we can use SWAP gates to move it to the principal block as follows.

$$\begin{aligned}
S \left( |0\rangle^{\otimes a} \otimes I_s |0\rangle^{\otimes b} \otimes I_t \right) &= \Pi_{i=1}^s \text{SWAP}_{a+b+i}^{a+i} \left( |0\rangle^{\otimes a} \otimes I_s |0\rangle^{\otimes b} \otimes I_t \right) \\
&= \Pi_{i=1}^{s-1} \text{SWAP}_{a+b+i}^{a+i} \text{SWAP}_{a+b+s}^{a+s} \left( |0\rangle^{\otimes a} \otimes I_s |0\rangle^{\otimes b} \otimes I_t \right) \\
&= \Pi_{i=1}^{s-1} \text{SWAP}_{a+b+i}^{a+i} \left( |0\rangle^{\otimes a} \otimes I_{s-1} |0\rangle^{\otimes b} \otimes I_{t+1} \right) \\
&= \dots \\
&= |0\rangle^{\otimes a+b} \otimes I_{s+t}
\end{aligned}$$

Similarly,

$$\left( \langle 0|^{\otimes a} \otimes I_s \otimes \langle 0|^{\otimes b} \otimes I_t \right) S^\dagger = \langle 0|^{\otimes a+b} \otimes I_{s+t}.$$

From Equation 65 we have

$$\begin{aligned}
\tilde{A}_1 \otimes \tilde{A}_2 &= \left( \langle 0|^{\otimes a} \otimes I_s \otimes \langle 0|^{\otimes b} \otimes I_t \right) S^\dagger S(U_1 \otimes U_2) S^\dagger S \left( |0\rangle^{\otimes a} \otimes I_s |0\rangle^{\otimes b} \otimes I_t \right) \\
&= \left( \langle 0|^{\otimes a+b} \otimes I_{s+t} \right) S(U_1 \otimes U_2) S^\dagger \left( |0\rangle^{\otimes a+b} \otimes I_{s+t} \right)
\end{aligned}$$

Next, we look at the subnormalization and error terms.

$$\begin{aligned}
\|A_1 \otimes A_2 - \alpha\beta \tilde{A}_1 \otimes \tilde{A}_2\|_2 &\leq \|(\alpha \tilde{A}_1 + \varepsilon_1 I_s) \otimes (\beta \tilde{A}_2 + \varepsilon_2 I_t) - \alpha \tilde{A}_1 \otimes \beta \tilde{A}_2\|_2 \\
&= \|\alpha \tilde{A}_1 \otimes \varepsilon_2 I_2 + \varepsilon_1 I_s \otimes \beta \tilde{A}_2 + \varepsilon_1 I_s \otimes \varepsilon_2 I_2\|_2 \\
&\leq \alpha \varepsilon_2 \|\tilde{A}_1\|_2 + \beta \varepsilon_2 \|\tilde{A}_2\|_2 + \varepsilon_1 \varepsilon_2 \\
&= \alpha \varepsilon_2 + \beta \varepsilon_1 + \varepsilon_1 \varepsilon_2
\end{aligned}$$

where we have used  $\|A_1\|_2 \leq \alpha \|\tilde{A}_1\|_2 + \varepsilon_1$  and  $\|\tilde{A}_1\|_2 \leq 1$  and similarly for  $A_2$ .

□