

Improved composable key rates for CV-QKD

Stefano Pirandola and Panagiotis Papanastasiou

Department of Computer Science, University of York, York YO10 5GH, United Kingdom

Modern security proofs of quantum key distribution (QKD) must take finite-size effects and composable aspects into consideration. This is also the case for continuous-variable (CV) protocols which are based on the transmission and detection of bosonic coherent states. In this paper, we build on previous theory to provide an improved formula for the composable key rate of a generic CV-QKD protocol under collective attacks. We then apply the refined formula to typical protocols, based on Gaussian modulation, comparing their performance with previous results.

I. INTRODUCTION

Quantum key distribution (QKD) is arguably one of the most advanced areas in quantum information, both theoretically and experimentally [1–4]. In particular, the continuous-variable (CV) version of QKD has been gradually improved in various aspects, such as the rigor of security proof, the speed of data processing techniques, and the distance of experimental implementations [1, Secs. 7 and 8]. In terms of CV-QKD theory and security proofs [5–23], the first asymptotic analyses were extended to finite-size effects and, later, to composable formulations [1, Sec. 9].

In this paper, we build on previous composable security analyses of CV-QKD, specifically the theory from Refs. [18–20], to provide an improved and refined formula for the secret key rate of a generic CV-QKD protocol under collective attacks. We then apply this formula to specific types of CV-QKD protocols, based on a continuous (Gaussian [24, 25]) modulation of coherent states, including the one-way protocols based on homodyne or heterodyne detection, and the CV measurement device independent (MDI) protocol [26, 27]. In all cases, we show the advantage of the new formulation in terms of better rate and reduced block size, with respect to previous over-pessimistic results. This is important in order to make CV-QKD accessible to realistic implementations.

In Sec. II, we present our improved composable formula for the key rate of CV-QKD under collective attacks. In Sec. III, we apply the formula to various CV-QKD protocols, comparing it with previous results. Finally, Sec. IV is for conclusions.

II. COMPOSABLE KEY RATE UNDER COLLECTIVE ATTACKS

A. Output state of the protocol

Consider a CV-QKD protocol where N single-mode systems are transmitted from Alice A to Bob B . A portion n of these systems will be used for key generation, while a portion $m = N - n$ will be used for parameter estimation. Let us assume that the bosonic communication channel depends on a number n_{pm} of parameters $\mathbf{p} = (p_1, p_2, \dots)$ (e.g., transmissivity and thermal noise

of the channel). These parameters are estimated by the parties and we will account for this partial knowledge at the end of the derivations. For now, let us assume that Alice and Bob have perfect knowledge of \mathbf{p} .

Under the action of a collective attack, the output classical-quantum (CQ) state of Alice (A), Bob (B) and Eve (E) has the tensor-structure form $\rho^{\otimes n}$, where

$$\rho = \sum_{k,l} p(k,l) |k\rangle_A \langle k| \otimes |l\rangle_B \langle l| \otimes \rho_E^{k,l}. \quad (1)$$

Here Alice's variable k and Bob's variable l are both multi-ary symbols (equivalent to d -bit strings) and $p(k,l)$ is their joint probability distribution (depending on the specific interaction used by Eve).

In the case of a protocol based on the Gaussian modulation of coherent states, the multi-ary symbols are the output of an analog-to-digital conversion (ADC) from Alice's and Bob's quadratures, x and y , i.e., we have $x \xrightarrow{\text{ADC}} k$ and $y \xrightarrow{\text{ADC}} l$. If the protocol is based on the homodyne detection, we have that y is randomly created by a random switching between the q and p quadrature (with Alice choosing the corresponding quadrature for each instance, upon Bob's classical communication). If the protocol is based on the heterodyne detection, both q and p quadratures are used, so we have $y = (q_B, p_B) \xrightarrow{\text{ADC}} (l_q, l_p)$ followed by the concatenation $l = l_q l_p$ (this is also the approach for CV-MDI). Finally, in the case of CV-QKD protocols based on discrete-alphabet coherent states, no ADC is necessary and the discretized variables are directly expressed by the encoding variables.

Whatever protocol is used, for n uses, there will be two sequences of multi-ary symbols, $\mathbf{k} = (k_1, k_2, \dots)$ and $\mathbf{l} = (l_1, l_2, \dots)$, each with length n , so their equivalent binary length would be nd . The associated probability is $p(\mathbf{k}, \mathbf{l}) = \prod_{i=1}^n p(k_i, l_i)$, and the total n -use state reads

$$\rho^{\otimes n} = \sum_{\mathbf{k}, \mathbf{l}} p(\mathbf{k}, \mathbf{l}) |\mathbf{k}\rangle_{A^n} \langle \mathbf{k}| \otimes |\mathbf{l}\rangle_{B^n} \langle \mathbf{l}| \otimes \rho_E^{\mathbf{k}, \mathbf{l}}, \quad (2)$$

where $|\mathbf{k}\rangle = \otimes_{i=1}^n |k_i\rangle$, $|\mathbf{l}\rangle = \otimes_{i=1}^n |l_i\rangle$ and

$$\rho_E^{\mathbf{k}, \mathbf{l}} = \otimes_{i=1}^n \rho_E^{k_i, l_i}. \quad (3)$$

B. Error Correction and epsilon correctness

Alice and Bob will then perform procedures of error correction (EC) and privacy amplification (PA) over the state $\rho^{\otimes n}$ with the final goal to approximate the s_n -bit ideal CQ state

$$\rho_{\text{ideal}}^n = \omega_{AB}^n \otimes \rho_{E^n}, \quad (4)$$

$$\omega_{AB}^n := 2^{-s_n} \sum_{\mathbf{z}} |\mathbf{z}\rangle_{A^n} \langle \mathbf{z}| \otimes |\mathbf{z}\rangle_{B^n} \langle \mathbf{z}|, \quad (5)$$

where Alice's and Bob's classical systems contain the same random binary sequence $\mathbf{z} = (z_1, z_2, \dots)$ of length s_n , from which Eve is completely decoupled (note that the final output is a binary sequence even if we start from multi-ary symbols k and l for Alice and Bob).

In reverse reconciliation, Alice attempts to reconstruct Bob's sequence \mathbf{l} . During EC, Bob publicly reveals leak_{ec} bits of information to help Alice to compute her guess $\hat{\mathbf{l}}$ of \mathbf{l} starting from her local data \mathbf{k} . In practical schemes of EC (based on linear codes, such as LDPC codes), these leak_{ec} bits of information correspond to a syndrome that Bob computes over his sequence \mathbf{l} , interpreted as a noisy codeword of a linear code agreed with Alice.

Then, as a verification, Alice and Bob publicly compare hashes computed over \mathbf{l} and $\hat{\mathbf{l}}$. If these hashes coincide, the two parties go ahead with probability p_{ec} , otherwise they abort the protocol. The hash comparison requires Bob sending $\lceil -\log_2 \varepsilon_{\text{cor}} \rceil$ bits to Alice for some suitable ε_{cor} (the number of these bits is negligible in comparison to leak_{ec}). Parameter ε_{cor} is called ε -correctness [28, Sec. 4.3] and it bounds the probability that the sequences are different even if their hashes coincide. The probability of such an error is bounded by [29]

$$p_{\text{ec}} \text{Prob}(\hat{\mathbf{l}} \neq \mathbf{l} | \text{no abort}) \leq p_{\text{ec}} 2^{-\lceil -\log_2 \varepsilon_{\text{cor}} \rceil} \leq \varepsilon_{\text{cor}}. \quad (6)$$

Upon success of EC and with residual error probability ε_{cor} , Alice's sequence $\hat{\mathbf{l}}$ is equal to Bob's sequence \mathbf{l} , where the latter remains unchanged during the process of EC, so that it maintains its i.i.d. feature (under the assumption of collective attacks). This means that, with probability p_{ec} and up to ε_{cor} , the pair $\{\hat{\mathbf{l}}, \mathbf{l}\}$ is i.i.d. and the conditional (post-EC) CQ state of Alice, Bob and Eve is in a tensor-product form $\tilde{\rho}^{\otimes n}$. We may write

$$\tilde{\rho}^{\otimes n} = p_{\text{ec}}^{-1} \sum_{\hat{\mathbf{l}}, \mathbf{l}} p(\hat{\mathbf{l}}, \mathbf{l}) |\hat{\mathbf{l}}\rangle_{A^n} \langle \hat{\mathbf{l}}| \otimes |\mathbf{l}\rangle_{B^n} \langle \mathbf{l}| \otimes \rho_{E^n}^{\hat{\mathbf{l}}, \mathbf{l}}, \quad (7)$$

where $|\hat{\mathbf{l}}\rangle = \otimes_{i=1}^n |\hat{l}_i\rangle$ and $\rho_{E^n}^{\hat{\mathbf{l}}, \mathbf{l}} = \otimes_{i=1}^n \rho_E^{l_i, \hat{l}_i}$.

It is important to remark that recognizing this i.i.d. tensor-product structure is crucial in order to get our improved rate, whereas previous treatments [18–20] ignored this aspect and assumed the possibility of EC procedures breaking this feature (which is however not the case in standard implementations, e.g., based on LDPC codes).

C. Privacy amplification and epsilon secrecy

The next step is PA which realizes the randomness extraction decoupling Eve. The parties agree to use a function f randomly chosen from a family F of 2-universal hash functions with a total of $|F|$ possible choices (note that it is necessary to randomize over the hash functions as discussed in Ref. [30]). In this way they compress their sequences $\{\hat{\mathbf{l}}, \mathbf{l}\}$ into a key pair $\{\hat{\mathbf{s}}, \mathbf{s}\}$ of $s_n < n$ random bits. The process of PA can be described by a CPTP map $\rho_F \otimes \tilde{\rho}_{ABE}^{\otimes n} \rightarrow \bar{\rho}_{ABEF}^n$, where

$$\bar{\rho}_{ABEF}^n = p_{\text{ec}}^{-1} \sum_{f, \hat{\mathbf{s}}, \mathbf{s}} \frac{p(\hat{\mathbf{s}}, \mathbf{s})}{|F|} \times |\hat{\mathbf{s}}\rangle_{A^n} \langle \hat{\mathbf{s}}| \otimes |\mathbf{s}\rangle_{B^n} \langle \mathbf{s}| \otimes \rho_{E^n}^{f, \hat{\mathbf{s}}, \mathbf{s}} \otimes |f\rangle_F \langle f|. \quad (8)$$

This also means that Alice's and Bob's sequences undergo data processing which cannot increase their distinguishability, i.e., we have

$$\text{Prob}(\hat{\mathbf{s}} \neq \mathbf{s} | \text{no abort}) \leq \text{Prob}(\hat{\mathbf{l}} \neq \mathbf{l} | \text{no abort}). \quad (9)$$

By tracing Alice, we can write the reduced state of Bob (containing the key) and Eve

$$\bar{\rho}_{BEF}^n = p_{\text{ec}}^{-1} \sum_{f, \hat{\mathbf{s}}, \mathbf{s}} \frac{p(\hat{\mathbf{s}}, \mathbf{s})}{|F|} |\mathbf{s}\rangle_{B^n} \langle \mathbf{s}| \otimes \rho_{E^n}^{f, \hat{\mathbf{s}}, \mathbf{s}} \otimes |f\rangle_F \langle f|. \quad (10)$$

On the latter state we impose the condition of ε -secrecy for Bob. This means that the distance from the ideal state $\omega_B^n \otimes \rho_{E^n F}$ is less than ε_{sec} , where $\omega_B^n = 2^{-s_n} \sum_{\mathbf{z}} |\mathbf{z}\rangle_{B^n} \langle \mathbf{z}|$. Basically, one has to impose

$$p_{\text{ec}} D(\bar{\rho}_{BEF}^n, \omega_B^n \otimes \rho_{E^n F}) \leq \varepsilon_{\text{sec}}. \quad (11)$$

D. Combining correctness and secrecy into epsilon security

Following Ref. [28, Th. 4.1], we can combine the features of correctness and secrecy into a single epsilon parameter. In fact, if Eqs. (6) and (11) hold, then we may write the condition for ε -security for Alice and Bob

$$p_{\text{ec}} D(\bar{\rho}_{ABEF}^n, \omega_{AB}^n \otimes \rho_{E^n F}) \leq \varepsilon := \varepsilon_{\text{cor}} + \varepsilon_{\text{sec}}. \quad (12)$$

It is instructive to repeat the proof of this result from Ref. [28, Sec. 4.3].

Proof. Let us define the following state, similar to $\bar{\rho}_{ABEF}^n$ but where Alice's system is copied from Bob's so they have exactly the same key string

$$\bar{\gamma}_{ABEF}^n = p_{\text{ec}}^{-1} \sum_{f, \hat{\mathbf{s}}, \mathbf{s}} \frac{p(\hat{\mathbf{s}}, \mathbf{s})}{|F|} \times |\mathbf{s}\rangle_{A^n} \langle \mathbf{s}| \otimes |\mathbf{s}\rangle_{B^n} \langle \mathbf{s}| \otimes \rho_{E^n}^{f, \hat{\mathbf{s}}, \mathbf{s}} \otimes |f\rangle_F \langle f|. \quad (13)$$

Then, we can use the triangle inequality to write

$$\begin{aligned} D(\bar{\rho}_{ABEF}^n, \omega_{AB}^n \otimes \rho_{E^n F}) &\leq \\ D(\bar{\rho}_{ABEF}^n, \bar{\gamma}_{ABEF}^n) + D(\bar{\gamma}_{ABEF}^n, \omega_{AB}^n \otimes \rho_{E^n F}). \end{aligned} \quad (14)$$

The first term accounts for correctness and can be bounded as follows

$$\begin{aligned} &D(\bar{\rho}_{ABEF}^n, \bar{\gamma}_{ABEF}^n) \\ &\leq p_{\text{ec}}^{-1} \sum_{f, \hat{s}, \mathbf{s}} \frac{p(\hat{\mathbf{s}}, \mathbf{s})}{|F|} D(|\hat{\mathbf{s}}\rangle_{A^n} \langle \hat{\mathbf{s}}|, |\mathbf{s}\rangle_{A^n} \langle \mathbf{s}|) \\ &= \sum_{\hat{\mathbf{s}} \neq \mathbf{s}} \frac{p(\hat{\mathbf{s}}, \mathbf{s})}{p_{\text{ec}}} \\ &= \text{Prob}(\hat{\mathbf{s}} \neq \mathbf{s} | \text{no abort}) \\ &\leq \text{Prob}(\hat{\mathbf{1}} \neq \mathbf{1} | \text{no abort}). \end{aligned} \quad (15)$$

The second term accounts for secrecy and can be bounded as follows

$$\begin{aligned} &D(\bar{\gamma}_{ABEF}^n, \omega_{AB}^n \otimes \rho_{E^n F}) \\ &= D(\bar{\gamma}_{BEF}^n, \omega_B^n \otimes \rho_{E^n F}) \\ &= D(\bar{\rho}_{BEF}^n, \omega_B^n \otimes \rho_{E^n F}). \end{aligned} \quad (16)$$

Thus we have

$$\begin{aligned} &p_{\text{ec}} D(\bar{\rho}_{ABEF}^n, \omega_{AB}^n \otimes \rho_{E^n F}) \\ &\leq p_{\text{ec}} \text{Prob}(\hat{\mathbf{1}} \neq \mathbf{1} | \text{no abort}) \\ &\quad + p_{\text{ec}} D(\bar{\rho}_{BEF}^n, \omega_B^n \otimes \rho_{E^n F}). \end{aligned} \quad (17)$$

Using Eqs. (6) and (11) in Eq. (17) leads to Eq. (12). ■

E. Leftover hash bound

We now resort to Cor. 5.6.1 of Ref. [33]. Consider a family F of 2-universal hash functions. Assume that we applied the hashing function to Bob's system, i.e., $\rho_F \otimes \bar{\rho}_{BE}^{\otimes n} \rightarrow \bar{\rho}_{BEF}^n$. Then, for any ε_s , we may bound the distance of the privacy amplified state $\bar{\rho}_{BEF}^n$ from the ideal state ω_B^n containing s_n random and decoupled bits, i.e.,

$$D(\bar{\rho}_{BEF}^n, \omega_B^n \otimes \rho_{E^n F}) \leq \varepsilon_s + \frac{1}{2} \sqrt{2^{s_n - H_{\min}^{\varepsilon_s}(B^n|E^n)_{\bar{\rho}^{\otimes n}}}}, \quad (18)$$

where $\bar{\rho}^{\otimes n} = \bar{\rho}_{BE}^{\otimes n}$ (before PA and after EC).

Now let us impose

$$\varepsilon_s + \frac{1}{2} \sqrt{2^{s_n - H_{\min}^{\varepsilon_s}(B^n|E^n)_{\bar{\rho}^{\otimes n}}}} \leq \varepsilon_{\text{sec}}. \quad (19)$$

It is clear that, via Eq. (18), this imposes the secrecy condition of Eq. (11). Furthermore, if we also impose the correctness condition of Eq. (6), then we reach the condition of epsilon security for Alice and Bob [see Eq. (12)].

Setting $\varepsilon_h := \varepsilon_{\text{sec}} - \varepsilon_s$ and re-arranging Eq. (19), we derive the following upper-bound for the binary length of the key

$$s_n \leq H_{\min}^{\varepsilon_s}(B^n|E^n)_{\bar{\rho}^{\otimes n}} + 2 \log_2(2\varepsilon_h). \quad (20)$$

Thus, if we want the protocol to be epsilon-secure $\varepsilon := \varepsilon_{\text{cor}} + \varepsilon_{\text{sec}} = \varepsilon_{\text{cor}} + \varepsilon_s + \varepsilon_h$, the length of the key cannot exceed the right-hand side of Eq. (20).

F. Including the leakage due to EC

The procedure above allows us to reduce the state to Bob and Eve's state $\bar{\rho}_{BE}^{\otimes n}$ before PA and after EC, i.e.,

$$\bar{\rho}_{BE}^{\otimes n} = p_{\text{ec}}^{-1} \sum_{\hat{\mathbf{l}}, \mathbf{l}} p(\hat{\mathbf{l}}, \mathbf{l}) |\mathbf{l}\rangle_{B^n} \langle \mathbf{l}| \otimes \rho_{E^n}^{\hat{\mathbf{l}}, \mathbf{l}}. \quad (21)$$

Here we can better describe Eve's system E^n as $E^n R$, where E^n are the systems used by Eve during the quantum communication while R is a register of dimension $\dim_R = 2^{\text{leak}_{\text{ec}} + \lceil -\log_2 \varepsilon_{\text{cor}} \rceil}$ and used to store the bits leaked during EC. Then, the chain rule for the smooth-min entropy leads to

$$\begin{aligned} H_{\min}^{\varepsilon_s}(B^n|E^n R)_{\bar{\rho}^{\otimes n}} &\geq H_{\min}^{\varepsilon_s}(B^n|E^n)_{\bar{\rho}^{\otimes n}} - \log_2 \dim_R \\ &= H_{\min}^{\varepsilon_s}(B^n|E^n)_{\bar{\rho}^{\otimes n}} - \text{leak}_{\text{ec}} - \lceil -\log_2 \varepsilon_{\text{cor}} \rceil. \\ &\geq H_{\min}^{\varepsilon_s}(B^n|E^n)_{\bar{\rho}^{\otimes n}} - \text{leak}_{\text{ec}} - \log_2(2/\varepsilon_{\text{cor}}). \end{aligned} \quad (22)$$

We then replace the above expression in Eq. (20), which leads to a stricter upper bound for the key length

$$\begin{aligned} s_n &\leq H_{\min}^{\varepsilon_s}(B^n|E^n)_{\bar{\rho}^{\otimes n}} + 2 \log_2(2\varepsilon_h) \\ &\quad - \text{leak}_{\text{ec}} - \log_2(2/\varepsilon_{\text{cor}}) \\ &= H_{\min}^{\varepsilon_s}(B^n|E^n)_{\bar{\rho}^{\otimes n}} + \log_2(2\varepsilon_h^2 \varepsilon_{\text{cor}}) - \text{leak}_{\text{ec}}. \end{aligned} \quad (23)$$

G. Asymptotic equipartition property

Note that the post-EC state of Bob and Eve has the following tensor-product structure

$$\begin{aligned} \bar{\rho}_{BE}^{\otimes n} &= \left[p_{\text{ec}}^{-1} \sum_{\hat{l}, l} p(\hat{l}, l) |l\rangle_B \langle l| \otimes \rho_E^{\hat{l}, l} \right]^{\otimes n} \\ &= \left[\sum_l p(l) |l\rangle_B \langle l| \otimes \tilde{\rho}_E^l \right]^{\otimes n}, \end{aligned} \quad (24)$$

where we have set

$$\tilde{\rho}_E^l := \sum_{\hat{l}} p_{\text{ec}}^{-1} p(\hat{l}, l) \rho_E^{\hat{l}, l}. \quad (25)$$

Because of the tensor-copy structure, we can bound the smooth-min entropy and reduce the computation to the

single-copy state $\tilde{\rho}_{BE}$. This is the asymptotic equipartition property (AEP) [32, Cor. 6.5]

$$H_{\min}^{\varepsilon_s}(B^n|E^n)_{\tilde{\rho}^{\otimes n}} \geq nH(B|E)_{\tilde{\rho}} - \sqrt{n}\Delta_{\text{aep}}, \quad (26)$$

where $H(B|E)_{\tilde{\rho}}$ is the conditional von Neumann entropy computed over the single-copy state $\tilde{\rho}_{BE}$, and

$$\begin{aligned} \Delta_{\text{aep}} &:= 4 \log_2 \left(\sqrt{\aleph} + 2 \right) \sqrt{-\log_2 \left(1 - \sqrt{1 - \varepsilon_s^2} \right)} \\ &\simeq 4 \log_2 \left(\sqrt{\aleph} + 2 \right) \sqrt{\log_2(2/\varepsilon_s^2)}, \end{aligned} \quad (27)$$

with $\aleph = 2^d$ being the cardinality of the discretized variable l (see Ref. [32, Th. 6.4] and Ref. [19, Sec. 2.F.1]).

H. Connecting the formulas to pre-EC state

In Eq. (26), we see that Bob and Eve's post-EC single-copy state $\tilde{\rho}_{BE}$ appears. However, it is easy to show that this state is equal to their pre-EC single-copy state, which is given by

$$\begin{aligned} \rho_{BE} &= \sum_{k,l} p(k,l)|l\rangle_B \langle l| \otimes \rho_E^{k,l} \\ &= \sum_l p(l)|l\rangle_B \langle l| \otimes \rho_E^l, \end{aligned} \quad (28)$$

where we have set

$$\rho_E^l := \sum_k p(k|l)\rho_E^{k,l}. \quad (29)$$

Intuitively, this is due to the fact that Alice has been traced out and the remaining correlations between Bob and Eve are not dependent on Alice's labels. In fact, from Eq. (2), consider the single-copy term

$$|k\rangle_A \langle k| \otimes |l\rangle_B \langle l| \otimes \rho_E^{k,l}. \quad (30)$$

With probability $p(\hat{l}|k)/p_{\text{ec}}$, the classical state $|k\rangle_A \langle k|$ is successfully transformed into $|\hat{l}\rangle_A \langle \hat{l}|$ (after EC and hash verification). Correspondingly, Eve's state must become

$$\rho_E^{\hat{l},l} = p_{\text{ec}} \sum_k p(k|\hat{l})\rho_E^{k,l}. \quad (31)$$

Replacing the latter in Eq. (25), we get $\tilde{\rho}_E^l = \rho_E^l$ and, therefore, we have $\tilde{\rho}_{BE} = \rho_{BE}$.

I. Composable formula for the secret key rate

Thus, we may write

$$H(B|E)_{\tilde{\rho}} = H(B|E)_{\rho}, \quad (32)$$

and the upper bound

$$\begin{aligned} s_n &\leq nH(B|E)_{\rho} - \text{leak}_{\text{ec}} \\ &\quad - \sqrt{n}\Delta_{\text{aep}} + \log_2(2\varepsilon_h^2\varepsilon_{\text{cor}}). \end{aligned} \quad (33)$$

We finally expand the conditional entropy as

$$H(B|E)_{\rho} = H(l|E)_{\rho} = H(l) - \chi(l : E)_{\rho}, \quad (34)$$

where $H(l)$ is the Shannon entropy of l , and $\chi(l : E)_{\rho}$ is Eve's Holevo bound with respect to l . Therefore, we get

$$\begin{aligned} s_n &\leq n[H(l) - \chi(l : E)_{\rho}] - \text{leak}_{\text{ec}} \\ &\quad - \sqrt{n}\Delta_{\text{aep}} + \log_2(2\varepsilon_h^2\varepsilon_{\text{cor}}). \end{aligned} \quad (35)$$

Alternatively, this can be written as

$$\boxed{s_n \leq nR_{\infty} - \sqrt{n}\Delta_{\text{aep}} + \log_2(2\varepsilon_h^2\varepsilon_{\text{cor}})}, \quad (36)$$

where we have introduced the asymptotic key rate

$$\boxed{R_{\infty} = H(l) - \chi(l : E)_{\rho} - n^{-1}\text{leak}_{\text{ec}}}. \quad (37)$$

This is an upper bound to the number of secret random bits that Alice and Bob can extract with epsilon security $\varepsilon = \varepsilon_{\text{cor}} + \varepsilon_s + \varepsilon_h$. Note that the secret key rate will need to account for the fact that this amount of bits is generated with probability p_{ec} and that only a fraction n/N of the total systems is used for key generation. Thus, the composable secret key rate (bits per use) of a generic CV-QKD protocol under collective attacks is given by

$$\boxed{R = \frac{p_{\text{ec}}s_n}{N}}. \quad (38)$$

1. Formula for discrete-alphabet coherent state protocols

The formula for a discrete-alphabet protocol is immediately derived. Let us define the reconciliation parameter $\beta \in [0, 1]$ by setting

$$H(l) - n^{-1}\text{leak}_{\text{ec}} = \beta I(k : l), \quad (39)$$

where $I(k : l)$ is Alice and Bob's mutual information. Then, the asymptotic key rate takes the form

$$R_{\infty} = \beta I(k : l) - \chi(l : E)_{\rho}. \quad (40)$$

This is to be replaced in Eq. (36) and then Eq. (38).

2. Formula for Gaussian-modulated coherent state protocols

In the case of a Gaussian-modulated protocol, we need to express the formula in terms of the quadratures. First, we re-define the reconciliation parameter $\beta \in [0, 1]$ as

$$H(l) - n^{-1}\text{leak}_{\text{ec}} = \beta I(x : y), \quad (41)$$

where $I(x : y) \geq I(k : l)$ is Alice and Bob's mutual information computed over their continuous variables. Second, we exploit data processing inequality for Eve's Holevo bound, so $\chi(l : E)_\rho \leq \chi(y : E)_\rho$ under digitalization $y \xrightarrow{\text{ADC}} l$. Thus, we can use the asymptotic rate

$$R_\infty = \beta I(x : y) - \chi(y : E)_\rho. \quad (42)$$

3. Other protocols

It is clear that protocols can be considered. The composable key rate of CV-MDI-QKD can be expressed as in Eqs. (36) and (38) once we replace the corresponding asymptotic expression R_∞ . The same can be stated for post-selection protocols, which however involve the use of an extra (post-selection) probability, appearing as a further pre-factor in Eq. (38).

J. Parameter estimation

The asymptotic key rate R_∞ depends on a number n_{pm} of parameters \mathbf{p} . By sacrificing m systems, Alice and Bob can compute maximum likelihood estimators $\hat{\mathbf{p}}$ and worst-case values \mathbf{p}_{wc} , which are w standard-deviations away from the mean values of the estimators. A worst-case value bounds the true value of a parameter up to an error probability $\varepsilon_{\text{pe}} = \varepsilon_{\text{pe}}(w)$. This means that, overall, n_{pm} worst-case values \mathbf{p}_{wc} will bound the parameters \mathbf{p} up to a total error probability $\simeq n_{\text{pm}}\varepsilon_{\text{pe}}$. Because PE occurs before EC, this probability needs to be multiplied by p_{ec} , so we have a total modified epsilon security

$$\varepsilon = \varepsilon_{\text{cor}} + \varepsilon_{\text{s}} + \varepsilon_{\text{h}} + p_{\text{ec}}n_{\text{pm}}\varepsilon_{\text{pe}}. \quad (43)$$

In the composable formula of Eq. (36), the asymptotic key rate $R_\infty = R_\infty(\mathbf{p})$ will be computed on the estimators and worst-case values, i.e., replaced by $R_\infty^{\text{pe}} := R_\infty(\hat{\mathbf{p}}, \mathbf{p}_{\text{wc}})$. More precisely, the expressions in Eqs. (40) and (42) will be replaced by

$$\boxed{R_\infty^{\text{pe}} = \beta[I]_{\hat{\mathbf{p}}} - [\chi_\rho]_{\mathbf{p}_{\text{wc}}}}. \quad (44)$$

K. From one block to a session of blocks

In a typical fiber-based scenario, a QKD session is stable, i.e., the main channel parameters are constant for a substantial period of time. This means that we can consider a session of n_{bks} blocks, each block with size N . In this scenario, the success probability p_{ec} becomes the fraction of blocks that survives EC. Assuming such a stable QKD session, PE can be performed on a large number of points, namely $n_{\text{bks}}m$. This approach leads to better estimators and worst-case values to be used in Eq. (44). Using this improved statistics, Alice and Bob will then implement EC block-by-block. Each block surviving EC

will undergo PA, where it is subject to a hash function randomly chosen from a 2-universal family. Each block compressed by PA is then concatenated into the final key.

III. APPLICATION TO VARIOUS PROTOCOLS

In order to use the composable formula in Eqs. (36) and (38), we need to specify the asymptotic key rate and the PE procedure, so that we can compute the rate R_∞^{pe} to be replaced in Eq. (36). Thus, in the following, we report the known formulas for the asymptotic key rates of the Gaussian-modulated coherent-state protocols (with homodyne and heterodyne detection) and the CV-MDI-QKD protocol. These asymptotic formulas can be found in a number of papers (e.g., see Ref. [1] and references therein). Then we consider the modifications due to PE.

A. Gaussian modulation of coherent states with homodyne detection

We model the link connecting the parties as a thermal-loss channel with transmissivity $T = 10^{-D/10}$ (where D is here the loss in dB) and excess noise ξ . The dilation of the channel is represented by a beam splitter with the same transmissivity T that Eve uses to inject one mode of a two-mode squeezed vacuum (TMSV) state with variance

$$\omega = \frac{T\xi}{1-T} + 1. \quad (45)$$

Eve's injected mode is therefore coupled with Alice's incoming mode via the beam splitter and the output is received by Bob, who detects it using a homodyne detector with efficiency η and electronic noise v_{el} (both local parameters that can be considered to be trusted in a well-calibrated scenario). The other, environmental, output of the beam splitter is stored by Eve in a quantum memory, together with the kept mode of the TMSV state. In this way, many modes are collected in Eve's quantum memory, which is finally subject to an optimal joint measurement (collective entangling-cloner attack).

Alice and Bob's mutual information is given by

$$I(x : y) = \frac{1}{2} \log_2 \left[1 + \frac{V}{\xi + (1 + v_{\text{el}})/(T\eta)} \right], \quad (46)$$

where V is Alice's modulation. The CM of Eve's output state (her partially-transmitted TMSV state) is given by

$$\mathbf{V}_E = \begin{pmatrix} \omega \mathbf{I} & \psi \mathbf{Z} \\ \psi \mathbf{Z} & \phi \mathbf{I} \end{pmatrix}, \quad (47)$$

where $\mathbf{I} = \text{diag}(1, 1)$, $\mathbf{Z} = \text{diag}(1, -1)$ and

$$\psi = \sqrt{T(\omega^2 - 1)}, \quad (48)$$

$$\phi = T\omega + (1 - T)(V + 1). \quad (49)$$

Then, Eve's conditional CM (conditioned on Bob's outcome) is given by

$$\mathbf{V}_{E|y} = \mathbf{V}_E - b^{-1} \begin{pmatrix} \gamma^2 \mathbf{\Pi} & \gamma \theta \mathbf{\Pi} \\ \gamma \theta \mathbf{\Pi} & \theta^2 \mathbf{\Pi} \end{pmatrix}, \quad (50)$$

where $\mathbf{\Pi} = \text{diag}\{1, 0\}$ and

$$b = T\eta(V + \xi) + 1 + u_{\text{el}}, \quad (51)$$

$$\gamma = \sqrt{\eta(1-T)(\omega^2 - 1)}, \quad (52)$$

$$\theta = \sqrt{\eta T(1-T)(\omega - V - 1)}. \quad (53)$$

By calculating the symplectic eigenvalues of the total CM, ν_+ and ν_- , and those of the conditional CM, $\tilde{\nu}_+$ and $\tilde{\nu}_-$, we obtain Eve's Holevo information on Bob's outcome

$$\chi(E : y) = h(\nu_+) + h(\nu_-) - h(\tilde{\nu}_+) - h(\tilde{\nu}_-), \quad (54)$$

where

$$h(\nu) = \frac{\nu + 1}{2} \log_2 \frac{\nu + 1}{2} - \frac{\nu - 1}{2} \log_2 \frac{\nu - 1}{2}. \quad (55)$$

Then the asymptotic secret key rate is given by the difference between the mutual information (multiplied by the reconciliation efficiency β) and Eve's Holevo information as in Eq. (42).

Let us now include PE, assuming that m signals are sacrificed for building the estimators of the channel parameters (to be used in the mutual information) and the associated worst-case values (to be used in Eve's Holevo bound). One therefore computes estimators $\hat{T} \simeq T$, $\hat{\xi} \simeq \xi$ and the following worst-case values

$$T_{\text{wc}} \simeq T - \frac{2wT}{\sqrt{V_0 m}} \sqrt{c_{\text{PE}} + \frac{\xi + \frac{V_0 + v_{\text{el}}}{\eta T}}{V}}, \quad (56)$$

$$\xi_{\text{wc}} \simeq \frac{\eta T \xi + \frac{\sqrt{2w}}{\sqrt{V_0 m}} (\eta T \xi + V_0 + v_{\text{el}})}{\eta T_{\text{wc}}}, \quad (57)$$

where

$$w = \sqrt{2} \text{erf}^{-1}(1 - \epsilon_{\text{PE}}). \quad (58)$$

In the equations above, $V_0 = 1$ for homodyne detection and, in Eq. (56), the term c_{PE} is here chosen to be equal to zero [12] (in fact, another choice would be $c_{\text{PE}} = 2$ [13] based on a weaker assumption [?]).

Finally, using $\hat{\mathbf{p}} = (\hat{T}, \hat{\xi})$ and $\mathbf{p}_{\text{wc}} = (T_{\text{wc}}, \xi_{\text{wc}})$ we compute the PE rate as in Eq. (44) to be replaced in Eq. (36) and then in Eq. (38). In Fig. 1, we plot the composable secret key rate with respect to the loss in the communication link assuming typical parameters. In Fig. 2, we instead present its behaviour as a function of the block size. We can see how the performance of the key rate is improved with respect to the previous results in Refs. [18, 19] (which can generally be considered to be more pessimistic evaluations).




FIG. 1. Composable secret key rate for the Gaussian-modulated coherent-state protocol using homodyne detection (black lines) and heterodyne detection (blue lines) with respect to loss in dB. Solid lines refer to the new rate, while dashed lines correspond to the performance of the previous rate from Refs. [18, 19]. We have set $\beta = 0.98$ and $p_{\text{ec}} = 0.95$. Excess noise is $\xi = 0.01$, detection efficiency $\eta = 0.98$, and electronic noise $v_{\text{el}} = 0.1$. Security epsilons have all been set to 2^{-32} . Cardinality of the alphabet is $\aleph = 2^7$ for homodyne and $\aleph = 2^{14}$ for heterodyne. Block size is $N = 10^7$ and PE is based on $m = N/10$ sacrificed signals.




FIG. 2. Composable secret key rate for the Gaussian-modulated coherent-state protocol using homodyne detection (black lines) and heterodyne detection (blue lines) with respect to the block size N . Solid lines refer to the new rate, while dashed lines correspond to the performance of the previous rate from Refs. [18, 19]. Loss is 7 dB while all the other parameters are chosen as in Fig. 3.

B. Gaussian modulation of coherent states with heterodyne detection

For the protocol with heterodyne detection, the mutual information is a simple modification of the previous one in Eq. (46), and given by

$$I(x : y) = \log_2 \left[1 + \frac{V}{\xi + (2 + u_{\text{el}})/(T\eta)} \right]. \quad (59)$$

Eve's CM is the same as in Eq. (47), but the conditional CM is instead given by

$$\mathbf{V}_{E|y} = \mathbf{V}_E - (b+1)^{-1} \begin{pmatrix} \gamma^2 \mathbf{I} & \gamma \theta \mathbf{Z} \\ \gamma \theta \mathbf{Z} & \theta^2 \mathbf{I} \end{pmatrix}. \quad (60)$$

We follow the same steps as in the previous section to calculate a similar asymptotic formula. Worst-case values are given in Eq. (56) and (57) but with $V_0 = 2$. Results are shown in Figs. 1 and 2, confirming the improvement.

C. Gaussian-modulated CV-MDI protocol

In the CV-MDI protocol, we assume that Eve interacts with Alice's and Bob's modes via two beam splitters with transmissivities T_A and T_B . Eve's input to these beam splitters is assumed to be a maximally-correlated Gaussian state. The latter is described by the CM

$$\mathbf{V}_{\text{attack}} = \begin{pmatrix} \omega_A \mathbf{I} & g_{\max} \mathbf{Z} \\ g_{\max} \mathbf{Z} & \omega_B \mathbf{I} \end{pmatrix}, \quad (61)$$

where $\omega_A = \frac{T_A \xi_A}{1-T_A} + 1$ and $\omega_B = \frac{T_B \xi_B}{1-T_B} + 1$ are the thermal-noise variances in the links (with ξ_A and ξ_B being the corresponding excess noises). Then, the correlation term is given by [?]

$$g_{\max} = \max \left[\sqrt{(\omega_A - 1)(\omega_B + 1)}, \sqrt{(\omega_A + 1)(\omega_B - 1)} \right]. \quad (62)$$

We assume efficiency η and electronic noise v_{el} for each homodyne detector in the Bell measurement at the relay.

The asymptotic key rate can be computed in entanglement-based representation, so that Eve's CM \mathbf{V}_E can be replaced by Alice and Bob's CM \mathbf{V}_{AB} , and Eve's conditional CM $\mathbf{V}_{E|y}$ can be replaced by Alice's conditional CM $\mathbf{V}_{A|y}$. All these CMs are implicitly conditioned to the outcome of the relay, but we simplify the notation by omitting this. One finds

$$\mathbf{V}_{AB} = \begin{pmatrix} \mathbf{V}_A & \phi \mathbf{Z} \\ \phi \mathbf{Z} & \mathbf{V}_B \end{pmatrix}, \quad \mathbf{V}_{A|y} = \left(\zeta - \frac{\eta^2}{\theta + 1} \right) \mathbf{I}, \quad (63)$$

where $\mathbf{V}_A = \zeta \mathbf{I}$, $\mathbf{V}_B = \theta \mathbf{I}$, and

$$\zeta = 1 + \sigma_A^2 - \frac{\frac{\eta}{2} T_A \sigma_A^2 (\sigma_A^2 + 2)}{\frac{\eta}{2} (T_B \sigma_B^2 + T_A \sigma_A^2) + \sigma_z^2}, \quad (64)$$

$$\theta = 1 + \sigma_B^2 - \frac{\frac{\eta}{2} T_B \sigma_B^2 (\sigma_B^2 + 2)}{\frac{\eta}{2} (T_B \sigma_B^2 + T_A \sigma_A^2) + \sigma_z^2}, \quad (65)$$

$$\phi = \frac{\frac{\eta}{2} \sqrt{T_A T_B \sigma_A^2 (\sigma_A^2 + 2) \sigma_B^2 (\sigma_B^2 + 2)}}{\frac{\eta}{2} (T_B \sigma_B^2 + T_A \sigma_A^2) + \sigma_z^2}. \quad (66)$$

Above, σ_A^2 and σ_B^2 are Alice's and Bob's modulation variances, while σ_z^2 is given by $\sigma_z^2 = \Xi + 1 + v_{\text{el}}$, where

$$\Xi = \frac{\eta}{2} (T_A \xi_A + T_B \xi_B) + \eta g_{\max} \sqrt{(1-T_A)(1-T_B)}. \quad (67)$$




FIG. 3. Composable secret key rate for the Gaussian-modulated CV-MDI protocol in asymmetric configuration (black lines) and symmetric configuration (blue lines) with respect to loss in dB. In the symmetric case ($T_A = T_B$), the loss refers to each link, while, in the asymmetric case, it only refers to Alice's link and we set $T_B = 0.98$ for Bob. Solid lines refer to the new rate, while dashed lines correspond to the performance of the previous rate from Refs. [26, 27]. We have set $\beta = 0.98$ and $p_{\text{ec}} = 0.95$. Excess noise is $\xi = 0.005$ for each link. At the relay, each detector has efficiency $\eta = 0.98$ and electronic noise $v_{\text{el}} = 0.01$. The security epsilons have been set equal to 2^{-32} and we consider $\aleph = 2^{14}$. Block size is $N = 10^7$ and PE is based on $m = N/10$ sacrificed signals.




FIG. 4. Composable secret key rate for the Gaussian-modulated CV-MDI protocol in asymmetric configuration (black lines) and symmetric configuration (blue lines) with respect to the block size N . We have set $T_A = 0.94$ and $T_B = 0.98$ for the asymmetric configuration, while $T_A = T_B = 0.94$ for the symmetric one. Solid lines refer to the new rate, while dashed lines correspond to the performance of the previous rate from Ref. [26, 27]. Other parameters are as in Fig. 3.

Eve's Holevo bound is calculated from the symplectic spectra of \mathbf{V}_{AB} and $\mathbf{V}_{A|y}$, while Alice and Bob's mutual information is given by

$$I(x : y) = \frac{1}{2} \log_2 \frac{\det \mathbf{V}_A + \text{tr} \mathbf{V}_A + 1}{\det \mathbf{V}_{A|y} + \text{tr} \mathbf{V}_{A|y} + 1}. \quad (68)$$

All these elements provide the asymptotic key rate.

From the m sacrificed signals, one computes the estimators and worst-case values for the main parameters:

$$[T_A]_{\text{wc}} \simeq T_A - 2w\sqrt{T_A\bar{T}_A}m^{-1/2}\sqrt{c_{\text{PE}} + \frac{\sigma_z^2}{\frac{\eta}{2}\bar{T}_A\sigma_A^2}}, \quad (69)$$

$$[T_B]_{\text{wc}} \simeq T_B - 2w\sqrt{T_B\bar{T}_B}m^{-1/2}\sqrt{c_{\text{PE}} + \frac{\sigma_z^2}{\frac{\eta}{2}\bar{T}_B\sigma_B^2}}, \quad (70)$$

$$[\sigma_z^2]_{\text{wc}} \simeq \sigma_z^2 + w\sqrt{2}m^{-1/2}\sigma_z^2, \quad (71)$$

where we use $c_{\text{PE}} = 0$ and

$$\bar{T}_A := T_A + \frac{T_B}{2} \frac{\sigma_B^2}{\sigma_A^2}, \quad \bar{T}_B := T_B + \frac{T_A}{2} \frac{\sigma_A^2}{\sigma_B^2}. \quad (72)$$

Replacing in the asymptotic rate we obtain the PE-modified rate of Eq. (44) and, therefore, we can compute the composable key rate according to Eqs. (36) and (38). As we can see from Figs. 3 and 4, the new rate provides an enhancement with respect to the previous performance in Ref. [27] both in terms of key rate versus loss (at fixed block size), and key rate versus block size (at fixed loss).

IV. CONCLUSIONS

In this paper, we have introduced an improved formula for the secret key rate of a generic CV-QKD protocol under collective attacks. This formula refines tools from previous theory and allows us to show an effective advantage, in terms of rate and block-size. For this reason, the present formulation allows CV-QKD protocols to achieve better overall performances, therefore making them more robust in realistic implementations.

We have specifically analyzed the advantage in the case of typical CV-QKD protocols, such as the Gaussian-modulated coherent-state protocols (with homodyne and heterodyne detection) and the CV-MDI protocol. Let us note that, for the case of the Gaussian-modulated protocol with heterodyne detection, the formula can immediately be extended to security against coherent attacks, by using the symmetrization tools introduced in Ref. [17] and following the same steps of Ref. [18].

-
- [1] S. Pirandola, U. L. Andersen, L. Banchi, M. Berta, D. Bunandar, R. Colbeck, D. Englund, T. Gehring, C. Lupo, C. Ottaviani, J. L. Pereira, M. Razavi, J. S. Shaari, M. Tomamichel, V. C. Usenko, G. Vallone, P. Villoresi, and P. Wallden, *Advances in quantum cryptography*, Adv. Opt. Photon. **12**, 1012 (2020).
- [2] F. Xu, X. Ma, Q. Zhang, H.-K. Lo, and J.-W. Pan, *Secure quantum key distribution with realistic devices*, Rev. Mod. Phys. **92**, 025002 (2020).
- [3] N. Gisin, G. Ribordy, W. Tittel, and H. Zbinden, *Quantum cryptography*, Rev. Mod. Phys. **74**, 145 (2002).
- [4] S. Pirandola, R. Laurenza, C. Ottaviani, and L. Banchi, *Fundamental limits of repeaterless quantum communications*, Nat. Commun. **8**, 15043 (2017). See also arXiv:1510.08863 (2015).
- [5] T. C. Ralph, *Continuous variable quantum cryptography*, Phys. Rev. A **61**, 010303 (1999).
- [6] M. Hillery, *Quantum cryptography with squeezed states*, Phys. Rev. A **61**, 022309 (2000).
- [7] N. J. Cerf, M. Levy, and G. van Assche, *Quantum distribution of Gaussian keys using squeezed states*, Phys. Rev. A **63**, 052311 (2001).
- [8] T. C. Ralph, *Security of continuous-variable quantum cryptography*, Phys. Rev. A textbf62, 062306 (2002).
- [9] F. Grosshans, and P. Grangier, *Continuous variable quantum cryptography using coherent states*, Phys. Rev. Lett. **88**, 057902 (2002).
- [10] M. Navascues, F. Grosshans, A. Acin, *Optimality of Gaussian attacks in continuous-variable quantum cryptography*, Phys. Rev. Lett. **97**, 190502 (2006).
- [11] S. Pirandola, S. L. Braunstein, and S. Lloyd, *Characterization of collective Gaussian attacks and security of coherent-state quantum cryptography*, Phys. Rev. Lett. **101**, 200504 (2008).
- [12] A. Leverrier, F. Grosshans, P. Grangier, *Finite-size analysis of a continuous-variable quantum key distribution*, Phys. Rev. A **81**, 062343 (2010).
- [13] L. Ruppert, V. C. Usenko, and R. Filip, *Long-distance continuous-variable quantum key distribution with efficient channel estimation*, Phys. Rev. A **90**, 062310 (2014).
- [14] V. C. Usenko, and F. Grosshans, *Unidimensional continuous-variable quantum key distribution*, Phys. Rev. A **92**, 062337 (2015).
- [15] A. Leverrier, *Composable security proof for continuous-variable quantum key distribution with coherent states*, Phys. Rev. Lett. **114**, 070501 (2015).
- [16] V. C. Usenko, R. Filip, *Trusted noise in continuous-variable quantum key distribution: a threat and a defense*, Entropy **18**, 20 (2016).
- [17] A. Leverrier, *Security of continuous-variable quantum key distribution via a Gaussian de Finetti reduction*, Phys. Rev. Lett. **118**, 200501 (2017).
- [18] S. Pirandola, *Limits and security of free-space quantum communications*, Physical Review Research **3**, 013279 (2021).
- [19] S. Pirandola, *Composable security for continuous variable quantum key distribution: Trust levels and practical key rates in wired and wireless networks*, Physical Review Research **3**, 043014 (2021).
- [20] P. Papanastasiou and S. Pirandola, *Continuous-variable quantum cryptography with discrete alphabets: Composable security under collective Gaussian attacks*, Phys. Rev. Research **3**, 013047 (2021).
- [21] T. Matsuura T. et al. *Finite-size security of continuous-variable quantum key distribution with digital signal processing*, Nat. Commun. **12**, 252 (2021).
- [22] A. G. Mountogiannakis, P. Papanastasiou, B. Braver-

- man, and S. Pirandola, *Composably secure data processing for Gaussian-modulated continuous-variable quantum key distribution*, Phys. Rev. Research **4**, 013099 (2022).
- [23] A. G. Mountogiannakis, P. Papanastasiou, S. Pirandola, *Data postprocessing for the one-way heterodyne protocol under composable finite-size security*, Phys. Rev. A **106**, 042606 (2022).
- [24] F. Grosshans et al., *Quantum key distribution using Gaussian-modulated coherent states*, Nature **421**, 238–241 (2003).
- [25] C. Weedbrook et al., *Quantum cryptography without switching*, Phys. Rev. Lett. **93**, 170504 (2004).
- [26] S. Pirandola, C. Ottaviani, G. Spedalieri, C. Weedbrook, S. L. Braunstein, S. Lloyd, T. Gehring, C. S. Jacobsen, and U. L. Andersen, *High-rate measurement-device-independent quantum cryptography*, Nature Photonics **9**, 397 (2015). See also arXiv:1312.4104v1 (2013).
- [27] P. Papanastasiou, A.G. Mountogiannakis, S. Pirandola, *Composable security of CV-MDI-QKD: Secret key rate and data processing*, To appear.
- [28] C. Portmann, and R. Renner, *Cryptographic security of quantum key distribution*, arXiv:1409.3525v1 (2014).
- [29] M. Tomamichel, C. C.W. Lim, N. Gisin, and R. Renner, *Tight finite-key analysis for quantum cryptography*, Nat. Commun. **3**, 634 (2012).
- [30] C. H. Bennett, G. Brassard, C. Crepeau and U. M. Maurer, *Generalized privacy amplification*, IEEE Trans. Inf. Theory **41**, 1915-1923 (1995).
- [31] M. Tomamichel, C. Schaffner, A. Smith, and R. Renner, *Leftover Hashing Against Quantum Side Information*, IEEE Trans. Inf. Theory **57**, 5524-5535 (2011).
- [32] M. Tomamichel, *A Framework for Non-Asymptotic Quantum Information Theory* (PhD thesis, Zurich 2005).
- [33] R. Renner, *Security of Quantum Key Distribution*, PhD Thesis, ETH Zurich, 2005. [Online]. Available: <http://arxiv.org/abs/quant-ph/0512258>