

$h(1) \oplus su(2)$ vector algebra eigenstates with eigenvalues in the matrix domain

Nibaldo Edmundo Alvarez Moraga*

Autonomous Center of Theoretical Physics and Applied Mathematics,
2805 Place de Darlington, Montreal (Quebec), H3S1L4, Canada

January 26, 2023

Abstract

A new set of $h(1) \oplus su(2)$ vector algebra eigenstates on the matrix domain is obtained by defining them as eigenstates of a generalized annihilation operator formed from a linear combination of the generators of this algebra which eigenvalues are distributed as the elements of a square complex normal matrix. A combined method is used to compute these eigenstates, namely, the method of exponential operators and that of a system of first-order linear differential equations. We compute these states for all possible combination of generators and classify them in different categories according to a generalized commutation relation as well as according to the value of a characteristic parameter related to the $su(2)$ algebra eigenvalues. Proceeding in this way, we found a subset of generalized vector coherent states in the matrix domain which can be easily separated from the general set of Schrödinger-Robertson minimum uncertainty intelligent states. In particular, for a special choice of the matrix eigenvalue parameters we found the so-called vector coherent states with matrices associated to the Heisenberg-Weyl group as well as a generalized version of them, and also a direct connection with the coherent state quantization of quaternions.

1 Introduction

Coherent states [1] expressed as eigenvectors of the lowering harmonic oscillator operator verifying important physical properties were first introduced by J. R. Klauder [2]. From there, several definitions of coherent states related to this and other quantum physical system were introduced in the literature as well as generalization of this concept of theoretical interest in Physics and Mathematics became to know, all of them assuring the accomplishment of some desired properties such as minimum uncertainty states, resolution of the identity, temporal stability or action-identity. Thus, some consider them as states generated from the action of a unitary irreducible representation of the group on a fixed state of the Hilbert space representation, others define these states as eigenstates of ladder operators generating a representation of the associated Lie algebra or as states associated to physical Hamiltonians having a non-degenerate spectra [3]– [11]. The concept of algebra eigenstates associated to an arbitrary Lie group was introduced by C. Brif who defined them as eigenstates of elements of the corresponding complex Lie algebra [12, 13]. He used this method, among others, to compute the algebra eigenstates of the $SU(2)$ and $SU(1, 1)$ Lie groups and shown that these states included different subsets of Perelomov's generalized coherent states as well as of the so called intelligent states that minimize the Schrödinger-Robertson uncertainty relation. An adaptation of this last concept to the $h(1) \oplus su(2)$ Lie algebra allowed us to generate new sets of generalized coherent and squeezed states associated with physical systems whose Hamiltonians were constructed as the product of well defined creation and annihilation operators extracted from the set of elements of this algebra [14]. Then, a new generalization of the concept of vector coherent states to the matrix domain arose by substituting the characteristic complex parameter of the canonical Heisenberg-Weyl coherent states by a normal matrix and requiring that the resulting

*Email address: nibaldo.alvarez.m@mail.pucv.cl

states to verify the resolution of the identity [15]. The same successful substitution was done in the $SU(1,1)$ Gilmore-Perelomov and Barut-Giraldello type coherent states. An important consequence of this extension is that it led to the coherent state quantization of quaternions [16]. In this article we extend the definition of algebra eigenstates with eigenvalues in the complex domain, where by the way the eigenvectors are states in the Hilbert space of representation of the algebra, to consider eigenvalues on the complex matrix domain, that is, complex matrix eigenvalues, where now the associated eigenvectors, that from now on we will call vector algebra eigenstates, are vectors whose components are by themselves states of the Hilbert space of representation of the algebra. We use this definition to compute the vector algebra eigenstates of the $h(1) \oplus su(2)$ Lie algebra, but it will be clear by regarding the subsequent development that it can be used to compute the vector algebra eigenstates for other Lie algebras.

This article is organized as follows. In section 2 we introduce the $h(1) \oplus su(2)$ Lie algebra generators, its commutation relations and its action on a chosen irreducible representation space of this algebra and establish the nomenclature to describe the vector states. In section 3 we give the definition and compute the vector algebra eigenstates of the annihilation operator associated to the quantum harmonic oscillator and compare the resulting expressions with the set of Heisenberg-Weyl vector coherent states on the matrix domain that we can find in the literature. Also, we choose the entries of the matrix eigenvalue as equal to the matrix elements of the elements of the $su(2) \oplus \hat{I}_j$ algebra in the j irreducible representation. This alternative allows us, for a particular choice of the parameters, to generalize the quaternionic vector coherent states to an arbitrary $su(2)$ irreducible representation space. Moreover, we there we show the connection of our general method with the coherent state quantization of quaternions. In section 4, we give the definition of vector algebra eigenstates for the $h(1) \oplus su(2)$ Lie algebra and compute these states for all possible linear combinations of generators of this algebra in the case when the matrix eigenvalue is complex and normal. In appendices A and B, we recalculate completely the $h(1) \oplus su(2)$ algebra eigenstates by combining the exponential operator and the linear differential equations system methods and prepare appropriately the expressions for using them in the main body of this article.

2 $h(1) \oplus su(2)$ Lie algebra and its generators

The $h(1) \oplus su(2)$ Lie algebra is the direct sum of the Heisenberg Weyl algebra, whose generators are given by \hat{a}, \hat{a}^\dagger and the identity \hat{I} , and the $su(2)$ algebra, generated by \hat{J}_-, \hat{J}_+ and \hat{J}_3 . These set of operators satisfy the commutation relations

$$[\hat{a}, \hat{a}^\dagger] = \hat{I}, \quad [\hat{I}, \hat{a}] = \hat{0} \quad \text{and} \quad [\hat{I}, \hat{a}^\dagger] = \hat{0}, \quad (2.1)$$

where $\hat{0}$ is the null operator, and

$$[\hat{J}_+, \hat{J}_-] = 2\hat{J}_3 \quad \text{and} \quad [\hat{J}_3, \hat{J}_\pm] = \pm\hat{J}_\pm, \quad (2.2)$$

respectively.

The action of the former on the orthonormal basis vectors $|n\rangle, n = 0, 1, 2, \dots$ spanning the infinite dimensional Hilbert space \mathcal{H} is given by

$$\hat{a}|n\rangle = \sqrt{n}|n-1\rangle, \quad \hat{a}^\dagger|n\rangle = \sqrt{n+1}|n+1\rangle \quad (2.3)$$

and

$$\hat{I}|n\rangle = |n\rangle, \quad (2.4)$$

with $n = 0, 1, 2, \dots$ and the action of the latter on the orthonormal basis vectors $|j, m\rangle$ of the irreducible representation j , of dimension $2j + 1$, is given by

$$\hat{J}_\pm|j, m\rangle = \sqrt{(j \mp m)(j \pm m + 1)}|j, m\rangle \quad \text{and} \quad \hat{J}_3|j, m\rangle = m|j, m\rangle, \quad (2.5)$$

where j is a not negative integer or half-integer and $m = -j, -j + 1, \dots, j - 1, j$.

The orthonormal basis vectors of the $h(1) \oplus su(2)$ algebra, for fixed j , can be written as the direct product

$$|n\rangle \otimes |j, m\rangle = |n; j, m\rangle, \quad n = 0, 1, 2, \dots; \quad m = -j, \dots, j. \quad (2.6)$$

Then, for fixed j , a general state $|\psi\rangle^j$ of the algebra $h(1) \oplus su(2)$ can be expressed in the form

$$|\psi\rangle^j = \sum_{n=0}^{\infty} \sum_{m=-j}^j C_{n,m}^j |n; j, m\rangle, \quad (2.7)$$

where $C_{n,m}^j$ are complex coefficients for all n, m .

2.1 Realization of $h(1)$ generators on analytic functions space

Another realization of the oscillator algebra can be found in the Fock-Bargman representation space \mathcal{H} of analytic functions $f(\zeta), \zeta \in \mathbb{C}$, verifying the scalar product

$$(f_1, f_2) = \int_{\mathbb{C}} f_1^*(\zeta) f_2(\zeta) e^{|\zeta|^2} \frac{d\zeta d\zeta^*}{2\pi i}, \quad \zeta \in \mathbb{C}. \quad (2.8)$$

In this space, an arbitrary analytic function $f(\zeta)$ can be expressed as a linear combination of analytic elementary functions $\langle \zeta | n \rangle = \varphi_n(\zeta) = \frac{\zeta^n}{\sqrt{n!}}, n = 0, 1, 2, \dots$, which span \mathcal{H} and verify the orthonormality property

$$(\varphi_r(\zeta), \varphi_s(\zeta)) = \delta_{rs}, \quad \forall r, s \in \mathbb{N}_0. \quad (2.9)$$

In terms of these states the function $f(\zeta)$ writes

$$f(\zeta) = \sum_{n=0}^{\infty} c_n \varphi_n(\zeta) = \sum_{n=0}^{\infty} c_n \frac{\zeta^n}{\sqrt{n!}}. \quad (2.10)$$

In this representation the $h(1)$ algebra generators take the form:

$$\hat{a} = \frac{d}{d\zeta}, \quad \hat{a}^\dagger = \zeta, \quad \text{and } \hat{I} = 1. \quad (2.11)$$

As we can see above, the elementary analytic states can be thought as projections of the number harmonic oscillator eigenstates $|n\rangle$ over the $|\zeta\rangle$ state. Using this fact, the projection of the general state (2.7) onto $|\zeta\rangle \otimes \hat{I}^j$ state, where $\hat{I}^j = \sum_{m=-j}^j |j, m\rangle \langle j, m|$ is the identity operator in the $2j + 1$ dimensional j space, is given by

$$|\psi(\zeta)\rangle^j = \hat{I}^j \otimes \langle \zeta | \psi \rangle^j = \sum_{m=-j}^j \psi_m^j(\zeta) \otimes |j, m\rangle, \quad (2.12)$$

where

$$\psi_m^j(\zeta) = \sum_{n=0}^{\infty} C_{n,m}^j \frac{\zeta^n}{\sqrt{n!}}, \quad m = -j, \dots, j, \quad (2.13)$$

are analytic states functions, which can also be interpreted as a kind of coefficients of the expansion of the state $|\psi(\zeta)\rangle^j$ in terms of the basis states $|j, m\rangle$.

3 Quantum oscillator annihilation operator vector eigenstates with matrix eigenvalues

In this section we define and solve the matrix eigenvalue equation for the quantum harmonic oscillator annihilation operator. We will use the basis vector associated to the $h(1) \oplus su(2)$ algebra representation to express the states and we will see that the set of solutions of this matrix eigenvalue equation contains the subset of vector coherent states over the matrix domain studied in the literature [15]. We note that, in this particular case, the use of the $su(2)$ sector representation space is optional, it could be replaced by another algebra representation space.

Let us start with a preliminary definition of the vector algebra eigenstates of \hat{a} as those states that satisfy the matrix eigenvalue equation

$$\hat{a} |\Psi\rangle_K^j = \tilde{M} |\Psi\rangle_K^j, \quad (3.1)$$

where $|\Psi\rangle_K^j$ is the K component vector state given by

$$|\Psi\rangle_K^j = \begin{pmatrix} |\psi\rangle_{[1]}^j \\ |\psi\rangle_{[2]}^j \\ \vdots \\ |\psi\rangle_{[K-1]}^j \\ |\psi\rangle_{[K]}^j \end{pmatrix}, \quad (3.2)$$

where each state $|\psi\rangle_{[s]}^j = \sum_{n=0}^{\infty} \sum_{m=-j}^j C_{nm}^{[s]j} |n\rangle \otimes |j, m\rangle$, $s = 1, \dots, K$ is a unknown state of the $h(1) \oplus su(2)$ representation space, to be determined, and \tilde{M} a diagonalizable complex square matrix of dimension $K \times K$.

3.1 When \tilde{M} is a normal matrix

In general, when \tilde{M} is normal, i.e., when $\tilde{M}\tilde{M}^\dagger = \tilde{M}^\dagger\tilde{M}$, a similarity transformation of \tilde{M} by an unitary matrix \tilde{U} can be done that leads (3.1) to the simplified form

$$\hat{a} |\tilde{\Psi}\rangle_K^j = \tilde{D} |\tilde{\Psi}\rangle_K^j, \quad (3.3)$$

where

$$\tilde{D} = \tilde{U}^\dagger \tilde{M} \tilde{U}, \quad \text{and} \quad |\tilde{\Psi}\rangle_K^j = \tilde{U}^\dagger |\Psi\rangle_K^j, \quad (3.4)$$

where \tilde{D} is a diagonal matrix which entries are the eigenvalues of \tilde{M} and $|\tilde{\Psi}\rangle_K^j$ is the corresponding transformed state. Thus, each component of the matrix equation (3.3) verifies the eigenvalue equation

$$\hat{a} |\tilde{\psi}\rangle_{[s]}^j = \lambda_{[s]}^j |\tilde{\psi}\rangle_{[s]}^j, \quad s = 1, \dots, K. \quad (3.5)$$

By solving this equations we realize that each component $|\tilde{\psi}\rangle_{[s]}^j$ can be written as a direct product between a canonical oscillator coherent state and a generic state of the j representation space of the $su(2)$ Lie algebra, i.e,

$$|\tilde{\psi}\rangle_{[s]}^j = e^{\lambda_{[s]}^j \hat{a}^\dagger} |0\rangle \otimes \sum_{m=-j}^j \tilde{\psi}_{[s]m}^j(0) |j, m\rangle, \quad s = 1, \dots, K, \quad (3.6)$$

then we have

$$|\Psi(\tilde{M})\rangle_K^j = \tilde{U} |\tilde{\Psi}(\Lambda)\rangle_K^j = \mathcal{N}^{-1/2} \tilde{U} e^{\tilde{D} \hat{a}^\dagger} |\tilde{\Psi}(0)\rangle_K^j = \mathcal{N}^{-1/2} e^{\tilde{M} \hat{a}^\dagger} |\Psi(0)\rangle_K^j \quad (3.7)$$

where \mathcal{N} is a normalization constant depending on $\lambda_{[s]}^j$ values but also on the choice of the $K \times 2j + 1$ arbitrary constants $\tilde{\psi}_{[s]m}^j(0)$, $s = 1, \dots, K$, $m = -j, \dots, j$, and

$$|\tilde{\Psi}(0)\rangle_K^j = \begin{pmatrix} |0\rangle \otimes |\tilde{\psi}(0)\rangle_{[1]}^j \\ |0\rangle \otimes |\tilde{\psi}(0)\rangle_{[2]}^j \\ \vdots \\ |0\rangle \otimes |\tilde{\psi}(0)\rangle_{[K-1]}^j \\ |0\rangle \otimes |\tilde{\psi}(0)\rangle_{[K]}^j \end{pmatrix}, \quad (3.8)$$

with $|\tilde{\psi}(0)\rangle_{[s]}^j = \sum_{m=-j}^j \tilde{\psi}_{[s]m}^j(0) |j, m\rangle$, $s = 1, \dots, K$.

We notice that (3.8) represent a set of $K \times 2j + 1$ vector eigenstates of \hat{a} with associated eigenvalues equal to zero, just like the states $|\Psi(0)\rangle_K^j = \tilde{U} |\tilde{\Psi}(0)\rangle_K^j$. Then, by using the Baker-Campbell-Hausdorff formula $\exp(A+B) = \exp(A)\exp(B)\exp(-\frac{1}{2}[A,B])$, for two operators A and B whose commutator commutes with both A and B , we get

$$|\Psi(\tilde{M})\rangle_K^j = \mathcal{N}^{-1/2} \tilde{U} e^{\frac{1}{2}\tilde{D}\tilde{D}^\dagger} e^{(\tilde{D}\hat{a}^\dagger - \tilde{D}^\dagger\hat{a})} |\tilde{\Psi}(0)\rangle_K^j = \mathcal{N}^{-1/2} e^{\frac{1}{2}\tilde{M}\tilde{M}^\dagger} e^{(\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a})} |\Psi(0)\rangle_K^j. \quad (3.9)$$

3.1.1 A special choice of basis vectors

The choice of the vector $|\tilde{\Psi}(0)\rangle_K^j$ has influence in the normalization constant \mathcal{N} . Choosing it as a vector which components form an orthonormal basis in the fixed j representation subspace makes it easier to compute, choosing, for example, $|\tilde{\psi}(0)\rangle_{[s]}^j = |0\rangle \otimes |j, m_s\rangle$, $s = 1, \dots, K$, with $\langle j, m_s | j, m_s \rangle = \delta_{ss}$, we get the normalized vector coherent states

$$|\Psi(\Lambda)\rangle_K^j = \frac{1}{\sqrt{\sum_{s=1}^K e^{\|\lambda_{[s]}^j\|^2}}} \tilde{U} e^{D\hat{a}^\dagger} |\tilde{\Psi}(0)\rangle_K^j, \quad (3.10)$$

which in the matrix form look like

$$|\Psi(\Lambda)\rangle_K^j = \frac{1}{\sqrt{\sum_{s=1}^K e^{\|\lambda_{[s]}^j\|^2}}} \times \tilde{U} \begin{pmatrix} e^{\lambda_{[1]}^j \hat{a}^\dagger} & 0 & 0 & \dots & \dots & 0 \\ 0 & e^{\lambda_{[2]}^j \hat{a}^\dagger} & 0 & \dots & \dots & 0 \\ 0 & 0 & \ddots & 0 & \dots & 0 \\ \vdots & \vdots & \vdots & \ddots & \vdots & \vdots \\ 0 & \dots & \dots & 0 & e^{\lambda_{[K-1]}^j \hat{a}^\dagger} & 0 \\ 0 & \dots & \dots & 0 & 0 & e^{\lambda_{[K]}^j \hat{a}^\dagger} \end{pmatrix} \begin{pmatrix} |0\rangle \otimes |j, m_1\rangle \\ |0\rangle \otimes |j, m_2\rangle \\ \vdots \\ |0\rangle \otimes |j, m_{K-1}\rangle \\ |0\rangle \otimes |j, m_K\rangle \end{pmatrix}. \quad (3.11)$$

On the other hand, if we choose these states in such a way that

$$|\tilde{\Psi}(0)\rangle_K^j = \tilde{U}^\dagger \begin{pmatrix} |0\rangle \otimes |j, m_1\rangle \\ |0\rangle \otimes |j, -m_2\rangle \\ \vdots \\ |0\rangle \otimes |j, m_{K-1}\rangle \\ |0\rangle \otimes |j, m_K\rangle \end{pmatrix}, \quad (3.12)$$

the corresponding vector coherent state in (3.7) writes

$$|\Psi(\tilde{M})\rangle^j = \mathcal{N}^{-1/2} e^{\tilde{M}\hat{a}^\dagger} \begin{pmatrix} |0\rangle \otimes |j, m_1\rangle \\ |0\rangle \otimes |j, m_2\rangle \\ \vdots \\ |0\rangle \otimes |j, m_{K-1}\rangle \\ |0\rangle \otimes |j, m_K\rangle \end{pmatrix} = \mathcal{N}^{-1/2} \sum_{n=0}^{\infty} \frac{\tilde{M}^n}{\sqrt{n!}} \begin{pmatrix} |n\rangle \otimes |j, m_1\rangle \\ |n\rangle \otimes |j, m_2\rangle \\ \vdots \\ |n\rangle \otimes |j, m_{K-1}\rangle \\ |n\rangle \otimes |j, m_K\rangle \end{pmatrix}, \quad (3.13)$$

which, with a little difference in the choice of the basis vectors, belong to the class of vector coherent states on the matrix domain studied in [15]. Now, the normalization constant \mathcal{N} is more difficult to calculate, the general expression for it is:

$$\mathcal{N} = {}^j\langle\Psi(0)| e^{\tilde{M}\tilde{M}^\dagger} |\Psi(0)\rangle^j. \quad (3.14)$$

In this way, the multiple possibilities of choosing the ground state vectors show us the high level of degeneracy [17] of the energy eigenvalues of the oscillator harmonic Hamiltonian $H = \hat{a}^\dagger \hat{a}$. Indeed, the construction of the energy eigenstates $|\mathbb{E}_n\rangle^j, n = 0, 1, \dots$, of H , associated to the eigenvalue n , which can be found in the usual way

$$|\mathbb{E}_n\rangle^j = \frac{\hat{a}^n}{\sqrt{n!}} |\tilde{\Psi}(0)\rangle^j, \quad (3.15)$$

makes evidence of this phenomena. In the remainder of this section, excepting section 3.1.4, in order to illustrate the theory, we will use the choice made in equation (3.11) for the fundamental vector state.

3.1.2 Vector coherent states linked to the matrix elements of the $su(2)$ algebra generators

In this section we will study the special case when the matrix elements of \tilde{M} are given by the matrix elements of the operator $\beta \hat{I}^j - \beta_+ \hat{J}_- + \beta_- \hat{J}_+ + \beta_3 \hat{J}_3$, where β, β_\pm and β_3 are complex numbers, in the usual basis spanning the j irreducible representation space of the $su(2)$ algebra, i.e,

$$\tilde{M}_{m\ell} = \langle j, m | [\beta \hat{I}^j - \beta_+ \hat{J}_- + \beta_- \hat{J}_+ + \beta_3 \hat{J}_3 | j, \ell \rangle, \quad m, \ell = -j, -j+1, \dots, j-1, j. \quad (3.16)$$

The explicit form of this matrix is given by

$$M = \begin{pmatrix} \beta+j\beta_3 & -\sqrt{2j}\beta_+ & 0 & 0 & \dots & 0 \\ -\sqrt{2j}\beta_- & \beta+(j-1)\beta_3 & -\sqrt{(2j-1)2}\beta_+ & 0 & \dots & 0 \\ 0 & -\sqrt{(2j-1)2}\beta_- & \beta+(j-2)\beta_3 & -\sqrt{(2j-2)3}\beta_+ & \dots & 0 \\ \vdots & \vdots & \ddots & \ddots & \ddots & \vdots \\ 0 & 0 & -\sqrt{3(2j-2)}\beta_- & \beta-(j-2)\beta_3 & -\sqrt{2(2j-1)}\beta_+ & 0 \\ 0 & 0 & 0 & -\sqrt{2(2j-1)}\beta_- & \beta-(j-1)\beta_3 & -\sqrt{2j}\beta_+ \\ 0 & 0 & 0 & 0 & -\sqrt{2j}\beta_- & \beta-j\beta_3 \end{pmatrix} \quad (3.17)$$

This matrix becomes normal when the β_\pm and β_3 parameters verify equation (A.32), i.e, $\|\beta_-\| = \|\beta_+\|$ and $\beta_3\beta_-^* = \beta_3^*\beta_+$. Under these conditions the eigenvalues of this matrix $\lambda_{[m]}^j = \beta + mb$, $m = -j, \dots, j$, where $b = \sqrt{4\beta_+\beta_- + \beta_3^2} \neq 0$, are all different. Thus with the help of equation (3.11) and by spanning the vector component states in the same $su(2)$ basis vector that we used to compute the matrix elements of \tilde{M} , we can build the vector coherent states associated to the $su(2)$ algebra:

$$|\Psi(\Lambda)\rangle^j = \frac{1}{\sqrt{\sum_{m=-j}^j e^{\|\beta-mb\|^2}}} \times \tilde{U} \begin{pmatrix} e^{(\beta+jb)\hat{a}^\dagger} & 0 & 0 & \dots & \dots & 0 \\ 0 & e^{(\beta+(j-1)b)\hat{a}^\dagger} & 0 & \dots & \dots & 0 \\ 0 & 0 & \ddots & 0 & \dots & 0 \\ \vdots & \vdots & \vdots & \ddots & \vdots & \vdots \\ 0 & \dots & \dots & 0 & e^{(\beta-(j-1)b)\hat{a}^\dagger} & 0 \\ 0 & \dots & \dots & 0 & 0 & e^{(\beta-jb)\hat{a}^\dagger} \end{pmatrix} \begin{pmatrix} |0; j, -j\rangle \\ |0; j, -j+1\rangle \\ \vdots \\ |0; j, j-1\rangle \\ |0; j, j\rangle \end{pmatrix}, \quad (3.18)$$

where the entries of the unitary matrix \tilde{U} are given in appendix B, more precisely in equation (B9):

$$U_{m\ell} = T_{m\ell}^j[\beta_+, \beta_-, \beta_3]. \quad (3.19)$$

3.1.3 Vector coherent states in the $j = \frac{1}{2}$ representation

For example, in the special case when $j = \frac{1}{2}$, the unitary matrix \tilde{U} is given by

$$U = \begin{pmatrix} \sqrt{\frac{b+\beta_3}{2b}} & \frac{2\beta_+}{\sqrt{2b(b+\beta_3)}} \\ \frac{-2\beta_-}{\sqrt{2b(b+\beta_3)}} & \sqrt{\frac{b+\beta_3}{2b}} \end{pmatrix} \quad (3.20)$$

and the normal vector coherent states in (3.18) becomes

$$|\Psi(\Lambda)\rangle^{\frac{1}{2}} = \frac{1}{\sqrt{e^{\|\beta+\frac{b}{2}\|^2} + e^{\|\beta-\frac{b}{2}\|^2}}} \begin{pmatrix} \sqrt{\frac{b+\beta_3}{2b}} & \frac{2\beta_+}{\sqrt{2b(b+\beta_3)}} \\ \frac{-2\beta_-}{\sqrt{2b(b+\beta_3)}} & \sqrt{\frac{b+\beta_3}{2b}} \end{pmatrix} \begin{pmatrix} e^{(\beta+b/2)\hat{a}^\dagger} & 0 \\ 0 & e^{(\beta-b/2)\hat{a}^\dagger} \end{pmatrix} \begin{pmatrix} |0; \frac{1}{2}, -\frac{1}{2}\rangle \\ |0; \frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix} \quad (3.21)$$

where $b = \sqrt{4\beta_+\beta_- + \beta_3^2}$, or better, after some few manipulations on the normalization constant:

$$|\Psi[\beta, b(\beta_+, \beta_-, \beta_3)]\rangle^{\frac{1}{2}} = \frac{e^{-\frac{1}{2}[\|\beta\|^2 + \frac{1}{4}\|b\|^2]}}{\sqrt{2 \cosh\left[\frac{1}{2}(\beta b^* + \beta^* b)\right]}} \begin{pmatrix} \sqrt{\frac{b+\beta_3}{2b}} & \frac{2\beta_+}{\sqrt{2b(b+\beta_3)}} \\ \frac{-2\beta_-}{\sqrt{2b(b+\beta_3)}} & \sqrt{\frac{b+\beta_3}{2b}} \end{pmatrix} \times \begin{pmatrix} e^{(\beta+\frac{1}{2}b)\hat{a}^\dagger} & 0 \\ 0 & e^{(\beta-\frac{1}{2}b)\hat{a}^\dagger} \end{pmatrix} \begin{pmatrix} |0; \frac{1}{2}, -\frac{1}{2}\rangle \\ |0; \frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix} \quad (3.22)$$

These last states are eigenstates of \hat{a} with matrix type eigenvalues:

$$\tilde{M} = \begin{pmatrix} \beta - \frac{1}{2}\beta_3 & -\beta_+ \\ -\beta_- & \beta + \frac{1}{2}\beta_3 \end{pmatrix}, \quad (3.23)$$

where β_\pm and β_3 verify (A.32).

3.1.4 Quaternionic canonical vector coherent states class from $su(2)$ algebra

For the special choice of parameters

$$\begin{aligned} \beta &= r \cos \theta & \beta_3 &= 2ir \sin \theta \cos \phi \\ \beta_+ &= -ir \sin \theta \sin \phi e^{i\psi} & \beta_- &= -ir \sin \theta \sin \phi e^{-i\psi}, \quad r \neq 0, \end{aligned} \quad (3.24)$$

the parameter $b = 2ir \sin \theta$ and the \tilde{M} matrix in (3.23) becomes

$$\tilde{M} = r \cos \theta \sigma_0 + i r \sin \theta \begin{pmatrix} \cos \phi & \sin \phi e^{i\psi} \\ \sin \phi e^{-i\psi} & -\cos \phi \end{pmatrix}, \quad (3.25)$$

which is a complex representation of quaternions by 2×2 matrices in polar coordinates. Inserting the values of (3.24) into equation (3.22), and simplifying the results we get the normalized vector coherent states

$$|\Psi[r, \theta, \phi, \psi]\rangle^{\frac{1}{2}} = \begin{pmatrix} \cos \frac{\phi}{2} & -\sin \frac{\phi}{2} e^{i\psi} \\ \sin \frac{\phi}{2} e^{-i\psi} & \cos \frac{\phi}{2} \end{pmatrix} \times \frac{e^{-\frac{r^2}{2}}}{\sqrt{2}} \begin{pmatrix} e^{(re^{i\theta})\hat{a}^\dagger} & 0 \\ 0 & e^{(re^{-i\theta})\hat{a}^\dagger} \end{pmatrix} \begin{pmatrix} |0; \frac{1}{2}, -\frac{1}{2}\rangle \\ |0; \frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix} \quad (3.26)$$

These states are eigenstates of the annihilation operator associated to the quantum harmonic oscillator with matrix eigenvalues given by \tilde{M} of equation (3.25). These states are the so-called quaternionic canonical coherent states that we can find in the literature [15]. The only difference here is that our states, by virtue of our particular choice of the ground state, mix the basis states of the $su(2)$ sector of the $h(1) \otimes su(2)$ algebra. Indeed, these states can be written in the form

$$|\Psi(r, \theta, \phi, \psi)\rangle^{\frac{1}{2}} = \frac{e^{-\frac{r^2}{2}}}{\sqrt{2}} \begin{pmatrix} \cos(\frac{\phi}{2}) |re^{i\theta}; \frac{1}{2}, -\frac{1}{2}\rangle - \sin(\frac{\phi}{2}) e^{i\psi} |re^{-i\theta}; \frac{1}{2}, +\frac{1}{2}\rangle \\ \sin(\frac{\phi}{2}) e^{-i\psi} |re^{-i\theta}; \frac{1}{2}, -\frac{1}{2}\rangle + \cos(\frac{\phi}{2}) |re^{-i\theta}; \frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix} \quad (3.27)$$

that shows us explicitly that mixture.

On the other hand, if we choose the fundamental state in the form shown in (3.12) and calculate the factor \mathcal{N} with the help of (3.14), as in this case $\tilde{M}\tilde{M}^\dagger = r^2 I$, we get $\mathcal{N} = 2 e^{r^2}$. Finally, if we insert this last result in equation (3.13), adapted to particular case that is being studied here, we obtain

$$|\Psi(\tilde{M})\rangle^{\frac{1}{2}} = \frac{e^{-\frac{r^2}{2}}}{\sqrt{2}} \sum_{n=0}^{\infty} \frac{\tilde{M}^n}{\sqrt{n!}} \left(|n\rangle \otimes \left| \frac{1}{2}, -\frac{1}{2} \right\rangle \right), \quad (3.28)$$

which reproduces the results studied in [15], again with the little difference of the mixing of the states on the $su(2)$ sector, due to the particular choice of the fundamental state we are using here.

3.2 Annihilation operator vector algebra eigenstates with non-normal but diagonalizable eigenvalue matrix

When \tilde{M} in (3.17) is diagonalizable but not normal, the process of obtaining the algebra eigenstates associated to \hat{a} is identical to that we followed when \tilde{M} was normal, except for the fact that now the passing matrix P that leads \tilde{M} to its diagonal form is not unitary. Indeed, the diagonalized form of \tilde{M} is reached by performing the similarity transformation $\tilde{D} = P^{-1}\tilde{M}P$, where P^{-1} denotes the inverse of P . Then, following the same reasoning of section 3.1, we can establish that the vector eigenstates are given by

$$|\Psi(\Lambda)\rangle^j = \tilde{\mathcal{N}}^{\frac{1}{2}} \times P \begin{pmatrix} e^{\lambda_{[j]}^j \hat{a}^\dagger} & 0 & 0 & \dots & \dots & 0 \\ 0 & e^{\lambda_{[j-1]}^j \hat{a}^\dagger} & 0 & \dots & \dots & 0 \\ 0 & 0 & \ddots & 0 & \dots & 0 \\ \vdots & \vdots & \vdots & \ddots & \vdots & \vdots \\ 0 & \dots & \dots & 0 & e^{\lambda_{[-j+1]}^j \hat{a}^\dagger} & 0 \\ 0 & \dots & \dots & 0 & 0 & e^{\lambda_{[-j]}^j \hat{a}^\dagger} \end{pmatrix} \begin{pmatrix} |0; j, -j\rangle \\ |0; j, -j+1\rangle \\ \vdots \\ |0; j, j-1\rangle \\ |0; j, j\rangle \end{pmatrix}, \quad (3.29)$$

where $\lambda_{[s]}^j$, $s = -j, \dots, j$, are the eigenvalues of \tilde{M} and $\tilde{\mathcal{N}}$ is a normalization constant to be determined.

As in general P is not unitary, the computation of the normalization constant of these vector states is now more difficult than the previous case when \tilde{U} was unitary. Indeed, the eigenvectors composing the columns of the matrix P are in general not orthogonal to each other.

3.2.1 Annihilation operator algebra eigenstates with a non-normal but diagonalizable $su(2)$ eigenvalue matrix

Returning to the $su(2)$ eigenvalue matrix $\tilde{M} = M$ given by (3.17). When that matrix is diagonalizable but when no special conditions on the beta parameters are given, in certain cases, the matrix P can still be computed with the formulas of appendix B. Indeed, that is the case when $\beta_\pm \neq 0$, whichever is the value of β_3 , provided that the b parameter is different from zero, or when β_+ or β_- is equal to zero, but not both, and $\beta_3 \neq 0$. In all these cases the matrix elements of P , for fixed j , can be extracted from the matrix elements of \hat{T} given in (B9) in the following way

$$P_{m\ell} = \begin{cases} T_{m\ell}^j[\beta_+, \beta_-, \beta_3] & \text{when } \beta_+ \neq 0, \beta_- \neq 0 \text{ and } \beta_3 \neq 0 \text{ with } b \neq 0 \\ T_{m\ell}^j[0, \beta_-, \beta_3] & \text{when } \beta_+ = 0, \beta_- \neq 0 \text{ and } \beta_3 \neq 0 \\ T_{m\ell}^j[\beta_+, 0, \beta_3] & \text{when } \beta_+ \neq 0, \beta_- = 0 \text{ and } \beta_3 \neq 0 \\ T_{m\ell}^j[\beta_+, \beta_-, 0] & \text{when } \beta_+ \neq 0, \beta_- \neq 0 \text{ and } \beta_3 = 0 \end{cases}. \quad (3.30)$$

For example for $j = \frac{1}{2}$, when $\beta_+ \neq 0, \beta_- \neq 0$ and $\beta_3 \neq 0$, with $b \neq 0$, the normalized vector states are given by

$$|\Psi(\Lambda)\rangle^{\frac{1}{2}} = \frac{\sqrt{2\|b\|\|b+\beta_3\|}}{\sqrt{(4\|\beta_-\|^2 + \|b+\beta_3\|^2)e^{\|(\beta+\frac{b}{2})\|^2} + (4\|\beta_+\|^2 + \|b+\beta_3\|^2)e^{\|(\beta-\frac{b}{2})\|^2}}} \\ \times \begin{pmatrix} \sqrt{\frac{b+\beta_3}{2b}} & \frac{2\beta_+}{\sqrt{2b(b+\beta_3)}} \\ \frac{-2\beta_-}{\sqrt{2b(b+\beta_3)}} & \sqrt{\frac{b+\beta_3}{2b}} \end{pmatrix} \begin{pmatrix} e^{(\beta+\frac{1}{2}b)\hat{a}^\dagger} & 0 \\ 0 & e^{(\beta-\frac{1}{2}b)\hat{a}^\dagger} \end{pmatrix} \begin{pmatrix} |0; \frac{1}{2}, -\frac{1}{2}\rangle \\ |0; \frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix},$$

which is an eigenstate of \hat{a} with eigenvalues on the matrix domain given by (3.23), but now without any constraint on the beta parameters regarding the normality of that matrix.

Furthermore, when for example, $\beta_+ \neq 0, \beta_- = 0$ and $\beta_3 \neq 0$, we get

$$|\Psi(\Lambda)\rangle^{\frac{1}{2}} = \frac{\|\beta_3\|}{\sqrt{\|\beta_3\|^2 e^{\|(\beta+\frac{\beta_3}{2})\|^2} + (\|\beta_+\|^2 + \|\beta_3\|^2) e^{\|(\beta-\frac{\beta_3}{2})\|^2}}} \\ \times \begin{pmatrix} 1 & \frac{\beta_+}{\beta_3} \\ 0 & 1 \end{pmatrix} \begin{pmatrix} e^{(\beta+\frac{1}{2}\beta_3)\hat{a}^\dagger} & 0 \\ 0 & e^{(\beta-\frac{1}{2}\beta_3)\hat{a}^\dagger} \end{pmatrix} \begin{pmatrix} |0; \frac{1}{2}, -\frac{1}{2}\rangle \\ |0; \frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix} \quad (3.31)$$

which is an eigenstate of \hat{a} with matrix eigenvalues

$$\begin{pmatrix} \beta + \frac{\beta_3}{2} & -\beta_+ \\ 0 & \beta - \frac{\beta_3}{2} \end{pmatrix}, \quad (3.32)$$

where no restrictions are assumed on the beta parameters with respect to the normality of this matrix.

3.2.2 An example with a non-diagonalizable $su(2)$ eigenvalue matrix

When \tilde{M} in (3.17) is not diagonalizable, the process of obtaining the algebra eigenstates of \hat{a} is, in general, more elaborate than the case when this matrix is diagonalizable, sometimes we can use the exponential form of the matrix M and the operator algebra or to solve the eigenvalue equation in a systematic way, component by component. Let us illustrate the solving techniques with a simple example using the $j = \frac{1}{2}$ basis vector representation for calculating the matrix elements of \tilde{M} and leaving free choice for the dimension of the irreducible representation used to span the components of the vector states. Let us take for this purpose the case when $\beta_+ \neq 0$ and $\beta_- = \beta_3 = 0$, and consequently $b = 0$. Thus, the eigenvalue we have to solve is

$$\hat{a} \begin{pmatrix} |\psi\rangle^1 \\ |\psi\rangle^2 \end{pmatrix} = \begin{pmatrix} \beta & -\beta_+ \\ 0 & \beta \end{pmatrix} \begin{pmatrix} |\psi\rangle^1 \\ |\psi\rangle^2 \end{pmatrix}, \quad (3.33)$$

where the states $|\psi\rangle^k = \sum_{n=0}^{\infty} \sum_{m=-j}^j C_{nm}^k |n\rangle \otimes |j, m\rangle$, $k = 1, 2$. By projecting both sides of this equation on the analytic basis states $\langle \zeta |$ and then using the realization (2.11) for the annihilation operator \hat{a} , we get a system of ordinary linear differential equation for the components of $\psi^k(\zeta) = \langle \zeta | \psi\rangle^k$, $k = 1, 2$, that is,

$$\frac{d}{d\zeta} \begin{pmatrix} \psi_m^1(\zeta) \\ \psi_m^2(\zeta) \end{pmatrix} = \begin{pmatrix} \beta & -\beta_+ \\ 0 & \beta \end{pmatrix} \begin{pmatrix} \psi_m^1(\zeta) \\ \psi_m^2(\zeta) \end{pmatrix}, \quad m = -1, \dots, j, \quad (3.34)$$

which explicitly corresponds to

$$\begin{aligned} \frac{d}{d\zeta} \psi_m^1(\zeta) &= \beta \psi_m^1(\zeta) - \beta_+ \psi_m^2(\zeta) \\ \frac{d}{d\zeta} \psi_m^2(\zeta) &= \beta \psi_m^2(\zeta), \quad m = -j, \dots, j. \end{aligned} \quad (3.35)$$

The integration of $\psi_m^2(\zeta)$ is direct, we get $\psi_m^2(\zeta) = e^{\beta\zeta} \psi_m^2(0)$, $m = -1, \dots, j$. Inserting this last result into the first of equations (3.35) and then integrating the resulting non-homogeneous first order linear differential equation for each function $\psi_m^1(\zeta)$, $m = -j, \dots, j$, we get $\psi_m^1(\zeta) = e^{\beta\zeta} \psi_m^1(0) - \beta_+ \zeta e^{\beta\zeta} \psi_m^2(0)$, $m = -j, \dots, j$. Finally, returning to the Fock basis of the number eigenstates $|n\rangle$ we obtain the vector component state

$$|\psi\rangle^1 = e^{\beta\hat{a}^\dagger} \left[\sum_{m=-j}^j \psi_m^1(0) |0\rangle \otimes |j, m\rangle - \beta_+ \hat{a}^\dagger \sum_{m=-j}^j \psi_m^2(0) |0\rangle \otimes |j, m\rangle \right]$$

and the vector component state

$$|\psi\rangle^2 = e^{\beta\hat{a}^\dagger} \sum_{m=-j}^j \psi_m^2(0) |0\rangle \otimes |j, m\rangle,$$

which represent the super-coherent states of the super-symmetric Harmonic oscillator introduced by Aragon and Zypman [18]. Let us recall that this same states also are included in the set of algebra eigenstates of the generalized annihilation operator $\hat{a} + \beta_+ \hat{J}_-$, the difference is that here these states arise as the components of a vector state, that is,

$$|\Psi\rangle_{\frac{1}{2}} = \begin{pmatrix} |\psi\rangle^1 \\ |\psi\rangle^2 \end{pmatrix} = e^{\beta\hat{a}^\dagger} \begin{pmatrix} 1 & -\beta_+ \hat{a}^\dagger \\ 0 & 1 \end{pmatrix} \begin{pmatrix} \sum_{m=-j}^j \psi_m^1(0) |0\rangle \otimes |j, m\rangle \\ \sum_{m=-j}^j \psi_m^2(0) |0\rangle \otimes |j, m\rangle \end{pmatrix} = e^{M\hat{a}^\dagger} \begin{pmatrix} \sum_{m=-j}^j \psi_m^1(0) |0\rangle \otimes |j, m\rangle \\ \sum_{m=-j}^j \psi_m^2(0) |0\rangle \otimes |j, m\rangle \end{pmatrix}, \quad (3.36)$$

and are eigenstates of the annihilator \hat{a} with matrix eigenvalues given by $\begin{pmatrix} \beta & -\beta_+ \\ 0 & \beta \end{pmatrix}$.

4 $h(1) \oplus su(2)$ vector algebra eigenstates with matrix eigenvalues

In this section we propose a generalization of the concept of vector coherent states associated to the annihilation operator \hat{a} to include those states which are eigenvectors of a class of generalized $h(1) \oplus su(2)$ type annihilation operator. To start, let us consider the problem of finding the vector states that satisfy the following eigenvalue equation system:¹

$$\left[\hat{a} + \beta_- \hat{J}_+ + \beta_+ \hat{J}_- + \beta_3 \hat{J}_3 \right] |\Psi\rangle_{[K]}^j = \tilde{M} |\Psi\rangle_{[K]}^j, \quad (4.1)$$

with \tilde{M} being now a $K \times K$ diagonalizable complex matrix and $|\Psi\rangle_{[K]}^j$ a vector state of K components having exactly the same characteristic they had in the last section, i.e.,

$$|\Psi\rangle_{[K]}^j = \begin{pmatrix} |\psi\rangle_{[1]}^j \\ |\psi\rangle_{[2]}^j \\ \vdots \\ |\psi\rangle_{[K-1]}^j \\ |\psi\rangle_{[K]}^j \end{pmatrix}, \quad (4.2)$$

¹In fact, we could define this equation as $[\alpha_- \hat{a} + \alpha_+ \hat{a}^\dagger + \alpha_3 \hat{I} + \beta_- \hat{J}_+ + \beta_+ \hat{J}_- + \beta_3 \hat{J}_3] |\Psi\rangle_{[K]}^j = \tilde{M} |\Psi\rangle_{[K]}^j$, but by performing a suitable squeezed state transformation and then by absorbing the identity operator coefficient into the β parameter we get (4.1), see appendix A.

where each state $|\psi\rangle_{[s]}^j = \sum_{m=-j}^j \sum_{n=0}^{\infty} C_{nm}^{[s]j} |n\rangle \otimes |j, m\rangle$, $1 \leq s \leq K$, is a unknown state of the $h(1) \oplus su(2)$ representation space to be determined.

As before, if \tilde{M} is diagonalizable, then there is a P matrix of dimension $K \times K$ such that $P^{-1}\tilde{M}P = \tilde{D}$ is a diagonal matrix which non-null entries are given by the eigenvalues of \tilde{M} . Therefore, firstly, defining

$$|\Psi\rangle_{[K]}^j = P |\tilde{\Psi}\rangle_{[K]}^j, \quad \text{or equivalently} \quad |\tilde{\Psi}\rangle_{[K]}^j = P^{-1} |\Psi\rangle_{[K]}^j, \quad (4.3)$$

and then by acting with P^{-1} from the left on both sides of equation (4.1), we get

$$[\hat{a} + \beta_- \hat{J}_+ + \beta_+ \hat{J}_- + \beta_3 \hat{J}_3] |\tilde{\Psi}\rangle_{[K]}^j = \tilde{D} |\tilde{\Psi}\rangle_{[K]}^j. \quad (4.4)$$

If we denote by $\tilde{\lambda}_{[s]}$, $s = 1, 2, \dots, K$, the eigenvalues of \tilde{M} which are distributed in this same order, from top to bottom, on the diagonal principal of \tilde{D} , we obtain a system of K independent $h(1) \oplus su(2)$ algebra eigenstates equations, that is

$$[\hat{a} + \beta_- \hat{J}_+ + \beta_+ \hat{J}_- + \beta_3 \hat{J}_3] |\tilde{\psi}\rangle_{[s]}^j = \tilde{\lambda}_{[s]} |\tilde{\psi}\rangle_{[s]}^j, \quad s = 1, 2, \dots, K. \quad (4.5)$$

As discussed in section 3.2.1, the $h(1) \oplus su(2)$ algebra eigenstates can be obtained for all different values of the beta parameters. That means a wide variety of situations to be analyzed, each of which provides us with an interesting set of vector states verifying the original equation system. For example, when $b \neq 0$, the general expression for the $h(1) \oplus su(2)$ algebra eigenstates $|\tilde{\psi}\rangle_{[s]}^j$ is given by equation (A.46), with the corresponding $\tilde{\lambda}_{[s]}$ in place of the β parameter, that is

$$\begin{aligned} |\tilde{\psi}\rangle_{[s]}^j &= N_{[s]}^{-1/2} \\ &\times \left(\tilde{\psi}_{[s],-j}^j(0) e^{\lambda_j^{[s]j} \hat{a}^\dagger} \tilde{\psi}_{[s],-j+1}^j(0) e^{\lambda_{j-1}^{[s]j} \hat{a}^\dagger} \dots \tilde{\psi}_{[s],j-1}^j(0) e^{\lambda_{-j+1}^{[s]j} \hat{a}^\dagger} \tilde{\psi}_{[s],j}^j(0) e^{\lambda_{-j}^{[s]j} \hat{a}^\dagger} \right) \\ &\times V^t \begin{pmatrix} |0; j, -j\rangle \\ |0; j, -j+1\rangle \\ \vdots \\ |0; j, j-1\rangle \\ |0; j, j\rangle \end{pmatrix}, \quad s = 1, 2, \dots, K, \end{aligned} \quad (4.6)$$

where $\lambda_m^{[s]j} = \tilde{\lambda}_{[s]} + mb$, $s = 1, 2, \dots, K$ and V is an invertible matrix whose matrix elements are given explicitly in equation (B9), then

$$V_{m\ell} = T_{m\ell}^j[\beta_+, \beta_-, \beta_3], \quad b \neq 0. \quad (4.7)$$

Finally using (4.3), we can return to the original vector states which are solutions of equation (4.1), thus we get the K components of the $h(1) \otimes su(2)$ vector state (4.2) that verifies (4.1), they are:

$$|\psi\rangle_{[u]}^j = \sum_{s=1}^K P_{us} |\tilde{\psi}\rangle_{[s]}^j, \quad u = 1, 2, \dots, K. \quad (4.8)$$

We recall that for each s , equation (4.6) represent the general solution of equation (4.5). It corresponds to a state formed from a set of $2j + 1$ linearly independent states which are by themselves solutions of (4.5). Then, for each s , we can choose an arbitrary combination of these states and then insert it in equation (4.8) to obtain the final structure of the vector states which verify equation (4.1). This freedom of choice implies a very large variety of linearly independent solutions, more precisely $K \times (2j + 1)$ independent solutions.

4.1 Generalized $h(1) \oplus su(2)$ vector coherent states on the matrix domain

In this article, we are interested in states that could be interpreted as vector coherent states of a given physics system. Then, instead of proceeding with the case-by-case analysis, let us select the parameters according to the necessary conditions they have to fulfill at the moment of constructing a suitable generalized annihilation operator extracted from the linear combination of generators shown in equation (4.5). Proceeding in this way, let us define the operator

$$\mathbb{A} = \hat{a} + \beta_- \hat{J}_+ + \beta_+ \hat{J}_- + \beta_3 \hat{J}_3, \quad (4.9)$$

whose commutator with \mathbb{A}^\dagger is given by

$$[\mathbb{A}, \mathbb{A}^\dagger] = \hat{I} + 2(\|\beta_-\|^2 - \|\beta_+\|^2) \hat{J}_3 + (\beta_3 \beta_+^* - \beta_3^* \beta_-) \hat{J}_+ + (\beta_3^* \beta_+ - \beta_3 \beta_-^*) \hat{J}_-. \quad (4.10)$$

From this last equation we can see that when $\|\beta_+\| = \|\beta_-\|$ and $\beta_3 \beta_+^* = \beta_3^* \beta_-$, which are the same conditions that make the matrix M in (3.17) normal, including certainty here the special case when $\beta_+ = \beta_- = 0$ and $\beta_3 \neq 0$, the commutator becomes

$$[\mathbb{A}, \mathbb{A}^\dagger] = \hat{I}, \quad (4.11)$$

i.e., the corresponding set of vector states which are solutions of equation(4.1) can be interpreted as vector coherent states in the context of the physical system whose Hamiltonian is given by $\mathbb{H} = \mathbb{A}^\dagger \mathbb{A}$. If we write the beta parameters in the form $\beta_\pm = R e^{i\theta_\pm}$ and $\beta_3 = R_3 e^{i\theta_3}$, with R and R_3 being no negative real numbers, the new operator thus defined takes the form

$$\mathbb{A} = \hat{a} + R[e^{i\theta_-} \hat{J}_+ + e^{i\theta_+} \hat{J}_-] + R_3 e^{i\frac{(\theta_+ + \theta_-)}{2}} \hat{J}_3, \quad (4.12)$$

and then the above newly defined Hamiltonian writes

$$\begin{aligned} \mathbb{H} &= \hat{a}^\dagger \hat{a} + R \hat{a}^\dagger [e^{i\theta_-} \hat{J}_+ + e^{i\theta_+} \hat{J}_-] + R [e^{-i\theta_-} \hat{J}_- + e^{-i\theta_+} \hat{J}_+] \hat{a} + R_3 [e^{i\frac{(\theta_+ + \theta_-)}{2}} \hat{a}^\dagger + e^{-i\frac{(\theta_+ + \theta_-)}{2}} \hat{a}] \hat{J}_3 \\ &+ R^2 [\hat{J}_- \hat{J}_+ + \hat{J}_+ \hat{J}_-] + R^2 [e^{i(\theta_+ - \theta_-)} \hat{J}_-^2 + e^{-i(\theta_+ - \theta_-)} \hat{J}_+^2] + R_3^2 \hat{J}_3^2 \\ &+ RR_3 e^{-i\frac{(\theta_+ - \theta_-)}{2}} [\hat{J}_+ \hat{J}_3 + \hat{J}_3 \hat{J}_+] + RR_3 e^{i\frac{(\theta_+ - \theta_-)}{2}} [\hat{J}_- \hat{J}_3 + \hat{J}_3 \hat{J}_-]. \end{aligned} \quad (4.13)$$

We can see that, by the way this last Hamiltonian was constructed and in accordance with the commutation relation (4.11), this Hamiltonian is isospectral with the standard harmonic oscillator Hamiltonian although its eigenstates are very different. Nevertheless, if we define $|\tilde{0}\rangle$ as being a suitable ground state of this system such that $\mathbb{A} |\tilde{0}\rangle = 0$, we can be sure that the associated vector coherent states, which are eigenstates of \mathbb{A} with the entries of \tilde{M} as its eigenvalues, are given by $e^{[\tilde{M}\mathbb{A}^\dagger - \tilde{M}^\dagger \mathbb{A}]} |\tilde{0}\rangle$, as long as \tilde{M} is normal. We will probe now in general this last assertion and show explicitly the technique used in doing that at the end of the following section with an example for the the special case $K = 2$ and $j = \frac{1}{2}$.

4.1.1 Generalized matrix displacement operator

Using the operator algebra described in appendix B, we can show that a generic algebra eigenstate $|\tilde{\psi}\rangle_{[s]m}^j$ verifying (4.5), in the case that $b \neq 0$, can be written in the form

$$|\tilde{\psi}\rangle_{[s]m}^j = |\tilde{\lambda}_{[s]} - mb\rangle \otimes \hat{T} |j, m\rangle = \hat{D}(\tilde{\lambda}_{[s]} - mb) |0\rangle \otimes \hat{T} |j, m\rangle, \quad (4.14)$$

where \hat{T} is the exponential operator defined in (B2), which parameters are defined in (B3). We notice that when $\beta_+ = \beta_- = 0$ and $\beta_3 \neq 0$, the operator $T = I$.

Using the displacement operator property $\hat{D}(z_1 + z_2) = \hat{D}(z_1) \hat{D}(z_2) \exp \frac{1}{2}[z_1^* z_2 - z_1 z_2^*]$, we get

$$|\tilde{\psi}\rangle_{[s]m}^j = \hat{D}(\tilde{\lambda}_{[s]}) \exp \frac{m}{2} [\tilde{\lambda}_{[s]} b^* - \tilde{\lambda}_{[s]}^* b] | -mb\rangle \otimes \hat{T} |j, m\rangle. \quad (4.15)$$

Defining $\vec{\beta} \cdot \vec{J} = \beta_+ \hat{J}_- + \beta_- \hat{J}_+ + \beta_3 \hat{J}_3$ and using the fact that in this particular case

$$(\vec{\beta} \cdot \vec{J}) \hat{T} |j, m\rangle = mb \hat{T} |j, m\rangle, \quad \text{and} \quad (\vec{\beta} \cdot \vec{J})^\dagger \hat{T} |j, m\rangle = mb^* \hat{T} |j, m\rangle, \quad (4.16)$$

equation (4.15) becomes

$$|\tilde{\psi}\rangle_{[s]m}^j = \hat{D}(\tilde{\lambda}_{[s]}) \exp\left(\frac{1}{2} \left[\tilde{\lambda}_{[s]}(\vec{\beta} \cdot \vec{f})^\dagger - \tilde{\lambda}_{[s]}^* \vec{\beta} \cdot \vec{f} \right]\right) | -mb \rangle \otimes \hat{T} | j, m \rangle. \quad (4.17)$$

Thus the normalized general solution of (4.5) is given by

$$|\tilde{\psi}\rangle_{[s]}^j = \frac{\sum_{m=-j}^j \varphi_{[s]m}^j(0) |\tilde{\psi}\rangle_{[s]m}^j}{\sqrt{\sum_{m=-j}^j \|\varphi_{[s]m}^j(0)\|^2}}, \quad (4.18)$$

or more explicitly by

$$|\tilde{\psi}\rangle_{[s]}^j = \hat{D}(\tilde{\lambda}_{[s]}) \exp\left(\frac{1}{2} \left[\tilde{\lambda}_{[s]}(\vec{\beta} \cdot \vec{f})^\dagger - \tilde{\lambda}_{[s]}^* \vec{\beta} \cdot \vec{f} \right]\right) \frac{\sum_{m=-j}^j \varphi_{[s]m}^j(0) | -mb \rangle \otimes \hat{T} | j, m \rangle}{\sqrt{\sum_{m=-j}^j \|\varphi_{[s]m}^j(0)\|^2}}. \quad (4.19)$$

Inserting this last result into equation (4.8), which give us the component of the general vector coherent states verifying (4.1), we obtain the matrix realization of these states:

$$|\Psi\rangle_{[K]}^j = \tilde{U} \begin{pmatrix} \hat{D}(\tilde{\lambda}_{[1]}) & 0 & \cdots & 0 & 0 \\ 0 & \hat{D}(\tilde{\lambda}_{[2]}) & 0 & \cdots & 0 \\ \vdots & 0 & \ddots & 0 & \vdots \\ 0 & \cdots & 0 & \hat{D}(\tilde{\lambda}_{[K-1]}) & 0 \\ 0 & 0 & \cdots & 0 & \hat{D}(\tilde{\lambda}_{[K]}) \end{pmatrix} \times \begin{pmatrix} \hat{B}(\tilde{\lambda}_{[1]}) & 0 & \cdots & 0 & 0 \\ 0 & \hat{B}(\tilde{\lambda}_{[2]}) & 0 & \cdots & 0 \\ \vdots & 0 & \ddots & 0 & \vdots \\ 0 & \cdots & 0 & \hat{B}(\tilde{\lambda}_{[K-1]}) & 0 \\ 0 & 0 & \cdots & 0 & \hat{B}(\tilde{\lambda}_{[K]}) \end{pmatrix} \begin{pmatrix} \frac{\sum_{m=-j}^j \varphi_{[1]m}^j(0) | -mb \rangle \otimes \hat{T} | j, m \rangle}{\sum_{m=-j}^j \|\varphi_{[1]m}^j(0)\|^2} \\ \frac{\sum_{m=-j}^j \varphi_{[2]m}^j(0) | -mb \rangle \otimes \hat{T} | j, m \rangle}{\sum_{m=-j}^j \|\varphi_{[2]m}^j(0)\|^2} \\ \vdots \\ \frac{\sum_{m=-j}^j \varphi_{[K]m}^j(0) | -mb \rangle \otimes \hat{T} | j, m \rangle}{\sum_{m=-j}^j \|\varphi_{[K]m}^j(0)\|^2} \end{pmatrix}, \quad (4.20)$$

where $\hat{B}(\tilde{\lambda}_{[s]}) = \exp\left(\frac{1}{2} \left[\tilde{\lambda}_{[s]}(\vec{\beta} \cdot \vec{f})^\dagger - \tilde{\lambda}_{[s]}^* \vec{\beta} \cdot \vec{f} \right]\right)$, $s = 1, \dots, K$. Equation (4.20) represent a set of $(2j + 1)^K$ linearly independent vector coherent states associated to the generalized harmonic oscillator system here defined.

By setting the integration parameters appropriately we can change the form of these states to a more familiar one, for example, by choosing

$$\varphi_{[s]m}^j(0) = \sum_{u=1}^K \sum_{r=1}^K \tilde{U}_{[s][u]}^\dagger \exp\left(\frac{m}{2} [\tilde{M}b^* - \tilde{M}^\dagger b]\right)_{[u][r]} \delta_{m_{[r]}m}, \quad (4.21)$$

where $\delta_{m_{[r]}m}$ is the Kronecker delta, (4.20) writes

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \tilde{U} \begin{pmatrix} \hat{D}(\tilde{\lambda}_{[1]}) & 0 & \cdots & 0 & 0 \\ 0 & \hat{D}(\tilde{\lambda}_{[2]}) & 0 & \cdots & 0 \\ \vdots & 0 & \ddots & 0 & \vdots \\ 0 & \cdots & 0 & \hat{D}(\tilde{\lambda}_{[K-1]}) & 0 \\ 0 & 0 & \cdots & 0 & \hat{D}(\tilde{\lambda}_{[K]}) \end{pmatrix} \\
&\times \begin{pmatrix} \hat{B}(\tilde{\lambda}_{[1]}) & 0 & \cdots & 0 & 0 \\ 0 & \hat{B}(\tilde{\lambda}_{[2]}) & 0 & \cdots & 0 \\ \vdots & 0 & \ddots & 0 & \vdots \\ 0 & \cdots & 0 & \hat{B}(\tilde{\lambda}_{[K-1]}) & 0 \\ 0 & 0 & \cdots & 0 & \hat{B}(\tilde{\lambda}_{[K]}) \end{pmatrix} \tilde{U}^\dagger \\
&\times \exp\left[\frac{1}{2}\left(\tilde{M}(\vec{\beta} \cdot \vec{f})^\dagger - \tilde{M}^\dagger(\vec{\beta} \cdot \vec{f})\right)\right] \begin{pmatrix} | -m_1 b \rangle \otimes \hat{T} | j, m_1 \rangle \\ | -m_2 b \rangle \otimes \hat{T} | j, m_2 \rangle \\ \vdots \\ | -m_K b \rangle \otimes \hat{T} | j, m_K \rangle \end{pmatrix}. \tag{4.22}
\end{aligned}$$

Finally, using the fact that the exponential of a diagonal square matrix is equal to a diagonal square matrix which elements are given by the exponential of the diagonal elements of the starting matrix and vice versa, and that $\tilde{U}\tilde{D}\tilde{U}^\dagger = \tilde{M}$, we can put (4.22) in the compact form

$$|\Psi\rangle_{[K]}^j = \exp\left[\tilde{M}\mathbf{A}^\dagger - \tilde{M}^\dagger\mathbf{A}\right] \begin{pmatrix} | -m_1 b \rangle \otimes \hat{T} | j, m_1 \rangle \\ | -m_2 b \rangle \otimes \hat{T} | j, m_2 \rangle \\ \vdots \\ | -m_K b \rangle \otimes \hat{T} | j, m_K \rangle \end{pmatrix}. \tag{4.23}$$

This result can evidently be obtained in a more heuristic way. Indeed, as here $[\hat{A}, \hat{A}^\dagger] = \hat{I}$, we can try a solution of (4.5) in the exponential form $|\Psi\rangle = \exp(\tilde{M}\hat{A})|\Omega\rangle$. Then with the help of the relation $\hat{A}\exp(\tilde{M}\hat{A}) = \exp(\tilde{M}\hat{A})\hat{A} + \tilde{M}\exp(\tilde{M}\hat{A})$, we can reduce the problem to simply calculate the fundamental state, that is, the eigenstate of \hat{A} with matrix eigenvalue equal to zero, $\hat{A}|\Omega\rangle = 0$.

This set of these vector coherent states verify all properties of the standard harmonic oscillator coherent states with respect to completeness, resolution of the identity and minimum uncertainty states. They are obtained by acting with a generalized matrix displacement operator on a zero energy eigenstate.

4.1.2 Vector coherent states of two components

When $K = 2$, the \tilde{M} matrix has the general form

$$\tilde{M} = \begin{pmatrix} \tilde{m}_{11} & \tilde{m}_{12} \\ \tilde{m}_{21} & \tilde{m}_{22} \end{pmatrix}, \tag{4.24}$$

and its associated eigenvalues are

$$\tilde{\lambda}_{[\pm]} = \frac{1}{2}(\tilde{m}_{11} + \tilde{m}_{22}) \pm \tilde{b}, \quad \text{where} \quad \tilde{b} = \sqrt{4\tilde{m}_{12}\tilde{m}_{21} + (\tilde{m}_{11} - \tilde{m}_{22})^2}. \tag{4.25}$$

Assuming that $\tilde{b} \neq 0$, we can show that the passing matrices take the form

$$P = \begin{pmatrix} 2\tilde{m}_{12} & \tilde{m}_{11} - \tilde{m}_{22} - \tilde{b} \\ \tilde{m}_{22} - \tilde{m}_{11} + \tilde{b} & 2\tilde{m}_{21} \end{pmatrix}, \quad P^{-1} = \frac{\begin{pmatrix} 2\tilde{m}_{21} & \tilde{m}_{22} - \tilde{m}_{11} + \tilde{b} \\ \tilde{m}_{11} - \tilde{m}_{22} - \tilde{b} & 2\tilde{m}_{12} \end{pmatrix}}{2\tilde{b}(1 + \tilde{m}_{22} - \tilde{m}_{11})}, \tag{4.26}$$

and we can verify that

$$P^{-1}\tilde{M}P = \tilde{D} = \begin{pmatrix} \tilde{\lambda}_+ & 0 \\ 0 & \tilde{\lambda}_- \end{pmatrix}. \quad (4.27)$$

Then the two component vector coherent state writes

$$|\Psi\rangle_{[2]}^j = \mathcal{N}^{-1/2} P |\tilde{\Psi}\rangle_{[2]}^j = \mathcal{N}^{-1/2} \begin{pmatrix} 2\tilde{m}_{12} & \tilde{m}_{11} - \tilde{m}_{22} - \tilde{b} \\ \tilde{m}_{22} - \tilde{m}_{11} + \tilde{b} & 2\tilde{m}_{21} \end{pmatrix} \begin{pmatrix} |\tilde{\psi}\rangle_{[1]}^j \\ |\tilde{\psi}\rangle_{[2]}^j \end{pmatrix} \quad (4.28)$$

where \mathcal{N} is a normalization constant to be determined by the condition ${}^j_{[2]}\langle\Psi|\Psi\rangle_{[2]}^j = 1$, or more explicitly

$$|\Psi\rangle_{[2]}^j = \mathcal{N}^{-1/2} \begin{pmatrix} 2\tilde{m}_{12} |\tilde{\psi}\rangle_{[1]}^j + [\tilde{m}_{11} - \tilde{m}_{22} - \tilde{b}] |\tilde{\psi}\rangle_{[2]}^j \\ [\tilde{m}_{22} - \tilde{m}_{11} + \tilde{b}] |\tilde{\psi}\rangle_{[1]}^j + 2\tilde{m}_{21} |\tilde{\psi}\rangle_{[2]}^j \end{pmatrix}. \quad (4.29)$$

When \tilde{M} in (4.24) is normal, i.e., when its entries verify $\tilde{m}_{12}(\tilde{m}_{11} - \tilde{m}_{22})^* = \tilde{m}_{21}^*(\tilde{m}_{11} - \tilde{m}_{22})$ and $\|\tilde{m}_{12}\| = \|\tilde{m}_{21}\|$, the P matrix in (4.26) becomes unitary, which we name \tilde{U} , then normalization constant in (4.28) is easier to compute.

4.1.3 Generalized quaternionic vector coherent states

When we choose the entries of \tilde{M} in equation (4.24) as

$$\begin{aligned} \tilde{m}_{11} &= r[\cos\theta + i\sin\theta\cos\phi], & \tilde{m}_{12} &= ir\sin\theta\sin\phi e^{i\psi} \\ \tilde{m}_{21} &= ir\sin\theta\sin\phi e^{-i\psi} & \text{and} & \tilde{m}_{22} = r[\cos\theta - i\sin\theta\cos\phi], \end{aligned} \quad (4.30)$$

then $\tilde{b} = 2ir\sin\theta$, $\tilde{\lambda}_{[\pm]} = re^{\pm i\theta}$ and \tilde{M} becomes normal and takes the form given in equation (3.25), which corresponds to a complex representation of quaternions by square matrices of dimension 2. Also, the matrix P becomes unitary and the states in equation (4.29) turn into the following generalized quaternionic vector coherent states:

$$|\Psi\rangle_{[2]}^j = \mathcal{N}^{-1/2} \begin{pmatrix} \cos\left(\frac{\phi}{2}\right) e^{i\psi} |\tilde{\psi}\rangle_{[1]}^j - \sin\left(\frac{\phi}{2}\right) |\tilde{\psi}\rangle_{[2]}^j \\ \sin\left(\frac{\phi}{2}\right) |\tilde{\psi}\rangle_{[1]}^j + \cos\left(\frac{\phi}{2}\right) e^{-i\psi} |\tilde{\psi}\rangle_{[2]}^j \end{pmatrix}, \quad (4.31)$$

where some multiplicative factors have been absorbed by the normalization constant \mathcal{N} .

For example, in the special case $j = \frac{1}{2}$, the states

$$|\tilde{\psi}\rangle_{[s]}^{\frac{1}{2}} = N_{[s]}^{-1/2} \begin{pmatrix} \tilde{\psi}_{[s]-\frac{1}{2}}^{\frac{1}{2}}(0) e^{\lambda_{\frac{1}{2}}^{[s]\frac{1}{2}} a^\dagger} & \tilde{\psi}_{[s]+\frac{1}{2}}^{\frac{1}{2}}(0) e^{-\lambda_{-\frac{1}{2}}^{[s]\frac{1}{2}} a^\dagger} \end{pmatrix} V^t \begin{pmatrix} |0; \frac{1}{2}, -\frac{1}{2}\rangle \\ |0; \frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix}, \quad s = 1, 2, \quad (4.32)$$

where $\lambda_{\pm\frac{1}{2}}^{[s]\frac{1}{2}} = \tilde{\lambda}_{[s]} + \frac{1}{2}b, s = 1, 2$ and $\lambda_{-\frac{1}{2}}^{[s]\frac{1}{2}} = \tilde{\lambda}_{[s]} - \frac{1}{2}b, s = 1, 2$, with $b = \sqrt{4\beta_+\beta_- + \beta_3^2}$, and

$$V = \begin{pmatrix} \sqrt{\frac{b+\beta_3}{2b}} & \frac{2\beta_+}{\sqrt{2b(b+\beta_3)}} \\ \frac{-2\beta_-}{\sqrt{2b(b+\beta_3)}} & \sqrt{\frac{b+\beta_3}{2b}} \end{pmatrix}, \quad (4.33)$$

where β_\pm and β_3 satisfy the necessary conditions for $[\mathbb{A}, \mathbb{A}^\dagger] = \mathbb{I}$. Explicitly, the eigenvalues of the $h(1) \otimes su(2)$ sector, depending on the eigenvalues of the \tilde{M} matrix, are given by

$$\begin{aligned} \lambda_{+\frac{1}{2}}^{[1]\frac{1}{2}} &= re^{i\theta} + \frac{b}{2}, & \lambda_{-\frac{1}{2}}^{[1]\frac{1}{2}} &= re^{i\theta} - \frac{b}{2}, \\ \lambda_{+\frac{1}{2}}^{[2]\frac{1}{2}} &= re^{-i\theta} + \frac{b}{2}, & \lambda_{-\frac{1}{2}}^{[2]\frac{1}{2}} &= re^{-i\theta} - \frac{b}{2}, \end{aligned} \quad (4.34)$$

with $b = e^{i\theta_3} \sqrt{4R^2 + R_3^2}$, where $e^{i\theta_3} = e^{\frac{i}{2}(\theta_+ + \theta_-)}$, and the unitary matrix V reads

$$V = \sqrt{\frac{R_3 + \sqrt{4R^2 + R_3^2}}{2\sqrt{4R^2 + R_3^2}}} \begin{pmatrix} 1 & \frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} \\ \frac{-2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} & 1 \end{pmatrix}. \quad (4.35)$$

Finally using (4.6) for the particular case being treated here we get the set of states

$$\begin{aligned} |\tilde{\psi}\rangle_{[1]}^{\frac{1}{2}} &= \sqrt{\frac{R_3 + \sqrt{4R^2 + R_3^2}}{2\sqrt{4R^2 + R_3^2}}} \\ &\times \left\{ \tilde{\psi}_{[1]^{-\frac{1}{2}}}^{\frac{1}{2}}(0) \left[|re^{i\theta} + \frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle - \frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |re^{i\theta} + \frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \right] \right. \\ &+ \left. \tilde{\psi}_{[1]^{\frac{1}{2}}}^{\frac{1}{2}}(0) \left[\frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |re^{i\theta} - \frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle + |re^{i\theta} - \frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \right] \right\} \end{aligned} \quad (4.36)$$

and

$$\begin{aligned} |\tilde{\psi}\rangle_{[2]}^{\frac{1}{2}} &= \sqrt{\frac{R_3 + \sqrt{4R^2 + R_3^2}}{2\sqrt{4R^2 + R_3^2}}} \\ &\times \left\{ \tilde{\psi}_{[2]^{-\frac{1}{2}}}^{\frac{1}{2}}(0) \left[|re^{-i\theta} + \frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle - \frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |re^{-i\theta} + \frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \right] \right. \\ &+ \left. \tilde{\psi}_{[2]^{\frac{1}{2}}}^{\frac{1}{2}}(0) \left[\frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |re^{-i\theta} - \frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle + |re^{-i\theta} - \frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \right] \right\}. \end{aligned} \quad (4.37)$$

Thus, if we insert these last results into equation (4.29) for fixed $j = 1/2$, with the corresponding unitary matrix \tilde{U} given by

$$\tilde{U} = \begin{pmatrix} \cos\left(\frac{\phi}{2}\right)e^{i\psi} & -\sin\left(\frac{\phi}{2}\right) \\ \sin\left(\frac{\phi}{2}\right) & \cos\left(\frac{\phi}{2}\right)e^{-i\psi} \end{pmatrix}, \quad (4.38)$$

we finally obtain the generalized quaternionic vector coherent states based on the $\mathfrak{h}(1) \oplus \mathfrak{su}(2)$ algebra.

$$|\Psi\rangle_{[2]}^{\frac{1}{2}} = \mathcal{N}^{-\frac{1}{2}} \tilde{U} \begin{pmatrix} |\tilde{\psi}\rangle_{[1]}^{\frac{1}{2}} \\ |\tilde{\psi}\rangle_{[2]}^{\frac{1}{2}} \end{pmatrix} = \mathcal{N}^{-\frac{1}{2}} \begin{pmatrix} \cos\left(\frac{\phi}{2}\right)e^{i\psi} |\tilde{\psi}\rangle_{[1]}^{\frac{1}{2}} - \sin\left(\frac{\phi}{2}\right) |\tilde{\psi}\rangle_{[2]}^{\frac{1}{2}} \\ \sin\left(\frac{\phi}{2}\right) |\tilde{\psi}\rangle_{[1]}^{\frac{1}{2}} + \cos\left(\frac{\phi}{2}\right)e^{-i\psi} |\tilde{\psi}\rangle_{[2]}^{\frac{1}{2}} \end{pmatrix}. \quad (4.39)$$

These last states are then eigenstates of the generalized annihilation operator \mathbb{A} with eigenvalues on a 2×2 complex matrix representing the quaternions. We emphasize that equation 4.39 represent a set of four linearly independent vector coherent states associated to the quantum system described by the Hamiltonian (4.13), in the $j = \frac{1}{2}$ representation. Also we note that in this case the vector coherent states

(4.39) can be written in the normalized form

$$\begin{aligned}
|\Psi\rangle_{[2]}^{\frac{1}{2}} &= \begin{pmatrix} \cos\left(\frac{\phi}{2}\right)e^{i\psi} & -\sin\left(\frac{\phi}{2}\right) \\ \sin\left(\frac{\phi}{2}\right) & \cos\left(\frac{\phi}{2}\right)e^{-i\psi} \end{pmatrix} \begin{pmatrix} e^{(re^{i\theta}\hat{a}^\dagger - re^{-i\theta}\hat{a})} & 0 \\ 0 & e^{(re^{-i\theta}\hat{a}^\dagger - re^{i\theta}\hat{a})} \end{pmatrix} \\
&\times \begin{pmatrix} e^{\frac{1}{2}(re^{i\theta}(\mathbb{A}-\hat{a})^\dagger - re^{-i\theta}(\mathbb{A}-\hat{a}))} & 0 \\ 0 & e^{\frac{1}{2}(re^{-i\theta}(\mathbb{A}-\hat{a})^\dagger - re^{i\theta}(\mathbb{A}-\hat{a}))} \end{pmatrix} \\
&\times \sqrt{\frac{R_3 + \sqrt{4R^2 + R_3^2}}{4\sqrt{4R^2 + R_3^2}}} \begin{pmatrix} \frac{\psi_{[1]-\frac{1}{2}}^{\frac{1}{2}}(0)}{\sqrt{\|\psi_{[1]-\frac{1}{2}}^{\frac{1}{2}}(0)\|^2 + \|\psi_{[1]+\frac{1}{2}}^{\frac{1}{2}}(0)\|^2}} & \frac{\psi_{[1]+\frac{1}{2}}^{\frac{1}{2}}(0)}{\sqrt{\|\psi_{[1]-\frac{1}{2}}^{\frac{1}{2}}(0)\|^2 + \|\psi_{[1]+\frac{1}{2}}^{\frac{1}{2}}(0)\|^2}} \\ \frac{\psi_{[2]-\frac{1}{2}}^{\frac{1}{2}}(0)}{\sqrt{\|\psi_{[2]-\frac{1}{2}}^{\frac{1}{2}}(0)\|^2 + \|\psi_{[2]+\frac{1}{2}}^{\frac{1}{2}}(0)\|^2}} & \frac{\psi_{[2]+\frac{1}{2}}^{\frac{1}{2}}(0)}{\sqrt{\|\psi_{[2]-\frac{1}{2}}^{\frac{1}{2}}(0)\|^2 + \|\psi_{[2]+\frac{1}{2}}^{\frac{1}{2}}(0)\|^2}} \end{pmatrix} \\
&\times \begin{pmatrix} |\frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle - \frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |\frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \\ \frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |-\frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle + |-\frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix}. \tag{4.40}
\end{aligned}$$

Choosing now the integration constants as follows

$$\begin{pmatrix} \frac{\psi_{[1]-\frac{1}{2}}^{\frac{1}{2}}(0)}{\sqrt{\|\psi_{[1]-\frac{1}{2}}^{\frac{1}{2}}(0)\|^2 + \|\psi_{[1]+\frac{1}{2}}^{\frac{1}{2}}(0)\|^2}} & \frac{\psi_{[1]+\frac{1}{2}}^{\frac{1}{2}}(0)}{\sqrt{\|\psi_{[1]-\frac{1}{2}}^{\frac{1}{2}}(0)\|^2 + \|\psi_{[1]+\frac{1}{2}}^{\frac{1}{2}}(0)\|^2}} \\ \frac{\psi_{[2]-\frac{1}{2}}^{\frac{1}{2}}(0)}{\sqrt{\|\psi_{[2]-\frac{1}{2}}^{\frac{1}{2}}(0)\|^2 + \|\psi_{[2]+\frac{1}{2}}^{\frac{1}{2}}(0)\|^2}} & \frac{\psi_{[2]+\frac{1}{2}}^{\frac{1}{2}}(0)}{\sqrt{\|\psi_{[2]-\frac{1}{2}}^{\frac{1}{2}}(0)\|^2 + \|\psi_{[2]+\frac{1}{2}}^{\frac{1}{2}}(0)\|^2}} \end{pmatrix} = \tilde{U}^\dagger \exp\left[-\frac{1}{2}\left(\tilde{M} \frac{b^*}{2} - \tilde{M}^\dagger \frac{b}{2}\right)\sigma_3\right] \tag{4.41}$$

and using the Baker–Campbell–Hausdorff formula for splitting the displacement operators and the fact that $\tilde{U} \exp\begin{pmatrix} re^{i\theta} & 0 \\ 0 & re^{-i\theta} \end{pmatrix} \tilde{U}^\dagger = \exp \tilde{M}$, and then recomposing the resulting expression following the inverse process, we can put (4.40) in the compact form

$$|\Psi(\tilde{M})\rangle_{[2]}^{\frac{1}{2}} = e^{(\tilde{M}\mathbb{A}^\dagger - \tilde{M}^\dagger\mathbb{A})} \sqrt{\frac{R_3 + \sqrt{4R^2 + R_3^2}}{4\sqrt{4R^2 + R_3^2}}} \begin{pmatrix} |\frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle - \frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |\frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \\ \frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |-\frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle + |-\frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix}, \tag{4.42}$$

from where we can extract one version of the fundamental state of the system governed by the Hamiltonian (4.13), that is

$$|\Psi(0)\rangle_{[2]}^{\frac{1}{2}} = \sqrt{\frac{R_3 + \sqrt{4R^2 + R_3^2}}{4\sqrt{4R^2 + R_3^2}}} \begin{pmatrix} |\frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle - \frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |\frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \\ \frac{2R e^{\frac{i}{2}(\theta_+ - \theta_-)}}{R_3 + \sqrt{4R^2 + R_3^2}} |-\frac{b}{2}; +\frac{1}{2}, -\frac{1}{2}\rangle + |-\frac{b}{2}; +\frac{1}{2}, +\frac{1}{2}\rangle \end{pmatrix}. \tag{4.43}$$

To conclude this section, let us say a few words about the system we are dealing with. The fundamental state (4.43) can be used for finding the energy eigenstates of the hamiltonian (4.13). By the way it latter was conceived, we know that it is isospectral with the harmonic oscillator Hamiltonian. The normalized energy eigenstates of this system are given by

$$|\tilde{n}\rangle^{\frac{1}{2}} = \frac{(\hat{\mathbb{A}}^\dagger)^n}{\sqrt{n!}} |\Psi(0)\rangle_{[2]}^{\frac{1}{2}}. \tag{4.44}$$

The vector coherent states (4.42) based on the $h(1) \oplus su(2)$ algebra constitute an interesting generalization of the quaternionic vector coherent states studied in the literature. It depends certainly on the choice of the integration constants that remains us the highly degenerate system we are studying.

4.2 Extended canonical commutation relation and intelligent states

Let us now choose the beta parameters in such a way that the commutation relation (4.10) verify

$$[\mathbb{A}, \mathbb{A}^\dagger] = \hat{I} + 2x\hat{J}_3, \quad (4.45)$$

where $x \in \mathbb{R}$ such that $x > 0$ or $x < 0$. Here four scenarios are possible, all of them requiring $\beta_3 = 0$:

$$\begin{aligned} (i) \quad & x > 0; \quad \beta_+ = \sqrt{x} \sinh \alpha e^{i\theta_+}, \quad \beta_- = \sqrt{x} \cosh \alpha e^{i\theta_-}; \quad \alpha \neq 0 \Rightarrow b \neq 0 \\ (ii) \quad & x > 0; \quad \beta_+ = 0, \quad \beta_- = \sqrt{x} e^{i\theta_-}; \Rightarrow b = 0 \\ (iii) \quad & x < 0; \quad \beta_+ = \sqrt{-x} \cosh \alpha e^{i\theta_+}, \quad \beta_- = \sqrt{-x} \cosh \alpha e^{i\theta_-}; \quad \alpha \neq 0; \Rightarrow b \neq 0 \\ (iv) \quad & x < 0; \quad \beta_+ = \sqrt{-x} e^{i\theta_+}, \quad \beta_- = 0; \Rightarrow b = 0 \end{aligned} \quad (4.46)$$

In the cases listed as (i) and (iii) the b parameter is different from zero and hence, in the process of solving the eigenvalue equation (4.5), which is necessary to solve the matrix eigenvalue equation (4.1), we find that the matrix formed from the matrix elements of the linear combination of the generators of the $su(2)$ algebra is diagonalizable but the passing matrix V is not unitary. However, the technique to obtain the generalized vector states has no difference with the one followed in the above section except for the fact that the computation of the normalization constants is now more difficult. We will not deal with this case now, we will leave it for last, we will treat it together with all similar cases. The cases listed as (ii) and (iv) are very special because in both the parameter b is equal to zero and the aforementioned matrix diagonalization process does not apply. In appendix B we show explicitly the method to solve the corresponding $h(1) \oplus su(2)$ eigenvalue type equations appearing after of performing the diagonalization of the \tilde{M} matrix in (4.1), in the special case where $\beta_- = \beta_3 = 0$ and $\beta_+ \neq 0$, and also we adapt the results of these latter for obtaining those in the case $\beta_+ = \beta_3 = 0$ and $\beta_- \neq 0$.

Thus, in the case listed as (iv), inserting (A.55) into (A.57) and this latter into (4.8), but not without first substituting the β parameter by the corresponding eigenvalues of \tilde{M} , i.e., $\tilde{\lambda}_{[s]}, s = 1, 2, \dots, K$, we get the components of the vector state verifying (4.1):

$$|\psi\rangle_{[u]}^j = \sum_{s=1}^K P_{us} |\Psi[\tilde{\lambda}_{[s]}, \beta_+]\rangle^j = \sum_{s=1}^K \sum_{m=-j}^j P_{us} \tilde{\varphi}_{[s]m}^j(0) |\psi[\tilde{\lambda}_{[s]}, \beta_+]\rangle_m^j \quad u = 1, 2, \dots, K, \quad (4.47)$$

or better using A.58

$$|\psi\rangle_{[u]}^j = \sum_{s=1}^K \sum_{m=-j}^j P_{us} \tilde{\varphi}_{[s]m}^j(0) \hat{D}(\tilde{\lambda}_{[s]}) |\tilde{\psi}[\tilde{\lambda}_{[s]}, \beta_+]\rangle_m^j \quad u = 1, 2, \dots, K, \quad (4.48)$$

which in the matrix form look like

$$|\Psi\rangle_{[K]}^j = P \begin{pmatrix} \hat{D}(\tilde{\lambda}_{[1]}) & 0 & \dots & 0 & 0 \\ 0 & \hat{D}(\tilde{\lambda}_{[2]}) & 0 & \dots & 0 \\ \vdots & 0 & \ddots & 0 & \vdots \\ 0 & \dots & 0 & \hat{D}(\tilde{\lambda}_{[K-1]}) & 0 \\ 0 & 0 & \dots & 0 & \hat{D}(\tilde{\lambda}_{[K]}) \end{pmatrix} \begin{pmatrix} \sum_{m=-j}^j \tilde{\varphi}_{[1]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[1]}, \beta_+]\rangle_m^j \\ \sum_{m=-j}^j \tilde{\varphi}_{[2]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[2]}, \beta_+]\rangle_m^j \\ \vdots \\ \sum_{m=-j}^j \tilde{\varphi}_{[K]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[K]}, \beta_+]\rangle_m^j \end{pmatrix}. \quad (4.49)$$

When \tilde{M} is normal $P = \tilde{U}$ is unitary, then the vector states (4.49) can be written in the suggested form

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \tilde{U} \begin{pmatrix} \sum_{m=-j}^j \tilde{\varphi}_{[1]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[1]}, \beta_+]\rangle_m^j \\ \sum_{m=-j}^j \tilde{\varphi}_{[2]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[2]}, \beta_+]\rangle_m^j \\ \vdots \\ \sum_{m=-j}^j \tilde{\varphi}_{[K]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[K]}, \beta_+]\rangle_m^j \end{pmatrix}. \quad (4.50)$$

We note that we cannot do the same with the vector states (4.49) due to the fact that in this case \tilde{M} is not normal. Indeed, in such a case we can use the Baker–Campbell–Hausdorff formula to separate

the harmonic oscillator type displacement operators but we cannot reconstitute it in a closed unitary exponential form by the inverse process because \tilde{M} does not commute with \tilde{M}^\dagger .

We remark that

$$\begin{pmatrix} \sum_{m=-j}^j \tilde{\varphi}_{[1]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[1]}, \beta_+]\rangle_m^j \\ \sum_{m=-j}^j \tilde{\varphi}_{[2]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[2]}, \beta_+]\rangle_m^j \\ \vdots \\ \sum_{m=-j}^j \tilde{\varphi}_{[K]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[K]}, \beta_+]\rangle_m^j \end{pmatrix} \quad (4.51)$$

is an eigenstate of $\hat{a} + \beta_+ \hat{J}_-$ with matrix eigenvalue equals to 0. Then using the displacement operator property $\exp[-(\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a})](\hat{a} + \beta_+ \hat{J}_-)\exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] = \hat{a} + \beta_+ \hat{J}_- + \tilde{M}$, we can also show that (4.50) is effectively an eigenstate of $\hat{a} + \beta_+ \hat{J}_-$ with matrix eigenvalue equals to \tilde{M} .

The vector states in (4.50) represent a large set of different states depending on the choice of the integration constants $\tilde{\varphi}_{[s]m}^j(0)$. In general, they cannot be considered as vector coherent states associated to the Hamiltonian $\mathbb{H} = \mathbb{A}^\dagger \mathbb{A} = \hat{a}^\dagger \hat{a} + \beta_+ \hat{a}^\dagger \hat{J}_+ + \beta_+^* \hat{a} \hat{J}_- + \|\beta_+\|^2 \hat{J}_- \hat{J}_+$, but as intelligent states in the sense that they minimize the generalized Schrödinger-Robertson uncertainty relation $(\Delta \hat{\mathcal{X}})^2 (\Delta \hat{\mathcal{P}})^2 \geq \frac{1}{4} [\langle \hat{C} \rangle^2 + \langle \hat{F} \rangle^2]$, where $i\hat{C} = [\hat{\mathcal{X}}, \hat{\mathcal{P}}]$ and $\langle \hat{F} \rangle = \langle \{\hat{\mathcal{X}}, \hat{\mathcal{X}}\} \rangle - 2\langle \hat{\mathcal{X}} \rangle \langle \hat{\mathcal{P}} \rangle$, with $\hat{\mathcal{X}} = \frac{\mathbb{A} + \mathbb{A}^\dagger}{\sqrt{2}}$ and $\hat{\mathcal{P}} = \frac{\mathbb{A} - \mathbb{A}^\dagger}{\sqrt{2}i}$.

4.2.1 Heisenberg-Weyl vector coherent states on the matrix domain

A special choice of the integration constants in (4.50) is given by

$$\tilde{\varphi}_{[s]m}^j(0) = \delta_{-j,m}^{[s]} \sum_{u=1}^K \tilde{U}_{su}^\dagger, \quad s = 1, \dots, K; \quad m = -j, \dots, j, \quad (4.52)$$

where $\delta_{-j,m}^{[s]}$ is the Kronecker delta which is equal to 1 if $m = -j$ and 0 otherwise. With this choice the states (4.50) become

$$|\Psi[\tilde{M}]\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \begin{pmatrix} |0\rangle \otimes |j, -j\rangle \\ |0\rangle \otimes |j, -j\rangle \\ \vdots \\ |0\rangle \otimes |j, -j\rangle \end{pmatrix}, \quad (4.53)$$

which are standard Heisenberg- Weyl vector coherent states on the matrix domain, which have been obtained here by applying the matrix extension of the harmonic oscillator displacement operator on the simpler vector eigenstate of $\hat{a} + \beta_+ \hat{J}_-$ with zero matrix eigenvalue.

4.2.2 Vector algebra eigenstates associated to the standard $h(1) \oplus su(2)$ annihilator operator

Looking at equation (4.50) we can see that we can go even further in the change of structure of these states and express them in a more compact form, where the contribution of each sub algebra is more easily visualized. To do this, we can insert equation (A.60) into (4.50) and proceed with the inverse diagonalization process in the same way we have done in previous subsections, doing all that we get

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \exp[-(\hat{a}^\dagger I + \tilde{M}^\dagger)\beta_+ \hat{J}_-] \tilde{U} \begin{pmatrix} \sum_{m=-j}^j \frac{\tilde{\varphi}_{[1]m}^j(0)}{\sqrt{\mathcal{N}_m^j[\tilde{\lambda}_{[1]}, \beta_+]}} |0\rangle \otimes |j, m\rangle \\ \sum_{m=-j}^j \frac{\tilde{\varphi}_{[2]m}^j(0)}{\sqrt{\mathcal{N}_m^j[\tilde{\lambda}_{[2]}, \beta_+]}} |0\rangle \otimes |j, m\rangle \\ \vdots \\ \sum_{m=-j}^j \frac{\tilde{\varphi}_{[K]m}^j(0)}{\sqrt{\mathcal{N}_m^j[\tilde{\lambda}_{[K]}, \beta_+]}} |0\rangle \otimes |j, m\rangle \end{pmatrix}. \quad (4.54)$$

Choosing now the set of arbitrary parameters in the form

$$\frac{\varphi_{[s]m}^j(0)}{\sqrt{\mathcal{N}_m^j[\tilde{\lambda}_{[s]}^j, \beta_+]}} = \sum_{r=1}^K \tilde{U}_{[s][r]}^+ \delta_{m[r]m}, \quad (4.55)$$

we arrive to the special set of $(2j+1)^K$ linearly independent vector states labeled by m_1, \dots, m_K , that is.

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \exp[-(\hat{a}^\dagger I + \tilde{M}^\dagger)\beta_+\hat{J}_-] \begin{pmatrix} |0\rangle \otimes |j, m_1\rangle \\ |0\rangle \otimes |j, m_2\rangle \\ \vdots \\ |0\rangle \otimes |j, m_K\rangle \end{pmatrix}. \quad (4.56)$$

Thus, for example, if $m_1 = m_2 = \dots = m_K = -j$, we recuperate the states (4.53). On the other hand, if we take $m_1 = m_2 = \dots = m_K = j$, and use the standard disentangled formula of the exponential operator

$$\exp\left[-\frac{\tilde{\theta}}{2}(e^{-i\tilde{\phi}}\hat{J}_+ - e^{i\tilde{\phi}}\hat{J}_-)\right] = \exp\left[\tan\left(\frac{\tilde{\theta}}{2}\right)e^{i\tilde{\phi}}\hat{J}_-\right] \exp\left[-\ln\left(\sec^2\left(\frac{\tilde{\theta}}{2}\right)\right)\hat{J}_3\right] \exp\left[-\tan\left(\frac{\tilde{\theta}}{2}\right)e^{-i\tilde{\phi}}\hat{J}_+\right],$$

we get formally the symmetric form

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \exp[-I\hat{a}^\dagger\beta_+\hat{J}_-] \\ \times \exp\left[\frac{\arctan(\|\beta_+\|\tilde{M}\tilde{M}^\dagger)}{\sqrt{\|\beta_+\|\tilde{M}\tilde{M}^\dagger}}(\tilde{M}\beta_+^*\hat{J}_+ - \tilde{M}^\dagger\beta_+\hat{J}_-)\right] \begin{pmatrix} |0\rangle \otimes |j, j\rangle \\ |0\rangle \otimes |j, j\rangle \\ \vdots \\ |0\rangle \otimes |j, j\rangle \end{pmatrix}, \quad (4.57)$$

which extrapolate between the Heisenberg-Weyl vector coherent states and the vector eigenstates of the generalized annihilation operator $\hat{a} + \beta_+\hat{J}_-$.

4.3 Non-canonical commutation relation

Let us now choose the beta parameters in such a way that the commutation relation (4.10) verify

$$[\mathbb{A}, \mathbb{A}^\dagger] = \hat{I} + \rho e^{i\nu}\hat{J}_+ + \rho e^{-i\nu}\hat{J}_- \quad (4.58)$$

where $\rho \in \mathbb{R}$ such that $\rho > 0$ and $0 \leq \nu \leq 2\pi$. Here two scenarios are possible depending of the value of b , both requiring $\|\beta_+\| = \|\beta_-\| = R > 0$, and $\beta_3 \neq 0$, with $\theta_3 \neq \frac{\theta_+ + \theta_-}{2} + k\pi, k = 0, 1, \dots$, they are

$$(i) \quad \beta_+ = Re^{i\theta_+}, \quad \beta_- = Re^{i\theta_-}; \quad \beta_3 = R_3 e^{i\theta_3} \\ R_3 \neq 2R \quad \text{or} \quad \theta_3 \neq \frac{\theta_+ + \theta_-}{2} + (k + \frac{1}{2})\pi, \quad k = 0, 1, \dots, \Rightarrow b \neq 0, \\ \rho e^{i\nu} = 2iRR_3 \sin\left(\theta_3 - \frac{\theta_+ + \theta_-}{2}\right) e^{-\frac{i}{2}(\theta_+ - \theta_-)}, \quad (4.59) \\ (ii) \quad \beta_+ = Re^{i\theta_+}, \quad \beta_- = Re^{i\theta_-}; \quad \beta_3 = R_3 e^{i\theta_3} \\ R_3 = 2R \quad \text{and} \quad \theta_3 = \frac{\theta_+ + \theta_-}{2} + (k + \frac{1}{2})\pi, \quad k = 0, 1, \dots, \Rightarrow b = 0, \\ \rho e^{i\nu} = 4R^2 e^{-\frac{i}{2}(\theta_+ - \theta_-)} e^{i(k + \frac{1}{2})\pi}, \quad k = 1, 2, \dots.$$

As before, we will leave the case listed in (i), where $b \neq 0$, for the last and we will analyze here the case listed in (ii), where $b = 0$. Then, if we insert the algebra eigenstates (A.69) into (4.8), which gives us the vector components of the state that represents the solutions of the matrix eigenvalue equation (4.1), and supposing that \tilde{M} is normal, we get

$$|\psi\rangle_{[u]}^j = \mathcal{N}_{[u]}^{-\frac{1}{2}} \sum_{s=1}^K \tilde{U}_{us} \sum_{m=-j}^j \tilde{\varphi}_m^j(0) \hat{D}(\tilde{\lambda}_{[s]}) |\tilde{\psi}[\tilde{\lambda}_{[s]}, \beta_+, \beta_-, \beta_3]\rangle_m^j \quad u = 1, 2, \dots, K, \quad (4.60)$$

with the states $|\tilde{\psi}[\tilde{\lambda}_{[s]}, \beta_+, \beta_-, \beta_3]\rangle_m^j$ given by equation (A.71):

$$\begin{aligned} |\tilde{\psi}[\tilde{\lambda}_{[s]}, \beta_+, \beta_-, \beta_3]\rangle_m^j &= \frac{1}{\sqrt{\tilde{\mathcal{N}}_m^j[\tilde{\lambda}_{[s]}, \beta_+, \beta_-, \beta_3]}} \sum_{n=0}^{j+m} \sum_{\ell=0}^{j+n-m} \frac{(\vartheta \hat{J}_+)^{\ell}}{\ell!} \\ &\times (-1)^n \frac{((\hat{a}^\dagger + \tilde{\lambda}_{[s]}^*)\beta_+ \hat{J}_-)^n}{n!} |0\rangle \otimes |j, m\rangle, \quad m = -j, \dots, j, \end{aligned} \quad (4.61)$$

where in this special case $\vartheta = \frac{\beta_3}{2\beta_+} = -\frac{2\beta_-}{\beta_3} = e^{i(\theta_3 - \theta_+)} = (-1)^k i e^{-\frac{i}{2}(\theta_+ - \theta_-)}$, $k = 1, 2$. In a first step we can write equation (4.60) in matrix form, in the same way we did in the last section,

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \tilde{U} \begin{pmatrix} \sum_{m=-j}^j \tilde{\varphi}_{[1]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[1]}, \beta_+, \beta_-, \beta_3]\rangle_m^j \\ \sum_{m=-j}^j \tilde{\varphi}_{[2]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[2]}, \beta_+, \beta_-, \beta_3]\rangle_m^j \\ \vdots \\ \sum_{m=-j}^j \tilde{\varphi}_{[K]m}^j(0) |\tilde{\psi}[\tilde{\lambda}_{[K]}, \beta_+, \beta_-, \beta_3]\rangle_m^j \end{pmatrix}. \quad (4.62)$$

We could do better but the states (4.61) are not easy to disentangle and write as a product of exponential factors acting on the basis states, except for the case $m = -j$, which we will study in the next subsection. To achieve this last goal, we will try another method in the subsequent subsection.

4.3.1 Vector coherent states from non-canonical commutation relations

When $m = -j$, from (4.61) we obtain the normalized state

$$\begin{aligned} |\tilde{\psi}[\tilde{\lambda}_{[s]}, \beta_+, \beta_-, \beta_3]\rangle_{-j}^j &= \frac{\sum_{\ell=0}^{2j} \frac{(\vartheta \hat{J}_+)^{\ell}}{\ell!}}{\sqrt{\tilde{\mathcal{N}}_{-j}^j[\tilde{\lambda}_{[s]}, \beta_+, \beta_-, \beta_3]}} |0\rangle \otimes |j, -j\rangle \\ &= \frac{\exp[\vartheta \hat{J}_+]}{\sqrt{\tilde{\mathcal{N}}_{-j}^j[\tilde{\lambda}_{[s]}, \beta_+, \beta_-, \beta_3]}} |0\rangle \otimes |j, -j\rangle \\ &= \exp\left[(-1)^k \frac{i\pi}{4} \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right)\right] |0\rangle \otimes |j, -j\rangle, \quad k = 0, 1, \end{aligned} \quad (4.63)$$

which is independent on $\tilde{\lambda}_{[s]}$.

Thus choosing (4.62) the integration constants as follows:

$$\varphi_{[s]m}^j(0) = \sum_{r=1}^K \tilde{U}_{[s][r]}^\dagger \delta_{m_{[r]}m}, \quad m_{[r]} = -j, \forall r = 1, \dots, K, \quad (4.64)$$

we finally reach the vector coherent states

$$\begin{aligned} |\Psi\rangle_{[K]}^j &= \frac{1}{\sqrt{K}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \\ &\times \exp\left[\frac{i\pi}{4} (-1)^k \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right)\right] \\ &\times \begin{pmatrix} |0\rangle \otimes |j, -j\rangle \\ |0\rangle \otimes |j, -j\rangle \\ \vdots \\ |0\rangle \otimes |j, -j\rangle \end{pmatrix}, \quad k = 0, 1. \end{aligned} \quad (4.65)$$

These last states, certainly, are eigenstates of the annihilation operator

$$\mathbb{A} = a + R e^{i\theta_+} \hat{J}_- + R e^{i\theta_-} \hat{J}_+ + 2iR(-1)^k e^{\frac{i}{2}(\theta_+ + \theta_-)}, \quad k = 0, 1, \quad (4.66)$$

with matrix eigenvalue equal to \tilde{M} .

4.3.2 Disentangling through a unitary transformation

The commutator (4.58) can be written in the form

$$[\mathbb{A}, \mathbb{A}^\dagger] = \hat{I} - 2\rho\hat{\mathbb{J}}_3, \quad (4.67)$$

where

$$\hat{\mathbb{J}}_3 = \frac{-1}{2} \left[e^{i\nu} \hat{J}_+ + e^{-i\nu} \hat{J}_- \right] = (-1)^{k+1} \frac{i}{2} \left[e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right], \quad k = 0, 1. \quad (4.68)$$

On the other hand, the operator \mathbb{A} in (4.66) also can be rewritten in a different way, that is:

$$\mathbb{A} = a + \mathcal{B}_+ \hat{\mathbb{J}}_-, \quad (4.69)$$

with

$$\mathcal{B}_+ = 2Re^{\frac{i}{2}(\theta_+ + \theta_-)} \quad \text{and} \quad \hat{\mathbb{J}}_- = \frac{1}{2} \left[e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- + e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ \right] + (-1)^k i \hat{J}_3, \quad k = 0, 1. \quad (4.70)$$

Thus, by defining $\hat{\mathbb{J}}_+ = \hat{\mathbb{J}}_-^\dagger$ we observe that the set generators $\hat{\mathbb{J}}_+, \hat{\mathbb{J}}_-$ and $\hat{\mathbb{J}}_3$ verify the $su(2)$ Lie algebra commutation relations (2.2), for all $k = 0, 1$. Hence, the problem of finding the algebra eigenstates of (4.66) reduces to the same already solved in the last section, the only difference is a change of the $su(2)$ representation basis vectors at the moment of spanning the states. We will denote this new basis vectors as $|\tilde{j}, \tilde{m}\rangle$, $\tilde{m} = -\tilde{j}, \dots, \tilde{j}$. Here, it is important to mention that the Casimir operator is invariant under the transformation, then the label \tilde{j} denoting the representation coincides with the label j . Using then equation (4.56), but taking into account the new operators and basis states, the solution of the eigenvalue equation (4.1), in this particular case, is given by

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M} \hat{a}^\dagger - \tilde{M}^\dagger \hat{a}] \exp[-(\hat{a}^\dagger I + \tilde{M}^\dagger) \mathcal{B}_+ \hat{\mathbb{J}}_-] \begin{pmatrix} |0\rangle \otimes |\tilde{j}, \tilde{m}_1\rangle \\ |0\rangle \otimes |\tilde{j}, \tilde{m}_2\rangle \\ \vdots \\ |0\rangle \otimes |\tilde{j}, \tilde{m}_K\rangle \end{pmatrix}, \quad (4.71)$$

where $|\tilde{j}, \tilde{m}_r\rangle$, $r = 1, \dots, k$ are eigenstates of $\hat{\mathbb{J}}_3$ associated to the eigenvalue \tilde{m}_r , respectively.

To know the connection of these last states with the regular states $|j, m\rangle$, we need to solve the following $su(2)$ algebra eigenstate equation for $\hat{\mathbb{J}}_3$ given in (4.68):

$$[\alpha_- \hat{J}_+ + \alpha_+ \hat{J}_-] |\tilde{j}, \tilde{m}\rangle = \tilde{m} |\tilde{j}, \tilde{m}\rangle, \quad (4.72)$$

where $\alpha_- = -\frac{1}{2} e^{-\frac{i}{2}(\theta_+ - \theta_-)} e^{i(k+\frac{1}{2})\pi}$, $k = 0, 1$, $\alpha_+ = -\frac{1}{2} e^{\frac{i}{2}(\theta_+ - \theta_-)} e^{-i(k+\frac{1}{2})\pi}$, $k = 0, 1$, and $\alpha_3 = 0$. Then using the results of appendix B, in particular, equations (B2) and (B3), we find the parameter $b = \sqrt{4\alpha_+ \alpha_- + \alpha_3^2} = 1$, which implies $\tilde{m} = mb = m$,

$$\frac{\tilde{\theta}}{2} = \arctan\left(\sqrt{\frac{b - \alpha_3}{b + \alpha_3}}\right) = \arctan(1) = \frac{\pi}{4}, \quad \text{and} \quad e^{i\tilde{\phi}} = \sqrt{\frac{\alpha_+}{\alpha_-}} = e^{\frac{i}{2}(\theta_+ - \theta_-)} e^{-i(k+\frac{1}{2})\pi}, \quad k = 0, 1, \quad (4.73)$$

from where we extract the unitary operator

$$T = \exp\left[\frac{i\pi}{4} (-1)^k \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right)\right], \quad k = 0, 1. \quad (4.74)$$

Thus, following the reasoning of appendix B, we finally conclude that the transformed states $|\tilde{j}, \tilde{m}\rangle = T |j, m\rangle$, $m = -j, \dots, j$, are eigenstates of $\hat{\mathbb{J}}_3$, corresponding to the eigenvalue $\tilde{m} = m$.

At this point, before concluding the section, let us return briefly to the case $m = -j$. As $\hat{\mathbb{J}}_- |\tilde{j}, -j\rangle = 0$, then when in (4.71) we choose $\tilde{m}_r = -\tilde{j} = -j, \forall r = 1, \dots, K$ and we use the results we have just obtained, we regain the vector coherent states (4.65).

Continuing now with the line of argument, using the recently obtained results, we can return to the original $su(2)$ representation basis states and write (4.71) in the disentangled form

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \exp[-(\hat{a}^\dagger I + \tilde{M}^\dagger)\mathcal{B}_+\hat{\mathbb{J}}_-] \\
&\exp\left[\frac{i\pi}{4}\left(e^{\frac{-i}{2}(\theta_+-\theta_-)}\hat{f}_+ + e^{\frac{i}{2}(\theta_+-\theta_-)}\hat{f}_-\right)I\right] \begin{bmatrix} |0\rangle\otimes|\tilde{j},m_1\rangle \\ |0\rangle\otimes|\tilde{j},m_2\rangle \\ \vdots \\ |0\rangle\otimes|\tilde{j},m_K\rangle \end{bmatrix}. \tag{4.75}
\end{aligned}$$

4.3.3 Disentangled form of the vector states

On the other hand, when we choose $\tilde{m}_r = \tilde{j} = j, \forall r = 1, \dots, K$ the vector states in (4.71) can be written in the form

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \\
&\times \exp[-I\hat{a}^\dagger\mathcal{B}_+\hat{\mathbb{J}}_-] \exp\left[\frac{\arctan(\|\mathcal{B}_+\|\sqrt{\tilde{M}\tilde{M}^\dagger})}{\|\mathcal{B}_+\|\sqrt{\tilde{M}\tilde{M}^\dagger}}(\tilde{M}\mathcal{B}_+^*\hat{\mathbb{J}}_+ - \tilde{M}^\dagger\mathcal{B}_+\hat{\mathbb{J}}_-)\right] \\
&\times \exp\left[\frac{i\pi}{4}(-1)^k\left(e^{\frac{-i}{2}(\theta_+-\theta_-)}\hat{f}_+ + e^{\frac{i}{2}(\theta_+-\theta_-)}\hat{f}_-\right)\right] \begin{bmatrix} |0\rangle\otimes|j,j\rangle \\ |0\rangle\otimes|j,j\rangle \\ \vdots \\ |0\rangle\otimes|j,j\rangle \end{bmatrix}, \quad k = 0, 1, \tag{4.76}
\end{aligned}$$

which extrapolates between the vector coherent states over the matrix domain associated to the quantum harmonic oscillator and the intelligent vector states associated to the generalized annihilation operator $\hat{a} + \mathcal{B}_+\hat{\mathbb{J}}_-$, whose matrix eigenvalues are given by \tilde{M} .

4.4 More general sets of vector algebra eigenstates

When we are interested in physics systems which Hamiltonian is formed from the suitable product of the generalized annihilation operator (4.9) and its adjoint, both verifying the commutation relation (4.10), and we want that all coefficients of the left side of this last expression be different from 0, again we need to distinguish between several possibilities, all of them requiring $\beta_3 \neq 0$. Indeed, in this case we need $\|\beta_-\|^2 - \|\beta_+\|^2 \neq 0$, and $\beta_3\beta_+^* - \beta_3^*\beta_- \neq 0$. Thus, we have

$$\begin{aligned}
(i) \quad & \beta_+ \neq 0, \quad \beta_- = 0, \quad \beta_3 \neq 0, \quad \Rightarrow b \neq 0 \\
(ii) \quad & \beta_+ = 0, \quad \beta_- \neq 0, \quad \beta_3 \neq 0, \quad \Rightarrow b \neq 0 \\
(iii) \quad & \beta_+ = R_+e^{i\theta_+} \neq 0, \quad \beta_- = R_-e^{i\theta_-} \neq 0, \quad \beta_3 = R_3e^{i\theta_3} \neq 0, \quad R_+ \neq R_- \\
& \text{and } R_3 \neq 2\sqrt{R_+R_-} \quad \text{or } \theta_3 \neq \frac{\theta_+ + \theta_-}{2} + \left(k + \frac{1}{2}\right)\pi, \quad k = 0, 1, \quad \Rightarrow b \neq 0 \quad . \tag{4.77} \\
(iv) \quad & \beta_+ = R_+e^{i\theta_+} \neq 0, \quad \beta_- = R_-e^{i\theta_-} \neq 0, \quad \beta_3 = R_3e^{i\theta_3} \neq 0, \quad R_+ \neq R_- \\
& R_3 = 2\sqrt{R_+R_-} \quad \text{and } \theta_3 = \frac{\theta_+ + \theta_-}{2} + \left(k + \frac{1}{2}\right)\pi, \quad k = 0, 1, \quad \Rightarrow b = 0 \\
& \rho e^{i\nu} = R_3(R_+ + R_-)e^{-\frac{i}{2}(\theta_+-\theta_-)} e^{i(k+\frac{1}{2})\pi}, \quad k = 0, 1.
\end{aligned}$$

The cases listed in (i,ii,iii), where parameter $b \neq 0$, will be treated in the next subsection together with their similar ones mentioned above. The case listed in (iv), where $b = 0$, will be solved here using the technique of the $su(2)$ operator algebra transformations used in the last subsection.

As we have done in the in section 4.3.2, the commutator (4.58) can be written in the form

$$[\mathbb{A}, \mathbb{A}^\dagger] = \hat{I} - 2\rho \frac{R_+ + R_-}{R_3} \hat{\mathbb{J}}_3, \tag{4.78}$$

where now

$$\begin{aligned}\hat{\mathbb{J}}_3 &= R_3 \frac{(R_+ - R_-)}{\rho} \hat{J}_3 - \frac{R_3}{2(R_+ + R_-)} \left[e^{i\nu} \hat{J}_+ + e^{-i\nu} \hat{J}_- \right] \\ &= \frac{(R_+ - R_-)}{(R_+ + R_-)} \hat{J}_3 - \frac{\sqrt{R_+ R_-}}{(R_+ + R_-)} \left[e^{-\frac{i}{2}(\theta_+ - \theta_-)} e^{i(k+\frac{1}{2})\pi} \hat{J}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)} e^{-i(k+\frac{1}{2})\pi} \hat{J}_- \right], \quad k = 0, 1.\end{aligned}\quad (4.79)$$

On the other hand, the operator \mathbb{A} in (4.66) again can be written in the form:

$$\mathbb{A} = a + \mathcal{B}_+ \hat{\mathbb{J}}_-, \quad (4.80)$$

where now

$$\mathcal{B}_+ = (R_+ + R_-) e^{\frac{i}{2}(\theta_+ + \theta_-)} \quad (4.81)$$

and

$$\hat{\mathbb{J}}_- = \frac{1}{(R_+ + R_-)} \left[R_+ e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- + R_- e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ + 2\sqrt{R_+ R_-} e^{i(k+\frac{1}{2})\pi} \hat{J}_3 \right], \quad k = 0, 1. \quad (4.82)$$

Thus, as before, by defining $\hat{\mathbb{J}}_+ = \hat{\mathbb{J}}_-^\dagger$, we realize that the transformed operators verify the $su(2)$ algebra. Then the problem of computing the algebra eigenstates reduces to that of the previous sections.

Using again equation (4.56), but taking into account the new operators and basis states, the solution of the eigenvalue equation (4.1), in this particular case, is given by

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M} \hat{a}^\dagger - \tilde{M}^\dagger \hat{a}] \exp[-(\hat{a}^\dagger I + \tilde{M}^\dagger) \mathcal{B}_+ \hat{\mathbb{J}}_-] \begin{pmatrix} |0\rangle \otimes |\tilde{j}, \tilde{m}_1\rangle \\ |0\rangle \otimes |\tilde{j}, \tilde{m}_2\rangle \\ \vdots \\ |0\rangle \otimes |\tilde{j}, \tilde{m}_K\rangle \end{pmatrix}, \quad (4.83)$$

where $|\tilde{j}, \tilde{m}_r\rangle$, $r = 1, \dots, k$ are eigenstates of $\hat{\mathbb{J}}_3$ associated to the eigenvalue \tilde{m}_r , respectively.

To know the connection of these last states with the original states $|j, m\rangle$, we have to solve the following $su(2)$ algebra eigenstate equation for $\hat{\mathbb{J}}_3$ given in (4.79):

$$[\alpha_- \hat{J}_+ + \alpha_+ \hat{J}_- + \alpha_3 \hat{J}_3] |\tilde{j}, \tilde{m}\rangle = \tilde{m} |\tilde{j}, \tilde{m}\rangle, \quad (4.84)$$

where

$$\alpha_- = -\frac{\sqrt{R_+ R_-}}{(R_+ + R_-)} e^{-\frac{i}{2}(\theta_+ - \theta_-)} e^{i(k+\frac{1}{2})\pi}, \quad \alpha_+ = -\frac{\sqrt{R_+ R_-}}{(R_+ + R_-)} e^{\frac{i}{2}(\theta_+ - \theta_-)} e^{-i(k+\frac{1}{2})\pi}, \quad k = 0, 1, \quad (4.85)$$

and

$$\alpha_3 = \frac{R_+ - R_-}{R_+ + R_-}, \quad k = 0, 1. \quad (4.86)$$

Then using the results of appendix B, in particular, equations (B2) and (B3), we find

$$b = \sqrt{4\alpha_+ \alpha_- + \alpha_3^2} = 1, \quad \text{which implies } \tilde{m} = m, \quad (4.87)$$

$$\frac{\tilde{\theta}}{2} = \arctan\left(\sqrt{\frac{b - \alpha_3}{b + \alpha_3}}\right) = \arctan\left(\sqrt{\frac{R_-}{R_+}}\right) \quad \text{and} \quad e^{i\tilde{\phi}} = \sqrt{\frac{\alpha_+}{\alpha_-}} = e^{\frac{i}{2}(\theta_+ - \theta_-)} e^{-i(k+\frac{1}{2})\pi}, \quad k = 0, 1, \quad (4.88)$$

from where we extract the unitary operator

$$T = \exp\left[i \arctan\left(\sqrt{\frac{R_-}{R_+}}\right) (-1)^k \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right)\right], \quad k = 0, 1. \quad (4.89)$$

Thus, following the reasoning of appendix B, we finally conclude that the transformed states $|\tilde{j}, \tilde{m}\rangle = T |j, m\rangle$, $m = -j, \dots, j$, are eigenstates of $\hat{\mathbb{J}}_3$, corresponding to the eigenvalue $\tilde{m} = m$.

Finally, inserting these last states into (4.83) and using (4.89) for T , we arrive to the generalized vector states

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \exp[-(\hat{a}^\dagger I + \tilde{M}^\dagger)\mathcal{B}_+\hat{\mathbb{J}}_-] \\
&\times \exp\left[i \arctan\left(\sqrt{\frac{R_-}{R_+}}\right) (-1)^k \left(e^{\frac{-i}{2}(\theta_+ - \theta_-)}\hat{f}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)}\hat{f}_-\right) I\right] \begin{pmatrix} |0\rangle \otimes |j, m_1\rangle \\ |0\rangle \otimes |j, m_2\rangle \\ \vdots \\ |0\rangle \otimes |j, m_K\rangle \end{pmatrix}, \quad k = 0, 1, \quad (4.90)
\end{aligned}$$

which constitute a set of $(2j+1)^K$ of linearly independent vector states.

4.4.1 Generalized disentangled form of new vector coherent states

If we choose $\tilde{m}_r = -\tilde{j} = -j, \forall r = 1, \dots, K$ the vector states in (4.83) can be written in the form

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \frac{1}{\sqrt{K}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \\
&\times \exp\left[i \arctan\left(\sqrt{\frac{R_-}{R_+}}\right) (-1)^k \left(e^{\frac{-i}{2}(\theta_+ - \theta_-)}\hat{f}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)}\hat{f}_-\right) I\right] \begin{pmatrix} |0\rangle \otimes |j, -j\rangle \\ |0\rangle \otimes |j, -j\rangle \\ \vdots \\ |0\rangle \otimes |j, -j\rangle \end{pmatrix}, \quad k = 0, 1, \quad (4.91)
\end{aligned}$$

that generalize (4.65), and represent the product of the canonical harmonic oscillator coherent states and the Perelomov type $su(2)$ coherent states, in the matrix domain.

4.4.2 Generalized disentangled form of the vector states II

On the other hand, if we choose $\tilde{m}_r = \tilde{j} = j, \forall r = 1, \dots, K$ the vector states in (4.83) can be written in the form

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \exp[\tilde{M}\hat{a}^\dagger - \tilde{M}^\dagger\hat{a}] \\
&\times \exp[-I\hat{a}^\dagger\mathcal{B}_+\hat{\mathbb{J}}_-] \exp\left[\frac{\arctan(\|\mathcal{B}_+\|\sqrt{\tilde{M}\tilde{M}^\dagger})}{\|\mathcal{B}_+\|\sqrt{\tilde{M}\tilde{M}^\dagger}} (\tilde{M}\mathcal{B}_+\hat{\mathbb{J}}_- - \tilde{M}^\dagger\mathcal{B}_+\hat{\mathbb{J}}_-)\right] \\
&\times \exp\left[i \arctan\left(\sqrt{\frac{R_-}{R_+}}\right) (-1)^k \left(e^{\frac{-i}{2}(\theta_+ - \theta_-)}\hat{f}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)}\hat{f}_-\right) I\right] \begin{pmatrix} |0\rangle \otimes |j, j\rangle \\ |0\rangle \otimes |j, j\rangle \\ \vdots \\ |0\rangle \otimes |j, j\rangle \end{pmatrix}, \quad k = 0, 1, \quad (4.92)
\end{aligned}$$

which extrapolates between the vector coherent states over the matrix domain associated to the harmonic oscillator annihilation operator \hat{a} , and the algebra eigenstates of the generalized operator $\hat{a} + \mathcal{B}_+\hat{\mathbb{J}}_-$, which associated eigenvalues are given by \tilde{M} .

4.5 The cases with $b \neq 0$

In this section we are going to compute the vector algebra eigenstates for the set of generators from the $su(2)$ sector whose parameter b is different from zero, except for the generators that give rise to the canonical case whose vector coherent states have already been calculated in section 4.1.1. In all the remaining non-canonical cases, the operator \hat{T} that act on the basis states spanning the complete space of the j irreducible representation of the $su(2)$ algebra is not unitary. In any case, this fact does not greatly affect the procedure for obtaining the desired states. Actually, the process of obtaining such states is identical to the one used in the canonical case. Furthermore, despite the non-unitary character of the T operators, there are some situations that depend on the choice of integration constants in which the states can be written in the form of a unitary operator acting on the ground state, in other words, it

is still possible to construct some vector coherent states. On the other hand, the non-unitary attribute of \hat{T} provides us with an adequate metric that can be used to construct some linear and quadratics $su(2)$ pseudo-Hermitian Hamiltonians [19] in the context of this article.

According to the results of appendices A and B, the solutions of the eigenvalue equation

$$[\hat{a} + \beta \cdot \vec{\hat{f}}] |\tilde{\psi}\rangle_{[s]}^j = \tilde{\lambda}_{[s]} |\tilde{\psi}\rangle_{[s]}^j \quad (4.93)$$

are given by

$$|\tilde{\psi}\rangle_{[s]}^j = |\tilde{\lambda}_{[s]} - mb\rangle \otimes \hat{T} |j, m\rangle, \quad m = -j, \dots, j. \quad (4.94)$$

Using the fact that $\hat{D}(\tilde{\lambda}_{[s]} - mb) = \hat{D}(\tilde{\lambda}_{[s]}) \hat{D}(-mb) \exp\left[\frac{1}{2}(\tilde{\lambda}_{[s]} b^* - \tilde{\lambda}_{[s]}^* b)m\right]$, we can see that this last equation can be written in the form

$$|\tilde{\psi}\rangle_{[s]}^j = \hat{D}(\tilde{\lambda}_{[s]}) \hat{T} \exp\left[\frac{1}{2}(\tilde{\lambda}_{[s]} b^* - \tilde{\lambda}_{[s]}^* b)\hat{f}_3\right] | -mb\rangle \otimes |j, m\rangle, \quad m = -j, \dots, j. \quad (4.95)$$

Thus, the general solution of the eigenvalue equation (4.93) is

$$|\tilde{\Psi}\rangle_{[s]}^j = \hat{D}(\tilde{\lambda}_{[s]}) \hat{T} \exp\left[\frac{1}{2}(\tilde{\lambda}_{[s]} b^* - \tilde{\lambda}_{[s]}^* b)\hat{f}_3\right] \sum_{m=-j}^j \tilde{\varphi}_{[s]m}^j(0) | -mb\rangle \otimes |j, m\rangle \quad (4.96)$$

and by consequent the $(2j+1)^K$ solutions of equation (4.1), depending on the $\tilde{\varphi}_{[s]m}^j$ parameter values are given by

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \hat{T} \exp\left[\frac{1}{2}(\tilde{M}b^* - \tilde{M}^\dagger b)\hat{f}_3\right] \tilde{U} \begin{pmatrix} \sum_{m=-j}^j \tilde{\varphi}_{[1]m}^j(0) | -mb\rangle \otimes |j, m\rangle \\ \sum_{m=-j}^j \tilde{\varphi}_{[2]m}^j(0) | -mb\rangle \otimes |j, m\rangle \\ \vdots \\ \sum_{m=-j}^j \tilde{\varphi}_{[K-1]m}^j(0) | -mb\rangle \otimes |j, m\rangle \\ \sum_{m=-j}^j \tilde{\varphi}_{[K]m}^j(0) | -mb\rangle \otimes |j, m\rangle \end{pmatrix}. \quad (4.97)$$

By choosing the integration constant in the form

$$\tilde{\varphi}_{[s]m}^j = \sum_{r=1}^K \tilde{U}_{[s][r]}^\dagger \delta_{m_{[r]}m} \quad (4.98)$$

we get the elementary set of solutions

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \hat{T} \exp\left[\frac{1}{2}(\tilde{M}b^* - \tilde{M}^\dagger b)\hat{f}_3\right] \begin{pmatrix} | -m_1 b\rangle \otimes |j, m_1\rangle \\ | -m_2 b\rangle \otimes |j, m_2\rangle \\ \vdots \\ | -m_{K-1} b\rangle \otimes |j, m_{K-1}\rangle \\ | -m_K b\rangle \otimes |j, m_K\rangle \end{pmatrix}. \quad (4.99)$$

4.5.1 The case $[\hat{\mathbb{A}}, \hat{\mathbb{A}}^\dagger] = \hat{I} + 2x \hat{f}_3$

- When $x > 0$ and with the choice of parameters $\beta_+ = \sqrt{x} \sinh \alpha e^{i\theta_+}$, $\beta_- = \sqrt{x} \cosh \alpha e^{i\theta_-}$ and $\beta_3 = 0$, we have $b = e^{\frac{i}{2}(\theta_+ - \theta_-)} \sqrt{2x \cosh(2\alpha)}$. Thus, from equations (B2) and (B3) we deduce

$$\hat{T} = \exp\left[-\frac{\pi}{4} \left(\sqrt{\coth(\alpha)} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - \sqrt{\tanh(\alpha)} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right)\right]. \quad (4.100)$$

Inserting this last result into equation (4.99), we obtain the vector algebra eigenstates of the element $\hat{\mathbb{A}} = a + \sqrt{x} \sinh \alpha e^{i\theta_+} \hat{f}_- + \sqrt{x} \cosh \alpha e^{i\theta_-} \hat{f}_+$, that is,

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp \left[-\frac{\pi}{4} \left(\sqrt{\coth(\alpha)} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ - \sqrt{\tanh(\alpha)} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right) \right] \\
&\times \exp \left[\frac{1}{2} (\tilde{M} b^* - \tilde{M}^\dagger b) \hat{J}_3 \right] \begin{pmatrix} | -m_1 b \rangle \otimes | j, m_1 \rangle \\ | -m_2 b \rangle \otimes | j, m_2 \rangle \\ \vdots \\ | -m_{K-1} b \rangle \otimes | j, m_{K-1} \rangle \\ | -m_K b \rangle \otimes | j, m_K \rangle \end{pmatrix}. \quad (4.101)
\end{aligned}$$

From this set of vector states we can extract two classes of vector coherent states. Indeed, if we choose $m_1 = m_2 = \dots = m_K = -j$, and suitably express the exponential operator \hat{T} as a product of three exponential operators depending of \hat{J}_+ , \hat{J}_3 and \hat{J}_- , respectively and then perform the action of the ensemble of the exponential operators on the state $|j, -j\rangle$, we obtain the equivalent exponential operator action on this last state: $\exp \left[-\sqrt{\coth(\alpha)} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ \right] |j, -j\rangle$. Finally, by replacing this last non-unitary exponential operator by its unitary equivalent, we obtain the normalized vector coherent states

$$|\Psi\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \exp \left[-\arctan(\sqrt{\coth(\alpha)}) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right) \right] \begin{pmatrix} | j b \rangle \otimes | j, -j \rangle \\ | j b \rangle \otimes | j, -j \rangle \\ \vdots \\ | j b \rangle \otimes | j, -j \rangle \\ | j b \rangle \otimes | j, -j \rangle \end{pmatrix}. \quad (4.102)$$

In the same way, if we choose $m_1 = m_2 = \dots = m_K = j$, and perform the same process that we just described, we get a second set of vector coherent states, that is,

$$|\Psi\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \exp \left[-\arctan(\sqrt{\tanh(\alpha)}) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right) \right] \begin{pmatrix} | -j b \rangle \otimes | j, j \rangle \\ | -j b \rangle \otimes | j, j \rangle \\ \vdots \\ | -j b \rangle \otimes | j, j \rangle \\ | -j b \rangle \otimes | j, j \rangle \end{pmatrix}. \quad (4.103)$$

- When $x < 0$ and with the choice of parameters $\beta_+ = \sqrt{-x} \cosh \alpha e^{i\theta_+}$, $\beta_- = \sqrt{-x} \sinh \alpha e^{i\theta_-}$ and $\beta_3 = 0$, we have $b = e^{\frac{i}{2}(\theta_+ - \theta_-)} \sqrt{2|x| \cosh(2\alpha)}$. The expressions for the corresponding algebra eigenstates in this case can be extracted from the expressions of the previous one by interchanging $\sinh \alpha$ by $\cosh(\alpha)$ and vice-versa. Doing that, we get

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp \left[-\frac{\pi}{4} \left(\sqrt{\tanh(\alpha)} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ - \sqrt{\coth(\alpha)} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right) \right] \\
&\times \exp \left[\frac{1}{2} (\tilde{M} b^* - \tilde{M}^\dagger b) \hat{J}_3 \right] \begin{pmatrix} | -m_1 b \rangle \otimes | j, m_1 \rangle \\ | -m_2 b \rangle \otimes | j, m_2 \rangle \\ \vdots \\ | -m_{K-1} b \rangle \otimes | j, m_{K-1} \rangle \\ | -m_K b \rangle \otimes | j, m_K \rangle \end{pmatrix}. \quad (4.104)
\end{aligned}$$

From this last expression, as before, we can also extract two classes of vector coherent states. Indeed, if we choose $m_1 = m_2 = \dots = m_K = -j$, following the same procedure as above, we get

$$|\Psi\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \exp \left[-\arctan(\sqrt{\tanh(\alpha)}) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{J}_- \right) \right] \begin{pmatrix} | j b \rangle \otimes | j, -j \rangle \\ | j b \rangle \otimes | j, -j \rangle \\ \vdots \\ | j b \rangle \otimes | j, -j \rangle \\ | j b \rangle \otimes | j, -j \rangle \end{pmatrix}. \quad (4.105)$$

On the other hand, if we choose $m_1 = m_2 = \dots = m_K = j$, we get

$$|\Psi\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \exp \left[-\arctan(\sqrt{\coth(\alpha)}) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right) \right] \begin{pmatrix} | -jb \rangle \otimes | j, j \rangle \\ | -jb \rangle \otimes | j, j \rangle \\ \vdots \\ | -jb \rangle \otimes | j, j \rangle \\ | -jb \rangle \otimes | j, j \rangle \end{pmatrix}. \quad (4.106)$$

4.5.2 The case $[\hat{A}, \hat{A}^\dagger] = \hat{I} + \rho e^{i\nu} \hat{f}_+ + \rho e^{-i\nu} \hat{f}_-$

In case that $\beta_+ = R e^{i\theta_+}$, $\beta_- = R e^{i\theta_-}$ and $\beta_3 = R_3 e^{i\theta_3}$, with $\theta_3 \neq \frac{1}{2}(\theta_+ + \theta_-) + k\pi$, $k = 1, 2, \dots$ and $R_3 \neq 2R$ or $\theta_3 \neq \frac{1}{2}(\theta_+ + \theta_-) + (k + \frac{1}{2})\pi$, then $b = 2R e^{\frac{i}{2}(\theta_+ + \theta_-)} \sqrt{1 + \left[\frac{R_3}{2R} e^{i(\theta_3 - \frac{1}{2}(\theta_+ + \theta_-))} \right]^2} \neq 0$. Thus, from equation (B3) we can compute the parameters $\tilde{\theta}$ and $\tilde{\phi}$, serving to construct the operator \hat{T} , we get

$$\tan\left(\frac{\tilde{\theta}}{2}\right) = \sqrt{\frac{b - \beta_3}{b + \beta_3}} = \sqrt{1 + \gamma^2} - \gamma, \quad e^{i\tilde{\phi}} = e^{\frac{i}{2}(\theta_+ - \theta_-)}, \quad (4.107)$$

where $\gamma = \frac{R_3}{2R} e^{i(\theta_3 - \frac{1}{2}(\theta_+ + \theta_-))}$. From these last relations we can see that $\tilde{\phi}$ is a real parameters whereas $\tilde{\theta}$ is, in general, a complex one. Indeed, if we write $\gamma = \rho e^{i\varphi}$, where $\rho = \frac{R_3}{2R}$ and $\varphi = \theta_3 - \frac{1}{2}(\theta_+ + \theta_-) \neq k\pi$, $k = 1, 2, \dots$, and insert it into (4.107), after some manipulations we obtain

$$\begin{aligned} \tan\left(\frac{\tilde{\theta}}{2}\right) &= \left[\sqrt{\frac{\sqrt{1 + \rho^4 + 2\rho^2 \cos(2\varphi)} + (1 + \rho^2 \cos(2\varphi))}{2}} - \rho \cos(\varphi) \right] \\ &+ i \left[\sqrt{\frac{\sqrt{1 + \rho^4 + 2\rho^2 \cos(2\varphi)} - (1 + \rho^2 \cos(2\varphi))}{2}} - \rho \sin(\varphi) \right]. \end{aligned} \quad (4.108)$$

We note that if we write $\tan\left(\frac{\tilde{\theta}}{2}\right) = \mathcal{Z} = \mathcal{Z}_R + i\mathcal{Z}_{Im}$, where \mathcal{Z}_{Re} and \mathcal{Z}_{Im} are the real and imaginary parts of the complex number \mathcal{Z} , respectively, then formally we have

$$\frac{\tilde{\theta}}{2} = \frac{i}{2} \ln \left[\frac{1 - i\mathcal{Z}}{1 + i\mathcal{Z}} \right] = -\frac{\delta}{2} + \frac{i}{2} \ln \left[\frac{\sqrt{(1 - \|\mathcal{Z}\|^2)^2 + 4\mathcal{Z}_{Re}^2}}{1 - 2\mathcal{Z}_{Im} + \|\mathcal{Z}\|^2} \right], \quad (4.109)$$

where $\delta = \arctan \left[\frac{2\mathcal{Z}_{Re}}{\|\mathcal{Z}\|^2 - 1} \right]$ when $\|\mathcal{Z}\| \neq 1$ and $\delta = -\frac{\pi}{2}$ if $\|\mathcal{Z}\| = 1$ and $\mathcal{Z}_{Re} > 0$ and $\delta = \frac{\pi}{2}$ if $\|\mathcal{Z}\| = 1$ and $\mathcal{Z}_{Re} < 0$, where \mathcal{Z}_R and \mathcal{Z}_{Im} represent the real and imaginary parts of the right side of equation (4.108), respectively. Thus, we can show that the general structure of the operator \hat{T} in this case is given by the product of two exponential operators, one of them unitary and the other one Hermitian:

$$\begin{aligned} \hat{T} &= \exp \left[\frac{\delta}{2} \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right) \right] \\ &\times \exp \left[-\frac{i}{2} \ln \left(\frac{\sqrt{(1 - \|\mathcal{Z}\|^2)^2 + 4\mathcal{Z}_{Re}^2}}{1 - 2\mathcal{Z}_{Im} + \|\mathcal{Z}\|^2} \right) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right) \right]. \end{aligned} \quad (4.110)$$

By inserting this operator into the general expression (4.97) or into (4.99) we finally obtain the vector algebra eigenstates of the operator $\hat{A} = \hat{a} + R e^{i\theta_+} \hat{f}_+ + R e^{i\theta_-} \hat{f}_- + R_3 e^{i\theta_3} \hat{f}_3$, which parameter satisfy the condition given in this subsection:

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp \left[\frac{\delta}{2} \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right) \right] \\
&\times \exp \left[-\frac{i}{2} \ln \left(\frac{\sqrt{(1 - \|\mathcal{Z}\|^2)^2 + 4\mathcal{Z}_{Re}^2}}{1 - 2\mathcal{Z}_{Im} + \|\mathcal{Z}\|^2} \right) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right) \right] \\
&\times \exp \left[\frac{1}{2} (\tilde{M}b^* - \tilde{M}^\dagger b) \hat{f}_3 \right] \begin{pmatrix} | -m_1 b \rangle \otimes | j, m_1 \rangle \\ | -m_2 b \rangle \otimes | j, m_2 \rangle \\ \vdots \\ | -m_{K-1} b \rangle \otimes | j, m_{K-1} \rangle \\ | -m_K b \rangle \otimes | j, m_K \rangle \end{pmatrix}. \tag{4.111}
\end{aligned}$$

If in (4.111) we choose $m_1 = m_2 = \dots = m_K = -j$, and proceed as in the previous sections, we get the set of normalized vector coherent states:

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \tag{4.112} \\
&\times \exp \left[-\arctan(\|\mathcal{Z}\|) \left(e^{-i\left(\frac{\theta_+ - \theta_-}{2} - \arctan\left(\frac{\mathcal{Z}_{Im}}{\mathcal{Z}_{Re}}\right)\right)} \hat{f}_+ - e^{i\left(\frac{\theta_+ - \theta_-}{2} - \arctan\left(\frac{\mathcal{Z}_{Im}}{\mathcal{Z}_{Re}}\right)\right)} \hat{f}_- \right) \right] \\
&\times \begin{pmatrix} | j b \rangle \otimes | j, -j \rangle \\ | j b \rangle \otimes | j, -j \rangle \\ \vdots \\ | j b \rangle \otimes | j, -j \rangle \\ | j b \rangle \otimes | j, -j \rangle \end{pmatrix}, \tag{4.113}
\end{aligned}$$

where $\arctan\left(\frac{\mathcal{Z}_{Im}}{\mathcal{Z}_{Re}}\right)$ is replaced by $\frac{\pi}{2}$ when $\mathcal{Z}_{Re} = 0$.

On the other hand, if we choose $m_1 = m_2 = \dots = m_K = j$, and again we proceed as in the previous sections, we get a second set of normalized vector coherent states:

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \tag{4.114} \\
&\times \exp \left[-\arctan(\|\mathcal{Z}\|) \left(e^{-i\left(\frac{\theta_+ - \theta_-}{2} + \arctan\left(\frac{\mathcal{Z}_{Im}}{\mathcal{Z}_{Re}}\right)\right)} \hat{f}_+ - e^{i\left(\frac{\theta_+ - \theta_-}{2} + \arctan\left(\frac{\mathcal{Z}_{Im}}{\mathcal{Z}_{Re}}\right)\right)} \hat{f}_- \right) \right] \\
&\times \begin{pmatrix} | -j b \rangle \otimes | j, j \rangle \\ | -j b \rangle \otimes | j, j \rangle \\ \vdots \\ | -j b \rangle \otimes | j, j \rangle \\ | -j b \rangle \otimes | j, j \rangle \end{pmatrix}. \tag{4.115}
\end{aligned}$$

Some special cases For example, in the special case where $\varphi = \frac{\pi}{2}$ and $\rho > 1$, we have $\mathcal{Z} = i(\sqrt{\rho^2 - 1} - \rho)$, that implies $\delta = 0$, and by consequent $\frac{\hat{\theta}}{2} = -\frac{i}{2} \ln\left(\sqrt{\frac{\rho+1}{\rho-1}}\right) = -\frac{i}{2} \ln\left(\sqrt{\frac{R_3+2R}{R_3-2R}}\right)$ and $b = i e^{\frac{i}{2}(\theta_+ + \theta_-)} \sqrt{R_3^2 - 4R^2}$. Thus, the vector eigenstates of $\mathbb{A} = \hat{a} + Re^{i\theta_+} \hat{f}_- + Re^{i\theta_-} \hat{f}_+ + iR_3 e^{\frac{i}{2}(\theta_+ + \theta_-)} \hat{f}_3$ with matrix eigenvalue \tilde{M} are given by

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp \left[\frac{i}{2} \ln \left(\sqrt{\frac{R_3 + 2R}{R_3 - 2R}} \right) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right) \right] \\
&\times \exp \left[\frac{1}{2} (\tilde{M} b^* - \tilde{M}^\dagger b) \hat{f}_3 \right] \begin{pmatrix} | -m_1 b \rangle \otimes | j, m_1 \rangle \\ | -m_2 b \rangle \otimes | j, m_2 \rangle \\ \vdots \\ | -m_{K-1} b \rangle \otimes | j, m_{K-1} \rangle \\ | -m_K b \rangle \otimes | j, m_K \rangle \end{pmatrix}. \tag{4.116}
\end{aligned}$$

On the other hand, when $\varphi = \frac{\pi}{2}$ and $0 < \rho < 1$, we have $\mathcal{Z} = \sqrt{1 - \rho^2} - i\rho$, that implies $\delta = -\frac{\pi}{2}$, and by consequent $\frac{\tilde{\theta}}{2} = \frac{\pi}{4} - \frac{i}{2} \ln \left(\sqrt{\frac{1+\rho}{1-\rho}} \right) = \frac{\pi}{4} - \frac{i}{2} \ln \left(\sqrt{\frac{2R+R_3}{2R-R_3}} \right)$ and $b = e^{\frac{i}{2}(\theta_+ + \theta_-)} \sqrt{4R^2 - R_3^2}$. Thus, the vector eigenstates of $\mathbf{A} = \hat{a} + R e^{i\theta_+} \hat{f}_- + R e^{i\theta_-} \hat{f}_+ + iR_3 e^{\frac{i}{2}(\theta_+ + \theta_-)} \hat{f}_3$ with matrix eigenvalue \tilde{M} are given by

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp \left[-\frac{\pi}{4} \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right) \right] \\
&\times \exp \left[\frac{i}{2} \ln \left(\sqrt{\frac{2R+R_3}{2R-R_3}} \right) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right) \right] \\
&\times \exp \left[\frac{1}{2} (\tilde{M} b^* - \tilde{M}^\dagger b) \hat{f}_3 \right] \begin{pmatrix} | -m_1 b \rangle \otimes | j, m_1 \rangle \\ | -m_2 b \rangle \otimes | j, m_2 \rangle \\ \vdots \\ | -m_{K-1} b \rangle \otimes | j, m_{K-1} \rangle \\ | -m_K b \rangle \otimes | j, m_K \rangle \end{pmatrix}. \tag{4.117}
\end{aligned}$$

From these last two expression we can also extract the corresponding set of vector coherent states. Indeed, putting $m_1 = m_2 = \dots = m_K = \mp j$ we can obtain the desired vector states:

$$|\Psi\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \tag{4.118}$$

$$\begin{aligned}
&\times \exp \left[\mp i \arctan \left(\frac{R_3 - \sqrt{R_3^2 - 4R^2}}{2R} \right) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_- \right) \right] \\
&\times \begin{pmatrix} | \pm j b \rangle \otimes | j, \mp j \rangle \\ | \pm j b \rangle \otimes | j, \mp j \rangle \\ \vdots \\ | \pm j b \rangle \otimes | j, \mp j \rangle \\ | \pm j b \rangle \otimes | j, \mp j \rangle \end{pmatrix}, \tag{4.119}
\end{aligned}$$

when $R_3 > 2R$, and

$$|\Psi\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \tag{4.120}$$

$$\begin{aligned}
&\times \exp \left[-\frac{\pi}{4} \left(e^{-i \left(\frac{\theta_+ - \theta_-}{2} \pm \arctan \left(\frac{R_3}{\sqrt{4R^2 - R_3^2}} \right) \right)} \hat{f}_+ - e^{i \left(\frac{\theta_+ - \theta_-}{2} \pm \arctan \left(\frac{R_3}{\sqrt{4R^2 - R_3^2}} \right) \right)} \hat{f}_- \right) \right] \\
&\times \begin{pmatrix} | \pm j b \rangle \otimes | j, \mp j \rangle \\ | \pm j b \rangle \otimes | j, \mp j \rangle \\ \vdots \\ | \pm j b \rangle \otimes | j, \mp j \rangle \\ | \pm j b \rangle \otimes | j, \mp j \rangle \end{pmatrix}, \tag{4.121}
\end{aligned}$$

when $0 < R_3 < 2R$.

4.5.3 The case $[\hat{A}, \hat{A}^\dagger] = \hat{I} + 2x \hat{f}_3 + \rho e^{i\nu} \hat{f}_+ + \rho e^{-i\nu} \hat{f}_-$, $x \neq 0$ and $\rho > 0$

In this subsection we will study the situation where the commutator between \hat{A} and \hat{A}^\dagger is equal to the identity plus a linear combination of the $su(2)$ algebra generators with non-zero coefficients. Here, three cases are possible, they are:

- When $\beta_- = R_- e^{i\theta_-} \neq 0$, $\beta_+ = 0$ and $\beta_3 = R_3 e^{i\theta_3} \neq 0$, the parameter $b = \beta_3$, $x = R_-^2$ and $\rho e^{i\nu} = -R_3 R_- e^{-\frac{i}{2}(\theta_3 - \theta_-)}$. Then, with help of equation (A.19) and the general structure (4.97) we can construct the vector states verifying (4.1), they are given by

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp\left[-\frac{\beta_-}{\beta_3} \hat{f}_+\right] \exp\left[\frac{1}{2}(\tilde{M}b^* - \tilde{M}^\dagger b) \hat{f}_3\right] \tilde{U} \begin{pmatrix} \sum_{m=-j}^j \tilde{\varphi}_{[1]m}^j(0) | -mb \rangle \otimes | j, m \rangle \\ \sum_{m=-j}^j \tilde{\varphi}_{[2]m}^j(0) | -mb \rangle \otimes | j, m \rangle \\ \vdots \\ \sum_{m=-j}^j \tilde{\varphi}_{[K-1]m}^j(0) | -mb \rangle \otimes | j, m \rangle \\ \sum_{m=-j}^j \tilde{\varphi}_{[K]m}^j(0) | -mb \rangle \otimes | j, m \rangle \end{pmatrix}. \quad (4.122)$$

By choosing $\tilde{\varphi}_{[s]m}^j$, $s = 1, 2, \dots, K$, as in equation (4.98) and then taking $m_r = -j$, $\forall r = 1, 2, \dots, K$, and after that, replacing the exponential operator depending on J_+ by its unitary equivalent, we get the set of normalized vector coherent states

$$|\Psi\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \exp\left[-\arctan\left(\frac{R_-}{R_3}\right) \left(e^{-i(\theta_3 - \theta_-)} \hat{f}_+ - e^{i(\theta_3 - \theta_-)} \hat{f}_-\right)\right] \begin{pmatrix} |jb\rangle \otimes |j, -j\rangle \\ |jb\rangle \otimes |j, -j\rangle \\ \vdots \\ |jb\rangle \otimes |j, -j\rangle \\ |jb\rangle \otimes |j, -j\rangle \end{pmatrix}. \quad (4.123)$$

- On the other hand, when $\beta_- = 0$, $\beta_+ = R_+ e^{i\theta_+} \neq 0$ and $\beta_3 = R_3 e^{i\theta_3} \neq 0$, the parameter $b = \beta_3$, $x = -R_+^2$ and $\rho e^{i\nu} = R_3 R_+ e^{i(\theta_3 - \theta_+)}$. Then, again, with help of equation (A.19) and the general structure (4.97) we can construct the vector states verifying (4.1), they are given by

$$|\Psi\rangle_{[K]}^j = \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp\left[\frac{\beta_+}{\beta_3} \hat{f}_-\right] \exp\left[\frac{1}{2}(\tilde{M}b^* - \tilde{M}^\dagger b) \hat{f}_3\right] \tilde{U} \begin{pmatrix} \sum_{m=-j}^j \tilde{\varphi}_{[1]m}^j(0) | -mb \rangle \otimes | j, m \rangle \\ \sum_{m=-j}^j \tilde{\varphi}_{[2]m}^j(0) | -mb \rangle \otimes | j, m \rangle \\ \vdots \\ \sum_{m=-j}^j \tilde{\varphi}_{[K-1]m}^j(0) | -mb \rangle \otimes | j, m \rangle \\ \sum_{m=-j}^j \tilde{\varphi}_{[K]m}^j(0) | -mb \rangle \otimes | j, m \rangle \end{pmatrix}. \quad (4.124)$$

By choosing again $\tilde{\varphi}_{[s]m}^j$, $s = 1, 2, \dots, K$, as in equation (4.98) and then taking $m_r = j$, $\forall r = 1, 2, \dots, K$, and after that, replacing the exponential operator depending on J_- by its unitary equivalent, we get the set of normalized vector coherent states

$$|\Psi\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \exp\left[-\arctan\left(\frac{R_+}{R_3}\right) \left(e^{i(\theta_3 - \theta_+)} \hat{f}_+ - e^{-i(\theta_3 - \theta_+)} \hat{f}_-\right)\right] \begin{pmatrix} | -jb \rangle \otimes | j, j \rangle \\ | -jb \rangle \otimes | j, j \rangle \\ \vdots \\ | -jb \rangle \otimes | j, j \rangle \\ | -jb \rangle \otimes | j, j \rangle \end{pmatrix}. \quad (4.125)$$

- Finally we have the case when $\beta_- = R_- e^{i\theta_-} \neq 0$, $\beta_+ = R_+ e^{i\theta_+} \neq 0$ and $\beta_3 = R_3 e^{i\theta_3} \neq 0$, provided that both, $R_+ \neq R_-$ and $R_3 \neq 2\sqrt{R_+ R_-}$ or $\theta_3 \neq \frac{1}{2}(\theta_+ - \theta_-) + \left(k + \frac{1}{2}\right)\pi$, $k = 1, 2, \dots$. Under these conditions

$$\rho e^{i\nu} = R_3 e^{-i(\theta_+ - \theta_-)} \sqrt{R_+^2 + R_-^2 - 2R_+ R_- \cos(2\varphi)} \exp\left[\frac{R_+ + R_-}{R_+ - R_-} \tan \varphi\right],$$

$b = 2\sqrt{R_+ R_-} e^{\frac{i}{2}(\theta_+ - \theta_-)} \sqrt{1 + \gamma^2}$ and $x = R_-^2 - R_+^2$, where $\gamma = \rho e^{i\varphi}$ with $\varphi = \theta_3 - \frac{1}{2}(\theta_+ + \theta_-)$ and now $\rho = \frac{R_3}{2\sqrt{R_+ R_-}}$. Then, as in previous subsection, from equation (B3) we can compute the parameters $\tilde{\theta}$ and $\tilde{\phi}$, serving to construct the operator \hat{T} , we get the following expressions

$$\tan\left(\frac{\tilde{\theta}}{2}\right) = \sqrt{\frac{b - \beta_3}{b + \beta_3}} = \sqrt{1 + \gamma^2} - \gamma, \quad e^{i\tilde{\phi}} = \sqrt{\frac{R_+}{R_-}} e^{\frac{i}{2}(\theta_+ - \theta_-)}. \quad (4.126)$$

We note that the expression used to calculate parameter $\tilde{\theta}$ has the same structure as the one in the previous subsection, then, to get its value we only have to use directly the expressions (4.108) and (4.109). On the other hand, with respect to the parameter $\tilde{\phi}$ now there is a little difference because it represents complex phase. Indeed, this last parameter can be written in the form $\tilde{\phi} = \tilde{\phi}_{Re} + i\tilde{\phi}_{Im}$, where $e^{-\tilde{\phi}_{Im}} = \sqrt{\frac{R_+}{R_-}}$ and $e^{i\tilde{\phi}_{Re}} = e^{\frac{i}{2}(\theta_+ - \theta_-)}$.

Thus, using (B2) we can show that the general structure of the operator \hat{T} in this case is given by the product of two exponential operators, none of which is unitary or Hermitian, that is,

$$\begin{aligned} \hat{T} &= \exp\left[\frac{\delta}{2}\left(\sqrt{\frac{R_-}{R_+}} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - \sqrt{\frac{R_+}{R_-}} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_-\right)\right] \\ &\times \exp\left[-\frac{i}{2} \ln\left(\frac{\sqrt{(1 - \|\mathcal{Z}\|^2)^2 + 4\mathcal{Z}_{Re}^2}}{1 - 2\mathcal{Z}_{Im} + \|\mathcal{Z}\|^2}\right)\left(\sqrt{\frac{R_-}{R_+}} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - \sqrt{\frac{R_+}{R_-}} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_-\right)\right]. \end{aligned} \quad (4.127)$$

By inserting this operator into the general expression (4.97) or into (4.99) we finally obtain the vector algebra eigenstates of the operator $\hat{A} = \hat{a} + R e^{i\theta_+} \hat{f}_+ + R e^{i\theta_-} \hat{f}_- + R_3 e^{i\theta_3}$, which parameters satisfy the condition given in this subsection:

$$\begin{aligned} |\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp\left[\frac{\delta}{2}\left(\sqrt{\frac{R_-}{R_+}} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - \sqrt{\frac{R_+}{R_-}} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_-\right)\right] \\ &\times \\ &\times \exp\left[-\frac{i}{2} \ln\left(\frac{\sqrt{(1 - \|\mathcal{Z}\|^2)^2 + 4\mathcal{Z}_{Re}^2}}{1 - 2\mathcal{Z}_{Im} + \|\mathcal{Z}\|^2}\right)\left(\sqrt{\frac{R_-}{R_+}} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - \sqrt{\frac{R_+}{R_-}} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_-\right)\right] \\ &\times \exp\left[\frac{1}{2}(\tilde{M}b^* - \tilde{M}^\dagger b) \hat{f}_3\right] \begin{pmatrix} | -m_1 b \rangle \otimes | j, m_1 \rangle \\ | -m_2 b \rangle \otimes | j, m_2 \rangle \\ \vdots \\ | -m_{K-1} b \rangle \otimes | j, m_{K-1} \rangle \\ | -m_K b \rangle \otimes | j, m_K \rangle \end{pmatrix}. \end{aligned} \quad (4.128)$$

From (4.128) we can find the associated vector coherent states for this case. If we choose $m_1 = m_2 = \dots = m_K = \mp j$, and proceed as in the previous sections, we get the set of normalized vector coherent states:

$$\begin{aligned} |\Psi\rangle_{[K]}^j &= \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \\ &\times \exp\left[-\arctan(\|\mathcal{Z}\| e^{\pm \tilde{\phi}_{Im}}) \left(e^{-i\left(\frac{\theta_+ - \theta_-}{2} \mp \arctan\left(\frac{\mathcal{Z}_{Im}}{\mathcal{Z}_{Re}}\right)\right)} \hat{f}_+ - e^{i\left(\frac{\theta_+ - \theta_-}{2} \mp \arctan\left(\frac{\mathcal{Z}_{Im}}{\mathcal{Z}_{Re}}\right)\right)} \hat{f}_-\right)\right] \\ &\times \begin{pmatrix} | \pm j b \rangle \otimes | j, \mp j \rangle \\ | \pm j b \rangle \otimes | j, \mp j \rangle \\ \vdots \\ | \pm j b \rangle \otimes | j, \mp j \rangle \\ | \pm j b \rangle \otimes | j, \mp j \rangle \end{pmatrix}, \end{aligned} \quad (4.130)$$

where $\arctan\left(\frac{\mathcal{Z}_{Im}}{\mathcal{Z}_{Re}}\right)$ is replaced by $\frac{\pi}{2}$ when $\mathcal{Z}_{Re} = 0$.

Some examples Let us illustrate the results of this section by choosing the same range of variation of the φ and ρ parameters used in the previous subsection. Thus, when $\varphi = \frac{\pi}{2}$ and $\rho > 1$, we have $\mathcal{Z} = i(\sqrt{\rho^2 - 1} - \rho)$, that implies $\delta = 0$, and by consequent $\frac{\tilde{\theta}}{2} = -\frac{i}{2} \ln\left(\sqrt{\frac{R_3 + 2\sqrt{R_+ R_-}}{R_3 - 2\sqrt{R_+ R_-}}}\right)$ and $b = i e^{\frac{i}{2}(\theta_+ + \theta_-)} \sqrt{R_3^2 - 4R_+ R_-}$. Thus, the vector eigenstates of $\mathcal{A} = \hat{a} + R_+ e^{i\theta_+} \hat{f}_- + R_- e^{i\theta_-} \hat{f}_+ + iR_3 e^{\frac{i}{2}(\theta_+ + \theta_-)} \hat{f}_3$ with matrix eigenvalue \tilde{M} are given by

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp\left[\frac{i}{2} \ln\left(\sqrt{\frac{R_3 + 2\sqrt{R_+ R_-}}{R_3 - 2\sqrt{R_+ R_-}}}\right) \left(\sqrt{\frac{R_-}{R_+}} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - \sqrt{\frac{R_+}{R_-}} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_-\right)\right] \\
&\times \exp\left[\frac{1}{2}(\tilde{M}b^* - \tilde{M}^\dagger b) \hat{f}_3\right] \begin{pmatrix} | -m_1 b \rangle \otimes | j, m_1 \rangle \\ | -m_2 b \rangle \otimes | j, m_2 \rangle \\ \vdots \\ | -m_{K-1} b \rangle \otimes | j, m_{K-1} \rangle \\ | -m_K b \rangle \otimes | j, m_K \rangle \end{pmatrix}. \quad (4.131)
\end{aligned}$$

On the other hand, when $\varphi = \frac{\pi}{2}$ and $0 < \rho < 1$, we have $\mathcal{Z} = \sqrt{1 - \rho^2} - i\rho$, that implies $\delta = -\frac{\pi}{2}$, and by consequent $\frac{\tilde{\theta}}{2} = \frac{\pi}{4} - \frac{i}{2} \ln\left(\sqrt{\frac{1+\rho}{1-\rho}}\right) = \frac{\pi}{4} - \frac{i}{2} \ln\left(\sqrt{\frac{2\sqrt{R_+ R_-} + R_3}{2\sqrt{R_+ R_-} - R_3}}\right)$ and $b = e^{\frac{i}{2}(\theta_+ + \theta_-)} \sqrt{4R_+ R_- - R_3^2}$. Thus, the vector eigenstates of $\mathcal{A} = \hat{a} + R_+ e^{i\theta_+} \hat{f}_- + R_- e^{i\theta_-} \hat{f}_+ + iR_3 e^{\frac{i}{2}(\theta_+ + \theta_-)} \hat{f}_3$ with matrix eigenvalue \tilde{M} are given by

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \mathcal{N}^{-\frac{1}{2}} \hat{D}(\tilde{M}) \exp\left[-\frac{\pi}{4} \left(\sqrt{\frac{R_-}{R_+}} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - \sqrt{\frac{R_+}{R_-}} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_-\right)\right] \\
&\times \exp\left[\frac{i}{2} \ln\left(\sqrt{\frac{2\sqrt{R_+ R_-} + R_3}{2\sqrt{R_+ R_-} - R_3}}\right) \left(\sqrt{\frac{R_-}{R_+}} e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ - \sqrt{\frac{R_+}{R_-}} e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_-\right)\right] \\
&\times \exp\left[\frac{1}{2}(\tilde{M}b^* - \tilde{M}^\dagger b) \hat{f}_3\right] \begin{pmatrix} | -m_1 b \rangle \otimes | j, m_1 \rangle \\ | -m_2 b \rangle \otimes | j, m_2 \rangle \\ \vdots \\ | -m_{K-1} b \rangle \otimes | j, m_{K-1} \rangle \\ | -m_K b \rangle \otimes | j, m_K \rangle \end{pmatrix}. \quad (4.132)
\end{aligned}$$

From these last two expression we can also extract the corresponding set of vector coherent states. Indeed, putting $m_1 = m_2 = \dots = m_K = \mp j$ we can obtain the desired vector states:

$$\begin{aligned}
|\Psi\rangle_{[K]}^j &= \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \quad (4.133) \\
&\times \exp\left[\mp i \arctan\left(\frac{R_3 - \sqrt{R_3^2 - 4R_+ R_-}}{2R_\pm}\right) \left(e^{-\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_+ + e^{\frac{i}{2}(\theta_+ - \theta_-)} \hat{f}_-\right)\right] \\
&\times \begin{pmatrix} | \pm j b \rangle \otimes | j, \mp j \rangle \\ | \pm j b \rangle \otimes | j, \mp j \rangle \\ \vdots \\ | \pm j b \rangle \otimes | j, \mp j \rangle \\ | \pm j b \rangle \otimes | j, \mp j \rangle \end{pmatrix}, \quad (4.134)
\end{aligned}$$

when $\varphi = \frac{\pi}{2}$ and $R_3 > 2\sqrt{R_+ R_-}$ and

$$|\Psi\rangle_{[K]}^j = \frac{1}{\sqrt{K}} \hat{D}(\tilde{M}) \quad (4.135)$$

$$\begin{aligned} & \times \exp \left[-\arctan \left(\frac{R_{\mp}}{R_{\pm}} \right) \left(e^{-i \left(\frac{\theta_+ - \theta_-}{2} \pm \arctan \left(\frac{R_3}{\sqrt{4R_+ R_- - R_3^2}} \right) \right)} \hat{J}_+ - e^{i \left(\frac{\theta_+ - \theta_-}{2} \pm \arctan \left(\frac{R_3}{\sqrt{4R_+ R_- - R_3^2}} \right) \right)} \hat{J}_- \right) \right] \\ & \times \begin{pmatrix} |\pm j b\rangle \otimes |j, \mp j\rangle \\ |\pm j b\rangle \otimes |j, \mp j\rangle \\ \vdots \\ |\pm j b\rangle \otimes |j, \mp j\rangle \\ |\pm j b\rangle \otimes |j, \mp j\rangle \end{pmatrix}, \quad (4.136) \end{aligned}$$

when $\varphi = \frac{\pi}{2}$ and $0 < R_3 < 2R$.

5 Conclusions

In this article we have defined and computed the vector algebra eigenstates associated to the $h(1) \oplus su(2)$ Lie algebra. We have shown that the set of these vector states includes the subset of vector coherent states over the matrix domain of the Heisenberg-Weyl algebra as well as those of the $su(2)$ Lie algebra. Other subsets of vector coherent states have been also obtained which appear as consequence of the combination as a direct sum of these two algebras. We have shown that it is possible to classify the set of all these vector eigenstates by giving to the elements of the algebra the role of a generalized annihilation operator and then using the commutator between it and its corresponding adjoint as a selection rule. Also with the help of these two operators we have constructed Hermitian Hamiltonians to which we can associate those vector coherent states. For example, this allowed us to find generalized Hamiltonians which are isospectral with the standard harmonic oscillator Hamiltonian. Moreover, in the particular case where the normal eigenvalue matrix have been constructed of the matrix elements of a complex linear combination of the $su(2)$ Lie algebra generators and the identity operator in a given $su(2)$ irreducible representation space, we have shown that for a special choice of the parameters, we can obtain the so-called quaternionic vector coherent states on the matrix domain [15] and the corresponding generalized oscillator algebra characteristic of the coherent state quantization of quaternions [16], as well as a generalized version of all that. The techniques used in this article and the results obtained can be easily adapted to construct families of linear and quadratic $su(2)$ and $h(1) \oplus su(2)$ pseudo-Hermitian Hamiltonians, see [19] and references therein. Also, all kind of intelligent and coherent states associated to the generalized Schrödinger-Robertson uncertainty relation [20] are included in ours results. Indeed, by choosing two Hermitian operators, $\hat{\mathcal{X}}$ and $\hat{\mathcal{P}}$, from the set of elements of the $h(1) \oplus su(2)$ Lie algebra, it can be shown that the minimum uncertainty states in the sense of the Schrödinger-Robertson relation verify the matrix eigenvalue equation $[\hat{\mathcal{X}} + i\lambda\hat{\mathcal{P}}] |\Phi\rangle = M |\Phi\rangle$, where $\lambda \in \mathbb{C}$. Then, families of vector coherent and squeezed states can be generated from it, depending on the values of the λ parameter, which selection rules in term of the commutator $[\hat{\mathcal{X}}, \hat{\mathcal{P}}]$ coincide with those of the generalized creation and annihilation rules mentioned above. Finally, an important relation involving the generators of the $su(2)$ algebra have been explicitly developed at the moment of disentangling the exponential operators in the case when the parameter $b = 0$, namely, that the non-canonical commutator $[\hat{a} + (\vec{\beta} \cdot \vec{J}), \hat{a}^\dagger + (\vec{\beta} \cdot \vec{J})^\dagger] = \hat{I} + 2x\hat{J}_3 + \rho e^{i\nu}\hat{J}_+ + \rho e^{-i\nu}\hat{J}_-$, where $|x| > 0$, is equivalent to the canonical one $[\hat{a} + \mathbb{B}_{\mp} \hat{J}_+, \hat{a}^\dagger + \mathbb{B}_{\mp}^* \hat{J}_{\mp}] = \hat{I} \pm 2\|\mathbb{B}_{\mp}\|^2 \hat{J}_3$, for suitably defined $su(2)$ Lie algebra transformed generators \hat{J}_+ , \hat{J}_- and \hat{J}_3 . In other words, we have shown that to each element of the complex Lie algebra of $su(2)$, whose coefficients verify $b = 0$, we can associate its adjoint element and the element formed from the commutator between them in such a way that the three generators reproduce the standard commutation relations of the $su(2)$ Lie algebra.

Acknowledgment

The author dedicates this article to his little purple doll Mary and his beloved children.

A Algebra eigenstates of $h(1) \oplus su(2)$ Lie algebra

The $h(1) \oplus su(2)$ algebra eigenstates are defined to be the solutions of the eigenvalue equation

$$[\alpha_- \hat{a} + \alpha_+ \hat{a}^\dagger + \alpha_3 \hat{I} + \beta_- \hat{J}_+ + \beta_+ \hat{J}_- + \beta_3 \hat{J}_3] |\Phi\rangle = \beta |\Phi\rangle, \quad (\text{A.1})$$

where $\alpha_\mp, \alpha_3, \beta_\mp$ and β_3 are given complex numbers and β a complex number representing the associated eigenvalue.

Equation (A.1) have been already studied in the literature. We will continue here the study of these states in order to prepare it suitably and to use it effectively in the construction, simplification and factorization of the $h(1) \oplus su(2)$ algebra eigenstates with eigenvalues over the matrix domain. From (A.1) we can see that without loss of generality we can set $\alpha_- = 1$ and $\alpha_3 = 0$. Then, by applying the following transformation to the states

$$|\Phi\rangle = \exp\left[-\frac{1}{2}\alpha_+ (\hat{a}^\dagger)^2\right] |\Psi\rangle, \quad (\text{A.2})$$

(A.1) reduces to:

$$[\hat{a} + \beta_- \hat{J}_+ + \beta_+ \hat{J}_- + \beta_3 \hat{J}_3] |\Psi\rangle = \beta |\Psi\rangle. \quad (\text{A.3})$$

Before continuing with the resolution of the eigenvalue problem, let us make some comments about the transformation we just performed. The transformation (A.2), corresponds to a standard squeezed transformation provided that $\|\alpha_+\| < 1$. When we apply it to the fundamental state $|0\rangle$, it can be replaced by the unitary transformation $\hat{S}(\xi) = \exp\left[-\frac{1}{2}(\xi \hat{a}^{\dagger 2} - \xi^* \hat{a}^2)\right] |0\rangle$, where $\xi = \frac{\alpha_+}{\|\alpha_+\|} \tanh^{-1}(\|\alpha_+\|)$.

On the other hand, when it is applied onto a coherent state, that is, $e^{-\frac{1}{2}\alpha_+ \hat{a}^{\dagger 2}} e^{z_1 \hat{a}^\dagger} |0\rangle$, where z_1 is an arbitrary complex number, we can first use the property $\hat{S}^\dagger(\xi) \hat{a}^\dagger \hat{S}(\xi) = \left[\hat{a}^\dagger \cosh(\|\xi\|) - \frac{\xi^*}{\|\xi\|} \sinh(\|\xi\|) \hat{a}\right]$ to shift the squeezed unitary operator to the left hand, and then rewrite the resulting expression in terms of the unitary displacement operator associated to the standard harmonic oscillator to get the normalized equivalent relation $\hat{S}(\xi) \hat{D}(z_1 \cosh(\|\xi\|)) |0\rangle$. Moreover, when, for example, the following situation occurs: $e^{-\frac{1}{2}\alpha_+ \hat{a}^{\dagger 2}} e^{\beta \hat{a}^\dagger} (z a^\dagger)^n |0\rangle$, where n is a non-negative integer, by using the well know properties of the squeezed and displacement operators we can write this state in the form

$$\hat{S}(\xi) \hat{D}(\beta \cosh(\|\xi\|)) \left[z \left((\hat{a}^\dagger + \beta^* \cosh(\|\xi\|)) \cosh(\|\xi\|) - \frac{\xi^*}{\|\xi\|} \sinh(\|\xi\|) (\hat{a} + \beta \cosh(\|\xi\|)) \right) \right]^n |0\rangle. \quad (\text{A.4})$$

When $\|\alpha_+\| \geq 1$, we can leave the transformation (squeezed-transformation) as it is. So in this way, once the solutions of the eigenvalue equation (A.3) are know, proceeding as we have indicated here, we will be able to obtain the complete set of solutions of equation (A.1).

Now, let us rewrite (A.3) in the form

$$\hat{a} |\Psi\rangle = [\beta - \beta_- \hat{J}_+ - \beta_+ \hat{J}_- - \beta_3 \hat{J}_3] |\Psi\rangle, \quad (\text{A.5})$$

Projecting both sides of (A.5) onto the state $|\zeta\rangle \otimes \hat{I}^j$ and using (2.13) the realization (2.11) for the \hat{a} annihilator, and the relations (2.5) for the $su(2)$ algebra generators, we obtain, for fixed j , the following coupled linear system of differential equations:

$$\begin{aligned} \frac{d}{d\zeta} \psi_m^j(\zeta) &= (\beta - m\beta_3) \psi_m^j(\zeta) \\ &- \beta_- \sqrt{(j-m)(j+m+1)} \psi_{m+1}^j(\zeta) \\ &- \beta_+ \sqrt{(j+m)(j-m+1)} \psi_{m-1}^j(\zeta), \quad m = -j, \dots, j. \end{aligned} \quad (\text{A.6})$$

This system can be written in the form

$$\frac{d}{d\zeta} \begin{pmatrix} \psi_{-j}^j(\zeta) \\ \psi_{-j+1}^j(\zeta) \\ \vdots \\ \psi_{j-1}^j(\zeta) \\ \psi_j^j(\zeta) \end{pmatrix} = M \begin{pmatrix} \psi_{-j}^j(\zeta) \\ \psi_{-j+1}^j(\zeta) \\ \vdots \\ \psi_{j-1}^j(\zeta) \\ \psi_j^j(\zeta) \end{pmatrix}, \quad (\text{A.7})$$

where M is the $2j+1 \times 2j+1$ dimensional matrix:

$$M = \begin{pmatrix} \beta+j\beta_3 & -\sqrt{2j}\beta_+ & 0 & 0 & \dots & 0 \\ -\sqrt{2j}\beta_- & \beta+(j-1)\beta_3 & -\sqrt{(2j-1)2}\beta_+ & 0 & \dots & 0 \\ 0 & -\sqrt{(2j-1)2}\beta_- & \beta+(j-2)\beta_3 & -\sqrt{(2j-2)3}\beta_+ & \dots & 0 \\ \vdots & \vdots & \ddots & \ddots & \ddots & \vdots \\ 0 & 0 & -\sqrt{3(2j-2)}\beta_- & \beta-(j-2)\beta_3 & -\sqrt{2(2j-1)}\beta_+ & 0 \\ 0 & 0 & 0 & -\sqrt{2(2j-1)}\beta_- & \beta-(j-1)\beta_3 & -\sqrt{2j}\beta_+ \\ 0 & 0 & 0 & 0 & -\sqrt{2j}\beta_- & \beta-j\beta_3 \end{pmatrix}. \quad (\text{A.8})$$

At this time it is important to mention that the eigenvalues of M are given by

$$\lambda_m^j = \beta + mb, \quad \text{where } b = \sqrt{4\beta_+\beta_- + \beta_3^2}, \quad m = -j, \dots, j, \quad (\text{A.9})$$

which implies that when $b \neq 0$, all λ_m^j 's are different and when $b = 0$, all λ_m^j 's are equal to β . Thus, in the first case, the matrix in (A.8) can be diagonalized by a similarity transformation, while in the second case it is not always possible to do it.

A.1 Case $b \neq 0$

In this subsection we will construct the $h(1) \oplus su(2)$ algebra eigenstates associated aux generators which parameters verify $b \neq 0$. We will see that in all the different cases the structure of these states presents the form of a product of two untangled operators that act on the base states, the first one depending solely on the $h(1)$ algebra generators and the second depending exclusively on the $su(2)$ algebra generators. The method that we will use in the different cases to solve the equation (A.1) will combine the techniques of the algebra of operators and that of differential equations.

A.1.1 Case $\beta_+ = \beta_- = 0$ and $\beta_3 \neq 0$

Let us start with the computation of the algebra eigenstates of the simplest generator combining operators from the $h(1)$ sector and $su(2)$ sector, that is,

$$[\hat{a} + \beta_3 \hat{J}_3] |\psi\rangle^j = \beta |\psi\rangle^j. \quad (\text{A.10})$$

It is clear that in this case $b = \beta_3 \neq 0$. Then, the set of normalized states verifying this equation is given by

$$|\psi\rangle_m^j = |\beta - m\beta_3\rangle \otimes |j, m\rangle, \quad m = -j, \dots, j. \quad (\text{A.11})$$

Thus, the general solution of equation (A.10) writes

$$|\psi\rangle^j = \sum_{m=-j}^j \frac{\tilde{\varphi}_m^j(0)}{\sqrt{\sum_{m=-j}^j \|\tilde{\varphi}_m^j(0)\|^2}} |\beta - m\beta_3\rangle \otimes |j, m\rangle, \quad (\text{A.12})$$

where $\tilde{\varphi}_m^j(0)$, $m = -1, \dots, j$, are constants.

Using the fact that $\hat{D}(\beta - m\beta_3) = \hat{D}(\beta)\hat{D}(-m\beta_3)\exp\left[\frac{m}{2}(\beta\beta_3^* - \beta^*\beta_3)\right]$, the states in equation (A.12) can be written in the form

$$|\psi\rangle^j = \hat{D}(\beta)\exp\left[\frac{1}{2}(\beta\beta_3^* - \beta^*\beta_3)\hat{J}_3\right]\sum_{m=-j}^j\frac{\tilde{\varphi}_m^j(0)}{\sqrt{\sum_{m=-j}^j\|\tilde{\varphi}_m^j(0)\|^2}}|-m\beta_3\rangle\otimes|j,m\rangle. \quad (\text{A.13})$$

A.1.2 Case $\beta_+ \neq 0, \beta_- = 0$ and $\beta_3 \neq 0$

When $\beta_+ \neq 0, \beta_- = 0$ and $\beta_3 \neq 0$, equation (A.1) becomes

$$[\hat{a} + \beta_+\hat{J}_- + \beta_3\hat{J}_3]|\psi\rangle^j = \beta|\psi\rangle^j. \quad (\text{A.14})$$

Again, in this case $b = \beta_3 \neq 0$.

By performing in (A.18) the following transformation on the states $|\psi\rangle^j = e^{\frac{\beta_+}{\beta_3}\hat{J}_-}|\tilde{\psi}\rangle^j$ and acting at the same time from the left on both sides of this equation with the operator $e^{-\frac{\beta_+}{\beta_3}\hat{J}_-}$, and then using the fact that $e^{-\frac{\beta_+}{\beta_3}\hat{J}_-}\beta_3\hat{J}_3e^{\frac{\beta_+}{\beta_3}\hat{J}_-}|\tilde{\psi}\rangle = -\beta_+\hat{J}_- + \beta_3\hat{J}_3$, we get

$$[\hat{a} + \beta_3\hat{J}_3]|\tilde{\psi}\rangle^j = \beta|\tilde{\psi}\rangle^j. \quad (\text{A.15})$$

Hence, the set of normalized eigenstates verifying this last equation is given by

$$|\tilde{\psi}\rangle_m^j = |\beta - m\beta_3\rangle\otimes|j,m\rangle, \quad m = -j, \dots, j. \quad (\text{A.16})$$

Finally, using the results of the previous subsection and then returning to the original states by performing the inverse transformation, we find that the general solution of equation (A.18) is given by

$$|\psi\rangle^j = \frac{1}{\sqrt{\mathcal{N}^j}}\hat{D}(\beta)e^{\frac{\beta_+}{\beta_3}\hat{J}_-}\exp\left[\frac{1}{2}(\beta\beta_3^* - \beta^*\beta_3)\hat{J}_3\right]\sum_{m=-j}^j\tilde{\varphi}_m^j(0)|-m\beta_3\rangle\otimes|j,m\rangle, \quad (\text{A.17})$$

where \mathcal{N}^j is a generic normalization constant.

A.1.3 Case $\beta_+ = 0, \beta_- \neq 0$ and $\beta_3 \neq 0$

When $\beta_+ = 0, \beta_- \neq 0$ and $\beta_3 \neq 0$, equation (A.1) becomes

$$[\hat{a} + \beta_-\hat{J}_+ + \beta_3\hat{J}_3]|\psi\rangle^j = \beta|\psi\rangle^j. \quad (\text{A.18})$$

Again, in this case $b = \beta_3 \neq 0$. Proceeding exactly as in the previous subsection, but taking in account that now the new transformation on the states is governed by the operator $e^{-\frac{\beta_-}{\beta_3}\hat{J}_+}$, we find the general solution of (A.18) is given by

$$|\psi\rangle^j = \frac{1}{\sqrt{\mathcal{N}^j}}\hat{D}(\beta)e^{\frac{-\beta_-}{\beta_3}\hat{J}_+}\exp\left[\frac{1}{2}(\beta\beta_3^* - \beta^*\beta_3)\hat{J}_3\right]\sum_{m=-j}^j\tilde{\varphi}_m^j(0)|-m\beta_3\rangle\otimes|j,m\rangle. \quad (\text{A.19})$$

A.1.4 Case $\beta_+ \neq 0, \beta_- \neq 0$ and $\beta_3 = 0$

When $\beta_+ \neq 0, \beta_- \neq 0$ and $\beta_3 = 0$, equation (A.1) becomes

$$[\hat{a} + \beta_-\hat{J}_+ + \beta_+\hat{J}_-]|\psi\rangle^j = \beta|\psi\rangle^j. \quad (\text{A.20})$$

Also, in this case $b = 2\sqrt{\beta_+\beta_-} \neq 0$. Then, by using equations (B2) and (B3), we can construct an operator \hat{T} with the following characteristics:

$$\hat{T} = \exp\left[-\frac{\pi}{4}\left(\sqrt{\frac{\beta_-}{\beta_+}}\hat{J}_+ - \sqrt{\frac{\beta_+}{\beta_-}}\hat{J}_-\right)\right], \quad (\text{A.21})$$

such that

$$\hat{T}^{-1}[\beta_- \hat{J}_+ + \beta_+ \hat{J}_-] \hat{T} = b \hat{J}_3. \quad (\text{A.22})$$

We notice that, in general, \hat{T} is not unitary, it becomes unitary if and only if $\|\beta_+\| = \|\beta_-\|$. Thus, using the following transformation $|\psi\rangle^j = \hat{T} |\tilde{\psi}\rangle^j$ in equation (A.20), and then acting from the left with \hat{T}^{-1} on both sides of the corresponding transformed equation we get

$$[\hat{a} + b \hat{J}_3] |\tilde{\psi}\rangle^j = \beta |\tilde{\psi}\rangle^j, \quad (\text{A.23})$$

which normalized solutions we already know from the previous sections, that is,

$$|\tilde{\psi}\rangle_m^j = |\beta - mb\rangle \otimes |j, m\rangle, \quad m = -j, \dots, j. \quad (\text{A.24})$$

Finally, proceeding as in the previous subsections, we reach the general solution of (A.20):

$$|\psi\rangle^j = \frac{1}{\sqrt{\mathcal{N}^j}} \hat{D}(\beta) \exp\left[-\frac{\pi}{4} \left(\sqrt{\frac{\beta_-}{\beta_+}} \hat{J}_+ - \sqrt{\frac{\beta_+}{\beta_-}} \hat{J}_- \right)\right] \exp\left[\frac{1}{2} (\beta b^* - \beta^* b) \hat{J}_3\right] \sum_{m=-j}^j \tilde{\varphi}_m^j(0) |\beta - mb\rangle \otimes |j, m\rangle. \quad (\text{A.25})$$

A.1.5 Case $\beta_+ \neq 0, \beta_- \neq 0$ and $\beta_3 \neq 0$

When all beta parameters of the $su(2)$ algebra sector, which in principle are complex numbers, are different from zero, we need to select a subset of parameters for which $b \neq 0$. If we define

$$\beta_+ = R_+ e^{i\theta_+}, \quad \beta_- = R_- e^{i\theta_-}, \quad \text{and} \quad \beta_3 = R_3 e^{i\theta_3}, \quad (\text{A.26})$$

where R_{\pm} and $R_3 \in \mathbb{R}_+$, and θ_{\pm} and $\theta_3 \in [0, 2\pi]$, the conditions for b being different from zero are

$$R_3 \neq 2\sqrt{R_+ R_-} \quad \text{or} \quad \theta_3 \neq \frac{1}{2}(\theta_+ + \theta_-) + \left(k + \frac{1}{2}\right)\pi, \quad k = 0, 1. \quad (\text{A.27})$$

Then, under these conditions, using again (B2) and (B3), we can construct an exponential operator \hat{T} such that

$$\hat{T}^{-1}[\beta_+ \hat{J}_- + \beta_- \hat{J}_+ + \beta_3 \hat{J}_3] \hat{T} = b \hat{J}_3. \quad (\text{A.28})$$

Hence, proceeding exactly as in the previous section, we can reduce (A.1) to

$$[\hat{a} + b \hat{J}_3] |\tilde{\psi}\rangle^j = \beta |\tilde{\psi}\rangle^j, \quad (\text{A.29})$$

which normalized solutions we already know from the previous sections, that is,

$$|\tilde{\psi}\rangle_m^j = |\beta - mb\rangle \otimes |j, m\rangle, \quad m = -j, \dots, j. \quad (\text{A.30})$$

and in consequence the general solution of (A.1) is given by

$$|\psi\rangle^j = \frac{1}{\sqrt{\mathcal{N}^j}} \hat{D}(\beta) \hat{T} \exp\left[\frac{1}{2} (\beta b^* - \beta^* b) \hat{J}_3\right] \sum_{m=-j}^j \tilde{\varphi}_m^j(0) |\beta - mb\rangle \otimes |j, m\rangle. \quad (\text{A.31})$$

Here, in general, \hat{T} is not unitary, it becomes unitary if and only if $R_+ = R_-$ and the angle $\theta_3 = \frac{1}{2}(\theta_+ + \theta_-) + \left(k + \frac{1}{2}\right)\pi$, $k = 0, 1$ and $R_3 \neq \sqrt{R_+ R_-}$. Remarkably, these same conditions make the matrix M in A.8 normal.

A.1.6 Case M normal

Indeed, when M in A.8 is a normal matrix, i.e., $M^\dagger M = M M^\dagger$, where M^\dagger denotes the conjugate transpose of M , the following conditions on the parameters forming the entries of M are imposed

$$\|\beta_+\| = \|\beta_-\|, \quad \text{and} \quad \beta_3 \beta_+^* - \beta_3^* \beta_- = 0, \quad (\text{A.32})$$

or if we define

$$\beta_\pm = \|\beta_\pm\| e^{\pm i\theta_\pm}, \quad \text{and} \quad \beta_3 = \|\beta_3\| e^{i\theta_3}, \quad (\text{A.33})$$

and insert it in (A.32) we get their equivalents:

$$\|\beta_+\| = \|\beta_-\| = \|\beta_\pm\| \quad \text{and} \quad e^{i(\theta_+ + \theta_-)} = e^{2i\theta_3}. \quad (\text{A.34})$$

From this last equation we can show that b in (A.9) is given $b = e^{\frac{i}{2}(\theta_+ + \theta_-)} \sqrt{4\|\beta_\pm\|^2 + \|\beta_3\|^2}$ which means that it is equal to zero if and only if $\beta_+ = \beta_- = \beta_3 = 0$, in which case $M = \beta I$, i.e, a diagonal matrix. On the other hand, when $\beta_+ = \beta_- = 0$ and $\beta_3 \neq 0$, the M matrix is still diagonal and then, the unitary matrix that makes it diagonal is the identity matrix. In a more general case, there exist a unitary matrix U such that $U^\dagger M U = D$, where

$$D = \begin{pmatrix} \lambda_{-j}^j & 0 & 0 & \cdots & 0 \\ 0 & \lambda_{-j+1}^j & 0 & \cdots & 0 \\ \vdots & \vdots & \ddots & \vdots & \vdots \\ 0 & \cdots & 0 & \lambda_{j-1}^j & 0 \\ 0 & \cdots & 0 & 0 & \lambda_j^j \end{pmatrix} \quad (\text{A.35})$$

is a diagonal matrix formed out of the eigenvalues of M .

Operating with U^\dagger on both sides of equation (A.7), we get the uncoupled linear differential equation system:

$$\frac{d}{d\zeta} \begin{pmatrix} \tilde{\psi}_{-j}^j(\zeta) \\ \tilde{\psi}_{-j+1}^j(\zeta) \\ \vdots \\ \tilde{\psi}_{j-1}^j(\zeta) \\ \tilde{\psi}_j^j(\zeta) \end{pmatrix} = D \begin{pmatrix} \tilde{\psi}_{-j}^j(\zeta) \\ \tilde{\psi}_{-j+1}^j(\zeta) \\ \vdots \\ \tilde{\psi}_{j-1}^j(\zeta) \\ \tilde{\psi}_j^j(\zeta) \end{pmatrix}, \quad (\text{A.36})$$

where the tilde vector verify

$$\begin{pmatrix} \psi_{-j}^j(\zeta) \\ \psi_{-j+1}^j(\zeta) \\ \vdots \\ \psi_{j-1}^j(\zeta) \\ \psi_j^j(\zeta) \end{pmatrix} = U \begin{pmatrix} \tilde{\psi}_{-j}^j(\zeta) \\ \tilde{\psi}_{-j+1}^j(\zeta) \\ \vdots \\ \tilde{\psi}_{j-1}^j(\zeta) \\ \tilde{\psi}_j^j(\zeta) \end{pmatrix}. \quad (\text{A.37})$$

The integration of equation (A.36) is direct, we obtain

$$\tilde{\psi}_m^j(\zeta) = e^{\lambda_{-m}^j \zeta} \tilde{\varphi}_m^j(0), \quad m = -j, \dots, j, \quad (\text{A.38})$$

where $\tilde{\varphi}_m^j(0)$, $m = -j, \dots, j$, are arbitrary integration constants. With help of equation (A.37), the solution of the original system (A.7) can be reached, that is

$$\psi_m^j(\zeta) = \sum_{\ell=-j}^j U_{m\ell} \tilde{\psi}_\ell^j(\zeta) = \sum_{m=-\ell}^j U_{m\ell} e^{\lambda_{-\ell}^j \zeta} \tilde{\varphi}_\ell^j(0). \quad (\text{A.39})$$

Inserting this result in equation (2.12) we arrive to

$$|\Psi(\zeta)\rangle^j = \sum_{m=-j}^j \tilde{\varphi}_m^j(0) e^{\lambda_{-m}^j \zeta} \otimes \sum_{\ell=-j}^j U_{m\ell}^t |j, \ell\rangle, \quad (\text{A.40})$$

where U^t stands for the transpose of U . We can then express this last states in terms of the energy eigenstates of the standard harmonic oscillator Hamiltonian, that is

$$|\Psi\rangle^j = N^{-\frac{1}{2}} \sum_{m=-j}^j \tilde{\varphi}_m^j(0) e^{\lambda_{-m}^j \hat{a}^\dagger} |0\rangle \otimes \sum_{\ell=-j}^j U_{m\ell}^t |j, \ell\rangle. \quad (\text{A.41})$$

where N is a normalization constant which must be fixed by imposing ${}^j\langle\Psi|\Psi\rangle^j = 1$. We notice that the general solution (A.41) is a superposition of $2j + 1$ independent solutions of the $h(1) \oplus su(1)$ algebra eigenstate equation which are orthogonal to each other. Indeed, each solution composing the general state in (A.41), in a normalized version, is given by

$$\begin{aligned} |\psi\rangle_m^j &= e^{-\frac{1}{2}\|\lambda_{-m}^j\|^2} e^{\lambda_{-m}^j \hat{a}^\dagger} |0\rangle \otimes \sum_{\ell=-j}^j U_{m\ell}^t |j, \ell\rangle \\ &= |\lambda_{-m}^j\rangle \otimes \sum_{\ell=-j}^j U_{m\ell}^t |j, \ell\rangle \quad m = -j, \dots, j, \end{aligned} \quad (\text{A.42})$$

where $|\lambda_{-m}^j\rangle, m = -1, \dots, j$ are the canonical coherent states of the harmonic oscillator system verifying $\hat{a} |\lambda_{-m}^j\rangle = \lambda_{-m}^j |\lambda_{-m}^j\rangle, m = -j, \dots, j$, and according with the normality condition imposed to M , that implies the unitarity of U , these states verify

$${}^j_\ell\langle\psi|\psi\rangle_m^j = \delta_{\ell,m}. \quad (\text{A.43})$$

Thus, the general state (A.41) can be written in the normalized form

$$|\Psi\rangle^j = N^{-\frac{1}{2}} \sum_{m=-j}^j \tilde{\varphi}_m^j(0) |\psi\rangle_m^j = N^{-\frac{1}{2}} \sum_{m=-j}^j \tilde{\varphi}_m^j(0) |\lambda_{-m}^j\rangle \otimes \sum_{\ell=-j}^j U_{m\ell}^t |j, \ell\rangle, \quad (\text{A.44})$$

where

$$N = \sum_{m=-j}^j \|\tilde{\varphi}_m^j(0)\|^2. \quad (\text{A.45})$$

For comparative purposes of these states structure with that of the vector algebra eigenstates with eigenvalues on the matrix domain settled in this article, it is convenient to rewrite the general solution (A.44) in the matrix form, that is

$$\begin{aligned} |\Psi\rangle^j &= N^{-1/2} \\ &\times \left(\tilde{\varphi}_{-j}^j(0) e^{\lambda_{-j}^j \hat{a}^\dagger} \quad \tilde{\varphi}_{-j+1}^j(0) e^{\lambda_{-j+1}^j \hat{a}^\dagger} \quad \dots \quad \tilde{\varphi}_{j-1}^j(0) e^{\lambda_{j-1}^j \hat{a}^\dagger} \quad \tilde{\varphi}_j^j(0) e^{\lambda_j^j \hat{a}^\dagger} \right) U^t \begin{pmatrix} |0; j, -j\rangle \\ |0; j, -j + 1\rangle \\ \vdots \\ |0; j, j - 1\rangle \\ |0; j, j\rangle \end{pmatrix}. \end{aligned} \quad (\text{A.46})$$

Equation (A.44) gives us the eigenstates of the operator $[\hat{a} + \beta_- \hat{J}_+ + \beta_+ \hat{J}_- + \beta_3 \hat{J}_3]$ when M is normal. In fact, the process for computing the $h(1) \oplus su(2)$ algebra eigenstates when $b \neq 0$ without imposing this

condition to M is similar, the only difference is that in this case the passing matrix U is not unitary, which implies that the set of solutions, which are still linearly independent, are in general not orthogonal. Also, the non-unitary character of the passing matrix makes it more difficult to find a simple general expression for the normalization constants.

The passing matrix U can be built using the techniques of general linear algebra, linear differential equations or operator algebra. In appendix B we have followed this last method to explicitly construct this matrix for all fixed values of j . In fact, there we have shown that the matrix element of U are given by $U_{\ell m} = \langle j, \ell | \hat{T} | j, m \rangle$, $\ell, m = -j, \dots, j$.

A.2 Case $b=0$

When $b = 0$, all the eigenvalues of the M matrix are equal. To obtain the $h(1) \oplus su(2)$ algebra eigenstates in this case we had better integrate systematically, function by function, the linear differential equation system (A.7). We distinguish here three cases, that is to say, when $\beta_- = \beta_3 = 0$, and $\beta_+ \neq 0$, when $\beta_+ = \beta_3 = 0$, and $\beta_- \neq 0$, or when $\beta_- \neq 0, \beta_3 \neq 0$ and $\beta_+ \neq 0$, but $\frac{\beta_3}{2\beta_+} = -\frac{2\beta_-}{\beta_3}$.

A.2.1 Case $\beta_- = \beta_3 = 0$ and $\beta_+ \neq 0$

In the special case where $b = 0$, with $\beta_- = \beta_3 = 0$ and $\beta_+ \neq 0$, the matrix M in A.8) becomes triangular superior and the corresponding linear differential equation system (A.7) can be integrated systematically row by row, from bottom to up or from up to bottom. As, in this case, all diagonal elements of M are equal to β , we can try a solution of the type $\psi_m^j(\zeta) = e^{\beta\zeta} \varphi_m^j(\zeta)$, $m = -j, \dots, j$. Inserting these functions in equation (A.7) and simplifying the expressions we get a simpler system of linear differential equations. For example, starting from bottom to up, we deduce

$$\frac{d}{d\zeta} \varphi_j^j(\zeta) = 0, \quad \text{then} \quad \varphi_j^j(\zeta) = \tilde{\varphi}_j^j(0), \quad (\text{A.47})$$

where $\tilde{\varphi}_j^j(0)$ is an integration constant. Continuing the process, we find

$$\frac{d}{d\zeta} \varphi_{j-1}^j(\zeta) = -\sqrt{(2j)!} \beta_+ \varphi_j^j(\zeta), \quad (\text{A.48})$$

then inserting in this equation the newly obtained value of $\varphi_j^j(\zeta)$ and integrating again we get

$$\varphi_{j-1}^j(\zeta) = \varphi_{j-1}^j(0) - \sqrt{(2j)!} \zeta \beta_+ \varphi_j^j(0), \quad (\text{A.49})$$

where $\tilde{\varphi}_j^j(0)$ is a new integration constant. Continuing with the process, we can show that the k th integration leads to

$$\varphi_{j-k}^j(\zeta) = \sum_{n=0}^k (-1)^n \sqrt{\frac{(2j-k+n)!(k!)}{(2j-k)!(k-n)!}} \frac{(\zeta \beta_+)^n}{n!} \tilde{\varphi}_{j-k+n}^j(0), \quad (\text{A.50})$$

where $\tilde{\varphi}_{j-k+n}^j(0)$ are the corresponding integration constants. Let us recall that these functions are the component of the state representing the general solution of the linear differential equation system (A.7), this latter then writes

$$|\Psi(\zeta)\rangle^j = \sum_{k=0}^{2j} \psi_{j-k}^j(\zeta) \otimes |j, j-k\rangle = \sum_{k=0}^{2j} e^{\beta\zeta} \varphi_{j-k}^j(\zeta) \otimes |j, j-k\rangle, \quad (\text{A.51})$$

or more explicitly

$$|\Psi(\zeta)\rangle^j = \sum_{k=0}^{2j} \sum_{n=0}^k (-1)^n \sqrt{\frac{(2j-k+n)!(k!)}{(2j-k)!(k-n)!}} e^{\beta\zeta} \frac{(\zeta \beta_+)^n}{n!} \tilde{\varphi}_{j-k+n}^j(0) \otimes |j, j-k\rangle. \quad (\text{A.52})$$

Interchanging the k, n order of summation and then defining a new index m in place of k , $m = j + n - k$, and again, interchanging the n, m order of summation we get the same state but now factorized according to the integration constants, that is,

$$|\Psi(\zeta)\rangle^j = \sum_{m=-j}^j \tilde{\varphi}_m^j(0) \left[\sqrt{\frac{(j+m)!}{(j-m)!}} \sum_{n=0}^{j+m} (-1)^n \sqrt{\frac{(j+n-m)!}{(j+m-n)!}} e^{\beta\zeta} \frac{(\zeta\beta_+)^n}{n!} \otimes |j, m-n\rangle \right], \quad (\text{A.53})$$

from where we can extract the $2j+1$ linearly independent states

$$|\psi(\zeta)\rangle_m^j = \sqrt{\frac{(j+m)!}{(j-m)!}} \sum_{n=0}^{j+m} (-1)^n \sqrt{\frac{(j+n-m)!}{(j+m-n)!}} e^{\beta\zeta} \frac{(\zeta\beta_+)^n}{n!} \otimes |j, m-n\rangle, \quad m = -j, \dots, j. \quad (\text{A.54})$$

Finally, returning to the Fock space representation, we get the $2j+1$ normalized linearly independent states that verify the eigenvalue equation (A.3) for this choice of parameters:

$$|\psi[\beta, \beta_+]\rangle_m^j = \frac{\sum_{n=0}^{j+m} (-1)^n \sqrt{\frac{(j+n-m)!}{(j+m-n)!}} \frac{(\hat{a}^\dagger \beta_+)^n}{n!} |\beta\rangle \otimes |j, m-n\rangle}{\left[\sum_{n=0}^{j+m} \frac{(j+n-m)!}{(j+m-n)!} \frac{\|\beta_+\|^{2n}}{n!} \sum_{k=0}^n \binom{n}{k} \frac{\|\beta\|^{2k}}{k!} \right]^{\frac{1}{2}}}, \quad m = -j, \dots, j. \quad (\text{A.55})$$

These states are not orthogonal to each other, they verify the relation

$${}_\ell^j \langle \psi[\beta, \beta_+] | \psi[\beta, \beta_+] \rangle_m^j = \frac{(-\beta^* \beta_+)^{m-\ell} \sum_{n=0}^{j+m} \frac{(j+n-m)!}{(j+m-n)!} \frac{\|\beta_+\|^{2(n+\ell-m)}}{(n+\ell-m)!} \sum_{k=0}^{n+\ell-m} \binom{n+\ell-m}{k} \frac{\|\beta\|^{2k}}{(m-\ell+k)!}}{\left[\sum_{n=0}^{j+\ell} \frac{(j+n-\ell)!}{(j+\ell-n)!} \frac{\|\beta_+\|^{2n}}{n!} \sum_{k=0}^n \binom{n}{k} \frac{\|\beta\|^{2k}}{k!} \right]^{\frac{1}{2}} \left[\sum_{n=0}^{j+m} \frac{(j+n-m)!}{(j+m-n)!} \frac{\|\beta_+\|^{2n}}{n!} \sum_{k=0}^n \binom{n}{k} \frac{\|\beta\|^{2k}}{k!} \right]^{\frac{1}{2}}}, \quad (\text{A.56})$$

where $\ell \leq m$, and when $\ell \geq m$, we only take the conjugate of this expression and then we interchange m with ℓ .

Finally, the general solution of (A.3) in this case is given by

$$|\Psi[\beta, \beta_+]\rangle^j = \sum_{m=-j}^j \tilde{\varphi}_m^j(0) |\psi[\beta, \beta_+]\rangle_m^j, \quad (\text{A.57})$$

with $|\psi[\beta, \beta_+]\rangle_m^j$, $m = -j, \dots, j$, being the normalized states (A.55). We note that by using the relation $\hat{D}^\dagger(\beta) \hat{a}^\dagger \hat{D}(\beta) = \hat{a}^\dagger + \beta^*$, where $\hat{D}(\beta) = \exp(\beta \hat{a}^\dagger - \beta^* \hat{a})$ is the displacement operator, these states can be written in the form

$$|\psi[\beta, \beta_+]\rangle_m^j = \hat{D}(\beta) \frac{\sum_{n=0}^{j+m} (-1)^n \sqrt{\frac{(j+n-m)!}{(j+m-n)!}} \frac{(\hat{a}^\dagger + \beta^*)^n \beta_+^n}{n!} |0\rangle \otimes |j, m-n\rangle}{\left[\sum_{n=0}^{j+m} \frac{(j+n-m)!}{(j+m-n)!} \frac{\|\beta_+\|^{2n}}{n!} \sum_{k=0}^n \binom{n}{k} \frac{\|\beta\|^{2k}}{k!} \right]^{\frac{1}{2}}} = \hat{D}(\beta) |\tilde{\psi}[\beta, \beta_+]\rangle_m^j, \quad (\text{A.58})$$

where $m = -j, \dots, j$, with the normalized states $|\tilde{\psi}[\beta, \beta_+]\rangle_m^j$ given explicitly by

$$|\tilde{\psi}[\beta, \beta_+]\rangle_m^j = \frac{\sum_{n=0}^{j+m} (-1)^n \sqrt{\frac{(j+n-m)!}{(j+m-n)!}} \frac{\beta_+^n}{n!} \sum_{k=0}^n \binom{n}{k} (\beta^*)^k \sqrt{(n-k)!} |n-k\rangle \otimes |j, m-n\rangle}{\left[\sum_{n=0}^{j+m} \frac{(j+n-m)!}{(j+m-n)!} \frac{\|\beta_+\|^{2n}}{n!} \sum_{k=0}^n \binom{n}{k} \frac{\|\beta\|^{2k}}{k!} \right]^{\frac{1}{2}}}, \quad m = -j, \dots, j, \quad (\text{A.59})$$

or in a more compact form by

$$|\tilde{\psi}[\beta, \beta_+]\rangle_m^j = \frac{\exp[-(\hat{a}^\dagger + \beta^*) \beta_+ \hat{J}_-] |0\rangle \otimes |j, m\rangle}{\sqrt{\tilde{\mathcal{N}}_m^j[\beta, \beta_+]}}}, \quad m = -j, \dots, j, \quad (\text{A.60})$$

where

$$\tilde{\mathcal{N}}_m^j[\beta, \beta_+] = \frac{(j+m)!}{(j-m)!} \left[\sum_{n=0}^{j+m} \frac{(j+n-m)!}{(j+m-n)!} \frac{\|\beta_+\|^{2n}}{n!} \sum_{k=0}^n \binom{n}{k} \frac{\|\beta\|^{2k}}{k!} \right]. \quad (\text{A.61})$$

A.2.2 Case $\beta_+ = \beta_3 = 0$ but $\beta_- \neq 0$,

In the case $\beta_+ = \beta_3 = 0$ but $\beta_- \neq 0$, the process of obtaining the solution of (A.7) is analogous to the one followed above. It is not necessary to repeat it here, it is better to adapt the equation (A.55) to obtain the solution. Indeed, by changing in this latter m by $-m$ on the top of the summation symbol and in the coefficients, n by $-n$ in the $su(2)$ basis states and β_+ by β_- , we get

$$|\psi[\beta, \beta_-]\rangle_m^j = \frac{\sum_{n=0}^{j-m} (-1)^n \sqrt{\frac{(j+n+m)!}{(j-m-n)!}} \frac{(\hat{a}^\dagger \beta_-)^n}{n!} |\beta\rangle \otimes |j, m+n\rangle}{\left[\sum_{n=0}^{j-m} \frac{(j+n+m)!}{(j-m-n)!} \frac{\|\beta_-\|^{2n}}{n!} \sum_{k=0}^n \binom{n}{k} \frac{\|\beta\|^{2k}}{k!} \right]^{\frac{1}{2}}} = \hat{D}(\beta) |\tilde{\psi}[\beta, \beta_-]\rangle_m^j, \quad m = -j, \dots, j, \quad (\text{A.62})$$

where the normalized states $|\tilde{\psi}[\beta, \beta_-]\rangle_m^j$ are given by

$$|\tilde{\psi}[\beta, \beta_-]\rangle_m^j = \frac{\exp[-(\hat{a}^\dagger + \beta_-^*)\beta_- \hat{J}_+] |0\rangle \otimes |j, m\rangle}{\sqrt{\tilde{\mathcal{N}}_m^j[\beta, \beta_+]}}}, \quad m = -j, \dots, j, \quad (\text{A.63})$$

where

$$\tilde{\mathcal{N}}_m^j[\beta, \beta_-] = \frac{(j-m)!}{(j+m)!} \left[\sum_{n=0}^{j-m} \frac{(j+n+m)!}{(j-m-n)!} \frac{\|\beta_-\|^{2n}}{n!} \sum_{k=0}^n \binom{n}{k} \frac{\|\beta\|^{2k}}{k!} \right]. \quad (\text{A.64})$$

Hence, in this case, the general solution of (A.3) is given by

$$|\Psi[\beta, \beta_-]\rangle^j = \sum_{m=-j}^j \tilde{\varphi}_m^j(0) |\psi[\beta, \beta_-]\rangle_m^j. \quad (\text{A.65})$$

A.2.3 Case $\beta_+ \neq 0, \beta_- \neq 0$ and $\beta_3 \neq 0$ but $\frac{\beta_3}{2\beta_+} = -\frac{2\beta_-}{\beta_3}$

When $\beta_+ \neq 0, \beta_- \neq 0$ and $\beta_3 \neq 0$, and $\frac{\beta_3}{2\beta_+} = -\frac{2\beta_-}{\beta_3}$, the parameter $b = 0$, i.e., matrix M in A.8) has again $2j+1$ repeated eigenvalues equal to β . Then, again, the differential equation system (A.7) must be integrated term by term. As in appendix B, we can first try a solution of the type $\psi_m^j(\zeta) = \exp(\beta\zeta) \varphi_m^j(\zeta)$, $m = -j, \dots, j$, and then manipulate the equations to find an isolated ordinary differential equation of $2j+1$ order for $\varphi_{-j}^j(\zeta)$, that is, $\prod_{m=-j}^j \left(\frac{d}{d\zeta} + j\beta_3 \right) \varphi_{-j}^j(\zeta) = 0$. The solution of this latter is given by $\varphi_{-j}^j(\zeta) = \exp(-j\beta_3\zeta) \sum_{q=0}^{2j} A_q \zeta^q$, where A_q , $q = 0, \dots, 2j$, are integration constants. Finally, reinserting this last solution into (A.7), integrating interactively function by function and factorizing the resulting expressions in terms of the integration constants A_q , we get the general solution

$$|\Psi(\zeta)\rangle^j = \sum_{q=0}^{2j} A_q \sum_{k=0}^q (-1)^k \binom{q}{k} \frac{(2j-k)!}{(2j)!} \times \exp(\beta\zeta) \zeta^{q-k} \left(\frac{1}{\beta_+} \right)^k \otimes \left\{ \frac{d^k}{d\vartheta^k} \left[\sum_{r=0}^{2j} \sqrt{\binom{2j}{r}} \vartheta^r |j, -j+r\rangle \right]_{\vartheta = \frac{\beta_3}{2\beta_+} = -\frac{2\beta_-}{\beta_3}} \right\}, \quad (\text{A.66})$$

which after some manipulations and redefinition of the integration constants takes the form

$$|\Psi(\zeta)\rangle^j = \frac{1}{\sqrt{\mathcal{N}^j}} \sum_{m=-j}^j \tilde{\varphi}_m^j(0) \sum_{n=0}^{j+m} (-1)^n \frac{(j+n-m)!}{(j+m-n)!} \times e^{\zeta\beta} \frac{(\zeta\beta_+)^n}{n!} \otimes \sum_{\ell=0}^{j+n-m} \sqrt{\frac{(j+m-n+\ell)!}{(j+n-m-\ell)!}} \frac{\vartheta^\ell}{\ell!} |j, m-n+\ell\rangle, \quad (\text{A.67})$$

where $\vartheta = \frac{\beta_3}{2\beta_+} = -\frac{2\beta_-}{\beta_3}$ and \mathcal{N}^j is a generic normalization constant. Returning to the Fock space representation we finally arrive to

$$\begin{aligned} |\Psi[\beta, \beta_+, \beta_-, \beta_3]\rangle^j &= \frac{1}{\sqrt{\mathcal{N}^j}} \sum_{m=-j}^j \tilde{\varphi}_m^j(0) \sum_{n=0}^{j+m} (-1)^n \frac{(j+n-m)!}{(j+m-n)!} \\ &\times \frac{(\hat{a}^\dagger \beta_+)^n}{n!} |\beta\rangle \otimes \sum_{\ell=0}^{j+n-m} \sqrt{\frac{(j+m-n+\ell)!}{(j+n-m-\ell)!}} \frac{\vartheta^\ell}{\ell!} |j, m-n+\ell\rangle, \end{aligned} \quad (\text{A.68})$$

This last equation can be written in the form

$$|\Psi[\beta, \beta_+, \beta_-, \beta_3]\rangle^j = \frac{1}{\sqrt{\mathcal{N}^j}} \sum_{m=-j}^j \tilde{\varphi}_m^j(0) \hat{D}(\beta) |\tilde{\psi}[\beta, \beta_+, \beta_-, \beta_3]\rangle_m^j \quad (\text{A.69})$$

where $|\tilde{\psi}[\beta, \beta_+, \beta_-, \beta_3]\rangle_m^j$, $m = -j \dots, j$, is a set of $2j+1$ normalized linearly independent states are given by

$$\begin{aligned} |\tilde{\psi}[\beta, \beta_+, \beta_-, \beta_3]\rangle_m^j &= \frac{1}{\sqrt{\tilde{\mathcal{N}}_m^j[\beta, \beta_+, \beta_-, \beta_3]}} \sqrt{\frac{(j+m)!}{(j-m)!}} \sum_{n=0}^{j+m} (-1)^n \frac{(j+n-m)!}{(j+m-n)!} \\ &\times \frac{((\hat{a}^\dagger + \beta^*)\beta_+)^n}{n!} |0\rangle \otimes \sum_{\ell=0}^{j+n-m} \sqrt{\frac{(j+m-n+\ell)!}{(j+n-m-\ell)!}} \frac{\vartheta^\ell}{\ell!} |j, m-n+\ell\rangle, \end{aligned} \quad (\text{A.70})$$

where $m = -j, \dots, j$, or

$$\begin{aligned} |\tilde{\psi}[\beta, \beta_+, \beta_-, \beta_3]\rangle_m^j &= \frac{1}{\sqrt{\tilde{\mathcal{N}}_m^j[\beta, \beta_+, \beta_-, \beta_3]}} \sum_{n=0}^{j+m} \sum_{\ell=0}^{j+n-m} \frac{(\vartheta \hat{J}_+)^{\ell}}{\ell!} \\ &\times (-1)^n \frac{((\hat{a}^\dagger + \beta^*)\beta_+)^n}{n!} |0\rangle \otimes |j, m\rangle, \quad m = -j, \dots, j, \end{aligned} \quad (\text{A.71})$$

where

$$\begin{aligned} \tilde{\mathcal{N}}_m^j[\beta, \beta_+, \beta_-, \beta_3] &= \frac{(j+m)!}{(j-m)!} \sum_{n=0}^{j+m} \sum_{\tilde{n}}^{j+m} (-1)^{(\tilde{n}-n)} \frac{(j+n-m)!(j+\tilde{n}-m)!}{(j+m-n)!(j+m-\tilde{n})!} \frac{(\beta_+^*)^{\tilde{n}} (\beta_+)^n}{\tilde{n}! n!} \\ &\times \sum_{\ell=0}^{j+n-m} \frac{(j+m-n+\ell)!}{(j+n-m-\ell)!} \frac{\|\vartheta\|^{2\ell} \vartheta^{*(\tilde{n}-n)}}{(\ell+\tilde{n}-n)!\ell!} \sum_{k=0}^{\min(\tilde{n}, n)} \binom{\tilde{n}}{k} \binom{n}{k} k! \beta^{(\tilde{n}-k)} \beta^{*(n-k)}, \end{aligned} \quad (\text{A.72})$$

where $\min(\tilde{n}, n)$ means the smaller between \tilde{n} and n .

B $su(2)$ algebra eigenstates, a useful operator

Let us recall that, in the case $\beta_- \neq 0, \beta_+ \neq 0$ and for arbitrary β_3 , such that

$$b = \sqrt{4\beta_+\beta_- + \beta_3^2} \neq 0, \quad (\text{B1})$$

in the process of computing the $su(2)$ algebra eigenstates, we have built an operator T with the following characteristics

$$\hat{T} = \exp\left(-\frac{\tilde{\theta}}{2}[e^{-i\tilde{\phi}}\hat{J}_+ - e^{i\tilde{\phi}}\hat{J}_-]\right), \quad (\text{B2})$$

where

$$\frac{\tilde{\theta}}{2} = \arctan\left(\sqrt{\frac{b-\beta_3}{b+\beta_3}}\right), \quad \text{and} \quad e^{i\tilde{\phi}} = \sqrt{\frac{\beta_+}{\beta_-}}, \quad (\text{B3})$$

so that applied on a pure state $|j, m\rangle$ of the irreducible representation j , gives as result an eigenstate of the the general operator $[\beta_-\hat{J}_+ + \beta_+\hat{J}_- + \beta_3\hat{J}_3]$ associated to the eigenvalue mb , that is

$$[\beta_-\hat{J}_+ + \beta_+\hat{J}_- + \beta_3\hat{J}_3](\hat{T}|j, m\rangle) = mb(\hat{T}|j, m\rangle). \quad (\text{B4})$$

An explicit and disentangled form of it is given by

$$\hat{T} = \exp\left(-\frac{2\beta_-}{b+\beta_3}\hat{J}_+\right) \exp\left(\log\left(\frac{2b}{b+\beta_3}\right)\hat{J}_3\right) \exp\left(\frac{2\beta_+}{b+\beta_3}\hat{J}_-\right). \quad (\text{B5})$$

Then, the action of \hat{T} on a pure state $|j, \ell\rangle$ is given explicitly by

$$\begin{aligned} \hat{T}|j, \ell\rangle &= \left(\frac{2b}{b+\beta_3}\right)^\ell \exp\left(-\frac{2\beta_-}{b+\beta_3}\hat{J}_+\right) \exp\left(\frac{\beta_+}{b}\hat{J}_-\right) |j, \ell\rangle \\ &= \left(\frac{2b}{b+\beta_3}\right)^\ell \sqrt{\frac{(j+\ell)!}{(j-\ell)!}} \\ &\times \left[\sum_{u=\ell+1}^j \left(\frac{-2\beta_-}{b+\beta_3}\right)^{(u-\ell)} \sqrt{\frac{(j+u)!}{(j-u)!}} \sum_{n=0}^{(j+\ell)} (-1)^n \left(\frac{1-\beta_3/b}{2}\right)^n \frac{(j-\ell+n)!}{n!(n+u-\ell)!(j+\ell-n)!} \right. \\ &\left. + \sum_{u=-j}^{\ell} \left(\frac{\beta_+}{b}\right)^{(\ell-u)} \sqrt{\frac{(j+u)!}{(j-u)!}} \sum_{n=0}^{(j+u)} (-1)^n \left(\frac{1-\beta_3/b}{2}\right)^n \frac{(j-u+n)!}{n!(n+\ell-u)!(j+u-n)!} \right] |j, u\rangle, \end{aligned} \quad (\text{B6})$$

which after some algebraic manipulations can be written in the form

$$\begin{aligned} \hat{T}|j, \ell\rangle &= \left(\frac{2b}{b+\beta_3}\right)^\ell \\ &\times \left[\sqrt{\frac{(j+\ell)!(j-\ell)!}{(2j)!}} \sum_{u=\ell+1}^j \sqrt{\frac{(2j)!}{(j+u)!(j-u)!}} \left(\frac{-2\beta_-}{b+\beta_3}\right)^{u-\ell} P_{j+\ell}^{-\ell+u, -\ell-u}\left(\frac{\beta_3}{b}\right) \right. \\ &\left. + \sqrt{\frac{(2j)!}{(j+\ell)!(j-\ell)!}} \sum_{u=-j}^{\ell} \sqrt{\frac{(j+u)!(j-u)!}{(2j)!}} \left(\frac{\beta_+}{b}\right)^{\ell-u} P_{j+u}^{-u+\ell, -u-\ell}\left(\frac{\beta_3}{b}\right) \right] |j, u\rangle, \end{aligned}$$

where

$$P_{j+u}^{-u+\ell, -u-\ell}\left(\frac{\beta_3}{b}\right) = \frac{(j+\ell)!}{(j-u)!} \sum_{n=0}^{(j+u)} (-1)^n \left(\frac{1-\beta_3/b}{2}\right)^n \frac{(j-u+n)!}{n!(n+\ell-u)!(j+u-n)!}. \quad (\text{B7})$$

are the Jacobi polynomials.

We are interested in the matrix elements of \hat{T} , that is

$$T_{m\ell}^j = \langle j, m | \hat{T} | j, \ell \rangle, \quad (\text{B8})$$

which are equal to

$$T_{m\ell}^j[\beta_+, \beta_-, \beta_3] = \begin{cases} \left(\frac{-2\beta_-}{b+\beta_3}\right)^m \left(\frac{-b}{\beta_-}\right)^\ell \sqrt{\frac{(j+\ell)!(j-\ell)!}{(j+m)!(j-m)!}} P_{j+\ell}^{-\ell+m, -\ell-m}\left(\frac{\beta_3}{b}\right), & \ell+1 \leq m \leq j \\ \left(\frac{2\beta_+}{b+\beta_3}\right)^\ell \left(\frac{b}{\beta_+}\right)^m \sqrt{\frac{(j+m)!(j-m)!}{(j+\ell)!(j-\ell)!}} P_{j+m}^{-m+\ell, -m-\ell}\left(\frac{\beta_3}{b}\right), & -j \leq m \leq \ell. \end{cases} \quad (\text{B9})$$

B.1 Unitary case

In the special case when $\|\beta_+\| = \|\beta_-\|$ and $\beta_3\beta_-^* - \beta_3^*\beta_+ = 0$, these matrix elements correspond to the matrix elements of a unitary matrix. Indeed, taking into account these conditions in equation (B3), we realize that the parameters $\tilde{\theta}$ and $\tilde{\phi}$ become real and then \hat{T} becomes unitary.

Now we will show that the unitary matrix T , which matrix elements are given in (B9), makes the normal matrix M given in (A.8) diagonal. Indeed, if we express the $su(2)$ algebra eigenstate $|\psi\rangle^j$ in terms of the $2j+1$ basis states spanning the j irreducible representation space in the form $|\psi\rangle^j = \sum_{m=-j}^j C_m^j |j, m\rangle$ and insert it in the equation

$$[\beta_- \hat{J}_+ + \beta_+ \hat{J}_- + \beta_3 \hat{J}_3] |\psi\rangle^j = \Gamma |\psi\rangle^j, \quad (\text{B10})$$

we can see that the algebraic linear equation system for the coefficients $C_m^j, -j \leq m \leq j$, can be written in the form

$$(\beta I - M) \begin{pmatrix} C_{-j}^j \\ C_{-j+1}^j \\ \vdots \\ C_{j-1}^j \\ C_j^j \end{pmatrix} = \Gamma \begin{pmatrix} C_{-j}^j \\ C_{-j+1}^j \\ \vdots \\ C_{j-1}^j \\ C_j^j \end{pmatrix}, \quad (\text{B11})$$

where M is given by equation (A.8). It is clear from this last equation that the unitary matrix which diagonalize $\mathcal{M} = \beta I - M$, also diagonalize M .

As $\hat{T} |j; u\rangle$, for all fixed u such that $u = -j, \dots, j$, is a normalized $su(2)$ algebra eigenstate verifying (B10), with eigenvalue $\Gamma_u^j = ub$,

$$|\psi\rangle_u^j = \sum_{\ell=-j}^j C_\ell^j |j, \ell\rangle = \hat{T} |j, u\rangle, \quad (\text{B12})$$

Projecting both sides of equation (B12) on a generic pure state $|j, \ell\rangle$ we obtain a connection between the C_ℓ^j coefficients and the matrix elements of \hat{T}

$$C_\ell^j = T_{\ell u}, \quad \ell = -j, \dots, j. \quad (\text{B13})$$

On the other hand, from (B11) we can see that the explicit form of the coefficient equation system is given by

$$\sum_{\ell=-j}^j \mathcal{M}_{m\ell} C_\ell^j = \Gamma^j C_m^j, \quad m = -j, \dots, j, \quad (\text{B14})$$

which is verified by (B13) for a given u , i.e.,

$$\sum_{\ell=-j}^j \mathcal{M}_{m\ell} T_{\ell u} = \Gamma_u^j T_{mu}, \quad m = -j, \dots, j, \quad \Gamma_u^j = ub. \quad (\text{B15})$$

Finally operating from the left with the unitary matrix T^\dagger on both sides of equation (B15) we obtain

$$\sum_{m=-j}^j \sum_{\ell=-j}^j T_{\rho m}^{\dagger} \tilde{M}_{m\ell} T_{\ell u} = \Gamma^j \sum_{m=-j}^j T_{\rho m}^{\dagger} T_{mu} = \Gamma_u^j \delta_{\rho u}, \quad (\text{B16})$$

for all chosen u , then we conclude that T diagonalize \tilde{M} , and consequently also diagonalize M .

In the case when M is not normal but diagonalizable, the same argument is valid, the only thing to do in the argumentation of the above process is to change T^{\dagger} by T^{-1} .

References

- [1] E. Schrödinger, Zum Heisenbergschen Unschärfepinzip, Sitzungberichten der Preussischen Akademie der Wissenschaften (Phys.-Math. Klasse), 19 (1932) ss. 296-323.
- [2] Klauder, John R (1960). *The action option and a Feynman quantization of spinor fields in terms of ordinary c-numbers*, Annals of Physics. Elsevier BV. 11 (2): 123–168. Bibcode:1960AnPhy..11..123K. doi:10.1016/0003-4916(60)90131-7. ISSN 0003-4916.
- [3] Glauber, Roy J. (1963-09-15). *Coherent and Incoherent States of the Radiation Field*, Physical Review. American Physical Society (APS). 131 (6): 2766–2788. Bibcode:1963PhRv..131.2766G. doi:10.1103/physrev.131.2766. ISSN 0031-899X.
- [4] A. M. Perelomov, *Coherent states for arbitrary Lie groups*, Commun. Math. Phys. 26 (1972) 222-236; Sov. Phys. Usp. 20 (1977), 703.: math-ph/0203002.
- [5] A. M. Perelomov, *Generalized Coherent States and their Applications*, Springer-Verlag, Berlin, 1986.
- [6] Gilmore, Robert (1972), *Geometry of symmetrized states*. Annals of Physics. Elsevier BV. 74 (2): 391–463. Rev. Mex. de Fisica 23 (1974), 142; J. Math. Phys. 15 (1974), 2090
- [7] R. Gilmore, *Lie Groups, Lie Algebras, and some of their Applications*, Krieger, Malabar, 1994.
- [8] D.A. Trifonov, *Completeness properties of the minimum uncertainty states*, Proceed. "Second International Workshop on Squeezed States and Uncertainty Relations". P.N. Lebedev Physics Institute, Moscow, Russia, May 25-29,1992.
- [9] D. A. Trifonov, *The uncertainty way of generalization of coherent states*, Geometry, Integrability and Quantization, Proceedings Series, 2000: 257-282 (2000). <https://doi.org/10.7546/giq-1-2000-257-282>
- [10] Gazeau, Jean Pierre; Klauder, John R., *Coherent states for systems with discrete and continuous spectrum*, Journal of Physics A: Mathematical and General. 32 (1): 123–132, 1999, *Coherent States in Quantum Physics*, Wiley-VCH, Berlin, 2009.
- [11] A. O. Barut and L. Girardello, Commun. Math. Phys. 21 (1971), 41.
- [12] C. Brif *Two-Photon Algebra Eigenstates: A Unified Approach to Squeezing* , Annals of Phys., 251:180-207,1996.
- [13] C. Brif, *SU(2) and SU(1,1) Algebra Eigenstates : A Unified Analytic Approach to Coherent and Intelligent States*, Int. J. Theor. Phys. 36:1651-1682,1997.
- [14] N. Alvarez M. and V. Hussin, *Generalized coherent and squeezed states based on the algebra $\mathfrak{h}(1) \oplus \mathfrak{su}(2)$* , J. Math. Phys. 43:2063, 2002.
- [15] K. Thirulogasanthar and S. Twareque Ali, *A class of vector coherent states defined over matrix domains*, J. Math. Phys. 44, 5070,2003.
- [16] B. Muraleetharan and K. Thirulogasanthar, *Coherent state quantization of quaternions*, J. Math. Phys. 56, 083510 (2015). arXiv:1406.0028v3 [math-ph] 7 Oct 2015.

- [17] Ali, S. Twareque; Bagarello, F. (2005). *Some physical appearances of vector coherent states and coherent states related to degenerate Hamiltonians*, Journal of Mathematical Physics. 46 (5): 053518. arXiv:quant-ph/0410151
- [18] C. Aragone and F.Zypman, *Supercoherent States*, J. Phys. A, Math. Gen., vol. **19**, 2267, 1986.
- [19] Paulo E G Assis, *Metric operators for non-Hermitian quadratic su(2) Hamiltonians*, Journal of Physics A: Mathematical and Theoretical, Volume 44, Number 26.
- [20] H. Robertson, *A general formulation of the uncertainty principle and its classical interpretation*, Phys. Rev. 35 (1930) Abstract 40, p.667.