

Extreme violation of local realism in quantum hypergraph states

Mariami Gachechiladze, Costantino Budroni, and Otfried Gühne

Naturwissenschaftlich-Technische Fakultät, Universität Siegen, Walter-Flex-Str. 3, 57068 Siegen, Germany

(Dated: September 30, 2018)

Hypergraph states form a family of multiparticle quantum states that generalizes the well-known concept of Greenberger-Horne-Zeilinger states, cluster states, and more broadly graph states. We study the nonlocal properties of quantum hypergraph states. We demonstrate that the correlations in hypergraph states can be used to derive various types of nonlocality proofs, including Hardy-type arguments and Bell inequalities for genuine multiparticle nonlocality. Moreover, we show that hypergraph states allow for an exponentially increasing violation of local realism which is robust against loss of particles. Our results suggest that certain classes of hypergraph states are novel resources for quantum metrology and measurement-based quantum computation.

PACS numbers: 03.65.Ta, 03.65.Ud

Introduction.— Multiparticle entanglement is central for discussions about the foundations of quantum mechanics, protocols in quantum information processing, and experiments in quantum optics. Its characterization has, however, turned out to be difficult. One problem hindering the exploration of multiparticle entanglement is the exponentially increasing dimension of the Hilbert space. This implies that making statements about general quantum states is difficult. So, one has to concentrate on families of multiparticle states with an easier-to-handle description. In fact, symmetries and other kinds of simplifications seem to be essential for a state to be a useful resource. Random states can often be shown to be highly entangled, but useless for quantum information processing [1].

An outstanding class of useful multiparticle quantum states is given by the family of graph states [2], which includes the Greenberger-Horne-Zeilinger (GHZ) states and the cluster states as prominent examples. Physically, these states have turned out to be relevant resources for quantum metrology, quantum error correction, or measurement-based quantum computation [2]. Mathematically, these states are elegantly given by graphs, which describe the correlations and also a possible interaction structure leading to the graph state. In addition, graph states can be defined via a so-called stabilizer formalism: A graph state is the unique eigenstate of a set of commuting observables, which are local in the sense that they are tensor products of Pauli measurements. These stabilizer observables are important for easily computing correlations leading to violations of Bell inequalities [3, 4], as well as designing simple schemes to characterize graph states experimentally [5].

Recently, this family of states has been generalized to hypergraph states [6–11]. These states have been recognized as special cases of the so-called locally maximally entangleable (LME) states [6]. Mathematically, they are described by hypergraphs, a generalization of graphs, where a single hyperedge can connect more than two vertices. They can also be described by a stabilizer




FIG. 1: Examples of hypergraphs. (a) A simple hypergraph with three vertices and a single edge $e = \{1, 2, 3\}$ connecting all three vertices. The corresponding hypergraph state $|H_3\rangle = C_{123}|+\rangle^{\otimes 3} = (|000\rangle + |001\rangle + \dots + |110\rangle - |111\rangle)/\sqrt{8}$ is discussed in detail in the text. (b) This hypergraph contains only two-edges, so it is an ordinary graph. The state corresponding to this fully connected graph is the five-qubit GHZ state. (c) The fully connected three-uniform hypergraph represents a state that can be seen as a generalization of the GHZ state.

formalism, but this time, the stabilizing operators are not local. So far, hypergraph states have turned out to play a role for search algorithms in quantum computing [12], quantum fingerprinting protocols [13], and they have been shown to be complex enough to serve as witnesses in all QMA problems [14]. They have recently been investigated in condensed matter physics as ground states of spin models with interesting topological properties [15, 16]. In addition, equivalence classes and further entanglement properties of hypergraph states have been studied [9].

In this paper we show that hypergraph states violate local realism in an extreme manner, but in a way that is robust against loss of particles. We demonstrate that this leads to applications of these states in quantum metrology and quantum computation. We see that the stabilizer formalism describing hypergraph states, despite being nonlocal, can be used to derive Hardy-type nonlocality arguments [17], Bell inequalities for genuine multiparticle entanglement [18], or a violation of local realism with a strength exponentially increasing with the number of particles. Our approach starts precisely with the properties of the stabilizer, in order to identify the useful

correlations provided by quantum mechanics. This is in contrast to previous approaches that were either too general, e.g. Bell inequalities for general multiparticle states [19, 20], or too restricted, considering only few specific examples of hypergraph states and leading to non robust criteria [9]. The violation of local realism is the key to further applications in information processing: Indeed, it is well known that violation of a Bell inequality leads to advantages, in distributed computation scenarios [21, 22]. In addition, we will explicitly show that certain classes of hypergraph states lead to Heisenberg scaling in quantum metrology and advantages in measurement-based quantum computation.

Hypergraph states.— A hypergraph $H = (V, E)$ consists of a set of vertices $V = \{1, \dots, N\}$ and a set of hyperedges $E \subset 2^V$, with 2^V the power set of V . While for graphs edges connect only two vertices, hyperedges can connect more than two vertices; examples of hypergraphs are depicted in Fig. 1. For any hypergraph we define the corresponding hypergraph state $|H\rangle$ as the N -qubit state

$$|H\rangle = \prod_{e \in E} C_e |+\rangle^{\otimes N}, \quad (1)$$

where $|+\rangle = (|0\rangle + |1\rangle)/\sqrt{2}$, e is a hyperedge and C_e is a multi-qubit phase gate acting on the Hilbert space associated with the vertices $v \in e$, given by the matrix $C_e = \mathbb{1} - 2|1\dots 1\rangle\langle 1\dots 1|$. The first nontrivial hypergraph state consists of $N = 3$ qubits connected by a single hyperedge [see Fig. 1(a)]. Hypergraph states have been recognized as special cases of LME states, generated via a fixed interaction phase of $\phi = \pi$ [6].

Alternatively, we can define the hypergraph states using a stabilizer formalism [9]. For each qubit i we define the operator

$$g_i = X_i \bigotimes_{e \in E} C_{e \setminus \{i\}}. \quad (2)$$

Here and in what follows, we denote by X_i and Z_i the Pauli matrices, acting on i^{th} qubit. The hypergraph state can be defined as the unique eigenstate for all of them, $g_i |H\rangle = |H\rangle$ with the eigenvalue $+1$. Consequently, the hypergraph state is an eigenstate of the entire stabilizer, i.e., the commutative group formed by all the products of the g_i . It should be noted that the g_i are, in general, non-local operators, as they are not tensor-products of operators acting on single parties. We say that a hyperedge has *cardinality* k , if it circumscribes k vertices and a hypergraph is *k-uniform*, if all edges are k -edges. Finally, note that different hypergraphs may lead to equivalent hypergraph states, in the sense that the two states can be converted into one other by a local basis change. For small numbers of qubits, the resulting equivalence classes have been identified [9].

Local correlations from the nonlocal stabilizer.— The key observation for the construction of our nonlocality

arguments is that the stabilizer of hypergraph states, despite being nonlocal, predicts perfect correlations for some local measurements. In the following, we explain this for the three-qubit hypergraph state $|H_3\rangle$, but the method is general. The stabilizing operators for the three-qubit hypergraph state are

$$g_1 = X_1 \otimes C_{23}, \quad g_2 = X_2 \otimes C_{13}, \quad g_3 = X_3 \otimes C_{12}. \quad (3)$$

We can expand the controlled phase gate C_{ij} on two qubits, leading to

$$g_1 = X_1 \otimes (|00\rangle\langle 00| + |01\rangle\langle 01| + |10\rangle\langle 10| - |11\rangle\langle 11|) \quad (4)$$

and similar expressions for the other g_i . Since $g_1 |H_3\rangle = +|H_3\rangle$, the outcomes for X measurements on the first qubit and Z measurements on the second and third qubits are correlated: if one measures ”+” on the first qubit, then the other two parties cannot both measure ”-” in Z direction, as this would produce -1 as the overall eigenvalue. So, we extract the first correlation from the stabilizer formalism:

$$P(+ - - |XZZ) = 0. \quad (5)$$

The l.h.s of Eq. (5) denotes the probability of measuring $+ - -$ in XZZ on the qubit 1, 2, and 3, respectively. Similarly, it follows that if one measures ”-” in X direction on the first qubit, then the other parties, both have to measure ”-” in Z direction. So we have:

$$P(- + + |XZZ) + P(- + - |XZZ) + P(- - + |XZZ) = 0, \quad (6)$$

which implies, of course, that each of the probabilities is zero. Since the three-qubit hypergraph state is symmetric, the same correlations for measuring X on other qubits can be obtained by considering g_2 and g_3 , leading to permutations of correlations in Eq. (5, 6).

The three-qubit hypergraph state $|H_3\rangle$.— We start with the discussion of fully local hidden variable (HV) models. Such models assign for any value of the HV λ results to all measurements of the parties in a local manner, meaning that the probabilities for a given HV factorize. If we denote by r_i the result and by s_i the measurement setting on the i^{th} particle, respectively, then the probabilities coming from local models are of the form

$$\begin{aligned} P(r_1, r_2, r_3 | s_1, s_2, s_3) &= \\ &= \int d\lambda p(\lambda) \chi^A(r_1 | s_1, \lambda) \chi^B(r_2 | s_2, \lambda) \chi^C(r_3 | s_3, \lambda). \end{aligned} \quad (7)$$

For probabilities of this form, it is well known that it suffices to consider models which are, for a given λ , deterministic. This means that χ^i takes only the values 0 or 1, and there is only a finite set of χ^i to consider.

Observation 1. *If a fully local hidden variable model satisfies the conditions from Eq. (5, 6) and their symmetric correlations coming from the permutations, then*

it must fulfill

$$P(+--|XXX) + P(-+-|XXX) + P(--+|XXX) = 0. \quad (8)$$

The proof of this statement is done by exhausting all possible local deterministic assignments.

In contrast, for $|H_3\rangle$ we have

$$P(+--|XXX) = \frac{1}{16} \quad (9)$$

and the same holds for the permutations of the qubits. The above is a so-called Hardy argument [17], namely, a set of joint probabilities equal to 0 or, equivalently, logical implications that together implies that some other probability is equal to zero.

Our method shows how the correlations of the nonlocal stabilizer can be used for Hardy-type arguments. We recall that Hardy-type arguments have been obtained for all permutation-symmetric states [23, 24]. However, they involved different settings and have no direct connection with the stabilizer formalism, making a generalization complicated. In contrast, we will see that our measurements can even be used to prove genuine multiparticle nonlocality of the hypergraph state. First, we translate the Hardy-type argument into a Bell inequality:

Remark 2. *Putting together all the null terms derived from the stabilizer formalism and subtracting the terms causing a Hardy-type argument, we obtain the Bell inequality*

$$\begin{aligned} \langle \mathcal{B}_3^{(1)} \rangle &= [P(+--|XZZ) + P(-++|XZZ) \\ &+ P(-+-|XZZ) + P(--+|XZZ) + \text{permutat.}] \\ &- [P(+--|XXX) + \text{permutations}] \geq 0, \quad (10) \end{aligned}$$

where the permutations include all distinct terms that are obtained by permuting the qubits. The three-uniform hypergraph state violates the inequality (10) with the value of $\langle \mathcal{B}_3^{(1)} \rangle = -3/16$.

This Bell inequality follows from the Hardy argument: If a deterministic local model predicts one of the results with the minus signs, it also has to predict at least one of the results corresponding to the terms with a plus sign, otherwise it contradicts with the Hardy argument. In addition, all the terms with a minus sign are exclusive, so a deterministic LHV model can predict only one of them.

The Hardy-type argument and the Bell inequality can be generalized to a higher number of qubits, if we consider N -qubit hypergraphs with the single hyperedge having a cardinality N :

Observation 3. *Consider the N -qubit hypergraph state with a single hyperedge of cardinality N . Then, all the correlations coming from the stabilizer [as generalizations of Eqs. (5,6)] imply that for any possible set of results $\{r_i\}$ where one $r_{i_1} = +1$ and two $r_{i_2} = r_{i_3} = -1$ one has*

$$P(r_1, r_2, \dots, r_N | X_1 X_2 \dots X_N) = 0. \quad (11)$$

For the hypergraph state, however, this probability equals $1/2^{(2^N-2)}$. This Hardy-type argument leads to a Bell inequality as in Eq. (10) which is violated by the state with a value of $-(2^N - N - 2)/2^{(2^N-2)}$.

Clearly, the violation of the Bell inequality is not strong, as it does not increase with the number of particles. Nevertheless, Observation 3 shows that the nonlocal stabilizer formalism allows one to easily obtain nonlocality proofs. In fact, one can directly derive similar arguments for other hypergraph states (e.g. states with one hyperedge of cardinality N and one further arbitrary hyperedge), these results will be presented elsewhere. Note that these states are not symmetric, so the results of Refs. [23, 24] do not apply.

So far, we only considered fully local models, where for a given HV all the probabilities factorise. Now we go beyond this restricted type of models to the so-called hybrid models [18]. We consider a bipartition of the three particles, say $A|BC$, and consider a model of the type $P(r_1, r_2, r_3 | s_1, s_2, s_3) = \int d\lambda p(\lambda) \chi^A(r_1 | s_1, \lambda) \chi^{BC}(r_2, r_3 | s_2, s_3, \lambda)$. Here, Alice is separated from the rest, but χ^{BC} may contain correlations, e.g., coming from an entangled state between B and C . In order to be physically reasonable, however, we still request χ^{BC} not to allow instantaneous signaling.

This kind of models, even if different bipartitions are mixed, cannot explain the correlations of the hypergraph state, meaning that the hypergraph state is genuine multiparticle nonlocal. First, one can see by direct inspection that the stabilizer conditions from Eqs. (5, 6) are not compatible with the hypergraph correlations $P(--+|XXX) = 1/16$ and $P(--+|ZZZ) = 1/8$. Contrary to the correlations in Eq. (9) these are symmetric, and allow the construction of a Bell-Svetlichny inequality [18] valid for all the different bipartitions:

Observation 4. *Putting all the terms from the hypergraph stabilizer formalism and the correlations $P(--+|XXX)$ and $P(--+|ZZZ)$ together, we obtain the following Bell-Svetlichny inequality for genuine multiparticle nonlocality,*

$$\begin{aligned} \langle \mathcal{B}_3^{(2)} \rangle &= [P(+--|XZZ) + P(-++|XZZ) \\ &+ P(-+-|XZZ) + P(--+|XZZ) + \text{permutat.}] \\ &+ P(--+|XXX) - P(--+|ZZZ) \geq 0, \quad (12) \end{aligned}$$

which is violated by the state $|H_3\rangle$ with $\langle \mathcal{B}_3^{(2)} \rangle = -1/16$.

The proof is done by an exhaustive assignments of nonsignaling and local models.

To investigate the noise tolerance of Ineq. (12), we consider states of the type $\rho = (1-\varepsilon)|H\rangle\langle H| + \varepsilon\mathbb{1}/8$ and ask how much noise can be added, while the inequality is still violated. The white noise tolerance of the Ineq. (12) is $\varepsilon = 1/13 \approx 7.69\%$ and is optimal in the sense that for larger values of ε a hybrid model can be found which explains all possible measurements of X and Z (within numerical precision). The existence of such a model can

be shown by linear programming (see Appendix A [25]). With the same method we can also prove that the state becomes fully local with respect to X and Z measurements for $\varepsilon \geq 2/3 \approx 66.6\%$.

Three uniform hypergraph states.— Let us extend our analysis to hypergraph states with a larger number of particles. Here, it is interesting to ask whether the violation of Bell inequalities increases exponentially with the number of parties. Such a behaviour has previously been observed only for GHZ states [3] and some cluster states [4].

GHZ states are described by fully connected graphs (see Fig. 1), i.e., fully connected two-uniform hypergraph states. It is thus natural to start with fully connected three-uniform hypergraph states. First, we observe that for such states on N qubits and for even m with $1 < m < N$

$$\langle \underbrace{X \dots X}_m Z \dots Z \rangle = \begin{cases} +\frac{1}{2} & \text{if } m = 2 \pmod{4}, \\ -\frac{1}{2} & \text{if } m = 0 \pmod{4}. \end{cases} \quad (13)$$

Moreover, if $m = N$, then the correlations are given by

$$\langle \underbrace{XX \dots XX}_N \rangle = \begin{cases} 0 & \text{if } N = 0 \pmod{4}, \\ 1 & \text{if } N = 2 \pmod{4}. \end{cases} \quad (14)$$

Finally, we always have $\langle ZZ \dots ZZ \rangle = 0$ (see Appendix B for details [25]).

We then consider the following Bell operator

$$\mathcal{B}_N = -[AAA \dots AA] + [BBA \dots A + \text{permutat.}] - [BBBB \dots A + \text{permutat.}] + [\dots] - \dots \quad (15)$$

Note that this Bell operator is similar to $\langle \mathcal{B}_N^M \rangle$ of the original Mermin inequality [3], but it differs in the number of B (always even) considered. Using the correlations computed above, we can state:

Observation 5. *If we fix in the Bell operator \mathcal{B}_N in Eq. (15) the measurements to be $A = Z$ and $B = X$, then the N -qubit fully-connected three-uniform hypergraph state violates the classical bound, by an amount that grows exponentially with number of qubits, namely*

$$\langle \mathcal{B}_N \rangle_C \leq 2^{\lfloor N/2 \rfloor} \quad \text{for local HV models, and} \\ \langle \mathcal{B}_N \rangle_Q \geq 2^{N-2} - \frac{1}{2} \quad \text{for the hypergraph state.} \quad (16)$$

The proof is given in Appendix C [25].

Four-uniform hypergraph states.— Finally, let us consider four-uniform complete hypergraph states. For them, the correlations of measurements as in Eq. (13) are not so simple: They are not constant, and depend on m as well as on N . Nevertheless, they can be explicitly computed, and detailed formulas are given in the Appendix D [25]. From these correlations, we can state:

Observation 6. *The N -qubit fully-connected four-uniform hypergraph state violates local realism by an*

amount that grows exponentially with number of qubits. More precisely, one can find a Mermin-like Bell operator \mathcal{B}_N such that

$$\frac{\langle \mathcal{B}_N \rangle_Q}{\langle \mathcal{B}_N \rangle_C} \underset{N \rightarrow \infty}{\sim} \frac{\left(1 + \frac{1}{\sqrt{2}}\right)^{N-1}}{\sqrt{2}^{N+3}} \approx \frac{1.20711^N}{2\sqrt{2} + 2}. \quad (17)$$

A detailed discussion is provided in Appendix E [25].

Robustness.— So far, we have shown that three- and four-uniform hypergraph states violate local realism comparable to GHZ states. A striking difference is, however, that the entanglement and Bell inequality violation of hypergraph states is robust under particle loss. This is in stark contrast to GHZ states, which become fully separable if a particle is lost. We can state:

Observation 7. *The N -qubit fully-connected four-uniform hypergraph state preserves the violation of the local realism even after loss of one particle. More precisely, for $N = 8k + 4$ we have $\langle \mathcal{B}_{N-1} \rangle_Q / \langle \mathcal{B}_N \rangle_Q \underset{N \rightarrow \infty}{\sim} 1/(\sqrt{2} + 1)$. This means that the reduced state shows the same exponential scaling of the Bell inequality violation as the original state.*

For the detailed discussions see Appendix F [25].

For three-uniform complete hypergraph states we can prove that the reduced states are highly entangled, as they violate inequalities testing for separability [26] exponentially. This violation decreases with the number of traced out qubits, but persists even if several qubits are lost. This suggests that this class of hypergraph states is also more robust than GHZ states, details can be found in Appendix G [25]. Despite the structural differences, this property resembles of the W state, which is itself less entangled but more robust than the GHZ state [31]. In addition, this may allow the lower detection efficiency in the experiments.

Discussion and conclusion.— A first application of our results is quantum metrology. In the standard scheme of quantum metrology one measures an observable M_θ and tries to determine the parameter θ which describes a phase in some basis [27, 28]. If one takes product states, one obtains a signal $\langle M_\theta \rangle \sim \cos(\theta)$ on a single particle, repeating it on N particles allows to determine θ with an accuracy $\delta\theta \sim 1/\sqrt{N}$, the so-called standard quantum limit. Using an N -qubit GHZ state, however, one observes $\langle (M_\theta)^{\otimes N} \rangle \sim \cos(N\theta)$ and this phase super-resolution allows to reach the Heisenberg limit $\delta\theta \sim 1/N$. For a general state ϱ , it has been shown that the visibility of the phase super-resolution is given by the expectation value of the Mermin-type inequality, $V = \text{Tr}(\mathcal{B}_N \varrho) / 2^{N-1}$ [28]. So, since the three-uniform hypergraph states violate this inequality with a value $\langle \mathcal{B}_N \rangle_Q \sim 2^{(N-2)}$ the visibility is $V \sim 1/2$, independently of the number of particles. This means that these states can be used for Heisenberg-limited metrology, and from our results they can be expected to have the advantage of being more robust to noise and particle losses.

The second application of exponential violation of Bell inequalities is *nonadaptive measurement based quantum computation with linear side-processing* ($NMQC_{\oplus}$) [29]. $NMQC_{\oplus}$ is a non-universal model of quantum computation where linear classical side-processing is combined with quantum measurements in a nonadaptive way, i.e., the choice of settings is independent of previous outcomes. In Ref. [29] the authors connect the expectation value of a full-correlation Bell expression [20] with the success probability of computing a Boolean function, specified as a function of the inequality coefficients, via $NMQC_{\oplus}$. In particular, the exponential violation of generalized Svetlichny inequalities [30] (equal to Mermin inequalities for even N), corresponds to a constant success probability P_{succ} of computing the pairwise AND on N bits extracted from a uniform distribution, whereas in the classical case $P_{\text{succ}} - 1/2$ decrease exponentially with N . As a consequence, the exponential violation of the full-correlation Bell expression \mathcal{B}_N can be directly related to an exponential advantage for computation tasks in the

$NMQC_{\oplus}$ framework. Moreover, in several cases, e.g., 4-uniform hypergraph states of $N = 6 \bmod 8$ qubits, also the Svetlichny inequality is violated exponentially, providing an advantage for computation of the pairwise AND discussed in Ref. [29].

In summary, we have shown that hypergraph states violate local realism in many ways. This suggests that they are interesting resources for quantum information processing, moreover, this makes the observation of hypergraph states a promising task for experimentalists. In our work, we focused only on some classes of hypergraph states, but for future research, it would be desirable to identify classes of hypergraph states which allow for an all-versus-nothing violation of local realism or which are strongly genuine multipartite nonlocal.

We thank D. Nagaj, F. Steinhoff, M. Wieśniak, and B. Yoshida for discussions. This work has been supported by the EU (Marie Curie CIG 293993/ENFOQI), the FQXi Fund (Silicon Valley Community Foundation), the DFG and the ERC.

APPENDIX A. GENUINE MULTIPARTICLE NONLOCALITY WITH LINEAR PROGRAMMING

Fixed the number of measurement settings and outcomes, probabilities arising from a hybrid local-nonsignalling model, as the one described in the main text for the splitting $A|BC$, form a polytope whose extremal points are given by combination of deterministic local assignments for the party A and extremal nonsignalling assignments, i.e., local deterministic and PR-boxes [21], for the parties BC . In order to detect genuine multipartite nonlocality, one has to consider all combinations of probabilities arising from the other local-nonsignalling splitting, namely $C|AB$ and $B|AC$. Geometrically, this corresponds to take the convex hull of the three polytopes associated with the three different splitting. Let us denote such polytopes as $\mathcal{P}_{A|BC}, \mathcal{P}_{C|AB}, \mathcal{P}_{B|AC}$ and their convex hull as \mathcal{P}_{L-NS} . By definition of convex hull, every vector $\mathbf{p} \in \mathcal{P}_{L-NS}$ can be written as a convex combination of three vectors $\mathbf{p}_{A|BC}, \mathbf{p}_{C|AB}$ and $\mathbf{p}_{B|AC}$, which, in turn, can be written as a convex combination of the vertices of the corresponding polytope.

To check whether a given point \mathbf{p} belongs to \mathcal{P}_{L-NS} it is, therefore, sufficient the description in terms of the extremal points of $\mathcal{P}_{A|BC}, \mathcal{P}_{C|AB}, \mathcal{P}_{B|AC}$. Let us denote them as $\{\mathbf{v}_i\}$. The membership problem can then be formulated as a linear program (LP) [21]

$$\begin{aligned} & \text{maximize: } \lambda \cdot \mathbf{p} - C \\ & \text{subject to: } \lambda \cdot \mathbf{v}_i - C \leq 0, \text{ for all } \mathbf{v}_i \\ & \lambda \cdot \mathbf{p} - C \leq 1. \end{aligned} \tag{18}$$

The variable of the LP are $\{\lambda, C\}$, where λ represents the coefficient of a Bell-Svetlichny inequality, detecting genuine multipartite nonlocality, and C the corresponding local-nonsignalling bound. The LP optimizes the coefficients λ to obtain the maximal value (at most $C + 1$) for the quantum probabilities, while keeping the local-nonsignaling bound C . As a consequence, the vector \mathbf{p} can be written as a convex combination of $\{\mathbf{v}_i\}$ if and only if the optimal value of the LP is 0.

The noise tolerance for $|H_3\rangle$ can then be computed by mixing it with white noise, i.e., $|H_3\rangle\langle H_3| \mapsto \varrho = (1 - \varepsilon)|H\rangle\langle H| + \varepsilon\mathbb{1}/8$, and compute for which values of ε the LP (18) gives optimal value 0. Standard numerical techniques for LP give that up to $\varepsilon \approx 1/13 \approx 7.69\%$ the probabilities for X and Z measurements cannot be explained by a hybrid local-nonsignalling model.

APPENDIX B: CORRELATIONS FOR THREE-UNIFORM HYPERGRAPH STATES

B.1. Preliminary calculations

Before starting with the actual calculations, we need to settle couple of identities and a look-up table, which we will refer to throughout the main proofs.

The first and probably the most important identity is a commutation relation between multi-qubit phase gates and Pauli X matrices [9],

$$C_e(\bigotimes_{i \in K} X_k) = (\bigotimes_{i \in K} X_k) \left(\prod_{f \in \mathcal{P}(K)} C_{e \setminus \{f\}} \right). \quad (19)$$

Here, $\mathcal{P}(K)$ denotes the power set of the index set K . Note that the product of the $C_{e \setminus \{f\}}$ may include the term C_\emptyset , which is defined to be $-\mathbb{1}$ and leads to a global sign.

Furthermore, it turns out to be useful to recall some basic facts about binomial coefficients, as they appear frequently in the following calculations.

Lemma 1. *The following equalities hold:*

$$\text{Re}[(1+i)^n] = \sum_{k=0,4,\dots}^n \binom{n}{k} - \binom{n}{k+2}, \quad (20)$$

$$\text{Im}[(1+i)^n] = \sum_{k=0,4,\dots}^n \binom{n}{k+1} - \binom{n}{k+3}. \quad (21)$$

Proof. Here we derive (20) and (21) together:

$$s := (1+i)^n = \sum_{k=0}^n \binom{n}{k} i^k = \sum_{k=0,4,\dots}^n \binom{n}{k} + i \left(\binom{n}{k+1} - \binom{n}{k+2} \right) - i \binom{n}{k+3}. \quad (22)$$

It is easy to spot that $\text{Re}[s]$ and $\text{Im}[s]$ indeed leads to the identities (20) and (21) respectively. \square

The following look-up table represents the values of (20) and (21) for different n . These values can be derived from the basic properties of complex numbers:

#	n	$\text{Re} (1+i)^n$	$\text{Im} (1+i)^n$	$\text{Re} (1+i)^n + \text{Im} (1+i)^n$	$\text{Re} (1+i)^n - \text{Im} (1+i)^n$
1.	$n = 0 \bmod 8$	$+2^{\frac{n}{2}}$	0	$+2^{\frac{n}{2}}$	$+2^{\frac{n}{2}}$
2.	$n = 1 \bmod 8$	$+2^{\frac{n-1}{2}}$	$+2^{\frac{n-1}{2}}$	$+2^{\frac{n+1}{2}}$	0
3.	$n = 2 \bmod 8$	0	$+2^{\frac{n}{2}}$	$+2^{\frac{n}{2}}$	$-2^{\frac{n}{2}}$
4.	$n = 3 \bmod 8$	$-2^{\frac{n-1}{2}}$	$+2^{\frac{n-1}{2}}$	0	$-2^{\frac{n+1}{2}}$
5.	$n = 4 \bmod 8$	$-2^{\frac{n}{2}}$	0	$-2^{\frac{n}{2}}$	$-2^{\frac{n}{2}}$
6.	$n = 5 \bmod 8$	$-2^{\frac{n-1}{2}}$	$-2^{\frac{n-1}{2}}$	$-2^{\frac{n+1}{2}}$	0
7.	$n = 6 \bmod 8$	0	$-2^{\frac{n}{2}}$	$-2^{\frac{n}{2}}$	$+2^{\frac{n}{2}}$
8.	$n = 7 \bmod 8$	$+2^{\frac{n-1}{2}}$	$-2^{\frac{n-1}{2}}$	0	$+2^{\frac{n+1}{2}}$

Table 0. Look-up table for the values of (20) and (21) .

B.2. Correlations for X and Z measurements on fully-connected three-uniform hypergraph states

Lemma 2. *Consider an arbitrary number of qubits N and the three-uniform fully-connected hypergraph (HG) states. Then, if m is even with $1 < m < N$ the following equality holds*

$$\underbrace{\langle X \dots X Z \dots Z \rangle}_m = \begin{cases} +\frac{1}{2} & \text{if } m = 2 \bmod 4, \\ -\frac{1}{2} & \text{if } m = 0 \bmod 4. \end{cases} \quad (23)$$

Proof. We can write:

$$K := \langle HG|X \dots XZ \dots Z|HG \rangle = \langle +|^{\otimes N} \left(\prod_{e \in E} C_e \right) X \dots XZ \dots Z \left(\prod_{e \in E} C_e \right) |+\rangle^{\otimes N}. \quad (24)$$

We can group all the controlled phase gates on the right hand side of the expression (24). Note that the operators C_e and X_i do not commute, but we can use the identity (19). While regrouping we count the multiplicity of each phase gate. If each phase gate appears even times, we get an identity as $C^2 = \mathbb{1}$, if not, we keep these phase gates with the multiplicity one for the further calculations.

For the purposes which will become apparent shortly, we denote the parties which measure in X direction by \otimes and ones in Z direction by \triangle , in a way that, for example, if an arbitrary phase gate acts on $XXXZZ$, it is represented as $\otimes \otimes \otimes \triangle \triangle$. Without loss of generality, we fix one phase gate C_e and consider all the possible scenarios of \otimes and \triangle it can be acting on. Since we work on three-uniform HG states, every phase gate acts on bashes of different three party systems. These parties can be either of type \otimes or \triangle and we have to consider all possible scenarios. Since we are working with symmetric states, we can sort the parties such that we have m \otimes 's followed by $(N - m)$ \triangle 's:

$$\underbrace{\otimes \dots \otimes}_m \underbrace{\triangle \dots \triangle}_{N-m} \quad (25)$$

and then we can enumerate all the scenarios of one phase gate acting on (25):

1. $C_e ZZZ$ corresponds to $\triangle \triangle \triangle$
2. $C_e XZZ$ corresponds to $\otimes \triangle \triangle$
3. $C_e XXXZ$ corresponds to $\otimes \otimes \triangle$
4. $C_e XXX$ corresponds to $\otimes \otimes \otimes$

We consider each case separately:

1. $C_e ZZZ = ZZZC_e$ as C_e and Z commute. C_e moves on the right side with the multiplicity one. To save us writing in the future, we will denote the multiplicity of the phase gate moving on the right side by $\#e$. In this particular case it is $\# \triangle \triangle \triangle = 1$. However, on the right side of the equation (24) we have a product of all three-party phase gates. Therefore, we get C_e with the multiplicity of two and $C_e^2 = \mathbb{1}$. Note that, as we have chosen an arbitrary three-qubit phase gate, the same result holds for every such phase gate. So, all three-qubit phase gates coming from the case 1, cancel out. We will see that with the same reasoning all three qubit phase gates cancel out (give an identity).

2. For $C_e XZZ$, we use the identity (19):

$$C_e XZZ = XC_e C_{\{e \setminus X\}} ZZ. \quad (26)$$

The three-qubit phase gate C_e , from (26), appears with the multiplicity one ($\# \otimes \triangle \triangle = 1$) and like in the case 1, it gives an identity when being multiplied by the same three-qubit phase gate at the right side of the expression in (24). It is more tricky to calculate the multiplicity of $C_{\{e \setminus X\}}$ ($\# \triangle \triangle$ as the \otimes part (or equivalently, X part) is removed from the set of vertices e). For this we need to fix $\triangle \triangle$ and count all the scenarios when an arbitrary C_e is reduced to $\triangle \triangle$. As we are working with the symmetric case, such scenario repeats $\binom{m}{1} = m$ times, where m is the number of parties measuring in X direction. We shortly denote this as $\# \triangle \triangle = \binom{m}{1} = m$. So, as m is an even number, $(C_{\{e \setminus X\}})^m = (C_{\triangle \triangle})^m = \mathbb{1}$.

Note that the gate $C_{\triangle \triangle}$ can only be generated from in case 2.

3. For $C_e XXXZ$, we use the identity (19):

$$C_e XXXZ = XXXC_e C_{\{e \setminus XX\}} \left[\prod_{\forall X} C_{\{e \setminus X\}} \right] Z. \quad (27)$$

The three-qubit phase gate C_e , from (26), appears with the multiplicity one ($\# \otimes \otimes \triangle = 1$); therefore, like in the two previous cases, it cancels out on the right side of the expression. A multiplicity of $C_{\{e \setminus XX\}}$ is calculated by fixing a

concrete Δ and counting all possible appearance of arbitrary \otimes . As the number of parties measuring in direction is X is m , this means that it is all combination of two parties with X measurements out of total m parties. So,

$$\#\Delta = \binom{m}{2} = \frac{m(m-1)}{2} = \begin{cases} \text{even, if } m = 0 \bmod 4 & \Rightarrow C_\Delta \text{ cancels out.} \\ \text{odd, if } m = 2 \bmod 4 & \Rightarrow C_\Delta \text{ remains.} \end{cases} \quad (28)$$

The last one from this case is the multiplicity of $C_{\{e\setminus X\}}$ or $\#\otimes\Delta$. Here we fix one qubit from m (X direction) and one from $N - m$ (Z direction) and count the number of such occurrences, when the third qubit is an arbitrary one of the type \otimes , which is exactly $\binom{m-1}{1}$. Therefore,

$$\#\otimes\Delta = \binom{m-1}{1} = m-1, \text{ which is odd, } \Rightarrow C_{\otimes\Delta} \text{ remains.} \quad (29)$$

4. For $C_e XXX$, we use the identity (19):

$$C_e XXX = XXX C_e \left[\prod_{\forall X} C_{\{e\setminus X\}} \right] \left[\prod_{\forall X} C_{\{e\setminus XX\}} \right] C_{\{ \}}. \quad (30)$$

C_e occurs once and it gives an identity with the other one from the right side like in the previous cases. The multiplicity of $C_{\{e\setminus X\}}$ is $\#\otimes\otimes$. Here we fix two parties in X direction and count the occurrence of this scenario by altering the third party, from the remaining $m-2$, in X direction. Therefore,

$$\#\otimes\otimes = \binom{m-2}{1} = m-2, \text{ which is even, } \Rightarrow C_{\otimes\otimes} \text{ cancels out.} \quad (31)$$

Similarly for $C_{\{e\setminus XX\}}$, we fix one party in X direction and count all possibilities of choosing two parties out of remaining $m-1$. Therefore,

$$\#\otimes = \binom{m-1}{2} = \frac{(m-1)(m-2)}{2} = \begin{cases} \text{odd, if } m = 0 \bmod 4 & \Rightarrow C_{\otimes} \text{ remains.} \\ \text{even if, } m = 2 \bmod 4 & \Rightarrow C_{\otimes} \text{ cancels out.} \end{cases} \quad (32)$$

At last, we consider $C_{\{ \}}$. This gate determines the global sign of the expectation value and it appears only when C_e acts on systems which are all measured in X direction. Therefore,

$$\#\{ \} = \binom{m}{3} = \frac{m(m-1)(m-2)}{2 \cdot 3}, \text{ which is even } \Rightarrow \text{ the global sign is positive.} \quad (33)$$

To go on, we need to consider two cases #1: $m = 0 \bmod 4$ and #2: $m = 2 \bmod 4$ and calculate the expectation value separately for both:

Case #1: When $m = 0 \bmod 4$, we write out all remaining phase gates and continue the derivation from equation (24):

$$\langle K \rangle := \langle + |^{\otimes N} X \dots X Z \dots Z \prod_{\forall \otimes, \forall \Delta} C_{\otimes\Delta} C_{\otimes} | + \rangle^{\otimes N}. \quad (34)$$

Using the fact that X is an eigenstate of $\langle + |$, we can get rid of all X s and then we can write C_Δ instead of Z :

$$\begin{aligned} \langle K \rangle &= \langle + |^{\otimes N} \prod_{\forall \otimes, \forall \Delta} C_{\otimes\Delta} C_{\otimes} C_\Delta | + \rangle^{\otimes N} = \frac{1}{\sqrt{2^N}} \sum_{i=00\dots 00}^{11\dots 11} \langle i | \prod_{\forall \otimes, \forall \Delta} C_{\otimes\Delta} C_{\otimes} C_\Delta \frac{1}{\sqrt{2^N}} \sum_{j=00\dots 00}^{11\dots 11} | j \rangle \\ &= \frac{1}{2^N} \left[\langle 00\dots 00 | \prod_{\forall \otimes, \forall \Delta} C_{\otimes\Delta} C_{\otimes} C_\Delta | 00\dots 00 \rangle + \dots + \langle 11\dots 11 | \prod_{\forall \otimes, \forall \Delta} C_{\otimes\Delta} C_{\otimes} C_\Delta | 11\dots 11 \rangle \right] \\ &= \frac{1}{2^N} \text{Tr} \left[\prod_{\forall \otimes, \forall \Delta} C_{\otimes\Delta} C_{\otimes} C_\Delta \right]. \end{aligned} \quad (35)$$

In (35), to get line two from the line one, note that $\prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta} C_{\otimes} C_{\Delta}$ is a diagonal matrix.

To evaluate the trace of the given diagonal matrix, we need to find the difference between the number of +1 and -1 on the diagonal. We write every row in the computational basis by enumerating it with the binary notation. For each row, we denote by α the number of 1's in binary notation appearing in the first m columns and by β , the same on the rest. For example, for $N = 7$, and $m = 4$, the basis element $|1101110\rangle$ leads to $\alpha=3$ and $\beta = 2$. Considering the phase gates in the equation (35), the expression $(-1)^s$ defines whether in the given row the diagonal element is +1 or -1, where :

$$s := \binom{\alpha}{1} \binom{\beta}{1} + \binom{\alpha}{1} + \binom{\beta}{1} = \alpha\beta + \alpha + \beta. \quad (36)$$

In s , $\binom{\alpha}{1} \binom{\beta}{1}$ denotes how many $C_{\otimes \Delta}$ acts on the row. Also, $\binom{\alpha}{1}$ determines the number of C_{\otimes} and $\binom{\beta}{1}$, number of C_{Δ} . Every time when the phase gate acts, it changes the sign of the diagonal element on the row. Therefore, we need to determine the number s :

To see whether s is even or odd, we have to consider the following cases exhaustively:

1. α is even & β is even $(-1)^s = +1$
2. α is even & β is odd $(-1)^s = -1$ \Rightarrow These two cases sum up to zero.
3. α is odd & β is even $(-1)^s = -1$
4. α is odd & β is odd $(-1)^s = -1$ \Rightarrow These two cases contribute with the negative sign.

From the cases 3 and 4, one can directly calculate the trace:

$$\langle K \rangle = \frac{1}{2^N} \left[- \sum_{\alpha=1,3,\dots}^m \binom{m}{\alpha} \sum_{\beta=0}^{N-m} \binom{N-m}{\beta} \right] = - \frac{2^{m-1} 2^{N-m}}{2^N} = -\frac{1}{2}. \quad (37)$$

So, we get that if m is divisible by 4,

$$\langle \underbrace{X \dots X}_m Z \dots Z \rangle = -\frac{1}{2}. \quad (38)$$

Case #2: We use the identical approach: when $m = 2 \bmod 4$, we write out all remaining phase gates and continue the derivation from equation (24):

$$\langle K \rangle = \langle + |^{\otimes N} X \dots X Z \dots Z \prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta} C_{\Delta} | + \rangle^{\otimes N}. \quad (39)$$

Again we use the fact that X is an eigenstate of $\langle + |$ and $Z = C_{\Delta}$. As in (40), there is already one (C_{Δ}) , they cancel. Therefore, we are left with:

$$\langle K \rangle = \langle + |^{\otimes N} \prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta} | + \rangle^{\otimes N} = \frac{1}{2^N} \text{Tr} \left[\prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta} \right]. \quad (40)$$

We need to define the sign of the diagonal element by $(-1)^s$, where

$$s = \binom{\alpha}{1} \binom{\beta}{1} = \alpha\beta. \quad (41)$$

1. α is even $(-1)^s = +1$ \Rightarrow This case contributes with the positive sign in the trace
 2. α is odd & β is even $(-1)^s = +1$
 3. α is odd & β is odd $(-1)^s = -1$ \Rightarrow These two give zero contribution together.
- As the case 2 and 3 add up to zero, we only consider the case 1:

$$\langle K \rangle = \frac{1}{2^N} \sum_{\alpha=0,2,\dots}^m \binom{m}{\alpha} \sum_{\beta=0}^{N-m} \binom{N-m}{\beta} = \frac{2^{m-1} 2^{N-m}}{2^N} = \frac{1}{2}. \quad (42)$$

So, we get that if m is NOT divisible by 4,

$$\langle \underbrace{X \dots X}_m Z \dots Z \rangle = \frac{1}{2}. \quad (43)$$

This completes the proof. \square

B.3. Correlations for X measurements on fully-connected three-uniform hypergraph states

Lemma 3. *If every party makes a measurement in X direction, then the expectations value is*

$$\langle \underbrace{XX \dots XX}_N \rangle = \begin{cases} 0 & \text{if } N = 0 \pmod{4}, \\ 1 & \text{if } N = 2 \pmod{4}. \end{cases} \quad (44)$$

Proof. In this proof we employ the notation introduced in details in the proof of the lemma 2.

$$\langle K \rangle := \langle H_3^N | XX \dots XX | H_3^N \rangle = \langle + |^{\otimes N} \left[\prod_{e \in E} C_e \right] XX \dots XX \left[\prod_{e \in E} C_e \right] | + \rangle^{\otimes N}. \quad (45)$$

We use the identity (19), to regroup the phase gates on the right hand side of the expression (45). Therefore, we count the multiplicity of the remaining phase gates:

$\# \otimes \otimes \otimes$ Each C_e , where $|e| = 3$, occurs once and cancels with the one on right hand side.

$\# \otimes \otimes = \binom{N-2}{1}$ is even $\Rightarrow C_{\otimes \otimes}$ cancels

$\# \otimes = \binom{N-1}{2} = \frac{(N-1)(N-2)}{2}$ is $\begin{cases} \text{odd, if } N = 0 \pmod{4} \Rightarrow C_{\otimes} \text{ remains.} \\ \text{even, if } N = 2 \pmod{4} \Rightarrow C_{\otimes} \text{ cancels.} \end{cases}$

$\# \{ \} = \binom{N}{3} = \frac{N(N-1)(N-2)}{2 \cdot 3}$ is even \Rightarrow global sign GS is positive.

Therefore, we need to consider two cases to continue the derivation of the expression (45):

Case #1: If $N = 0 \pmod{4}$, then

$$\langle K \rangle = \langle + |^{\otimes N} XX \dots XX \prod_{\otimes \in E} C_{\otimes} | + \rangle^{\otimes N} = \langle + |^{\otimes N} \prod_{\otimes \in E} C_{\otimes} | + \rangle^{\otimes N} = 0. \quad (46)$$

Case #2: If $N = 2 \pmod{4}$, then

$$\langle K \rangle = \langle + |^{\otimes N} XX \dots XX | + \rangle^{\otimes N} = \left[\langle + | + \rangle \right]^N = 1. \quad (47)$$

\square

B.4. Correlations for Z measurements on fully-connected three-uniform hypergraph states

Lemma 4. *If every party makes a measurement in Z direction, the expectation value is zero. Therefore, we need to show that*

$$\langle K \rangle := \langle ZZ \dots ZZ \rangle = 0 \quad (48)$$

Proof.

$$\langle K \rangle = \langle + |^{\otimes N} \left[\prod_{e \in E} C_e \right] ZZ \dots ZZ \left[\prod_{e \in E} C_e \right] | + \rangle^{\otimes N} = \langle + |^{\otimes N} ZZ \dots ZZ | + \rangle^{\otimes N} = \pm \frac{1}{2^N} \text{Tr}(Z \dots ZZ) = 0. \quad (49)$$

\square

APPENDIX C: PROOF OF OBSERVATION 5

Observation 5. *If we fix in the Bell operator \mathcal{B}_N in Eq. (15) the measurements to be $A = Z$ and $B = X$, then the N -qubit fully-connected three-uniform hypergraph state violates the classical bound, by an amount that grows exponentially with number of qubits, namely*

$$\begin{aligned} \langle \mathcal{B}_N \rangle_C &\leq 2^{\lfloor N/2 \rfloor} \quad \text{for local HV models, and} \\ \langle \mathcal{B}_N \rangle_Q &\geq 2^{N-2} - \frac{1}{2} \quad \text{for the hypergraph state.} \end{aligned} \quad (50)$$

The classical bound can be computed using the bound for Mermin inequality, i.e., $\langle \mathcal{B}_N^M \rangle_C \leq 2^{\lfloor N/2 \rfloor}$. If N is odd, our Bell inequality is exactly the Mermin inequality. If N is even, $\langle \mathcal{B}_N \rangle_C = \langle A \cdot \mathcal{B}_{N-1}^M + B \cdot \tilde{\mathcal{B}}_{N-1}^M \rangle_C \leq 2 \langle \mathcal{B}_{N-1}^M \rangle_C$, where $\tilde{\mathcal{B}}$ denotes the inequality where A and B are exchanged, and the claim follows. The quantum value is computed directly. In particular, for odd N , we have $\langle \mathcal{B}_N \rangle_Q = \sum_{k \text{ even}}^N \binom{N}{k} \frac{1}{2} = 2^{N-2}$. If $N = 0 \pmod 4$, then $\langle \mathcal{B}_N \rangle_Q = \sum_{k \text{ even}}^{N-1} \binom{N}{k} \frac{1}{2} - \langle X \dots X \rangle = 2^{N-2} - 1/2$ and for $N = 2 \pmod 4$, we have $\langle \mathcal{B}_N \rangle_Q = \sum_{k \text{ even}}^{N-1} \binom{N}{k} \frac{1}{2} - \langle X \dots X \rangle = 2^{N-2} + 1/2$.

Notice that, since Eq. (15) in the main text is a full-correlation Bell inequality, it can be written as a sum of probabilities minus a constant equal to the number of terms. With the proper normalization, such probabilities exactly correspond to the success probability of computing a Boolean function (cf. conclusive discussion and Ref. [29]).

APPENDIX D: CORRELATIONS FOR FOUR-UNIFORM HYPERGRAPH STATES

Lemma 5. *The following statements hold for N -qubit, four-uniform hypergraph states:*

1. *For the case $N = 8k - 2$ or $N = 8k - 1$, or $8k$, we have:*

(i)

$$\langle \underbrace{X \dots X}_m Z \dots Z \rangle = \begin{cases} + \frac{2^{\lfloor N/2 \rfloor - m + 1}}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}} & \text{if } (m-1) = 0 \pmod 4, \\ - \frac{2^{\lfloor N/2 \rfloor - m + 1}}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}} & \text{if } (m-1) = 2 \pmod 4. \end{cases} \quad (51)$$

(ii) *For $N = 8k - 1$, we have:*

$$\langle \underbrace{XX \dots XX}_N \rangle = -1. \quad (52)$$

For $N = 8k - 2$ or $N = 8k$, these correlations will not be needed.

2. *For $N = 4k + 1$, we have:*

$$\langle \underbrace{X \dots X}_m Z \dots Z \rangle = \begin{cases} + \frac{1}{2^{\lfloor m/2 \rfloor}}, & \text{if } (m-1) = 0 \pmod 4, \\ - \frac{1}{2^{\lfloor m/2 \rfloor}}, & \text{if } (m-1) = 2 \pmod 4, \\ \frac{1}{2^{\lfloor N/2 \rfloor}}, & \text{if } m = N. \end{cases} \quad (53)$$

3. *For $N = 8k + 2$, or $8k + 4$, we have for even m :*

(i)

$$\langle \underbrace{X \dots X}_m Z \dots Z \rangle = \begin{cases} + \frac{2^{m/2-1}}{2^{N/2}} & \text{if } (N-m) = 0 \pmod 4, \\ - \frac{2^{m/2-1}}{2^{N/2}} & \text{if } (N-m) = 2 \pmod 4. \end{cases} \quad (54)$$

(ii)

$$\langle XX \dots XX \rangle = \frac{2^{\frac{N}{2}-1} + 1}{2^{\frac{N}{2}}}. \quad (55)$$

4. For $N = 8k + 3$, $\langle \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \rangle$ for even m gives the same exact result as the part 3, so we have:

$$\langle \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \rangle = \begin{cases} +\frac{2^{m/2-1}}{2^{M/2}} & \text{if } (M-m) = 0 \pmod{4}, \\ -\frac{2^{m/2-1}}{2^{M/2}} & \text{if } (M-m) = 2 \pmod{4}, \end{cases} \quad (56)$$

where $M = N - 1$.

Proof. Each part of the theorem needs a separate consideration. note that the notation and machinery that is employed in the proof is based on the proof of the Lemma 2. Therefore, we advise the reader to become familiar with that one first.

Part 1. We consider the cases when $N = 8k - 2$, $N = 8k - 1$ or $8k$ and odd m together. We prove (i) first:

$$\langle G_1 \rangle = \langle H_4^N | \underbrace{X \dots X}_m Z \dots Z | H_4^N \rangle = \langle + |^{\otimes N} \left(\prod_{e \in E} C_e \right) X X \dots X Z \dots Z \left(\prod_{e \in E} C_e \right) | + \rangle^{\otimes N}. \quad (57)$$

We need to use the identity (19) to regroup all the phase gates on the right hand side of the expression (57). If each phase gate occurs even number of times, they give an identity, otherwise, they are used in the further calculations. We consider each case separately in the following table:

1. $\#\Delta \Delta \Delta = \binom{m}{1}$ is odd $\Rightarrow C_{\Delta\Delta\Delta}$ remains.
2. $\#\Delta\Delta = \binom{m}{2} = \frac{m(m-1)}{2}$ is $\begin{cases} \text{even, if } (m-1) = 0 \pmod{4} & \Rightarrow C_{\Delta\Delta} \text{ cancels.} \\ \text{odd, if } (m-1) = 2 \pmod{4} & \Rightarrow C_{\Delta\Delta} \text{ remains.} \end{cases}$
 $\#\otimes \Delta \Delta = \binom{m-1}{1}$ is even $\Rightarrow C_{\otimes\Delta\Delta}$ cancels.
3. $\#\Delta = \binom{m}{3} = \frac{m(m-1)(m-2)}{2 \cdot 3}$ is $\begin{cases} \text{even, if } (m-1) = 0 \pmod{4} & \Rightarrow C_{\Delta} \text{ cancels.} \\ \text{odd, if } (m-1) = 2 \pmod{4} & \Rightarrow C_{\Delta} \text{ remains.} \end{cases}$
 $\#\otimes \otimes \Delta = \binom{m-2}{1}$ is odd $\Rightarrow C_{\otimes\otimes\Delta}$ remains.
 $\#\otimes \Delta = \binom{m-1}{2} = \frac{(m-1)(m-2)}{2}$ is $\begin{cases} \text{even, if } (m-1) = 0 \pmod{4} & \Rightarrow C_{\otimes\Delta} \text{ cancels.} \\ \text{odd, if } (m-1) = 2 \pmod{4} & \Rightarrow C_{\otimes\Delta} \text{ remains.} \end{cases}$
4. $\#\otimes \otimes \otimes = \binom{m-3}{1}$ is even $\Rightarrow C_{\otimes\otimes\otimes}$ cancels.
 $\#\otimes \otimes = \binom{m-2}{2} = \frac{(m-2)(m-3)}{2}$ is $\begin{cases} \text{odd, if } (m-1) = 0 \pmod{4} & \Rightarrow C_{\otimes\otimes} \text{ remains.} \\ \text{even, if } (m-1) = 2 \pmod{4} & \Rightarrow C_{\otimes\otimes} \text{ cancels.} \end{cases}$
 $\#\otimes = \binom{m-1}{3} = \frac{(m-1)(m-2)(m-3)}{2 \cdot 3}$ is even $\Rightarrow C_{\otimes}$ cancels.
 $\#\{\} = \binom{m}{4} = \frac{(m-1)(m-2)(m-3)(m-4)}{2 \cdot 3 \cdot 4}$ affects global sign (GL) and will be discussed separately.

Table 1. Counting phase gates for a four-uniform case. m is odd.

Remark: All four-qubit phase gates move with the multiplicity one to the right side and therefore, cancel out with the same phase gate on the right. The detailed reasoning was discussed in proof of the Lemma (2) in the Appendix A. So, we skipped such scenarios in the Table 1.

Now we consider two cases of $(m-1)$ separately and for each case we fix the global sign (GL) defined in the Table 1.

Case # 1: $(m-1) = 0 \pmod{4}$:

$$\langle G_1 \rangle = \pm \langle + |^{\otimes N} X X \dots X Z \dots Z \prod_{\forall \otimes, \forall \Delta} C_{\Delta\Delta\Delta} C_{\otimes\otimes\Delta} C_{\otimes\otimes} | + \rangle^{\otimes N} = \pm \frac{1}{2^N} Tr \left(\prod_{\forall \otimes, \forall \Delta} C_{\Delta\Delta\Delta} C_{\otimes\otimes\Delta} C_{\otimes\otimes} C_{\Delta} \right). \quad (58)$$

Remark: We write the ' \pm ' sign as we have not fixed the global sign yet.

To evaluate the trace of the given diagonal matrix, we need to find the difference between the number of +1's and -1's on the diagonal. We write every row in the computational basis by enumerating it with the binary notation. Due to the symmetry of the problem, we assign the first m columns to X measurement (\otimes) and the rest to, $Z(\Delta)$. For each row, we denote by α the number of 1's in binary notation appearing in the first m column and by β , the same on the rest. This notation is also adopted. See the proof of Lemma 2 for more detailed explanation.

Considering the phase gates in (58), the expression $(-1)^s$ defines whether in the given row the diagonal element is +1 or -1, where :

$$s := \binom{\beta}{3} + \binom{\alpha}{2} \binom{\beta}{1} + \binom{\alpha}{2} + \binom{\beta}{1} = \frac{\beta(\beta-1)(\beta-2)}{2 \cdot 3} + \frac{\alpha(\alpha-1)}{2}(\beta+1) + \beta. \quad (59)$$

The sign of the diagonal element is determined at follows:

1. α is even & β is even: if $\alpha = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $\alpha = 2 \pmod 4 \Rightarrow (-1)^s = -1$
2. α is odd & β is even: if $(\alpha-1) = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $(\alpha-1) = 2 \pmod 4 \Rightarrow (-1)^s = -1$
3. (Any α) & β is odd: if $(\beta-1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\beta-1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$

Having established the ± 1 values for each row, we can sum them up to find the trace in (58). Here we use the identities (20) and (21) and afterwards the look-up Table 0 to insert the numerical values where necessary:

$$\begin{aligned} \langle G_1 \rangle &= \pm \frac{1}{2^N} \left[\sum_{\beta=0,2,4,\dots}^{N-m} \binom{N-m}{\beta} \left[\sum_{\alpha=0,4,\dots}^m \binom{m}{\alpha} + \binom{m}{\alpha+1} - \binom{m}{\alpha+2} - \binom{m}{\alpha+3} \right] \right. \\ &\quad \left. + \sum_{\beta=1,5,\dots} \left[- \binom{N-m}{\beta} \sum_{\alpha} \binom{m}{\alpha} + \binom{N-m}{\beta+2} \sum_{\alpha} \binom{m}{\alpha} \right] \right] \\ &= \pm \frac{1}{2^N} \left[\left[\text{Re}[(1+i)^m] + \text{Im}[(1+i)^m] \right] 2^{N-m-1} + 2^m \sum_{\beta=1,5,\dots}^{N-m} \left[- \binom{N-m}{\beta} + \binom{N-m}{\beta+2} \right] \right] \\ &= \pm \frac{1}{2^N} \left[\left[\text{Re}[(1+i)^m] + \text{Im}[(1+i)^m] \right] 2^{N-m-1} - 2^m \text{Im}[(1+i)^{N-m}] \right] \equiv \pm \frac{1}{2^N} E. \end{aligned} \quad (60)$$

We have to consider $N = 8k - 1$ and $N = 8k$ or $N = 8k - 2$ separately to continue the derivation of (60):

1. For $N = 8k - 1$, using the values from the Table 0:

$$\langle G_1 \rangle = \pm \frac{1}{2^N} \left[2^{\frac{m+1}{2}} 2^{N-m-1} - 2^m \text{Im}[(1+i)^{N-m}] \right] = \pm \frac{2^{\frac{m+1}{2}} 2^{N-m-1} + 2^m 2^{\frac{N-m}{2}}}{2^N} = \pm \frac{2^{\lfloor N/2 \rfloor - m} + 1}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}}. \quad (61)$$

2. For $N = 8k$ or $N = 8k - 2$, using the values from the Table 0:

$$\langle G_1 \rangle = \pm \frac{1}{2^N} \left[2^{\frac{m+1}{2}} 2^{N-m-1} - 2^m \text{Im}[(1+i)^{N-m}] \right] = \pm \frac{2^{\frac{m+1}{2}} 2^{N-m-1} + 2^m 2^{\frac{N-m-1}{2}}}{2^N} = \pm \frac{2^{\lfloor N/2 \rfloor - m} + 1}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}}. \quad (62)$$

Therefore,

$$\langle G_1 \rangle = \pm \frac{2^{\lfloor N/2 \rfloor - m} + 1}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}}. \quad (63)$$

Concerning the sign in (63), it is affected by the product of two components: one from the case 4 from Table 1: GL and the other by E from (60). If $(m-1) = 0 \pmod 8$, the equation E has a positive sign and also $GL = +1$.

And if $(m-1) = 4 \pmod 8$, E has a negative sign and $GL = -1$. Therefore, in both cases or equivalently, for $(m-1) = 0 \pmod 4$,

$$\langle G_1 \rangle = + \frac{2^{\lfloor N/2 \rfloor - m} + 1}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}}. \quad (64)$$

Case # 2: $(m-1) = 2 \pmod 4$:

$$\begin{aligned} \langle G_1 \rangle &= \pm \langle + |^{\otimes N} X X \dots X Z \dots Z \prod_{\forall \otimes, \forall \Delta} C_{\Delta \Delta \Delta} C_{\Delta \Delta} C_{\otimes \otimes \Delta} C_{\otimes \Delta} C_{\Delta} | + \rangle^{\otimes N} \\ &= \pm \frac{1}{2^N} \text{Tr} \left(\prod_{\forall \otimes, \forall \Delta} C_{\Delta \Delta \Delta} C_{\Delta \Delta} C_{\otimes \otimes \Delta} C_{\otimes \Delta} \right). \end{aligned} \quad (65)$$

In this case, we apply the same technique to determine the sign:

$$s := \binom{\beta}{3} + \binom{\beta}{2} + \binom{\alpha}{2} \binom{\beta}{1} + \binom{\alpha}{1} \binom{\beta}{1} = \frac{\beta(\beta-1)(\beta-2)}{2 \cdot 3} + \frac{\beta(\beta-1)}{2} + \frac{\alpha(\alpha-1)}{2} \beta + \alpha\beta. \quad (66)$$

The sign of s , is determined at follows:

1. β is even & any α if $\beta = 0 \pmod 4 \Rightarrow (-1)^s = +1$
 if $\beta = 2 \pmod 4 \Rightarrow (-1)^s = -1$
2. β is odd & α is even: if $\alpha = 0 \pmod 4 \Rightarrow (-1)^s = +1$
 if $\alpha = 2 \pmod 4 \Rightarrow (-1)^s = -1$
3. β is odd & α is odd: if $(\alpha-1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
 if $(\alpha-1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$

$$\begin{aligned} \langle G_1 \rangle &= \pm \frac{1}{2^N} \left[\sum_{\beta=0,4,\dots} \left[\binom{N-m}{\beta} \sum_{\alpha=0}^m \binom{m}{\alpha} - \binom{N-m}{\beta+2} \sum_{\alpha=0}^m \binom{m}{\alpha} \right] \right. \\ &\quad \left. + \sum_{\beta=1,3,\dots} \binom{N-m}{\beta} \left[\sum_{\alpha=0,4,\dots}^m \binom{m}{\alpha} - \binom{m}{\alpha+1} - \binom{m}{\alpha+2} + \binom{m}{\alpha+3} \right] \right] \\ &= \pm \frac{1}{2^N} \left[2^m \sum_{\beta=0,4,\dots} \left[\binom{N-m}{\beta} - \binom{N-m}{\beta+2} \right] + 2^{N-m-1} \left[\text{Re} \left[(1+i)^m \right] - \text{Im} \left[(1+i)^m \right] \right] \right] \\ &= \pm \frac{1}{2^N} \left[2^m \text{Re} \left[(1+i)^{N-m} \right] + 2^{N-m-1} \left[\text{Re} \left[(1+i)^m \right] - \text{Im} \left[(1+i)^m \right] \right] \right] \equiv \frac{1}{2^N} E. \end{aligned} \quad (67)$$

We have to consider $N = 8k - 1$ and $N = 8k$ or $N = 8k - 2$ separately to continue the derivation of (60):

1. For $N = 8k - 1$, using the values from the Table 0:

$$\langle G_1 \rangle = \pm \frac{1}{2^N} \left[2^m \text{Re} \left[(1+i)^{N-m} \right] + 2^{\frac{m+1}{2}} 2^{N-m-1} \right] = \pm \frac{2^m 2^{\frac{N-m}{2}} + 2^{\frac{m+1}{2}} 2^{N-m-1}}{2^N} = \pm \frac{2^{\lfloor N/2 \rfloor - m} + 1}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}}. \quad (68)$$

2. For $N = 8k$ or $N = 8k - 2$, using the values from the Table 0:

$$\langle G_1 \rangle = \pm \frac{1}{2^N} \left[2^m \text{Re} \left[(1+i)^{N-m} \right] + 2^{\frac{m+1}{2}} 2^{N-m-1} \right] = \pm \frac{2^m 2^{\frac{N-m-1}{2}} + 2^{\frac{m+1}{2}} 2^{N-m-1}}{2^N} = \pm \frac{2^{\lfloor N/2 \rfloor - m} + 1}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}}. \quad (69)$$

Therefore,

$$\langle G_1 \rangle = \pm \frac{2^{\lfloor N/2 \rfloor - m} + 1}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}}. \quad (70)$$

Concerning the sign in (70), it is affected by the product of two components: one from the case 4 from Table 1: GL and the other by E in (67).

Hence, if $(m-3) = 0 \pmod 8$, E has a negative sign and $GL = +1$. And if $(m-3) = 4 \pmod 8$, E has a positive sign and $GL = -1$. Therefore, in both cases or equivalently, for $(m-1) = 2 \pmod 4$,

$$\langle G_1 \rangle = -\frac{2^{\lfloor N/2 \rfloor - m + 1}}{2^{\lfloor N/2 \rfloor - \lfloor m/2 \rfloor}}. \quad (71)$$

This completes the proof of part 1 (i).

Part 1 (ii) For $N = 8k - 1$, show that

$$\langle G_2 \rangle = \underbrace{\langle XX \dots XX \rangle}_N = -1. \quad (72)$$

Here as well we use the identity (19) to count the multiplicity of remaining phase gates. Since all the measurements are in X direction, we need to make a new table with the same notations as in the previous case:

1. $\# \otimes \otimes \otimes \otimes$ every gate occurs only once \Rightarrow every C_e cancels with the C_e on the right hand side.
2. $\# \otimes \otimes \otimes \binom{8k-4}{1}$ is even $\Rightarrow C_{\otimes \otimes \otimes}$ cancels.
3. $\# \otimes \otimes \binom{8k-3}{2}$ is even $\Rightarrow C_{\otimes \otimes}$ cancels.
4. $\# \otimes \binom{8k-2}{3}$ is even $\Rightarrow C_{\otimes}$ cancels.
5. $\# \{ \} \binom{8k-1}{4}$ is odd \Rightarrow we get a global negative sign.

Table 2. Counting phase gates for a four-uniform HG when each system is measured in X direction.

Therefore,

$$\langle G_2 \rangle = -\frac{1}{2^N} \text{Tr}(\mathbb{1}) = -1. \quad (73)$$

This finishes the proof of part 1.

Part 2: We show that, for $N = 4k + 1$:

$$\langle G_3 \rangle = \underbrace{\langle X \dots X Z \dots Z \rangle}_m = \begin{cases} +\frac{1}{2^{\lfloor m/2 \rfloor}}, & \text{if } (m-1) = 0 \pmod 4, \\ -\frac{1}{2^{\lfloor m/2 \rfloor}}, & \text{if } (m-1) = 2 \pmod 4, \\ \frac{1}{2^{\lfloor N/2 \rfloor}}, & \text{if } m = N. \end{cases} \quad (74)$$

Since the number of systems measured in the X direction is the same in this part as it was in part 1, we can use the results demonstrated in the Table 1. Therefore, we use equation (60) when $m-1 = 0 \pmod 4$ and (67), for $m-1 = 2 \pmod 4$.

Case # 1: $(m-1) = 0 \pmod 4$:

$$\langle G_3 \rangle = \pm \frac{1}{2^N} \left[\left[\text{Re} \left[(1+i)^m \right] + \text{Im} \left[(1+i)^m \right] \right] 2^{N-m-1} - 2^m \text{Im} \left[(1+i)^{N-m} \right] \right] = \pm \frac{1}{2^N} E. \quad (75)$$

As $N = 4k+1$, we have that $N-m = 4k+1-m = 4k-(m-1)$, which is divisible by 4. Therefore $\text{Im} \left[(1+i)^{N-m} \right] = 0$. and equation (75) reduces to:

$$\langle G_3 \rangle = \pm \frac{2^{N-m-1}}{2^N} \left[\text{Re} \left[(1+i)^m \right] + \text{Im} \left[(1+i)^m \right] \right] = \pm \frac{1}{2^{\lfloor m/2 \rfloor}}. \quad (76)$$

We need to fix the global sign GL from the Table 1. For this, we consider two cases. First, if $(m - 1) = 0 \pmod{8}$, then $GL = +$ and so is the sign E in equation (75):

$$\langle G_3 \rangle = + \frac{1}{2^{\lceil m/2 \rceil}}. \quad (77)$$

Second, if $(m - 1) = 4 \pmod{8}$, then $GL = -$ and so is the sign of E in equation (75):

$$\langle G_3 \rangle = + \frac{1}{2^{\lceil m/2 \rceil}}. \quad (78)$$

Case # 2: For $(m - 1) = 2 \pmod{4}$:

$$\langle G_3 \rangle = \pm \frac{1}{2^N} \left[2^m \operatorname{Re} \left[(1+i)^{N-m} \right] + 2^{N-m-1} \left[\operatorname{Re} \left[(1+i)^m \right] - \operatorname{Im} \left[(1+i)^m \right] \right] \right]. \quad (79)$$

As $N = 4k + 1$, we have $N - m = 4k + 1 - m = 4k - (m - 1)$, which is not divisible by 4 but is an even number. Therefore, $\operatorname{Re} \left[(1+i)^{N-m} \right] = 0$. So, the equation (79) reduces to:

$$\langle G_3 \rangle = \pm \frac{2^{N-m-1}}{2^N} \left[\operatorname{Re} \left[(1+i)^m \right] - \operatorname{Im} \left[(1+i)^m \right] \right] \equiv \pm \frac{2^{N-m-1}}{2^N} E. \quad (80)$$

We need to fix the global sign GL from the Table 1. For this, we consider two cases. First, if $(m - 3) = 0 \pmod{8}$, then the global sign is positive but the sign of E in (80) is negative. Therefore,

$$\langle G_3 \rangle = - \frac{1}{2^{\lceil m/2 \rceil}}. \quad (81)$$

Second, if $(m - 3) = 4 \pmod{8}$, then the global sign is negative but the sign of E in (80) is positive. Therefore,

$$\langle G_3 \rangle = - \frac{1}{2^{\lceil m/2 \rceil}}. \quad (82)$$

Case # 3: $m = N$ resembles part 1 (ii). The only difference comes in with the number of qubits we are currently working with:

1. $\# \otimes \otimes \otimes \otimes$ e every gate occurs only once \Rightarrow every C_e cancels with the C_e on the right hand side.
2. $\# \otimes \otimes \otimes \binom{4k-2}{1}$ is even $\Rightarrow C_{\otimes \otimes \otimes}$ cancels.
3. $\# \otimes \otimes \binom{4k-1}{2}$ is odd $\Rightarrow C_{\otimes \otimes}$ remains.
4. $\# \otimes \binom{4k}{3}$ is even $\Rightarrow C_{\otimes}$ cancels.
5. $\#\{\}$ the global sign depends on k , as $\binom{4k+1}{4} = \frac{(4k+1)4k(4k-1)(4k-2)}{2 \cdot 3 \cdot 4}$

Table 3. Counting phase gates for a four-uniform HG when each system is measured in X direction.

Back to the expectation value,

$$\langle G_3 \rangle = \pm \frac{1}{2^N} \operatorname{Tr} \left[\prod_{\forall \otimes} C_{\otimes \otimes \otimes} \right]. \quad (83)$$

So, we have to count the difference between the amount of $+1$'s and -1 's on the diagonal. As we use exactly the same techniques before, we will skip the detailed explanation. The sign on the diagonal is:

$$(-1)^{\binom{\alpha}{2}} = (-1)^{\frac{\alpha(\alpha-1)}{2}}. \quad (84)$$

and it is straightforward to evaluate it for each value of α .

$$\langle G_3 \rangle = \pm \frac{1}{2^N} \left[\sum_{\alpha=0,4,\dots}^N \binom{N}{\alpha} + \binom{N}{\alpha+1} - \binom{N}{\alpha+2} - \binom{N}{\alpha+3} \right] = \pm \frac{1}{2^N} \left[\text{Re}[(1+i)^N] + \text{Im}[(1+i)^N] \right] \equiv \pm \frac{1}{2^N} E. \quad (85)$$

Keeping in mind that $N = 4k + 1$, the global sign from the Table 3 is positive for even k and negative for odd. The the sign of E in (85) is positive if k is even and negative, otherwise. Therefore,

$$\langle G_3 \rangle = \frac{1}{2^{\lfloor N/2 \rfloor}}. \quad (86)$$

This completes the proof of part 2.

Part 3: We start with (ii). We show that for $N = 8k + 2$, or $8k + 4$:

(ii)

$$\langle G_4 \rangle = \langle XX \dots XX \rangle = \frac{2^{\frac{N}{2}-1} + 1}{2^{\frac{N}{2}}}. \quad (87)$$

Although the result seems identical, unfortunately, each case needs a separate treatment. The technique is similar to the previous proofs, though. We just mind the number of qubits we are working with:

For $N = 8k + 2$ we find the remaining phase gates as follows:

1. $\# \otimes \otimes \otimes \otimes$ each gate only once; thus, every C_e cancels with the C_e on the right hand side.
2. $\# \otimes \otimes \otimes \binom{8k-1}{1}$ is odd $\Rightarrow C_{\otimes \otimes \otimes}$ remains.
3. $\# \otimes \otimes \binom{8k}{2}$ is even $\Rightarrow C_{\otimes \otimes}$ cancels.
4. $\# \otimes \binom{8k+1}{3}$ is even $\Rightarrow C_{\otimes}$ cancels.
5. $\# \{ \} \binom{8k+2}{4}$ is even times \Rightarrow we get a global positive sign.

Table 4. Counting phase gates for a four-uniform HG when each system is measured in X direction.

Therefore,

$$\langle G_4 \rangle = \frac{1}{2^N} \text{Tr} \left[\prod_{\forall \otimes} C_{\otimes \otimes \otimes} \right]. \quad (88)$$

We use $(-1)^s$ to define the sign of the diagonal element and $s = \binom{\alpha}{3}$. So, after considering all possible values of α , it is directly obtained that

$$\begin{aligned} \langle G_4 \rangle &= \frac{1}{2^N} \text{Tr}(C_{\otimes \otimes \otimes}) = \frac{1}{2^N} \left[\sum_{\alpha=0,2,\dots}^N \binom{N}{\alpha} + \sum_{\alpha=1,5,\dots} \left[\binom{N}{\alpha} - \binom{N}{\alpha+2} \right] \right] \\ &= \frac{1}{2^N} \left[2^{N-1} + \text{Im}[(1+i)^N] \right] = \frac{2^{\frac{N}{2}-1} + 1}{2^{\frac{N}{2}}}. \end{aligned} \quad (89)$$

For $N = 8k + 4$ we find the remaining phase gates as follows:

1. $\# \otimes \otimes \otimes \otimes$ each gate occurs only once \Rightarrow every C_e cancels with the C_e on the right hand side.
2. $\# \otimes \otimes \otimes \binom{8k+1}{1}$ is odd $\Rightarrow C_{\otimes \otimes \otimes}$ remains.
3. $\# \otimes \otimes \binom{8k+2}{2}$ is odd $\Rightarrow C_{\otimes \otimes}$ remains.
4. $\# \otimes \binom{8k+3}{3}$ is odd $\Rightarrow C_{\otimes}$ remains.
5. $\# \{ \} \binom{8k+4}{4}$ is odd \Rightarrow we get a global negative sign, $GL = -1$.

Table 5. Counting phase gates for a four-uniform case in all X direction.

Therefore,

$$\langle G_4 \rangle = -\frac{1}{2^N} \text{Tr} \left[\prod_{\forall \otimes} C_{\otimes \otimes \otimes} C_{\otimes \otimes} C_{\otimes} \right]. \quad (90)$$

We use $(-1)^s$ to define the sign of the diagonal element and $s = \binom{\alpha}{3} + \binom{\alpha}{2} + \binom{\alpha}{1}$. So, after considering all possible values of α , it is directly obtained that

$$\begin{aligned} \langle G_4 \rangle &= -\frac{1}{2^N} \text{Tr}(C_{\otimes \otimes \otimes} C_{\otimes \otimes} C_{\otimes}) = -\frac{1}{2^N} \left[\sum_{\alpha=0,4,\dots}^N \left[\binom{N}{\alpha} - \binom{N}{\alpha+2} \right] - \sum_{\alpha=1,3,\dots}^N \binom{N}{\alpha} \right] \\ &= -\frac{1}{2^N} \left[-2^{N-1} + \text{Re}[(1+i)^N] \right] = \frac{2^{N-1} + 2^{N/2}}{2^N} = \frac{2^{\frac{N}{2}-1} + 1}{2^{\frac{N}{2}}}. \end{aligned} \quad (91)$$

This finishes the proof of part (i).

(ii) We need to show that

$$\langle G_4 \rangle = \langle \underbrace{X \dots X}_m Z \dots Z \rangle = \begin{cases} +\frac{2^{m/2-1}}{2^{N/2}} & \text{if } (N-m) = 0 \pmod{4}, \\ -\frac{2^{m/2-1}}{2^{N/2}} & \text{if } (N-m) = 2 \pmod{4}. \end{cases} \quad (92)$$

Note that in this case m is an even number. Therefore, we have to derive again from the scratch how phase gates can be moved to the right hand side of the expression and for this we use the identity (19).

1. $\# \triangle \triangle \triangle = \binom{m}{1}$ is even $\Rightarrow C_{\triangle \triangle \triangle}$ cancels.
2. $\# \triangle \triangle = \binom{m}{2} = \frac{m(m-1)}{2}$ is $\begin{cases} \text{even, if } m = 0 \pmod{4} \Rightarrow C_{\triangle \triangle} \text{ cancels.} \\ \text{odd, if } m = 2 \pmod{4} \Rightarrow C_{\triangle \triangle} \text{ remains.} \end{cases}$
 $\# \otimes \triangle \triangle = \binom{m-1}{1}$ is odd $\Rightarrow C_{\otimes \triangle \triangle}$ remains.
3. $\# \triangle = \binom{m}{3} = \frac{m(m-1)(m-2)}{2 \cdot 3}$ is even $\Rightarrow C_{\triangle}$ cancels.
 $\# \otimes \otimes \triangle = \binom{m-2}{1}$ is even $\Rightarrow C_{\otimes \otimes \triangle}$ cancels.
 $\# \otimes \triangle = \binom{m-1}{2} = \frac{(m-1)(m-2)}{2}$ is $\begin{cases} \text{odd, if } m = 0 \pmod{4} \Rightarrow C_{\otimes \triangle} \text{ remains.} \\ \text{even, if } m = 2 \pmod{4} \Rightarrow C_{\otimes \triangle} \text{ cancels.} \end{cases}$
4. $\# \otimes \otimes \otimes = \binom{m-3}{1}$ is odd $\Rightarrow C_{\otimes \otimes \otimes}$ remains.
 $\# \otimes \otimes = \binom{m-2}{2} = \frac{(m-2)(m-3)}{2}$ is $\begin{cases} \text{odd, if } m = 0 \pmod{4} \Rightarrow C_{\otimes \otimes} \text{ remains.} \\ \text{even, if } m = 2 \pmod{4} \Rightarrow C_{\otimes \otimes} \text{ cancels.} \end{cases}$
 $\# \otimes = \binom{m-1}{3} = \frac{(m-1)(m-2)(m-3)}{2 \cdot 3}$ is $\begin{cases} \text{odd, if } m = 0 \pmod{4} \Rightarrow C_{\otimes} \text{ remains.} \\ \text{even, if } m = 2 \pmod{4} \Rightarrow C_{\otimes} \text{ cancels.} \end{cases}$
 $\# \{ \} = \binom{m}{4} = \frac{m(m-1)(m-2)(m-3)}{2 \cdot 3 \cdot 4}$ affects the global sign (GL) and will be discussed separately.

Table 6. Counting phase gates for a four-uniform HG state, for even m .

Remark: Similarly to previous proofs the four-qubit phase gates cancel out. Therefore, we directly skip the discussion about them.

We need to consider two cases, when $m = 0 \pmod 4$ and $m = 2 \pmod 4$ for each $N = 8k + 2$ and $8k + 4$ separately:

Case # 1: If $m = 0 \pmod 4$:

$$\begin{aligned} \langle G_4 \rangle &= \pm \langle + |^{\otimes N} X X \dots X Z \dots Z \prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta \Delta} C_{\otimes \Delta} C_{\otimes \otimes \otimes} C_{\otimes \otimes} C_{\otimes} | + \rangle^{\otimes N} \\ &= \pm \frac{1}{2^N} \text{Tr} \left[\prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta \Delta} C_{\otimes \Delta} C_{\otimes \otimes \otimes} C_{\otimes \otimes} C_{\otimes} C_{\Delta} \right]. \end{aligned} \quad (93)$$

We use $(-1)^s$ to define the sign of the diagonal element and $s = \binom{\alpha}{1} \binom{\beta}{2} + \binom{\alpha}{1} \binom{\beta}{1} + \binom{\alpha}{3} + \binom{\alpha}{2} + \binom{\alpha}{1} + \binom{\beta}{1}$. If s is even, the value on the diagonal is $+1$ and -1 , otherwise. We consider all possible values of α and β :

1. α is even & β is even if $\alpha = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $\alpha = 2 \pmod 4 \Rightarrow (-1)^s = -1$
2. α is even & β is odd: if $\alpha = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $\alpha = 2 \pmod 4 \Rightarrow (-1)^s = +1$

From here one can easily spot that for even α , there is equal number of $+1$ and -1 on the diagonal. So, they do not contribute in the calculations. We now consider the odd α :

3. α is odd & β is even if $\beta = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $\beta = 2 \pmod 4 \Rightarrow (-1)^s = +1$
4. α is odd & β is odd: if $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$

We now continue calculation of the trace from (136):

$$\begin{aligned} \langle G_4 \rangle &= \pm \frac{1}{2^N} \sum_{\alpha=1,3,5,\dots} \binom{m}{\alpha} \left[\sum_{\beta=0,4,\dots}^{N-m} -\binom{N-m}{\beta} - \binom{N-m}{\beta+1} + \binom{N-m}{\beta+2} + \binom{N-m}{\beta+3} \right] \\ &= \pm \frac{2^{m-1}}{2^N} \left[-\text{Re} \left[(1+i)^{N-m} \right] - \text{Im} \left[(1+i)^{N-m} \right] \right] = \pm \frac{2^{m-1}}{2^N} \left(\mp 2^{\frac{N-m}{2}} \right). \end{aligned} \quad (94)$$

We have to take care of the sign which appears from the product of the sign of the sum of real and imaginary part in (94) and global sign (GL), which we defined while deriving the remaining phase gates. If m is divisible by 8, $GL = +1$ and since we are in $N = 8k + 2$ case, $(N - m = 8k + 2 - m) - 2 \pmod 8$ and therefore:

$$\langle G_4 \rangle = \frac{2^{m-1}}{2^N} \left(-2^{\frac{N-m}{2}} \right) = -\frac{2^{m/2-1}}{2^{N/2}}. \quad (95)$$

If m is not divisible by 8, the global sign $GL = -1$, and the sum of real and imaginary part also contribute with a negative sign. Thus,

$$\langle G_4 \rangle = -\frac{2^{m-1}}{2^N} \left(-(-2^{\frac{N-m}{2}}) \right) = -\frac{2^{m/2-1}}{2^{N/2}}. \quad (96)$$

Since the $N = 8k + 4$ case is identical, we only have to mind the sign of the sum of the real and imaginary part. Here as well we consider two cases: if m is divisible by 8, then the global sign $GL = +1$, and the sign of the sum of real and imaginary part is " - ". Therefore,

$$\langle G_4 \rangle = \frac{2^{m-1}}{2^N} \left(-(-2^{\frac{N-m}{2}}) \right) = +\frac{2^{m/2-1}}{2^{N/2}}. \quad (97)$$

And if m is not divisible by 8, $GL = -1$, and the sign of real and imaginary part is ” + ”. Therefore,

$$\langle G_4 \rangle = -\frac{2^{m-1}}{2^N} \left(- (+2^{\frac{N-m}{2}}) \right) = +\frac{2^{m/2-1}}{2^{N/2}}. \quad (98)$$

Case # 2: If $m = 2 \pmod 4$:

$$\begin{aligned} \langle G_4 \rangle &= \pm \langle + |^{\otimes N} X X \dots X Z \dots Z \prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta \Delta} C_{\otimes \otimes \otimes} C_{\Delta \Delta} | + \rangle^{\otimes N} \\ &= \pm \frac{1}{2^N} \text{Tr} \left(\prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta \Delta} C_{\otimes \otimes \otimes} C_{\Delta \Delta} C_{\Delta} \right). \end{aligned} \quad (99)$$

We use $(-1)^s$ to define the sign of the diagonal element and $s = \binom{\alpha}{1} \binom{\beta}{2} + \binom{\alpha}{3} + \binom{\beta}{2} + \binom{\beta}{1}$. If s is even, the value on the diagonal is $+1$ and -1 , otherwise. We consider all possible values of α and β :

Considering the terms from odd α :

1. α is odd & β is even if $(\alpha - 1) = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $(\alpha - 1) = 2 \pmod 4 \Rightarrow (-1)^s = -1$
2. α is odd & β is odd: if $(\alpha - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\alpha - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$

It is easy to see that these cases adds up to 0.

3. α is even & β is even if $\beta = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $\beta = 2 \pmod 4 \Rightarrow (-1)^s = -1$
4. α is even & β is odd: if $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$

Therefore,

$$\begin{aligned} \langle G_4 \rangle &= \pm \frac{1}{2^N} \sum_{\alpha=0,2,4,\dots} \binom{m}{\alpha} \left[\sum_{\beta=0,4,\dots}^{N-m} \binom{N-m}{\beta} - \binom{N-m}{\beta+1} - \binom{N-m}{\beta+2} + \binom{N-m}{\beta+3} \right] \\ &= \pm 2^{m-1} \left[\text{Re} \left[(1+i)^{N-m} \right] - \text{Im} \left[(1+i)^{N-m} \right] \right] = \pm \frac{2^{m/2-1}}{2^{N/2}}. \end{aligned} \quad (100)$$

To fix the sign, we need to first consider $N = 8k + 2$, and $(m - 2) = 0 \pmod 8$. Then the global sign $GL = +1$ and type of $N - m$ also yields a positive sign. But if $(m - 2) = 4 \pmod 8$, global sign in negative and the $N - m$ also yields the negative sign. So,

$$\langle G_4 \rangle = \frac{2^{m/2-1}}{2^{N/2}}. \quad (101)$$

$N = 8k + 4$ case is identical to $N = 8k + 2$, therefore we will just state the result. For $N = 8k + 4$

$$\langle G_4 \rangle = -\frac{2^{m/2-1}}{2^{N/2}}. \quad (102)$$

To sum up,

$$\langle G_4 \rangle = \begin{cases} +\frac{2^{m/2-1}}{2^{N/2}} & \text{if } (N - m) = 0 \pmod 4, \\ -\frac{2^{m/2-1}}{2^{N/2}} & \text{if } (N - m) = 2 \pmod 4. \end{cases} \quad (103)$$

This finishes the proof of part 3.

Part 4: We show that for $N = 8k + 3$, $\langle \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \rangle$ for even m gives the same exact result as the part 3 (i).

We tackle the problem as follows: We make a measurement on one of the qubits in Z direction and depending on the measurement outcome, we obtain the new $|H_{4_{new}}^M\rangle$ state, where $M := N - 1$. Then we consider the expectation values for the all possible measurement outcomes and $|H_{4_{new}}^M\rangle$. From that we conclude the statement in the part 4.

Initial HG state $|H_4^N\rangle$ can be written in the following form as well:

$$|H_4^N\rangle = \prod_e C_e |+\rangle^{\otimes N} = \prod_{e', e''} C_{e'} C_{e''} |+\rangle^{\otimes N} = \prod_{e', e''} [\mathbb{1}_{e' \setminus N} |0\rangle_N \langle 0|_N + C_{e' \setminus N} |1\rangle_N \langle 1|_N] C_{e''} |+\rangle^{\otimes N}, \quad (104)$$

where e' represents the gates containing the last qubit, N and e'' represents the ones which do not contain N^{th} qubit. And $e = e' + e''$. Then if one makes a measurement in Z basis on the last qubit and obtains outcome $+$,

$$\begin{aligned} |H_{4_{new}}^{M+}\rangle &= \langle 0_N | H_4^N \rangle = \prod_{e', e''} [\langle 0_N | \mathbb{1}_{e' \setminus N} |0\rangle_N \langle 0|_N + \langle 0_N | C_{e' \setminus N} |1\rangle_N \langle 1|_N] C_{e''} |+\rangle^{\otimes N} \\ &= \prod_{e', e''} \mathbb{1}_{e' \setminus N} \langle 0_N | C_{e''} |+\rangle^{\otimes N} = \langle 0_N | \prod_{e', e''} \mathbb{1}_{e' \setminus N} C_{e''} |+\rangle^{\otimes M} (|0\rangle_N + |1\rangle_N). \\ &= \prod_{e', e''} \mathbb{1}_{e' \setminus N} C_{e''} |+\rangle^{\otimes M} = \prod_{e''} C_{e''} |+\rangle^{\otimes M}. \end{aligned} \quad (105)$$

So, $+$ outcome after measuring in Z direction leaves us with $|H_{4_{new}}^{M+}\rangle$, which is precisely four uniform M -qubit HG state. Now, let us see what is the remaining state if one gets $-$ as an outcome result:

$$\begin{aligned} |H_{4_{new}}^{M-}\rangle &= \langle 1_N | H_4^N \rangle = \prod_{e', e''} [\langle 1_N | \mathbb{1}_{e' \setminus N} |0\rangle_N \langle 0|_N + \langle 1_N | C_{e' \setminus N} |1\rangle_N \langle 1|_N] C_{e''} |+\rangle^{\otimes N} \\ &= \prod_{e', e''} C_{e' \setminus N} \langle 1_N | C_{e''} |+\rangle^{\otimes N} = \langle 1_N | \prod_{e', e''} C_{e' \setminus N} C_{e''} |+\rangle^{\otimes M} (|0\rangle_N + |1\rangle_N) \\ &= \prod_{e', e''} C_{e' \setminus N} C_{e''} |+\rangle^{\otimes M}. \end{aligned} \quad (106)$$

So, $-$ outcome after measuring in Z direction leaves us with $|H_{4_{new}}^{M-}\rangle$, which is precisely a symmetric M -qubit HG state with all possible edges of cardinality four and three. We will call such HG state a three- and four-uniform HG state.

Therefore, problem boils down to showing that,

- (i) If the measurement outcome is $+$, we get the $M = 8k + 2$ four-uniform HG state and the correlations are given in part 3.
- (ii) If the measurement outcome is $-$, we get $M = 8k + 2$ three- and fouruniform HG state and the following holds:

$$\langle G_5^- \rangle = \langle H_{4_{new}}^{M-} | \underbrace{X \dots X}_m Z \dots Z | H_{4_{new}}^{M-} \rangle = \begin{cases} -\frac{2^{m/2-1}}{2^{M/2}} & \text{if } (M - m) = 0 \pmod{4}, \\ +\frac{2^{m/2-1}}{2^{M/2}} & \text{if } (M - m) = 2 \pmod{4}. \end{cases} \quad (107)$$

(i) $|H_{4_{new}}^{M+}\rangle$, where $M = 8k + 2$ was already considered in part 3.

(ii). For $|H_{4_{new}}^{M-}\rangle$,

$$\langle G_5^- \rangle = \langle + |^{\otimes M} \left[\prod_{e', e'' \in E} C_{e'} C_{e''} \right] \underbrace{X \dots X}_m Z \dots Z \left[\prod_{e', e'' \in E} C_e C_{e''} \right] | + \rangle^{\otimes M}. \quad (108)$$

Before, we treated three- and four-uniform cases separately. Now, we just need to put them together.

Case # 1: If $m = 0 \pmod{4}$:

Then from equations (35) and (136), we can directly write down that

$$\langle G_5^- \rangle = \frac{1}{2^M} \text{Tr} \left[\prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta \Delta} C_{\otimes \otimes \otimes} C_{\otimes \otimes} C_{\Delta} \right]. \quad (109)$$

We check the sign of each term on the diagonal by $(-1)^s$, where $s = \binom{\alpha}{1}\binom{\beta}{2} + \binom{\alpha}{3} + \binom{\alpha}{2} + \binom{\beta}{1}$. For this we need to consider each value of α and β separately.

1. α is even & β is even $\alpha = 0 \pmod 4 \Rightarrow +1$
 $\alpha = 2 \pmod 4 \Rightarrow -1$
 \Rightarrow These two give zero contribution together.
2. α is even & β is odd $\alpha = 0 \pmod 4 \Rightarrow -1$
 $\alpha = 2 \pmod 4 \Rightarrow +1$
3. α is odd & β is even $\beta = 0 \pmod 4 \Rightarrow +1$
 $\beta = 2 \pmod 4 \Rightarrow -1$
4. α is odd & β is odd $\beta - 1 = 0 \pmod 4 \Rightarrow -1$
 $\beta - 1 = 2 \pmod 4 \Rightarrow +1$

$$\begin{aligned} \langle G_5^- \rangle &= \pm \frac{1}{2^M} \sum_{\alpha \text{ odd}}^m \binom{m}{\alpha} \left[\sum_{\beta=0,4}^{M-m} \binom{M-m}{\beta} - \binom{M-m}{\beta+1} - \binom{M-m}{\beta+2} + \binom{M-m}{\beta+3} \right] \\ &= \pm \frac{2^{m-1}}{2^M} \left[\text{Re}(1+i)^{M-m} - \text{Im}(1+i)^{M-m} \right] = \pm \frac{2^{\frac{m}{2}-1}}{2^{M/2}}. \end{aligned} \quad (110)$$

If $m = 0 \pmod 8$, real and imaginary part in (110) has a negative sign and the global sign coming from Table 6, GL is positive. Note from equation (33) that three uniform gate moving does not introduce any global signs. And if $m = 4 \pmod 8$, real and imaginary part in (110) has a positive sign and the global sign coming from Table 6, GL is negative. Therefore,

$$\langle G_5^+ \rangle = -\frac{2^{\frac{m}{2}-1}}{2^{M/2}}. \quad (111)$$

Case # 2: If $m = 2 \pmod 4$:

Then from equations (40) and (121), we can directly write down that

$$\langle G_5^- \rangle = \pm \frac{1}{2^M} \text{Tr} \left[\prod_{\forall \otimes, \forall \Delta} C_{\otimes \Delta \Delta} C_{\otimes \Delta} C_{\otimes \otimes \otimes} C_{\Delta \Delta} \right]. \quad (112)$$

We check the sign of each term on the diagonal by $(-1)^s$, where $s = \binom{\alpha}{1}\binom{\beta}{2} + \binom{\alpha}{3} + \binom{\beta}{2} + \binom{\alpha}{1}\binom{\beta}{1}$. For this we need to consider each value of α and β separately.

1. α is even & β is even $\beta = 0 \pmod 4 \Rightarrow +1$
 $\beta = 2 \pmod 4 \Rightarrow -1$
2. α is even & β is odd $\beta - 1 = 0 \pmod 4 \Rightarrow +1$
 $\beta - 1 = 2 \pmod 4 \Rightarrow -1$
3. α is odd & β is even $\alpha - 1 = 0 \pmod 4 \Rightarrow +1$
 $\alpha - 1 = 2 \pmod 4 \Rightarrow -1$
 \Rightarrow These two give zero contribution together.
4. α is odd & β is odd $\alpha - 1 = 0 \pmod 4 \Rightarrow -1$
 $\alpha - 1 = 2 \pmod 4 \Rightarrow +1$

$$\begin{aligned} \langle G_5^- \rangle &= \pm \frac{1}{2^M} \sum_{\alpha \text{ even}}^m \binom{m}{\alpha} \left[\sum_{\beta=0,4}^{M-m} \binom{M-m}{\beta} + \binom{M-m}{\beta+1} - \binom{M-m}{\beta+2} - \binom{M-m}{\beta+3} \right] \\ &= \pm \frac{1}{2^M} 2^{m-1} \left[\text{Re}(1+i)^{M-m} + \text{Im}(1+i)^{M-m} \right] = \pm \frac{2^{\frac{m}{2}-1}}{2^{M/2}}. \end{aligned} \quad (113)$$

If $m - 2 = 0 \pmod 8$, real and imaginary part in (122) has a positive sign and the global sign coming from Table 6, GL is positive. Note from equation (33) that the three uniform gate moving does not introduce any global signs.

And if $m - 2 = 4 \pmod 8$, real and imaginary part in (122) has a negative sign and the global sign coming from Table 6, GL is negative. Therefore,

$$\langle G_5^- \rangle = + \frac{2^{\frac{m}{2}-1}}{2^{M/2}}. \quad (114)$$

Finally, we can put everything together. Since one can observe that $\langle G_5^- \rangle = -\langle G_5^+ \rangle$,

$$|0\rangle\langle 0|\langle G_5^+ \rangle - |1\rangle\langle 1|\langle G_5^- \rangle = |0\rangle\langle 0|\langle G_5^+ \rangle + |1\rangle\langle 1|\langle G_5^+ \rangle = \mathbb{1}\langle G_5^+ \rangle = \langle \underbrace{X \dots X}_m \underbrace{Z \dots Z}_m \mathbb{1} \rangle. \quad (115)$$

This completes the proof of part 4 and entire lemma. \square

APPENDIX E: BELL INEQUALITY VIOLATIONS FOR FULLY-CONNECTED FOUR-UNIFORM HYPERGRAPH STATES

Lemma 6. *An arbitrary four-uniform HG state violates the classical bound by an amount that grows exponentially along with number of qubits.*

Proof. To show this, either in Eq. (15) or in the original Mermin operator, $\langle \mathcal{B}_N^M \rangle$, we fix $A = Z$ and $B = X$. The choice of the Bell operator depends on the number of qubits: From Lemma (5) for a given N either the correlations for an even m or an odd m are given. If m is even, we choose Eq. (15) and $\langle \mathcal{B}_N^M \rangle$, otherwise.

From Lemma 5, it is clear that we need to consider separate cases. However, we choose the one which encounters the smallest growth in violation and this is the $N = 8k + 3$ case. Other cases just encounter different factors in the growth or are greater. For the $N = 8k + 3$, the strategy consists of measuring the Bell operator from Eq. (15) on $M = N - 1$ qubits. Then we have:

$$\begin{aligned} \langle \mathcal{B}_N \rangle_Q &\geq \sum_{m=2,4,\dots}^M \binom{M}{m} \left(\frac{1}{\sqrt{2}}\right)^{M-m+2} = \frac{1}{2} \left[\sum_{m \text{ even}}^M \binom{M}{m} \left(\frac{1}{\sqrt{2}}\right)^{M-m} \right] - \left(\frac{1}{\sqrt{2}}\right)^{M+2} \\ &= \frac{1}{4} \left[\left(1 + \frac{1}{\sqrt{2}}\right)^M - \left(1 - \frac{1}{\sqrt{2}}\right)^M \right] - \left(\frac{1}{\sqrt{2}}\right)^{M+2}. \end{aligned} \quad (116)$$

Checking the ratio of the quantum and classical values, we have that

$$\frac{\langle \mathcal{B}_N \rangle_Q}{\langle \mathcal{B}_N \rangle_C} \underset{N \rightarrow \infty}{\sim} \frac{\frac{1}{4} \left(1 + \frac{1}{\sqrt{2}}\right)^{N-1}}{2^{\frac{N-1}{2}}} = \frac{\left(1 + \frac{1}{\sqrt{2}}\right)^{N-1}}{\sqrt{2}^{N+3}} \approx \frac{1.20711^N}{2\sqrt{2} + 2}. \quad (117)$$

Looking at the expectation values from Lemma 5, it is straightforward to see that in all other cases of N , correlations are stronger than in the $N = 8k + 3$ case, so the quantum violation increases. \square

APPENDIX F: BELL AND SEPARABILITY INEQUALITY VIOLATIONS FOR FULLY-CONNECTED FOUR-UNIFORM HYPERGRAPH STATES AFTER LOSING ONE QUBIT

Lemma 7. *The following statement holds for $N = 8k + 4$ qubit, four-uniform complete hypergraph states:*

$$\langle G_6 \rangle = \langle \underbrace{X \dots X}_m \underbrace{Z \dots Z}_m \mathbb{1} \rangle = \begin{cases} -\left(\frac{1}{\sqrt{2}}\right)^{N-m+2} & \text{if } m = 0 \pmod 4, \\ +\left(\frac{1}{\sqrt{2}}\right)^{N-m+2} & \text{if } m = 2 \pmod 4. \end{cases} \quad (118)$$

Proof. The derivation of this result is very similar to the combinatorial calculations in the appendices D and E. Since m is even, we refer to the Table 6 to see what gates remain after regrouping hyperedges on the right hand side of the expression (118):

Case # 1: If $m = 0 \pmod 4$:

$$\begin{aligned} \langle G_6 \rangle &= \pm \langle + |^{\otimes N} \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \prod_{\forall \otimes, \Delta, \diamond} C_{\otimes \Delta \Delta} C_{\otimes \Delta} C_{\otimes \Delta \diamond} C_{\otimes \diamond} C_{\otimes \otimes \otimes} C_{\otimes \otimes} C_{\otimes} | + \rangle^{\otimes N} \\ &= \pm \frac{1}{2^N} \text{Tr} \left[\prod_{\forall \otimes, \Delta, \diamond} C_{\otimes \Delta \Delta} C_{\otimes \Delta} C_{\otimes \Delta \diamond} C_{\otimes \diamond} C_{\otimes \otimes \otimes} C_{\otimes \otimes} C_{\otimes} C_{\Delta} \right]. \end{aligned} \quad (119)$$

Here \otimes again refers to X operator, Δ to Z and \diamond to $\mathbb{1}$ and it is denoted as γ . The strategy now is similar to the previous proofs: count the number of +1's and -1's on the diagonal and then their difference divided by 2^N gives the trace.

We use $(-1)^s$ to define the sign of the diagonal element and $s = \binom{\alpha}{1} \binom{\beta}{2} + \binom{\alpha}{1} \binom{\beta}{1} + \binom{\alpha}{1} \binom{\beta}{1} (\gamma) + \binom{\alpha}{1} (\gamma) + \binom{\alpha}{3} + \binom{\alpha}{2} + \binom{\alpha}{1} + \binom{\beta}{1}$. If s is even, the value on the diagonal is +1 and -1, otherwise. We consider all possible values of α , β , and γ :

a) If γ is even (that is $\gamma = 0$):

1. α is even & β is even if $\alpha = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $\alpha = 2 \pmod 4 \Rightarrow (-1)^s = -1$
2. α is even & β is odd: if $\alpha = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $\alpha = 2 \pmod 4 \Rightarrow (-1)^s = +1$

From here one can easily spot that for even α , there is equal number of +1 and -1 on the diagonal. So, they do not contribute in the calculations. We now consider the odd α :

3. α is odd & β is even if $\beta = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $\beta = 2 \pmod 4 \Rightarrow (-1)^s = +1$
4. α is odd & β is odd: if $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$

b) If γ is odd (that is $\gamma = 1$):

The cases **1** and **2** don't change. Therefore, they sum up to 0.

3. α is odd & β is even if $\beta = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $\beta = 2 \pmod 4 \Rightarrow (-1)^s = -1$

4. Stays the same as in the previous case.

Therefore the result is:

$$\begin{aligned} \langle G_6 \rangle &= \pm \frac{1}{2^N} \left(\sum_{\gamma \text{ even}} \binom{\gamma}{0} \left[\sum_{\alpha \text{ odd}} \binom{m}{\alpha} \left[\sum_{\beta=0,4,\dots}^{N-m-1} -\binom{N-m-1}{\beta} - \binom{N-m-1}{\beta+1} + \binom{N-m-1}{\beta+2} + \binom{N-m-1}{\beta+3} \right] \right] \right. \\ &\quad \left. + \sum_{\gamma \text{ odd}} \binom{\gamma}{1} \left[\sum_{\alpha \text{ odd}} \binom{m}{\alpha} \left[\sum_{\beta=0,4,\dots}^{N-m-1} \binom{N-m-1}{\beta} - \binom{N-m-1}{\beta+1} - \binom{N-m-1}{\beta+2} + \binom{N-m-1}{\beta+3} \right] \right] \right) \\ &= \pm \frac{2^m}{2^N} \cdot (-\text{Im}[(1+i)^{N-m-1}]) = \mp \left(\frac{1}{\sqrt{2}} \right)^{N-m+2} \end{aligned} \quad (120)$$

It is time to fix a sign. One needs to keep in mind that the sign of the Eq. (120) is negative: if $m = 4 \pmod 8$, the global sign from the Table 6 is negative, and $\text{Im}[(1+i)^{N-m-1}] = -2^{\frac{N-m-2}{2}}$. Therefore, an overall sign is negative. If $m = 0 \pmod 8$, global sign is positive and $\text{Im}[(1+i)^{N-m-1}] = 2^{\frac{N-m-2}{2}}$. Therefore, an overall sign is negative.

Case # 2: If $m = 2 \pmod 4$:

$$\begin{aligned} \langle G_6 \rangle &= \pm \langle + | \otimes^N \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \prod_{\forall \otimes, \Delta, \diamond} C_{\otimes \Delta \Delta} C_{\otimes \otimes \otimes} C_{\Delta \Delta} C_{\otimes \Delta \diamond} C_{\Delta \diamond} | + \rangle^{\otimes N} \\ &= \pm \frac{1}{2^N} \text{Tr} \left(\prod_{\forall \otimes, \Delta, \diamond} C_{\otimes \Delta \Delta} C_{\otimes \otimes \otimes} C_{\Delta \Delta} C_{\otimes \Delta \diamond} C_{\Delta \diamond} C_{\Delta} \right). \end{aligned} \quad (121)$$

We use $(-1)^s$ to define the sign of the diagonal element and $s = \binom{\alpha}{1} \binom{\beta}{2} + \binom{\alpha}{1} \binom{\beta}{1} \binom{\gamma}{1} + \binom{\alpha}{3} + \binom{\beta}{2} + \binom{\beta}{1} \binom{\gamma}{1} + \binom{\beta}{1}$. If s is even, the value on the diagonal is $+1$ and -1 , otherwise. We consider all possible values of α , β , and γ :

a) If γ is even (that is $\gamma = 0$):

Considering the terms from even α :

1. α is even & β is even if $\beta = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $\beta = 2 \pmod 4 \Rightarrow (-1)^s = -1$
2. α is even & β is odd: if $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$

Considering odd α :

3. α is odd & β is even if $(\alpha - 1) = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $(\alpha - 1) = 2 \pmod 4 \Rightarrow (-1)^s = -1$
4. α is odd & β is odd: if $(\alpha - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\alpha - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$

It is easy to see that cases **3** and **4** adds up to 0.

b) If γ is odd (that is $\gamma = 1$):

1. Stays the same as in the previous case.
2. Gets an opposite sign, therefore, will cancel out with the a) case **2** in the sum.
3. Stays the same as in the previous case.
4. Stays the same as in the previous case.

Therefore the result is:

$$\langle G_6 \rangle = \pm \frac{1}{2^N} 2^m \left[\sum_{\beta=0,4,\dots}^{N-m-1} \binom{N-m-1}{\beta} - \binom{N-m-1}{\beta+2} \right] = \pm \frac{2^m}{2^N} \text{Re}[(1+i)^{N-m-1}]. \quad (122)$$

It is time to fix a sign: if $m = 2 \pmod 8$, the global sign is positive from the Table 6, and $\text{Re}[(1+i)^{N-m-1}] = 2^{\frac{N-m-2}{2}}$. Therefore, an overall sign is positive. If $m = 6 \pmod 8$, overall sign is negative and $\text{Re}[(1+i)^{N-m-1}] = -2^{\frac{N-m-2}{2}}$. Therefore, an overall sign is positive. \square

Lemma 8. *A N -qubit ($N = 8k + 4$) four-uniform HG state even after tracing out one party violates the classical bound by an amount that grows exponentially with number of qubits. Moreover, the violation only decreases with the constant factor.*

Proof. Denote $M \equiv N - 1$. Then

$$\begin{aligned} \langle \mathcal{B}_N \rangle_Q &= \sum_{m=2,4,\dots}^M \binom{M}{m} \left(\frac{1}{\sqrt{2}} \right)^{M-m+3} = \frac{1}{2\sqrt{2}} \left[\sum_{m \text{ even}}^M \binom{M}{m} \left(\frac{1}{\sqrt{2}} \right)^{M-m} \right] - \left(\frac{1}{\sqrt{2}} \right)^{M+3} \\ &= \frac{1}{4\sqrt{2}} \left[\left(1 + \frac{1}{\sqrt{2}} \right)^M - \left(1 - \frac{1}{\sqrt{2}} \right)^M \right] - \left(\frac{1}{\sqrt{2}} \right)^{M+3} \end{aligned} \quad (123)$$

Checking the ratio of the quantum and classical values, we have that

$$\frac{\langle \mathcal{B}_{N-1} \rangle_Q}{\langle \mathcal{B}_{N-1} \rangle_C} \stackrel{N \rightarrow \infty}{\sim} \frac{\frac{1}{4\sqrt{2}} \left(1 + \frac{1}{\sqrt{2}}\right)^{N-1}}{2^{\frac{N-2}{2}}} = \frac{\left(1 + \frac{1}{\sqrt{2}}\right)^{N-1}}{\sqrt{2}^{N+3}} \approx \frac{1.20711^N}{2\sqrt{2} + 2}. \quad (124)$$

While the same value for the $N = 8k + 4$ qubit four-uniform complete HG state is $\frac{\langle \mathcal{B}_N \rangle_Q}{\langle \mathcal{B}_N \rangle_C} \stackrel{N \rightarrow \infty}{\sim} \approx \frac{1.20711^N}{4}$. Therefore, after tracing out a single qubit, the local realism violation decreases with the small constant factor. \square

It is important to note that the similar violation is maintained after tracing out more than one qubit. For example, numerical evidence confirms for $N = 12$, that if one takes a Bell inequality with the odd number of X measurements, instead of the even ones as we have chosen in the proof, an exponential violation is maintained after tracing out 2 qubits. But even if 5 qubit is traced out, the state is still entangled and this can be verified using the separability inequality [26]. Exact violation is given in the following table:

#k	Quantum Value	Classical Bound	Separability Bound	\approx Ratio
0	153.141	64		2.39283
1	89.7188	32		2.78125
2	37.1563	32		1.16113
3	15.4219	-	$\sqrt{2}$	10.9049
4	6.375	-	$\sqrt{2}$	4.50781
5	2.70313	-	$\sqrt{2}$	1.9114

Table 7. Violation of Bell (for odd m) and Separability inequalities in $N = 12$ qubit 4-uniform HG state. Here k is the number of traced out qubits. Red line represents that when $k = 1$, or equivalently one qubit is traced out, the violation of Bell inequalities increases. This is caused by decrease in the classical bound [3].

APPENDIX G: SEPARABILITY INEQUALITY VIOLATIONS FOR FULLY-CONNECTED THREE-UNIFORM HYPERGRAPH STATES AFTER LOSING ONE QUBIT

Lemma 9. *The following statements holds three-uniform complete hypergraph states:*

(i) For $N = 8k + 5$, $N = 8k + 6$, or $N = 8k + 7$:

$$\langle G_7 \rangle = \langle \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \rangle = \begin{cases} -\frac{1}{2^{\lfloor \frac{N-1}{2} \rfloor}} & \text{if } (m-1) = 0 \text{ mod } 4, \\ +\frac{1}{2^{\lfloor \frac{N-1}{2} \rfloor}} & \text{if } (m-1) = 2 \text{ mod } 4. \end{cases} \quad (125)$$

(ii) For $N = 8k + 1$, $N = 8k + 2$, or $N = 8k + 3$:

$$\langle G_7 \rangle = \langle \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \rangle = \begin{cases} +\frac{1}{2^{\lfloor \frac{N-1}{2} \rfloor}} & \text{if } (m-1) = 0 \text{ mod } 4, \\ -\frac{1}{2^{\lfloor \frac{N-1}{2} \rfloor}} & \text{if } (m-1) = 2 \text{ mod } 4. \end{cases} \quad (126)$$

(iii) For $N = 4k$:

$$\langle G_7 \rangle = \langle \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \rangle = 0 \quad (127)$$

Proof. As a starting point, we derive the remaining gates on the right hand side of the equations (125), the same derivation turns out to be working for Eq. (126) and (127). This approach is analogous to the Appendix B, but now, m is odd.

1. $\# \otimes \otimes = \binom{m-2}{1}$ is odd $\Rightarrow C_{\otimes \otimes}$ remains.
2. $\# \otimes = \binom{m-1}{2} = \frac{(m-1)(m-2)}{2}$ is $\begin{cases} \text{even, if } (m-1) = 0 \pmod{4} & \Rightarrow C_{\otimes} \text{ cancels.} \\ \text{odd, if } (m-1) = 2 \pmod{4} & \Rightarrow C_{\otimes} \text{ remains.} \end{cases}$
3. $\# \{ \} = \binom{m}{3} = \frac{m(m-1)(m-2)}{2 \cdot 3}$ is $\begin{cases} \text{even, if } (m-1) = 0 \pmod{4} & \Rightarrow \text{gives a positive sign.} \\ \text{odd, if } (m-1) = 2 \pmod{4} & \Rightarrow \text{gives a negative sign.} \end{cases}$
4. $\# \triangle \triangle = \binom{m}{1}$ is odd $\Rightarrow C_{\triangle \triangle}$ remains.
5. $\# \otimes \triangle = \binom{m-1}{1}$ is even $\Rightarrow C_{\otimes \triangle}$ cancels.
6. $\# \triangle = \binom{m}{2} = \frac{m(m-1)}{2 \cdot 3}$ is $\begin{cases} \text{even, if } (m-1) = 0 \pmod{4} & \Rightarrow C_{\triangle} \text{ cancels.} \\ \text{odd, if } (m-1) = 2 \pmod{4} & \Rightarrow C_{\triangle} \text{ remains.} \end{cases}$

Table 8. Counting phase gates for a three-uniform HG when m (m is odd) systems are measured in X direction.

Consider two cases:

1. If $(m-1) = 0 \pmod{4}$:

$$\begin{aligned} \langle G_7 \rangle &= \pm \langle + |^{\otimes N} \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \prod_{\forall \otimes, \triangle, \diamond} C_{\otimes \otimes} C_{\triangle \triangle} C_{\triangle \diamond} | + \rangle^{\otimes N} \\ &= \pm \frac{1}{2^N} \text{Tr} [C_{\otimes \otimes} C_{\triangle \triangle} C_{\triangle \diamond} C_{\triangle}]. \end{aligned} \quad (128)$$

Here \otimes again refers to X operator, \triangle to Z and \diamond to $\mathbb{1}$ and is denoted by γ . The strategy is similar to the previous case: count the number of +1's and -1's on the diagonal. Their difference divided by 2^N , gives the trace.

We use $(-1)^s$ to define the sign of the diagonal element and $s = \binom{\alpha}{2} + \binom{\beta}{2} + \binom{\beta}{1} \binom{\gamma}{1} + \binom{\beta}{1}$. If s is even, the value on the diagonal is +1 and -1, otherwise. We consider all possible values of α , β and γ :

- a) If γ is even (that is $\gamma = 0$):

Considering the terms from even β :

1. β is even & α is even if $\alpha = 0 \pmod{4}$ and $\beta = 0 \pmod{4} \Rightarrow (-1)^s = +1$
if $\alpha = 0 \pmod{4}$ and $\beta = 2 \pmod{4} \Rightarrow (-1)^s = -1$
if $\alpha = 2 \pmod{4}$ and $\beta = 0 \pmod{4} \Rightarrow (-1)^s = -1$
if $\alpha = 2 \pmod{4}$ and $\beta = 2 \pmod{4} \Rightarrow (-1)^s = +1$
2. β is even & α is odd if $(\alpha-1) = 0 \pmod{4}$ and $\beta = 0 \pmod{4} \Rightarrow (-1)^s = +1$
if $(\alpha-1) = 0 \pmod{4}$ and $\beta = 2 \pmod{4} \Rightarrow (-1)^s = -1$
if $(\alpha-1) = 2 \pmod{4}$ and $\beta = 0 \pmod{4} \Rightarrow (-1)^s = -1$
if $(\alpha-1) = 2 \pmod{4}$ and $\beta = 2 \pmod{4} \Rightarrow (-1)^s = +1$

Considering odd β :

- 3.** β is odd & α is even if $\alpha = 0 \pmod 4$ and $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $\alpha = 0 \pmod 4$ and $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$
if $\alpha = 2 \pmod 4$ and $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $\alpha = 2 \pmod 4$ and $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = -1$
- 4.** β is odd & α is odd if $(\alpha - 1) = 0 \pmod 4$ and $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\alpha - 1) = 0 \pmod 4$ and $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$
if $(\alpha - 1) = 2 \pmod 4$ and $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $(\alpha - 1) = 2 \pmod 4$ and $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = -1$

b) If γ is odd (that is $\gamma = 1$):

Considering the terms from even β :

1. and **2.** Nothing changes in comparison to a) **1.** and **2.**

3. and **4.** These two terms have opposite sign from a) **3.** and **4.** Therefore, in the sum they cancel (γ is always 1.)

Therefore,

$$\begin{aligned} \langle G_7 \rangle &= \frac{1}{2^{N-1}} \left[\sum_{\beta=0,4,\dots}^{N-m-1} \binom{N-m-1}{\beta} - \binom{N-m-1}{\beta+2} \right] \left[\sum_{\alpha=0,4,\dots}^m \binom{m}{\alpha} + \binom{m}{\alpha+1} - \binom{m}{\alpha+2} - \binom{m}{\alpha+3} \right] \\ &= \frac{1}{2^{N-1}} \operatorname{Re}[(1+i)^{N-m-1}] \cdot \left(\operatorname{Re}[(1+i)^m] + \operatorname{Im}[(1+i)^m] \right). \end{aligned} \quad (129)$$

Now we can consider each cases separately, for this we use the lookup **table 0**:

(i) If $N = 8k + 5$ and if $(m - 1) = 4 \pmod 8$, $\operatorname{Re}[(1+i)^{N-m-1}] = -2^{\frac{N-m-2}{2}}$ and $\operatorname{Re}[(1+i)^m] + \operatorname{Im}[(1+i)^m] = 2^{\frac{m+1}{2}}$. Therefore,

$$\langle G_7 \rangle = -\frac{2^{\frac{N-m-2}{2}} \cdot 2^{\frac{m+1}{2}}}{2^{N-1}} = -\left(\frac{1}{2}\right)^{\frac{N-1}{2}}. \quad (130)$$

And, if $(m - 1) = 0 \pmod 8$, $\operatorname{Re}[(1+i)^{N-m-1}] = +2^{\frac{N-m-2}{2}}$ and $\operatorname{Re}[(1+i)^m] + \operatorname{Im}[(1+i)^m] = -2^{\frac{m+1}{2}}$. Therefore,

$$\langle G_7 \rangle = -\frac{2^{\frac{N-m-2}{2}} \cdot 2^{\frac{m+1}{2}}}{2^{N-1}} = -\left(\frac{1}{2}\right)^{\frac{N-1}{2}}. \quad (131)$$

Exactly the same is true for $N = 8k + 7$. But for $N = 8k + 6$ and if $(m - 1) = 4 \pmod 8$, $\operatorname{Re}[(1+i)^{N-m-1}] = -2^{\frac{N-m-1}{2}}$ and $\operatorname{Re}[(1+i)^m] + \operatorname{Im}[(1+i)^m] = 2^{\frac{m+1}{2}}$. Therefore,

$$\langle G_7 \rangle = -\frac{2^{\frac{N-m-1}{2}} \cdot 2^{\frac{m+1}{2}}}{2^{N-1}} = -\left(\frac{1}{2}\right)^{\lfloor \frac{N-1}{2} \rfloor}. \quad (132)$$

And, if $(m - 1) = 0 \pmod 8$, $\operatorname{Re}[(1+i)^{N-m-1}] = 2^{\frac{N-m-1}{2}}$ and $\operatorname{Re}[(1+i)^m] + \operatorname{Im}[(1+i)^m] = -2^{\frac{m+1}{2}}$. Therefore,

$$\langle G_7 \rangle = -\frac{2^{\frac{N-m-1}{2}} \cdot 2^{\frac{m+1}{2}}}{2^{N-1}} = -\left(\frac{1}{2}\right)^{\lfloor \frac{N-1}{2} \rfloor}. \quad (133)$$

(ii) If $N = 8k + 1$ and if $(m - 1) = 4 \pmod 8$, $\operatorname{Re}[(1+i)^{N-m-1}] = -2^{\frac{N-m-2}{2}}$ and $\operatorname{Re}[(1+i)^m] + \operatorname{Im}[(1+i)^m] = -2^{\frac{m+1}{2}}$. Therefore,

$$\langle G_7 \rangle = \frac{2^{\frac{N-m-2}{2}} \cdot 2^{\frac{m+1}{2}}}{2^{N-1}} = \left(\frac{1}{2}\right)^{\frac{N-1}{2}}. \quad (134)$$

And, if $(m-1) = 0 \pmod 8$, $Re[(1+i)^{N-m-1}] = 2^{\frac{N-m-1}{2}}$ and $Re[(1+i)^m] + Im[(1+i)^m] = 2^{\frac{m+1}{2}}$. Therefore,

$$\langle G_7 \rangle = \frac{2^{\frac{N-m-1}{2}} \cdot 2^{\frac{m+1}{2}}}{2^{N-1}} = \left(\frac{1}{2}\right)^{\lfloor \frac{N-1}{2} \rfloor}. \quad (135)$$

It is analogous for other two cases as well.

(iii) For $N = 4k$, $Re[(1+i)^{N-m-1}] = 0$. Therefore, $\langle G_7 \rangle = 0$.

2. If $(m-1) = 2 \pmod 4$:

$$\begin{aligned} \langle G_7 \rangle &= \langle + |^{\otimes N} \underbrace{X \dots X}_m \underbrace{Z \dots Z}_{N-m-1} \mathbb{1} \prod_{\forall \otimes, \Delta, \diamond} C_{\otimes \otimes} C_{\otimes} C_{\Delta \Delta} C_{\Delta \diamond} C_{\Delta} C_{\diamond} | + \rangle^{\otimes N} \\ &= \frac{1}{2^N} Tr \left[C_{\otimes \otimes} C_{\otimes} C_{\Delta \Delta} C_{\Delta \diamond} C_{\diamond} \right]. \end{aligned} \quad (136)$$

Here \otimes again refers to X operator, Δ to Z and \diamond to $\mathbb{1}$ and is denoted by γ . The strategy is similar to the previous case: count the number of +1's and -1's on the diagonal and their difference divided by 2^N , gives the trace.

We use $(-1)^s$ to define the sign of the diagonal element and $s = \binom{\alpha}{2} + \binom{\alpha}{1} + \binom{\beta}{2} + \binom{\beta}{1} \binom{\gamma}{1} + \binom{\gamma}{1}$. If s is even, the value on the diagonal is +1 and -1, otherwise. We consider all possible values of α , β and γ :

a) If γ is even (that is $\gamma = 0$):

Considering the terms from even β :

1. β is even & α is even if $\alpha = 0 \pmod 4$ and $\beta = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $\alpha = 0 \pmod 4$ and $\beta = 2 \pmod 4 \Rightarrow (-1)^s = -1$
if $\alpha = 2 \pmod 4$ and $\beta = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $\alpha = 2 \pmod 4$ and $\beta = 2 \pmod 4 \Rightarrow (-1)^s = +1$
2. β is even & α is odd if $(\alpha - 1) = 0 \pmod 4$ and $\beta = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\alpha - 1) = 0 \pmod 4$ and $\beta = 2 \pmod 4 \Rightarrow (-1)^s = +1$
if $(\alpha - 1) = 2 \pmod 4$ and $\beta = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $(\alpha - 1) = 2 \pmod 4$ and $\beta = 2 \pmod 4 \Rightarrow (-1)^s = -1$

Considering odd β :

3. β is odd & α is even if $\alpha = 0 \pmod 4$ and $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $\alpha = 0 \pmod 4$ and $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = -1$
if $\alpha = 2 \pmod 4$ and $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $\alpha = 2 \pmod 4$ and $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$
4. β is odd & α is odd if $(\alpha - 1) = 0 \pmod 4$ and $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = -1$
if $(\alpha - 1) = 0 \pmod 4$ and $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = +1$
if $(\alpha - 1) = 2 \pmod 4$ and $(\beta - 1) = 0 \pmod 4 \Rightarrow (-1)^s = +1$
if $(\alpha - 1) = 2 \pmod 4$ and $(\beta - 1) = 2 \pmod 4 \Rightarrow (-1)^s = -1$

b) If γ is odd (that is $\gamma = 1$):

1. and 2. These two terms have opposite sign from a) 1. and 2. Therefore, in the sum they cancel (γ is always 1.)

3. and 4. Nothing changes in comparison to a) 3. and 4.

Therefore,

$$\begin{aligned} \langle G_7 \rangle &= \frac{1}{2^{N-1}} \left[\sum_{\beta=0,4,\dots}^{N-m-1} \binom{N-m-1}{\beta+1} - \binom{N-m-1}{\beta+3} \right] \left[\sum_{\alpha=0,4,\dots}^m \binom{m}{\alpha} - \binom{m}{\alpha+1} - \binom{m}{\alpha+2} + \binom{m}{\alpha+3} \right] \\ &= \frac{1}{2^{N-1}} \text{Im}[(1+i)^{N-m-1}] \cdot \left(\text{Re}[(1+i)^m] - \text{Im}[(1+i)^m] \right). \end{aligned} \quad (137)$$

Now we can consider each cases separately, for this we use the lookup **table 0**:

(i) If $N = 8k + 5$ and if $(m-1) = 4 \pmod{8}$, $\text{Im}[(1+i)^{N-m-1}] = 2^{\frac{N-m-2}{2}}$ and $\text{Re}[(1+i)^m] - \text{Im}[(1+i)^m] = -2^{\frac{m+1}{2}}$. And the overall sign from the Table 8 is negative. Therefore,

$$\langle G_7 \rangle = -\frac{2^{\frac{N-m-2}{2}} \cdot (-2^{\frac{m+1}{2}})}{2^{N-1}} = \left(\frac{1}{2}\right)^{\frac{N-1}{2}}. \quad (138)$$

And, if $(m-1) = 0 \pmod{8}$, $\text{Im}[(1+i)^{N-m-1}] = -2^{\frac{N-m-2}{2}}$ and $\text{Re}[(1+i)^m] - \text{Im}[(1+i)^m] = 2^{\frac{m+1}{2}}$. Overall sign in negative. Therefore,

$$\langle G_7 \rangle = -\frac{-2^{\frac{N-m-2}{2}} \cdot 2^{\frac{m+1}{2}}}{2^{N-1}} = \left(\frac{1}{2}\right)^{\frac{N-1}{2}}. \quad (139)$$

The same holds for $N = 8k + 6$ and $N = 8k + 7$. Besides, (ii) differs with the sign flip and is trivial to check. It is also trivial to prove (iii), as when $N = 4k$, $\text{Im}[(1+i)^{N-m-1}] = 0$. \square

Lemma 10. *A N -qubit (except when $N = 4k$) three-uniform HG state violates the separability inequality exponentially after tracing out a single qubit.*

Proof. We consider only one case, $N = 8k + 5$, as others are analogous. Here $M = N - 1$:

$$\langle \mathcal{B}_N \rangle_Q = \sum_{m \text{ odd}}^M \binom{M}{m} \left(\frac{1}{\sqrt{2}}\right)^M = 2^{M-1} \cdot 2^{-M/2} = \sqrt{2}^{N-3}. \quad (140)$$

Separability bound is $\sqrt{2}$ [26] and it does not depend on the number of qubits. \square

It is important to note that the similar violation is maintained after tracing out more than one qubit. Numerical evidence for $N = 11$ is presented below.

#k	Quantum Value	Separability Bound	\approx Ratio
0	511.5	$\sqrt{2}$	361.69
1	16	$\sqrt{2}$	11.31
2	8	$\sqrt{2}$	5.66
3	4	$\sqrt{2}$	2.83
4	2	$\sqrt{2}$	1.414

Table 9. Violation of the separability inequalities [26] in $N = 11$ -qubit 3-uniform HG states. Here k is the number of traced out qubits. When $k = 0$, the Mermin inequality is violated as expected.

-
- [1] P. Hayden, D.W. Leung, and A. Winter, *Comm. Math. Phys.* **265**, 95 (2006); D. Gross, S. Flammia, and J. Eisert, *Phys. Rev. Lett.* **102**, 190501 (2009); M. J. Bremner, C. Mora, and A. Winter, *Phys. Rev. Lett.* **102**, 190502 (2009).
[2] M. Hein, W. Dür, J. Eisert, R. Raussendorf, M. Van den

- Nest, and H.-J. Briegel, *Entanglement in Graph States and its Applications*, in *Quantum Computers, Algorithms and Chaos*, edited by G. Casati, D.L. Shepelyansky, P. Zoller, and G. Benenti (IOS Press, Amsterdam, 2006), quant-ph/0602096.
[3] N. D. Mermin, *Phys. Rev. Lett.* **65**, 1838 (1990).
[4] O. Gühne, G. Tóth, P. Hyllus, and H. J. Briegel, *Phys. Rev. Lett.* **95**, 120405 (2005); G. Tóth, O. Gühne, H. J. Briegel, *Phys. Rev. A* **73**, 022303 (2006).

- [5] O. Gühne and G. Tóth, *Phys. Rep.* **474**, 1 (2009).
- [6] C. Kruszynska and B. Kraus, *Phys. Rev. A* **79**, 052304 (2009).
- [7] R. Qu, J. Wang, Z. Li, and Y. Bao, *Phys. Rev. A* **87**, 022311 (2013).
- [8] M. Rossi, M. Huber, D. Bruß, and C. Macchiavello, *New J. Phys.* **15**, 113022 (2013).
- [9] O. Gühne, M. Cuquet, F. E. S. Steinhoff, T. Moroder, M. Rossi, D. Bruß, B. Kraus, and C. Macchiavello, *J. Phys. A: Math. Theor.* **47**, 335303 (2014).
- [10] X.-Y. Chen and L. Wang, *J. Phys. A: Math. Theor.* **47**, 415304 (2014).
- [11] D. W. Lyons, D. J. Upchurch, S. N. Walck, and C. D. Yetter, *J. Phys. A: Math. Theor.* **48**, 095301 (2015).
- [12] M. Rossi, D. Bruß, and C. Macchiavello, *Phys. Scr.* **T160**, 014036 (2014).
- [13] H. Buhrman, R. Cleve, J. Watrous, and R. de Wolf, *Phys. Rev. Lett.* **87**, 167902 (2001), C.E. Mora, H.J. Briegel, and B. Kraus, *Int. J. Quantum Inform.* **5**, 729 (2007).
- [14] A. B. Grilo, I. Kerenidis, and J. Sikora, arXiv:1410.2882.
- [15] B. Yoshida, arXiv:1508.03468.
- [16] J. Miller and A Miyake, arXiv:1508.02695.
- [17] L. Hardy, *Phys. Rev. Lett.* **71**, 1665 (1993).
- [18] G. Svetlichny, *Phys. Rev. D* **35**, 3066 (1987).
- [19] S. Popescu and D. Rohrlich, *Phys. Lett. A* **166**, 293 (1992).
- [20] R. F. Werner and M. M. Wolf, *Phys. Rev. A* **64**, 032112 (2001); M. Żukowski and C. Brukner, *Phys. Rev. Lett.* **88**, 210401 (2002).
- [21] N. Brunner, D. Cavalcanti, S. Pironio, V. Scarani, and S. Wehner, *Rev. Mod. Phys.* **86**, 419 (2014).
- [22] C. Brukner, M. Żukowski, J.-W. Pan, and A. Zeilinger, *Phys. Rev. Lett.* **92**, 127901 (2004).
- [23] S. Abramsky and C. Constantin, *Electronic Proc. Theor. Comp. Science* **171**, 10 (2014), arXiv:1412.5213.
- [24] Z. Wang and D. Markham, *Phys. Rev. Lett.* **108**, 210407 (2012).
- [25] The appendix can be found in the supplementary online material.
- [26] S. M. Roy, *Phys. Rev. Lett.* **94**, 010402 (2005).
- [27] V. Giovannetti, S. Lloyd, and L. Maccone, *Science* **306**, 1330 (2004).
- [28] W.-B. Gao, C.-Y. Lu, X.-C. Yao, P. Xu, O. Gühne, A. Goebel, Y.-A. Chen, C.-Z. Peng, Z.-B. Chen, and J.-W. Pan, *Nature Phys.* **6**, 331 (2010).
- [29] M. J. Hoban, E. T. Campbell, K. Loukopoulos, and D. E. Browne, *New J. Phys.* **13**, 023014 (2011).
- [30] D. Collins, N. Gisin, S. Popescu, D. Roberts, and V. Scarani, *Phys. Rev. Lett.* **88**, 170405 (2002).
- [31] M. Koashi, V. Buzek, and N. Imoto, *Phys. Rev. A* **62**, 050302(R) (2000).