

2CIM: Area-Efficient 2-Cycle Integer Multipliers

Ahmad Houraniah

*Department of Computer Science
Özyeğin University
Istanbul, Turkey
ahmad.houraniah@ozu.edu.tr*

H. Fatih Ugurdag

*Department of Electrical
and Electronics Engineering
Özyeğin University
Istanbul, Turkey
fatih.ugurdag@ozyegin.edu.tr*

Cengiz Emre Dedeagac

*Department of Computer Science
Özyeğin University
Istanbul, Turkey
emre.dedeagac@ozu.edu.tr*

Abstract—Fast multipliers with large bit widths can occupy significant silicon area, which, in turn, can be minimized by employing multi-cycle multipliers. This paper introduces architectures and parameterized Verilog circuit generators for 2-cycle integer multipliers. When implementing an algorithm in hardware, it is common that less than 1 multiplication needs to be performed per clock cycle. It is also possible that the multiplications per cycle is a fractional number, e.g., 3.5. In such case, we can surely use 4 multipliers, each with a throughput of 1 result per cycle. However, we can instead use 3 such multipliers plus a multiplier with a throughput of 1/2. Resource sharing allows a multiplier with a lower throughput to be smaller, hence area savings. These multipliers offer customization in regards to the latency and clock frequency. All proposed designs were automatically synthesized and tested for various bit widths. Two main architectures are presented in this work, and each has several variants. Our 2-cycle multipliers offer up to 21%, 42%, 32%, 41%, and 48% of area savings for bit widths of 8, 16, 32, 64, and 128, with respect to synthesizing the “*” operator with throughput of 1. Furthermore, some of the proposed designs also offer power savings under certain conditions.

Index Terms—computer arithmetic, multi-cycle multiplier, resource-sharing, pipelining

I. INTRODUCTION

An integer multiplier is an essential building block for various ASICs and CPUs. Integer multipliers can get quite expensive in terms of area as bit width increases. Large integers are used in a wide range of applications that require a high degree of precision. Floating-point operations are unsuitable for some applications because of so-called “catastrophic cancellations” [1]. The addition and subtraction of floating-point numbers that greatly vary in magnitude can produce rounding errors, resulting in significant data loss. Floating-point operations are significantly more expensive than fixed-point operations regarding area complexity and latency. For these reasons, fixed point representation is preferred for many applications. The CUDA [2] programming model and software environment, which NVIDIA develops, recently introduced a 128-bit integer data type, which is intended for applications that require a higher degree of precision within a predetermined range. This signifies the importance of large fixed-point integers. Multiplying such large integers can require significant hardware resources. For this reason, decreasing the area complexity for integer multipliers can be very beneficial.

There exists a large number of applications containing data flow paths that require less than one multiplication every two or more clock cycles. Such a case is found in RSIC-V softcore implementations, where area efficiency is vital, even if it comes at the expense of increasing the latency of ALU operations such as multiplication.

Applications can contain numerous multiplications in their data flow paths. Due to the area complexity of these multipliers, the same multiplication circuits are used multiple times to minimize the area complexity of the system. These multiplications typically need to be computed within a predefined period. Since a conventional multiplier can only be used once in every clock cycle, using a single multiplier can severely limit the system’s throughput. The throughput can be maintained by using several multiplication circuits operating in parallel. The number of multipliers necessary can be calculated by dividing the number of multiplications by the period they need to be computed within (in clock cycles). Using this formula, the number of multipliers required is not always an integer. The conventional approach is to round up this value, which causes one of these multipliers to be underutilized. A fully-pipelined multiplier that can accept new inputs in consecutive clock cycles would remain underutilized in such applications.

In this work, various 2-cycle unsigned integer multiplier (2CIM) designs are proposed to decrease the area complexity for these underutilized multipliers. 2CIM architectures can be extended for signed integer multiplication as well. 2CIM designs offer partial multipliers that can offer area-efficient designs with a throughput of 1/2. The conventional approach of multiplying unsigned integers comprises two steps: partial product generation (PPG) and partial production summation. The PPG stage is typically done using AND gates, where one integer is shifted and multiplied with each bit of the other integer. The PPG stage produces multiple variables that must be summed to produce the multiplication result. This is done using a tree of full adder (FA) and half adder (HA) cells. Using a standard ripple carry adder structure to handle the partial product summation can result in a long critical path and an increased area complexity. The optimization of integer multiplications has been a thoroughly studied topic, and the conventional approach is to use a carry-save adder for the summation stage.

Multiplication can be solved using a divide and conquer

strategy, where any multiplication can be divided into multiple smaller ones, this is often seen as an algorithmic problem, and a great deal of research was done to reduce the algorithmic complexity of multiplications. The same concepts used for reducing the algorithmic complexity can be applied to hardware for area reductions since multiplication can be spread across multiple clock cycles. The conventional schoolbook approach is to divide multiplication using the distributive property. One multiplication can be split into various smaller multiplications. Equation 1 shows how a single multiplication can be divided into two smaller multiplications using the schoolbook approach, where N is the bit width of the second multiplicand B .

$$Y = A * B = A * \{B_1, B_0\} = A * B_0 + A * B_1 * 2^{N/2} \quad (1)$$

Such an approach can be applied for area reductions, where a smaller multiplication circuit can be used repetitively to compute several smaller multiplications. Although multiplication can be implemented using a recursive approach, implementing several division levels requires more control logic. Since the smaller multiplier needed for a single division level is expected to be used twice for each multiplication, new inputs can only arrive once every two clock cycles (CCs), which will be called the initiation interval (II).

The rest of the paper is organized as follows: Section II presents the previous work. Section III presents the architectures proposed in this work. Section IV describes the methodology used for the design generation, synthesis, and verification. Section V presents the implementation results of all the proposed architectures and explains the implications of these results. Section VI concludes the paper.

II. PREVIOUS WORK

A great degree of research has been done to improve the efficiency of integer multipliers. This is due to the large area complexities that can require. In [3], Wallace et al. proposed an efficient approach to dealing with integer multiplications by using carry-save trees for row and column compression. Their approach significantly decreased the critical path for the summation of more than two numbers. A carry-save adder structure uses FA and HA cells in a parallel fashion, reducing the number of rows to two before the ripple carry adder, thus significantly reducing the critical path. The architecture proposed by Wallace [3] heavily impacted the industry and continues to be applied in modern research. In [4], Dadda presented an improvement over the previously proposed carry save adder tree structure proposed by [3]. This reduced the number of FA and HA cells required for the column and row compression. Ugurdag et al. in [5] proposed a new and faster carry-save tree structure called row and column compression trees (RoCoCo). Their structure allowed for smaller and faster final adders for integer multiplication circuits. Using these structures, they presented faster multiplication circuits than much of the literature on FPGAs, outperforming Dadda multipliers [4] and the built-in multiplication circuits by Xilinx. Considering how RoCoCo trees can offer an improvement

over Wallace [3] and Dadda [4] trees, their architectures were utilized in this work.

Multi-cycle (MC) multipliers have also been studied in the past, both for FPGA and ASIC applications. The focus of these studies was to decrease the area complexity for integer multiplication (similar to ours). However, recent work only target FPGA applications due to the limited resources available. The authors in [6] extensively studied the topic of large integer multiplication, with a focus on FPGA implementation. They proposed several MC architectures involving Schoolbook multiplication, Comba multiplication, Karatsuba multiplication, and Number Theoretic Transforms. These architectures are each suited for different applications, each having different characteristics. In their architectures, the latency depends on the bit widths of the multiplicands, allowing for a higher degree of resource sharing depending on the multiplication size, minimizing the number of required DSP slices. DSP slices are an FPGA-specific type of resource. Thus, more optimized architectures can be presented for ASIC applications. In [7], a design implementing the Karatsuba algorithm was implemented. Due to the recursive nature of the Karatsuba algorithm, they proposed using a ‘‘Coprocessor,’’ which was responsible for the sub-functions of the Karatsuba algorithm, such as multiplication, addition, and shifting operations. The ‘‘Coprocessor’’ has a fixed size, and a Block RAM was used to store intermediate results. They were able to produce a circuit that could handle different bit widths using the same area resources. The only varying part is the latency required. This approach means the latency can increase rapidly as the multiplication size increases, requiring 120 clock cycles to implement a 128×128 multiplication. This approach also implies a long II since the ‘‘Coprocessor’’ is expected to be reused several times for a single computation. This architecture provides an area-efficient approach to computing large multiplications on FPGAs, yet, it is only suitable for very low-bandwidth applications. This architecture made further improvements to other FPGA-based MC multiplication circuits proposed in [8], [9], and [10]. Such architectures heavily rely on the usage of DSP slices and Block RAMs, which are expected to increase the speed of an FPGA application while decreasing the slice usage of the design. Since ASICs do not have these built-in hardware resources, more optimized solutions can be proposed. The authors in [11] proposed a design based on an MC Karatsuba multiplication. Their design achieves significant area reduction for FPGAs. Their design required 1/9th of the DSP resources for a conventional 2048×2048 multiplication. For a 2048×2048 multiplication, they achieve a latency of 118 cycles and an II of 9 cycles. Although the design has a relatively low throughput of 1/9, they achieve significant area savings for large multiplications, which would otherwise be too costly in terms of area requirements. This design is only feasible for very large multiplications with a more limited number of applications.

A few work have evaluated MC multiplications for ASIC, offering significant area reductions at the cost of speed/latency. Li et al. presented an area-efficient MC multiplier in [12].

Their architecture heavily relies on resource sharing. Their designs require an II of N for $N \times N$ multiplication and have a latency of $N+1$. Such a high II and latency can severely limit the design's applications and scalability. In [13], an iterative multiplication circuit for 64×64 was proposed, having an II of 4 CCs and a latency of 10 CCs. They used an internally generated clock using NOT gates. Therefore, the clock generation circuitry requires manual modification to work with different system clocks. Such an approach can limit the design's capability of being pipelined. Another design was proposed in [14], implementing an MC multiplication circuit based on a modified-Booth encoding, similar to [13]. They use self-timed clocks that do not require manual modification to change the operating frequency, allowing them to work with any system clock. Their architecture offered an area reduction of 86.6% in comparison with an array implementation, coming at the cost of an 18.8% reduction in speed. Although this architecture presents significant area savings, a speed reduction can be a major limitation for high-speed applications. Furthermore, using a self-timed clock can limit the design's ability to be pipelined. This architecture is considered a combinational circuit; hence, the design can accept inputs in consecutive clock cycles. The system clock, however, would be limited by the maximum frequency of the design.

III. PROPOSED ARCHITECTURES

Integer multiplication can be represented by three stages, partial product generation (PPG), partial product reduction (PPR), and the final addition. Since multiplication can be described as the sum of several smaller multiplications as shown in equation 1. These smaller multiplications can be computed using the same hardware resource when applying resource-sharing. Thus, the circuit responsible for the smaller multiplications will be used multiple times for each multiplication, reducing the throughput to less than one. This approach reduces the area requirements and the critical path of the circuit. Both the critical path and the area requirements for the PPG stage for a conventional integer multiplier can be reduced by 50% when implementing a 2-cycle approach (implementing equation 1). For any multiplication greater than 4×4 , more than two rows are generated after the PPG stage. This means that the PPR stage is expected to handle large reductions. Furthermore, all the intermediate values must be stored in registers until they reach the PPR stage. Such an approach can limit the area reduction that can be achieved. A more optimized approach is to separate the PPR stage into two parts. The first part would be connected to the outputs of the PPG stage. This allows for applying resource sharing on a large part of the PPR stage since this circuit is expected to be used twice for each multiplication. This combination of a PPG and a smaller PPR is called a partial product multiplier (PPM). PPMs have a shorter critical path than regular multipliers since they do not require the final addition stage. The PPM will be used twice for each multiplication, producing four results. These results are then reduced using the second part of the PPR, which will be called a compressor.

A. Sub-module Architectures

Our architectures consist of three core sub-modules: PPM, compressor, and final adder. Several architectures for these sub-modules were used in this work, each having certain advantages. DW02_multp is a synthesis-based PPM offered by Synopsys [15] which can produce fast and efficient PPMs. The outputs' sizes for an $M \times N$ multiplication is $M+N+2$ due to the nature of the design. DW02_multp produces signed results that require sign extension. Since the sign of both outputs can vary, the sign extension was implemented using the following three steps.

- 1) Applying a NOT gate to the most significant bits of all PPMs' outputs (bit position $M+N+2$, where M and N are the sizes of the multiplicands).
- 2) Pad the outputs with 1's after the most significant bit (bit positions greater than $M+N+2$).
- 3) Sum all constants to reduce the compression size (before synthesis).

Steps 1 and 2 allow DW02_multp to be used for unsigned multiplications, even though DW02_multp produces signed results. Step 3 sums up all the constants, including the sign extension padding bits, reducing the size of the numbers that should be compressed in the next stage, and providing further area reductions. Like DW02_mult, DW02_tree is a synthesis-based compression tree offered by Synopsys [15], which can provide fast and efficient compressors.

RoCoCo, proposed in [5], presents a row and column compression tree that can be used to create fast and efficient integer multipliers and compressors. RoCoCo aims to maximize the reduction in the row and column compression tree, allowing for a smaller final addition. RoCoCo multipliers can be used as PPMs by omitting the final addition stage. RoCoCo also presents RTL generators that can produce compressors. Their architecture can reduce the area complexity and the critical path of the overall design. The compressor used for the RoCoCo multiplier maximizes the reduction made, where several of the least significant bits of the second output are reduced to 0. This reduces required computations in the following stages, reducing the overall area complexity and the critical path.

A custom area-efficient compression tree is proposed in this work as well. This compression tree aims at reducing the number of rows into two while minimizing the resources required. This compressor is tailored for a feed-forward architecture (which will be discussed in III-C) utilizing a DW02_multp PPM. Since this compressor is designed to minimize the required hardware resources, it does not achieve identical bit reductions as RoCoCo. This approach can be helpful since the final addition can be spread into multiple cycles using resource sharing or pipelining.

The final addition stage, which comes after the partial product reduction stage, typically consists of ripple carry adders, which can often be the critical path of a design. This can increase the area complexity since the synthesis tool is forced to use larger library cells with greater driving strength and a shorter propagation delay. Since the designs

target MC multiplications, the final adder will remain idle 50% of the time for 2-cycle multipliers. This presents another opportunity to implement resource sharing. The size of the adder can be reduced by 50% by applying resource-sharing and using it in two consecutive cycles. This approach creates a loop around the adders, which makes pipelining the design complex, requiring additional control logic. Such a 2-cycle resource shared adder (2CA) architecture is unsuitable for strict timing targets. The feedback loop presents a limitation since the designs cannot always meet the timing target. For more relaxed timing targets, creating a feedback loop around a smaller adder reduces the area complexity because it reduces the size of the final adder. Pipelining the 2CA architecture can allow resource sharing to be implemented without limiting the maximum frequency. A pipelined 2-cycle adder (2CPA) can be achieved by placing registers in the path of the final adders. Such an approach would not work since variables would start to overlap. This was solved by adding a delay register in the path, making the total latency for the final adder five clock cycles. However, when inputs arrive at odd intervals with respect to the previous inputs, this again causes an overlap of variables. Thus, an internal state machine is required for such cases, which requires more complicated control logic and memory elements.

MC multiplication circuits offer various opportunities for resource sharing since any multiplication stage can be reused for Π times. However, resource sharing can also create feedback loops in the design. Feedback loops limit a design's ability to be pipelined. And thus, there exists a trade-off between the design's ability to be pipelined (which determines the maximum frequency) and the degree of resource sharing to be implemented. A design containing no feedback loops can easily be pipelined by placing registers in the path. This allows a design to meet very strict timing targets at the cost of increased latency. Designs containing feedback loops have a fixed critical path since the feedback loop cannot be pipelined. This means that the maximum frequency can become a limitation for high-speed applications. Furthermore, since the area of a standard library cell depends on its driving strength and speed, pipelining allows for the reduction of area usage since the synthesis tool can use smaller cells that have longer propagation delays. Due to this, a feed-forward design can significantly outperform a design with a feedback loop in its data flow path when the clock target is strict enough, even if the designs implementing a feedback loop can meet timing. Nevertheless, feedback loops enable a greater degree of resource sharing, maximizing the area reductions when dealing with more relaxed timing targets. As a result, both approaches have their benefits. Depending on the target frequency, either approach could outperform the other.

Two designs are proposed in this work using the previously discussed concepts, each having different variations in the sub-modules used. These designs are optimized for specific applications in terms of operating frequency, maximizing the area reductions that can be achieved.

B. Feedback Design

Feedback loops allow for a greater degree of resource sharing. As a result, we present an architecture that uses feedback loops to reduce the area complexity. In this architecture, all three multiplier stages are resource-shared: the PPM, the compressor, and the final adder. These stages are fully utilized for 100% of clock cycles under regular operation (when inputs arrive back to back). This is achieved by creating a feedback loop around the compressor and final adder, reducing the size of both. The feedback loop in this design contains a 3:2 compressor and a ripple carry adder. For an $M \times N$ multiplication, this architecture uses an $M \times (\lceil N/2 \rceil)$ PPM, a final adder, and a 3:2 compressor of width $M + \lceil N/2 \rceil$. This design is represented by figure 1. The number of FA cells in the feedback loop, which determines the critical path of the design, can be calculated using equation 2, where M and N are the bit widths of the multiplicands.

$$CriticalPath = 1 + (\lceil M/2 \rceil + N), \quad (2)$$

This approach uses the least amount of resources out of our designs. However, due to the loop, it can be outperformed by feed-forward designs for strict timing targets, where the feedback loop can be a limiting factor. This design is based on the schoolbook approach and can be represented by figure 1 for 2C multiplication. This architecture can be extended for any




Fig. 1. 2-cycle feedback design

Π , decreasing the size of the core sub-modules. The Π and the area complexity of the three stages (PPM, compressor, and the final adder) have an exponential decay relationship. However, the number of registers storing intermediate results increases linearly. Due to this relationship, diminishing returns will be seen as the Π increases. Furthermore, continuously increasing the Π after some point would also increase the area complexity of the design.

C. Feed-forward Design

Multiplication circuits are frequently used with high-frequency applications; ergo, architectures with short critical paths can be very beneficial. The critical path directly affects both area and speed. The critical path limits the maximum operating frequency, and the area complexity is indirectly affected by the critical path. A circuit synthesized using its maximum frequency consumes significantly more area than one synthesized for a relaxed frequency. When operating under strict timing conditions, the synthesis tool instantiates larger library cells with shorter delays to meet timing. In contrast, the synthesis tool can use small library cells with longer propagation delays when dealing with relaxed timing targets. The critical path is caused by the combinational circuit that has to be executed within the same clock cycle. If this combinational logic were to be divided across multiple clock cycles, the critical path would be decreased, and thus, both speed and area would improve. As previously discussed, having a feedback loop in the design limits the design's ability to be pipelined. For this reason, we propose a design that contains no feedback loops. This architecture has three main steps. Firstly, the partial product multiplications are computed using one module, thus requiring two clock cycles. In the final clock cycle, four results need to be added, these are first sent to a compressor, and then the result of the compression is sent to a ripple carry adder. Only the PPM is used twice in this architecture which does not create any feedback loops. This design can easily be pipelined to meet very strict timing targets. The area savings of this design come from the fact that it requires smaller PPG and PPR stages, which contribute a large portion of the overall complexity for an integer multiplier. All the stages in this design can be efficiently pipelined, which allows the critical path to be continuously decreased at the cost of longer latency. The PPM's size equals $M + \lceil (N/2) \rceil$. The compressor's size depends on the bit widths of the inputs, as well as the type of PPM used. The compression tree has at most four rows to be reduced, and several bit-positions contain fewer rows due to the shifting operations. DW02_multp produces signed outputs that require sign extension, while RoCoCo produces unsigned results; ergo, the compression trees needed for these two PPMs are not identical. This architecture is ideal to be used with an II of 2. In such a case, the stage can be reduced by around 50% while keeping the control logic simple and not requiring a significant number of registers for storing intermediate results. Since the PPM has two outputs and it is used twice, a 4:2 compressor is required, where the inputs would be the first 2 PPM results and the shifted version of the second 2 PPM results. This design is represented by figure 2.

This architecture can also be extended for different IIs; however, maintaining a feed-forward approach becomes a limitation. A feed-forward design with an II of 3 would require a 6:2 compressor. This increase in the compressor's size undermines the area reductions gained by the smaller PPM. Furthermore, such a design requires significantly more registers to store the intermediate results until all PPMs are




Fig. 2. 2 cycle feed-forward with a 4:2 comp

computed. Such an architecture is not expected to provide any area savings. A better approach would be to add a loop around the 4:2 compressor. Such a design allows the II to be increased without significantly affecting the architecture. However, The feedback loop limits the design's ability to be pipelined. This loop has a short critical path of only 2 FAs, but it also requires more registers to store the intermediate results. Moreover, this approach also requires a significantly larger compressor, requiring 96% more FAs and HAs for the case of 3C versus 2C II. Although a 4:2 compressor is used in both cases, the 4:2 compressor required for a 2C design contains more columns with only 2 bits to be reduced. All this results in a higher area requirement when compared to the 2C version. Therefore, a feed-forward design with this approach is only viable for an II of 2.

IV. IMPLEMENTATION

The proposed designs were tested thoroughly, using different bit widths, latencies, and timing targets. This required several steps, including design generation, synthesis, pipelining, simulation, and reporting power. These steps were automated using a series of scripts that handle these tasks accordingly. This automation allows for a greater degree of testing required for a complete evaluation of all these designs. The designs are generated using RTL generation scripts written in Python, synthesized using the Synopsys Design Compiler and a TSMC 40 nm technology, and simulated using Icarus Verilog.

In this work, two main architectures are proposed, which can have variations in the type of compressors, PPMs, and final adders. Due to this, design generation scripts were used to accommodate these variations easily. All designs are instantiated with a wrapper, automatically setting the input/output delays and loads. The wrapper applies a register to each of the inputs and outputs of the design except the clock signal.

There are two different generators for 2CIM designs, one for each architecture. All the generators create both a wrapper and a testbench, thus allowing for easy and accurate testing for each design. The feedback architecture's generator takes the size of the multiplicands, the type of PPM (DW02_multp or RoCoCo), and the added pipeline stages as inputs and then generates the design. The feed-forward design has some differences in the design generation parameters since it has multiple options for the compressor and final adder to be used. This generator takes the multiplicands' size, the PPM and compressor's type, and the number of pipeline stages as the input parameters. These variations in sub-modules are required to achieve optimal performance since each offers some advantages.

Retiming is a technique used to optimize digital circuits by moving flip-flops. It can significantly reduce the critical path and improve the area. Since strict timing targets require larger library cells, reducing the critical path can also decrease the area complexity. The Synopsys Design Compiler offers the retiming feature, which was utilized to achieve optimized pipelining for any design. To increase the depth of the pipeline, registers are added at the end of the design. The synthesis tool can freely move these registers as long as they do not affect a feedback loop in the design. Increasing the pipeline's depth also increases the latency, but it can decrease both the area complexity and the critical path while maintaining the same throughput.

Synthesis is not a linear computation. It has to handle various constraints to meet timing, optimize area, and minimize power consumption. Over-constraining is another technique to meet strict timing targets when the synthesis tool fails. This is done by further restricting the timing target, allowing the synthesis tool to make decisions that expect a more strict timing target. This can often allow our designs to meet the required timing target even if the initial synthesis attempt was unsuccessfully in meeting timing. The automation scripts attempt over-constraining whenever a design does not meet timing; this is done by reducing the timing target by 5% and re-attempting synthesis. Over-constraining is attempted three times before increasing the depth of the pipeline (adding registers to the design and applying retiming).

In this work, area complexities of all 2CIM designs and the standard multiplication circuit generated by Synopsys using the "*" operator (which will be referred to as Star) are compared. The same target frequency should be used for a fair comparison of results between any two designs. The area complexity, power consumption, and operating frequency are all interdependent. However, in most applications, the operating frequency is a design decision that needs to be preserved. The initial timing target is set as the maximum frequency achieved by the Star multiplier without adding any additional pipeline stages. In addition, over-constraining is used to test if a higher maximum frequency can be achieved. Timing is then increased by 15% and 30% to see how the designs perform in more relaxed timing targets. Furthermore, the target is set to 0.31, representing the clock-to-q + setup + hold delay for 1 FA

placed between registers, using the smallest library cell for a FA. However, such a strict timing target is not suitable for multiplications larger than 32×32 since large multipliers require many pipeline stages to meet the target timing. Larger multipliers used less strict timing targets according to the actual multiplication size. Using such strict timing targets is useful to check how effectively the designs can be pipelined to meet very strict timing targets. The designs are also synthesized with additional pipeline stages until the latency reaches the maximum latency of other designs. This is because increasing the pipeline depth can decrease the area complexity as well. All this was accomplished by using automation scripts. The scripts first synthesize the Star multiplier to get the three timing targets. Two more timing targets are used, representing strict and relaxed timing conditions. For each timing target, it follows a series of steps to produce the complete results table. The first step is the design generation, which is done using the RTL generators of each architecture. It then synthesizes each design using retiming and over-constraining to meet the timing target. After that, it simulates the generated netlist and estimates the power consumption. This is repetitively done for all designs, variations, and timing targets. Since the designs are tested using a strict timing target, the target is not always met from the initial synthesis attempt. The script will first attempt to meet timing using over-constraining. If the design is still unable to meet timing, a pipeline stage is added. This iteration is repetitively done until either timing is met or the number of pipeline stages exceeds 8. This usually means that the target timing cannot be met even when pipelined. All architectures are simulated using a set of 200 randomly generated inputs. Self-checking test benches were used, where the output is sampled depending on the latency of the design. Furthermore, both design and netlist simulations were performed.

Power consumption can be an important aspect to consider when designing a digital circuit. All the proposed designs were analyzed for power consumption. Randomly generated inputs were used, being set every 2 clock cycles. This represents a worst-case scenario, where the power consumption is analyzed under heavy loads. Post-synthesis simulation was performed on all the designs, generating a file that contains the switching activities of all nets and ports. This file is then used by the synthesis tool (Synopsys Design Compiler) to estimate the power consumption of a design, including both dynamic and static power consumption in the estimation. Analyzing power using the post-synthesis netlist simulation can generate more accurate results when compared to the RTL simulation since it contains more accurate switching activities. Power consumption can be affected by several factors. However, there are three main factors to consider, the critical path of the circuit, the length of the MC path (which includes the parts to be resource shared), and the area of the design. Under strict timing conditions, the synthesis tool uses large library cells to meet timing, which consumes more power than smaller library cells having longer delays. Longer MC paths produce more glitches in the design, and these glitches (part of the switching activity) increase power consumption. And lastly, a larger area

implies that there are more gates in the design, thus consuming more power since even idle gates contribute to static power consumption.

V. RESULTS

All the proposed 2CIM designs were tested thoroughly in this work. Each design has advantages and disadvantages, offering significant area saving under the right conditions. All the proposed 2CIM designs and variants should be synthesized under the same timing conditions and compared to perform a thorough evaluation. All 2CIM designs were synthesized under a wide range of multiplication sizes and various timing targets. All the designs were tested using a wide range of operating frequencies since each 2CIM architecture targets a specific type of application with respect to the operating frequency. Moreover, the scalability of these designs is an important feature. The designs were tested for various multiplication sizes to show that these area savings are consistent for various multiplication sizes. This section will present two tables that can represent strict and relaxed timing conditions. Since our designs usually achieve a longer latency, they should be compared with a Star multiplier design using the same number of pipeline stages. However, the Star multiplier is relatively faster, so it will reach its minimum area using a smaller number of pipeline stages than that of 2CIM designs. The area results that are reported for the Star multiplier are the best area results that can be achieved using any number of pipeline stages.

A. Synthesis Under Relaxed Timing Conditions

A relaxed timing target can show the actual area requirements of each design since a strict timing target would affect the results depending on the critical path. The relaxed timing conditions case is represented by a timing target of 10 ns. Such a target allowed all the designs to meet timing without requiring additional pipeline stages while being able to use small library cells. Table I presents the synthesis results for a 16×16 multiplication. Since the timing target is very relaxed, retiming and over-constraining were not required. Thus, the latency presented in table I represents the minimum latency (L) for these designs.

The feedback (FB) designs best suit applications that do not require very strict timing targets. The area complexity of these designs is always the lowest under such circumstances. For 16×16 multiplications, the feedback designs can offer around 30% area savings. But it comes at the cost of an increase in power consumption. And so, a trade-off exists between the area complexity and power consumption for such multiplications with relaxed timing targets. It can be seen that the 2CA final adder cannot offer any benefits in terms of area savings compared to either the feed-forward (FF) design implementing no spread (SCA) or the feedback design. This can be explained by the fact that under very relaxed timing conditions, the area complexity coming from the final adder is lower than the required logic to implement resource sharing. Thus, 2CA is not expected to offer additional area savings

TABLE I
SYNTHESIS RESULTS FOR 16×16 MULTIPLICATIONS UNDER RELAXED TIMING CONDITIONS (TARGET = 10 ns)

Design	Final Adder	PPM	Comp.	L	Area	Power (uW)
Star	N/A	N/A	N/A	1	1348	79
FB	N/A	DW02	FAs	2	942	100
	N/A	RoCoCo	FAs	2	960	108
FF	RCA	DW02	DW02	2	1096	124
	RCA	DW02	RoCoCo	2	1145	127
	RCA	DW02	Custom	2	1105	124
	RCA	RoCoCo	DW02	2	1051	120
	RCA	RoCoCo	RoCoCo	2	1122	122
	2CA	DW02	DW02	3	1352	159
	2CA	DW02	RoCoCo	3	1181	148
	2CA	DW02	Custom	3	1420	168
	2CA	RoCoCo	DW02	3	1115	138
	2CA	RoCoCo	RoCoCo	3	1155	140
	2CPA	DW02	DW02	6	2102	250
	2CPA	DW02	RoCoCo	6	2053	251
	2CPA	DW02	Custom	6	2086	248
	2CPA	RoCoCo	DW02	6	2120	244
	2CPA	RoCoCo	RoCoCo	6	2129	243

under these conditions. 2CPA is designed to provide area savings for strict timing targets. Therefore, it cannot offer any area savings under such relaxed timing conditions. This is due to the added complexity in the control logic, which is required for scheduling inputs based on their arrival time, and the increased number of registers needed for storing intermediate results. The proposed designs consume more power than the Star multiplier since they have a longer MC path. A longer MC path increases the circuit's glitches, increasing the dynamic power consumption. The Star multiplier employs no resource sharing. Therefore, only a part of the circuit is active simultaneously when a throughput of less than one is needed. In our testing, inputs are received every two cycles, making the Star multiplier remain idle 50% of the time.

B. Synthesis Under Strict Timing Conditions

An essential aspect of ASICs is their ability to operate at high frequencies. For this reason, the ability of any multiplication circuit to operate at high frequencies is vital. All 2CIM designs were tested under high frequencies as well. They were synthesized using a very strict timing target of 0.31 ns, equal to the clock-to-q + setup + hold delay for 1 FA placed between registers. Such a strict target shows how well these designs can be pipelined. Table II contains the synthesis results of the proposed designs, both retiming and over-constraining were used to meet timing. The feed-forward designs that use a 2CA final adder have a longer critical path than the feedback designs; ergo, they are unsuitable for high-frequency applications. Designs using the 2CPA final adders could achieve high frequencies as intended. However, the added complexity from the more complicated control logic resulted in a greater area complexity. Therefore, 2CPA is consistently outperformed by a pipelined RCA using the same latency. For such high-frequency applications, the only viable options are fully feed-forward designs because of their ability

to be efficiently pipelined without requiring additional control logic. As seen in table II, the feed-forward (FF) designs can

TABLE II
SYNTHESIS RESULTS FOR 16×16 MULTIPLICATIONS UNDER STRICT TIMING CONDITIONS (TARGET = 0.31 ns)

Design	FA	PPM	Comp.	L	Area	Timing (ns)	Power (mW)
Star	N/A	N/A	N/A	7	5178	0.31	7.52
FF	RCA	RoCoCo	DW02	9	3963	0.31	7.13
	RCA	DW02	DW02	9	3984	0.31	7.92
	RCA	RoCoCo	RoCoCo	7	4065	0.31	6.57
	RCA	DW02	Custom	9	4065	0.31	7.83
	RCA	DW02	RoCoCo	9	4200	0.31	7.98
	2CPA	DW02	DW02	11	4971	0.31	10.17
	2CPA	DW02	Custom	10	5115	0.31	9.72
	2CPA	RoCoCo	RoCoCo	12	5192	0.31	9.58
	2CPA	RoCoCo	DW02	12	5202	0.31	10.11
	2CPA	DW02	RoCoCo	11	5307	0.31	10.06
	2CA	DW02	DW02	5	4394	0.46	4.43
	2CA	DW02	RoCoCo	7	4208	0.49	4.18
	2CA	DW02	Custom	5	4600	0.48	4.46
	2CA	RoCoCo	DW02	5	3255	0.55	2.96
2CA	RoCoCo	RoCoCo	6	3434	0.58	3.05	
FB	N/A	DW02	FAs	4	3712	0.46	4.47
	N/A	RoCoCo	FAs	6	3554	0.49	4.34

offer up to 23% area savings and 13% power reduction. The Star multiplier is not able to meet timing without pipelining. It requires a minimum pipeline depth of 6 for the designs to meet timing and a depth of 7 to achieve the optimal area. The Star multiplier achieves a similar latency to the proposed designs while having a greater area complexity. Therefore, the MC path for 2CIM designs is shorter or equivalent to that of Star, explaining the power reduction 2CIM designs offer for such strict timing targets.

C. Discussions

The proposed 2CIM designs can offer significant area savings for various applications. Table III contains the area savings provided by the best-performing design under different bit widths and timing targets. This table presents the optimal design under either very strict or semi-relaxed timing conditions. The feed-forward (FF) design is best suited for strict timing targets, and the feedback (FB) design is best suited for more relaxed timing targets. The 2CA and 2CPA final adders do not offer any area savings when compared to the other designs. The 2CA creates a feedback loop in the feed-forward design. This means that a feed-forward design implementing a 2CA final adder will consistently be outperformed by either the feedback designs or a feed-forward design that uses an RCA final adder.

2CIM designs have a throughput of $1/2$, i.e., they can compute one multiplication every two clock cycles. 2CIM designs can be used when i multiplications are required within j clock cycles, and $(i \bmod j)/j$ is less than or equal to $1/2$. Another case in which 2CIM designs can be used is when there is a latency constraint. For 128×128 multipliers with a clock target of 0.8, both the feed-forward design and the Star multiplier achieve the same latency. This is because the feed-forward architecture can be pipelined very efficiently.

TABLE III
AREA SAVINGS FOR DIFFERENT BIT WIDTHS

Design	PPM	Comp.	Timing (ns)	L	Area	Savings
8×8						
Star	N/A	N/A	0.31	4	1377	-
FF	RoCoCo	RoCoCo	0.31	5	1088	21%
Star	N/A	N/A	0.5705	2	738	-
FB	DW02	FAs	0.5705	4	600	19%
16×16						
Star	N/A	N/A	0.31	7	5179	-
FF	RoCoCo	DW02	0.31	9	3964	23%
Star	N/A	N/A	1.001	1	2160	-
FB	DW02	FAs	1.001	3	1255	42%
32×32						
Star	N/A	N/A	0.31	10	17790	-
FF	DW02	Custom	0.31	9	13653	23%
Star	N/A	N/A	1.287	2	6057	-
FB	DW02	FAs	1.287	3	4093	32%
64×64						
Star	N/A	N/A	0.4	7	51638	-
FF	DW02	Custom	0.4	7	47496	8%
Star	N/A	N/A	1.3915	2	22841	-
FB	DW02	FAs	1.3915	3	13389	41%
128×128						
Star	N/A	N/A	0.8	4	121634	-
FF	DW02	Custom	0.8	4	63777	48%
Star	N/A	N/A	1.457	2	89165	-
FB	DW02	FAs	1.457	3	48911	45%

Suppose there is a latency constraint of 4 cycles, and the throughput of these multipliers does not exceed $1/2$. In such a case, multiple instances of the feed-forward design can be used to calculate any number of multiplications, providing a great degree of area savings. Such cases are only seen for large multiplications operating under high frequencies. In most cases, however, a 2CIM design can slightly increase the latency. This is because conventional multipliers are somewhat faster than the proposed 2CIM designs. Thus, 2CIM designs might require more pipeline stages to meet a strict timing target. This is usually around one or two additional clock cycles. For large multipliers with very strict timing targets, however, the feed-forward architecture can be pipelined more efficiently, achieving identical latencies as those of the Star multiplier.

VI. CONCLUSION

The number of multiplications required in a clock cycle is not always an integer, which is the case when an odd number of multiplications is required within two clock cycles, e.g., three multiplications are required within two clock cycles, i.e., 1.5 multiplications per clock cycle. Such cases can be found in a variety of applications across any domain since multiplication circuits are essential building blocks. The conventional way of dealing with such cases is to utilize complete multipliers for these fractional multiplications. Or in other words, using a multiplier for only 50% of the time. This approach is not optimal since it requires more area than necessary and does not take full advantage of the allocated resources. This work presents a range of MC unsigned integer multi-

pliers that offer fractional multipliers. These designs provide significant area savings for a variety of applications. 2CIM designs are designed to replace fully-pipelined multipliers, i.e., multipliers that can accept inputs in a consecutive clock cycle, for applications where they remain underutilized. 2CIM designs have a throughput of 1/2, i.e., they can compute one multiplication every two clock cycles. This work presents two main architectures, each having multiple possible variations. The feed-forward architecture has the advantage of speed. It can run at very high frequencies due to the feed-forward design aspect, which allows it to be continuously pipelined until the timing is met. The feedback design implements a higher degree of resource sharing, enabling it to require significantly fewer hardware resources. However, it also requires a feedback loop. Feedback loops can limit a design's ability to operate at high frequencies since feedback loops are not easily pipelined. Both architectures have advantages, and depending on the target application, either can be the optimal choice. 2CIM designs can be used for any application that requires i multiplications within j clock cycles, and $(i \bmod j)/j$ is less than or equal to 1/2. This can be especially useful for area-efficient low-bandwidth applications. 2CIM designs can provide up to 21%, 42%, 32%, 41%, and 48% area savings for multiplications bit widths of 8, 16, 32, 64, and 128, respectively. 2CIM designs were tested thoroughly through automation scripts using various multiplication sizes and timing targets. 2CIM designs consistently offered significant area savings throughout our testing. Moreover, 2CIM designs can provide power savings when dealing with strict timing targets. All designs were synthesized using the Synopsys Design Compiler and a 40 nm TSMC technology.

REFERENCES

- [1] D. Goldberg, "What every computer scientist should know about floating-point arithmetic," *ACM Computing Surveys*, vol. 23, pp. 5–48, 1991.
- [2] C. Hoekstra, K. Shukla, and M. Harris, "Implementing high-precision decimal arithmetic with CUDA int128," <https://developer.nvidia.com/blog/implementing-high-precision-decimal-arithmetic-with-cuda-int128> (accessed 14 July 2022).
- [3] C. S. Wallace, "A suggestion for a fast multiplier," *IEEE Transactions on Electronic Computers*, vol. EC-13, pp. 14–17, 1964.
- [4] L. Dadda, "Some schemes for parallel multipliers," *Alta Frequenza*, vol. 34, pp. 349–356, 1965.
- [5] F. Ugurdag, O. Keskin, C. Tunc, F. Temizkan, G. Fici, and S. Dedeoglu, "RoCoCo: Row and column compression for high-performance multiplication on FPGAs," in *Proc. East-West Design & Test Symp. (EWDTS)*, 2011, pp. 98–101.
- [6] C. Rafferty, M. O'Neill, and N. Hanley, "Evaluation of large integer multiplication methods on hardware," *IEEE Transactions on Computers*, vol. 66, pp. 1369–1382, 2017.
- [7] I. San and N. At, "On increasing the computational efficiency of long integer multiplication on FPGA," in *Proc. IEEE Int. Conf. on Trust, Security and Privacy in Computing and Communications (TrustCom)*, 2012, pp. 1149–1154.
- [8] J. Von Zur Gathen and J. Shokrollahi, "Efficient FPGA-based karatsuba multipliers for polynomials over F_2 ," in *Proc. Selected Areas in Cryptography (SAC)*. Springer, 2005, pp. 359–369.
- [9] S. Gao, D. Al-Khalili, and N. Chabini, "Efficient scheme for implementing large size signed multipliers using multigranular embedded DSP blocks in FPGAs," *Int. Journal of Reconfigurable Computing*, 2009.

- [10] F. de Dinechin and B. Pasca, "Large multipliers with fewer DSP blocks," in *Proc. IEEE Int. Conf. on Field Programmable Logic and Applications (FPL)*, 2009, pp. 250–255.
- [11] M. Langhammer and B. Pasca, "Folded integer multiplication for FPGAs," in *Proc. ACM/SIGDA Int. Symp. on Field-Programmable Gate Arrays (FPGA)*, 2021, pp. 160–170.
- [12] J. Li, Y. Du, and J. Wang, "Design a pocket multi-bit multiplier in FPGA," in *Proc. IEEE Int. Conf. on ASIC (ASICON)*, 1996, pp. 275–279.
- [13] M. R. Santoro and M. A. Horowitz, "SPIM: a pipelined 64*64-bit iterative multiplier," *IEEE Journal of Solid-state Circuits*, vol. 24, pp. 487–493, 1989.
- [14] M.-C. Shin, S.-H. Kang, and I.-C. Park, "An area-efficient iterative modified-booth multiplier based on self-timed clocking," in *Proc. IEEE Int. Conf. on Computer Design: VLSI in Computers and Processors (ICCD)*, 2001, pp. 511–512.
- [15] Synopsys, "DesignWare Library," <https://www.synopsys.com/dw/buildingblock.php> (accessed: 2021-03-01).