

CONVERGENCE RATE FOR A RADAU HP COLLOCATION METHOD APPLIED TO CONSTRAINED OPTIMAL CONTROL *

WILLIAM W. HAGER[†], HONGYAN HOU[‡], SUBHASHREE MOHAPATRA[§], AND ANIL V. RAO[¶]

Abstract. For control problems with control constraints, a local convergence rate is established for an hp -method based on collocation at the Radau quadrature points in each mesh interval of the discretization. If the continuous problem has a sufficiently smooth solution and the Hamiltonian satisfies a strong convexity condition, then the discrete problem possesses a local minimizer in a neighborhood of the continuous solution, and as either the number of collocation points or the number of mesh intervals increase, the discrete solution converges to the continuous solution in the sup-norm. The convergence is exponentially fast with respect to the degree of the polynomials on each mesh interval, while the error is bounded by a polynomial in the mesh spacing. An advantage of the hp -scheme over global polynomials is that there is a convergence guarantee when the mesh is sufficiently small, while the convergence result for global polynomials requires that a norm of the linearized dynamics is sufficiently small. Numerical examples explore the convergence theory.

Key words. hp collocation, Radau collocation, convergence rate, optimal control, orthogonal collocation

AMS subject classifications. 49M25, 49M37, 65K05, 90C30

1. Introduction. A convergence rate is established for an hp -orthogonal collocation method applied to a constrained control problem of the form

$$\left. \begin{array}{ll} \text{minimize} & C(\mathbf{x}(1)) \\ \text{subject to} & \dot{\mathbf{x}}(t) = \mathbf{f}(\mathbf{x}(t), \mathbf{u}(t)), \quad \mathbf{u}(t) \in \mathcal{U}, \quad t \in \Omega_0, \\ & \mathbf{x}(0) = \mathbf{a}, \quad (\mathbf{x}, \mathbf{u}) \in \mathcal{C}^1(\Omega_0) \times \mathcal{C}^0(\Omega_0), \end{array} \right\} \quad (1.1)$$

where $\Omega_0 = [0, 1]$, the control constraint set $\mathcal{U} \subset \mathbb{R}^m$ is closed and convex with nonempty interior, the state $\mathbf{x}(t) \in \mathbb{R}^n$, $\dot{\mathbf{x}}$ denotes the derivative of \mathbf{x} with respect to t , $\mathbf{f} : \mathbb{R}^n \times \mathbb{R}^m \rightarrow \mathbb{R}^n$, $C : \mathbb{R}^n \rightarrow \mathbb{R}$, and \mathbf{a} is the initial condition, which we assume is given; $\mathcal{C}^l(\Omega_0)$ denotes the space of l times continuously differentiable functions mapping Ω_0 to \mathbb{R}^d for some d . The value of d should be clear from context; states and costates always have n components and controls have m components. It is assumed that \mathbf{f} and C are at least continuous. When the dynamics in (1.1) can be solved for the state \mathbf{x} as a function of the control \mathbf{u} , the control problem reduces to a constrained minimization over \mathbf{u} .

The development of hp -techniques in the context of finite element methods for boundary-value problems began with the work of Babuška and Gui in [24, 25, 26], and Babuška and Suri in [1, 2, 3]. In the hp -collocation approach that we develop for (1.1), the time domain Ω_0 is initially partitioned into a mesh. To simplify the discussion, we focus on a uniform mesh consisting of K intervals $[t_{k-1}, t_k]$ defined by the mesh

* October 24, 2017. The authors gratefully acknowledge support by the Office of Naval Research under grants N00014-11-1-0068 and N00014-15-1-2048, and by the National Science Foundation under grants DMS-1522629 and CBET-1404767.

[†]hager@ufl.edu, <http://people.clas.ufl.edu/hager/>, PO Box 118105, Department of Mathematics, University of Florida, Gainesville, FL 32611-8105. Phone (352) 294-2308. Fax (352) 392-8357.

[‡]hongyan388@gmail.com, Chemical Engineering, Carnegie Mellon University, 5000 Forbes Avenue, Pittsburgh, PA 15213.

[§]subha@ufl.edu, Department of Mathematics, University of Florida, Gainesville, FL 32611.

[¶]anilvrao@ufl.edu, <http://www.mae.ufl.edu/rao>, Department of Mechanical and Aerospace Engineering, P.O. Box 116250, Gainesville, FL 32611-6250. Phone (352) 392-0961. Fax:(352) 392-7303.

points $t_k = k/K$ where $0 \leq k \leq K$. The dynamics of (1.1) are reformulated using a change of variables. Let $t_{k+1/2} = (t_k + t_{k+1})/2$ be the midpoint of the mesh interval $[t_k, t_{k+1}]$. We make the change of variables $t = t_{k-1/2} + h\tau$, where $h = 1/(2K)$ is half the width of the mesh interval and $\tau \in \Omega := [-1, 1]$; let us define $\mathbf{x}_k : \Omega \rightarrow \mathbb{R}^n$ by $\mathbf{x}_k(\tau) = \mathbf{x}(t_{k-1/2} + h\tau)$. Thus \mathbf{x}_k corresponds to the restriction of \mathbf{x} to the mesh interval $[t_{k-1}, t_k]$. Similarly, we define a control \mathbf{u}_k corresponding to the restriction of \mathbf{u} to the mesh interval $[t_{k-1}, t_k]$. In the new variables, the control problem reduces to finding K state-control pairs $(\mathbf{x}_k, \mathbf{u}_k)$, $1 \leq k \leq K$, each pair defined on the interval $[-1, 1]$, to solve the problem

$$\left. \begin{array}{ll} \text{minimize} & C(\mathbf{x}_K(1)) \\ \text{subject to} & \dot{\mathbf{x}}_k(\tau) = h\mathbf{f}(\mathbf{x}_k(\tau), \mathbf{u}_k(\tau)), \quad \mathbf{u}_k(\tau) \in \mathcal{U}, \quad \tau \in \Omega, \\ & \mathbf{x}_k(-1) = \mathbf{x}_{k-1}(1), \quad 1 \leq k \leq K, \\ & (\mathbf{x}_k, \mathbf{u}_k) \in \mathcal{C}^1(\Omega) \times \mathcal{C}^0(\Omega). \end{array} \right\} \quad (1.2)$$

Since the function \mathbf{x}_0 does not exist (there is no 0-th mesh interval), we simply define $\mathbf{x}_0(1) = \mathbf{a}$, the initial condition. The condition

$$\mathbf{x}_k(-1) = \mathbf{x}_{k-1}(1) \quad (1.3)$$

in (1.2) corresponds to the initial condition $\mathbf{x}(0) = \mathbf{a}$ when $k = 1$ and to continuity of the state across a mesh interval boundary when $k > 1$. Throughout the paper, (1.3) is referred to as the *continuity condition*.

In the *hp*-scheme developed in this paper, the dynamics for \mathbf{x}_k are approximated by the Radau collocation scheme developed in [9, 21, 22, 30]. Let \mathcal{P}_N denote the space of polynomials of degree at most N defined on the interval Ω , and let \mathcal{P}_N^n denote the n -fold Cartesian product $\mathcal{P}_N \times \dots \times \mathcal{P}_N$. We analyze a discrete approximation to (1.2) of the form

$$\left. \begin{array}{ll} \text{minimize} & C(\mathbf{x}_K(1)) \\ \text{subject to} & \dot{\mathbf{x}}_k(\tau_i) = h\mathbf{f}(\mathbf{x}_k(\tau_i), \mathbf{u}_{ki}), \quad 1 \leq i \leq N, \quad \mathbf{u}_{ki} \in \mathcal{U}, \\ & \mathbf{x}_k(-1) = \mathbf{x}_{k-1}(1), \quad 1 \leq k \leq K, \quad \mathbf{x}_k \in \mathcal{P}_N^n. \end{array} \right\} \quad (1.4)$$

Note that there is no polynomial associated with the control; \mathbf{u}_{ki} corresponds to the value of the control at $t_{k-1/2} + h\tau_i$. In (1.4) the dimension of \mathcal{P}_N is $N + 1$ and there are K mesh intervals, so a component of the state variable is chosen from a space of dimension $K(N + 1)$. Similarly, there are $KN + K$ equations in (1.4) corresponding to the collocated dynamics at KN points and the K continuity conditions.

For simplicity in the analysis, the same degree polynomials are used in each mesh interval, while in practical implementations of the *hp*-scheme [9, 10, 36, 38], polynomials of different degrees are often used on different intervals. On intervals where the solution is smooth, high degree polynomials are employed, while on intervals where the solution is nonsmooth, low degree polynomials are used.

We focus on a collocation scheme based on the N Radau quadrature points satisfying

$$-1 < \tau_1 < \tau_2 < \dots < \tau_N = 1.$$

The interior abscissa τ_i , $1 \leq i \leq N - 1$ are the zeros of the degree $N - 1$ Jacobi polynomial $P_{N-1}^{(1,0)}$ associated with the weight $1 - \tau$. These quadrature points are sometimes called the flipped Radau points, while the standard Radau points are $-\tau_i$,

$1 \leq i \leq N$. The analysis is the same for either set of points, while the notation is a little cleaner for the flipped points. Besides the N collocation points, our analysis also utilizes the noncollocated point $\tau_0 = -1$.

As pointed out in [31], in a global collocation scheme where $K = 1$, it may not be possible to solve for the discrete state in terms of the discrete controls for certain choices of N . In this paper, we show that locally, it is possible to solve for the discrete state in terms of the discrete control when K is sufficiently large, or equivalently, when h is sufficiently small, regardless of the choice for N . In this respect, the hp -collocation approach is more robust than a global scheme.

Other global collocation schemes that have been presented in the literature are based on the Lobatto quadrature points [16, 19], on the Chebyshev quadrature points [17, 20], on the Gauss quadrature points [4, 22], and on the extrema of Jacobi polynomials [43]. Kang [34, 35] considers control systems in feedback linearizable normal form, and shows that when the Lobatto discretized control problem is augmented with bounds on the states and control, and on certain Legendre polynomial expansion coefficients, then the objectives in the discrete problem converge to the optimal objective of the continuous problem at an exponential rate. Kang's analysis does not involve coercivity assumptions for the continuous problem, but instead imposes bounds in the discrete problem. Also, in [23] a consistency result is established for a scheme based on Lobatto collocation.

Any of the global schemes could be developed into an hp -collocation scheme. Our rationale for basing our hp -scheme on the Radau collocation points was the following: In numerical experiments such as those in [22], there is often not much difference between the convergence speed of approximations based on either Gauss or Radau collocation, while the Lobatto scheme often converged much slower; and in some cases, the Lobatto costate approximation did not converge due to a null space that arises in the first-order optimality conditions – see [22]. On the other hand, the implementation of an hp -scheme based on the Radau quadrature points was much simpler than the implementation based on the Gauss quadrature points. The Gauss points lie in the interior of each mesh interval, which requires the introduction of the state value at the mesh points. Since one of the Radau points is a mesh point, there is no need to introduce an additional noncollocated point. The implementation ease of Chebyshev quadrature should be similar to that of Gauss and was not pursued. The hp -collocation scheme analyzed in this paper corresponds to the scheme implemented in the popular GPOPS-II software package [40] for solving optimal control problems. This paper, in essence, provides a theoretical justification for the algorithm implemented in the software.

For $\mathbf{x} \in \mathcal{C}^0(\Omega_0)$, we use the sup-norm $\|\cdot\|_\infty$ given by

$$\|\mathbf{x}\|_\infty = \sup\{|\mathbf{x}(t)| : t \in \Omega_0\},$$

where $|\cdot|$ is the Euclidean norm. Given $\mathbf{y} \in \mathbb{R}^n$, the ball with center \mathbf{y} and radius ρ is denoted

$$\mathcal{B}_\rho(\mathbf{y}) = \{\mathbf{x} \in \mathbb{R}^n : |\mathbf{x} - \mathbf{y}| \leq \rho\}.$$

The following regularity assumption is assumed to hold throughout the paper.

Smoothness. The problem (1.1) has a local minimizer $(\mathbf{x}^*, \mathbf{u}^*)$ in $\mathcal{C}^1(\mathcal{O}_0) \times \mathcal{C}^0(\mathcal{O}_0)$. There exists an open set $\mathcal{O} \subset \mathbb{R}^{m+n}$ and $\rho > 0$ such that

$$\mathcal{B}_\rho(\mathbf{x}^*(t), \mathbf{u}^*(t)) \subset \mathcal{O} \text{ for all } t \in \Omega_0.$$

Moreover, the first two derivative of f and C are Lipschitz continuous on the closure of \mathcal{O} and on $\mathcal{B}_\rho(\mathbf{x}^*(1))$ respectively.

Let $\boldsymbol{\lambda}^*$ denote the solution of the linear costate equation

$$\dot{\boldsymbol{\lambda}}^*(t) = -\nabla_x H(\mathbf{x}^*(t), \mathbf{u}^*(t), \boldsymbol{\lambda}^*(t)), \quad \boldsymbol{\lambda}^*(1) = \nabla C(\mathbf{x}^*(1)), \quad (1.5)$$

where H is the Hamiltonian defined by $H(\mathbf{x}, \mathbf{u}, \boldsymbol{\lambda}) = \boldsymbol{\lambda}^\top \mathbf{f}(\mathbf{x}, \mathbf{u})$ and ∇ denotes gradient. By the first-order optimality conditions (Pontryagin's minimum principle), we have

$$-\nabla_u H(\mathbf{x}^*(t), \mathbf{u}^*(t), \boldsymbol{\lambda}^*(t)) \in N_{\mathcal{U}}(\mathbf{u}^*(t)) \text{ for all } t \in \Omega_0. \quad (1.6)$$

For any $\mathbf{u} \in \mathcal{U}$,

$$N_{\mathcal{U}}(\mathbf{u}) = \{\mathbf{w} \in \mathbb{R}^m : \mathbf{w}^\top (\mathbf{v} - \mathbf{u}) \leq 0 \text{ for all } \mathbf{v} \in \mathcal{U}\},$$

while $N_{\mathcal{U}}(\mathbf{u}) = \emptyset$ if $\mathbf{u} \notin \mathcal{U}$.

We will show that the first-order optimality conditions (Karush-Kuhn-Tucker conditions) for (1.4) are equivalent to the existence of $\boldsymbol{\lambda}_k \in \mathcal{P}_{N-1}^n$, $1 \leq k \leq K$, such that

$$\dot{\boldsymbol{\lambda}}_k(\tau_i) = -h \nabla_x H(\mathbf{x}_k(\tau_i), \mathbf{u}_{ki}, \boldsymbol{\lambda}_k(\tau_i)), \quad 1 \leq i < N, \quad (1.7)$$

$$\dot{\boldsymbol{\lambda}}_k(1) = -h \nabla_x H(\mathbf{x}_k(1), \mathbf{u}_{kN}, \boldsymbol{\lambda}_k(1)) + (\boldsymbol{\lambda}_k(1) - \boldsymbol{\lambda}_{k+1}(-1)) / \omega_N, \quad (1.8)$$

$$\text{where } \boldsymbol{\lambda}_{K+1}(-1) := \nabla C(\mathbf{x}_K(1))$$

$$N_{\mathcal{U}}(\mathbf{u}_{ki}) \ni -\nabla_u H(\mathbf{x}_k(\tau_i), \mathbf{u}_{ki}, \boldsymbol{\lambda}_k(\tau_i)), \quad 1 \leq i \leq N. \quad (1.9)$$

Since the $K+1$ mesh interval does not exist, (1.8) includes a definition for $\boldsymbol{\lambda}_{K+1}(-1)$. As we will see in Proposition 2.1, $\boldsymbol{\lambda}_k(-1)$ for $k \leq K$ is the multiplier associated with the continuity condition (1.3). Throughout the paper, ω_i , $1 \leq i \leq N$, is the Radau quadrature weight associated with τ_i . By [41, Eq. (3.134b)],

$$\omega_i = \frac{2(1 + \tau_i)}{[(1 - \tau_i^2) \dot{P}_{N-1}^{(1,0)}(\tau_i)]^2}, \quad 1 \leq i \leq N-1, \quad \omega_N = \frac{2}{N^2}.$$

Szegő in [42, Thm. 8.9.1] provides tight estimates for both the τ_i and the derivatives of the Jacobi polynomial at τ_i which yield a bound of the form

$$\omega_i \leq cN^{-1} \sqrt{1 - \tau_i^2}, \quad 1 \leq i < N.$$

By [41, Thm. 3.26],

$$\int_{-1}^1 p(\tau) d\tau = \sum_{i=1}^N \omega_i p(\tau_i)$$

for every $p \in \mathcal{P}_{2N-2}$.

Notice that the system (1.7)–(1.9) for the costate approximation does not contain a continuity condition as in the primal discretization (1.4), so the costate approximation could be discontinuous across the mesh points. Since \mathcal{P}_{N-1} has dimension N and $1 \leq k \leq K$, the approximation to a component of the costate has dimension KN , while (1.7)–(1.8) provides KN equations. Hence, if a continuity condition for the costate were imposed at the mesh points, the system of equations (1.7)–(1.9) along with the continuity condition would be overdetermined.

The following two assumptions are utilized in the convergence analysis.

- (A1) For some $\alpha > 0$, the smallest eigenvalue of the Hessian matrices $\nabla^2 C(\mathbf{x}^*(1))$ and $\nabla_{(x,u)}^2 H(\mathbf{x}^*(t), \mathbf{u}^*(t), \boldsymbol{\lambda}^*(t))$ is greater than or equal to α , uniformly for $t \in \Omega_0$.
- (A2) K is large enough, or equivalently h is small enough, that $2hd_1 < 1$ and $2hd_2 < 1$, where

$$d_1 = \sup_{t \in \Omega_0} \|\nabla_x \mathbf{f}(\mathbf{x}^*(t), \mathbf{u}^*(t))\|_\infty \quad \text{and} \quad d_2 = \sup_{t \in \Omega_0} \|\nabla_x \mathbf{f}(\mathbf{x}^*(t), \mathbf{u}^*(t))^\top\|_\infty. \quad (1.10)$$

Here $\|\cdot\|_\infty$ is the matrix sup-norm (largest absolute row sum).

The coercivity assumption (A1) ensures that the solution of the discrete problem is a local minimizer. The condition (A2) enters into the analysis of stability for the perturbed dynamics; as we will see, it ensures that we can solve the linearized dynamics for the discrete state in terms of the discrete control. In [31, p. 804], where we analyze a Gauss collocation scheme on a single interval, there is no h in the analogue of (A2). Hence, the convergence theory in [31] only applies to problems for which $\nabla_x \mathbf{f}(\mathbf{x}^*(t), \mathbf{u}^*(t))$ is sufficiently small. Consequently, the convergence theory for the hp -scheme is more robust since it applies to a broader class of problems.

In addition to the two assumptions, the analysis utilizes four properties of the Radau collocation scheme. Let \mathbf{D} be the N by $N + 1$ matrix defined by

$$D_{ij} = \dot{L}_j(\tau_i), \text{ where } L_j(\tau) := \prod_{\substack{l=0 \\ l \neq j}}^N \frac{\tau - \tau_l}{\tau_j - \tau_l}, \quad 1 \leq i \leq N \text{ and } 0 \leq j \leq N. \quad (1.11)$$

The matrix \mathbf{D} is a differentiation matrix in the sense that $(\mathbf{D}\mathbf{p})_i = \dot{p}(\tau_i)$, $1 \leq i \leq N$, whenever $p \in \mathcal{P}_N$ is the polynomial that satisfies $p(\tau_j) = p_j$ for $0 \leq j \leq N$. The submatrix $\mathbf{D}_{1:N}$, consisting of the trailing N columns of \mathbf{D} , has the following properties:

- (P1) $\mathbf{D}_{1:N}$ is invertible and $\|\mathbf{D}_{1:N}^{-1}\|_\infty = 2$.
- (P2) If \mathbf{W} is the diagonal matrix containing the Radau quadrature weights $\boldsymbol{\omega}$ on the diagonal, then the rows of the matrix $[\mathbf{W}^{1/2}\mathbf{D}_{1:N}]^{-1}$ have Euclidean norm bounded by $\sqrt{2}$.

The fact that $\mathbf{D}_{1:N}$ is invertible is established in [21, Prop. 1], while a proof for the bound on the inverse in (P1) is given in the appendix of [33]; however, there is still no proof for (P2). Numerically, we have checked the rows of $[\mathbf{W}^{1/2}\mathbf{D}_{1:N}]^{-1}$ for N up to 300 and found that the last row of $[\mathbf{W}^{1/2}\mathbf{D}_{1:N}]^{-1}$ always had the largest Euclidean norm. From the formula given in [22, Eq. (53)], the elements in the last row of $\mathbf{D}_{1:N}^{-1}$ are the quadrature weights $\boldsymbol{\omega}$. Hence, the elements in the last row of $[\mathbf{W}^{1/2}\mathbf{D}_{1:N}]^{-1}$ are the square roots of the Radau quadrature weights, and the Euclidean norm of the last row is $\sqrt{2}$, the constant appearing in (P2). Nonetheless, there is still no proof of (P2) for general N .

There is a related matrix that enters into the convergence analysis of the hp -scheme. Let \mathbf{D}^\dagger be the N by N matrix defined by

$$D_{ij}^\dagger = -\left(\frac{\omega_j}{\omega_i}\right) D_{ji}, \quad 1 \leq i \leq N, \quad 1 \leq j \leq N. \quad (1.12)$$

The matrix \mathbf{D}^\dagger arises in the analysis of the costate equation. In Section 4.2.1 of [22], we introduce a matrix \mathbf{D}^\dagger which is a differentiation matrix for the collocation points

τ_i , $1 \leq i \leq N$. That is, if p is a polynomial of degree at most $N - 1$ and \mathbf{p} is the vector with components $p(\tau_i)$, $1 \leq i \leq N$, then $(\mathbf{D}^\dagger \mathbf{p})_i = \dot{p}(\tau_i)$. The matrix \mathbf{D}^\dagger only differs from \mathbf{D}^\dagger in a single entry: $D_{NN}^\dagger = D_{NN}^\dagger - 1/\omega_N$. As a result,

$$(\mathbf{D}^\dagger \mathbf{p})_i = \dot{p}(\tau_i), \quad 1 \leq i < N, \quad (\mathbf{D}^\dagger \mathbf{p})_N = \dot{p}(\tau_N) - p(1)/\omega_N. \quad (1.13)$$

If $\mathbf{D}^\dagger \mathbf{p} = \mathbf{0}$, then $\dot{p}(\tau_i) = 0$ for $i < N$ by the first equality in (1.13). Since \dot{p} has degree $N - 2$ and it vanishes at $N - 1$ points, \dot{p} is identically zero and p is constant. By the final equation in (1.13), $p(1) = 0$ when $\mathbf{D}^\dagger \mathbf{p} = \mathbf{0}$, which implies that p is identically zero. This shows that \mathbf{D}^\dagger is invertible. We find that \mathbf{D}^\dagger has the following properties:

(P3) \mathbf{D}^\dagger is invertible and $\|(\mathbf{D}^\dagger)^{-1}\|_\infty \leq 2$.

(P4) The rows of the matrix $[\mathbf{W}^{1/2} \mathbf{D}^\dagger]^{-1}$ have Euclidean norm bounded by $\sqrt{2}$.

In Proposition 10.1 at the end of the paper, an explicit formula is given for the inverse of \mathbf{D}^\dagger . However, it is not clear from the formula that $\|(\mathbf{D}^\dagger)^{-1}\|_\infty$ is bounded by 2. Numerically, we find that the norms in (P3) and (P4) achieve their maximum in the first row of the matrix, and in the Appendix, we observe that for N up to 300, these norms increase monotonically towards the given bounds. Again, a proof of (P3) and (P4) for general N is missing. Properties (P1)–(P4) differ from the assumptions (A1)–(A2) in the sense that (A1)–(A2) only hold for certain control problems; in contrast, (P1) has been established for general N , while (P2), (P3), and (P4) hold for all choices of N that we have checked. The properties (P1)–(P4) are stated as four separate properties since they are used in different ways in the analysis, however, (P2) implies (P1) and (P4) implies (P3) by the Schwarz inequality, as pointed out in the introduction of [33].

In the analysis of the Gauss scheme [31], properties (P3) and (P4) follow immediately from (P1) and (P2) since the analogue of \mathbf{D}^\dagger in [31] is related to $\mathbf{D}_{1:N}$ through an exchange operation. However, due to the asymmetry of the Radau collocation points and the lower degree of the polynomials in the discrete adjoint system (1.7)–(1.9), a corresponding relationship between \mathbf{D}^\dagger and $\mathbf{D}_{1:N}$ in the Radau scheme does not seem to hold. Nonetheless, the bounds in (P3) and (P4) are observed to be the same as the bounds in (P1) and (P2).

Given a local minimizer $(\mathbf{x}^*, \mathbf{u}^*)$ of (1.1), let \mathbf{x}_k^* , \mathbf{u}_k^* , and $\boldsymbol{\lambda}_k^*$ be the state, control, and costate associated with the mesh interval $[t_{k-1}, t_k]$ and the change of variables $t = t_{k-1/2} + h\tau$. The domain of \mathbf{x}_k^* , \mathbf{u}_k^* , or $\boldsymbol{\lambda}_k^*$ is $[-1, +1]$ where -1 corresponds to t_{k-1} and $+1$ corresponds to t_k . We define the following related discrete variables:

$$\begin{aligned} \mathbf{X}_{kj}^* &= \mathbf{x}_k^*(\tau_j), \quad 0 \leq j \leq N, \quad 1 \leq k \leq K, \\ \mathbf{U}_{kj}^* &= \mathbf{u}_k^*(\tau_j), \quad 1 \leq j \leq N, \quad 1 \leq k \leq K, \\ \boldsymbol{\Lambda}_{kj}^* &= \boldsymbol{\lambda}_k^*(\tau_j), \quad 0 \leq j \leq N, \quad 1 \leq k \leq K. \end{aligned}$$

Suppose that $\mathbf{x}_k^N \in \mathcal{P}_N^n$, $1 \leq k \leq K$, is a polynomial which is a stationary point of (1.4) for some discrete controls \mathbf{u}_k^N , and suppose that $\boldsymbol{\lambda}_k^N \in \mathcal{P}_{N-1}^n$ satisfy (1.7)–(1.9). We define the following related discrete variables:

$$\begin{aligned} \mathbf{X}_{kj}^N &= \mathbf{x}_k^N(\tau_j), \quad 0 \leq j \leq N, \quad 1 \leq k \leq K, \\ \mathbf{U}_{kj}^N &= \mathbf{u}_k^N(\tau_j), \quad 1 \leq j \leq N, \quad 1 \leq k \leq K, \\ \boldsymbol{\Lambda}_{kj}^N &= \boldsymbol{\lambda}_k^N(\tau_j), \quad 0 \leq j \leq N, \quad 1 \leq k \leq K. \end{aligned}$$

Thus capital letters always refer to discrete variables. As noted earlier, the costate polynomials associated with the discrete problem are typically discontinuous across the mesh points, and $\boldsymbol{\Lambda}_{kN}^N \neq \boldsymbol{\Lambda}_{k+1,0}^N$.

The convergence analysis only involves the smoothness of the optimal state and associated costate on the interior of each mesh interval. Let $\mathcal{H}^p(a, b)$ denote the Sobolev space of functions with square integrable derivatives on (a, b) through order p . Let $\mathcal{PH}^p(\Omega_0)$ denote the space of continuous functions whose restrictions to (t_{k-1}, t_k) are contained in $\mathcal{H}^p(t_{k-1}, t_k)$ for each k between 1 and K (piecewise \mathcal{H}^p). The norm on $\mathcal{PH}^p(\Omega_0)$ is the same as the norm on $\mathcal{H}^p(\Omega_0)$ except that the integral is computed over the interior of each mesh interval. In this paper, the error bounds are expressed in terms of a seminorm $|\cdot|_{\mathcal{PH}^p(\Omega_0)}$ which only involves the p -th order derivative:

$$|\mathbf{x}|_{\mathcal{PH}^p(\Omega_0)} = \left(\sum_{k=1}^K \int_{t_{k-1}}^{t_k} \left| \frac{d^p \mathbf{x}(t)}{dt^p} \right|^2 dt \right)^{1/2}.$$

The following convergence result relative to the vector sup-norm (largest absolute element) will be established.

THEOREM 1.1. *If $(\mathbf{x}^*, \mathbf{u}^*)$ is a local minimizer for the continuous problem (1.1) with \mathbf{x}^* and $\boldsymbol{\lambda}^* \in \mathcal{PH}^\eta(\Omega_0)$ for some $\eta \geq 2$, and (A1), (A2), and (P1)–(P4) hold, then for N sufficiently large or for h sufficiently small with $N \geq 2$, the discrete problem (1.4) has a local minimizer and associated multiplier satisfying (1.7)–(1.9), and we have*

$$\begin{aligned} & \max \{ \|\mathbf{X}^N - \mathbf{X}^*\|_\infty, \|\mathbf{U}^N - \mathbf{U}^*\|_\infty, \|\boldsymbol{\Lambda}^N - \boldsymbol{\Lambda}^*\|_\infty \} \\ & \leq h^{p-1} \left(\frac{c}{N} \right)^{p-1} |\mathbf{x}^*|_{\mathcal{PH}^p(\Omega_0)} + h^{q-1} \left(\frac{c}{N} \right)^{q-1.5} |\boldsymbol{\lambda}^*|_{\mathcal{PH}^q(\Omega_0)}, \end{aligned} \quad (1.14)$$

where $p = \min(\eta, N + 1)$, $q = \min(\eta, N)$, and c is independent of h , N , and η .

In a recent paper [33], where we analyze a Gauss collocation scheme on a single interval, $p = q = \min(\eta, N + 1)$. The differences between Radau and Gauss collocation are due to the asymmetry of the Radau points, and the asymmetry in the Radau first-order optimality conditions since $\boldsymbol{\lambda}_k \in \mathcal{P}_{N-1}^n$ and $\mathbf{x}_k \in \mathcal{P}_N^n$.

In the proof of Theorem 1.1, we need to make the right side of (1.14) sufficiently small to establish the existence of the claimed solution to the discrete problem. The conditions $\eta \geq 2$ and $N \geq 2$ in the statement of the theorem ensure that as h goes to zero, h^{p-1} and h^{q-1} go to zero, and as N tends to infinity, $(c/N)^{p-1}$ and $(c/N)^{q-1.5}$ go to zero.

Since the discrete costate could be discontinuous across a mesh point, Theorem 1.1 implies convergence of the discrete costate on either side of the mesh point to the continuous costate at the mesh point. The discrete problem provides an estimate for the optimal control at $t = 1$ in the continuous problem, but not at $t = 0$ since this is not a collocation point. Due to the strong convexity assumption (A1), an estimate for the discrete control at $t = 0$ can be obtained from the minimum principle (1.6) since the initial state is given, while we have an estimate for the associated costate at $t = 0$. Alternatively, polynomial interpolation could be used to obtain estimates for the optimal control at $t = 0$.

The paper is organized as follows. In Section 2 the discrete optimization problem (1.4) is reformulated as a nonlinear system obtained from the first-order optimality conditions, and a general approach to convergence analysis is presented. In Section 3 we obtain a bound for the \mathcal{H}^1 error in interpolation at both the collocation points and $\tau = -1$. Section 4 obtains an estimate for how closely the solution to the continuous problem satisfies the first-order optimality conditions for the discrete problem.

Section 5 establishes the invertibility of the linearized dynamics in the sup-norm. Section 6 shows the invertibility of the linearized differential inclusion, while Section 7 establishes Lipschitz stability of the inverse. This Lipschitz stability property is the basis of Theorem 1.1. Numerical examples are studied in Section 8.

Notation. We let Ω denote the interval $[-1, 1]$, while Ω_0 is the interval $[0, 1]$. Let \mathcal{P}_N denote the space of polynomials of degree at most N , while \mathcal{P}_N^0 is the subspace consisting of polynomials in \mathcal{P}_N that vanish at $t = -1$ and $t = 1$. The meaning of the norm $\|\cdot\|_\infty$ is based on context. If $\mathbf{x} \in \mathcal{C}^0(\Omega)$, then $\|\mathbf{x}\|_\infty$ denotes the maximum of $|\mathbf{x}(t)|$ over $t \in [-1, 1]$, where $|\cdot|$ is the Euclidean norm. For a vector $\mathbf{v} \in \mathbb{R}^m$, $\|\mathbf{v}\|_\infty$ is the maximum of $|v_i|$ over $1 \leq i \leq m$. If $\mathbf{A} \in \mathbb{R}^{m \times n}$, then $\|\mathbf{A}\|_\infty$ is the largest absolute row sum (the matrix norm induced by the ℓ_∞ vector norm). We let $|\mathbf{A}|$ denote the matrix norm induced by the Euclidean vector norm. Throughout the paper, the index k is used for the mesh interval, while the indices i and j are associated with collocation points. If $\mathbf{p} \in \mathbb{R}^{KNn}$, then \mathbf{p}_k for $1 \leq k \leq K$ refers to vector with components $\mathbf{p}_{kj} \in \mathbb{R}^n$, for $1 \leq j \leq N$. The dimension of the identity matrix \mathbf{I} is often clear from context; when necessary, the dimension of \mathbf{I} is specified by a subscript. For example, \mathbf{I}_n is the n by n identity matrix. The gradient is denoted ∇ , while ∇^2 denotes the Hessian; subscripts indicate the differentiation variables. Throughout the paper, c is a generic constant which has different values in different equations. The value of c is always independent of h , N , and η . The vector $\mathbf{1}$ has all entries equal to one, while the vector $\mathbf{0}$ has all entries equal to zero; again, their dimension should be clear from context. If \mathbf{D} is the differentiation matrix introduced in (1.11), then \mathbf{D}_j is the j -th column of \mathbf{D} and $\mathbf{D}_{i:j}$ is the submatrix formed by columns i through j . We let \otimes denote the Kronecker product. If $\mathbf{U} \in \mathbb{R}^{m \times n}$ and $\mathbf{V} \in \mathbb{R}^{p \times q}$, then $\mathbf{U} \otimes \mathbf{V}$ is the mp by nq block matrix whose (i, j) block is $u_{ij}\mathbf{V}$. We let $\mathcal{L}^2(\Omega)$ denote the usual space of square integrable functions on Ω , while $\mathcal{H}^p(\Omega)$ is the Sobolev space consisting of functions with square integrable derivatives through order p . The seminorm in $\mathcal{H}^p(\Omega)$, corresponding to the $\mathcal{L}^2(\Omega)$ norm of the p -order derivatives, is denoted $|\cdot|_{\mathcal{H}^p(\Omega)}$. The subspace of $\mathcal{H}^1(\Omega)$ corresponding to functions that vanish at $t = -1$ and $t = 1$ is denoted $\mathcal{H}_0^1(\Omega)$.

2. Abstract setting. Given a feasible point for the discrete problem (1.4), define $\mathbf{X}_{kj} = \mathbf{x}_k(\tau_j)$ and $\mathbf{U}_{ki} = \mathbf{u}_{ki}$. As noted earlier, \mathbf{D} is a differentiation matrix in the sense that

$$\sum_{j=0}^N D_{ij} \mathbf{X}_{kj} = \dot{\mathbf{x}}_k(\tau_i), \quad 1 \leq i \leq N.$$

Hence, the discrete problem (1.4) can be reformulated as

$$\left. \begin{array}{ll} \text{minimize} & C(\mathbf{X}_{KN}) \\ \text{subject to} & \sum_{j=0}^N D_{ij} \mathbf{X}_{kj} = h\mathbf{f}(\mathbf{X}_{ki}, \mathbf{U}_{ki}), \quad \mathbf{U}_{ki} \in \mathcal{U}, \quad 1 \leq i \leq N, \\ & \mathbf{X}_{k0} = \mathbf{X}_{k-1,N}, \quad 1 \leq k \leq K, \end{array} \right\} \quad (2.1)$$

where $\mathbf{X}_{0N} = \mathbf{a}$, the starting condition.

We introduce multipliers λ_{ki} associated with the constraints in (2.1) and write the Lagrangian as

$$\mathcal{L}(\lambda, \mathbf{X}, \mathbf{U}) = C(\mathbf{X}_{KN}) + \sum_{k=1}^K \sum_{i=1}^N \left\langle \lambda_{ki}, h\mathbf{f}(\mathbf{X}_{ki}, \mathbf{U}_{ki}) - \sum_{j=0}^N D_{ij} \mathbf{X}_{kj} \right\rangle + \sum_{k=1}^K \langle \lambda_{k0}, (\mathbf{X}_{k-1,N} - \mathbf{X}_{k0}) \rangle.$$

The first-order optimality conditions for (2.1) lead to the following relations (we show the variable with which we differentiate followed by the associated condition):

$$\mathbf{X}_{k0} \Rightarrow \sum_{i=1}^N D_{i0} \boldsymbol{\lambda}_{ki} = -\boldsymbol{\lambda}_{k0}, \quad (2.2)$$

$$\mathbf{X}_{kj} \Rightarrow \sum_{i=1}^N D_{ij} \boldsymbol{\lambda}_{ki} = h \nabla_x H(\mathbf{X}_{kj}, \mathbf{U}_{kj}, \boldsymbol{\lambda}_{kj}), \quad 1 \leq j < N, \quad (2.3)$$

$$\mathbf{X}_{kN} \Rightarrow \sum_{i=1}^N D_{iN} \boldsymbol{\lambda}_{ki} = h \nabla_x H(\mathbf{X}_{kN}, \mathbf{U}_{kN}, \boldsymbol{\lambda}_{kN}) + \boldsymbol{\lambda}_{k+1,0}, \quad (2.4)$$

$$\boldsymbol{\lambda}_{K+1,0} := \nabla C(\mathbf{X}_{KN}), \quad (2.5)$$

$$\mathbf{U}_{ki} \Rightarrow -\nabla_u H(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \boldsymbol{\lambda}_{ki}) \in N_{\mathcal{U}}(\mathbf{U}_{ki}). \quad (2.6)$$

We first relate the KKT multipliers to the polynomials satisfying (1.7)–(1.9).

PROPOSITION 2.1. *The multipliers $\boldsymbol{\lambda}_k \in \mathbb{R}^{Nn}$ satisfy (2.2)–(2.6) if and only if the polynomial $\boldsymbol{\lambda}_k \in \mathcal{P}_{N-1}^n$ given by $\boldsymbol{\lambda}_k(\tau_i) = \boldsymbol{\lambda}_{ki}/\omega_i$, $1 \leq i \leq N$, satisfies (1.7)–(1.9). Moreover, $\boldsymbol{\lambda}_{k0} = \boldsymbol{\lambda}_k(-1)$.*

Proof. We start with multipliers $\boldsymbol{\lambda}_k$ satisfying (2.2)–(2.6). Define $\boldsymbol{\Lambda}_{ki} = \boldsymbol{\lambda}_{ki}/\omega_i$ for $1 \leq i \leq N$, and let $\boldsymbol{\lambda}_k \in \mathcal{P}_{N-1}^n$ be the polynomial that satisfies $\boldsymbol{\lambda}_k(\tau_i) = \boldsymbol{\Lambda}_{ki}$. Also, set $\boldsymbol{\Lambda}_{k0} = \boldsymbol{\lambda}_{k0}$. In terms of $\boldsymbol{\Lambda}_{ki}$ and the matrix $D_{ij}^\dagger = -\omega_j D_{ji}/\omega_i$, the equations (2.3), (2.4), and (2.6) become

$$\sum_{j=1}^N D_{ij}^\dagger \boldsymbol{\Lambda}_{kj} = -h \nabla_x H(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \boldsymbol{\Lambda}_{ki}), \quad 1 \leq i < N, \quad (2.7)$$

$$\sum_{i=1}^N D_{Ni}^\dagger \boldsymbol{\Lambda}_{ki} = -[h \nabla_x H(\mathbf{X}_{kN}, \mathbf{U}_{kN}, \boldsymbol{\Lambda}_{kN}) + \boldsymbol{\Lambda}_{k+1,0}/\omega_N], \quad (2.8)$$

$$N_{\mathcal{U}}(\mathbf{U}_{ki}) \ni -\nabla_u H(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \boldsymbol{\Lambda}_{ki}), \quad 1 \leq i \leq N. \quad (2.9)$$

Since the polynomial that is identically equal to $\mathbf{1}$ has derivative $\mathbf{0}$ and since \mathbf{D} is a differentiation matrix, we have $\mathbf{D}\mathbf{1} = \mathbf{0}$, which implies that $\mathbf{D}_0 = -\sum_{j=1}^N \mathbf{D}_j$, where \mathbf{D}_j is the j -th column of \mathbf{D} . Hence, the first definition in (2.2) can be written

$$\begin{aligned} \boldsymbol{\Lambda}_{k0} &= -\sum_{i=1}^N \boldsymbol{\lambda}_{ki} D_{i0} = \sum_{i=1}^N \sum_{j=1}^N \boldsymbol{\lambda}_{ki} D_{ij} = \sum_{i=1}^N \sum_{j=1}^N \omega_j \left(\frac{\boldsymbol{\lambda}_{ki}}{\omega_i} \right) (\omega_i D_{ij}/\omega_j) \\ &= -\sum_{i=1}^N \sum_{j=1}^N \omega_i D_{ij}^\dagger \boldsymbol{\Lambda}_{kj} \end{aligned} \quad (2.10)$$

$$= \boldsymbol{\Lambda}_{k+1,0} + h \sum_{i=1}^N \omega_i \nabla_x H(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \boldsymbol{\Lambda}_{ki}), \quad (2.11)$$

where (2.11) is due to (2.7)–(2.8).

As noted in (1.13),

$$\sum_{j=1}^N D_{ij}^\dagger \mathbf{\Lambda}_{kj} = \dot{\boldsymbol{\lambda}}_k(\tau_i), \quad 1 \leq i < N, \quad \text{and} \quad (2.12)$$

$$\sum_{j=1}^N D_{Nj}^\dagger \mathbf{\Lambda}_{kj} = \dot{\boldsymbol{\lambda}}_k(1) - \boldsymbol{\lambda}_k(1)/\omega_N. \quad (2.13)$$

This substitution in (2.10) yields

$$\mathbf{\Lambda}_{k0} = \boldsymbol{\lambda}_k(1) - \sum_{i=1}^N \omega_i \dot{\boldsymbol{\lambda}}_k(\tau_i). \quad (2.14)$$

Since $\dot{\boldsymbol{\lambda}}_k \in \mathcal{P}_{N-2}^n$ and N -point Radau quadrature is exact for these polynomial, we have

$$\sum_{i=1}^N \omega_i \dot{\boldsymbol{\lambda}}_k(\tau_i) = \int_{-1}^1 \dot{\boldsymbol{\lambda}}_k(\tau) d\tau = \boldsymbol{\lambda}_k(1) - \boldsymbol{\lambda}_k(-1). \quad (2.15)$$

Combine (2.14) and (2.15) to obtain

$$\mathbf{\Lambda}_{k0} = \boldsymbol{\lambda}_k(-1). \quad (2.16)$$

Let $\mathbf{x}_k \in \mathcal{P}_N^n$ be the polynomial that satisfies $\mathbf{x}_k(\tau_j) = \mathbf{X}_{kj}$ for all $0 \leq j \leq N$. By (2.12), (1.7) is equivalent to (2.7) which is equivalent to (2.3) after a change of variables. By (2.13) and (2.16), (1.8) is equivalent to (2.8), which is equivalent to (2.4) after a change of variables. Finally, (1.9) is the same as (2.9) which is equivalent to (2.6) after a change of variables. The equivalence between $\mathbf{\Lambda}_{k0}$ and $\boldsymbol{\lambda}_k(-1)$ was derived in (2.16). This shows that the polynomial $\boldsymbol{\lambda}_k(\tau)$ satisfies (1.7)–(1.9). The converse of the proposition follows by reversing all the steps in the derivation. \square

The dynamics for (2.1), the first-order optimality conditions (2.7)–(2.9), the formula (2.11) for $\mathbf{\Lambda}_{k0}$, and the terminal costate condition (2.5) can be written as $\mathcal{T}(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}) \in \mathcal{F}(\mathbf{U})$ where

$$\begin{aligned} \mathcal{T}_{1ki}(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}) &= \left(\sum_{j=0}^N D_{ij} \mathbf{X}_{kj} \right) - h\mathbf{f}(\mathbf{X}_{ki}, \mathbf{U}_{ki}), \quad 1 \leq i \leq N, \\ \mathcal{T}_{2k}(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}) &= \mathbf{X}_{k0} - \mathbf{X}_{k-1,N}, \\ \mathcal{T}_{3ki}(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}) &= \left(\sum_{j=1}^N D_{ij}^\dagger \mathbf{\Lambda}_{kj} \right) + h\nabla_x H(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \mathbf{\Lambda}_{ki}), \quad 1 \leq i < N, \\ \mathcal{T}_{3kN}(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}) &= \sum_{j=1}^N D_{Nj}^\dagger \mathbf{\Lambda}_{kj} + h\nabla_x H(\mathbf{X}_{kN}, \mathbf{U}_{kN}, \mathbf{\Lambda}_{kN}) + \mathbf{\Lambda}_{k+1,0}/\omega_N, \\ \mathcal{T}_{4k}(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}) &= \mathbf{\Lambda}_{k0} - \mathbf{\Lambda}_{k+1,0} - h \sum_{i=1}^N \omega_i \nabla_x H(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \mathbf{\Lambda}_{ki}), \\ \mathcal{T}_5(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}) &= \nabla C(\mathbf{X}_{KN}) - \mathbf{\Lambda}_{K+1,0}, \\ \mathcal{T}_{6ki}(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}) &= -h\nabla_u H(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \mathbf{\Lambda}_{ki}), \quad 1 \leq i \leq N, \end{aligned}$$

where $1 \leq k \leq K$. The initial state is $\mathbf{X}_{0N} = \mathbf{X}_{10} = \mathbf{a}$. The components of \mathcal{F} are given by

$$\mathcal{F}_1 = \mathcal{F}_2 = \mathcal{F}_3 = \mathcal{F}_4 = \mathcal{F}_5 = \mathbf{0}, \quad \text{and } \mathcal{F}_{6ki}(\mathbf{U}) = N_{\mathcal{U}}(\mathbf{U}_{ki}).$$

The proof of Theorem 1.1 is based on [15, Proposition 3.1], given below in a slightly simplified form. Other results like this are contained in Theorem 3.1 of [14], in Proposition 5.1 of [28], in Theorem 2.1 of [29], and in Theorem 1 of [27].

PROPOSITION 2.2. *Let \mathcal{X} be a Banach space and let \mathcal{Y} be a linear normed space with the norms in both spaces denoted $\|\cdot\|$. Let $\mathcal{F} : \mathcal{X} \mapsto 2^{\mathcal{Y}}$ and let $\mathcal{T} : \mathcal{X} \mapsto \mathcal{Y}$ with \mathcal{T} continuously Fréchet differentiable in $B_r(\boldsymbol{\theta}^*)$, the ball with center $\boldsymbol{\theta}^*$ and radius r , for some $\boldsymbol{\theta}^* \in \mathcal{X}$ and $r > 0$. Suppose that the following conditions hold for some $\boldsymbol{\delta} \in \mathcal{Y}$ and scalars ϵ and $\gamma > 0$:*

(C1) $\mathcal{T}(\boldsymbol{\theta}^*) + \boldsymbol{\delta} \in \mathcal{F}(\boldsymbol{\theta}^*)$.

(C2) $\|\nabla \mathcal{T}(\boldsymbol{\theta}) - \nabla \mathcal{T}(\boldsymbol{\theta}^*)\| \leq \epsilon$ for all $\boldsymbol{\theta} \in B_r(\boldsymbol{\theta}^*)$.

(C3) The map $(\mathcal{F} - \nabla \mathcal{T}(\boldsymbol{\theta}^*))^{-1}$ is single-valued and Lipschitz continuous with Lipschitz constant γ .

If $\epsilon\gamma < 1$ and $\|\boldsymbol{\delta}\| \leq (1 - \gamma\epsilon)r/\gamma$, then there exists a unique $\boldsymbol{\theta} \in B_r(\boldsymbol{\theta}^*)$ such that $\mathcal{T}(\boldsymbol{\theta}) \in \mathcal{F}(\boldsymbol{\theta})$. Moreover, we have the estimate

$$\|\boldsymbol{\theta} - \boldsymbol{\theta}^*\| \leq \frac{\gamma}{1 - \gamma\epsilon} \|\boldsymbol{\delta}\|. \quad (2.17)$$

We apply Proposition 2.2 with $\boldsymbol{\theta}^* = (\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*)$ and $\boldsymbol{\theta} = (\mathbf{X}^N, \mathbf{U}^N, \boldsymbol{\Lambda}^N)$, where the discrete variables were defined before Theorem 1.1. We use the sup-norm for \mathcal{X} :

$$\|\boldsymbol{\theta}\| = \|(\mathbf{X}, \mathbf{U}, \boldsymbol{\Lambda})\|_{\infty} = \max\{\|\mathbf{X}\|_{\infty}, \|\mathbf{U}\|_{\infty}, \|\boldsymbol{\Lambda}\|_{\infty}\}. \quad (2.18)$$

For this norm, the left side of (1.14) and the left side of (2.17) are the same. The space \mathcal{Y} corresponds to the codomain of \mathcal{T} . If $\mathbf{y} \in \mathcal{Y}$, then we let \mathbf{y}_l denote the part of \mathbf{y} associated with \mathcal{T}_l , $1 \leq l \leq 6$. The norm of $\mathbf{y} \in \mathcal{Y}$ is given by

$$\|\mathbf{y}\|_{\mathcal{Y}} = \|\mathbf{y}_1\|_{\omega} + |\mathbf{y}_2| + \|\mathbf{y}_3\|_{\omega} + |\mathbf{y}_4| + h^{1/2}|\mathbf{y}_5| + h^{-1/2}\|\mathbf{y}_6\|_{\infty},$$

where for $\mathbf{z} \in \mathbb{R}^{KNn}$, the ω -norm is defined by

$$\|\mathbf{z}\|_{\omega} = \left(\sum_{k=1}^K \sum_{i=1}^N \omega_i |\mathbf{z}_{ki}|^2 \right)^{1/2}, \quad \mathbf{z}_{ki} \in \mathbb{R}^n.$$

For $\mathbf{z} \in \mathbb{R}^{Nn}$, the ω -norm is

$$\|\mathbf{z}\|_{\omega} = \left(\sum_{i=1}^N \omega_i |\mathbf{z}_i|^2 \right)^{1/2}, \quad \mathbf{z}_i \in \mathbb{R}^n.$$

3. Interpolation error in \mathcal{H}^1 . Our error analysis is based on a result concerning the error in interpolation at the point set τ_i , $0 \leq i \leq N$, where τ_i for $i > 0$ are the N Radau quadrature points on Ω , and $\tau_0 = -1$.

LEMMA 3.1. *If $u \in \mathcal{H}^{\eta}(\Omega)$ for some $\eta \geq 1$, then there exists a constant c , independent of N and η , such that*

$$|u - u^I|_{\mathcal{H}^1(\Omega)} \leq (c/N)^{p-1} |u|_{\mathcal{H}^p(\Omega)}, \quad p = \min\{\eta, N+1\}, \quad (3.1)$$

where $u^I \in \mathcal{P}_N$ is the interpolant of u satisfying $u^I(\tau_i) = u(\tau_i)$, $0 \leq i \leq N$, and $N > 0$.

Proof. Throughout the analysis, c denotes a generic constant whose value is independent of N and η , and which may have different values in different equations. Let ℓ denote the linear function for which $\ell(\pm 1) = u(\pm 1)$. If the lemma holds for all $u \in \mathcal{H}_0^1(\Omega) \cap \mathcal{H}^\eta(\Omega)$, then it holds for all $u \in \mathcal{H}^\eta(\Omega)$ since $|u - u^I|_{\mathcal{H}^1(\Omega)} = |(u - \ell) - (u - \ell)^I|_{\mathcal{H}^1(\Omega)}$ and $|u - \ell|_{\mathcal{H}^p(\Omega)} \leq c|u|_{\mathcal{H}^p(\Omega)}$. Hence, without loss of generality, it is assumed that $u \in \mathcal{H}_0^1(\Omega) \cap \mathcal{H}^\eta(\Omega)$.

Let $\pi_N u$ denote the projection of u into \mathcal{P}_N^0 relative to the norm $|\cdot|_{\mathcal{H}^1(\Omega)}$. Define $E_N = u - \pi_N u$ and $e_N = E_N^I = (u - \pi_N u)^I = u^I - \pi_N u$. Since $E_N - e_N = u - u^I$, it follows that

$$|u - u^I|_{\mathcal{H}^1(\Omega)} \leq |E_N|_{\mathcal{H}^1(\Omega)} + |e_N|_{\mathcal{H}^1(\Omega)}. \quad (3.2)$$

In [18, Prop. 3.1] it is shown that

$$|E_N|_{\mathcal{H}^1(\Omega)} \leq (c/N)^{p-1} |u|_{\mathcal{H}^p(\Omega)}, \quad \text{where } p = \min\{\eta, N+1\}. \quad (3.3)$$

We will establish the bound

$$|e_N|_{\mathcal{H}^1(\Omega)} \leq c|E_N|_{\mathcal{H}^1(\Omega)}. \quad (3.4)$$

Combine (3.2)–(3.4) to obtain (3.1) for an appropriate choice of c .

By [5, Lem. 4.4] and the fact that $e_N \in \mathcal{P}_N^0$, it follows that

$$|e_N|_{\mathcal{H}^1(\Omega)} \leq cN \left(\int_{\Omega} \frac{e_N^2(\tau)}{1-\tau^2} d\tau \right)^{1/2}. \quad (3.5)$$

Since $e_N \in \mathcal{P}_N^0$ and $e_N^2(\tau)/(1-\tau^2) \in \mathcal{P}_{2N-2}^0$, N -point Radau quadrature is exact, and we have

$$\left(\int_{\Omega} \frac{e_N^2(\tau)}{1-\tau^2} d\tau \right)^{1/2} = \left(\sum_{i=1}^{N-1} \frac{\omega_i e_N^2(\tau_i)}{1-\tau_i^2} \right)^{1/2} = \left(\sum_{i=1}^{N-1} \frac{\omega_i E_N^2(\tau_i)}{1-\tau_i^2} \right)^{1/2}. \quad (3.6)$$

The last equality holds since $e_N = E_N$ at τ_i , $0 \leq i \leq N$. Although Lemma 4.3 in [5] was given for Lobatto quadrature, exactly the same proof can be used for both Gauss and Radau quadrature. Consequently, since $E_N \in \mathcal{H}_0^1(\Omega)$, it follows from [5, Lem. 4.3] that

$$\left(\sum_{i=1}^N \frac{\omega_i E_N^2(\tau_i)}{1-\tau_i^2} \right)^{1/2} \leq c \left[\left(\int_{\Omega} \frac{E_N^2(\tau)}{1-\tau^2} d\tau \right)^{1/2} + N^{-1} |E_N|_{\mathcal{H}^1(\Omega)} \right]. \quad (3.7)$$

By [33, Prop. 9.1], we have

$$N \left[\left(\int_{\Omega} \frac{E_N^2(\tau)}{1-\tau^2} d\tau \right)^{1/2} + N^{-1} |E_N|_{\mathcal{H}^1(\Omega)} \right] \leq 2|E_N|_{\mathcal{H}^1(\Omega)}. \quad (3.8)$$

Combine (3.5)–(3.8) to obtain (3.4). \square

REMARK 3.1. In the analogue of Lemma 3.1 for the Gauss quadrature points given in [33, Lem. 4.1], the exponent in the error bound is $p - 1.5$ instead of $p - 1$. The difference in the exponent is due to the treatment of endpoints. In the Radau result, the polynomial interpolates at both $\tau = -1$ and $\tau = 1$, while in the Gauss result, the polynomial interpolates only at $\tau = -1$.

4. Analysis of the residual. We now establish a bound for the distance from $\mathcal{T}(\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*)$ to $\mathcal{F}(\mathbf{U}^*)$. This bound for the residual ultimately enters into the right side of the error estimate (1.14).

LEMMA 4.1. *If \mathbf{x}^* and $\boldsymbol{\lambda}^* \in \mathcal{PH}^\eta(\Omega_0)$ for some $\eta \geq 2$, then there exists a constant c , independent of N , h , and η , such that*

$$\begin{aligned} & \text{dist}[\mathcal{T}(\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*), \mathcal{F}(\mathbf{U}^*)]_{\mathcal{Y}} \\ & \leq h^{p-1/2} \left(\frac{c}{N} \right)^{p-1} |\mathbf{x}^*|_{\mathcal{PH}^p(\Omega_0)} + h^{q-1/2} \left(\frac{c}{N} \right)^{q-1.5} |\boldsymbol{\lambda}^*|_{\mathcal{PH}^q(\Omega_0)}, \end{aligned} \quad (4.1)$$

where $p = \min(\eta, N+1)$ and $q = \min(\eta, N)$.

Proof. Since $\mathcal{T}(\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*)$ appears throughout the analysis, it is abbreviated \mathcal{T}^* . Since the minimum principle (1.6) holds for all $t \in \Omega_0$, it holds at the collocation points, which implies that $\mathcal{T}_6^* \in \mathcal{F}_6(\mathbf{U}^*)$. Also, $\mathcal{T}_2^* = \mathcal{T}_5^* = \mathbf{0}$ since the optimal state is continuous and it satisfies the terminal condition (1.5) in the costate equation. Thus we only need to analyze \mathcal{T}_1^* , \mathcal{T}_3^* , and \mathcal{T}_4^* .

Let us first consider \mathcal{T}_1^* . Since \mathbf{D} is a differentiation matrix associated with the collocation points, we have

$$\sum_{j=0}^N D_{ij} \mathbf{X}_{kj}^* = \dot{\mathbf{x}}_k^I(\tau_i), \quad 1 \leq i \leq N, \quad (4.2)$$

where $\mathbf{x}_k^I \in \mathcal{P}_N^n$ is the (interpolating) polynomial that passes through $\mathbf{x}_k^*(\tau_j)$ for $0 \leq j \leq N$. Since \mathbf{x}^* satisfies the dynamics of (1.1),

$$h\mathbf{f}(\mathbf{X}_{ki}^*, \mathbf{U}_{ki}^*) = \dot{\mathbf{x}}_k^*(\tau_i). \quad (4.3)$$

Combine (4.2) and (4.3) to obtain

$$\mathcal{T}_{1ki}^* = \dot{\mathbf{x}}_k^I(\tau_i) - \dot{\mathbf{x}}_k^*(\tau_i) = \dot{\mathbf{x}}_k^I(\tau_i) - (\dot{\mathbf{x}}_k^*)^J(\tau_i), \quad (4.4)$$

where $(\dot{\mathbf{x}}_k^*)^J \in \mathcal{P}_{N-1}^n$ is the interpolant that passes through $\dot{\mathbf{x}}_k^*(\tau_i)$ for $1 \leq i \leq N$. Since both $\dot{\mathbf{x}}^I$ and $(\dot{\mathbf{x}}^*)^J$ are polynomials of degree $N-1$ and Radau quadrature is exact for polynomials of degree $2N-2$, it follows that

$$\begin{aligned} \|\mathcal{T}_1^*\|_{\omega}^2 &= \sum_{k=1}^K \sum_{i=1}^N \omega_i |\dot{\mathbf{x}}_k^I(\tau_i) - (\dot{\mathbf{x}}_k^*)^J(\tau_i)|^2 \\ &= \sum_{k=1}^K \int_{-1}^1 |\dot{\mathbf{x}}_k^I(\tau) - (\dot{\mathbf{x}}_k^*)^J(\tau)|^2 d\tau \\ &\leq 2 \sum_{k=1}^K \int_{-1}^1 (|\dot{\mathbf{x}}_k^I(\tau) - \dot{\mathbf{x}}_k^*(\tau)|^2 + |\dot{\mathbf{x}}_k^*(\tau) - (\dot{\mathbf{x}}_k^*)^J(\tau)|^2) d\tau. \end{aligned} \quad (4.5)$$

By Lemma 3.1, we have

$$\|\dot{\mathbf{x}}_k^I - \dot{\mathbf{x}}_k^*\|_{\mathcal{L}^2(\Omega)} \leq (c/N)^{p-1} |\mathbf{x}_k^*|_{\mathcal{H}^p(\Omega)}, \quad p = \min\{\eta, N+1\}. \quad (4.6)$$

The second term in (4.5) involves the difference between $\dot{\mathbf{x}}_k^* \in \mathcal{H}^{(\eta-1)}$ and its interpolant $(\dot{\mathbf{x}}_k^*)^J \in \mathcal{P}_{N-1}^n$ at the N Radau points. By the bound given in [8, (5.4.33)]

for the \mathcal{L}^2 error in Radau interpolation, this term has exactly the same bound as that on the right side of (4.6). Since $\mathbf{x}_k(\tau) = \mathbf{x}(t_{k-1/2} + h\tau)$, the derivatives contained in the right side of (4.6) satisfy

$$\frac{d^p \mathbf{x}_k^*(\tau)}{d\tau^p} = h^p \frac{d^p \mathbf{x}^*(t)}{dt^p} \Big|_{t=t_{k-1/2}+h\tau}.$$

Consequently, after a change of variables, we have

$$\int_{-1}^1 \left| \frac{d^p \mathbf{x}_k^*(\tau)}{d\tau^p} \right|^2 d\tau = h^{2p-1} \int_{t_{k-1}}^{t_k} \left| \frac{d^p \mathbf{x}^*(t)}{dt^p} \right|^2 dt.$$

Combine this with (4.5) and (4.6) to deduce that $\|\mathcal{T}_1^*\|_\omega$ is bounded by the first term on the right side of (4.1).

The analysis of \mathcal{T}_3^* is similar to the analysis of \mathcal{T}_1^* . Let $\boldsymbol{\lambda}_k^I \in \mathcal{P}_{N-1}^n$ be the polynomial that interpolates $\boldsymbol{\lambda}_k^*(\tau_j)$ for $1 \leq j \leq N$. By (2.12) and (2.13), we have

$$\sum_{j=1}^N D_{ij}^\dagger \mathbf{A}_{kj}^* = \dot{\boldsymbol{\lambda}}_k^I(\tau_i), \quad 1 \leq i < N, \quad (4.7)$$

$$\sum_{j=1}^N D_{Nj}^\dagger \mathbf{A}_{kj}^* = \dot{\boldsymbol{\lambda}}_k^I(\tau_i) - \boldsymbol{\lambda}_k^*(1)/\omega_N. \quad (4.8)$$

Since $\boldsymbol{\lambda}^*$ satisfies (1.5), it follows that

$$h \nabla_x H(\mathbf{X}_{ki}^*, \mathbf{U}_{ki}^*, \mathbf{A}_{ki}^*) = h \nabla_x H(\mathbf{x}_k^*(\tau_i), \mathbf{u}_k^*(\tau_i), \boldsymbol{\lambda}_k^*(\tau_i)) = -\dot{\boldsymbol{\lambda}}_k^*(\tau_i), \quad (4.9)$$

$1 \leq i \leq N$. We substitute (4.7)–(4.9) in the definition of \mathcal{T}_3 to obtain

$$\mathcal{T}_{3ki}(\mathbf{X}^*, \mathbf{U}^*, \mathbf{A}^*) = \dot{\boldsymbol{\lambda}}_k^I(\tau_i) - \dot{\boldsymbol{\lambda}}_k^*(\tau_i) = \dot{\boldsymbol{\lambda}}_k^I(\tau_i) - (\dot{\boldsymbol{\lambda}}_k^*)^J(\tau_i), \quad 1 \leq i \leq N,$$

where $(\dot{\boldsymbol{\lambda}}_k^*)^J \in \mathcal{P}_{N-1}^n$ is the polynomial that passes through $\dot{\boldsymbol{\lambda}}_k^*(\tau_i)$, $1 \leq i \leq N$. Note that the term $-\boldsymbol{\lambda}_k^*(1)/\omega_N$ in (4.8) cancels the corresponding term in \mathcal{T}_{3k} due to the continuity of $\boldsymbol{\lambda}^*$. Since $\dot{\boldsymbol{\lambda}}_k^I \in \mathcal{P}_{N-2}^n$ and $(\dot{\boldsymbol{\lambda}}_k^*)^J \in \mathcal{P}_{N-1}^n$, and since Radau quadrature is exact for polynomials of degree $2N-2$, we obtain, as in (4.5),

$$\|\mathcal{T}_3^*\|_\omega^2 \leq 2 \sum_{k=1}^K \int_{-1}^1 \left(|\dot{\boldsymbol{\lambda}}_k^I(\tau) - \dot{\boldsymbol{\lambda}}_k^*(\tau)|^2 + |\dot{\boldsymbol{\lambda}}_k^*(\tau) - (\dot{\boldsymbol{\lambda}}_k^*)^J(\tau)|^2 \right) d\tau. \quad (4.10)$$

The last term in (4.10) has the bound

$$\|(\dot{\boldsymbol{\lambda}}_k^*)^J - \dot{\boldsymbol{\lambda}}_k^*\|_{\mathcal{L}^2(\Omega)} \leq h^p (c/N)^{p-1} |\boldsymbol{\lambda}^*|_{\mathcal{H}^p(t_{k-1}, t_k)}, \quad p = \min\{\eta, N+1\}, \quad (4.11)$$

corresponding to the \mathcal{L}^2 error in interpolation at the Radau points. The other term, however, is different from the state since $\boldsymbol{\lambda}_k^I$ has degree $N-1$ while the state \mathbf{x}_k^I has degree N , and the state interpolates at both the quadrature points and at $\tau = -1$, while $\boldsymbol{\lambda}_k^I$ only interpolates at the quadrature points. The error in the derivative of the interpolant at the Radau points has the bound [8, (5.4.34)]

$$\|\dot{\boldsymbol{\lambda}}_k^I - \dot{\boldsymbol{\lambda}}_k^*\|_{\mathcal{L}^2(\Omega)} \leq h^q (c/N)^{q-1.5} |\boldsymbol{\lambda}^*|_{\mathcal{H}^q(\Omega)}, \quad q = \min\{\eta, N\}. \quad (4.12)$$

The exponent changes from $p-1$ in (4.11) to $q-1.5$ due to the fact that $\boldsymbol{\lambda}_k^I$ does not interpolate at $\tau = -1$, and $q \leq p$ since the polynomial associated with $\boldsymbol{\lambda}_k^I$ has degree $N-1$. Note that if $\boldsymbol{\lambda}^* \in \mathcal{PH}^\eta(\Omega_0)$, then $\boldsymbol{\lambda}^* \in \mathcal{PH}^{(\eta-1)}(\Omega_0)$, so we can always ensure that the error bound (4.12) dominates the error bound (4.11) by lowering η in (4.11) if necessary. Utilizing the bound (4.12) in (4.10) and changing variables from τ to t , we deduce that $\|\mathcal{T}_3\|_\omega$ is bounded by the second term on the right side of (4.1).

Finally, let us consider \mathcal{T}_4^* . Applying (4.9) and utilizing the continuity of $\boldsymbol{\lambda}^*$ and the exactness of Radau quadrature, we have

$$\begin{aligned} \mathcal{T}_{4k}^* &= \boldsymbol{\lambda}_k^*(-1) - \boldsymbol{\lambda}_{k+1}^*(-1) + \sum_{i=1}^N \omega_i \dot{\boldsymbol{\lambda}}_k^*(\tau_i) \\ &= \boldsymbol{\lambda}_k^*(-1) - \boldsymbol{\lambda}_k^*(1) + \sum_{i=1}^N \omega_i (\dot{\boldsymbol{\lambda}}_k^*)^J(\tau_i) \\ &= \boldsymbol{\lambda}_k^*(-1) - \boldsymbol{\lambda}_k^*(1) + \int_{-1}^1 (\dot{\boldsymbol{\lambda}}_k^*)^J(\tau) d\tau = \int_{-1}^1 [(\dot{\boldsymbol{\lambda}}_k^*)^J(\tau) - \dot{\boldsymbol{\lambda}}_k^*(\tau)] d\tau. \end{aligned}$$

By (4.11) and the Schwarz inequality, we have

$$|\mathcal{T}_{4k}^*| \leq \sqrt{2} \|(\dot{\boldsymbol{\lambda}}_k^*)^J - \dot{\boldsymbol{\lambda}}_k^*\|_{\mathcal{L}^2(\Omega)} \leq h^p (c/N)^{p-1} |\boldsymbol{\lambda}^*|_{\mathcal{H}^p(\Omega)}, \quad p = \min\{\eta, N+1\}.$$

As in the analysis of \mathcal{T}_3 , we square this, sum over k , change variables from τ to t , and take the square root to obtain a bound that can be dominated by the last term in (4.1). This completes the proof. \square

5. Invertibility of linearized dynamics. In this section, we introduce the linearized inclusion and establish the invertibility of the linearized dynamics for both the state and costate. Given $\mathbf{Y} \in \mathcal{Y}$, the linearized problem is to find $(\mathbf{X}, \mathbf{U}, \boldsymbol{\Lambda})$ such that

$$\nabla \mathcal{T}(\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*)[\mathbf{X}, \mathbf{U}, \boldsymbol{\Lambda}] + \mathbf{y} \in \mathcal{F}(\mathbf{U}). \quad (5.1)$$

Here $\nabla \mathcal{T}(\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*)[\mathbf{X}, \mathbf{U}, \boldsymbol{\Lambda}]$ denotes the derivative of \mathcal{T} evaluated at $(\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*)$ operating on $[\mathbf{X}, \mathbf{U}, \boldsymbol{\Lambda}]$. Since $\nabla \mathcal{T}(\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*)$ appears frequently in the analysis, it is abbreviated $\nabla \mathcal{T}^*$. The derivative $\nabla \mathcal{T}^*$ is built from the following matrices for $1 \leq k \leq K$:

$$\begin{aligned} \mathbf{A}_{ki} &= \nabla_x \mathbf{f}(\mathbf{x}_k^*(\tau_i), \mathbf{u}_k^*(\tau_i)), & \mathbf{B}_{ki} &= \nabla_u \mathbf{f}(\mathbf{x}_k^*(\tau_i), \mathbf{u}_k^*(\tau_i)), \\ \mathbf{Q}_{ki} &= \nabla_{xx}^2 H(\mathbf{x}_k^*(\tau_i), \mathbf{u}_k^*(\tau_i), \boldsymbol{\lambda}_k^*(\tau_i)), & \mathbf{S}_{ki} &= \nabla_{xu}^2 H(\mathbf{x}_k^*(\tau_i), \mathbf{u}_k^*(\tau_i), \boldsymbol{\lambda}_k^*(\tau_i)), \\ \mathbf{R}_{ki} &= \nabla_{uu}^2 H(\mathbf{x}_k^*(\tau_i), \mathbf{u}_k^*(\tau_i), \boldsymbol{\lambda}_k^*(\tau_i)), & \mathbf{T} &= \nabla^2 C(\mathbf{x}^*(1)), \end{aligned}$$

With this notation, the elements of $\nabla \mathcal{T}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}]$ are as follows:

$$\begin{aligned}
\nabla \mathcal{T}_{1ki}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}] &= \left(\sum_{j=0}^N D_{ij} \mathbf{X}_{kj} \right) - h(\mathbf{A}_{ki} \mathbf{X}_{ki} + \mathbf{B}_{ki} \mathbf{U}_{ki}), \quad 1 \leq i \leq N, \\
\nabla \mathcal{T}_{2k}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}] &= \mathbf{X}_{k0} - \mathbf{X}_{k-1,N}, \quad \text{where } \mathbf{X}_{0N} = \mathbf{0}, \\
\nabla \mathcal{T}_{3ki}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}] &= \left(\sum_{j=1}^N D_{ij}^\dagger \mathbf{\Lambda}_{kj} \right) + h(\mathbf{A}_{ki}^\top \mathbf{\Lambda}_{ki} + \mathbf{Q}_{ki} \mathbf{X}_{ki} + \mathbf{S}_{ki} \mathbf{U}_{ki}), \quad 1 \leq i < N, \\
\nabla \mathcal{T}_{3kN}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}] &= \left(\sum_{j=1}^N D_{Nj}^\dagger \mathbf{\Lambda}_{kj} \right) + h(\mathbf{A}_{kN}^\top \mathbf{\Lambda}_{kN} + \mathbf{Q}_{kN} \mathbf{X}_{kN} + \mathbf{S}_{kN} \mathbf{U}_{kN}) \\
&\quad + \mathbf{\Lambda}_{k+1,0}/\omega_N, \\
\nabla \mathcal{T}_{4k}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}] &= \mathbf{\Lambda}_{k0} - \mathbf{\Lambda}_{k+1,0} - h \sum_{i=1}^N \omega_i (\mathbf{A}_{ki}^\top \mathbf{\Lambda}_{ki} + \mathbf{Q}_{ki} \mathbf{X}_{ki} + \mathbf{S}_{ki} \mathbf{U}_{ki}), \\
\nabla \mathcal{T}_{5k}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}] &= \mathbf{T} \mathbf{X}_{KN} - \mathbf{\Lambda}_{K+1,0}, \\
\nabla \mathcal{T}_{6ki}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}] &= -h(\mathbf{B}_{ki}^\top \mathbf{\Lambda}_{ki} + \mathbf{S}_{ki}^\top \mathbf{X}_{ki} + \mathbf{R}_{ki} \mathbf{U}_{ki}), \quad 1 \leq i \leq N,
\end{aligned} \tag{5.2}$$

where $1 \leq k \leq K$.

The following result establishes invertibility of the linearized state dynamics.

LEMMA 5.1. *If (P1), (P2), and (A2) hold, then for each $\mathbf{q} \in \mathbb{R}^{Kn}$ and $\mathbf{p} \in \mathbb{R}^{KNn}$ with \mathbf{q}_k and $\mathbf{p}_{ki} \in \mathbb{R}^n$, the linear system*

$$\sum_{j=0}^N D_{ij} \mathbf{X}_{kj} = h \mathbf{A}_{ki} \mathbf{X}_{ki} + \mathbf{p}_{ki}, \quad 1 \leq i \leq N, \tag{5.3}$$

$$\mathbf{X}_{k0} = \mathbf{X}_{k-1,N} + \mathbf{q}_k, \quad \mathbf{X}_{0N} = \mathbf{0}, \tag{5.4}$$

$1 \leq k \leq K$, has a unique solution $\mathbf{X} \in \mathbb{R}^{K(N+1)n}$. This solution has the bound

$$\sup_{\substack{1 \leq k \leq K \\ 1 \leq j \leq N}} \|\mathbf{X}_{kj}\|_\infty \leq h^{-1/2} \left(\frac{\sqrt{2} \|\mathbf{p}\|_\omega + |\mathbf{q}|}{(1 - 2hd_1)^K} \right). \tag{5.5}$$

REMARK 5.1. Recall that d_1 is defined in (1.10). Since the denominator expression $(1 - 2hd_1)^K = (1 - d_1/K)^K$ in the bound (5.5) approaches e^{-d_1} as K tends to infinity, the denominator is bounded away from zero, uniformly in K . Hence, (5.5) also implies a uniform bound, independent of K .

Proof. Let $\bar{\mathbf{X}}_k$ be the vector obtained by vertically stacking \mathbf{X}_{k1} through \mathbf{X}_{kN} . By the analysis given in [33, Lem. 5.1] for a single mesh interval, it follows from (P1), (P2), and (A2) that

$$\|\bar{\mathbf{X}}_k\|_\infty \leq \left(\frac{1}{1 - 2hd_1} \right) \left(\|\mathbf{X}_{k-1,N}\|_\infty + \sqrt{2} \|\mathbf{p}_k\|_\omega + |\mathbf{q}_k| \right), \tag{5.6}$$

where

$$\|\mathbf{p}_k\|_\omega = \left(\sum_{i=1}^N \omega_i |\mathbf{p}_{ki}|^2 \right).$$

By (A2), $2hd_1 < 1$. Since $\mathbf{X}_{kN} = \mathbf{0}$ for $k = 0$ and $\|\mathbf{X}_{k,N}\|_\infty \leq \|\overline{\mathbf{X}}_k\|_\infty$ for $k > 0$, (5.6) yields

$$\|\overline{\mathbf{X}}_k\|_\infty \leq \sum_{j=1}^k \frac{\sqrt{2}\|\mathbf{p}_j\|_\omega + |\mathbf{q}_j|}{(1 - 2hd_1)^{k-j+1}} \quad (5.7)$$

for $1 \leq k \leq K$. The upper bound (5.5) is obtained by replacing $1/(1 - 2hd_1)^{k-j+1}$ by its maximum $1/(1 - 2hd_1)^K$ and by utilizing the Schwarz inequality as in

$$\sum_{j=1}^k \|\mathbf{p}_j\|_\omega \leq \sqrt{k}\|\mathbf{p}\|_\omega \leq h^{-1/2}\|\mathbf{p}\|_\omega \quad \text{and} \quad \sum_{j=1}^k |\mathbf{q}_j| \leq \sqrt{k}|\mathbf{q}| \leq h^{-1/2}|\mathbf{q}|. \quad (5.8)$$

□

The linearized costate dynamics has an analogous bound.

LEMMA 5.2. *If (P3), (P4), and (A2) hold, then for each $\mathbf{q} \in \mathbb{R}^{Kn}$, $\mathbf{p} \in \mathbb{R}^{KNn}$, and $\mathbf{\Lambda}_{K+1,0} \in \mathbb{R}^n$ with \mathbf{q}_k and $\mathbf{p}_{ki} \in \mathbb{R}^n$, the linear system*

$$\sum_{j=1}^N D_{ij}^\dagger \mathbf{\Lambda}_{kj} = \mathbf{p}_{ki} - h\mathbf{A}_{ki}^\top \mathbf{\Lambda}_{ki}, \quad 1 \leq i < N, \quad (5.9)$$

$$\sum_{j=1}^N D_{Nj}^\dagger \mathbf{\Lambda}_{kj} = \mathbf{p}_{kN} - h\mathbf{A}_{kN}^\top \mathbf{\Lambda}_{kN} - \mathbf{\Lambda}_{k+1,0}/\omega_N, \quad (5.10)$$

$$\mathbf{\Lambda}_{k0} = \mathbf{\Lambda}_{k+1,0} + \mathbf{q}_k + h \sum_{i=1}^N \omega_i \mathbf{A}_{ki}^\top \mathbf{\Lambda}_{ki}, \quad (5.11)$$

$1 \leq k \leq K$, has a unique solution $\mathbf{\Lambda} \in \mathbb{R}^{K(N+1)n}$. This solution has the bound

$$\|\mathbf{\Lambda}\|_\infty \leq \frac{\|\mathbf{\Lambda}_{K+1,0}\|_\infty + h^{-1/2}\sqrt{2}\|\mathbf{p}\|_\omega + \sum_{k=1}^K |\mathbf{q}_k|}{(1 - 2hd_2)^K}. \quad (5.12)$$

Proof. Define $\overline{\mathbf{D}}^\dagger = \mathbf{D}^\dagger \otimes \mathbf{I}_n$, where \otimes is the Kronecker product. Equations (5.9) and (5.10) can be combined into the single equation

$$\overline{\mathbf{D}}^\dagger \overline{\mathbf{\Lambda}}_k = \mathbf{p}_k - h\mathbf{A}_k^\top \overline{\mathbf{\Lambda}}_k - (\mathbf{e}_N \otimes \mathbf{I}_n) \mathbf{\Lambda}_{k+1,0}/\omega_N, \quad (5.13)$$

where $\overline{\mathbf{\Lambda}}_k$ is obtained by vertically stacking $\mathbf{\Lambda}_{k1}$ through $\mathbf{\Lambda}_{kN}$ and \mathbf{e}_N is the vector whose N components are all zero except for the last component which is 1. By (2.12) and (2.13), $\mathbf{D}^\dagger \mathbf{1} = -\mathbf{e}_N/\omega_N$, which implies that

$$\mathbf{D}^{\dagger-1} \mathbf{e}_N = -\omega_N \mathbf{1}. \quad (5.14)$$

Hence, we have

$$\overline{\mathbf{D}}^{\dagger-1} (\mathbf{e}_N \otimes \mathbf{I}_n)/\omega_N = [\mathbf{D}^{\dagger-1} \otimes \mathbf{I}_n] (\mathbf{e}_N \otimes \mathbf{I}_n)/\omega_N = -\mathbf{1} \otimes \mathbf{I}_n.$$

Multiply (5.13) by $\overline{\mathbf{D}}^{\dagger-1}$ and rearrange to obtain

$$(\mathbf{I} + h\overline{\mathbf{D}}^{\dagger-1} \mathbf{A}_k^\top) \overline{\mathbf{\Lambda}}_k = \overline{\mathbf{D}}^{\dagger-1} \mathbf{p}_k + (\mathbf{1} \otimes \mathbf{I}_n) \mathbf{\Lambda}_{k+1,0}. \quad (5.15)$$

By (P3), $\|\bar{\mathbf{D}}^{\dagger^{-1}}\|_{\infty} \leq 2$, and by (A2), $h\|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{A}_k^{\top}\|_{\infty} \leq 2hd_2 < 1$. Consequently, the matrix $\mathbf{I} + h\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{A}_k^{\top}$ is invertible with

$$\left\| \left(\mathbf{I} + h\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{A}_k^{\top} \right)^{-1} \right\|_{\infty} \leq \frac{1}{1 - 2hd_2}.$$

Multiply (5.15) by $(\mathbf{I} + h\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{A}_k^{\top})^{-1}$ and take the norm of each side to obtain

$$\|\bar{\mathbf{A}}_k\|_{\infty} \leq \left(\frac{1}{1 - 2hd} \right) (\|\mathbf{A}_{k+1,0}\|_{\infty} + \|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{p}_k\|_{\infty}) \quad (5.16)$$

$$\leq \left(\frac{1}{1 - 2hd} \right) (\|\mathbf{A}_{k+1,0}\|_{\infty} + \|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{p}_k\|_{\infty} + \|\mathbf{q}_k\|_{\infty}) \quad (5.17)$$

The norm of (5.11) gives

$$\begin{aligned} \|\mathbf{A}_{k0}\|_{\infty} &\leq \|\mathbf{A}_{k+1,0}\|_{\infty} + \|\mathbf{q}_k\|_{\infty} + h \sum_{i=1}^N \omega_i \|\mathbf{A}_{ki}^{\top}\|_{\infty} \|\mathbf{A}_{ki}\|_{\infty} \\ &\leq \|\mathbf{A}_{k+1,0}\|_{\infty} + \|\mathbf{q}_k\|_{\infty} + 2hd_2 \|\bar{\mathbf{A}}_k\|_{\infty} \end{aligned}$$

since the ω_i sum to 2. Using the bound for $\|\bar{\mathbf{A}}_k\|_{\infty}$ from (5.16) and the fact that $2hd_2 < 1$, we have

$$\begin{aligned} \|\mathbf{A}_{k0}\|_{\infty} &\leq \|\mathbf{q}_k\|_{\infty} + \left(\frac{1}{1 - 2hd_2} \right) (\|\mathbf{A}_{k+1,0}\|_{\infty} + 2hd_2 \|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{p}_k\|_{\infty}) \\ &\leq \left(\frac{1}{1 - 2hd_2} \right) (\|\mathbf{A}_{k+1,0}\|_{\infty} + 2hd_2 \|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{p}_k\|_{\infty} + \|\mathbf{q}_k\|_{\infty}) \\ &\leq \left(\frac{1}{1 - 2hd_2} \right) (\|\mathbf{A}_{k+1,0}\|_{\infty} + \|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{p}_k\|_{\infty} + \|\mathbf{q}_k\|_{\infty}). \end{aligned} \quad (5.18)$$

Since $\mathbf{A}_{k,0}$ is contained in \mathbf{A}_k , it follows that $\|\mathbf{A}_{k,0}\|_{\infty} \leq \|\mathbf{A}_k\|_{\infty}$. Combine (5.17) and (5.18) to obtain

$$\|\mathbf{A}_k\|_{\infty} \leq \left(\frac{1}{1 - 2hd_2} \right) (\|\mathbf{A}_{k+1}\|_{\infty} + \|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{p}_k\|_{\infty} + \|\mathbf{q}_k\|_{\infty}),$$

where we define $\mathbf{A}_{K+1,j} = \mathbf{0}$ for $j > 0$ so that $\|\mathbf{A}_{K+1}\|_{\infty} = \|\mathbf{A}_{K+1,0}\|_{\infty}$. This inequality is applied recursively to obtain

$$\|\mathbf{A}_k\|_{\infty} \leq \frac{\|\mathbf{A}_{K+1}\|_{\infty}}{(1 - 2hd_2)^{K+1-k}} + \sum_{j=k}^K \left(\frac{\|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{p}_j\|_{\infty} + \|\mathbf{q}_j\|_{\infty}}{(1 - 2hd_2)^{j-k+1}} \right).$$

To bound the right side, the factors $1/(1 - 2hd_2)^{j-k+1}$ are replaced by their maximum $1/(1 - 2hd_2)^K$ to obtain

$$\|\mathbf{A}_k\|_{\infty} \leq \frac{\|\mathbf{A}_{K+1}\|_{\infty} + \sum_{j=k}^K [\|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{p}_j\|_{\infty} + \|\mathbf{q}_j\|_{\infty}]}{(1 - 2hd_2)^K}.$$

By the analysis given in [33, Lem. 5.1], (P4) implies that $\|\bar{\mathbf{D}}^{\dagger^{-1}}\mathbf{p}_j\|_{\infty} \leq \sqrt{2}\|\mathbf{p}_j\|_{\omega}$. Hence, we have

$$\|\mathbf{A}_k\|_{\infty} \leq \frac{\|\mathbf{A}_{K+1}\|_{\infty} + \sum_{j=k}^K [\sqrt{2}\|\mathbf{p}_j\|_{\omega} + \|\mathbf{q}_j\|_{\infty}]}{(1 - 2hd_2)^K}.$$

The first inequality in (5.8) completes the proof of (5.12). \square

6. Invertibility of $\mathcal{F} - \nabla \mathcal{T}^*$. The invertibility of $\mathcal{F} - \nabla \mathcal{T}^*$ is now established.

PROPOSITION 6.1. *If (A1)–(A2) and (P1)–(P4) hold, then for each $\mathbf{Y} \in \mathcal{Y}$, there is a unique solution $(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda})$ to (5.1).*

Proof. As in our earlier work [11, 12, 13, 15, 27, 30, 31, 33], we formulate a strongly convex quadratic programming problem in \mathbf{X} and \mathbf{U} whose first-order optimality conditions reduce to (5.1). Let us consider the problem

$$\left. \begin{array}{ll} \text{minimize} & \frac{1}{2} \mathcal{Q}(\mathbf{X}, \mathbf{U}) + \mathcal{L}(\mathbf{X}, \mathbf{U}, \mathbf{Y}) \\ \text{subject to} & \sum_{j=0}^N D_{ij} \mathbf{X}_{kj} = h(\mathbf{A}_{ki} \mathbf{X}_{ki} + \mathbf{B}_{ki} \mathbf{U}_{ki}) - \mathbf{y}_{1ki}, \quad \mathbf{U}_{ki} \in \mathcal{U}, \\ & \mathbf{X}_{k0} = \mathbf{X}_{k-1,N} - \mathbf{y}_{2k}, \quad \mathbf{X}_{0N} = \mathbf{0}, \end{array} \right\} \quad (6.1)$$

where $1 \leq i \leq N$ and $1 \leq k \leq K$. The quadratic and linear terms in the objective are

$$\mathcal{Q}(\mathbf{X}, \mathbf{U}) = \mathbf{X}_{KN}^\top \mathbf{T} \mathbf{X}_{KN} + h \sum_{k=1}^K \sum_{i=1}^N \omega_i \begin{bmatrix} \mathbf{X}_{ki} \\ \mathbf{U}_{ki} \end{bmatrix}^\top \begin{bmatrix} \mathbf{Q}_{ki} & \mathbf{S}_{ki} \\ \mathbf{S}_{ki}^\top & \mathbf{R}_{ki} \end{bmatrix} \begin{bmatrix} \mathbf{X}_{ki} \\ \mathbf{U}_{ki} \end{bmatrix}, \quad (6.2)$$

$$\mathcal{L}(\mathbf{X}, \mathbf{U}, \mathbf{Y}) = \mathbf{y}_5^\top \mathbf{X}_{KN} + \sum_{k=1}^K \sum_{i=1}^N \omega_i (\mathbf{y}_{3ki}^\top \mathbf{X}_{ki} - \mathbf{y}_{6ki}^\top \mathbf{U}_{ki}) \quad (6.3)$$

$$- \sum_{k=1}^K \mathbf{X}_{k0}^\top \left(\mathbf{y}_{4k} + \sum_{i=1}^N \omega_i \mathbf{y}_{3ki} \right). \quad (6.4)$$

In (6.1), the minimization is over \mathbf{X} and \mathbf{U} , while \mathbf{Y} is a fixed parameter. By Lemma 5.1, the quadratic programming problem (6.1) is feasible, and by the continuity condition, \mathbf{X}_{k0} can be eliminated from (6.1). Since the Radau quadrature weights ω_i are strictly positive, it follows from (A1) that \mathcal{Q} is strongly convex relative to \mathbf{X}_{ki} and \mathbf{U}_{ki} , where $1 \leq i \leq N$ and $1 \leq k \leq K$. Hence, there exists a unique optimal solution to (6.1) for any choice of \mathbf{Y} . We now show that the first-order optimality conditions for (6.1) reduce to $\nabla \mathcal{T}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}] + \mathbf{Y} \in \mathcal{F}(\mathbf{U})$. The first-order optimality conditions hold since \mathcal{U} has nonempty interior and the state dynamics have full rank by Lemma 5.1. Since the first-order optimality conditions are both necessary and sufficient for optimality in this convex setting, there exists a solution to (5.1). Uniqueness of \mathbf{X} and \mathbf{U} is due to (A1) and the strong convexity of (6.1). Uniqueness of $\mathbf{\Lambda}$ is by Lemma 5.2.

The derivation of the first-order optimality conditions for (6.1) is essentially the same process that we used in Section 2 to write the first-order optimality conditions for the discrete problem (1.4) as $\mathcal{T}(\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}) \in \mathcal{F}(\mathbf{U})$. The first two components of $\nabla \mathcal{T}^*[\mathbf{X}, \mathbf{U}, \mathbf{\Lambda}] + \mathbf{Y} \in \mathcal{F}(\mathbf{U})$ are simply the constraints of (6.1). The Lagrangian L for (6.1) is

$$\begin{aligned} L(\boldsymbol{\lambda}, \mathbf{X}, \mathbf{U}) &= \frac{1}{2} \mathcal{Q}(\mathbf{X}, \mathbf{U}) + \mathcal{L}(\mathbf{X}, \mathbf{U}, \mathbf{Y}) + \sum_{k=1}^K \langle \boldsymbol{\lambda}_{k0}, (\mathbf{X}_{k-1,N} - \mathbf{y}_{2k} - \mathbf{X}_{k0}) \rangle \\ &\quad + \sum_{k=1}^K \sum_{i=1}^N \left\langle \boldsymbol{\lambda}_{ki}, h(\mathbf{A}_{ki} \mathbf{X}_{ki} + \mathbf{B}_{ki} \mathbf{U}_{ki}) - \mathbf{y}_{1ki} - \sum_{j=0}^N D_{ij} \mathbf{X}_{kj} \right\rangle \end{aligned}$$

The negative derivative of the Lagrangian with respect to \mathbf{U}_{ki} is

$$-h [\mathbf{B}_{ki}^\top \boldsymbol{\lambda}_{ki} + \omega_i (\mathbf{S}_{ki}^\top \mathbf{X}_{ki} + \mathbf{R}_{ki} \mathbf{U}_{ki})] + \omega_i \mathbf{y}_{6ki}.$$

After the substituting $\lambda_{ki} = \omega_i \Lambda_{ki}$, the requirement that this vector lies in $N_{\mathcal{U}}(\mathbf{U}_{ki})$ leads the 6th component of (5.1). Equating to zero the derivative of the Lagrangian with respect to \mathbf{X}_{kj} , $1 \leq j < N$, yields the relation

$$\sum_{i=1}^N D_{ij} \lambda_{ki} = h [\mathbf{A}_{kj}^T \lambda_{kj} + \omega_j (\mathbf{Q}_{kj} \mathbf{X}_{kj} + \mathbf{S}_{kj} \mathbf{U}_{kj})] + \omega_j \mathbf{y}_{3kj}.$$

Equating to zero the derivative of the Lagrangian with respect to \mathbf{X}_{kN} yields the relation

$$\sum_{i=1}^N D_{ij} \lambda_{ki} = h [\mathbf{A}_{kj}^T \lambda_{kj} + \omega_j (\mathbf{Q}_{kj} \mathbf{X}_{kj} + \mathbf{S}_{kj} \mathbf{U}_{kj})] + \omega_j \mathbf{y}_{3kj} + \lambda_{k+1,0},$$

where $\lambda_{K+1,0} = \mathbf{T} \mathbf{X}_{KN} + \mathbf{y}_5$. After substituting $D_{ij} = -D_{ji}^\dagger \omega_j / \omega_i$, $\lambda_{ki} = \omega_i \Lambda_{ki}$, and $\lambda_{k0} = \Lambda_{k0}$, we obtain the 3rd and 5th components of (5.1).

Finally, we equate to zero the derivative of the Lagrangian with respect to \mathbf{X}_{k0} :

$$\sum_{i=1}^N D_{i0} \lambda_{ki} = - \left(\lambda_{k0} + \mathbf{y}_{4k} + \sum_{i=1}^N \omega_i \mathbf{y}_{3ki} \right).$$

Utilizing the identity (2.10), it follows that

$$\sum_{i=1}^N \sum_{j=1}^N \omega_i D_{ij}^\dagger \Lambda_{kj} = - \left(\Lambda_{k0} + \mathbf{y}_{4k} + \sum_{i=1}^N \omega_i \mathbf{y}_{3ki} \right). \quad (6.5)$$

Multiply the equations in the 3rd component of (5.1) by ω_i and sum over i to obtain

$$\sum_{i=1}^N \sum_{j=1}^N \omega_i D_{ij}^\dagger \Lambda_{kj} = -\Lambda_{k+1,0} - \sum_{i=1}^N \omega_i [\mathbf{y}_{3ki} + h (\mathbf{A}_{ki}^T \Lambda_{ki} + \mathbf{Q}_{ki} \mathbf{X}_{ki} + \mathbf{S}_{ki} \mathbf{U}_{ki})].$$

By (6.5), it follows that

$$\Lambda_{k0} - \Lambda_{k+1,0} - h \sum_{i=1}^N \omega_i (\mathbf{A}_{ki}^T \Lambda_{ki} + \mathbf{Q}_{ki} \mathbf{X}_{ki} + \mathbf{S}_{ki} \mathbf{U}_{ki}) + \mathbf{y}_{4k} = \mathbf{0},$$

which is the 4th component of (5.1). This completes the proof. \square

7. Lipschitz continuity of $(\mathcal{F} - \nabla \mathcal{T}^*)^{-1}$ and proof of the main theorem.

We begin by making the change of variables $\mathbf{X} = \mathbf{Z} + \chi(\mathbf{Y})$ where $\chi(\mathbf{Y})$ denotes the solution of the state dynamics (5.3) corresponding to $\mathbf{p}_{ki} = -\mathbf{y}_{1ki}$ and $\mathbf{q}_k = -\mathbf{y}_{2k}$. With this change of variables, \mathbf{y}_1 and \mathbf{y}_2 disappear from the dynamics of the quadratic program (6.1) and the quadratic program in \mathbf{Z} and \mathbf{U} reduces to

$$\left. \begin{aligned} & \text{minimize} \quad \frac{1}{2} \mathcal{Q}(\mathbf{Z}, \mathbf{U}) + \bar{\mathcal{L}}(\mathbf{Z}, \mathbf{U}, \mathbf{Y}) \\ & \text{subject to} \quad \sum_{j=0}^N D_{ij} \mathbf{Z}_{kj} = h (\mathbf{A}_{ki} \mathbf{Z}_{ki} + \mathbf{B}_{ki} \mathbf{U}_{ki}), \quad \mathbf{U}_{ki} \in \mathcal{U}, \\ & \quad \mathbf{Z}_{k0} = \mathbf{Z}_{k-1,N}, \quad \mathbf{Z}_{0N} = \mathbf{0}, \end{aligned} \right\} \quad (7.1)$$

where $1 \leq i \leq N$, $1 \leq k \leq K$, and

$$\begin{aligned} \bar{\mathcal{L}}(\mathbf{Z}, \mathbf{U}, \mathbf{Y}) &= \mathcal{L}(\mathbf{Z}, \mathbf{U}, \mathbf{Y}) + \chi_{KN}(\mathbf{Y})^T \mathbf{T} \mathbf{Z}_{KN} \\ &\quad + h \sum_{k=1}^K \sum_{i=1}^N \omega_i [\chi_{ki}^T(\mathbf{Y}) \mathbf{Q}_{ki} \mathbf{Z}_{ki} + \chi_{ki}^T(\mathbf{Y}) \mathbf{S}_{ki} \mathbf{U}_{ki}]. \end{aligned} \quad (7.2)$$

Note that \mathbf{Z}_{k0} can be eliminated from the optimization problem with the substitution $\mathbf{Z}_{k0} = \mathbf{Z}_{k-1,N}$. In the analysis that follows, it is assumed that the \mathbf{Z}_{k0} component of \mathbf{Z} has been deleted. Note that \mathcal{Q} does not depend on \mathbf{Z}_{k0} , the \mathbf{Z}_{k0} in L can be replaced by $\mathbf{Z}_{k-1,N}$, and the ω -norm of \mathbf{Z} does not depend on \mathbf{Z}_{k0} . If $(\mathbf{Z}^j, \mathbf{U}^j)$ denotes the solution of (7.1) corresponding to $\mathbf{Y}^j \in \mathcal{Y}$, $j = 1$ and 2 , then by [12, Lem. 4], the solution change $\Delta\mathbf{Z} = \mathbf{Z}^1 - \mathbf{Z}^2$ and $\Delta\mathbf{U} = \mathbf{U}^1 - \mathbf{U}^2$ satisfies the relation

$$\mathcal{Q}(\Delta\mathbf{Z}, \Delta\mathbf{U}) \leq |\bar{\mathcal{L}}(\Delta\mathbf{Z}, \Delta\mathbf{U}, \Delta\mathbf{Y})| \quad (7.3)$$

where $\Delta\mathbf{Y} = \mathbf{Y}^1 - \mathbf{Y}^2$. By (A1) we have the lower bound

$$\mathcal{Q}(\Delta\mathbf{Z}, \Delta\mathbf{U}) \geq \alpha (|\Delta\mathbf{Z}_{KN}|^2 + h\|\Delta\mathbf{Z}\|_\omega^2 + h\|\Delta\mathbf{U}\|_\omega^2).$$

Now consider the terms in \mathcal{L} . By the Schwarz inequality,

$$\left| \sum_{k=1}^K \sum_{i=1}^N \omega_i \Delta\mathbf{y}_{3ki}^\top \Delta\mathbf{Z}_{ki} \right| \leq \|\Delta\mathbf{y}_3\|_\omega \|\Delta\mathbf{Z}\|_\omega \leq \|\Delta\mathbf{Y}\|_{\mathcal{Y}} \|\Delta\mathbf{Z}\|_\omega.$$

Let c denote a generic constant which is independent of K and N . For the control term in \mathcal{L} , the triangle and Schwarz inequalities give

$$\begin{aligned} \left| \sum_{k=1}^K \sum_{i=1}^N \omega_i \Delta\mathbf{y}_{6ki}^\top \Delta\mathbf{U}_{ki} \right| &\leq c \|\Delta\mathbf{y}_6\|_\infty \sum_{k=1}^K \sum_{i=1}^N \omega_i |\Delta\mathbf{U}_{ki}| \leq c \|\Delta\mathbf{y}_6\|_\infty \sum_{k=1}^K \|\Delta\mathbf{U}_k\|_\omega \\ &\leq ch^{-1/2} \|\Delta\mathbf{y}_6\|_\infty \|\Delta\mathbf{U}\|_\omega \leq c \|\Delta\mathbf{Y}\|_{\mathcal{Y}} \|\Delta\mathbf{U}\|_\omega. \end{aligned}$$

The last inequality is due to the $h^{-1/2}$ factor in the \mathcal{Y} -norm.

For the \mathbf{Z}_{k0} -term in \mathcal{L} , we have

$$\left| \Delta\mathbf{Z}_{k0}^\top \left(\Delta\mathbf{y}_{4k} + \sum_{i=1}^N \omega_i \Delta\mathbf{y}_{3ki} \right) \right| \leq c \|\Delta\mathbf{Z}\|_\infty \left(|\Delta\mathbf{y}_{4k}| + \sum_{i=1}^N \omega_i |\Delta\mathbf{y}_{3ki}| \right). \quad (7.4)$$

By Lemma 5.1 with $\mathbf{p}_{ki} = h\mathbf{B}_{ki}\mathbf{U}_{ki}$ and $\mathbf{q}_k = 0$, we have $\|\Delta\mathbf{Z}\|_\infty \leq ch^{1/2}\|\Delta\mathbf{U}\|_\omega$. Inserting this in (7.4) and applying the Schwarz inequality gives

$$\left| \sum_{k=1}^K \Delta\mathbf{Z}_{k0}^\top \left(\Delta\mathbf{y}_{4k} + \sum_{i=1}^N \omega_i \Delta\mathbf{y}_{3ki} \right) \right| \leq \|\Delta\mathbf{U}\|_\omega (|\Delta\mathbf{y}_4| + \|\Delta\mathbf{y}_3\|_\omega) \leq c \|\Delta\mathbf{U}\|_\omega \|\Delta\mathbf{Y}\|_{\mathcal{Y}}.$$

For the latter χ terms in (7.2), we have a bound such as

$$h \left| \sum_{k=1}^K \sum_{i=1}^N \omega_i \chi_{ki}^\top (\Delta\mathbf{Y}) \mathbf{Q}_{ki} \Delta\mathbf{Z}_{ki} \right| \leq ch \|\chi(\Delta\mathbf{Y})\|_\omega \|\Delta\mathbf{Z}\|_\omega. \quad (7.5)$$

By Lemma 5.1, we have

$$\|\chi(\Delta\mathbf{Y})\|_\infty \leq ch^{-1/2} (\|\Delta\mathbf{y}_1\|_\omega + |\Delta\mathbf{y}_2|) \leq ch^{-1/2} \|\Delta\mathbf{Y}\|_{\mathcal{Y}}. \quad (7.6)$$

Since $\|\chi(\Delta\mathbf{Y})\|_\omega \leq h^{-1/2} \|\chi(\Delta\mathbf{Y})\|_\infty$, it follows from (7.5) and (7.6) that

$$h \left| \sum_{k=1}^K \sum_{i=1}^N \omega_i \chi_{ki}^\top (\Delta\mathbf{Y}) \mathbf{Q}_{ki} \Delta\mathbf{Z}_{ki} \right| \leq c \|\Delta\mathbf{Y}\|_\omega \|\Delta\mathbf{Z}\|_\omega.$$

For the terminal term in (7.2), we have the bound

$$|\chi_{KN}(\Delta \mathbf{Y})^\top \mathbf{T} \Delta \mathbf{Z}_{KN}| \leq c |\chi_{KN}(\Delta \mathbf{Y})| |\Delta \mathbf{Z}_{KN}| \leq ch^{-1/2} (\|\Delta \mathbf{y}_1\|_\omega + |\mathbf{y}_2|) |\Delta \mathbf{Z}_{KN}|.$$

The \mathbf{y}_5 term in \mathcal{L} is similar. By the Schwarz inequality,

$$|\Delta \mathbf{y}_5^\top \Delta \mathbf{Z}_{KN}| \leq |\Delta \mathbf{y}_5| |\Delta \mathbf{Z}_{KN}| \leq h^{-1/2} \|\Delta \mathbf{Y}\|_{\mathcal{Y}} |\Delta \mathbf{Z}_{KN}|,$$

where the $h^{-1/2}$ on the right cancels the $h^{1/2}$ factor inside the \mathcal{Y} -norm.

Combine these bounds for the linear term to obtain

$$\begin{aligned} |\bar{\mathcal{L}}(\Delta \mathbf{Z}, \Delta \mathbf{U}, \Delta \mathbf{Y})| &\leq c \|\Delta \mathbf{Y}\|_{\mathcal{Y}} \left(h^{-1/2} |\Delta \mathbf{Z}_{KN}| + \|\Delta \mathbf{Z}\|_\omega + \|\Delta \mathbf{U}\|_\omega \right) \\ &= ch^{-1/2} \|\Delta \mathbf{Y}\|_{\mathcal{Y}} \left(|\Delta \mathbf{Z}_{KN}| + \sqrt{h} \|\Delta \mathbf{Z}\|_\omega + \sqrt{h} \|\Delta \mathbf{U}\|_\omega \right) \\ &\leq ch^{-1/2} \|\Delta \mathbf{Y}\|_{\mathcal{Y}} \left(|\Delta \mathbf{Z}_{KN}|^2 + h \|\Delta \mathbf{Z}\|_\omega^2 + h \|\Delta \mathbf{U}\|_\omega^2 \right)^{1/2}. \end{aligned}$$

Combining the lower bound for \mathcal{Q} with the upper bound for $\bar{\mathcal{L}}$ gives

$$\left(|\Delta \mathbf{Z}_{KN}|^2 + h \|\Delta \mathbf{Z}\|_\omega^2 + h \|\Delta \mathbf{U}\|_\omega^2 \right)^{1/2} \leq ch^{-1/2} \|\Delta \mathbf{Y}\|_{\mathcal{Y}}. \quad (7.7)$$

Next, the ω -type norm on the left side of (7.7) will be converted to an ∞ -norm. To do this, we first apply Lemma 5.1 with $\mathbf{p}_{ki} = \Delta \mathbf{y}_{1ki} + h \mathbf{B}_{ki} \Delta \mathbf{U}_{ki}$ and $\mathbf{q}_k = \mathbf{0}$. The bound (7.7) implies that $\|\Delta \mathbf{U}\|_\omega \leq ch^{-1} \|\Delta \mathbf{Y}\|_{\mathcal{Y}}$; consequently,

$$\|\mathbf{p}\|_\omega \leq c (\|\Delta \mathbf{y}_1\|_\omega + h \|\Delta \mathbf{U}\|_\omega) \leq c \|\Delta \mathbf{Y}\|_{\mathcal{Y}}. \quad (7.8)$$

It follows from (5.5) that $\|\Delta \mathbf{Z}\|_\infty \leq ch^{-1/2} \|\Delta \mathbf{Y}\|_{\mathcal{Y}}$. Hence, by (7.6) we deduce that

$$\|\Delta \mathbf{X}\|_\infty = \|\Delta \mathbf{Z} + \chi(\Delta \mathbf{Y})\|_\infty \leq ch^{-1/2} \|\Delta \mathbf{Y}\|_{\mathcal{Y}}. \quad (7.9)$$

Since $\Delta \mathbf{X}_{k0} = \Delta \mathbf{X}_{k-1,0} + \Delta \mathbf{y}_{2k}$, it also follows that

$$\|\Delta \mathbf{X}_{k0}\|_\infty \leq \|\Delta \mathbf{X}\|_\infty + |\Delta \mathbf{y}_2| \leq ch^{-1/2} \|\Delta \mathbf{Y}\|_{\mathcal{Y}}.$$

Let us now apply Lemma 5.2 with

$$\begin{aligned} \mathbf{p}_{ki} &= \Delta \mathbf{y}_{3ki} + h(\mathbf{Q}_{ki} \Delta \mathbf{X}_{ki} + \mathbf{S}_{ki} \Delta \mathbf{U}_{ki}), \quad \Delta \mathbf{A}_{K+1,0} = \mathbf{T} \Delta \mathbf{X}_{KN}, \quad \text{and} \\ \mathbf{q}_k &= \sum_{i=1}^N \omega_i (h [\mathbf{Q}_{ki} \Delta \mathbf{X}_{ki} + \mathbf{S}_{ki} \Delta \mathbf{U}_{ki}] + \Delta \mathbf{y}_{4ki}). \end{aligned}$$

By (5.12), we have

$$\|\Delta \mathbf{A}\|_\infty \leq c \left(\|\Delta \mathbf{X}_{KN}\|_\infty + h^{-1/2} \|\mathbf{p}\|_\omega + \sum_{k=1}^K |\mathbf{q}_k| \right). \quad (7.10)$$

By (7.9), $\|\Delta \mathbf{X}_{KN}\|_\infty \leq ch^{-1/2} \|\Delta \mathbf{Y}\|_{\mathcal{Y}}$. Exactly as in (7.8), $\|\mathbf{p}\|_\omega \leq c \|\Delta \mathbf{Y}\|_{\mathcal{Y}}$. The Schwarz inequality yields

$$\begin{aligned} \sum_{k=1}^K |\mathbf{q}_k| &\leq c \sum_{k=1}^K (\|\Delta \mathbf{y}_{2k}\|_\omega + h \|\Delta \mathbf{X}_k\|_\omega + h \|\Delta \mathbf{U}_k\|_\omega) \\ &\leq ch^{-1/2} \|\Delta \mathbf{y}_2\|_\omega + h^{1/2} [\|\Delta \mathbf{X}\|_\omega + \|\Delta \mathbf{U}\|_\omega] \leq ch^{-1/2} \|\Delta \mathbf{Y}\|_{\mathcal{Y}}. \end{aligned}$$

The last inequality utilizes both (7.7) to bound the \mathbf{U} term and (7.9) to bound the \mathbf{X} term. Inserting these bounds in (7.10) yields

$$\|\Delta\mathbf{A}\|_\infty \leq ch^{-1/2}\|\Delta\mathbf{Y}\|_{\mathcal{Y}}. \quad (7.11)$$

By (A2) \mathbf{R}_{ki} is positive definite with smallest eigenvalue greater than or equal to $\alpha > 0$. It follows from the 6th component of the inclusion (5.1) that the control associated with \mathbf{Y} solves the quadratic program

$$\min_{\mathbf{U}_{ki}} h \left(\frac{1}{2} \mathbf{U}_{ki}^\top \mathbf{R}_{ki} \mathbf{U}_{ki} + \mathbf{X}_{ki}^\top \mathbf{S}_{ki} + \mathbf{A}_{ki}^\top \mathbf{B}_{ki} \right) \mathbf{U}_{ki} + \mathbf{y}_{6ki}^\top \mathbf{U}_{ki}.$$

Again by [12, Lem. 4], the solution change associated with the data change $\Delta\mathbf{Y}$ has the bound

$$h\alpha|\Delta\mathbf{U}_{ki}|^2 \leq \left| h \left(\Delta\mathbf{X}_{ki}^\top \mathbf{S}_{ki} + \Delta\mathbf{A}_{ki}^\top \mathbf{B}_{ki} \right) \Delta\mathbf{U}_{ki} + \Delta\mathbf{y}_{6ki} \Delta\mathbf{U}_{ki} \right|.$$

Hence, we deduce that

$$\|\Delta\mathbf{U}_{ki}\|_\infty \leq |\Delta\mathbf{U}_{ki}| \leq c \left(\|\Delta\mathbf{X}_{ki}\|_\infty + \|\Delta\mathbf{A}_{ki}\|_\infty + h^{-1}\|\Delta\mathbf{y}_{6ki}\|_\infty \right).$$

Utilizing the bounds (7.9) and (7.11), and the $h^{-1/2}$ factor associated with the 6-th component of the \mathcal{Y} -norm, yields

$$\|\Delta\mathbf{U}_{ki}\|_\infty \leq ch^{-1/2}\|\Delta\mathbf{Y}\|_{\mathcal{Y}}. \quad (7.12)$$

The bounds (7.9), (7.11), and (7.12) combine to establish the following Lipschitz continuity property:

LEMMA 7.1. *If (A1), (A2), and (P1)–(P4) hold, then there exists a unique solution of (5.1) for each $\mathbf{Y} \in \mathcal{Y}$, and there exists a constant c , independent of K and N , such that the solution change $\Delta\mathbf{X}$, $\Delta\mathbf{U}$, and $\Delta\mathbf{A}$ relative to the change $\Delta\mathbf{Y}$ satisfies*

$$\|(\Delta\mathbf{X}, \Delta\mathbf{U}, \Delta\mathbf{A})\|_\infty \leq ch^{-1/2}\|\Delta\mathbf{Y}\|_{\mathcal{Y}}.$$

Theorem 1.1 is proved using Proposition 2.2. The Lipschitz constant γ of Proposition 2.2 is given by $\gamma = ch^{-1/2}$ where c is the constant of Lemma 7.1. The terms involving \mathbf{D} , \mathbf{D}^\dagger , \mathbf{A}_{k0} , $\mathbf{A}_{k+1,0}$, \mathbf{X}_{k0} , and $\mathbf{X}_{k-1,N}$ are constants in the derivative $\nabla\mathcal{T}$ and hence these terms cancel when we compute the difference $\nabla\mathcal{T}(\boldsymbol{\theta}) - \nabla\mathcal{T}(\boldsymbol{\theta}^*)$, where $\boldsymbol{\theta} = (\mathbf{X}, \mathbf{U}, \mathbf{A})$ and $\boldsymbol{\theta}^* = (\mathbf{X}^*, \mathbf{U}^*, \mathbf{A}^*)$. We are left with terms involving the difference of derivatives of \mathbf{f} or C up to second order at points in a neighborhood of $\boldsymbol{\theta}^*$. By the Smoothness assumption, these derivatives are Lipschitz continuous in a neighborhood of $(\mathbf{X}^*, \mathbf{U}^*)$. Hence, there exists constants τ and $r > 0$ such that

$$\begin{aligned} \|\nabla[\mathbf{f}(\mathbf{X}_{ki}, \mathbf{U}_{ki}) - \mathbf{f}(\mathbf{X}_{ki}^*, \mathbf{U}_{ki}^*)]\|_\infty &\leq \tau\|\boldsymbol{\theta} - \boldsymbol{\theta}^*\|_\infty, \\ \|\nabla[\nabla_x \mathbf{H}(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \mathbf{A}_{ki}) - \nabla_x \mathbf{H}(\mathbf{X}_{ki}^*, \mathbf{U}_{ki}^*, \mathbf{A}_{ki}^*)]\|_\infty &\leq \tau\|\boldsymbol{\theta} - \boldsymbol{\theta}^*\|_\infty, \\ \|\nabla[\nabla_u \mathbf{H}(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \mathbf{A}_{ki}) - \nabla_u \mathbf{H}(\mathbf{X}_{ki}^*, \mathbf{U}_{ki}^*, \mathbf{A}_{ki}^*)]\|_\infty &\leq \tau\|\boldsymbol{\theta} - \boldsymbol{\theta}^*\|_\infty, \\ \|\nabla[\nabla C(\mathbf{X}_{KN}) - \nabla C(\mathbf{X}_{KN}^*)]\|_\infty &\leq \tau\|\boldsymbol{\theta} - \boldsymbol{\theta}^*\|_\infty, \end{aligned}$$

whenever $\|\boldsymbol{\theta} - \boldsymbol{\theta}^*\|_\infty \leq r$. In applying Proposition 2.2, we need a bound for the \mathcal{Y} -norm of $\nabla\mathcal{T}(\boldsymbol{\theta}) - \nabla\mathcal{T}(\boldsymbol{\theta}^*)$. Taking into account the location of h 's in \mathcal{T} and the

location of h 's in the \mathcal{Y} -norm, it follows from the Lipschitz bounds relative to τ that there exists a constant κ such that

$$\|\nabla\mathcal{T}(\boldsymbol{\theta}) - \nabla\mathcal{T}(\boldsymbol{\theta}^*)\|_{\mathcal{Y}} \leq \kappa h^{1/2} \|\boldsymbol{\theta} - \boldsymbol{\theta}^*\|_{\infty},$$

whenever $\|\boldsymbol{\theta} - \boldsymbol{\theta}^*\|_{\infty} \leq r$. Choose $r > 0$ smaller if necessary to ensure that $c\kappa r < 1$, where c is the constant in Lemma 7.1. In Proposition 2.2, $\epsilon = \kappa h^{1/2}r$ and $\gamma = ch^{-1/2}$. Hence, $\gamma\epsilon = c\kappa r < 1$. Referring to Lemma 4.1, choose N large enough or h small enough so that

$$\text{dist}[\mathcal{T}(\boldsymbol{\theta}^*), \mathcal{F}(\mathbf{U}^*)] \leq \frac{(1 - \gamma\epsilon)r}{\gamma}.$$

Combine Lemma 4.1 with (2.17) and the formula $\gamma = ch^{-1/2}$ to obtain the bound (1.14) of Theorem 1.1.

The solution to $\mathcal{T}(\mathbf{X}, \mathbf{U}, \boldsymbol{\Lambda}) \in \mathcal{F}(\mathbf{U})$ corresponds to the first-order optimality condition for either (2.1) or (1.4). We use the second-order sufficient optimality conditions to show that this stationary point is a local minimum when it is sufficiently close to $(\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*)$. After replacing the KKT multipliers by the transformed quantities given by $\boldsymbol{\Lambda}_{ki} = \boldsymbol{\lambda}_{ki}/\omega_i$, the Hessian of the Lagrangian is a block diagonal matrix with the following matrices forming the diagonal blocks:

$$\begin{aligned} \omega_i \nabla_{(x,u)}^2 H(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \boldsymbol{\Lambda}_{ki}), & \quad 1 \leq i < N, \\ \omega_i \nabla_{(x,u)}^2 H(\mathbf{X}_{ki}, \mathbf{U}_{ki}, \boldsymbol{\Lambda}_{ki}) + \nabla_{(x,u)}^2 C(\mathbf{X}_{ki}), & \quad i = N, \end{aligned}$$

where H is the Hamiltonian and $1 \leq k \leq K$. In computing the Hessian, we assume that the \mathbf{X} and \mathbf{U} variables are arranged in the following order: $\mathbf{X}_{k1}, \mathbf{U}_{k1}, \mathbf{X}_{k2}, \mathbf{U}_{k2}, \dots, \mathbf{X}_{kN}, \mathbf{U}_{kN}$, $1 \leq k \leq K$. By (A1) the Hessian is positive definite when evaluated at $(\mathbf{X}^*, \mathbf{U}^*, \boldsymbol{\Lambda}^*)$. By the Lipschitz continuity of the second derivative of C and \mathbf{f} , and by the convergence result (1.14), we conclude that the Hessian of the Lagrangian, evaluated at the solution of $\mathcal{T}(\mathbf{X}, \mathbf{U}, \boldsymbol{\Lambda}) \in \mathcal{F}(\mathbf{U})$ satisfying (1.14), is positive definite for N sufficiently large or for h sufficiently small with $N \geq 2$. Hence, by the second-order sufficient optimality condition [37, Thm. 12.6], (\mathbf{X}, \mathbf{U}) is a strict local minimizer of (2.1). This completes the proof of Theorem 1.1.

8. Numerical illustrations. In this section we illustrate the performance of the proposed method with numerical examples.

8.1. Example 1. First we consider the unconstrained control problem given by

$$\min \left\{ -x(2) : \dot{x}(t) = \frac{5}{2}(-x(t) + x(t)u(t) - u^2(t)), \quad x(0) = 1 \right\}. \quad (8.1)$$

The optimal solution and associated costate are

$$\begin{aligned} x^*(t) &= 4/a(t), \quad a(t) = 1 + 3 \exp(2.5t), \\ u^*(t) &= x^*(t)/2, \\ \lambda^*(t) &= -a^2(t) \exp(-2.5t) / [\exp(-5) + 9 \exp(5) + 6]. \end{aligned}$$

The time domain $[0, 2]$ is divided into equally spaced mesh intervals, and on each mesh interval, we collocate at the Radau points using polynomials of the same degree. We consider polynomials of degree $N = 2, 3$, and 4. Convergence to the true solution




FIG. 8.1. The logarithm of the sup-norm error in Example 1 as a function of mesh size for polynomials of degree $N = 2, 3$, and 4 . The errors in the controls, marked by plus signs, are beneath the state error plots. The errors in the costate, marked by diamonds, are above the state error plots.

is achieved by increasing the number of mesh intervals. Figure 8.1 plots the base 10 logarithm of the error at the collocation points in the sup-norm versus the base 10 logarithm of mesh size for Example 1. Observe that the error decays roughly linearly in this log-log plot. We use the slope of the least squares linear fit to the data to estimate the decay rate. For degree $N = 2$, the error in sup-norm is $O(10^{-\beta N})$ with $\beta = 4.0$ for both the state and control variable, and $\beta = 3$ for the costate. For $N = 3$, $\beta = 5.0$ for state and control and 3.8 for costate, while for $N = 4$, $\beta = 5.7$ for state and control and $\beta = 4.8$ for costate.

The results shown in Figure 8.1 are obtained using the software GPOPS-II [39] and the optimizer IPOPT [6] to solve the discrete nonlinear program. The interior point code IPOPT could achieve an error around the square root of the machine epsilon (approximately 10^{-8}). As a result, for $N = 3$ and $N = 4$, we were not able to take h small enough to achieve the asymptotic range before exceeding the accuracy of the optimizer. Based on the results shown in Figure 8.1, it appears that the pointwise error is $O(h^{N+2})$ in the state and control, and $O(h^{N+1})$ in the costate for fixed N .

The bound given in Theorem 1.1 for fixed N is $O(h^{N-1})$, which is much slower than the observed convergence rate $O(h^{N+1})$. This discrepancy could be due to either the simple nature of the example, or to looseness in the analysis. In our analysis, the exponent of h is reduced by the following effects:

- (a) Although the state is approximated by a polynomial of degree N , the costate is approximated by a polynomial of degree $N - 1$. This difference between the state and the costate becomes apparent in Proposition 2.1. We are not free to choose the costate polynomial, its degree comes from the KKT conditions. In the analysis of the residual given in Lemma 4.1, the reduced degree for the costate polynomial implies that the exponent of h in the bound (4.1) is the minimum of N and η rather than the minimum of $N + 1$ and η .
- (b) In our analysis of the Lipschitz constant γ and the product $\epsilon\gamma$ in the denominator of the error bound (2.17), we obtain $\gamma \leq ch^{-1/2}$ and $\gamma\epsilon$ strictly bounded from one. Since γ can grow like $h^{-1/2}$ as h tends to zero, we lose a half power of h through the Lipschitz constant in the error bound (2.17).

If example 1 indeed represents the typical behavior of the error, then the analysis must be sharpened to address the losses described in (a) and (b).

It is interesting to compare the analysis in this paper to the analysis of Runge-Kutta schemes given in [7, 28]. For a fixed N , the Radau scheme in this paper is equivalent to a Runge-Kutta scheme where the \mathbf{A} matrix and \mathbf{b} vector of [28] describing the Runge-Kutta scheme are $\mathbf{D}_{1:N}^{-1}/2$ and the last row of $\mathbf{D}_{1:N}^{-1}/2$ respectively. For $N = 2$ and $N = 3$, the corresponding Runge-Kutta schemes have order 3 and 4 respectively, which means that the error in the Runge-Kutta schemes are $O(h^3)$ and $O(h^4)$ respectively. This exactly matches the costate error for the hp -scheme in this example. A fundamental difference between the results of [28] and the results in this paper is that [28] estimates the error at the mesh points, and there is no information about the error at the intermediate points, while in Theorem 1.1, we estimate the error at both collocation and mesh points. In the hp -framework, it is important to have estimates at the collocation points since K could be fixed, and the convergence is achieved by letting N grow.

Based on the theory developed in the paper [7] of Bonnans and Laurent-Varin, many conditions must be satisfied to achieve high order convergence of a Runge-Kutta scheme for optimal control (4116 conditions for order 7). Potentially, the hp -scheme based on Radau collocation could be used to generate high order Runge-Kutta schemes.

Next, we examine in Figure 8.2 the exponential convergence rate predicted by Theorem 1.1 when there is a single interval and the degree of the polynomials is increased. Since the plot of the base-10 logarithm of the error versus the degree of the polynomial is nearly linear, the error behaves like $c10^{-\alpha N}$ where $\alpha \approx 0.6$ for either the state or the control and $\alpha \approx 0.8$ for the costate. Since the solution to this problem is infinitely smooth, we can take $\eta = N$ in Theorem 1.1. The error bound in Theorem 1.1 is somewhat complex since it involves the derivatives of the solution. Nonetheless, when we take the base-10 logarithm of the error bound, the asymptotically dominant term appears to be $-N \log_{10} N$ for Example 1. Consequently, the slope of the curve in the error bound varies like $-\log_{10} N$. For N between 4 and 16, $\log_{10} N$ varies from about 0.6 to 1.2. Hence, our observed slopes 0.6 and 0.8 fall in the anticipated range.

8.2. Example 2. Next we consider the problem [32] given by

$$\begin{aligned} & \text{minimize} && \frac{1}{2} \int_0^1 [x^2(t) + u^2(t)] dt \\ & \text{subject to} && \dot{x}(t) = u(t), \quad u(t) \leq 1, \quad x(t) \leq \frac{2\sqrt{e}}{1-e} \quad \text{for all } t \in [0, 1], \\ & && x(0) = \frac{5e+3}{4(1-e)}. \end{aligned}$$

The exact solution to this problem is

$$\begin{aligned} 0 \leq t \leq \frac{1}{4} : & \quad x^*(t) = t - \frac{1}{4} + \frac{1+e}{1-e}, & u^*(t) &= 1, \\ \frac{1}{4} \leq t \leq \frac{3}{4} : & \quad x^*(t) = \frac{e^{t-\frac{1}{4}}}{1-e} (1 + e^{\frac{3}{2}-2t}), & u^*(t) &= \frac{e^{t-\frac{1}{4}}}{1-e} (1 - e^{\frac{3}{2}-2t}), \\ \frac{3}{4} \leq t \leq 1 : & \quad x^*(t) = \frac{2\sqrt{e}}{1-e}, & u^*(t) &= 0. \end{aligned}$$

The solution of this problem is smooth on the three intervals $[0, 0.25]$, $[0.25, 0.75]$, and $[0.75, 1.0]$, however, at the contact points where one of the constraints changes from




FIG. 8.2. The base 10 logarithm of the error in the sup-norm as a function of the number of collocation points for Example 1.




FIG. 8.3. The error in the solution to Example 2 as a function of the degree of the polynomials used in the hp-approximation. In (a) the polynomials are defined on the interval $[0, 1]$. In (b) there are three mesh intervals $[0, 0.25]$, $[0.25, 0.75]$, and $[0.75, 1.0]$, and different polynomials of the same degree are used on each mesh interval.

active to inactive, there is a discontinuity in the derivative of the optimal control and a discontinuity in the second derivative of the optimal state. The goal with this test problem is to determine whether exponential convergence occurs for the hp -scheme with a careful choice of the mesh.

First, we solve the problem using $K = 1$, in which case convergence is achieved by increasing the degree N of the polynomials. In Figure 8.3(a) we plot the logarithm of the error at the collocation points in the sup-norm versus the logarithm of the polynomial degree. Convergence occurs, but it is slow due to the discontinuity in the derivatives.

Next, we divide the time interval $[0, 1]$ into three subintervals $[0, 0.25]$, $[0.25, 0.75]$, and $[0.75, 1.0]$, and use different polynomials of the same degree on each subinterval. By this careful choice of the mesh intervals, we obtain an exponential convergence rate in Figure 8.3(b). Comparing Figures 8.3(a) and 8.3(b), we see that a huge

improvement in the error is possible when we have good estimates for the contact points where the constraints change between active and inactive. Note that 16-digit accuracy was obtained in Figure 8.3(b) by using MATLAB's QUADPROG to solve the quadratic program associated with the hp -discretization of Example 2.

9. Conclusions. A convergence rate is derived for an hp -orthogonal collocation method based on the Radau quadrature points applied to a control problem with convex control constraints. If the problem has a smooth local solution and a Hamiltonian which satisfies a strong convexity assumption, then the discrete approximation has a local minimizer in a neighborhood of the continuous solution. For the hp -scheme, both the number of mesh intervals in the discretization and the degree of the polynomials on each mesh interval can be freely chosen. As the number of mesh intervals increases, convergence occurs at a polynomial rate relative to the mesh width. When there is control over the growth in derivatives, the convergence rate is exponentially fast relative to the polynomial degree. Convergence rates were investigated further using numerical examples. When the polynomial degree is fixed and the mesh width tends to zero, the observed convergence rate was faster than the rate associated with the error bound. For a problem with control and state constraints, exponentially fast convergence was achieved when mesh points are located at the contact points where the constraints change between active and inactive.

10. Appendix. Before stating property (P3) in the Introduction, we showed that \mathbf{D}^\dagger is an invertible matrix. In this section, we give an analytic formula for the inverse.

PROPOSITION 10.1. *The inverse of \mathbf{D}^\dagger is given by*

$$\begin{aligned} D_{ij}^{\dagger-1} &= \omega_N M_j(1) + \int_1^{\tau_i} M_j(\tau) d\tau, & 1 \leq i < N, \quad 1 \leq j < N, \\ D_{iN}^{\dagger-1} &= -\omega_N, & 1 \leq i \leq N, \\ D_{Nj}^{\dagger-1} &= \omega_N M_j(1), & 1 \leq j < N, \end{aligned}$$

where M_j , $1 \leq j < N$, is the Lagrange interpolating basis relative to the point set $\tau_1, \dots, \tau_{N-1}$. That is,

$$M_j(\tau) = \prod_{\substack{i=1 \\ i \neq j}}^{N-1} \frac{\tau - \tau_i}{\tau_j - \tau_i}, \quad j = 1, \dots, N-1.$$

Proof. The relation (1.13) holds for any polynomial p of degree at most $N-1$. Let $\dot{\mathbf{p}} \in \mathbb{R}^N$ denote the vector with i -th component $\dot{p}(\tau_i)$. In vector form, the system of equations (1.13) can be expressed $\mathbf{D}^\dagger \dot{\mathbf{p}} = \dot{\mathbf{p}} - \mathbf{e}_N p(1)/\omega_N$. Multiply by $\mathbf{D}^{\dagger-1}$ and exploit the identity $\mathbf{D}^{\dagger-1} \mathbf{e}_N = -\omega_N \mathbf{1}$ of (5.14) to obtain

$$\mathbf{D}^{\dagger-1} \dot{\mathbf{p}} = \dot{\mathbf{p}} - \mathbf{1} p(1). \quad (10.1)$$

Since \dot{p} is a polynomial of degree at most $N-2$, we can only specify the derivative of p at $N-1$ distinct points. Given any j satisfying $1 \leq j < N$, let us insert in (10.1) a polynomial $p \in \mathcal{P}_{N-1}$ satisfying

$$\dot{p}(\tau_j) = 1 \quad \text{and} \quad \dot{p}(\tau_i) = 0 \quad \text{for all } i < N, \quad i \neq j.$$

A specific polynomial with this property is

$$p(\tau) = \int_1^\tau M_j(\tau) d\tau. \quad (10.2)$$

Since $p_N = p(1) = 0$, the last component of the right side of (10.1) vanishes to give the relation $D_{Nj}^{\dagger-1} + D_{NN}^{\dagger-1} \dot{p}(1) = 0$. In (5.14) we showed that all the elements in the last column of $\mathbf{D}^{\dagger-1}$ are equal to $-\omega_N$, and by (10.2), $\dot{p}(1) = M_j(1)$. Hence, we obtain the relation

$$D_{Nj}^{\dagger-1} = -D_{NN}^{\dagger-1} \dot{p}(1) = \omega_N \dot{p}(1) = \omega_N M_j(1), \quad 1 \leq j < N. \quad (10.3)$$

Finally, let us consider $D_{ij}^{\dagger-1}$ for $i < N$ and $j < N$. We combine the i -th component of (10.1) for $i < N$ with (10.2) to obtain

$$(\mathbf{D}^{\dagger-1} \dot{\mathbf{p}})_i = \int_1^{\tau_i} M_j(\tau) d\tau. \quad (10.4)$$

Recall that all components of $\dot{\mathbf{p}}$ vanish except for the j -th, which is 1, and the N -th, which is $M_j(1)$ by (10.2). Hence, (10.4) and the fact that the elements in the last column of $\mathbf{D}^{\dagger-1}$ are all $-\omega_N$ yield

$$D_{ij}^{\dagger-1} = \int_1^{\tau_i} M_j(\tau) d\tau - D_{iN}^{\dagger-1} M_j(1) = \omega_N M_j(1) + \int_1^{\tau_i} M_j(\tau) d\tau$$

This completes the proof. \square

Tables 10.1 and 10.2 show $\|\mathbf{D}^{\dagger-1}\|_\infty$ and the maximum Euclidean norm of the rows of $\mathbf{D}^{\dagger-1} \mathbf{W}^{-1/2}$ for an increasing sequence of dimensions. The norms in Table 10.1 approach 2 as N grows, consistent with (P3), while the norms in Table 10.2 approach $\sqrt{2}$, consistent with (P4).

N	25	50	75	100	125	150
norm	1.995376	1.998844	1.999486	1.999711	1.999815	1.999871
N	175	200	225	250	275	300
norm	1.999906	1.999928	1.999943	1.999954	1.999962	1.999968

TABLE 10.1
 $\|\mathbf{D}^{\dagger-1}\|_\infty$

N	25	50	75	100	125	150
norm	1.412209	1.413691	1.413982	1.414083	1.414130	1.414156
N	175	200	225	250	275	300
norm	1.414171	1.414181	1.414188	1.414193	1.414196	1.414199

TABLE 10.2
Maximum Euclidean norm for the rows of $[\mathbf{W}^{1/2} \mathbf{D}^{\dagger}]^{-1}$

REFERENCES

- [1] I. BABUŠKA AND M. SURI, *The h - p version of the finite element method with quasiuniform meshes*, RAIRO, Modélisation Mathématique et Analyse Numérique, 21 (1987), pp. 199–238.
- [2] ———, *The p - and h - p version of the finite element method, an overview*, Comput. Methods Appl. Mech. Engrg., 80 (1990), pp. 5–26.
- [3] ———, *The p and h - p version of the finite element method, basic principles and properties*, SIAM Rev., 36 (1994), pp. 578–632.
- [4] D. A. BENSON, G. T. HUNTINGTON, T. P. THORVALDSEN, AND A. V. RAO, *Direct trajectory optimization and costate estimation via an orthogonal collocation method*, J. Guid. Control Dyn., 29 (2006), pp. 1435–1440.
- [5] C. BERNARDI AND Y. MADAY, *Polynomial interpolation results in Sobolev spaces*, J. Comput. Appl. Math., (1992), pp. 53–82.
- [6] L. T. BIEGLER AND V. M. ZAVALA, *Large-scale nonlinear programming using IPOPT: An integrating framework for enterprise-wide optimization*, Comput. Chem. Eng., 33 (2008), pp. 575–582.
- [7] J. F. BONNANS AND J. LAURENT-VARIN, *Computation of order conditions for symplectic partitioned Runge-Kutta schemes with application to optimal control*, Numer. Math., 103 (2006), pp. 1–10.
- [8] C. CANUTO, M. HUSSAINI, A. QUARTERONI, AND T. ZANG, *Spectral methods, Fundamentals in single domains*, Springer, 2006.
- [9] C. L. DARBY, W. W. HAGER, AND A. V. RAO, *Direct trajectory optimization using a variable low-order adaptive pseudospectral method*, J. Spacecr. Rockets, 48 (2011), pp. 433–445.
- [10] ———, *An hp -adaptive pseudospectral method for solving optimal control problems*, Optim. Control Appl. Meth., 32 (2011), pp. 476–502.
- [11] A. DONTCHEV, W. W. HAGER, A. POORE, AND B. YANG, *Optimality, stability, and convergence in nonlinear control*, Applied Math. and Optim., 31 (1995), pp. 297–326.
- [12] A. L. DONTCHEV AND W. W. HAGER, *Lipschitzian stability in nonlinear control and optimization*, SIAM J. Control Optim., 31 (1993), pp. 569–603.
- [13] ———, *A new approach to Lipschitz continuity in state constrained optimal control*, Systems and Control Letters, 35 (1998), pp. 137–143.
- [14] ———, *The Euler approximation in state constrained optimal control*, Math. Comp., 70 (2001), pp. 173–203.
- [15] A. L. DONTCHEV, W. W. HAGER, AND V. M. VELIOV, *Second-order Runge-Kutta approximations in constrained optimal control*, SIAM J. Numer. Anal., 38 (2000), pp. 202–226.
- [16] G. ELNAGAR, M. KAZEMI, AND M. RAZZAGHI, *The pseudospectral Legendre method for discretizing optimal control problems*, IEEE Trans. Automat. Control, 40 (1995), pp. 1793–1796.
- [17] G. N. ELNAGAR AND M. A. KAZEMI, *Pseudospectral Chebyshev optimal control of constrained nonlinear dynamical systems*, Comput. Optim. Appl., 11 (1998), pp. 195–217.
- [18] J. ELSCHNER, *The h - p -version of spline approximation methods for Melin convolution equations*, J. Integral Equations Appl., 5 (1993), pp. 47–73.
- [19] F. FAHROO AND I. M. ROSS, *Costate estimation by a Legendre pseudospectral method*, J. Guid. Control Dyn., 24 (2001), pp. 270–277.
- [20] ———, *Direct trajectory optimization by a Chebyshev pseudospectral method*, J. Guid. Control Dyn., 25 (2002), pp. 160–166.
- [21] D. GARG, M. A. PATTERSON, C. L. DARBY, C. FRANÇOLIN, G. T. HUNTINGTON, W. W. HAGER, AND A. V. RAO, *Direct trajectory optimization and costate estimation of finite-horizon and infinite-horizon optimal control problems using a Radau pseudospectral method*, Comput. Optim. Appl., 49 (2011), pp. 335–358.
- [22] D. GARG, M. A. PATTERSON, W. W. HAGER, A. V. RAO, D. A. BENSON, AND G. T. HUNTINGTON, *A unified framework for the numerical solution of optimal control problems using pseudospectral methods*, Automatica, 46 (2010), pp. 1843–1851.
- [23] Q. GONG, I. M. ROSS, W. KANG, AND F. FAHROO, *Connections between the covector mapping theorem and convergence of pseudospectral methods for optimal control*, Comput. Optim. Appl., 41 (2008), pp. 307–335.
- [24] W. GUI AND I. BABUŠKA, *The h , p and h - p versions of the finite element method in 1 dimension. Part I. The error analysis of the p -version*, Numer. Math., 49 (1986), pp. 577–612.
- [25] ———, *The h , p and h - p versions of the finite element method in 1 dimension. Part II. The error analysis of the h - and h - p versions*, Numer. Math., 49 (1986), pp. 613–657.
- [26] ———, *The h , p and h - p versions of the finite element method in 1 dimension. Part III. The adaptive h - p version*, Numer. Math., 49 (1986), pp. 659–683.

- [27] W. W. HAGER, *Multiplier methods for nonlinear optimal control*, SIAM J. Numer. Anal., 27 (1990), pp. 1061–1080.
- [28] ———, *Runge-Kutta methods in optimal control and the transformed adjoint system*, Numer. Math., 87 (2000), pp. 247–282.
- [29] ———, *Numerical analysis in optimal control*, in International Series of Numerical Mathematics, K.-H. Hoffmann, I. Lasiecka, G. Leugering, J. Sprekels, and F. Tröltzsch, eds., vol. 139, Basel/Switzerland, 2001, Birkhauser Verlag, pp. 83–93.
- [30] W. W. HAGER, H. HOU, AND A. V. RAO, *Convergence rate for a Radau collocation method applied to unconstrained optimal control*, (2015, arXiv.org/abs/1508.03783).
- [31] ———, *Convergence rate for a Gauss collocation method applied to unconstrained optimal control*, J. Optim. Theory Appl., 169 (2016), pp. 801–824.
- [32] W. W. HAGER AND G. IANCULESCU, *Dual approximations in optimal control*, SIAM J. Control Optim., 22 (1984), pp. 423–465.
- [33] W. W. HAGER, J. LIU, S. MOHAPATRA, A. V. RAO, AND X.-S. WANG, *Convergence rate for a Gauss collocation method applied to constrained optimal control*, (2017, arXiv.org/abs/1607.02798).
- [34] W. KANG, *The rate of convergence for a pseudospectral optimal control method*, in Proceeding of the 47th IEEE Conference on Decision and Control, IEEE, 2008, pp. 521–527.
- [35] ———, *Rate of convergence for the Legendre pseudospectral optimal control of feedback linearizable systems*, J. Control Theory Appl., 8 (2010), pp. 391–405.
- [36] F. LIU, W. W. HAGER, AND A. V. RAO, *Adaptive mesh refinement method for optimal control using nonsmoothness detection and mesh size reduction*, J. Franklin Inst., 352 (2015), pp. 4081–4106.
- [37] J. NOCEDAL AND S. J. WRIGHT, *Numerical Optimization*, Springer, New York, 2nd ed., 2006.
- [38] M. A. PATTERSON, W. W. HAGER, AND A. V. RAO, *A hp mesh refinement method for optimal control*, Optim. Control Appl. Meth., 36 (2015), pp. 398–421.
- [39] M. A. PATTERSON AND A. V. RAO, *GPOPS-II: A MATLAB software for solving multi-phase optimal control problems using hp-adaptive Gaussian quadrature collocation methods and sparse non-linear programming*, ACM Trans. Math. Software, 41 (2014), pp. 1–37.
- [40] M. A. PATTERSON AND A. V. RAO, *GPOPS – III, a MATLAB software for solving multiple-phase optimal control problems using hp-adaptive Gaussian quadrature collocation methods and sparse nonlinear programming*, ACM Transactions on Mathematical Software, 41 (2015), pp. 1–37.
- [41] J. SHEN, T. TANG, AND L.-L. WANG, *Spectral Methods*, Springer, Berlin, 2011.
- [42] G. SZEGŐ, *Orthogonal Polynomials*, American Mathematical Society, Providence, RI, 1939.
- [43] P. WILLIAMS, *Jacobi pseudospectral method for solving optimal control problems*, J. Guid. Control Dyn., 27 (2004), pp. 293–297.