

SU(1,1) and SU(2) Y-Maps in Loop Quantum Gravity

Leonid Perlov,
Department of Physics, University of Massachusetts, Boston, USA
leonid.perlov@umb.edu

December 12, 2021

Abstract

By using $SU(1,1)$ LQG simplicity constraints we define $SU(1,1)$ Y-Map from the square-integrable functions on $SU(1,1)$ to the functions on $SL(2, C)$, and prove its convergence. Before considering $SU(1,1)$ Y-Map, we repeat our proof of $SU(2)$ Y-Map convergence that we had proved earlier as part of a more general result - Peter-Weyl Theorem for the Lorentz group [3].

1 Introduction

Y-Map takes one of the central places in the Loop Quantum Gravity. The $SU(2)$ -Y-Map was first introduced in [6] and [7]. We proved its convergence in [3] as part of the more general theorem. In this paper we define $SU(1,1)$ -Y-Map and prove its convergence. $SU(2)$ -Y-Map is a map from square integrable functions on $SU(2)$ to functions on $SL(2, C)$ provided by the solution of the simplicity constraints [5]. Likewise, $SU(1,1)$ -Y-Map is a map from square integrable functions on $SU(1,1)$ to functions on $SL(2, C)$ provided by the $SU(1,1)$ simplicity constraints [2]. Y-Maps are important as they provide the way to define a Hilbert space on the space of non-square integrable functions on $SL(2, C)$ by using a projective inner product, i.e. the inner product on the functions on $SU(2)$.

The paper is organized as follows. In section 2 we repeat our previous result - the proof of $SU(2)$ Y-Map convergence. In the next section 3 we define $SU(1,1)$ Y-Map and prove its convergence. Section 4 concludes the paper.

2 SU(2)-Y-Map

Before we define a new $SU(1,1)$ Y-Map and prove its convergence in the next section, it is instructional to repeat our previous result - the proof of the $SU(2)$ - Y-Map convergence. The proof of $SU(2)$ Y-Map convergence was published back in 2015 as a part of a more general result - the analog of the Peter-Weyl theorem for

Lorentz group [3] (Chapter 4). We are going to prove that any square integrable function $\phi(u)$ on $SU(2)$ can be mapped to a function $\psi(g)$ on $SL(2, C)$ (not necessary square integrable), by using the solution of the $SU(2)$ Simplicity Constraints [5]: ($n = j, \rho = \gamma j, j \in Z, \gamma \in C$) in the following manner:

$$\phi(u) \rightarrow \psi(g) = \sum_{j=|p|}^{\infty} \sum_{|m| \leq j} \sum_{|n| \leq j} d_{|p|m}^{\frac{j}{2}} D_{jm, jn}^{(j, \gamma j)} \quad (1)$$

, where $d_{|p|m}^{\frac{j}{2}}$ is $\phi(u)$'s Fourier transform:

$$d_{|p|m}^{\frac{j}{2}} = (j+1)^{\frac{1}{2}} \int_{SU(2)} \phi(u) \overline{D_{|p|m}^{\frac{j}{2}}} du \quad (2)$$

, where $p, j, m, n \in Z, \gamma \in C, u \in SU(2), g \in SL(2, C)$ Note that the parameter j in $SL(2, C)$ matrix coefficients is an integer, while the parameter of the $SU(2)$ in $d_{|p|m}^{\frac{j}{2}}$ is half-integer. Let us prove that (1) is convergent:

Lemma

The sum $\sum_{k=\frac{|p|}{2}}^{\infty} \sum_{|m| \leq k} d_{\frac{|p|}{2}m}^k$ is convergent, where $k = \frac{|p|}{2} + n, n \in N, p \in Z$

Proof:

By the Paley-Wiener Theorem ([1] page 60, 91, see also [4]) the Fourier transform $d_{\frac{|p|}{2}m}^k$ satisfies the following asymptotic inequality:

$$\lim_{k \rightarrow \infty} \sup_m (|d_{\frac{|p|}{2}m}^k k^n) = 0, \quad \forall n \in N \quad (3)$$

or

$$|k^n d_{\frac{|p|}{2}m}^k| \leq C_n \quad (4)$$

$\forall n \in N$ or we can rewrite it as:

$$|d_{\frac{|p|}{2}m}^k| \leq \frac{C_n}{|k|^n} \quad (5)$$

which means that the Fourier transform is a fast dropping function and decreases faster than any polynomial of power n . Then the sum :

$$\sum_{k=\frac{|p|}{2}}^{\infty} \sum_{|m| \leq k} |d_{\frac{|p|}{2}m}^k| \leq \sum_{k=\frac{|p|}{2}}^{\infty} \sum_{|m| \leq k} \frac{C_n}{|k|^n} \leq C_n \sum_{k=\frac{|p|}{2}}^{\infty} \frac{(2k+1)}{|k|^n} \quad (6)$$

and the latter is a Riemann zeta function and is convergent $\forall n > 2$.

This proves the absolute convergence and therefore the regular convergence.

If we pass in the notation from the half-integer k to the integer j by writing $k = \frac{j}{2}$, we obtain that $\sum_{j=|p|}^{\infty} \sum_{|m| \leq j} d_{|p|m}^{\frac{j}{2}}$ is convergent.

□

SU(2)-Y-Map Existence Theorem:

The sum $\phi(u) \rightarrow \psi(g) = \sum_{j=|p|}^{\infty} \sum_{|m| \leq j} \sum_{|n| \leq j} d_{|p|m}^{\frac{j}{2}} D_{jm,jn}^{(j,\gamma j)}(g)$ is convergent.

Proof:

$$\sum_{j=|p|}^k \sum_{|m| \leq j} \sum_{|n| \leq j} d_{|p|m}^{\frac{j}{2}} D_{jm,jn}^{(j,\gamma j)}(g) \leq \sum_{j=|p|}^k \sum_{|m| \leq j} |d_{|p|m}^{\frac{j}{2}}| \times \sum_{j=0}^k \left| \sum_{|m| \leq j} \sum_{|n| \leq j} D_{jm,jn}^{(j,\gamma j)}(g) \right| \quad (7)$$

$\forall k \geq |p|$ and therefore it is true in the limit when $k \rightarrow \infty$.

$$\sum_{j=|p|}^{\infty} \sum_{|m| \leq j} \sum_{|n| \leq j} d_{|p|m}^{\frac{j}{2}} D_{jm,jn}^{(j,\gamma j)}(g) \leq \sum_{j=|p|}^{\infty} \sum_{|m| \leq j} |d_{|p|m}^{\frac{j}{2}}| \times \sum_{j=0}^{\infty} \left| \sum_{|m| \leq j} \sum_{|n| \leq j} D_{jm,jn}^{(j,\gamma j)}(g) \right| \quad (8)$$

The first sum on the right hand side converges due to the Lemma above. The second sum converges due to the Lemma 1 in [3]. The proof of the second sum convergence is long and challenging. It is provided in all details in [3], so we do not repeat its details here.

The limit is a function on $SL(2, C)$ since each $g \in SL(2, C)$ we map to the sum limit and the limit is unique by construction.

□

The SU(2)-Y-Map Theorem establishes a map from the space of square integrable functions on $SU(2)$ to the space of functions (not necessarily square integrable) on $SL(2, C)$.

3 SU(1,1)-Y-Map

In order to define an SU(1,1)-Y-Map similar to SU(2)-Y-Map, we need two components: the Fourier coefficients of the function $\phi(v), v \in SU(1, 1)$, and the matrix coefficients of the function $\psi(g), g \in SL(2, C)$. However these matrix coefficients should be from the basis of the functions on $SU(1, 1)$, rather than on the usual $SU(2)$ ones: $D_{j_1, m_1, j_2, m_2}^{(n, \rho)}$. Fortunately such basis exists.

The groups $SU(1, 1)$ and $SL(2, R)$ are isomorphic. Consider an element a of the group

$SL(2, R)$. It can be decomposed as [1]:

$$a = u_1 d u_2 \quad (9)$$

$$, \text{ where } d = \begin{bmatrix} e^{1/2\eta} & 0 \\ 0 & e^{-1/2\eta} \end{bmatrix}, \eta \geq 0$$

, while u_1 and u_2 are $SU(2)$ rotation matrices of the form:

$$u = \begin{bmatrix} \cos(1/2\psi) & -\sin(1/2\psi) \\ \sin(1/2\psi) & \cos(1/2\psi) \end{bmatrix}$$

In all known facts of $SU(1, 1)$ harmonic analysis until the $SU(1,1)$ -Y-Map definition we will follow [1].

The function $x(v)$ on $SU(1, 1)$ is called q_1, q_2 bi-covariant if

$$v = e^{i/2\psi_1\sigma_3} e^{1/2\eta\sigma_2} e^{i/2\psi_2\sigma_3} \quad (10)$$

implies:

$$x_{q_1 q_2}(v) = e^{i(q_1\psi_1 + q_2\psi_2)} x_{q_1 q_2}(\eta) \quad (11)$$

, where $v \in SU(1, 1)$, $\eta \geq 0$, q_1, q_2 – half-integers, $\psi_1, \psi_2 \in R$

It is very useful as bi-covariant functions on $SL(2, C)$ remain bi-covariant when restricted to $SU(1, 1)$

$$x_{j_1 q_1 j_2 q_2}(v) = e^{i(q_1\psi_1 + q_2\psi_2)} x_{j_1 q_1 j_2 q_2}(\eta) \quad (12)$$

The principal series $SL(2, C)$ representation can be decomposed either into the canonical $SU(2)$ basis $D_{1/2n, q}^j(u)$ or $SU(1, 1)$ basis: $D_{1/2\tau n, q}^j(v)$. More than that, the $SU(1, 1)$ basis can be expressed via $SU(2)$ one ([1] p 229):

$$D_{1/2n\tau, q}^j(v) = (2j+1)^{1/2} (2s-1)^{(i/2)\rho-1} D_{((1/2)n, q)}^j(u_\tau(v)) \quad (13)$$

, where (n, ρ) are $SL(2, C)$ principal series parameters,

$\tau = \pm 1$, $s \in R, s \geq 0$, j, q – half-integers, $u \in SU(2), v \in SU(1, 1)$, for $(u_\tau(v))$ expression see [1] page 229.

$SL(2, C)$ matrix coefficients with $SU(1, 1)$ basis can be defined as:

$$p_{j_1 q_1 j_2 q_2}^{n, \rho, \tau}(v) = \langle j_1, \tau q_1 | T_v^{n, \rho} | j_2 \tau q_2 \rangle \quad (14)$$

or for the bi-covariant functions:

$$p_{j_1 q_1 j_2 q_2}^{n, \rho, \tau}(\eta) = \langle j_1, \tau q_1 | T_{exp(1/2\eta\sigma_2)}^{n, \rho} | j_2 \tau q_2 \rangle \quad (15)$$

The Fourier coefficients of the $SU(1, 1)$ discrete and continuous series representations are as follows:

Discrete Series:

$$F_{q_1 q_2}^+(J) = \frac{1}{2} \int_0^\infty x_{q_1 q_2}(\cosh \eta) \sinh(\eta) d\eta \quad (16)$$

Continues (Principal) Series:

$$F_{q_1 q_2}(J) = \frac{1}{2} \int_0^\infty x_{q_1 q_2}(\cosh \eta) \sinh(\eta) d\eta \quad (17)$$

Before we begin elaborating on the $SU(1, 1)$ Y-Map definition, it is important to note that the inverse Fourier transform of the functions on $SU(1, 1)$ contains both discrete and continuous series representation matrix coefficients. In other words one can not decompose a function on $SU(1, 1)$ by using only one of the two series of representation. That's why it is important to use both discrete and continuous series representations in the $SU(1, 1)$ Y-Map definition.

Given a function $\phi(v)$ on $SU(1, 1)$ we define $SU(1, 1)$ Y-Map similar to $SU(2)$ Y-Map, i.e as a sum of products of the $\phi(v)$ Fourier transform coefficients $F(J)$ with the $SL(2, C)$ matrix coefficients $p_{j_1 q_1 j_2 q_2}^{n, \rho, \tau}(v)$, with the parameters provided by the solutions of $SU(1, 1)$ simplicity constraints. As we show below there is only one free parameter n of the $SL(2, C)$ principal series, all others can be expressed via it, by using the simplicity constraints. We first write two sums below and then we will define each index by using $SU(1, 1)$ simplicity constraints:

$$\phi_{q_1 q_2}(\eta) \rightarrow \psi_{q_1 q_2}(\eta) = \sum_{\tau=\pm 1} \sum_{J \geq 0}^\infty F_{q_1 q_2}^+(J) p_{j_1 q_1 j_2 q_2}^{J, \tau}(\eta) + \sum_{\tau=\pm 1} \sum_{J=0}^{-1/2+i\infty} F_{q_1 q_2}^{n, \rho}(J) p_{j_1 q_1 j_2 q_2}^{J, \tau}(\eta) \quad (18)$$

For Discrete Series: $J = j-1$, For Continues Series: $J = -1/2+is$, $0 \leq s \leq \infty$

j_1, j_2, q_1, q_2 —half-integers, $\tau = \pm 1$, (n, ρ) — $SL(2, C)$ principal series parameters (19)

The $SU(1, 1)$ simplicity constraints solution were obtained in [2]:

For Discrete Series:

$$\rho = \gamma n, \quad j = n/2, \quad \gamma \in R, n \in Z \quad (20)$$

or taking into account (19):

$$\rho = \gamma n, \quad J = n/2 - 1 \quad (21)$$

For Continuous Principle Series:

$$\rho = -n/\gamma, \quad s^2 + 1/4 = -J(J+1) = \rho^2/4 \quad (22)$$

or

$$\rho = -n/\gamma, \quad s = \frac{1}{2} \sqrt{((n^2/\gamma^2) - 1)} \quad (23)$$

we selected the positive sign as $s \geq 0$. By using (19), we can write for continues series:

$$\rho = -n/\gamma, \quad J = -1/2 + \frac{i}{2} \sqrt{((n^2/\gamma^2) - 1)} \quad (24)$$

By substituting from (20), (21), (24) into (18) the expressions for J and ρ for both discrete and continuous series, and by setting $j_1 = j_2 = j = n/2$ we obtain:

$$\phi_{q_1 q_2}(\eta) \rightarrow \psi_{q_1 q_2}(\eta) = \sum_{\tau=\pm 1} \sum_{n=0}^{\infty} F_{q_1 q_2}^+(n) p_{(n/2)q_1, (n/2)q_2}^{(n/2-1), \tau}(\eta) + \sum_{\tau=\pm 1} \sum_{n=0}^{\infty} F_{q_1 q_2}^{n, -n/\gamma}(n) p_{(n/2)q_1, (n/2)q_2}^{(-\frac{1}{2} + \frac{i}{2} \sqrt{((n^2/\gamma^2) - 1)}, \tau)}(\eta) \quad (25)$$

The reason we set $j_1 = j_2 = j = n/2$ for the discrete series follows from the simplicity constraint, while for the continuous it follows from the expression of the $SU(1, 1)$ matrix coefficients via $SU(2)$ ones ([1] page 234):

$$\sum_{\tau=\pm 1} p_{j_1 q_1, j_2 q_2}^{n, \rho, \tau}(\eta) = e^{\frac{i}{2} \pi (q_1 + q_2)} \sum_q e^{-i \pi q} d_{q_1 q}^{j_1}(0) \times d_{q q_2}^{j_2}(0) d_{j_1 j_2 q}^{n, \rho}(\eta) \quad (26)$$

So j_1 and j_2 are $SU(2)$ spins and therefore by the simplicity constraint are equal $n/2$. By using the bi-covariance (12) and replacing the notation n to j to be in line with $SU(2)$ Y-Map notation we finally can give the complete definition of the $SU(1, 1)$ Y-Map:

$SU(1, 1)$ -Y-Map Definition:

$$\begin{aligned} \phi(v) &= e^{i(q_1 \psi_1 + q_2 \psi_2)} \phi_{q_1 q_2}(\eta) \rightarrow e^{i(q_1 \psi_1 + q_2 \psi_2)} \psi_{q_1 q_2}(\eta) = \\ &= e^{i(q_1 \psi_1 + q_2 \psi_2)} \left(\sum_{\tau=\pm 1} \sum_{j=3}^{\infty} F_{q_1 q_2}^+(j) p_{(\frac{j}{2} q_1, \frac{j}{2} q_2)}^{\frac{j}{2}-1, \tau}(\eta) + \sum_{\tau=\pm 1} \sum_{j=1}^{\infty} F_{q_1 q_2}^{j, -j/\gamma}(j) p_{(\frac{j}{2} q_1, \frac{j}{2} q_2)}^{(-\frac{1}{2} + \frac{i}{2} \sqrt{((j^2/\gamma^2) - 1)}, \tau)}(\eta) \right) \end{aligned} \quad (27)$$

Let us now prove the convergence of both sums.

$SU(1, 1)$ -Y-Map Existence Theorem:

The $SU(1, 1)$ Y-Map of a square-integrable function $\phi(v)$, $v \in SU(1, 1)$ to the function

$\psi(g), g \in SL(2, C)$ defined as:

$$\begin{aligned} \phi(v) &= e^{i(q_1 \psi_1 + q_2 \psi_2)} \phi_{q_1 q_2}(\eta) \rightarrow e^{i(q_1 \psi_1 + q_2 \psi_2)} \psi_{q_1 q_2}(\eta) = \\ &= e^{i(q_1 \psi_1 + q_2 \psi_2)} \left(\sum_{\tau=\pm 1} \sum_{j=3}^{\infty} F_{q_1 q_2}^+(j) p_{(\frac{j}{2} q_1, \frac{j}{2} q_2)}^{\frac{j}{2}-1, \tau}(\eta) + \sum_{\tau=\pm 1} \sum_{j=1}^{\infty} F_{q_1 q_2}^{j, -j/\gamma}(j) p_{(\frac{j}{2} q_1, \frac{j}{2} q_2)}^{(-\frac{1}{2} + \frac{j}{2} \sqrt{(j^2/\gamma^2)-1}), \tau}(\eta) \right) \end{aligned} \quad (28)$$

is convergent.

Proof:

First, we note that the functions $p_{(\frac{j}{2} q_1, \frac{j}{2} q_2)}^{\frac{j}{2}-1, \tau}(\eta)$ and $p_{(\frac{j}{2} q_1, \frac{j}{2} q_2)}^{(-\frac{1}{2} + \frac{j}{2} \sqrt{(j^2/\gamma^2)-1}), \tau}(\eta)$ are bounded, since the values of J that we obtained from the simplicity constraints were based on the (n, ρ) of the $SL(2, C)$ principal series, and for that case the following bound is true (see [1] page 235):

$$|p_{j_1 q_1 j_2 q_2}^{J, \tau}(\eta)| < C \frac{\eta}{\sinh \eta}, \quad C \in R \quad (29)$$

, where for the discrete series $J = \frac{j}{2} - 1$, while for continuous:

$$J = -\frac{1}{2} + \frac{j}{2} \sqrt{(j^2/\gamma^2) - 1}$$

Secondly, by the Paley-Wiener theorem the Fourier coefficients of the continuous series are polynomially bounded on the lines $Re(J) = \text{const}$ for bi-covariant functions $x(a)$, which vanish for $|a| > N$ see [1] page 218:

$$|F(J)| \leq \frac{M(N, C) \times \sup_{0 \leq \eta \leq \infty} |D^m(\cosh(\eta)x(\eta))|}{|J(J+1)|^m}, \quad m = 0, 1, 2, \dots \quad (30)$$

, where D is a derivative operator.

Or by remembering that from the simplicity constraints (22)

$$J(J+1) = -\rho^2/4 = -j^2/4\gamma^2 \quad (31)$$

By introducing in (33) notation:

$$c_m = (2\gamma)^{2m} M(N, C) \times \sup_{0 \leq \eta \leq \infty} |D^m(\cosh(\eta)x(\eta))| \quad (32)$$

and substituting (31) and (32) into (33) we can right the upper bound for the Fourier coefficients of the continuous series as:

$$|F(j)| \leq \frac{c_m}{|j|^{2m}}, \quad j \in Z, m = 0, 1, 2, \dots, \text{ and } c_m = \text{const} \quad (33)$$

For the discrete series the Paley-Wiener theorem provides a similar result: for any $m = 0, 1, 2, \dots$ [1] page 218:

$$|F^+(J)| \leq \frac{d_m}{|J(J+1)|^m}, \quad m = 0, 1, 2, \dots \text{ and } d_m = \text{const} \quad (34)$$

By remembering that for the discrete series $J = j/2 - 1$, we obtain:

$$|F^+(J)| \leq \frac{d_m}{|j(j-2)|^m}, \quad j \in \mathbb{Z}, \quad m = 0, 1, 2, \dots, \text{ and } d_m = \text{const} \quad (35)$$

Thus, we have received similar upper estimates for the discrete and continuous series Fourier coefficients. Substituting all upper estimates: (29), (33) and (35) into SU(1,1) Y-Map definition (27), we obtain:

$$\begin{aligned} \phi(v) &= e^{i(q_1\psi_1 + q_2\psi_2)} \phi_{q_1 q_2}(\eta) \rightarrow e^{i(q_1\psi_1 + q_2\psi_2)} \psi_{q_1 q_2}(\eta) \\ &\leq \sum_{\tau=\pm 1} \sum_{j=3}^{\infty} \frac{d_m}{|j(j-2)|^m} \frac{\eta}{\sinh \eta} + \sum_{\tau=\pm 1} \sum_{j=1}^{\infty} \frac{c_m}{|j|^{2m}} \frac{\eta}{\sinh \eta} = \\ &\quad \frac{2\eta}{\sinh \eta} \left(\sum_{j=3}^{\infty} \frac{d_m}{|j(j-2)|^m} + \sum_{j=1}^{\infty} \frac{c_m}{|j|^{2m}} \right) \quad (36) \end{aligned}$$

The second sum is convergent for any $m \geq 1$, since the value is a Riemann zeta function. The first sum can be written as

$$\sum_{j=3}^{\infty} \frac{1}{|j(j-2)|^m} = \sum_{j=3}^{\infty} \left| \frac{1}{j-2} - \frac{1}{j} \right|^m \leq \sum_{j=3}^{\infty} \left| \frac{1}{j-2} \right|^m + \sum_{j=3}^{\infty} \left| \frac{1}{j} \right|^m \quad (37)$$

, where we used the triangle (Minkowsky) inequality. Both sums on the right are convergent as they are Riemann zeta functions. Therefore the first sum in (36) is convergent. Thus, we have proved the SU(1,1) Y-Map convergence Theorem.

□

4 Discussion

We have defined SU(1,1)-Y-Map from the square integrable functions on $SU(1,1)$ to the functions (not necessarily square integrable) on $SL(2, \mathbb{C})$, by using: $SL(2, \mathbb{C})$ matrix coefficients in the basis of functions on $SU(1,1)$, Fourier transform coefficients in both discrete and principal series, and the solution of the $SU(1,1)$ simplicity constraints. We then proved that the newly defined SU(1,1)-Y-Map is convergent. We also reviewed the SU(2)-Y-Map and repeated our earlier proof of its convergence. The Y-Map is used in Loop Quantum Gravity to define a Hilbert space on the functions on $SL(2, \mathbb{C})$ with the help of the projective inner product.

Acknowledgment

I would like to thank Michael Bukatin for reading this paper and making his comments.

References

- [1] W. Ruhl, "The Lorentz Group and Harmonic Analysis", (Benjamin, Inc 1970)
- [2] F. Conrady, J. Hnybida "A spin foam model for general Lorentzian 4-geometries", *Class.Quant.Grav.* 27(18), (2010)
- [3] L. Perlov "Analog of the Peter-Weyl expansion for Lorentz group", *Journal of Mathematical Physics* 56, 111703 (2015)
- [4] I. M. Gelfand, M. I. Graev, and N. Ya Vilenkin ""Integral Geometry and Related Issues of the Representation Theory (Academic Press, 1966)
- [5] J. Engle, E. Livine, R. Pereira, C. Rovelli, "LQG vertex with finite Immirzi parameter", *Nuclear Physics B*, vol 799, 136-149, (2008)
- [6] C. Rovelli, "A new look at loop quantum gravity", *Class. Quant. Grav.*, vol. 28, 11, (2010)
- [7] C. Rovelli, F. Vidotto "Covariant Loop Quantum Gravity: An Elementary Introduction to Quantum Gravity and Spinfoam Theory", Cambridge University Press, Cambridge, (2014)