

Second-order coding rates for key distillation in quantum key distribution

Sumeet Khatri,¹ Eneet Kaur,¹ Saikat Guha,^{2,3} and Mark M. Wilde¹

¹*Hearne Institute for Theoretical Physics, Department of Physics and Astronomy,
and Center for Computation and Technology, Louisiana State University, Baton Rouge, Louisiana 70803, USA*

²*College of Optical Sciences, University of Arizona,
1630 E. University Blvd., Tucson, Arizona 85719, USA*

³*Department of Electrical and Computer Engineering, University of Arizona,
1230 E Speedway Blvd., Tucson, Arizona 85719, USA*

(Dated: January 4, 2022)

The security of quantum key distribution has traditionally been analyzed in either the asymptotic or non-asymptotic regimes. In this paper, we provide a bridge between these two regimes, by determining second-order coding rates for key distillation in quantum key distribution under collective attacks. Our main result is a formula that characterizes the backoff from the known asymptotic formula for key distillation—our formula incorporates the reliability and security of the protocol, as well as the mutual information variances to the legitimate receiver and the eavesdropper. In order to determine secure key rates against collective attacks, one should perform a joint optimization of the Holevo information and the Holevo information variance to the eavesdropper. We show how to do so by analyzing several examples, including the six-state, BB84, and continuous-variable quantum key distribution protocols (the last involving Gaussian modulation of coherent states along with heterodyne detection). The technical contributions of this paper include one-shot and second-order analyses of private communication over a compound quantum wiretap channel with fixed marginal and key distillation over a compound quantum wiretap source with fixed marginal. We also establish the second-order asymptotics of the smooth max-relative entropy of quantum states acting on a separable Hilbert space, and we derive a formula for the Holevo information variance of a Gaussian ensemble of Gaussian states.

CONTENTS

I. Introduction	2	A. One-shot setting	19
II. Second-order coding rates for key distillation in quantum key distribution	4	B. Secret key distillation via position-based coding and convex splitting	20
A. Generic prepare-and-measure QKD protocol	4	V. Second-order asymptotics of private communication and secret key distillation	21
1. Quantum part	4	VI. Discussion of collective attacks in QKD and the compound wiretap channel and source	22
2. Sifting	5	A. Remarks on the Devetak–Winter formula and security against collective attacks	24
3. Parameter estimation	6	VII. Other contributions	24
4. Key distillation	7	VIII. Conclusion	25
B. Examples	8	References	25
1. General setup for the six-state and BB84 DV-QKD protocols	8	A. Mutual and Holevo informations and variances for six-state and BB84 protocols	30
2. Six-state protocol	11	B. Relation between smooth max-mutual informations	33
3. BB84 DV-QKD protocol	12	C. Smooth universal convex split lemma for states acting on a separable Hilbert space	34
4. CV-QKD protocol with coherent states and heterodyne detection	13	D. Duality of smooth max-relative entropy	35
C. Routes to a full second-order analysis that includes parameter estimation	16	E. Relation between smooth max-relative entropy and hypothesis testing relative entropy	37
III. Private communication over a compound wiretap channel with fixed marginal	16	F. Second-order asymptotics of smooth	
A. One-shot setting	16		
B. Distinguishability and information measures	17		
C. Private communication via position-based coding and convex splitting	18		
IV. Secret key distillation from a compound quantum wiretap source with fixed marginal	19		

max-relative entropy for states acting on a separable Hilbert space	38
G. Mutual information variance and T quantity of classical–quantum states	39
H. Holevo information and Holevo information variance of a Gaussian ensemble of Gaussian states	40

I. INTRODUCTION

One of the near-term applications of quantum information science is quantum key distribution (QKD) [BB84, Eke91]. By making use of an insecure quantum channel and a public, authenticated classical channel, two parties can share an information-theoretically secure secret key, which can be used later on for one-time pad encryption of a private message. There has been significant progress on this topic in the decades since it was conceived [SBPC⁺09, Lüt14, LCT14, DLQY16, XMZ⁺19].

A critical challenge for this research area is to establish security proofs for quantum key distribution. In particular, we are interested in determining the maximum possible rates that are achievable in principle and guaranteed to be secure against any possible eavesdropper allowed by quantum mechanics. Security proofs have been developed for discrete-variable quantum key distribution (DV-QKD) protocols, both in the asymptotic [LC99, SP00, May01, RGK05, Koa06] and non-asymptotic regimes [Ren05, TLGR12, HT12, TL17]. There are also advanced numerical approaches for addressing the asymptotic security of DV-QKD protocols [CML16, WLC18]. Additionally, security proofs have been developed for continuous-variable quantum key distribution (CV-QKD) protocols [GG02a, GG02b], in the asymptotic [NGA06, GPC06, RC09] and non-asymptotic regimes [FFB⁺12, Fur14, Lev17]. Furthermore, security proofs have appeared for asymptotic security of discrete-modulation protocols for CV-QKD [ZHRL09, BW18, KGW19, GGDL19, LUL19].

In this work, we address the security of quantum key distribution in a regime that represents a bridge between the asymptotic and non-asymptotic regimes. Namely, we employ the methods of second-order asymptotics [Li14, TH13] in order to determine secure key rates for the key distillation step of a quantum key distribution protocol, under the assumption that an adversary applies a collective attack. Our development here covers both DV-QKD and CV-QKD protocols, due to various technical advances that we make in this paper. Second-order quantum information theory grew out of earlier developments in classical information theory [Hay09, PPV10], and it has since been explored extensively for various quantum communication tasks [TT15b, DL15, DTW16, WRG16, TBR16, WTB17, Will7a, OMW19]. The goal of a second-order information-theoretic analysis is to de-

termine the extra backoff from or overhead on the rates that are achievable in the asymptotic case, which are due to finite-size effects. In the context of quantum key distribution, the approach has been used for analyzing information reconciliation [TMMPE17], for proving upper bounds on secure key rates [WTB17, KW17], and to address the entropy accumulation problem in device-independent QKD [DF19]. See also [Hay06] for earlier work on this topic.

One contribution of our paper is that it is possible to evaluate distillable key rates in a regime that goes beyond a first-order asymptotic analysis, which is the typical case studied in several of the aforementioned works [LC99, SP00, May01, Koa06, CML16, WLC18, NGA06, GPC06, RC09, ZHRL09, BW18, KGW19, GGDL19, LUL19]. It has been found in several preceding information-theoretic contributions that a second-order analysis gives excellent agreement with what is actually achievable in the finite-size regime [Hay09, PPV10, TBR16, WTB17]. Thus, it is expected that our second-order analysis should agree well with secure distillable key rates that are achievable in principle in the finite-size regime.

To summarize our main contribution to QKD security analysis, suppose that \mathcal{S} is an “uncertainty set” indexing the states of the eavesdropper Eve that are consistent with the observed measurement results of the sender Alice and the receiver Bob. Let $p_{XY}(x, y)$ be the probability distribution estimated by Alice and Bob after the parameter estimation step of a QKD protocol [Nota]. For fixed $s \in \mathcal{S}$, let $\{p_{XY}(x, y), \rho_E^{x, y, s}\}_{x, y, s}$ be an ensemble of states that is consistent with the measurement results of Alice and Bob. Here we are assuming that Eve employs a collective attack, meaning that she applies the same quantum channel to every transmission of Alice. Then our contribution is that the following is the rate at which secret key bits can be generated in the key distillation step of a direct reconciliation protocol, for sufficiently large n , such that Bob’s decoding error probability is no larger than $\varepsilon_I \in (0, 1)$ and the security parameter of the key is no larger than $\varepsilon_{II} \in (0, 1)$:

$$I(X; Y) + \sqrt{\frac{1}{n} V(X; Y)} \Phi^{-1}(\varepsilon_I) - \sup_{s \in \mathcal{S}} \left[I(X; E)_s - \sqrt{\frac{1}{n} V(X; E)_s} \Phi^{-1}(\varepsilon_{II}^2) \right] + O\left(\frac{\log n}{n}\right), \quad (1)$$

where

$$\Phi^{-1}(\varepsilon) := \sup \{a \in \mathbb{R} \mid \Phi(a) \leq \varepsilon\}, \quad (2)$$

$$\Phi(a) := \frac{1}{\sqrt{2\pi}} \int_{-\infty}^a dx \exp\left(-\frac{x^2}{2}\right). \quad (3)$$

In the above, $I(X; Y)$ is the Alice–Bob mutual information, $V(X; Y)$ is the Alice–Bob mutual information variance, $I(X; E)_s$ is the Alice–Eve Holevo information for

fixed s , and $V(X; E)_s$ is the Alice–Eve Holevo information variance for fixed s . The first-order term is given by $I(X; Y) - \sup_{s \in \mathcal{S}} I(X; E)_s$, which is the standard information quantity considered in asymptotic security analyses (see, e.g., [Lüt14]). In such a first-order asymptotic analysis, the quantity $I(X; Y) - \sup_{s \in \mathcal{S}} I(X; E)_s$ is typically understood as the asymptotic rate at which an imperfect ensemble can be converted to a perfectly secure key. However, this conversion is only perfect in a precise sense in the asymptotic limit. What the mutual information variance $V(X; Y)$ and the Holevo information variance $V(X; E)_s$ characterize are the fluctuations about the first-order terms, which are due to finite-size effects, much like the variance of a random variable characterizes the speed of convergence toward the mean in the central-limit theorem [KS10, She11]. The second-order terms $\sqrt{\frac{1}{n} V(X; Y) \Phi^{-1}(\varepsilon_I)}$ and $\sqrt{\frac{1}{n} V(X; E)_s \Phi^{-1}(\varepsilon_{II}^2)}$ are negative for $\varepsilon_I, \varepsilon_{II}^2 < 1/2$, and thus they characterize the back-off from the asymptotic limit for sufficiently large, yet finite n . In Section II A 4, we define all of these information quantities formally and explain them in more detail.

For the key distillation step of a reverse reconciliation protocol, the key rate is given by

$$I(X; Y) + \sqrt{\frac{1}{n} V(X; Y) \Phi^{-1}(\varepsilon_I)} - \sup_{s \in \mathcal{S}} \left[I(Y; E)_s - \sqrt{\frac{1}{n} V(Y; E)_s \Phi^{-1}(\varepsilon_{II}^2)} \right] + O\left(\frac{\log n}{n}\right). \quad (4)$$

The information quantities appearing in the above formula and their interpretations are essentially the same as those given in (1), with the difference being the substitutions $I(X; E)_s \rightarrow I(Y; E)_s$ and $V(X; E)_s \rightarrow V(Y; E)_s$ to account for reverse reconciliation.

The formulas in (1) and (4) apply regardless of whether the variables X and Y are continuous or discrete, and whether the system E is finite- or infinite-dimensional. It is thus an advantage of our results that the expressions are given in terms of mutual informations and their variances rather than conditional entropies and their variances, as the former ones are well defined for infinite-dimensional systems (see the discussion in [LGG10, Section IV-B]). Furthermore, the above formulas apply whenever n is large enough so that $n \sim \max\{\varepsilon_I^{-2}, \varepsilon_{II}^{-2}\}$. However, as we stated above, in prior work, this kind of second-order approximation has given excellent agreement with actual finite-size achievability statements [Hay09, PPV10, TBR16, WTB17].

When performing the optimization given by

$$\sup_{s \in \mathcal{S}} \left[I(Y; E)_s - \sqrt{\frac{1}{n} V(Y; E)_s \Phi^{-1}(\varepsilon_{II}^2)} \right], \quad (5)$$

it is possible for large enough n to employ a perturbative approach, in which the first-order term $I(Y; E)_s$ is optimized first, and then among all of the ensembles achieving the optimum first-order term, one further optimizes the second-order term $-\sqrt{\frac{1}{n} V(Y; E)_s \Phi^{-1}(\varepsilon_{II}^2)}$. See [PPV10, Lemmas 63 and 64] for a justification of this approach.

In Section II, we evaluate achievable secure key rates for three standard QKD protocols: the six-state DV-QKD protocol [Bru98, BPG99], the BB84 DV-QKD protocol [BB84], and the CV-QKD protocol involving Gaussian-modulation coherent-state encodings along with heterodyne detection [GG02a, GG02b]. We find various analytical expressions for the achievable second-order coding rates, and we plot their performance in order to have a sense of what rates are achievable in principle.

We remark here that the contribution of our paper goes beyond the setting of quantum key distribution and applies more broadly in the context of private communication in quantum information theory. A starting point for our development is [Wil17a], but here our result applies more broadly to the scenario in which the Alice–Eve correlations are not precisely known but instead chosen from an “uncertainty set.” Furthermore, our results apply to the scenario in which the underlying quantum states act on an infinite-dimensional, separable Hilbert space (see [HZ12] for a review of this setting of quantum information theory). See Sections III and IV for a one-shot analysis and Section V for a second-order analysis. The information-theoretic setting that we consider here (secure communication against collective attacks) is strongly related to universal private communication and secret key distillation [DH10], as well as the compound wiretap channel and compound wiretap source settings [CCD12, BCCD14, BJ16]. We note here that the compound wiretap setting has been of considerable interest in classical information theory recently [SBP15].

As a side note, it is unclear to us from reading the literature whether researchers working on security analyses against collective attacks in QKD and those working on universal and compound information-theoretic secrecy questions are fully aware of each other, and so one byproduct of our work could be to develop more interaction between these communities. Related to this, the QKD security proof community has been consistently applying the Devetak–Winter formula [DW05] to analyze secret key rates for collective attacks in QKD, in spite of the fact that the Devetak–Winter protocol from [DW05] does not generally apply to such a scenario and instead only applies to a known, fixed attack. The results of our paper also clarify and bridge this gap, and we discuss all of these points in more detail in Section VI.

On a technical level, an important contribution of our paper is to determine the second-order asymptotics of the smooth max-relative entropy (see Appendix F), and this is the main reason why our security analysis applies to the infinite-dimensional case. This result also has impli-

cations for the distinguishability dilution task in the resource theory of asymmetric distinguishability [WW19]. We also extend some other known relations from the finite- to infinite-dimensional case (see Appendices B, C, D, and E). Combined with the second-order asymptotics of the hypothesis testing relative entropy for the infinite-dimensional case [DPR16, KW17, OMW19], we are then led to our claim concerning second-order coding rates for private communication, secret key distillation, and key distillation in quantum key distribution.

Another technical contribution of our paper is a formula for the Holevo information variance of a Gaussian ensemble of quantum Gaussian states (see Proposition 3 in Appendix H). This formula is useful in a second-order analysis of CV-QKD protocols, and we expect it to be useful in other contexts besides those considered here. We also derive a novel expression for the Holevo information of a Gaussian ensemble of quantum Gaussian states (see Proposition 3).

The rest of the paper proceeds as follows. We first consider the second-order analysis of the key distillation step of quantum key distribution in Section II, and therein we analyze the approach for the important examples mentioned above (six state, BB84, CV-QKD). After that, we then develop the information-theoretic compound wiretap settings and protocols and the corresponding secure rates in detail. In Section VI, we provide a historical discussion of the compound wiretap setting and collective attacks in quantum key distribution, with the stated goal of bridging the communities working on these related topics. We finally conclude in Section VIII with a summary and a list of open questions. The appendices provide details of various technical contributions that are useful for this work and might be of independent interest.

II. SECOND-ORDER CODING RATES FOR KEY DISTILLATION IN QUANTUM KEY DISTRIBUTION

We begin by presenting one of our main results, which is the application of the second-order coding rates in (1) and (4) to the key distillation step of a quantum key distribution protocol. The claim here rests upon the one-shot information-theoretic key distillation protocol from Section IV and its second-order expansion in Section V, the details of which are presented in these later sections. Here we first review a generic prepare-and-measure QKD protocol and then state how (1) and (4) apply in this context. We finally analyze the approach in the context of the six-state DV-QKD protocol [Bru98, BPG99], the BB84 DV-QKD protocol [BB84], and the reverse-reconciliation CV-QKD protocol [GG02b]. All source code files needed to generate the plots in this section are available as ancillary files with the arXiv posting of this paper.

We should clarify that our main emphasis, as indicated above, is on the key distillation step of a quantum key

distribution protocol and how to incorporate a second-order coding rate analysis. As part of this, we are assuming that the parameter estimation step of a QKD protocol yields reliable estimates of the classical channel from Alice to Bob that is induced by the quantum part of the QKD protocol. We expand more upon this point in what follows, and we note up front here that it is an open question to incorporate a full second-order analysis that includes the parameter estimation step in addition to the key distillation step.

A. Generic prepare-and-measure QKD protocol

Let us recall the structure of a generic prepare-and-measure protocol for quantum key distribution, in which the adversary applies a collective attack. The protocol consists of three steps: a quantum part, parameter estimation, and key distillation (the last combines information reconciliation and privacy amplification into a single step). We consider both direct and reverse reconciliation settings for key distillation.

1. Quantum part

The quantum part of the protocol consists of the following steps:

1. It begins with the sender Alice picking a state ρ_A^x randomly from an ensemble

$$\mathcal{E}_A := \{p_X(x), \rho_A^x\}_{x \in \mathcal{X}}, \quad (6)$$

where p_X is a probability distribution and each state ρ_A^x is described by a density operator acting on an input Hilbert space \mathcal{H}_A .

2. Alice transmits the system A through an unknown quantum channel $\mathcal{N}_{A \rightarrow B}$, with input system A and output system B . It is assumed that the channel itself is controlled by the eavesdropper Eve, and the output system B is given to the legitimate receiver Bob. It is a standard feature of quantum information that every quantum channel has an isometric extension [Sti55] (see also, e.g., [Wil17b]), from which the original channel can be realized by a partial trace over an environment system. Thus, there exists an isometric channel $\mathcal{U}_{A \rightarrow BE}^{\mathcal{N}}$ extending the channel $\mathcal{N}_{A \rightarrow B}$ such that

$$\mathcal{N}_{A \rightarrow B} = \text{Tr}_E \circ \mathcal{U}_{A \rightarrow BE}^{\mathcal{N}}. \quad (7)$$

In the worst-case scenario, the eavesdropper has full access to the environment system E , and so we assume that she does (as is standard in QKD security proof analyses).

3. Upon receiving the system B , the receiver Bob performs a measurement channel $\mathcal{M}_{B \rightarrow Y}$, which

is uniquely specified by a positive operator-valued measure (POVM) $\{\Lambda_B^y\}_{y \in \mathcal{Y}}$, such that

$$\Lambda_B^y \geq 0 \quad \forall y \in \mathcal{Y}, \quad \sum_{y \in \mathcal{Y}} \Lambda_B^y = I_B. \quad (8)$$

According to the Born rule, the measurement channel $\mathcal{M}_{B \rightarrow Y}$ gives the outcome y with probability $\text{Tr}[\Lambda_B^y \omega_B]$ if the input state is ω_B .

One round of this protocol leads to the following ensemble:

$$\begin{aligned} \mathcal{E}_{\text{QKD}} &:= \mathcal{E}_{\text{QKD}}(\mathcal{E}_A, \mathcal{U}_{A \rightarrow BE}^{\mathcal{N}}, \mathcal{M}_{B \rightarrow Y}) \\ &:= \{p_{XY}(x, y), \rho_E^{x, y}\}_{x \in \mathcal{X}, y \in \mathcal{Y}}, \end{aligned} \quad (9)$$

$$(10)$$

where the joint distribution $p_{XY}(x, y)$ is given as

$$p_{XY}(x, y) = p_X(x) p_{Y|X}(y|x), \quad (11)$$

$$p_{Y|X}(y|x) := \text{Tr}[\Lambda_B^y \mathcal{N}_{A \rightarrow B}(\rho_A^x)], \quad (12)$$

and the eavesdropper states $\rho_E^{x, y}$ are as follows:

$$\rho_E^{x, y} := \frac{\text{Tr}_B[\Lambda_B^y \mathcal{U}_{A \rightarrow BE}^{\mathcal{N}}(\rho_A^x)]}{p_{Y|X}(y|x)}. \quad (13)$$

Observe how the protocol induces a classical channel $p_{Y|X}(y|x)$ from Alice to Bob via the Born rule in (12).

The above steps are repeated $m = k + n$ times, where k is the number of rounds used for parameter estimation and n is the number of rounds used for key distillation. The ensemble shared between Alice, Bob, and Eve after these m rounds is as follows:

$$\mathcal{E}_{\text{QKD}}^{\otimes m} := \mathcal{E}_{\text{QKD}}^{\otimes m}(\mathcal{E}_A^{\otimes m}, (\mathcal{U}_{A \rightarrow BE}^{\mathcal{N}})^{\otimes m}, (\mathcal{M}_{B \rightarrow Y})^{\otimes m}) \quad (14)$$

$$:= \left\{ p_{X^m Y^m}(x^m, y^m), \rho_{E^m}^{x^m, y^m} \right\}_{x^m \in \mathcal{X}^m, y^m \in \mathcal{Y}^m}, \quad (15)$$

where

$$p_{X^m Y^m}(x^m, y^m) := \prod_{i=1}^m p_{X_i Y_i}(x_i, y_i), \quad (16)$$

$$\rho_{E^m}^{x^m, y^m} := \rho_{E_1}^{x_1, y_1} \otimes \dots \otimes \rho_{E_m}^{x_m, y_m}, \quad (17)$$

$$\rho_{E_i}^{x_i, y_i} := \frac{\text{Tr}_{B_i}[\Lambda_{B_i}^{y_i} \mathcal{U}_{A_i \rightarrow B_i E_i}^{\mathcal{N}}(\rho_{A_i}^{x_i})]}{p_{Y_i|X_i}(y_i|x_i)}, \quad (18)$$

$$p_{Y_i|X_i}(y_i|x_i) := \text{Tr}[\Lambda_{B_i}^{y_i} \mathcal{N}_{A_i \rightarrow B_i}(\rho_{A_i}^{x_i})]. \quad (19)$$

A critical assumption that we make in the above is that Eve employs a *collective attack*, meaning that the isometric channel she applies over the m rounds is the tensor-power channel $(\mathcal{U}_{A \rightarrow BE}^{\mathcal{N}})^{\otimes m}$.

a. Channel twirling In order to simplify or symmetrize the collective attacks that need to be considered, Alice and Bob can employ an additional symmetrization of the protocol in each round, called channel twirling, introduced in a different context in [BDSW96]. Let

$\{U_A^g\}_{g \in \mathcal{G}}$ and $\{V_B^g\}_{g \in \mathcal{G}}$ be unitary representations of a group \mathcal{G} , such that the unitaries act on the input Hilbert space \mathcal{H}_A and output Hilbert space \mathcal{H}_B , respectively. Then before sending out her state ρ_A^x , Alice can select g uniformly at random from the group \mathcal{G} , apply the unitary U_A^g to her state, communicate the value of g over a public classical communication channel to Bob, who then performs $V_B^{g^\dagger}$ on his system before acting with his measurement. If Alice and Bob then discard the value of g , this twirling procedure transforms the original quantum channel $\mathcal{N}_{A \rightarrow B}$ to the following symmetrized quantum channel:

$$\bar{\mathcal{N}}_{A \rightarrow B}(\omega_A) := \frac{1}{|\mathcal{G}|} \sum_{g \in \mathcal{G}} (\mathcal{V}_A^{g^\dagger} \circ \mathcal{N}_{A \rightarrow B} \circ \mathcal{U}_A^g)(\omega_A), \quad (20)$$

where

$$\mathcal{U}_A^g(\cdot) := U_A^g(\cdot) U_A^{g^\dagger}, \quad \mathcal{V}_B^g(\cdot) := V_B^g(\cdot) V_B^{g^\dagger}. \quad (21)$$

Although channel twirling produces a worse (noisier) channel from the original one, the main benefit is that the number of parameters that are needed to specify $\bar{\mathcal{N}}_{A \rightarrow B}$ can be far fewer than the number needed to specify $\mathcal{N}_{A \rightarrow B}$. For example, if the original channel $\mathcal{N}_{A \rightarrow B}$ is a qubit channel and the unitaries consist of the Pauli operators, then the resulting twirled channel is a Pauli channel and thus specified by only three parameters. If the original channel $\mathcal{N}_{A \rightarrow B}$ is a single-mode bosonic channel and the unitaries consist of the four equally spaced phase rotations $\{0, \pi/2, \pi, 3\pi/2\}$, then the resulting channel is a phase covariant (phase insensitive) channel [KGW19] and has fewer parameters that characterize it.

b. Finite-dimensional assumptions In the trusted device scenario that we are dealing with here, if the Hilbert space \mathcal{H}_A is finite dimensional, then we are making an implicit assumption that the union of the supports of the states ρ_A^x are fully contained in the Hilbert space \mathcal{H}_A and there is no leakage outside of it. In the case that system B is finite dimensional (i.e., the Hilbert space \mathcal{H}_B is finite dimensional), then we are making an implicit assumption that the measurement operators $\{\Lambda_B^y\}_{y \in \mathcal{Y}}$ satisfy $\sum_{y \in \mathcal{Y}} \Lambda_B^y = I_B$ and that I_B is indeed the identity operator for \mathcal{H}_B . Thus, if both the input and output Hilbert spaces \mathcal{H}_A and \mathcal{H}_B are finite dimensional, then by the Choi–Kraus theorem (see, e.g., [Wil17b]), it is not necessary for Eve’s system to be any larger than $\dim(\mathcal{H}_A) \cdot \dim(\mathcal{H}_B)$. So it follows that the finite dimensional assumption leads to strong constraints about Eve’s attack, which may not necessarily hold in practice and thus should be stated up front. This is especially the case when dealing with photonic states and measurements acting on subspaces of an infinite-dimensional bosonic Fock space.

2. Sifting

Some QKD protocols, such as the six-state and BB84 protocols, incorporate a sifting step, in which a fraction

of the data generated by the protocol is discarded. The main reason for incorporating sifting is that some input-output pairs in $\mathcal{X} \times \mathcal{Y}$ do not give any useful information about the channel (Eve's attack) and thus can be discarded. For example, if the input state is $|0\rangle\langle 0|$ or $|1\rangle\langle 1|$ and Bob measures in the basis $\{|+\rangle\langle +|, |-\rangle\langle -|\}$, then even in the noiseless case of no eavesdropping, the outcome of the measurement is independent of the input and thus yields no useful information.

This sifting step can be described mathematically as a filter onto a subset $\mathcal{F} \subseteq \mathcal{X} \times \mathcal{Y}$, with the sifting probability given by

$$p_{\text{sift}} := \sum_{(x,y) \in \mathcal{F}} p_{XY}(x,y), \quad (22)$$

and the conditioned ensemble by

$$\mathcal{E}_{\text{QKD}}^{\text{sift}} := \{p'_{XY}(x,y), \rho_E^{x,y}\}_{(x,y) \in \mathcal{F}}, \quad (23)$$

where

$$p'_{XY}(x,y) := p_{XY}(x,y)/p_{\text{sift}}. \quad (24)$$

As a consequence of sifting, some number m' of the original m rounds are selected, and the remaining systems of Alice, Bob, and Eve are described by the tensor-power ensemble:

$$(\mathcal{E}_{\text{QKD}}^{\text{sift}})^{\otimes m'} := \left\{ p'_{X^{m'}Y^{m'}}(x^{m'}, y^{m'}), \rho_{E^{m'}}^{x^{m'}, y^{m'}} \right\}_{(x^{m'}, y^{m'}) \in \mathcal{F}^{m'}}, \quad (25)$$

with the above quantities defined similarly as in (14)–(19).

In the discussion that follows in Section II A 3, we simply relabel m' as m and the distribution $p'_{XY}(x,y)$ as $p_{XY}(x,y)$, with it understood that elements of $p_{XY}(x,y)$ with (x,y) outside of \mathcal{F} are set to zero. The distribution p_X is the marginal of p_{XY} , and the conditional distribution $p_{Y|X}$ is a classical channel computed from p_{XY} as usual via $p_{Y|X}(y|x)/p_X(x)$.

3. Parameter estimation

After m rounds of the protocol are complete, k of the XY classical systems are randomly selected by Alice and Bob for parameter estimation, in order to estimate the set \mathcal{S} of possible collective attacks of Eve. To be clear, the classical systems used for parameter estimation are $X_{i_1}, Y_{i_1}, \dots, X_{i_k}, Y_{i_k}$ for some randomly selected (without replacement) $i_1, \dots, i_k \in \{1, \dots, n\}$.

In what follows, we assume that k is large enough such that Alice and Bob get a very reliable (essentially exact) estimate of the classical channel $p_{Y|X}(y|x)$. This assumption is strong, but as stated above, our main focus in this paper is on analyzing second-order coding rates in

the key distillation step of the quantum key distribution protocol. In Section II C, we discuss various routes for addressing this problem.

The goal of the parameter estimation step is to estimate the classical channel $p_{Y|X}(y|x)$ reliably in order to produce an estimate of the unknown quantum channel $\mathcal{N}_{A \rightarrow B}$ connecting Alice and Bob. Doing so then allows them to estimate the isometric channel $\mathcal{U}_{A \rightarrow BE}^{\mathcal{N}}$, up to an information theoretically irrelevant isometry acting on the system E . In more detail, note that any other isometric extension of the original channel $\mathcal{N}_{A \rightarrow B}$ is related to $\mathcal{U}_{A \rightarrow BE}^{\mathcal{N}}$ by an isometric channel acting on the system E . That is, suppose that $\mathcal{V}_{A \rightarrow BE'}^{\mathcal{N}}$ is another isometric channel satisfying $\mathcal{N}_{A \rightarrow B} = \text{Tr}_{E'} \circ \mathcal{V}_{A \rightarrow BE'}^{\mathcal{N}}$. Then there exists an isometric channel $\mathcal{W}_{E \rightarrow E'}$ such that $\mathcal{V}_{A \rightarrow BE'}^{\mathcal{N}} = \mathcal{W}_{E \rightarrow E'} \circ \mathcal{U}_{A \rightarrow BE}^{\mathcal{N}}$ [Wil17b]. However, Eve's information about the classical systems X and Y is the same regardless of which particular isometric extension is considered. Thus, as stated above, the goal of the parameter estimation step is to estimate the channel $\mathcal{N}_{A \rightarrow B}$ by employing the estimate of $p_{Y|X}(y|x)$.

As a result of the parameter estimation step, Alice and Bob determine an uncertainty set \mathcal{S} , each element s of which indexes a quantum channel $\mathcal{N}_{A \rightarrow B}^s$ that is consistent with the classical channel $p_{Y|X}(y|x)$, in the sense that

$$p_{Y|X}(y|x) = \text{Tr}[\Lambda_B^y \mathcal{N}_{A \rightarrow B}^s(\rho_A^x)], \quad (26)$$

for all $s \in \mathcal{S}$, $x \in \mathcal{X}$, and $y \in \mathcal{Y}$. It is generally not possible to determine the actual quantum channel $\mathcal{N}_{A \rightarrow B}$ exactly, so that $|\mathcal{S}| > 1$. However, if the input ensemble $\mathcal{E}_A = \{p_X(x), \rho_A^x\}_{x \in \mathcal{X}}$ and the POVM $\{\Lambda_B^y\}_{y \in \mathcal{Y}}$ form a tomographically complete set [CN97, PCZ97], then it is possible to determine an exact estimate of the actual, unknown quantum channel $\mathcal{N}_{A \rightarrow B}$ from the classical channel $p_{Y|X}(y|x)$. That is, in the tomographically complete case, there exists an invertible linear map relating $p_{Y|X}(y|x)$ and $\mathcal{N}_{A \rightarrow B}$. So in this special case, there is a unique quantum channel $\mathcal{N}_{A \rightarrow B}$ corresponding to the classical channel $p_{Y|X}(y|x)$.

In some parameter estimation protocols, Alice and Bob do not estimate the entries of $p_{Y|X}(y|x)$ for all $x \in \mathcal{X}$ and $y \in \mathcal{Y}$, but they instead do so for a subset of $\mathcal{X} \times \mathcal{Y}$ (for example as a consequence of sifting). Furthermore, they could reduce the number of parameters that need to be estimated by employing additional symmetrization of $p_{Y|X}(y|x)$, in which some of the entries are averaged or simple functions of them are computed. These latter approaches are commonly employed in the parameter estimation phase of the BB84 and six-state protocols, in which quantum bit error rates (QBERs) are estimated in lieu of all entries of $p_{Y|X}(y|x)$. Another example for which the full $p_{Y|X}(y|x)$ is not typically estimated is CV-QKD, where only two scalar parameters are estimated in order to derive a key-rate lower bound under a collective-attack assumption, even in a finite key-length regime [Lev15].

4. Key distillation

After the parameter estimation step, the ensemble characterizing each of the n remaining systems shared by Alice, Bob, and Eve is as follows:

$$\mathcal{E}_{\text{QKD}}^s := \{p_{XY}(x, y), \rho_E^{x, y, s}\}_{x \in \mathcal{X}, y \in \mathcal{Y}, s \in \mathcal{S}}, \quad (27)$$

where

$$p_{XY}(x, y) = p_X(x)p_{Y|X}(y|x), \quad (28)$$

$$p_{Y|X}(y|x) := \text{Tr}[\Lambda_B^y \mathcal{N}_{A \rightarrow B}^s(\rho_A^x)], \quad (29)$$

and the eavesdropper states $\rho_E^{x, y, s}$ are as follows:

$$\rho_E^{x, y, s} := \frac{\text{Tr}_B[\Lambda_B^y \mathcal{U}_{A \rightarrow BE}^{s, \mathcal{N}^s}(\rho_A^x)]}{p_{Y|X}(y|x)}. \quad (30)$$

The full ensemble for the n remaining systems is an n -fold tensor power of the above, similar to that given in (14)–(19), except with the substitutions $m \rightarrow n$ and $\mathcal{N} \rightarrow \mathcal{N}^s$. Note that the classical channel $p_{Y|X}(y|x)$ is known and independent of s , due to our assumption of a collective attack and that k is large enough so that Alice and Bob can estimate $p_{Y|X}(y|x)$ reliably. That is, there could be many quantum channels $\mathcal{N}_{A \rightarrow B}^s$ that lead to the same classical channel $p_{Y|X}(y|x)$ if the input preparation and the output measurements are not tomographically complete. Furthermore, the distribution $p_X(x)$ is known because Alice controls the random selection of the states $\{\rho_A^x\}_{x \in \mathcal{X}}$.

The ensemble in (27) is then a particular instance of the information-theoretic model presented later on in Section IV. Specifically, the ensemble in (27) is an instance of the compound wiretap source with fixed marginal from (211), in which the system B in (211) is in correspondence with the classical system Y in (27). As a result, we can apply (251) (itself a consequence of Theorem 6) to conclude that the following rate is achievable for key distillation for the remaining n rounds, by using direct reconciliation:

$$\begin{aligned} & I(X; Y)_{\mathcal{E}^s} + \sqrt{\frac{1}{n} V(X; Y)_{\mathcal{E}^s} \Phi^{-1}(\varepsilon_I)} \\ & - \sup_{s \in \mathcal{S}} \left[I(X; E)_{\mathcal{E}^s} - \sqrt{\frac{1}{n} V(X; E)_{\mathcal{E}^s} \Phi^{-1}(\varepsilon_{\text{II}}^2)} \right] \\ & + O\left(\frac{\log n}{n}\right), \quad (31) \end{aligned}$$

for sufficiently large n and with decoding error probability not larger than ε_I and security parameter not larger than ε_{II} (these latter two quantities are defined in Section IV A). In the above, the first two terms depend on the probability distribution p_{XY} in (27), but they have no dependence on s . The inverse cumulative Gaussian distribution function $\Phi^{-1}(\cdot)$ is defined in (2). The clas-

sical mutual information is defined as

$$I(X; Y)_{\mathcal{E}^s} := \sum_{x \in \mathcal{X}, y \in \mathcal{Y}} p_{XY}(x, y) \log_2 \left(\frac{p_{XY}(x, y)}{p_X(x)p_Y(y)} \right), \quad (32)$$

the classical mutual information variance as [Str62, Hay09, PPV10]

$$\begin{aligned} V(X; Y)_{\mathcal{E}^s} &:= \\ & \sum_{x \in \mathcal{X}, y \in \mathcal{Y}} p_{XY}(x, y) \left[\log_2 \left(\frac{p_{XY}(x, y)}{p_X(x)p_Y(y)} \right) - I(X; Y)_{\mathcal{E}^s} \right]^2, \end{aligned} \quad (33)$$

the Holevo information as [Hol73]

$$I(X; E)_{\mathcal{E}^s} := \sum_{x \in \mathcal{X}} p_X(x) D(\rho_E^{x, s} \| \rho_E^s), \quad (34)$$

and the Holevo information variance as

$$\begin{aligned} V(X; E)_{\mathcal{E}^s} &:= \\ & \sum_{x \in \mathcal{X}} p_X(x) \left[V(\rho_E^{x, s} \| \rho_E^s) + [D(\rho_E^{x, s} \| \rho_E^s)]^2 \right] - [I(X; E)_{\mathcal{E}^s}]^2, \end{aligned} \quad (35)$$

where

$$\rho_E^{x, s} := \sum_{y \in \mathcal{Y}} p_{Y|X}(y|x) \rho_E^{x, y, s}, \quad (36)$$

$$\rho_E^s := \sum_{x \in \mathcal{X}} p_X(x) \rho_E^{x, s}. \quad (37)$$

The quantum relative entropy of states ω and τ is defined as [Ume62]

$$D(\omega \| \tau) := \text{Tr}[\omega (\log_2 \omega - \log_2 \tau)], \quad (38)$$

and the quantum relative entropy variance as [Li14, TH13]

$$V(\omega \| \tau) := \text{Tr}[\omega (\log_2 \omega - \log_2 \tau - D(\omega \| \tau))^2]. \quad (39)$$

These quantities are defined more generally in (248)–(249) for states acting on separable Hilbert spaces. If either alphabet \mathcal{X} or \mathcal{Y} is continuous, then the corresponding sum is replaced with an integral.

If Alice and Bob employ reverse reconciliation instead for key distillation, then the following distillable key rate is achievable:

$$\begin{aligned} & I(X; Y)_{\mathcal{E}^s} + \sqrt{\frac{1}{n} V(X; Y)_{\mathcal{E}^s} \Phi^{-1}(\varepsilon_I)} \\ & - \sup_{s \in \mathcal{S}} \left[I(Y; E)_{\mathcal{E}^s} - \sqrt{\frac{1}{n} V(Y; E)_{\mathcal{E}^s} \Phi^{-1}(\varepsilon_{\text{II}}^2)} \right] \\ & + O\left(\frac{\log n}{n}\right), \quad (40) \end{aligned}$$

with the Holevo information defined as

$$I(Y; E)_{\mathcal{E}^s} := \sum_{y \in \mathcal{Y}} p_Y(y) D(\rho_E^{y,s} \| \rho_E^s), \quad (41)$$

and the Holevo information variance as

$$V(Y; E)_{\mathcal{E}^s} := \sum_{y \in \mathcal{Y}} p_Y(y) \left[V(\rho_E^{y,s} \| \rho_E^s) + [D(\rho_E^{y,s} \| \rho_E^s)]^2 \right] - [I(Y; E)_{\mathcal{E}^s}]^2, \quad (42)$$

where

$$\rho_E^{y,s} := \sum_{x \in \mathcal{X}} p_{X|Y}(x|y) \rho_E^{x,y,s}. \quad (43)$$

Remark 1 We emphasize that the formulas in (31) and (40) represent the number of secret key bits per sifted bit. If we include all of the rounds of the protocol as part of the key rate, then the formulas in (31) and (40) must be multiplied by the fraction of bits used for sifting; see, e.g., [TL17, Eq. (121)].

a. On reconciliation efficiency and privacy amplification overhead It is common in the key distillation step of a first-order asymptotic analysis to incorporate a reconciliation efficiency parameter $\beta \in [0, 1]$, which recognizes the fact that it is never possible in any realistic scheme to achieve the Shannon limit $I(X; Y)_{\mathcal{E}^s}$. That is, the information reconciliation rate is written as $\beta I(X; Y)_{\mathcal{E}^s}$. Typically, the reconciliation efficiency β is chosen as a constant independent of the channel, the blocklength n , and the decoding error probability ε_I . As argued in [TMMPE17], this approximation is rather rough, and one can instead employ a second-order analysis to get a much better approximation of the reconciliation efficiency. What we find from (31) and (40) is that the ideal reconciliation efficiency is characterized in terms of p_{XY} , n , and ε_I as follows:

$$\beta(p_{XY}, n, \varepsilon_I) := 1 + \frac{\sqrt{\frac{1}{n} V(X; Y)_{\mathcal{E}^s} \Phi^{-1}(\varepsilon_I)}}{I(X; Y)_{\mathcal{E}^s}}, \quad (44)$$

so that

$$\begin{aligned} \beta(p_{XY}, n, \varepsilon_I) I(X; Y)_{\mathcal{E}^s} \\ = I(X; Y)_{\mathcal{E}^s} + \sqrt{\frac{1}{n} V(X; Y)_{\mathcal{E}^s} \Phi^{-1}(\varepsilon_I)}. \end{aligned} \quad (45)$$

(Keep in mind that $\Phi^{-1}(\varepsilon_I) < 0$ for $\varepsilon_I < 1/2$.) One can also find very good fits of the information reconciliation performance for actual codes by allowing for constants β_1 and β_2 , each not necessarily equal to one, to characterize the reconciliation efficiency empirically as follows [TMMPE17]:

$$\beta(p_{XY}, n, \varepsilon_I, \beta_1, \beta_2) := \beta_1 + \beta_2 \frac{\sqrt{\frac{1}{n} V(X; Y)_{\mathcal{E}^s} \Phi^{-1}(\varepsilon_I)}}{I(X; Y)_{\mathcal{E}^s}}. \quad (46)$$

Thus, the formula above is a more useful guideline for reconciliation efficiency.

What we also notice in (31) and (40) is the presence of terms related to privacy amplification overhead. Privacy amplification overhead beyond the term $\sup_{s \in \mathcal{S}} I(Y; E)_{\mathcal{E}^s}$ is not typically taken into account in first-order asymptotic security analyses, in spite of the fact that other factors are inevitably necessary. To be clear, the privacy amplification overhead is a factor $\gamma > 1$ that multiplies the asymptotic, first-order term $\sup_{s \in \mathcal{S}} I(Y; E)_{\mathcal{E}^s}$. By employing [PPV10, Lemma 63], the following expansion in n holds for direct-reconciliation privacy amplification for sufficiently large n :

$$\sup_{s \in \mathcal{S}} [I(X; E)_{\mathcal{E}^s}] - \sqrt{\frac{1}{n} V(X, \mathcal{S}^*) \Phi^{-1}(\varepsilon_{II}^2)} + o(1/\sqrt{n}), \quad (47)$$

where

$$V(X, \mathcal{S}^*) := \begin{cases} \sup_{s \in \mathcal{S}^*} V(X; E)_{\mathcal{E}^s} & \text{if } \varepsilon_{II}^2 \leq \frac{1}{2} \\ \inf_{s \in \mathcal{S}^*} V(X; E)_{\mathcal{E}^s} & \text{else} \end{cases}, \quad (48)$$

$$\mathcal{S}^* := \arg \max_{s \in \mathcal{S}} I(X; E)_{\mathcal{E}^s}. \quad (49)$$

In the above, we are applying the perturbative approach of [PPV10, Lemma 63], in which we optimize the first-order term $I(X; E)_{\mathcal{E}^s}$, and then among all of the optimizers of this first-order term, we are optimizing the second-order term $V(X; E)_{\mathcal{E}^s}$. Thus, the ideal privacy amplification overhead is given by

$$\gamma(\mathcal{S}, n, \varepsilon_{II}) := 1 - \frac{\sqrt{\frac{1}{n} V(X, \mathcal{S}^*) \Phi^{-1}(\varepsilon_{II}^2)}}{\sup_{s \in \mathcal{S}} [I(X; E)_{\mathcal{E}^s}]}, \quad (50)$$

so that

$$\begin{aligned} \gamma(\mathcal{S}, n, \varepsilon_{II}) \sup_{s \in \mathcal{S}} [I(X; E)_{\mathcal{E}^s}] = \\ \sup_{s \in \mathcal{S}} [I(X; E)_{\mathcal{E}^s}] - \sqrt{\frac{1}{n} V(X, \mathcal{S}^*) \Phi^{-1}(\varepsilon_{II}^2)}. \end{aligned} \quad (51)$$

As above, we could also allow for a more refined expression as follows, in terms of constants γ_1 and γ_2 , in order to fit the performance of realistic privacy amplification protocols:

$$\gamma(\mathcal{S}, n, \varepsilon_{II}, \gamma_1, \gamma_2) := \gamma_1 - \gamma_2 \frac{\sqrt{\frac{1}{n} V(X, \mathcal{S}^*) \Phi^{-1}(\varepsilon_{II}^2)}}{\sup_{s \in \mathcal{S}} [I(X; E)_{\mathcal{E}^s}]}. \quad (52)$$

B. Examples

1. General setup for the six-state and BB84 DV-QKD protocols

We begin this example section by providing the general setup for both the ideal, trusted six-state [Bru98, BPG99]

and BB84 [BB84] DV-QKD protocols, which are particular instances of the generic prepare-and-measure protocol presented in Section II A.

In both of these protocols, the random variable X for Alice's encoding is a joint random variable consisting of random variables X_1 and X_2 , where X_1 represents Alice's basis choice, and X_2 is the binary random variable corresponding to the state taken from the chosen basis. The random variables X_1 and X_2 are independent. We similarly have that the output random variable Y for Bob is a joint random variable consisting of random variables Y_1 and Y_2 , where Y_1 represents the choice of measurement basis, and Y_2 represents the outcome of the measurement.

Let the alphabet \mathcal{B} contain the possible basis choices. The random variables X_1 and Y_1 take values in \mathcal{B} . For the six-state protocol, $\mathcal{B}_{\text{six-state}} = \{0, 1, 2\}$, with "0" denoting the X -basis, "1" the Z -basis, and "2" the Y -basis. For the BB84 protocol, $\mathcal{B}_{\text{BB84}} = \{0, 1\}$. Then, let q_b^A and q_b^B be the probabilities that Alice and Bob, respectively, choose the basis $b \in \mathcal{B}$. In other words,

$$q_b^A := \Pr[X_1 = b], \quad q_b^B := \Pr[Y_1 = b]. \quad (53)$$

Let us define the following:

$$\Pi_0^0 := |+\rangle\langle+| \equiv \rho_A^{0,0}, \quad (54)$$

$$\Pi_1^0 := |-\rangle\langle-| \equiv \rho_A^{0,1}, \quad (55)$$

$$\Pi_0^1 := |0\rangle\langle 0| \equiv \rho_A^{1,0}, \quad (56)$$

$$\Pi_1^1 := |1\rangle\langle 1| \equiv \rho_A^{1,1}, \quad (57)$$

$$\Pi_0^2 := |+\rangle\langle+| \equiv \rho_A^{2,0}, \quad (58)$$

$$\Pi_1^2 := |-\rangle\langle-| \equiv \rho_A^{2,1}, \quad (59)$$

where

$$|+\rangle := (|0\rangle + |1\rangle)/\sqrt{2}, \quad (60)$$

$$|-\rangle := (|0\rangle - |1\rangle)/\sqrt{2}, \quad (61)$$

$$|+i\rangle := (|0\rangle + i|1\rangle)/\sqrt{2}, \quad (62)$$

$$|-i\rangle := (|0\rangle - i|1\rangle)/\sqrt{2}, \quad (63)$$

Now, Alice chooses the basis $b_A \in \mathcal{B}$ with probability $q_{b_A}^A$, and with probability $\frac{1}{2}$ chooses one of the two states $\{\rho_A^{b_A,0}, \rho_A^{b_A,1}\}$ in the basis to send to Bob. These choices are independent, and so we have that

$$p_{X_1 X_2}(b_A, x) = q_{b_A}^A \cdot \frac{1}{2}. \quad (64)$$

The encoding ensemble \mathcal{E}_A is thus

$$\mathcal{E}_A := \{p_{X_1 X_2}(b_A, x), \rho_A^{b_A, x}\}_{b_A \in \mathcal{B}, x \in \{0,1\}}. \quad (65)$$

The decoding POVM for Bob is

$$\{q_{b_B}^B \Pi_y^{b_B}\}_{b_B \in \mathcal{B}, y \in \{0,1\}}, \quad (66)$$

which is equivalent to Bob picking the basis b_B at random according to $q_{b_B}^B$ and then performing the measurement $\{\Pi_0^{b_B}, \Pi_1^{b_B}\}$.

The protocol is finite dimensional, meaning that the assumptions stated in Section II A 1 b, come into play. Thus, the attack $\mathcal{N}_{A \rightarrow B}$ that Eve applies is a qubit channel.

The channel twirling that Alice and Bob perform in this case is a Pauli channel twirl [BDSW96]. That is, before sending out her state, Alice applies, uniformly at random, one of the Pauli operators I , X , Y , or Z and Bob applies the corresponding Pauli after receiving the state from the channel. Thus, both $\{U_A^g\}_{g \in \mathcal{G}}$ and $\{V_B^g\}_{g \in \mathcal{G}}$, as discussed in Section II A 1 a, are the Pauli group $\{I, X, Y, Z\}$. Then the resulting twirled channel is as given in (20), and it is well known that a Pauli twirl of a qubit channel leads to a Pauli channel [DHC05]:

$$\overline{\mathcal{N}}_{A \rightarrow B}(\omega_A) = p_I \omega_A + p_X X \omega_A X + p_Y Y \omega_A Y + p_Z Z \omega_A Z, \quad (67)$$

where $p_I, p_X, p_Y, p_Z \geq 0$ and $p_I + p_X + p_Y + p_Z = 1$.

Note that it is not necessary for Alice and Bob to apply the Pauli channel twirl in an active way in the quantum domain. Since the encoding ensemble in (65) is invariant with respect to the Pauli group (for both the six-state and BB84 protocols), Alice can keep track of the twirl in classical processing. Similarly, the decoding POVM of Bob in (66) is invariant with respect to the Pauli group, so that Bob can keep track of the twirl in classical processing.

At the end of the quantum part of the protocol, the induced classical channel is as follows

$$p_{Y_1 Y_2 | X_1 X_2}(b_B, y | b_A, x) = q_{b_B}^B \text{Tr}[\Pi_y^{b_B} \overline{\mathcal{N}}_{A \rightarrow B}(\rho_A^{b_A, x})]. \quad (68)$$

The joint probability distribution shared by Alice and Bob is then as follows:

$$p_{X_1 X_2 Y_1 Y_2}(b_A, x, b_B, y) = p_{Y_1 Y_2 | X_1 X_2}(b_B, y | b_A, x) p_{X_1 X_2}(b_A, x) \quad (69)$$

$$= \frac{1}{2} q_{b_A}^A q_{b_B}^B \text{Tr}[\Pi_y^{b_B} \overline{\mathcal{N}}_{A \rightarrow B}(\rho_A^{b_A, x})]. \quad (70)$$

Both the six-state and BB84 protocols involve a sifting step, as discussed in Section II A 2. Only the data are kept for which the sender and receiver's basis bits agree. The probability that Alice and Bob choose the same basis is given by

$$p_{\text{sift}} := \sum_{b \in \mathcal{B}} q_b^A q_b^B \quad (71)$$

The resulting probability distribution shared by Alice and Bob is

$$p_{X_1 X_2 Y_1 Y_2}^{\text{sift}}(b, x, b, y) := \frac{q_b^A q_b^B}{2 p_{\text{sift}}} \text{Tr}[\Pi_y^b \overline{\mathcal{N}}_{A \rightarrow B}(\rho_A^{b, x})], \quad (72)$$

and it is for this (conditional) probability distribution that parameter estimation occurs and using which key distillation occurs in both the six-state and BB84 protocols.

The full classical-classical-quantum state of Alice, Bob, and the eavesdropper, can be written via an isometric extension $\mathcal{U}_{A \rightarrow BE}^{\mathcal{N}}$ of the channel $\mathcal{N}_{A \rightarrow B}$. Specifically,

$$\begin{aligned} \rho_{X_1 X_2 Y_1 Y_2 E}^{\text{sift}} = & \sum_{b \in \mathcal{B}} \sum_{x, y=0}^1 \frac{q_b^A q_b^B}{p_{\text{sift}}} p_{X_2 Y_2 | X_1 Y_1}(x, y | b, b) |b, b\rangle\langle b, b|_{X_1 Y_1} \\ & \otimes |x, y\rangle\langle x, y|_{X_2 Y_2} \otimes \rho_E^{b, x, y}, \end{aligned} \quad (73)$$

where

$$p_{X_2 Y_2 | X_1 Y_1}(x, y | b, b) = \frac{1}{2} \text{Tr}[\Pi_y^b \overline{\mathcal{N}}_{A \rightarrow B}(\rho_A^{b, x})], \quad (74)$$

$$\rho_E^{b, x, y} = \frac{\text{Tr}_B[\Pi_y^b \mathcal{U}_{A \rightarrow BE}^{\mathcal{N}}(\rho_A^{b, x})]}{p_{X_2 Y_2 | X_1 Y_1}(x, y | b, b)}. \quad (75)$$

The channel parameters p_X , p_Y , and p_Z in (67) can be rewritten in terms of three quantum bit error rates (QBERs) Q_x , Q_y , and Q_z , which in each case corresponds to the expected probability that Bob measures a different state from what Alice sent with respect to a given basis:

$$Q_x := \frac{1}{2} (\langle - | \overline{\mathcal{N}}(|+\rangle\langle +|) | - \rangle + \langle + | \overline{\mathcal{N}}(|-\rangle\langle -|) | + \rangle), \quad (76)$$

$$\begin{aligned} Q_y := \frac{1}{2} & \langle -i | \overline{\mathcal{N}}(|+\rangle\langle +|) | -i \rangle \\ & + \frac{1}{2} \langle +i | \overline{\mathcal{N}}(|-\rangle\langle -|) | +i \rangle, \end{aligned} \quad (77)$$

$$Q_z := \frac{1}{2} (\langle 1 | \overline{\mathcal{N}}(|0\rangle\langle 0|) | 1 \rangle + \langle 0 | \overline{\mathcal{N}}(|1\rangle\langle 1|) | 0 \rangle). \quad (78)$$

The probabilities p_X , p_Y , and p_Z are then related to Q_x , Q_y , and Q_z as follows:

$$p_X = \frac{1}{2} (Q_z - Q_x + Q_y), \quad (79)$$

$$p_Y = \frac{1}{2} (Q_x - Q_y + Q_z), \quad (80)$$

$$p_Z = \frac{1}{2} (Q_y - Q_z + Q_x). \quad (81)$$

See [Kha16, Chapter 2] for a derivation of these equations. In the six-state protocol, it is possible to estimate all of the QBERs reliably, while in BB84, it is only possible to estimate Q_x and Q_z reliably.

Another further symmetrization of the protocol, in addition to channel twirling, is possible if Alice and Bob discard the basis information in X_1 and Y_1 . This is commonly employed in both the six-state and BB84 protocols in order to simplify their analysis. Discarding the basis information corresponds to tracing out the registers X_1 and Y_1 containing the basis information for Alice and Bob, respectively:

$$\begin{aligned} \rho_{X_2 Y_2 E}^{\text{sift}} := & \text{Tr}_{X_1 Y_1} [\rho_{X_1 X_2 Y_1 Y_2 E}^{\text{sift}}] = \\ & \sum_{x, y=0}^1 \sum_{b \in \mathcal{B}} \frac{q_b^A q_b^B}{p_{\text{sift}}} p_{X_2 Y_2 | X_1 Y_1}(x, y | b, b) |x, y\rangle\langle x, y|_{X_2 Y_2} \end{aligned}$$

$$\otimes \rho_E^{b, x, y}, \quad (82)$$

This discarding of basis information in either the six-state or BB84 protocols is equivalent to a further channel twirl. Let us consider first the six-state protocol, and let T denote the following unitary

$$T := |+\rangle\langle 0| - i|-\rangle\langle 1| = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & -i \\ 1 & i \end{bmatrix}, \quad (83)$$

so that T is a unitary changing the Pauli basis as

$$T X T^\dagger = Y, \quad (84)$$

$$T Y T^\dagger = Z, \quad (85)$$

$$T Z T^\dagger = X. \quad (86)$$

Due to the fact that this gate swaps information encoded into the Pauli eigenstates around, discarding of basis information in the six-state protocol is equivalent to a further channel twirl as [Myh10, Section 2.2.7]

$$\begin{aligned} \overline{\mathcal{N}}_{A \rightarrow B}^Q(\omega_A) & := \frac{1}{3} \sum_{j \in \{0, 1, 2\}} T^{j\dagger} \overline{\mathcal{N}}_{A \rightarrow B}(T^j \omega_A T^{j\dagger}) T^j \\ & = \left(1 - \frac{3Q}{2}\right) \omega_A + \frac{Q}{2} (X \omega_A X + Y \omega_A Y + Z \omega_A Z), \end{aligned} \quad (87)$$

where

$$Q = \frac{1}{3} (Q_x + Q_y + Q_z). \quad (89)$$

The channel $\overline{\mathcal{N}}_{A \rightarrow B}^Q$ above is the well known quantum depolarizing channel. It is completely positive for $Q \in [0, 2/3]$, and it is entanglement breaking when $Q \in [1/3, 2/3]$. An entanglement breaking channel is not capable of distilling secret key, as argued in [CLL04], with a strong limitation for the finite-key regime established in [WTB17].

Now let us consider the BB84 protocol. Let H denote the following unitary Hadamard transformation:

$$H := |+\rangle\langle 0| + |-\rangle\langle 1| = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}, \quad (90)$$

so that H changes the Pauli X and Z bases as $H X H^\dagger = Z$ and $H Z H^\dagger = X$. Due to the fact that the H gate swaps information encoded into the Pauli X and Z eigenstates around, discarding of basis information in the BB84 protocol is equivalent to a further channel twirl as [Myh10, Section 2.2.7]

$$\begin{aligned} \overline{\mathcal{N}}_{A \rightarrow B}^{\text{BB84}, Q}(\omega_A) & := \frac{1}{2} \sum_{j \in \{0, 1\}} H^{j\dagger} \overline{\mathcal{N}}_{A \rightarrow B}(H^j \omega_A H^{j\dagger}) H^j \\ & = (1 - 2Q + s) \omega_A + (Q - s) X \omega_A X \end{aligned} \quad (91)$$

$$+ sY\omega_A Y + (Q - s)Z\omega_A Z, \quad (92)$$

where in this case

$$Q = \frac{1}{2}(Q_x + Q_z), \quad (93)$$

$$s = Q - Q_y/2. \quad (94)$$

The channel $\overline{\mathcal{N}}_{A \rightarrow B}^{\text{BB84}, Q}$ is thus known as the BB84 channel in the literature [SS08]. Observe that $s \in [2Q - 1, Q]$ in order for complete positivity to hold. By computing the Choi state of this channel and using the condition for separability from [ADH08], we find that the BB84 channel is entanglement breaking for $s \in [0, 1/2]$ and $Q \in [(s + 1/2)/2, (s + 1)/2]$. As before, it is not possible to distill secret key from the BB84 channel when it is entanglement breaking.

We call a protocol in which the basis information is discarded a “coarse-grained protocol”. We find analytic expressions for the key distillation rate of the coarse-grained BB84 and six-state protocols in the following sections.

2. Six-state protocol

For the six-state protocol, we have $\mathcal{B} = \mathcal{B}_{\text{six-state}} = \{0, 1, 2\}$, corresponding to the X , Y , and Z bases. We typically take $q_b^A = \frac{1}{3} = q_b^B$ for all $b \in \mathcal{B}$, so that $p_{\text{sift}} = \frac{1}{3}$. The joint distribution shared by Alice and Bob after sifting is as follows:

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(b, x, b, y) = \frac{q_b^A q_b^B}{2p_{\text{sift}}} \text{Tr}[\Pi_y^b \overline{\mathcal{N}}_{A \rightarrow B}(\rho_A^{b,x})], \quad (95)$$

for $b \in \{0, 1, 2\}$ and $x, y \in \{0, 1\}$. Each of the relevant entries is given by

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(0, 0, 0, 0) = \frac{1}{6}(1 - Q_x), \quad (96)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(0, 0, 0, 1) = \frac{1}{6}Q_x, \quad (97)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(0, 1, 0, 0) = \frac{1}{6}Q_x, \quad (98)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(0, 1, 0, 1) = \frac{1}{6}(1 - Q_x), \quad (99)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(1, 0, 1, 0) = \frac{1}{6}(1 - Q_z), \quad (100)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(1, 0, 1, 1) = \frac{1}{6}Q_z, \quad (101)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(1, 1, 1, 0) = \frac{1}{6}Q_z, \quad (102)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(1, 1, 1, 1) = \frac{1}{6}(1 - Q_z), \quad (103)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(2, 0, 2, 0) = \frac{1}{6}(1 - Q_y), \quad (104)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(2, 0, 2, 1) = \frac{1}{6}Q_y, \quad (105)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(2, 1, 2, 0) = \frac{1}{6}Q_y, \quad (106)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{6-state|sift}}(2, 1, 2, 1) = \frac{1}{6}(1 - Q_y). \quad (107)$$

Let us define the average QBER as

$$Q := \frac{1}{3}(Q_x + Q_y + Q_z). \quad (108)$$

If Alice and Bob discard the basis information in X_1 and Y_1 , then the resulting probability distribution is

$$p_{X_2 Y_2}^{\text{6-state|sift}}(0, 0) = \frac{1}{2}(1 - Q), \quad (109)$$

$$p_{X_2 Y_2}^{\text{6-state|sift}}(0, 1) = \frac{1}{2}Q, \quad (110)$$

$$p_{X_2 Y_2}^{\text{6-state|sift}}(1, 0) = \frac{1}{2}Q, \quad (111)$$

$$p_{X_2 Y_2}^{\text{6-state|sift}}(1, 1) = \frac{1}{2}(1 - Q). \quad (112)$$

In other words, when discarding the basis information, Alice and Bob’s data can be characterized by the single parameter Q .

For the six-state protocol, there is a reliable estimate of Eve’s collective attack. This means that the uncertainty set \mathcal{S} discussed in Section II A 3 has cardinality equal to one. With the further assumption of discarding basis information, the average QBER Q uniquely identifies the attack of Eve, as in (88). By following the derivations in Appendix A, we find that the mutual and Holevo informations and variances as a function of the average QBER Q are as follows:

$$I(X; Y)_\rho = 1 - h_2(Q), \quad (113)$$

$$V(X; Y)_\rho = Q(1 - Q) \left(\log_2 \left(\frac{1 - Q}{Q} \right) \right)^2, \quad (114)$$

$$I(X; E)_\rho = - \left(1 - \frac{3Q}{2} \right) \log_2 \left(1 - \frac{3Q}{2} \right) - \frac{3Q}{2} \log_2 \left(\frac{Q}{2} \right) - h_2(Q), \quad (115)$$

$$V(X; E)_\rho = Q + \left(1 - \frac{3Q}{2} \right) \left(\log_2 \left(\frac{1 - \frac{3Q}{2}}{1 - Q} \right) \right)^2 + \frac{Q}{2} \left(\log_2 \left(\frac{\frac{Q}{2}}{1 - Q} \right) \right)^2 - I(X; E)_\rho^2, \quad (116)$$

where

$$h_2(Q) := -Q \log_2(Q) - (1 - Q) \log_2(1 - Q) \quad (117)$$

is the binary entropy. The achievable distillable key with direct reconciliation is then given by evaluating the general formula in (31):

$$K_{\text{6-state}}(Q, n, \varepsilon_I, \varepsilon_{II}) = 1 + \left(1 - \frac{3Q}{2} \right) \log_2 \left(1 - \frac{3Q}{2} \right)$$




FIG. 1. Distillable key rates for the coarse-grained six-state protocol after sifting with $Q = 0.05$. The purple solid line indicates the asymptotic key rate.

$$\begin{aligned}
 & + \frac{3Q}{2} \log_2 \left(\frac{Q}{2} \right) \\
 & + \sqrt{\frac{Q(1-Q)}{n}} \log_2 \left(\frac{1-Q}{Q} \right) \Phi^{-1}(\varepsilon_I) \\
 & + \sqrt{\frac{V(X; E)_\rho}{n}} \Phi^{-1}(\varepsilon_{II}^2). \quad (118)
 \end{aligned}$$

We note that the first-order rate term in the above expression is equal to the known asymptotic key rate for the six-state protocol and coincides with the result from [Lo01].

Figure 1 plots the second-order coding rate for key distillation using the six-state protocol. These rates can be compared with the finite-key analysis from [AMKB11], but the comparison is not necessarily fair, due to our assumption of reliable parameter estimation.

We finally note that incorporating the methods of [KR08] can improve the key rate.

3. BB84 DV-QKD protocol

For the BB84 protocol, we have $\mathcal{B} = \mathcal{B}_{\text{BB84}} = \{0, 1\}$, corresponding to the X and Z bases. We typically take $q_b^A = \frac{1}{2} = q_b^B$ for all $b \in \mathcal{B}$, so that $p_{\text{sift}} = \frac{1}{2}$. The relevant probability distribution is

$$p_{X_1 X_2 Y_1 Y_2}^{\text{BB84|sift}}(b, x, b, y) = \frac{q_b^A q_b^B}{2p_{\text{sift}}} \text{Tr}[\Pi_y^b \bar{\mathcal{N}}_{A \rightarrow B}(\rho_A^{b,x})], \quad (119)$$

for $b \in \{0, 1\}$ and $x, y \in \{0, 1\}$. We then have

$$p_{X_1 X_2 Y_1 Y_2}^{\text{BB84|sift}}(0, 0, 0, 0) = \frac{1}{4}(1 - Q_x), \quad (120)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{BB84|sift}}(0, 0, 0, 1) = \frac{1}{4}Q_x, \quad (121)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{BB84|sift}}(0, 1, 0, 0) = \frac{1}{4}Q_x, \quad (122)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{BB84|sift}}(0, 1, 0, 1) = \frac{1}{4}(1 - Q_x), \quad (123)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{BB84|sift}}(1, 0, 1, 0) = \frac{1}{4}(1 - Q_z), \quad (124)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{BB84|sift}}(1, 0, 1, 1) = \frac{1}{4}Q_z, \quad (125)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{BB84|sift}}(1, 1, 1, 0) = \frac{1}{4}Q_z, \quad (126)$$

$$p_{X_1 X_2 Y_1 Y_2}^{\text{BB84|sift}}(1, 1, 1, 1) = \frac{1}{4}(1 - Q_z) \quad (127)$$

Let us define the average QBER as

$$Q := \frac{1}{2}(Q_x + Q_z). \quad (128)$$

If Alice and Bob discard the basis information in X_1 and Y_1 , then the probability distribution is

$$p_{X_2 Y_2}^{\text{BB84|sift}}(0, 0) = \frac{1}{2}(1 - Q), \quad (129)$$

$$p_{X_2 Y_2}^{\text{BB84|sift}}(0, 1) = \frac{1}{2}Q, \quad (130)$$

$$p_{X_2 Y_2}^{\text{BB84|sift}}(1, 0) = \frac{1}{2}Q, \quad (131)$$

$$p_{X_2 Y_2}^{\text{BB84|sift}}(1, 1) = \frac{1}{2}(1 - Q). \quad (132)$$

In other words, when discarding the basis information, Alice and Bob's classical data can be characterized using the single parameter Q .

For the parameter estimation step of the protocol, it is possible for Alice and Bob to determine the QBERs Q_x and Q_z reliably. However, it is not possible to estimate Q_y because the encoding and decoding do not involve the eigenbasis of the Pauli Y operator. Thus, the uncertainty set \mathcal{S} in this case consists of all Pauli channels satisfying (79)–(81) for fixed Q_x and Q_z . If we further simplify the protocol by throwing away the basis information, then the analysis simplifies. By following the derivations in Appendix A, we find that the mutual and Holevo informations and variances as a function of the average QBER Q and the optimization parameter $s \in [0, Q]$ are as follows:

$$I(X; Y)_\rho = 1 - h_2(Q), \quad (133)$$

$$V(X; Y)_\rho = Q(1 - Q) \left(\log_2 \left(\frac{1 - Q}{Q} \right) \right)^2, \quad (134)$$

$$I(X; E)_\rho = H(\{1 - 2Q + s, Q - s, Q - s, s\}) - h_2(Q), \quad (135)$$

$$\begin{aligned}
 V(X; E)_\rho &= (1 - 2Q + s) \left(\log_2 \left(\frac{1 - 2Q + s}{1 - Q} \right) \right)^2 \\
 &+ (Q - s) \left(\log_2 \left(\frac{Q - s}{1 - Q} \right) \right)^2 \\
 &+ (Q - s) \left(\log_2 \left(\frac{Q - s}{Q} \right) \right)^2
 \end{aligned}$$




FIG. 2. Distillable key rates for the coarse-grained BB84 protocol after sifting with $Q = 0.05$. The purple solid line indicates the asymptotic key rate.

$$+ s \left(\log_2 \left(\frac{s}{Q} \right) \right)^2 - I(X; E)_\rho^2. \quad (136)$$

The achievable key rate for direct reconciliation is then given by evaluating the general formula in (31) and performing an optimization over the parameter $s \in [0, Q]$. We note that the first-order rate term $I(X; Y) - I(X; E)$ is equal to the known asymptotic key rate for the BB84 protocol and coincides with the result from [SP00].

Figure 2 plots the second-order coding rate for key distillation using the BB84 protocol. These rates can be compared with the finite-key analysis from [TL17], but the comparison is not necessarily fair, due to our assumption of reliable parameter estimation.

We again note that incorporating the methods of [SRS08] can improve the key rate.

4. CV-QKD protocol with coherent states and heterodyne detection

We finally analyze the performance of the CV-QKD Gaussian modulation protocol with reverse reconciliation. This protocol involves Gaussian modulation of coherent states by Alice and heterodyne detection by Bob, and it is a particular instance of the prepare-and-measure protocol from Section II A.

The encoding ensemble \mathcal{E}_A in this case is

$$\{p_{\bar{n}}(\alpha), |\alpha\rangle\langle\alpha|\}_{\alpha \in \mathbb{C}}, \quad (137)$$

where $\bar{n} > 0$, $p_{\bar{n}}(\alpha)$ is an isotropic complex Gaussian distribution:

$$p_{\bar{n}}(\alpha) := \frac{1}{\pi \bar{n}} \exp \left(-|\alpha|^2 / \bar{n} \right), \quad (138)$$

and $|\alpha\rangle\langle\alpha|$ is a coherent state [GK04] such that

$$|\alpha\rangle := e^{-|\alpha|^2/2} \sum_{n=0}^{\infty} \frac{\alpha^n}{\sqrt{n!}} |n\rangle, \quad (139)$$

with $\{|n\rangle\}_{n=0}^{\infty}$ the orthonormal photon number basis. The decoding POVM for Bob is heterodyne detection [GK04], given by

$$\left\{ \frac{1}{\pi} |\alpha\rangle\langle\alpha| \right\}_{\alpha \in \mathbb{C}}. \quad (140)$$

Let X be a complex random variable corresponding to the choice of α in Alice's encoding, and let Y be a complex random variable corresponding to Bob's measurement outcome.

The encoding and decoding act on a single bosonic mode, which implies that the channel $\mathcal{N}_{A \rightarrow B}$ that Eve employs is a single-mode bosonic channel.

The channel twirling that Alice and Bob employ in this case is the phase symmetrization from [KGW19]. In particular, before Alice sends out a coherent state, she applies the unitary $e^{-i\hat{n}\phi}$, with the phase ϕ selected uniformly at random from $\{0, \pi/2, \pi, 3\pi/2\}$. She communicates this choice to Bob, who then applies $e^{i\hat{n}\phi}$ to his received mode. They both then discard the classical memory of which phase ϕ was applied. This phase symmetrization significantly reduces the number of parameters that Alice and Bob need to estimate in the parameter estimation part of the protocol. Like the other protocols, this phase symmetrization need not be applied in the quantum domain because the encoding ensemble in (137) and the decoding POVM (140) are invariant under the actions of Alice and Bob mentioned above. Thus, it can be carried out in classical processing that keeps track of the twirl.

During the parameter estimation step of the protocol, Alice and Bob estimate

$$\gamma_{12} := \mathbb{E}\{(X - \mathbb{E}\{X\})^* (Y - \mathbb{E}\{Y\})\}, \quad (141)$$

$$\gamma_{22} := \mathbb{E}\{|Y - \mathbb{E}\{Y\}|^2\}. \quad (142)$$

We suppose here that the photon number variance of the channel output system B is finite, in order to ensure that reliable estimation of the parameters γ_{12} and γ_{22} is possible. Here we also assume that they estimate $p_{Y|X}(y|x)$. The following parameter is known

$$\gamma_{11} := \mathbb{E}\{|X - \mathbb{E}\{X\}|^2\}, \quad (143)$$

being a function of Alice's encoding ensemble. The uncertainty set \mathcal{S} in this case then consists of all single-mode bosonic channels, with system B having finite photon number variance, that lead to the estimates γ_{12} and γ_{22} , as well as $p_{Y|X}(y|x)$. The achievable key rate is given by evaluating the formula in (40) as a function of the encoding in (137), the decoding in (140), and the set \mathcal{S} mentioned above. To evaluate this formula, we apply the perturbative approach from [PPV10, Lemmas 63 and 64],

which is valid for sufficiently large n . In this approach, we optimize the first-order Holevo information term of Eve first, and then among all of the channels optimizing the first-order term, we optimize the second-order Holevo information variance of Eve. In this case, the Gaussian extremality theorem of [WGC06], as observed in [GPC06], implies that a Gaussian attack achieves the optimal first-order Holevo information of Eve. The same conclusion has been reached in [NGA06] by a different line of reasoning. In fact, by examining the proof in [NGA06] and employing the faithfulness of quantum relative entropy, we conclude that for every non-Gaussian attack, there is a Gaussian attack that achieves a strictly higher Holevo information of Eve. Thus, it suffices to optimize Eve's Holevo information over Gaussian attacks exclusively, and among all of these Gaussian attacks, there is a unique one that achieves the optimum [Lev15, Appendix D], which is a thermal channel consistent with the observed estimates γ_{11} , γ_{12} , and γ_{22} . So applying the perturbative approach mentioned above, there is no need to perform a further optimization of the Holevo information variance of Eve, and we just evaluate it with respect to the optimal and unique Gaussian attack.

We stress here that, even though the actual attack of Eve need not be a Gaussian channel, the Gaussian optimality theorem and the perturbative extension of it is useful in order to bound Eve's information from above. Without this result, the optimization would be too difficult (perhaps impossible) because the underlying Hilbert space is infinite-dimensional.

Let us analyze the performance of the above protocol in a particular physical scenario. Suppose that the underlying physical channel is indeed a thermal channel $\mathcal{L}_{A \rightarrow B}^{\eta, N_B}$ [Ser17], characterized by transmissivity $\eta \in (0, 1)$ and environment thermal photon number N_B . However, Alice and Bob are not aware of this, as is the usual case in a QKD protocol. They execute the above protocol, and after the parameter estimation phase, suppose that they have estimated the classical channel $p_{Y|X}(y|x)$ and the parameters in (141)–(142). From the parameters in (141)–(142), they conclude that the optimal Gaussian attack of Eve is a thermal channel of transmissivity η and environment thermal photon number N_B . Let $\mathcal{U}_{A \rightarrow BE}^{\mathcal{L}_{A \rightarrow B}^{\eta, N_B}}$ be an isometric channel extending $\mathcal{L}_{A \rightarrow B}^{\eta, N_B}$. An isometric channel extending $\mathcal{L}_{A \rightarrow B}^{\eta, N_B}$ can be physically realized by the action of a beamsplitter of transmissivity η acting on the input mode A and one share E_1 of a two-mode squeezed vacuum state [CG06, CGH06], as

$$\mathcal{U}_{A \rightarrow BE}^{\mathcal{L}_{A \rightarrow B}^{\eta, N_B}}(\omega_A) = \mathcal{B}_{AE_1 \rightarrow BE_1}^\eta(\omega_A \otimes \psi_{E_1 E_2}^{N_B}), \quad (144)$$

where ω_A is the input state, $\mathcal{B}_{AE_1 \rightarrow BE_1}^\eta$ denotes the beamsplitter channel of transmissivity η , the system E consists of modes E_1 and E_2 , and the two-mode squeezed

vacuum state $\psi_{E_1 E_2}^{N_B} := |\psi^{N_B}\rangle\langle\psi^{N_B}|_{E_1 E_2}$ is defined from

$$|\psi^{N_B}\rangle_{E_1 E_2} := \frac{1}{\sqrt{N_B + 1}} \sum_{n=0}^{\infty} \left(\sqrt{\frac{N_B}{N_B + 1}} \right)^n |n\rangle_{E_1} |n\rangle_{E_2}. \quad (145)$$

We now calculate the various quantities in (40) for this case and for a reverse reconciliation protocol. We begin by determining the mutual information $I(X; Y)$ and the mutual information variance $V(X; Y)$. The classical channel $p_{Y|X}(y|x)$ induced by heterodyne detection of a Gaussian-distributed ensemble of coherent states transmitted through the thermal channel $\mathcal{L}_{A \rightarrow B}^{\eta, N_B}$ is as follows (see, e.g., [Guh04, Sav12]):

$$p_{Y|X}(y|x) = \frac{\exp\left(-\frac{|y - \sqrt{\eta}x|^2}{\pi((1-\eta)N_B + 1)}\right)}{\pi((1-\eta)N_B + 1)}, \quad (146)$$

where $x, y \in \mathbb{C}$. As mentioned previously, we assume that this classical channel $p_{Y|X}$ is reliably estimated during the parameter estimation step [Notb]. Then it follows that

$$I(X; Y) = \log_2(1 + P), \quad (147)$$

$$V(X; Y) = \frac{1}{\ln^2 2} \frac{P(P+2)}{(P+1)^2}, \quad (148)$$

where

$$P := \frac{\eta \bar{n}}{(1-\eta)N_B + 1}. \quad (149)$$

The formulas above follow from the fact that the channel $p_{Y|X}(y|x)$ in (146) can be understood as two independent real Gaussian channels each with signal-to-noise ratio P , and then by applying Shannon's formula [Sha48] and the mutual information variance formula from [PPV10, TT15a] (with a prefactor of two to account for the two independent channels).

We now turn to calculating the Holevo information $I(Y; E)$ and the Holevo information variance $V(Y; E)$, the latter of which can be calculated as a special case of Proposition 3 below. For a Gaussian-distributed ensemble of coherent states as in (138), the expected input density operator is a thermal state of the following form [Ser17]:

$$\theta(\bar{n}) := \frac{1}{\bar{n} + 1} \sum_{n=0}^{\infty} \left(\frac{\bar{n}}{\bar{n} + 1} \right)^n |n\rangle\langle n|, \quad (150)$$

with covariance matrix $V(\bar{n}) := (2\bar{n} + 1)I_2$, where I_2 is the 2×2 identity matrix. It then follows that the covariance matrix of the state $\rho_{BE} := \mathcal{U}_{A \rightarrow BE}^{\mathcal{L}_{A \rightarrow B}^{\eta, N_B}}(\theta(\bar{n}))$ is

$$V_{\rho_{BE}} := \begin{bmatrix} V_B & V_{BE} \\ V_{BE} & V_E \end{bmatrix} \quad (151)$$

$$= (B(\eta) \oplus I_2)(V(\bar{n}) \oplus V_E(N_B))(B^T(\eta) \oplus I_2), \quad (152)$$

where

$$B(\eta) := \begin{bmatrix} \sqrt{\eta} I_2 & \sqrt{1-\eta} I_2 \\ -\sqrt{1-\eta} I_2 & \sqrt{\eta} I_2 \end{bmatrix}, \quad (153)$$

$$V_E(N_B) := \begin{bmatrix} (2N_B + 1) I_2 & 2\sqrt{N_B(N_B + 1)} \sigma_Z \\ 2\sqrt{N_B(N_B + 1)} \sigma_Z & (2N_B + 1) I_2 \end{bmatrix}. \quad (154)$$

For this example, note that Eve's actual attack and Alice and Bob's estimation of it coincide, due to our assumption that the underlying channel is a thermal channel. We then obtain the covariance matrix of the reduced state $\rho_E = \text{Tr}_B[\rho_{BE}]$ from the above, which can be used to calculate the entropy $H(E)_\rho$. The covariance matrix of the reduced state ρ_E^y of Eve's system, given the outcome y of Bob's heterodyne detection is as follows:

$$V_{E|Y} := V_E - V_{BE} (V_B + I_2)^{-1} V_{BE}^T, \quad (155)$$

and the probability of obtaining the outcome y is

$$p_Y(y) := \frac{\exp\left(-\frac{|y|^2}{\pi(\eta\bar{n} + (1-\eta)N_B + 1)}\right)}{\pi(\eta\bar{n} + (1-\eta)N_B + 1)}. \quad (156)$$

This allows us to compute the conditional entropy as

$$H(E|Y) = \int dy p_Y(y) H(E)_{\rho^y}. \quad (157)$$

Now combining $H(E)_\rho - H(E|Y) = I(Y; E)$, we can calculate Eve's Holevo information.

To calculate the Holevo information variance $V(Y; E)$, we apply the formula from Proposition 3 below. To understand this formula, we first provide a definition for a Gaussian ensemble of quantum Gaussian states.

Definition 2 (Gaussian ensemble) A Gaussian ensemble of m -mode Gaussian states consists of a Gaussian prior probability distribution of the form

$$p_Y(y) := \mathcal{N}(\mu, \Sigma) \quad (158)$$

$$:= \frac{\exp\left(-\frac{1}{2}(y - \mu)^T \Sigma^{-1}(y - \mu)\right)}{\sqrt{(2\pi)^{2n} \det(\Sigma)}}, \quad (159)$$

and a set $\{\rho_E^y\}_{y \in \mathbb{R}^{2n}}$ of Gaussian states, each having $2m \times 1$ mean vector $Wy + \nu$ and $2m \times 2m$ quantum covariance matrix V . In the above, y is a $2n \times 1$ vector, μ is the $2n \times 1$ mean vector of the random vector Y , Σ is the $2n \times 2n$ covariance matrix of the random vector Y , W is a $2m \times 2n$ matrix, and ν is a $2m$ -dimensional vector.

Proposition 3 The Holevo information of the ensemble in Definition 2 is given by

$$I(Y; E) = \frac{1}{2 \ln 2} \left[\ln\left(\frac{Z_E}{Z}\right) + \frac{1}{2} \text{Tr}[V\Delta] + \text{Tr}[W\Sigma W^T G_E] \right], \quad (160)$$




FIG. 3. Distillable key rates for the reverse reconciliation CV-QKD protocol, when conducted over a thermal channel with transmissivity $\eta = 0.2$ and environment photon number $N_B = 10^{-2}$. The purple solid line indicates the asymptotic key rate.

and the Holevo information variance of the ensemble in Definition 2 is given by

$$V(Y; E) = \frac{1}{8 \ln^2 2} \left[\text{Tr}[(\Delta V)^2] + \text{Tr}[(\Delta \Omega)^2] \right] + \frac{1}{2 \ln^2 2} \left[\text{Tr}[W\Sigma W^T G_E V G_E] + \text{Tr}[(W\Sigma W^T G_E)^2] \right], \quad (161)$$

where

$$Z := \det([V + i\Omega]/2), \quad (162)$$

$$G := 2i\Omega \text{arccoth}(iV\Omega), \quad (163)$$

$$V_E := V + 2W\Sigma W^T, \quad (164)$$

$$Z_E := \det([V_E + i\Omega]/2), \quad (165)$$

$$G_E := 2i\Omega \text{arccoth}(iV_E\Omega), \quad (166)$$

$$\Delta := G_E - G. \quad (167)$$

See Appendix H for a review of quantum Gaussian states and measurements and for a proof of Proposition 3.

Putting everything above together, we find that the achievable secret key rate is given by evaluating the above quantities in the formula in (40). Figure 3 plots the second-order coding rate for key distillation using the CV-QKD reverse reconciliation protocol. One can compare these rates to the finite-key analysis presented in [Lev15], but the comparison is not necessarily fair due to our assumption of reliable parameter estimation. We also note that the first-order term in (40) is equal to the known asymptotic key rate from [Lev15].

C. Routes to a full second-order analysis that includes parameter estimation

As we have mentioned in Section II A 3, our second-order analysis above is incomplete, in the sense that it does not incorporate details of the parameter estimation step. That is, we have assumed that k is large enough to allow for a reliable estimate of the induced classical channel $p_{Y|X}$, and from there, we applied a second-order analysis to the key distillation step. Here we discuss a potential route around this issue and an avenue for future work on this topic.

For finite-dimensional protocols, the collective attack of Eve is constrained to a finite-dimensional quantum channel. This quantum channel is realized by a unitary acting on a larger, yet finite-dimensional Hilbert space. If we limit Eve to a finite set of quantum computations that can be realized from a finite, universal gate set, which could in principle realize any unitary on the space to any desired accuracy, then the resulting channel is selected from a very large, yet finite and known set. In this case, the parameter estimation procedure of [Pol13, Section III-D] can be applied, and it has negligible overhead. Indeed, it is possible to estimate the channel chosen from a finite set with $k = O(\log n)$ and such that the decoding error probability is increased by no more than $1/\sqrt{n}$, which has no impact on the second-order terms in (31) and (40) for sufficiently large n . However, the main drawback of this approach is that, even though this constraint on the eavesdropper might be considered reasonable, it is still a computational assumption and thus lies outside the quantum information-theoretic security that is ultimately desired in quantum key distribution. Furthermore, this does not address CV-QKD protocols in which there is not a finite-dimensional assumption.

Another approach to address the issue is to incorporate recent advances in universal coding up to the second order [Hay19]. A universal code does not depend on the particular channel over which communication is being conducted, and it only requires an estimate of the first- and second-order terms. This approach has been analyzed in detail in [Hay19], and it is likely that it could be combined with the information-theoretic protocol considered in this paper and the parameter estimation step in order to arrive at a full second-order analysis for both the parameter estimation and key distillation steps in a quantum key distribution protocol. A benefit of this approach is that quantum information-theoretic security would be retained. We leave a full investigation of this approach for future work.

III. PRIVATE COMMUNICATION OVER A COMPOUND WIRETAP CHANNEL WITH FIXED MARGINAL

We now present the one-shot information-theoretic results that underlie the previous claims for key distillation

in quantum key distribution. We begin by considering private communication over a compound wiretap channel with fixed marginal, and then in Section IV, we move on to a key distillation protocol for a compound wiretap source with fixed marginal.

A. One-shot setting

In the setting of private communication, we suppose that Alice, Bob, and Eve are connected by means of the following classical-quantum-quantum (cqq) compound wiretap channel with fixed marginal:

$$\mathcal{N}_{X \rightarrow BE}^s : x \rightarrow \rho_{BE}^{x,s}, \quad (168)$$

where the classical input $x \in \mathcal{X}$, the alphabet \mathcal{X} is countable, the index $s \in \mathcal{S}$ represents the choice or state of the channel, the set \mathcal{S} can be uncountable, and $\rho_{BE}^{x,s}$ is a density operator acting on the tensor-product separable Hilbert space $\mathcal{H}_B \otimes \mathcal{H}_E$. We suppose that the channel has a fixed marginal; i.e., the reduced Alice-Bob channel

$$\mathcal{N}_{X \rightarrow B}^s : x \rightarrow \rho_B^{x,s} := \text{Tr}_E[\rho_{BE}^{x,s}] \quad (169)$$

is known to Alice and Bob, so that

$$\rho_B^{x,s} = \rho_B^x \quad \text{for all } s \in \mathcal{S}. \quad (170)$$

However, the reduced s -dependent Alice-Eve channel

$$\mathcal{N}_{X \rightarrow E}^s : x \rightarrow \rho_E^{x,s} := \text{Tr}_B[\rho_{BE}^{x,s}] \quad (171)$$

is not fully known to or characterized by Alice or Bob during their communication. Thus, the channel $\mathcal{N}_{X \rightarrow BE}^s$ is a particular member of a set \mathcal{S} of channels, for which

$$\text{Tr}_E[\rho_{BE}^{x,s}] = \rho_B^x \quad \text{for all } s \in \mathcal{S}. \quad (172)$$

To be clear, we suppose that the set \mathcal{S} is known to Alice and Bob, but the particular channel indexed by $s \in \mathcal{S}$, which is actually being employed during the communication protocol, is not known. The goal of a private communication protocol is for Alice to send a message securely to Bob, such that it is secure against the channel $\mathcal{N}_{X \rightarrow BE}^s$ for all $s \in \mathcal{S}$.

The action of the channel in (168) can be described in the fully quantum picture as follows:

$$\mathcal{N}_{X \rightarrow BE}^s(\omega_X) := \sum_x \langle x|_X \omega_X |x\rangle_X \rho_{BE}^{x,s}, \quad (173)$$

where $\{|x\rangle_X\}_{x \in \mathcal{X}}$ is a countable orthonormal basis for an input separable Hilbert space \mathcal{H}_X .

In our model of communication, we suppose also that public shared randomness is available for free to Alice and Bob. Since it is public, Eve gets a copy of all of the shared randomness. In particular, therefore, this shared randomness is not the same as prior secret key shared by Alice and Bob.

Let $\bar{\Psi}_{R_A R_B R_E}$ denote the following public shared randomness state:

$$\bar{\Psi}_{R_A R_B R_E} := \sum_{r=1}^{|\mathcal{R}|} p(r) |r\rangle\langle r|_{R_A} \otimes |r\rangle\langle r|_{R_B} \otimes |r\rangle\langle r|_{R_E}, \quad (174)$$

where \mathcal{R} is the alphabet for the shared randomness, Alice possesses the classical register R_A , Bob R_B , and Eve R_E . The systems R_A , R_B , and R_E have the same dimension. A private coding scheme for the channel in (168) consists of the public shared randomness state $\bar{\Psi}_{R_A R_B R_E}$, an encoding channel $\mathcal{E}_{R_A M \rightarrow X}$ taking the register R_A and a message register M to the channel input register X , and a decoding channel $\mathcal{D}_{R_B B \rightarrow \hat{M}}$. Two parameters ε_I and ε_{II} determine the decoding error probability and the security of the protocol, respectively. Alice uses the coding scheme and the channel in (168) to send a message $m \in \mathcal{M}$, where \mathcal{M} is the message alphabet, and the conditional probability of decoding as $m' \in \mathcal{M}$ is given by

$$\Pr[\hat{M} = m' | M = m] := \langle m' |_{\hat{M}} \mathcal{D}_{R_B B \rightarrow \hat{M}}(\rho_{B R_B}^m) | m' \rangle_{\hat{M}}, \quad (175)$$

where

$$\rho_{B R_B}^m := \text{Tr}_{R_E}[\rho_{B E R_B R_E}^{m,s}], \quad (176)$$

$$\rho_{B E R_B R_E}^{m,s} :=$$

$$(\mathcal{N}_{X \rightarrow B E}^s \circ \mathcal{E}_{R_A M \rightarrow X})(|m\rangle\langle m|_M \otimes \bar{\Psi}_{R_A R_B R_E}). \quad (177)$$

Note that the reduced state $\rho_{B R_B}^m$ has no dependence on s , due to the assumption stated in (172). To see (175) in a different way, we can alternatively consider Bob's positive operator-valued measure $\{\Lambda_{R_B B}^m\}_{m \in \mathcal{M}}$ to consist of the following elements:

$$\Lambda_{R_B B}^m := (\mathcal{D}_{R_B B \rightarrow \hat{M}})^\dagger(|m\rangle\langle m|_{\hat{M}}), \quad (178)$$

where $(\mathcal{D}_{R_B B \rightarrow \hat{M}})^\dagger$ is the Hilbert-Schmidt adjoint of the decoding channel $\mathcal{D}_{R_B B \rightarrow \hat{M}}$, so that we can write $\Pr[\hat{M} = m' | M = m]$ in terms of the Born rule as

$$\Pr[\hat{M} = m' | M = m] = \text{Tr}[\Lambda_{R_B B}^{m'} \rho_{B R_B}^m]. \quad (179)$$

The protocol is ε_I -reliable, with $\varepsilon_I \in [0, 1]$, if the following condition holds for all $m \in \mathcal{M}$:

$$\Pr[\hat{M} = m | M = m] \geq 1 - \varepsilon_I. \quad (180)$$

Equivalently, we require that

$$\sup_{m \in \mathcal{M}} \left(1 - \Pr[\hat{M} = m | M = m]\right) \leq \varepsilon_I. \quad (181)$$

The protocol is ε_{II} -secret, with $\varepsilon_{II} \in [0, 1]$, if for all channel states $s \in \mathcal{S}$, there exists a fixed state $\sigma_{E R_E}^s$ of Eve's systems, such that for all messages $m \in \mathcal{M}$, the following inequality holds

$$\frac{1}{2} \|\rho_{E R_E}^{m,s} - \sigma_{E R_E}^s\|_1 \leq \varepsilon_{II}. \quad (182)$$

Equivalently, we require that

$$\sup_{s \in \mathcal{S}} \inf_{\sigma_{E R_E}^s} \sup_{m \in \mathcal{M}} \frac{1}{2} \|\rho_{E R_E}^{m,s} - \sigma_{E R_E}^s\|_1 \leq \varepsilon_{II}. \quad (183)$$

Thus, for each $s \in \mathcal{S}$, the protocol allows for sending a message securely, such that the eavesdropper cannot determine the message m , no matter which channel $\mathcal{N}_{X \rightarrow B E}^s$ is selected from \mathcal{S} .

The number of private bits communicated by the scheme is equal to $\log_2 |\mathcal{M}|$. Thus, a given protocol for private communication over the channel in (168) is described by the three parameters $|\mathcal{M}|$, ε_I , and ε_{II} .

We remark that this setting reduces to the traditional one-shot, shared-randomness-assisted private communication setting considered in quantum information theoretic contexts in the case that $|\mathcal{S}| = 1$. See [Wil17a] for details of this special case.

B. Distinguishability and information measures

Before stating Theorem 4 regarding the number of private messages that can be transmitted in the above setting, we briefly review the basic distinguishability measures and information quantities needed to understand the statement of Theorem 4.

Let ρ and σ be states acting on a separable Hilbert space \mathcal{H} . The hypothesis testing relative entropy $D_H^\varepsilon(\rho \| \sigma)$ is defined for $\varepsilon \in [0, 1]$ as [BD10, BD11, WR12]

$$D_H^\varepsilon(\rho \| \sigma) := -\log_2 \inf_{\Lambda \geq 0} \{ \text{Tr}[\Lambda \sigma] : \text{Tr}[\Lambda \rho] \geq 1 - \varepsilon, \Lambda \leq I \}. \quad (184)$$

Note that, without loss of generality, we can set the first constraint above to be an equality [KW17], so that

$$D_H^\varepsilon(\rho \| \sigma) = -\log_2 \inf_{\Lambda \geq 0} \{ \text{Tr}[\Lambda \sigma] : \text{Tr}[\Lambda \rho] = 1 - \varepsilon, \Lambda \leq I \}. \quad (185)$$

The max-relative entropy $D_{\max}(\rho \| \sigma)$ is defined as [Dat09b]

$$D_{\max}(\rho \| \sigma) := \inf \{ \lambda : \rho \leq 2^\lambda \sigma \}. \quad (186)$$

The following alternative characterization of $D_{\max}(\rho \| \sigma)$ is well known [Dat09a]:

$$D_{\max}(\rho \| \sigma) = \inf_{\lambda, \omega \geq 0} \{ \lambda : \sigma = 2^{-\lambda} \rho + (1 - 2^{-\lambda}) \omega, \text{Tr}[\omega] = 1 \}, \quad (187)$$

which allows for thinking of σ as a convex combination of ρ and some other state ω . The smooth max-relative entropy for $\varepsilon \in [0, 1]$ is defined as [Dat09b]

$$D_{\max}^\varepsilon(\rho \| \sigma) := \inf \{ \lambda : \tilde{\rho} \leq 2^\lambda \sigma, \tilde{\rho} \geq 0, \text{Tr}[\tilde{\rho}] = 1, P(\tilde{\rho}, \rho) \leq \varepsilon \}, \quad (188)$$

where the sine distance $P(\tilde{\rho}, \rho)$ is defined as [Ras02, Ras03, Ras06, GLN05]

$$P(\tilde{\rho}, \rho) := \sqrt{1 - F(\tilde{\rho}, \rho)}, \quad (189)$$

$$F(\tilde{\rho}, \rho) := \left\| \sqrt{\tilde{\rho}} \sqrt{\rho} \right\|_1^2, \quad (190)$$

the latter quantity being the quantum fidelity [Uhl76].

Let ρ_{AE} be a state acting on a separable Hilbert space $\mathcal{H}_A \otimes \mathcal{H}_E$. Then a mutual-information like quantity is defined for $\varepsilon \in [0, 1]$ as

$$D_{\max}^\varepsilon(\rho_{AE} \| \rho_A \otimes \rho_E). \quad (191)$$

We also define the alternate smooth max-mutual information as [AJW19b, Wil17a]

$$\tilde{I}_{\max}^\varepsilon(E; A)_\rho := \inf_{\tilde{\rho}_{AE} : P(\tilde{\rho}_{AE}, \rho_{AE}) \leq \varepsilon} D_{\max}(\tilde{\rho}_{AE} \| \rho_A \otimes \tilde{\rho}_E). \quad (192)$$

A simple relation between these two generalizations of mutual information is given in Appendix B. Note that we adopt the particular notation in (192) in order to maintain consistency with the notation of [BCR11].

The hypothesis testing mutual information of a bipartite state ρ_{AB} acting on a separable Hilbert space $\mathcal{H}_A \otimes \mathcal{H}_B$ is defined for $\varepsilon \in [0, 1]$ as [WR12]

$$I_H^\varepsilon(A; B)_\rho := D_H^\varepsilon(\rho_{AB} \| \rho_A \otimes \rho_B). \quad (193)$$

C. Private communication via position-based coding and convex splitting

The communication protocol that we develop here is the same as that considered in [Wil17a], but with the added observation that its security holds universally for any channel selected from the set \mathcal{S} and for channels whose output states act on a separable Hilbert space. The protocol from [Wil17a] built upon the ideas of position-based coding and convex splitting, which were in turn introduced in [AJW19b] and [ADJ17], respectively. Our main one-shot achievability theorem, for the communication setting described in Section III A, is as follows:

Theorem 4 Fix $\varepsilon_I, \varepsilon_{II} \in (0, 1)$, $\eta_I \in (0, \varepsilon_I)$, and $\eta_{II} \in (0, \varepsilon_{II})$. Then the following quantity is an achievable number of private message bits that can be transmitted over the compound wiretap channel in (168), with decoding error probability not larger than ε_I and security parameter not larger than ε_{II} :

$$\sup_{p_X} \left[I_H^{\varepsilon_I - \eta_I}(X; B)_\rho - \sup_{s \in \mathcal{S}} \tilde{I}_{\max}^{\varepsilon_{II} - \eta_{II}}(E; X)_{\rho^s} \right] - \log_2(4\varepsilon_I/\eta_I^2) - 2\log_2(1/2\eta_{II}), \quad (194)$$

where the entropic quantities are evaluated with respect to the following state:

$$\rho_{XBE}^s := \sum_{x \in \mathcal{X}} p_X(x) |x\rangle\langle x|_X \otimes \rho_{BE}^{x,s}. \quad (195)$$

Proof. Consider the compound wiretap channel in (168). Let p_X be a probability distribution over the channel input alphabet \mathcal{X} . Let $\rho_{XX'X''}$ denote the following public shared randomness state:

$$\rho_{XX'X''} := \sum_{x \in \mathcal{X}} p_X(x) |x\rangle\langle x|_X \otimes |x\rangle\langle x|_{X'} \otimes |x\rangle\langle x|_{X''}. \quad (196)$$

We suppose that Alice, Bob, and Eve share the state

$$\rho_{XX'X''}^{\otimes |\mathcal{M}||\mathcal{R}|} \quad (197)$$

before communication begins and that the X systems are indexed as $X_{m,r}$, i.e., in lexicographic order by $m \in \mathcal{M}$ and $r \in \mathcal{R}$, where $\mathcal{R} := \{1, \dots, |\mathcal{R}|\}$. Alice possesses all of the X systems, Bob the X' systems, and Eve the X'' systems.

To send the message $m \in \mathcal{M}$, Alice's encoding consists of picking $r \in \mathcal{R}$ uniformly at random from the set \mathcal{R} , and then she sends the classical system $X_{m,r}$ through the channel in (173). For fixed values of m, r , and s , the global shared state at this point is given by

$$\begin{aligned} \rho_{X|\mathcal{M}||\mathcal{R}|}^{m,r,s} &:= \rho_{X_{1,1}X'_{1,1}X''_{1,1}} \otimes \dots \\ &\otimes \rho_{X_{m,r-1}X'_{m,r-1}X''_{m,r-1}} \otimes \rho_{X_{m,r}X'_{m,r}X''_{m,r}}^{s,BE} \otimes \\ &\rho_{X_{m,r+1}X'_{m,r+1}X''_{m,r+1}} \otimes \dots \otimes \rho_{X_{|\mathcal{M}|,|\mathcal{R}|}X'_{|\mathcal{M}|,|\mathcal{R}|}X''_{|\mathcal{M}|,|\mathcal{R}|}} \end{aligned} \quad (198)$$

where

$$\begin{aligned} \rho_{X_{m,r}X'_{m,r}X''_{m,r}}^{s,BE} &:= \\ \sum_{x \in \mathcal{X}} p_X(x) |x, x, x\rangle\langle x, x, x|_{X_{m,r}X'_{m,r}X''_{m,r}} \otimes \rho_{BE}^{x,s} \end{aligned} \quad (199)$$

The resulting state of Bob, for fixed values m and r , is as follows:

$$\begin{aligned} \rho_{X'|\mathcal{M}||\mathcal{R}|}^{m,r} &:= \rho_{X'_{1,1}} \otimes \dots \otimes \rho_{X'_{m,r-1}} \otimes \rho_{X'_{m,r}}^{B} \\ &\otimes \rho_{X'_{m,r+1}} \otimes \dots \otimes \rho_{X'_{|\mathcal{M}|,|\mathcal{R}|}} \end{aligned} \quad (200)$$

where

$$\rho_{X'_{m,r}}^B := \sum_{x \in \mathcal{X}} p_X(x) |x\rangle\langle x|_{X'_{m,r}} \otimes \rho_B^x. \quad (201)$$

By employing the sequential and position-based decoding scheme from [OMW19] (which has been shown therein to hold for states acting on separable Hilbert spaces), it follows that Bob can decode both the message m and r with probability not smaller than $1 - \varepsilon_I$ as long as

$$\log_2(|\mathcal{M}| |\mathcal{R}|) = I_H^{\varepsilon_I - \eta_I}(X; B)_\rho - \log_2(4\varepsilon_I/\eta_I^2), \quad (202)$$

where $\eta_I \in (0, \varepsilon_I)$ and

$$\rho_{XB} := \sum_{x \in \mathcal{X}} p_X(x) |x\rangle\langle x|_X \otimes \rho_B^x. \quad (203)$$

To Eve, who is unaware of the random choice of the local randomness variable $r \in \mathcal{R}$, the state of her systems for a fixed value of the message m is as follows:

$$\rho_{X''|\mathcal{M}||\mathcal{R}|E}^{m,s} := \frac{1}{|\mathcal{R}|} \sum_{r \in \mathcal{R}} \rho_{X''_{1,1}} \otimes \cdots \otimes \rho_{X''_{m,r-1}} \otimes \rho_{X''_{m,r}E}^s \otimes \rho_{X''_{m,r+1}} \otimes \cdots \otimes \rho_{X''_{|\mathcal{M}|,|\mathcal{R}|}} \quad (204)$$

By the invariance of the trace distance with respect to tensor-product states, i.e., $\|\sigma \otimes \tau - \omega \otimes \tau\|_1 = \|\sigma - \omega\|_1$, we find that

$$\begin{aligned} & \frac{1}{2} \|\rho_{X''|\mathcal{M}||\mathcal{R}|E}^{m,s} - \rho_{X''|\mathcal{M}||\mathcal{R}|} \otimes \tilde{\rho}_E^s\|_1 \\ &= \frac{1}{2} \|\rho_{X''_{m,1} \dots X''_{m,|\mathcal{R}|}E}^{m,s} - \rho_{X''_{m,1} \dots X''_{m,|\mathcal{R}|}} \otimes \tilde{\rho}_E^s\|_1, \end{aligned} \quad (205)$$

for any state $\tilde{\rho}_E^s$. It follows from the smooth universal convex-split lemma (see Appendix C) that if

$$\log_2 |\mathcal{R}| = \sup_{s \in \mathcal{S}} \tilde{I}_{\max}^{\varepsilon_{\text{II}} - \eta_{\text{II}}}(E; X)_{\rho^s} + 2 \log_2(1/2\eta_{\text{II}}), \quad (206)$$

then the following bound holds for all $m \in \mathcal{M}$ and for all $s \in \mathcal{S}$

$$\frac{1}{2} \|\rho_{X''|\mathcal{M}||\mathcal{R}|E}^{m,s} - \rho_{X''|\mathcal{M}||\mathcal{R}|} \otimes \tilde{\rho}_E^s\|_1 \leq \varepsilon_{\text{II}}, \quad (207)$$

where the state $\tilde{\rho}_E^s$ satisfies $P(\tilde{\rho}_E^s, \rho_E^s) \leq \varepsilon_{\text{II}} - \eta_{\text{II}}$ and the alternate smooth max-mutual information $\tilde{I}_{\max}^{\sqrt{\varepsilon_{\text{II}}} - \eta_{\text{II}}}(E; X)_{\rho^s}$ is evaluated with respect to the state

$$\rho_{XE}^s := \sum_{x \in \mathcal{X}} p_X(x) |x\rangle\langle x|_X \otimes \rho_E^{x,s}. \quad (208)$$

The analysis of this step is similar to that given in [Wil17a]. We provide details of the smooth universal convex-split lemma, as applicable to states acting on separable Hilbert spaces, in Appendix C. Thus, the number of private message bits that can be established with this scheme is equal to

$$\begin{aligned} \log_2 |\mathcal{M}| &= I_H^{\varepsilon_{\text{I}} - \eta_{\text{I}}}(X; B)_{\rho} - \sup_{s \in \mathcal{S}} \tilde{I}_{\max}^{\varepsilon_{\text{II}} - \eta_{\text{II}}}(E; X)_{\rho^s} \\ &\quad - \log_2(4\varepsilon_{\text{I}}/\eta_{\text{I}}^2) - 2 \log_2(1/2\eta_{\text{II}}). \end{aligned} \quad (209)$$

Since the above number of private message bits is achievable for a fixed distribution p_X , it is then possible to optimize over all distributions to conclude that it is possible to send the following number of private message bits:

$$\begin{aligned} \log_2 |\mathcal{M}| &= \\ &\sup_{p_X} \left[I_H^{\varepsilon_{\text{I}} - \eta_{\text{I}}}(X; B)_{\rho} - \sup_{s \in \mathcal{S}} \tilde{I}_{\max}^{\varepsilon_{\text{II}} - \eta_{\text{II}}}(E; X)_{\rho^s} \right] \\ &\quad - \log_2(4\varepsilon_{\text{I}}/\eta_{\text{I}}^2) - 2 \log_2(1/2\eta_{\text{II}}), \end{aligned} \quad (210)$$

concluding the proof. ■

Remark 5 If desired, this private communication scheme can be derandomized along the lines shown in [Wil17a], in order to end up with a scheme that does not require public shared randomness. After doing so, the protocol is no longer guaranteed to be secure against an arbitrary state of the eavesdropper in the uncertainty set \mathcal{S} . The resulting protocol is only guaranteed to be secure against a fixed, known eavesdropper, similar to the standard information-theoretic model of private communication from [Dev05, CWY04].

IV. SECRET KEY DISTILLATION FROM A COMPOUND QUANTUM WIRETAP SOURCE WITH FIXED MARGINAL

A. One-shot setting

The setting of secret key distillation from a compound quantum wiretap source with fixed marginal can be considered the static version of the dynamic setting presented in Section III A, and so many aspects are similar. In this setting, we suppose that Alice has system X , Bob system B , and Eve system E of the following classical-quantum-quantum compound wiretap source state with fixed marginal:

$$\rho_{XBE}^s := \sum_x p_X(x) |x\rangle\langle x|_X \otimes \rho_{BE}^{x,s}, \quad (211)$$

where $s \in \mathcal{S}$. In this model, the marginal state of Alice and Bob is fixed, such that they know their reduced state ρ_{XB} . That is,

$$\rho_B^{x,s} = \rho_B^x \quad \text{for all } s \in \mathcal{S}, \quad (212)$$

where

$$\rho_B^{x,s} := \text{Tr}_E[\rho_{BE}^{x,s}], \quad (213)$$

but they do not know the full state. We suppose that forward public classical communication from Alice to Bob is allowed for free. The goal is to use this compound wiretap source state in (211), along with the free public classical communication, in order to distill a key that is secure for all ρ_{XBE}^s and $s \in \mathcal{S}$.

A secret key distillation scheme consists of a classical encoding channel $\mathcal{E}_{X \rightarrow KL}$ and a decoding channel $\mathcal{D}_{LB \rightarrow \hat{K}}$. In the above, K is the classical key register of Alice, and L is a classical register communicated to Bob. Two parameters ε_{I} and ε_{II} determine the error probability when decoding and the security of the protocol, respectively. Alice uses the distillation scheme and the state in (211) to produce a uniformly random key value $k \in \mathcal{K}$ (the probability $\Pr[K = k] = 1/|\mathcal{K}|$), and the conditional probability of Bob decoding $k' \in \mathcal{K}$ from his systems is given by

$$\Pr[\hat{K} = k' | K = k] := \langle k' |_{\hat{K}} \mathcal{D}_{LB \rightarrow \hat{K}}(\rho_{KLB}^k) | k' \rangle_{\hat{K}}, \quad (214)$$

where

$$\rho_{KLB}^k := \text{Tr}_E[\rho_{KLEB}^{k,s}], \quad (215)$$

$$\rho_{KLEB}^{k,s} := \frac{\langle k|_K \mathcal{E}_{X \rightarrow KL}(\rho_{XBE})|k\rangle_K}{\text{Pr}[K=k]}, \quad (216)$$

$$= \langle k|_K \mathcal{E}_{X \rightarrow KL}(\rho_{XBE})|k\rangle_K \cdot |\mathcal{K}|. \quad (217)$$

Alternatively, we can consider Bob's positive operator-valued measure $\{\Lambda_{LB}^k\}_{k \in \mathcal{K}}$ to consist of the following elements

$$\Lambda_{LB}^k := (\mathcal{D}_{LB \rightarrow \hat{K}})^\dagger(|k\rangle\langle k|_{\hat{K}}), \quad (218)$$

where $(\mathcal{D}_{LB \rightarrow \hat{K}})^\dagger$ is the Hilbert–Schmidt adjoint of the decoding channel $\mathcal{D}_{LB \rightarrow \hat{K}}$, so that we can write the probability $\text{Pr}[\hat{K} = k'|K = k]$ in terms of the Born rule as

$$\text{Pr}[\hat{K} = k'|K = k] = \text{Tr}[\Lambda_{LB}^{k'} \rho_{KLB}^k]. \quad (219)$$

The protocol is ε_I -reliable, with $\varepsilon_I \in [0, 1]$, if the following condition holds for all $k \in \mathcal{K}$:

$$\text{Pr}[\hat{K} = k|K = k] \geq 1 - \varepsilon_I. \quad (220)$$

Equivalently, we require that

$$\sup_{k \in \mathcal{K}} \left(1 - \text{Pr}[\hat{K} = k|K = k]\right) \leq \varepsilon_I. \quad (221)$$

The protocol is ε_{II} -secret, with $\varepsilon_{II} \in [0, 1]$, if for all source values $s \in \mathcal{S}$, there exists fixed state σ_{ERE}^s of Eve's systems, such that for all key values $k \in \mathcal{K}$, the following inequality holds

$$\frac{1}{2} \left\| \rho_{LE}^{k,s} - \sigma_{LE}^s \right\|_1 \leq \varepsilon_{II}. \quad (222)$$

Equivalently, we require that

$$\sup_{s \in \mathcal{S}} \inf_{\sigma_{LE}^s} \sup_{k \in \mathcal{K}} \frac{1}{2} \left\| \rho_{LE}^{k,s} - \sigma_{LE}^s \right\|_1 \leq \varepsilon_{II}. \quad (223)$$

Thus, for each $s \in \mathcal{S}$, the protocol allows for distilling a secure key no matter which state ρ_{XBE}^s is selected from \mathcal{S} .

The number of key bits established by the scheme is equal to $\log_2 |\mathcal{K}|$. Thus, a given protocol for secret key distillation using the source in (211) is described by the three parameters $|\mathcal{K}|$, ε_I , and ε_{II} .

We remark here that the definition given above implies the usual trace-distance based criterion [KRBM07, TLGR12] for security that is commonly employed in quantum key distribution. Let K and \hat{K} denote the respective classical key registers of Alice and Bob (we identify both the random variable and the system label with the same symbol). Then the final state of the protocol, for fixed $s \in \mathcal{S}$, can be written as follows:

$$\rho_{K\hat{K}LE}^s := \sum_k \frac{1}{|\mathcal{K}|} |k\rangle\langle k|_K \otimes \sum_{k'} p(k'|k) |k'\rangle\langle k'|_{\hat{K}} \otimes \rho_{LE}^{k,s}, \quad (224)$$

where $p(k'|k) := \text{Tr}[\Lambda_{LB}^{k'} \rho_{KLB}^k]$, while the ideal state, for the same s , is as follows:

$$\bar{\Phi}_{K\hat{K}} \otimes \sigma_{LE}^s, \quad (225)$$

for some fixed state σ_{LE}^s and where $\bar{\Phi}_{K\hat{K}} := \sum_k \frac{1}{|\mathcal{K}|} |k\rangle\langle k|_K \otimes |k\rangle\langle k|_{\hat{K}}$. The conditions in (220) and (223) and the triangle inequality for trace distance imply that

$$\frac{1}{2} \left\| \rho_{K\hat{K}LE}^s - \bar{\Phi}_{K\hat{K}} \otimes \sigma_{LE}^s \right\|_1 \leq \varepsilon_I + \varepsilon_{II}. \quad (226)$$

Equivalently, we require

$$\sup_{s \in \mathcal{S}} \inf_{\sigma_{LE}^s} \frac{1}{2} \left\| \rho_{K\hat{K}LE}^s - \bar{\Phi}_{K\hat{K}} \otimes \sigma_{LE}^s \right\|_1 \leq \varepsilon_I + \varepsilon_{II}, \quad (227)$$

which is the standard trace-distance based criterion considered in the context of secret key distillation [TLGR12]. As pointed out in [TLGR12, PR14], however, this criterion is not composable. The criterion that is known to be composable is

$$\sup_{s \in \mathcal{S}} \frac{1}{2} \left\| \rho_{K\hat{K}LE}^s - \bar{\Phi}_{K\hat{K}} \otimes \rho_{LE}^s \right\|_1 \leq \varepsilon, \quad (228)$$

where $\rho_{LE}^s := \text{Tr}_{K\hat{K}}[\rho_{K\hat{K}LE}^s]$. As shown in [PR14, Appendix B], if the criterion in (227) is satisfied, then (228) is satisfied with $\varepsilon = 2(\varepsilon_I + \varepsilon_{II})$.

We end this section by remarking that this setting reduces to the traditional one-shot, secret key distillation setting from a known source, considered in quantum information-theoretic contexts [RR12], in the case that $|\mathcal{S}| = 1$.

B. Secret key distillation via position-based coding and convex splitting

Our main one-shot achievability theorem, corresponding to the key distillation setting discussed in the previous section, is as follows:

Theorem 6 Fix $\varepsilon_I, \varepsilon_{II} \in (0, 1)$, $\eta_I \in (0, \varepsilon_I)$, and $\eta_{II} \in (0, \varepsilon_{II})$. Then the following quantity is an achievable number of secret key bits that can be distilled from the compound wiretap source in (211), with decoding error probability not larger than ε_I and security parameter not larger than ε_{II} :

$$I_H^{\varepsilon_I - \eta_I}(X; B)_\rho - \sup_{s \in \mathcal{S}} \tilde{I}_{\max}^{\varepsilon_{II} - \eta_{II}}(E; X)_{\rho^s} - \log_2(4\varepsilon_I/\eta_I^2) - 2\log_2(1/2\eta_{II}), \quad (229)$$

where the entropic quantities are evaluated with respect to the state in (211).

Proof. The secret key distillation scheme consists of the following steps. Alice, Bob, and Eve begin with the

classical-quantum-quantum state in (211). Alice picks a value $k \in \mathcal{K}$ uniformly at random, and she picks a value $r \in \mathcal{R}$ uniformly at random, where $\mathcal{R} := \{1, \dots, |\mathcal{R}|\}$. She then labels her X system of the state in (211) by the pair (k, r) , as $X_{k,r}$. She prepares $|\mathcal{K}||\mathcal{R}| - 1$ independent instances of the classical state

$$\rho_X = \sum_{x \in \mathcal{X}} p_X(x) |x\rangle\langle x| \quad (230)$$

and labels the systems as $X_{1,1}, \dots, X_{k,r-1}, X_{k,r+1}, \dots, X_{|\mathcal{K}||\mathcal{R}|}$. Alice sends the classical registers $X_{1,1}, \dots, X_{|\mathcal{K}||\mathcal{R}|}$ in lexicographic order over a public classical communication channel, so that Bob and Eve receive copies of them. For fixed values of k, r , and s , the global shared state at this point is given by

$$\begin{aligned} \rho_{X^{|\mathcal{K}||\mathcal{R}|} X'^{|\mathcal{K}||\mathcal{R}|} X''^{|\mathcal{K}||\mathcal{R}|} BE} &:= \rho_{X_{1,1} X'_{1,1} X''_{1,1}} \otimes \dots \\ &\otimes \rho_{X_{k,r-1} X'_{k,r-1} X''_{k,r-1}} \otimes \rho_{X_{k,r} X'_{k,r} X''_{k,r} BE} \\ &\otimes \rho_{X_{k,r+1} X'_{k,r+1} X''_{k,r+1}} \otimes \dots \otimes \rho_{X_{|\mathcal{K}||\mathcal{R}|} X'_{|\mathcal{K}||\mathcal{R}|} X''_{|\mathcal{K}||\mathcal{R}|}}. \end{aligned} \quad (231)$$

Thus, the reduced state of Bob, for fixed k and r , is as follows:

$$\begin{aligned} \rho_{X^{|\mathcal{K}||\mathcal{R}|} B} &:= \rho_{X'_{1,1}} \otimes \dots \otimes \rho_{X'_{k,r-1}} \otimes \rho_{X'_{k,r} B} \\ &\otimes \rho_{X'_{k,r+1}} \otimes \dots \otimes \rho_{X'_{|\mathcal{K}||\mathcal{R}|}}. \end{aligned} \quad (232)$$

The reduced state of Eve, for a fixed value of k and s , is as follows:

$$\begin{aligned} \rho_{X''^{|\mathcal{K}||\mathcal{R}|} E} &:= \frac{1}{|\mathcal{R}|} \sum_{r \in \mathcal{R}} \rho_{X'_{1,1}} \otimes \dots \otimes \rho_{X'_{k,r-1}} \otimes \rho_{X'_{k,r} E} \\ &\otimes \rho_{X'_{k,r+1}} \otimes \dots \otimes \rho_{X'_{|\mathcal{K}||\mathcal{R}|}}. \end{aligned} \quad (233)$$

These reduced states are exactly the same as they are in (200) and (204), and so the same analysis applies. Bob decodes both the key value k and the local randomness value r with success probability not smaller than $1 - \varepsilon_I$, as long as

$$\log_2(|\mathcal{K}||\mathcal{R}|) = I_H^{\varepsilon_I - \eta_I}(X; B)_\rho - \log_2(4\varepsilon_I/\eta_I^2), \quad (234)$$

while the following security condition holds for all $k \in \mathcal{K}$ and $s \in \mathcal{S}$:

$$\frac{1}{2} \left\| \rho_{X''^{|\mathcal{K}||\mathcal{R}|} E}^{k,s} - \rho_{X''^{|\mathcal{K}||\mathcal{R}|}} \otimes \tilde{\rho}_E^s \right\|_1 \leq \varepsilon_{II}, \quad (235)$$

for some state $\tilde{\rho}_E^s$, as long as

$$\log_2 |\mathcal{R}| = \sup_{s \in \mathcal{S}} \tilde{I}_{\max}^{\varepsilon_{II} - \eta_{II}}(E; X)_{\rho^s} + 2 \log_2(1/2\eta_{II}). \quad (236)$$

Thus, the number of key bits that can be established with this scheme is equal to

$$\begin{aligned} \log_2 |\mathcal{K}| &= I_H^{\varepsilon_I - \eta_I}(X; B)_\rho - \sup_{s \in \mathcal{S}} \tilde{I}_{\max}^{\varepsilon_{II} - \eta_{II}}(E; X)_{\rho^s} \\ &\quad - \log_2(4\varepsilon_I/\eta_I^2) - 2 \log_2(1/2\eta_{II}), \end{aligned} \quad (237)$$

as claimed. ■

V. SECOND-ORDER ASYMPTOTICS OF PRIVATE COMMUNICATION AND SECRET KEY DISTILLATION

In this section, we show how to apply the one-shot results from Sections III and IV to the case of independent and identically distributed (i.i.d.) resources. First, let us suppose that Alice, Bob, and Eve are connected by means of a cq compound wiretap channel of the form in (168):

$$\mathcal{N}_{X \rightarrow BE}^s : x \rightarrow \rho_{BE}^{x,s}, \quad (238)$$

with all the same assumptions discussed previously in Section III A. However, now we allow them to use the channel multiple times, and we suppose that the particular value of s is fixed but unknown for all channel uses. Thus, the resource they are employing for private communication is the tensor-power channel $(\mathcal{N}_{X \rightarrow BE}^s)^{\otimes n}$, where n is a large positive integer. This setting is directly related to a collective attack in quantum key distribution, as discussed in Section II.

By applying the result of Theorem 4 to this setting, invoking Lemma 7 and the second-order asymptotic expansions discussed in (F5) and Corollary 11, with $\eta_I = \eta_{II} = 1/\sqrt{n}$, we find that it is possible to send private message bits at the following rate, for sufficiently large n , with decoding error probability not larger than ε_I and security parameter not larger than ε_{II} :

$$\begin{aligned} \frac{\log_2 |\mathcal{M}|}{n} &= \sup_{p_X} I(X; B)_\rho + \sqrt{\frac{1}{n} V(X; B)_\rho} \Phi^{-1}(\varepsilon_I) \\ &\quad - \sup_{s \in \mathcal{S}} \left[I(X; E)_{\rho^s} - \sqrt{\frac{1}{n} V(X; E)_{\rho^s}} \Phi^{-1}(\varepsilon_{II}^2) \right] \\ &\quad + O\left(\frac{\log n}{n}\right). \end{aligned} \quad (239)$$

In the above, the information quantities are evaluated with respect to the following classical-quantum state:

$$\rho_{XBE}^s := \sum_x p_X(x) |x\rangle\langle x|_X \otimes \rho_{BE}^{x,s}, \quad (240)$$

and

$$I(X; B)_\rho := \sum_x p_X(x) D(\rho_B^x \| \rho_B), \quad (241)$$

$$I(X; E)_{\rho^s} := \sum_x p_X(x) D(\rho_E^{x,s} \| \rho_E^s) \quad (242)$$

$$\rho_B := \sum_x p_X(x) \rho_B^x, \quad (243)$$

$$\rho_E^s := \sum_x p_X(x) \rho_E^{x,s}. \quad (244)$$

The Holevo information variances $V(X; B)_\rho$ and $V(X; E)_{\rho^s}$ are given by

$$V(X; B)_\rho := \sum_{x \in \mathcal{X}} p_X(x) \left[V(\rho_B^{x,s} \| \rho_B) + [D(\rho_B^{x,s} \| \rho_B)]^2 \right] - [I(X; B)_\rho]^2, \quad (245)$$

$$V(X; E)_{\rho^s} := \sum_{x \in \mathcal{X}} p_X(x) \left[V(\rho_E^{x,s} \| \rho_E^s) + [D(\rho_E^{x,s} \| \rho_E^s)]^2 \right] - [I(X; E)_{\rho^s}]^2, \quad (246)$$

with these formulas considered in more detail in Appendix G. The term $O\left(\frac{\log n}{n}\right)$ hides constants involving ε_I , ε_{II} , $T(X; B)_\rho$, and $T(X; E)_{\rho^s}$, with the latter two quantities defined in Appendix G. By noting that all of the quantities $I(X; B)_\rho$, $I(X; E)_{\rho^s}$, $V(X; B)_\rho$, $V(X; E)_{\rho^s}$, $T(X; B)_\rho$, and $T(X; E)_{\rho^s}$ involve an expectation with respect to the distribution p_X , it follows from an approximation argument that the same formula in (239) is an achievable rate for private communication when p_X is a probability distribution over a continuous alphabet. In this case, all of the expectations for the various quantities are evaluated by integration.

In the case that the states involved in the above formulas act on separable Hilbert spaces, then we should define the various quantities in more detail because the formulas in (38) and (39) need to be interpreted in a particular way (that is, the trace cannot be taken with respect to an arbitrary orthonormal basis). Suppose that ρ and σ have the following spectral decompositions:

$$\rho = \sum_x \lambda_x |\psi_x\rangle\langle\psi_x|, \quad \sigma = \sum_y \mu_y |\phi_y\rangle\langle\phi_y|. \quad (247)$$

Then the quantum relative entropy [Fal70, Lin73] and the relative entropy variance [TH13, Li14, KW17] are defined as

$$D(\rho \| \sigma) := \sum_{x,y} |\langle\phi_y | \psi_x\rangle|^2 \lambda_x \log_2 \left(\frac{\lambda_x}{\mu_y} \right), \quad (248)$$

$$V(\rho \| \sigma) := \sum_{x,y} |\langle\phi_y | \psi_x\rangle|^2 \lambda_x \left[\log_2 \left(\frac{\lambda_x}{\mu_y} \right) - D(\rho \| \sigma) \right]^2. \quad (249)$$

We can also consider the application to secret key distillation. Suppose now that Alice, Bob, and Eve share n copies of the following cqg state:

$$\rho_{XBE}^s := \sum_x p_X(x) |x\rangle\langle x|_X \otimes \rho_{BE}^{x,s}, \quad (250)$$

with all of the same assumptions discussed previously in Section IV B. Then by the same reasoning as given above, but this time applying Theorem 6, the following formula represents an achievable rate for secret key distillation, for sufficiently large n and with decoding error probability not larger than ε_I and security parameter not larger than ε_{II} :

$$\begin{aligned} \frac{\log_2 |\mathcal{K}|}{n} &= I(X; B)_\rho + \sqrt{\frac{1}{n} V(X; B)_\rho} \Phi^{-1}(\varepsilon_I) \\ &\quad - \sup_{s \in \mathcal{S}} \left[I(X; E)_{\rho^s} - \sqrt{\frac{1}{n} V(X; E)_{\rho^s}} \Phi^{-1}(\varepsilon_{II}^2) \right] \\ &\quad + O\left(\frac{\log n}{n}\right), \end{aligned} \quad (251)$$

where all information quantities are evaluated with respect to the state in (250).

VI. DISCUSSION OF COLLECTIVE ATTACKS IN QKD AND THE COMPOUND WIRETAP CHANNEL AND SOURCE

As mentioned in the introduction, from what we can gather by combing through the literature, it seems that there is a disconnect between the community of researchers working on security proofs against collective attacks in quantum key distribution and those working on key distillation from a compound wiretap source. Thus, one contribution of this paper is to connect these two research directions, with Theorem 6 and its applications in Sections II and V providing a direct link between them.

The main purpose of this section is to trace some of the historical developments and early roots of these disparate communities. This might help with unifying them going forward. To begin with, let us note that there are several reviews of quantum key distribution in which collective attacks are discussed [SBPC⁺09, Lüt14, DLQY16, XMZ⁺19]. Furthermore, there is a recent review of the compound wiretap channel that traces its development in classical information theory [SBP15].

The compound channel for classical communication was introduced in [BBT59, Wol59]. The basic idea here is that the actual communication channel is chosen from an uncertainty set $\{p_{Y|X}^s\}_s$, it is the same over a large block-length (used in an i.i.d. way), and the goal is to be able to communicate regardless of which channel is selected. The main result of [BBT59, Wol59] is that Shannon's formula for capacity becomes modified to

$$\max_{p_X} \min_s I(X; Y)_{p^s}, \quad (252)$$

where $p_{XY}^s = p_X p_{Y|X}^s$.

The classical wiretap channel $p_{YZ|X}$ and its private capacity were introduced in [Wyn75] and studied further by [CK78, Csi96, MW00]. In this model, the sender inputs the random variable X , the legitimate receiver obtains Y , and the wiretapper (eavesdropper) Z . The conditional probability distribution $p_{YZ|X}$ is known to all parties involved. The culmination of these papers was to identify the formula

$$\max_{U \rightarrow X \rightarrow YZ} [I(U; Y) - I(U; Z)] \quad (253)$$

as the private capacity of an arbitrary classical wiretap channel. The optimization is over Markov chains

$U \rightarrow X \rightarrow YZ$, where U is known as an auxiliary random variable. Interestingly, this formula provides the insight that noise at the encoder (the channel from X to U) can increase private capacity, with the reasoning being that, even though it decreases both informations $I(U; Y)$ and $I(U; Z)$, it can happen that it decreases the wiretapper's information $I(U; Z)$ by more, so that there can be a noise benefit. The main reason why the classical wiretap channel model has not been embraced by the classical cryptography community is that the model assumes that the channel to the eavesdropper is known, and this is too much to assume in practice. Interestingly, it would be some years before the compound wiretap channel and source were defined.

The source model for secret key agreement was introduced by [AC93]. In this model, two legitimate parties have access to respective random variables X and Y and an eavesdropper has access to a random variable Z described by the joint probability distribution p_{XYZ} , and the legitimate parties are allowed public classical communication. All parties know the distribution p_{XYZ} . If public classical communication is allowed only in one round from X to Y , then the secret key agreement capacity is given by the formula [AC93]

$$\max_{P_{UV|X}} [I(V; Y|U) - I(V; Z|U)]. \quad (254)$$

In independent work, it was shown that public communication can enhance the secret key agreement capacity of a wiretap channel [Mau93], and an upper bound on the secret key agreement capacity was established in the case that arbitrary public classical communication is allowed.

The notion of a collective attack in quantum key distribution was proposed by [BM97, BBB⁺02]. Since then, it has been studied intensively in quantum key distribution [SBPC⁺09, Lüt14, DLQY16, XMZ⁺19]. Quantum de Finetti theorems and their variants were proved [Ren05, CKR09], which demonstrate that general coherent (arbitrary) attacks are no better than collective attacks in the limit of large blocklength. Quantum de Finetti theorems thus establish the significance of focusing on collective attacks in the context of quantum key distribution.

The quantum wiretap channel was proposed and studied in [Dev05, CWY04]. In this model, the wiretap channel is given by $x \rightarrow \rho_{BE}^x$, with the sender having access to the input, the legitimate receiver to the quantum system B , and the eavesdropper to the quantum system E . It is assumed that the full channel is known to both the sender and legitimate receiver. An important result from [Dev05, CWY04] is that

$$\max_{U \rightarrow X} [I(U; B) - I(U; E)] \quad (255)$$

is an achievable rate at which they can communicate privately, paralleling the formula in (253) for the classical case. It is not known whether this achievable rate is optimal in general. That is, it is an open problem to

determine the private capacity of the classical-quantum wiretap channel in the general case.

The quantum wiretap source was proposed and studied in [DW05]. The model is that Alice, Bob, and Eve share a state of the form $\sum_x p(x)|x\rangle\langle x|_X \otimes \rho_{BE}^x$, and the goal is to use many copies of this state along with public classical communication in order to distill a secret key. The authors of [DW05] found that the rate

$$I(X; B) - I(X; E) \quad (256)$$

is achievable for key distillation using many copies of the aforementioned state. It is important to stress that, in this model, it is assumed that Alice and Bob have full knowledge of the state, including the state of the eavesdropper. For this reason, it is not justified to apply the formula in (256) generally when analyzing the security of quantum key distribution against collective attacks. In the special case that the quantum key distribution protocol involves preparations and measurements that are tomographically complete, the legitimate parties determine the state of the eavesdropper up to an information-theoretically irrelevant isometry, and it is then justified to apply the formula in (256) for security against collective attacks.

The classical compound wiretap channel was proposed and studied in [LKPS09] and studied further in [BBS13] (see also [SBP15] for a review). The model is that the actual wiretap channel is chosen from an uncertainty set $\{p_{YZ|X}^s\}_s$, it is the same over a large blocklength (used in an i.i.d. way), and the goal is to be able to communicate privately regardless of which channel is selected. One critical result of [LKPS09] is that the following formula is an achievable rate for private communication in this setting, when the uncertainty set is finite:

$$\max_{U \rightarrow X \rightarrow Y_s Z_s} \left[\min_s I(U; Y_s) - \max_s I(U; Z_s) \right]. \quad (257)$$

The classical compound wiretap channel model is more acceptable from a cryptographic perspective than is the standard wiretap channel model, because it allows for uncertainty in the channel to the wiretapper. However, it is still difficult to argue that anything about the channel to the wiretapper would be known in a fully classical context.

The classical compound wiretap source was considered in [BW13] and further studied in [TBS17]. The special case of a classical compound source with one fixed marginal was considered previously in [Blo10]. The model from [BW13, TBS17] is that two legitimate parties and an eavesdropper share a source chosen from an uncertainty set $\{p_{XYZ}^s\}_s$, and they are allowed public classical communication to assist in the task of distilling a secret key. In [TBS17], a formula for the achievable distillable secret key was given, and we refer to [TBS17] for the details. In the special case that the marginals X and Y are fixed, the results of [Blo10, TBS17] imply that the rate

$$I(X; Y) - \max_s I(X; Z) \quad (258)$$

is achievable for key distillation.

The compound quantum wiretap source was proposed and studied in [BJ16]. The model studied there is that the legitimate parties and the eavesdropper share a state $\rho_{XBE}^s = \sum_x p^s(x) |x\rangle\langle x|_X \otimes \rho_{BE}^{x,s}$ selected from an uncertainty set $\{\rho_{XBE}^s\}_s$, and the goal is to use one round of forward public classical communication from X to B in order to distill a secret key. In [BJ16], a formula for the achievable distillable secret key was given, and we refer to [BJ16] for the details. In the special case that the marginals X and B are fixed, the results of [BJ16] imply that the rate

$$I(X; B) - \max_s I(X; E) \quad (259)$$

is achievable. An even further special case is when the B system is classical. Thus, the results of [BJ16] can be used to analyze the security of quantum key distribution against collective attacks. This model is acceptable from a cryptographic setting because one can determine the uncertainty set for the state of the eavesdropper during the parameter estimation round of a quantum key distribution protocol. This is possible under the assumption that the eavesdropper is constrained by the laws of quantum mechanics and due to the structure of quantum mechanics. One of the contributions of our paper is to extend these results (with fixed marginal on X and B) to a second-order coding rate and have the formula apply to infinite-dimensional systems of interest in continuous-variable quantum key distribution.

The compound quantum wiretap channel was presented in [DH10, BCCD14]. In [DH10], the model is that the wiretap channel is selected from an uncertainty set $x \rightarrow \rho_{BE}^{x,s}$, indexed by s , the channel is the same over the whole blocklength (used in an i.i.d. way), and the goal is to communicate privately to the legitimate receiver B regardless of which channel is selected from the set. It is unclear whether the claims of [DH10] hold as generally as stated therein, but in the case that public shared randomness is available to the legitimate parties, then the claims of [DH10] appear to hold. The main issue with the claims of [DH10] is that the code is derandomized, and when this is done, it is no longer the case that the code is secure against all of the possible states of the adversaries, as claimed therein. One would need to apply a union bound argument, as is done in [BCCD14, Section IV]. However, this issue does not arise if the code is not derandomized (in the case that the legitimate parties have public shared randomness). The coding scheme of [DH10] is universal in the sense that all that is required for communication is a lower bound on the Holevo information with the legitimate receiver and an upper bound on the Holevo information with the wiretapper. The paper [BCCD14] considered the same model, but with the uncertainty set being known and finite. They found that the following rate is achievable for private communication in this setting:

$$\max_{U \rightarrow X \rightarrow B_s E_s} \left[\min_s I(U; B_s) - \max_s I(U; E_s) \right], \quad (260)$$

representing a quantum generalization of the main result of [LKPS09].

Going forward from here, it would be interesting to develop the compound wiretap channel and source in more detail, in order to extend the scope of the results and given the applicability to key distillation in quantum key distribution. This is one contribution of the present paper, since we have established second-order coding rates for compound wiretap channels and sources for infinite-dimensional quantum systems when there is a fixed marginal. Furthermore, the quantum key distribution application is well motivated from a cryptographic perspective, given that it is possible to constrain the possible states (uncertainty set) of an eavesdropper who operates according to the laws of quantum mechanics. This is a critical difference with the classical compound wiretap channel, in which it is not possible to do so.

A. Remarks on the Devetak–Winter formula and security against collective attacks

We now comment briefly on the use of the Devetak–Winter argument in the context of collective attacks in quantum key distribution. The formula in (259) has been consistently employed by the quantum key distribution community as an achievable rate for distillable key against collective attacks. This formula is indeed correct. However, as discussed above, the argument of [DW05] did not justify this formula. Instead, it argued for the achievability of (259) when there is a known collective attack, which is applicable in the case that the preparation and measurement procedure in a QKD protocol is tomographically complete. Specifically, one can analyze the proof of [DW05, Theorem 2.1] to see that the key distillation scheme constructed ends up depending on the state shared by all three parties and security is only guaranteed in this case. From what we can tell, the formula in (259) was first proven by [RGK05] for the qubit case and then in [Ren05, Corollary 6.5.2] for general finite-dimensional states. The latter case has also been considered in [BJ16]. For infinite-dimensional states, the present paper has established a proof that the formula in (259) is achievable.

VII. OTHER CONTRIBUTIONS

In this section, we briefly list some other consequences of our work. First, the task of entanglement-assisted private communication over a broadcast channel was considered recently in [QSW18]. The technique behind the proof of Theorem 4 applies to this setting, allowing for protection against a quantum wiretap channel with fixed marginal to the decoding set. The result also applies to the infinite-dimensional case (separable Hilbert spaces).

We can also combine the techniques from Theorem 4 with those in [AJW19a, Theorem 1] and [Sen18, Corol-

lary 2] to find achievable rates for one-shot private communication over a compound wiretap channel with a finite uncertainty set, when the sender and receiver possess public shared randomness. These results can then be extended to second-order coding rates, and they also hold for the infinite-dimensional case (separable Hilbert spaces).

Our results lead to achievable second-order coding rates for classical communication over single-mode bosonic channels, when assisted by randomness, and thus extend the findings of [WRG16, OMW19]. Our results also lead to achievable second-order coding rates for private classical communication over the same channels, when assisted by public shared randomness, thus generalizing the findings of [Wil17a].

VIII. CONCLUSION

In this paper, we have provided a second-order analysis of quantum key distribution as a bridge between the asymptotic and non-asymptotic regimes. The technical contributions that allowed for this advance are a coding theorem for one-shot key distillation from a compound quantum wiretap source with fixed marginal, as well as the establishment of the second-order asymptotics for the smooth max-relative entropy. Another contribution is a coding theorem for private communication over a compound quantum wiretap channel with fixed marginal. We also showed how to optimize the second-order coding rate for several exemplary QKD protocols, including six-state, BB84, and continuous-variable QKD. In Section VII, we briefly mentioned several other immediate applications of our technical results.

Going forward from here, an important open problem is to provide a full second-order analysis of both the pa-

rameter estimation and key distillation steps of a quantum key distribution protocol. At the moment, we have exclusively analyzed second-order coding rates for the key distillation step, under the assumption that the parameter estimation step provides reliable estimates. It seems plausible to incorporate the latest developments from [Hay19], in combination with the methods of this paper, in order to have a complete second-order analysis of both parameter estimation and key distillation.

Another practical concern is to reduce the amount of public shared randomness that the protocol from Theorem 4 employs. Likewise, it would be ideal to reduce the amount of public classical communication used by the protocol from Theorem 6. Even though these resources are typically considered essentially free in a private communication setting, it would still be ideal to minimize their consumption. We note here that this large usage of a free resource is typical of the methods of position-based coding [AJW19b] and convex splitting [ADJ17], which seems to be the cost for obtaining such simple formulas in the one-shot case. Recent work in other domains has shown how to reduce the amount of free resource that these kinds of protocols consume [Ans18].

We think it would also be interesting to consider secret key distillation in the setting of private communication per unit cost from [DPW19]. It seems likely that the key distillation protocol given in Theorem 6 could be helpful for this task.

We acknowledge discussions with Nilanjana Datta, Anthony Leverrier, Stefano Mancini, and Samad Khabbazi Oskouei. MMW, SK, and EK acknowledge support from the National Science Foundation under grant no. 1714215. SG acknowledges support from the National Science Foundation (NSF) RAISE-EQuIP: “Engineering Quantum Integrated Platforms for Quantum Communication” Program, under University of Arizona Grant Number 1842559.

-
- [ABJT18] Anurag Anshu, Mario Berta, Rahul Jain, and Marco Tomamichel. Partially smoothed information measures. July 2018. arXiv:1807.05630v2.
- [ABJT19] Anurag Anshu, Mario Berta, Rahul Jain, and Marco Tomamichel. A minimax approach to one-shot entropy inequalities. June 2019. arXiv:1906.00333v1.
- [AC93] Rudolf Ahlswede and Imre Csiszar. Common randomness in information theory and cryptography. i. secret sharing. *IEEE Transactions on Information Theory*, 39(4):1121–1132, July 1993.
- [ADH08] Remigiusz Augusiak, Maciej Demianowicz, and Paweł Horodecki. Universal observable detecting all two-qubit entanglement and determinant-based separability tests. *Physical Review A*, 77(3):030301, March 2008. arXiv:quant-ph/0604109.
- [ADJ17] Anurag Anshu, Vamsi Krishna Devabathini, and Rahul Jain. Quantum communication using coherent rejection sampling. *Physical Review Letters*, 119(12):120506, September 2017. arXiv:1410.3031.
- [AJW19a] Anurag Anshu, Rahul Jain, and Naqeeb A. Warsi. A hypothesis testing approach for communication over entanglement-assisted compound quantum channel. *IEEE Transactions on Information Theory*, 65(4):2623–2636, April 2019. arXiv:1706.08286.
- [AJW19b] Anurag Anshu, Rahul Jain, and Naqeeb Ahmad Warsi. One shot entanglement assisted classical and quantum communication over noisy quantum channels: A hypothesis testing and convex split approach. *IEEE Transactions on Information Theory*, 65(2):1287–1306, February 2019. arXiv:1702.01940.
- [AMKB11] Silvestre Abruzzo, Markus Mertz, Hermann Kampermann, and Dagmar Bruss. Finite-key analysis of the six-state protocol with photon number resolution detectors. In Roberto Zamoni, François Kajzar, Attila A. Szepe, Mark T. Gruneisen, Miloslav Dusek, John G. Rarity, Colin Lewis, and Douglas Burgess, editors, *Optics and Photonics for Counterterrorism and Crime Fighting VII; Optical Materials in Defence Systems Technology*

- VIII; and *Quantum-Physics-based Information Security*, volume 8189, pages 352–362. International Society for Optics and Photonics, SPIE, 2011. arXiv:1111.2798.
- [Ans18] Anurag Anshu. *One-Shot Protocols for Communication over Quantum Networks: Achievability and Limitations*. PhD thesis, National University of Singapore, May 2018. <https://scholarbank.nus.edu.sg/handle/10635/146923>.
- [BB84] Charles H. Bennett and Gilles Brassard. Quantum cryptography: Public key distribution and coin tossing. In *Proceedings of IEEE International Conference on Computers Systems and Signal Processing*, pages 175–179, Bangalore, India, December 1984.
- [BBB⁺02] Eli Biham, Michel Boyer, Gilles Brassard, Jeroen van de Graaf, and Tal Mor. Security of quantum key distribution against all collective attacks. *Algorithmica*, 34(4):372–388, November 2002. arXiv:quant-ph/9801022.
- [BBS13] Igor Bjelaković, Holger Boche, and Jochen Sommerfeld. Secrecy results for compound wiretap channels. *Problems of Information Transmission*, 49(1):73–98, January 2013. arXiv:1106.2013.
- [BBT59] David Blackwell, Leo Breiman, and A. J. Thomasian. The capacity of a class of channels. *The Annals of Mathematical Statistics*, 30(4):1229–1241, 12 1959.
- [BCCD14] Holger Boche, Minglai Cai, Ning Cai, and Christian Deppe. Secrecy capacities of compound quantum wiretap channels and applications. *Physical Review A*, 89(5):052320, May 2014. arXiv:1302.3412.
- [BCR11] Mario Berta, Matthias Christandl, and Renato Renner. The quantum reverse Shannon theorem based on one-shot information theory. *Communications in Mathematical Physics*, 306(3):579–615, August 2011. arXiv:0912.3805.
- [BD10] Francesco Buscemi and Nilanjana Datta. The quantum capacity of channels with arbitrarily correlated noise. *IEEE Transactions on Information Theory*, 56(3):1447–1460, March 2010. arXiv:0902.0158.
- [BD11] Fernando G. S. L. Brandao and Nilanjana Datta. One-shot rates for entanglement manipulation under non-entangling maps. *IEEE Transactions on Information Theory*, 57(3):1754–1760, March 2011. arXiv:0905.2673.
- [BDSW96] Charles H. Bennett, David P. DiVincenzo, John A. Smolin, and William K. Wootters. Mixed-state entanglement and quantum error correction. *Physical Review A*, 54(5):3824–3851, November 1996. arXiv:quant-ph/9604024.
- [BJ16] Holger Boche and Gisbert Janßen. Distillation of secret-key from a class of compound memoryless quantum sources. *Journal of Mathematical Physics*, 57(8):082201, August 2016. arXiv:1604.05530.
- [Blo10] Matthieu Bloch. Channel intrinsic randomness. In *2010 IEEE International Symposium on Information Theory*, pages 2607–2611, June 2010.
- [BM97] Eli Biham and Tal Mor. Security of quantum cryptography against collective attacks. *Physical Review Letters*, 78(11):2256–2259, March 1997. arXiv:quant-ph/9605007.
- [BPG99] H. Bechmann-Pasquinucci and Nicolas Gisin. Incoherent and coherent eavesdropping in the six-state protocol of quantum cryptography. *Physical Review A*, 59(6):4238–4248, June 1999.
- [Bru98] Dagmar Bruß. Optimal eavesdropping in quantum cryptography with six states. *Physical Review Letters*, 81(14):3018–3021, October 1998. arXiv:quant-ph/9805019.
- [BW13] Holger Boche and Rafael F. Wyrembelski. Secret key generation using compound sources - optimal key-rates and communication costs. In *SCC 2013; 9th International ITG Conference on Systems, Communication and Coding*, pages 1–6, January 2013.
- [BW18] Kamil Brádler and Christian Weedbrook. Security proof of continuous-variable quantum key distribution using three coherent states. *Physical Review A*, 97(2):022310, February 2018. arXiv:1709.01758.
- [CCD12] Minglai Cai, Ning Cai, and Christian Deppe. Capacities of classical compound quantum wiretap and classical quantum compound wiretap channels. In *Proceedings of the 2012 IEEE International Symposium on Information Theory*, pages 726–730, July 2012. arXiv:1202.0773.
- [CG06] Filippo Caruso and Vittorio Giovannetti. Degradability of bosonic Gaussian channels. *Physical Review A*, 74(6):062307, December 2006. arXiv:quant-ph/0603257.
- [CGH06] Filippo Caruso, Vittorio Giovannetti, and Alexander S. Holevo. One-mode bosonic Gaussian channels: a full weak-degradability classification. *New Journal of Physics*, 8(12):310, December 2006. arXiv:quant-ph/0609013.
- [Che05] Xiao-yu Chen. Gaussian relative entropy of entanglement. *Physical Review A*, 71(6):062320, June 2005. arXiv:quant-ph/0402109.
- [CK78] Imre Csiszár and Janos Körner. Broadcast channels with confidential messages. *IEEE Transactions on Information Theory*, 24(3):339–348, May 1978.
- [CKR09] Matthias Christandl, Robert König, and Renato Renner. Postselection technique for quantum channels with applications to quantum cryptography. *Physical Review Letters*, 102(2):020504, January 2009. arXiv:0809.3019.
- [CLL04] Marcos Curty, Maciej Lewenstein, and Norbert Lütkenhaus. Entanglement as a precondition for secure quantum key distribution. *Physical Review Letters*, 92(21):217903, May 2004. arXiv:quant-ph/0307151.
- [CML16] Patrick J. Coles, Eric M. Metodiev, and Norbert Lütkenhaus. Numerical approach for unstructured quantum key distribution. *Nature Communications*, 7:11712, May 2016. arXiv:1510.01294.
- [CN97] Isaac L. Chuang and M. A. Nielsen. Prescription for experimental determination of the dynamics of a quantum black box. *Journal of Modern Optics*, 44(11-12):2455–2467, 1997. arXiv:quant-ph/9610001.
- [Csi96] Imre Csiszár. Almost independence and secrecy capacity. *Problems of Information Transmission*, 32(1):40–47, 1996.
- [CWY04] Ning Cai, Andreas Winter, and Raymond W. Yeung. Quantum privacy and quantum wiretap channels. *Problems of Information Transmission*, 40(4):318–336, October 2004.
- [Dat09a] Nilanjana Datta. Max-relative entropy of entanglement, alias log robustness. *International Journal of Quantum Information*, 7(02):475–491, January 2009. arXiv:0807.2536.
- [Dat09b] Nilanjana Datta. Min- and max-relative entropies and a new entanglement monotone. *IEEE Transactions*

- on *Information Theory*, 55(6):2816–2826, June 2009. arXiv:0803.2770.
- [Dev05] Igor Devetak. The private classical capacity and quantum capacity of a quantum channel. *IEEE Transactions on Information Theory*, 51(1):44–55, January 2005. arXiv:quant-ph/0304127.
- [DF19] Frederic Dupuis and Omar Fawzi. Entropy accumulation with improved second-order term. *IEEE Transactions on Information Theory (to appear)*, 2019. arXiv:1805.11652.
- [DH10] Nilanjana Datta and Min-Hsiu Hsieh. Universal coding for transmission of private information. *Journal of Mathematical Physics*, 51(12):122202, December 2010. arXiv:1007.2629.
- [DHC05] W. Dür, M. Hein, J. I. Cirac, and H.-J. Briegel. Standard forms of noisy quantum operations via depolarization. *Physical Review A*, 72(5):052326, November 2005. arXiv:quant-ph/0507134.
- [DL15] Nilanjana Datta and Felix Leditzky. Second-order asymptotics for source coding, dense coding, and pure-state entanglement conversions. *IEEE Transactions on Information Theory*, 61(1):582–608, January 2015. arXiv:1403.2543.
- [DLQY16] Eleni Diamanti, Hoi-Kwong Lo, Bing Qi, and Zhiliang Yuan. Practical challenges in quantum key distribution. *npj Quantum Information*, 2:16025, November 2016. arXiv:1606.05853.
- [DPR16] Nilanjana Datta, Yan Pautrat, and Cambyse Rouzé. Second-order asymptotics for quantum hypothesis testing in settings beyond i.i.d. - quantum lattice systems and more. *Journal of Mathematical Physics*, 57(6):062207, June 2016. arXiv:1510.04682.
- [DPW19] Dawei Ding, Dimitri S. Pavlichin, and Mark M. Wilde. Quantum channel capacities per unit cost. *IEEE Transactions on Information Theory*, 65(1):418–435, January 2019. arXiv:1705.08878.
- [DTW16] Nilanjana Datta, Marco Tomamichel, and Mark M. Wilde. On the second-order asymptotics for entanglement-assisted communication. *Quantum Information Processing*, 15(6):2569–2591, June 2016. arXiv:1405.1797.
- [DW05] Igor Devetak and Andreas Winter. Distillation of secret key and entanglement from quantum states. *Proceedings of the Royal Society A*, 461(2053):207–235, January 2005. arXiv:quant-ph/0306078.
- [Eke91] Artur K. Ekert. Quantum cryptography based on Bell’s theorem. *Physical Review Letters*, 67(6):661–663, August 1991.
- [Fal70] Harold Falk. Inequalities of J. W. Gibbs. *American Journal of Physics*, 38(7):858–869, July 1970.
- [FAR11] Fabian Furrer, Johan Aberg, and Renato Renner. Min- and max-entropy in infinite dimensions. *Communications in Mathematical Physics*, 306(1):165–186, August 2011. arXiv:1004.1386.
- [FFB⁺12] Fabian Furrer, Torsten Franz, Mario Berta, Anthony Leverrier, Volkher B. Scholz, Marco Tomamichel, and Reinhard F. Werner. Continuous variable quantum key distribution: Finite-key analysis of composable security against coherent attacks. *Physical Review Letters*, 109(10):100502, September 2012. arXiv:1112.2179.
- [Fur14] Fabian Furrer. Reverse-reconciliation continuous-variable quantum key distribution based on the uncertainty principle. *Physical Review A*, 90(4):042325, October 2014. arXiv:1405.5965.
- [GG02a] Frédéric Grosshans and Philippe Grangier. Continuous variable quantum cryptography using coherent states. *Physical Review Letters*, 88(5):057902, January 2002. arXiv:quant-ph/0109084.
- [GG02b] Frédéric Grosshans and Philippe Grangier. Reverse reconciliation protocols for quantum cryptography with continuous variables. *Proceedings of the 6th International Conference on Quantum Communications, Measurement, and Computing*, 2002. arXiv:quant-ph/0204127.
- [GGDL19] Shouvik Ghorai, Philippe Grangier, Eleni Diamanti, and Anthony Leverrier. Asymptotic security of continuous-variable quantum key distribution with a discrete modulation. *Physical Review X*, 9(2):021059, June 2019. arXiv:1902.01317.
- [GK04] Christopher Gerry and Peter Knight. *Introductory Quantum Optics*. Cambridge University Press, November 2004.
- [GLN05] Alexei Gilchrist, Nathan K. Langford, and Michael A. Nielsen. Distance measures to compare real and ideal quantum processes. *Physical Review A*, 71(6):062310, June 2005. arXiv:quant-ph/0408063.
- [GLS16] Marco G. Genoni, Ludovico Lami, and Alessio Serafini. Conditional and unconditional gaussian quantum dynamics. *Contemporary Physics*, 57(3):331–349, January 2016. arXiv:1607.02619.
- [GPC06] Raúl García-Patrón and Nicolas J. Cerf. Unconditional optimality of Gaussian attacks against continuous-variable quantum key distribution. *Physical Review Letters*, 97(19):190503, November 2006. arXiv:quant-ph/0608032.
- [Guh04] Saikat Guha. Classical capacity of the free-space quantum-optical channel. Master’s thesis, Massachusetts Institute of Technology, January 2004.
- [Hay06] Masahito Hayashi. Practical evaluation of security for quantum key distribution. *Physical Review A*, 74(2):022307, August 2006. arXiv:quant-ph/0602113.
- [Hay09] Masahito Hayashi. Information spectrum approach to second-order coding rate in channel coding. *IEEE Transactions on Information Theory*, 55(11):4947–4966, November 2009. arXiv:0801.2242.
- [Hay19] Masahito Hayashi. Universal channel coding for general output alphabet. *IEEE Transactions on Information Theory*, 65(1):302–321, January 2019. arXiv:1502.02218.
- [Hol73] Alexander S. Holevo. Bounds for the quantity of information transmitted by a quantum communication channel. *Problems of Information Transmission*, 9:177–183, 1973.
- [Hol10] Alexander S. Holevo. The entropy gain of infinite-dimensional quantum channels. *Doklady Mathematics*, 82(2):730–731, October 2010. arXiv:1003.5765.
- [Hol12] Alexander S. Holevo. *Quantum systems, channels, information: a mathematical introduction*, volume 16. Walter de Gruyter, 2012.
- [HT12] Masahito Hayashi and Toyohiro Tsurumaru. Concise and tight security analysis of the Bennett-Brassard 1984 protocol with finite key lengths. *New Journal of Physics*, 14(9):093014, September 2012. arXiv:1107.0589.
- [HZ12] Teiko Heinosaari and Mário Ziman. *The Mathematical Language of Quantum Theory: From Uncertainty to Entanglement*. Cambridge University Press, 2012.
- [Iss18] Leon Isserlis. On a formula for the product-moment coefficient of any order of a normal frequency dis-

- tribution in any number of variables. *Biometrika*, 12(1/2):134–139, 1918.
- [JN12] Rahul Jain and Ashwin Nayak. Short proofs of the quantum substate theorem. *IEEE Transactions on Information Theory*, 58(6):3664–3669, June 2012. arXiv:1103.6067.
- [KGW19] Eneet Kaur, Saikat Guha, and Mark M. Wilde. Asymptotic security of discrete-modulation protocols for continuous-variable quantum key distribution. January 2019. arXiv:1901.10099.
- [Kha16] Sumeet Khatri. Symmetric extendability of quantum states and the extreme limits of quantum key distribution. Master’s thesis, University of Waterloo, 2016. <https://uwspace.uwaterloo.ca/handle/10012/10993>.
- [Koa06] Masato Koashi. Unconditional security of quantum key distribution and the uncertainty principle. *Journal of Physics: Conference Series*, 36:98–102, April 2006.
- [KR08] Oliver Kern and Joseph M. Renes. Improved one-way rates for BB84 and 6-state protocols. *Quantum Information and Computation*, 8(8):756–772, September 2008. arXiv:0712.1494.
- [KRBm07] Robert König, Renato Renner, Andor Bariska, and Ueli Maurer. Small accessible quantum information does not imply security. *Physical Review Letters*, 98(14):140502, April 2007. arXiv:quant-ph/0512021.
- [Kru06] Ole Krueger. *Quantum Information Theory with Gaussian Systems*. PhD thesis, Technische Universität Braunschweig, April 2006. Available at https://publikationsserver.tu-braunschweig.de/receive/dbbs_mods_00020741.
- [KS10] V. Yu. Korolev and Irina G. Shevtsova. On the upper bound for the absolute constant in the Berry-Esseen inequality. *Theory of Probability & Its Applications*, 54(4):638–658, November 2010.
- [KW17] Eneet Kaur and Mark M. Wilde. Upper bounds on secret key agreement over lossy thermal bosonic channels. *Physical Review A*, 96(6):062318, December 2017. arXiv:1706.04590.
- [LC99] Hoi-Kwong Lo and Hoi Fung Chau. Unconditional security of quantum key distribution over arbitrarily long distances. *Science*, 283(5410):2050–2056, March 1999. arXiv:quant-ph/9803006.
- [LCT14] Hoi-Kwong Lo, Marcos Curty, and Kiyoshi Tamaki. Secure quantum key distribution. *Nature Photonics*, 8:595–604, July 2014. arXiv:1505.05303.
- [Lev15] Anthony Leverrier. Composable security proof for continuous-variable quantum key distribution with coherent states. *Physical Review Letters*, 114(7):070501, February 2015. arXiv:1408.5689.
- [Lev17] Anthony Leverrier. Security of continuous-variable quantum key distribution via a Gaussian de Finetti reduction. *Physical Review Letters*, 118(20):200501, May 2017. arXiv:1701.03393.
- [LGG10] Anthony Leverrier, Frédéric Grosshans, and Philippe Grangier. Finite-size analysis of a continuous-variable quantum key distribution. *Physical Review A*, 81(6):062343, June 2010. arXiv:1005.0339.
- [Li14] Ke Li. Second order asymptotics for quantum hypothesis testing. *Annals of Statistics*, 42(1):171–189, February 2014. arXiv:1208.1400.
- [Lin73] Göran Lindblad. Entropy, information and quantum measurements. *Communications in Mathematical Physics*, 33(4):305–322, December 1973.
- [LKPS09] Yingbin Liang, Gerhard Kramer, H. Vincent Poor, and Shlomo Shamai (Shitz). Compound wiretap channels. *EURASIP Journal on Wireless Communications and Networking*, 2009(1):142374, 2009.
- [Lo01] Hoi-Kwong Lo. Proof of unconditional security of six-state quantum key distribution scheme. *Quantum Information and Computation*, 1(2):81–94, August 2001. arXiv:quant-ph/0102138.
- [LUL19] Jie Lin, Twesh Upadhyaya, and Norbert Lütkenhaus. Asymptotic security analysis of discrete-modulated continuous-variable quantum key distribution. May 2019. arXiv:1905.10896.
- [Lüt14] Norbert Lütkenhaus. *Quantum Information and Coherence*, chapter Quantum Key Distribution, pages 107–146. Springer International Publishing, 2014.
- [LW19] Zi-Wen Liu and Andreas Winter. Resource theories of quantum channels and the universal role of resource erasure. April 2019. arXiv:1904.04201v1.
- [Mau93] Ueli M. Maurer. Secret key agreement by public discussion from common information. *IEEE Transactions on Information Theory*, 39(3):733–742, May 1993.
- [May01] Dominic Mayers. Unconditional security in quantum cryptography. *Journal of the ACM*, 48(3):351–406, May 2001. arXiv:quant-ph/9802025.
- [MW00] Ueli Maurer and Stefan Wolf. Information-theoretic key agreement: From weak to strong secrecy for free. In Bart Preneel, editor, *Advances in Cryptology — EUROCRYPT 2000*, pages 351–368, Berlin, Heidelberg, 2000. Springer Berlin Heidelberg.
- [Myh10] Geir Ove Myhr. *Symmetric extension of bipartite quantum states and its use in quantum key distribution with two-way postprocessing*. PhD thesis, Friedrich-Alexander-Universität Erlangen-Nürnberg, November 2010. arXiv:1103.0766.
- [NGA06] Miguel Navascués, Frédéric Grosshans, and Antonio Acín. Optimality of Gaussian attacks in continuous-variable quantum cryptography. *Physical Review Letters*, 97(19):190502, November 2006. arXiv:quant-ph/0608034.
- [Nota] In some QKD protocols, the entire joint distribution of Alice’s and Bob’s classical data $p_{XY}(x, y)$ need not be estimated in order to distill a secure key. A well known example is CV-QKD, where only two scalar parameters need to be estimated in order to derive a key-rate lower bound under a collective-attack assumption, even in a finite key-length regime [Lev15]. It is possible that, for such protocols, the second-order correction to the key distillation rate that we present in this paper could be extended to a formulation that does not require the estimation of $p_{XY}(x, y)$.
- [Notb] When estimating $p_{Y|X}$, we can bin the outcomes of the joint distribution p_{XY} to get a discrete distribution $p_{X_m Y_m}$. Then we can estimate this finite distribution $p_{X_m Y_m}$ instead, which is reasonable since there are a finite number of parameters, and plug the values into the classical mutual information $I(X_m; Y_m)$ and classical mutual information variance $V(X_m; Y_m)$ for a second-order coding rate for information reconciliation. Then the limits $I(X_m; Y_m) \rightarrow I(X; Y)$ and $V(X_m; Y_m) \rightarrow V(X; Y)$ hold as the bin size gets smaller.
- [OMW19] Samad Khazbazi Oskoui, Stefano Mancini, and Mark M. Wilde. Union bound for quantum information processing. *Proceedings of the Royal Society A*, 475(2221):20180612, January 2019. arXiv:1804.08144.

- [PCZ97] J. F. Poyatos, J. Ignacio Cirac, and Peter Zoller. Complete characterization of a quantum process: The two-bit quantum gate. *Physical Review Letters*, 78(2):390–393, January 1997. arXiv:quant-ph/9611013.
- [Pir17] Pirandola *et al.* Fundamental limits of repeaterless quantum communications. *Nat. Comm.*, 8(15043), 2017.
- [Pol13] Yury Polyanskiy. On dispersion of compound DMCs. In *2013 51st Annual Allerton Conference on Communication, Control, and Computing (Allerton)*, pages 26–32, October 2013.
- [PPV10] Yury Polyanskiy, H. Vincent Poor, and Sergio Verdú. Channel coding rate in the finite blocklength regime. *IEEE Transactions on Information Theory*, 56(5):2307–2359, May 2010.
- [PR14] Christopher Portmann and Renato Renner. Cryptographic security of quantum key distribution. 2014. arXiv:1409.3525.
- [QSW18] Haoyu Qi, Kunal Sharma, and Mark M. Wilde. Entanglement-assisted private communication over quantum broadcast channels. *Journal of Physics A: Mathematical and Theoretical*, 51(37):374001, August 2018. arXiv:1803.03976.
- [Ras02] Alexey E. Rastegin. Relative error of state-dependent cloning. *Physical Review A*, 66(4):042304, October 2002.
- [Ras03] Alexey E. Rastegin. A lower bound on the relative error of mixed-state cloning and related operations. *Journal of Optics B: Quantum and Semiclassical Optics*, 5(6):S647, December 2003. arXiv:quant-ph/0208159.
- [Ras06] Alexey E. Rastegin. Sine distance for quantum states. February 2006. arXiv:quant-ph/0602112.
- [RC09] Renato Renner and J. I. Cirac. de Finetti representation theorem for infinite-dimensional quantum systems and applications to quantum cryptography. *Physical Review Letters*, 102(11):110504, March 2009. arXiv:0809.2243.
- [Ren05] Renato Renner. *Security of Quantum Key Distribution*. PhD thesis, ETH Zurich, September 2005. arXiv:quant-ph/0512258.
- [RGK05] Renato Renner, Nicolas Gisin, and Barbara Kraus. Information-theoretic security proof for quantum-key-distribution protocols. *Physical Review A*, 72(1):012332, July 2005. arXiv:quant-ph/0502064.
- [RR12] Joseph M. Renes and Renato Renner. One-shot classical data compression with quantum side information and the distillation of common randomness or secret keys. *IEEE Transactions on Information Theory*, 58(3):1985–1991, March 2012. arXiv:1008.0452.
- [RS78] M. Reed and B. Simon. *Methods of Modern Mathematical Physics*, volume I: Functional Analysis. Academic Press, New York, 1978.
- [Sav12] Ivan Savov. *Network information theory for classical-quantum channels*. PhD thesis, McGill University, School of Computer Science, July 2012.
- [SBP15] Rafael F. Schaefer, Holger Boche, and H. Vincent Poor. Secure communication under channel uncertainty and adversarial attacks. *Proceedings of the IEEE*, 103(10):1796–1813, October 2015.
- [SBPC⁺09] Valerio Scarani, Helle Bechmann-Pasquinucci, Nicolas J. Cerf, Miloslav Dušek, Norbert Lütkenhaus, and Momtchil Peev. The security of practical quantum key distribution. *Reviews of Modern Physics*, 81(3):1301–1350, September 2009. arXiv:0802.4155.
- [Sen18] Pranab Sen. A one-shot quantum joint typicality lemma. June 2018. arXiv:1806.07278v2.
- [Ser17] Alessio Serafini. *Quantum Continuous Variables: A Primer of Theoretical Methods*. CRC Press, Taylor & Francis Group, 2017.
- [Sha48] Claude E. Shannon. A mathematical theory of communication. *Bell System Technical Journal*, 27:379–423, 1948.
- [She11] Irina Shevtsova. On the absolute constants in the Berry-Esseen type inequalities for identically distributed summands. November 2011. arXiv:1111.6554.
- [SP00] Peter W. Shor and John Preskill. Simple proof of security of the BB84 quantum key distribution protocol. *Physical Review Letters*, 85(2):441–444, July 2000. arXiv:quant-ph/0003004.
- [SRS08] Graeme Smith, Joseph M. Renes, and John A. Smolin. Structured codes improve the Bennett-Brassard-84 quantum key rate. *Physical Review Letters*, 100(17):170502, April 2008. arXiv:quant-ph/0607018.
- [SS08] Graeme Smith and John A. Smolin. Additive extensions of a quantum channel. In *2008 IEEE Information Theory Workshop*, pages 368–372, May 2008. arXiv:0712.2471.
- [Sti55] William F. Stinespring. Positive functions on C^* -algebras. *Proceedings of the American Mathematical Society*, 6:211–216, 1955.
- [Str62] Volker Strassen. Asymptotische abschätzungen in Shannons informationstheorie. In *Transactions of the Third Prague Conference on Information Theory*, pages 689–723, Prague, 1962. <http://www.math.cornell.edu/~pmlut/strassen.pdf>.
- [TBR16] Marco Tomamichel, Mario Berta, and Joseph M. Renes. Quantum coding with finite resources. *Nature Communications*, 7:11419, May 2016. arXiv:1504.04617.
- [TBS17] Nima Tavangaran, Holger Boche, and Rafael F. Schaefer. Secret-key generation using compound sources and one-way public communication. *IEEE Transactions on Information Forensics and Security*, 12(1):227–241, January 2017. arXiv:1601.07513.
- [TH13] Marco Tomamichel and Masahito Hayashi. A hierarchy of information quantities for finite block length analysis of quantum tasks. *IEEE Transactions on Information Theory*, 59(11):7693–7710, November 2013. arXiv:1208.1478.
- [TL17] Marco Tomamichel and Anthony Leverrier. A largely self-contained and complete security proof for quantum key distribution. *Quantum*, 1:14, July 2017. arXiv:1506.08458.
- [TLGR12] Marco Tomamichel, Charles Ci Wen Lim, Nicolas Gisin, and Renato Renner. Tight finite-key analysis for quantum cryptography. *Nature Communications*, 3:634, January 2012. arXiv:1103.4130.
- [TMMPE17] Marco Tomamichel, Jesus Martinez-Mateo, Christoph Pacher, and David Elkouss. Fundamental finite key limits for one-way information reconciliation in quantum key distribution. *Quantum Information Processing*, 16(11):280, October 2017. arXiv:1401.5194.
- [Tom15] Marco Tomamichel. *Quantum Information Processing with Finite Resources: Mathematical Foundations*, volume 5. Springer, 2015. arXiv:1504.00233.
- [TT15a] Vincent Y. F. Tan and Marco Tomamichel. The third-order term in the normal approximation for the awgn channel. *IEEE Transactions on Information Theory*, 61(5):2430–2438, May 2015. arXiv:1311.2337.
- [TT15b] Marco Tomamichel and Vincent Y. F. Tan. Second-order asymptotics for the classical capacity of image-

- additive quantum channels. *Communications in Mathematical Physics*, 338(1):103–137, August 2015. arXiv:1308.6503.
- [Uhl76] Armin Uhlmann. The “transition probability” in the state space of a *-algebra. *Reports on Mathematical Physics*, 9(2):273–279, April 1976.
- [Ume62] Hisaharu Umegaki. Conditional expectations in an operator algebra IV (entropy and information). *Kodai Mathematical Seminar Reports*, 14(2):59–85, 1962.
- [WGC06] Michael M. Wolf, Geza Giedke, and J. Ignacio Cirac. Extremality of Gaussian quantum states. *Physical Review Letters*, 96(8):080502, March 2006. arXiv:quant-ph/0509154.
- [Wil36] John Williamson. On the algebraic problem concerning the normal forms of linear dynamical systems. *American Journal of Mathematics*, 58(1):141–163, January 1936.
- [Wil17a] Mark M. Wilde. Position-based coding and convex splitting for private communication over quantum channels. *Quantum Information Processing*, 16(10):264, October 2017. arXiv:1703.01733.
- [Wil17b] Mark M. Wilde. *Quantum Information Theory*. Cambridge University Press, second edition, February 2017. arXiv:1106.1445.
- [WLC18] Adam Winick, Norbert Lütkenhaus, and Patrick J. Coles. Reliable numerical key rates for quantum key distribution. *Quantum*, 2:77, July 2018. arXiv:1710.05511.
- [Wol59] J. Wolfowitz. Simultaneous channels. *Archive for Rational Mechanics and Analysis*, 4(1):371–386, January 1959.
- [WR12] Ligong Wang and Renato Renner. One-shot classical-quantum capacity and hypothesis testing. *Physical Review Letters*, 108(20):200501, 2012. arXiv:1007.5456.
- [WRG16] Mark M. Wilde, Joseph M. Renes, and Saikat Guha. Second-order coding rates for pure-loss bosonic channels. *Quantum Information Processing*, 15(3):1289–1308, March 2016. arXiv:1408.5328.
- [WTB17] Mark M. Wilde, Marco Tomamichel, and Mario Berta. Converse bounds for private communication over quantum channels. *IEEE Transactions on Information Theory*, 63(3):1792–1817, March 2017. arXiv:1602.08898.
- [WTLB17] Mark M. Wilde, Marco Tomamichel, Seth Lloyd, and Mario Berta. Gaussian hypothesis testing and quantum illumination. *Physical Review Letters*, 119(12):120501, September 2017. arXiv:1608.06991.
- [WW18] Xin Wang and Mark M. Wilde. Exact entanglement cost of quantum states and channels under PPT-preserving operations. September 2018. arXiv:1809.09592v1.
- [WW19] Xin Wang and Mark M. Wilde. Resource theory of asymmetric distinguishability. May 2019. arXiv:1905.11629.
- [Wyn75] Aaron D. Wyner. The wire-tap channel. *Bell System Technical Journal*, 54(8):1355–1387, October 1975.
- [XMZ⁺19] Feihu Xu, Xiongfeng Ma, Qiang Zhang, Hoi-Kwong Lo, and Jian-Wei Pan. Quantum cryptography with realistic devices. March 2019. arXiv:1903.09051v1.
- [ZHL09] Yi-Bo Zhao, Matthias Heid, Johannes Rigas, and Norbert Lütkenhaus. Asymptotic security of binary modulated continuous-variable quantum key distribution under collective attacks. *Physical Review A*, 79(1):012307, January 2009. arXiv:0807.3751.

Appendix A: Mutual and Holevo informations and variances for six-state and BB84 protocols

When Alice and Bob discard their basis information in the six-state or BB84 protocols, then their classical data can be described via the following quantum channel:

$$\mathcal{N}_{A \rightarrow B}(\rho_A) = p_1 \rho_A + p_2 Z \rho_A Z + p_3 X \rho_A X + p_4 Y \rho_A Y, \quad (\text{A1})$$

where $p_1, p_2, p_3, p_4 \geq 0$, $p_1 + p_2 + p_3 + p_4 = 1$, and there are further constraints on p_1, p_2, p_3, p_4 .

For the six-state protocol,

$$p_1 = 1 - \frac{3Q}{2}, \quad (\text{A2})$$

$$p_2 = p_3 = p_4 = \frac{Q}{2}, \quad (\text{A3})$$

$$Q = \frac{1}{3}(Q_x + Q_y + Q_z). \quad (\text{A4})$$

For these values of p_1, p_2, p_3, p_4 , we obtain

$$p_{XY}(0, 0) := \frac{1}{2} \text{Tr}[[0 \times 0]_B \mathcal{N}_{A \rightarrow B}(|0 \times 0\rangle_A)] \quad (\text{A5})$$

$$= \frac{1}{2}(1 - Q), \quad (\text{A6})$$

$$p_{XY}(0, 1) := \frac{1}{2} \text{Tr}[[1 \times 1]_B \mathcal{N}_{A \rightarrow B}(|0 \times 0\rangle_A)] \quad (\text{A7})$$

$$= \frac{1}{2}Q, \quad (\text{A8})$$

$$p_{XY}(1, 0) := \frac{1}{2} \text{Tr}[[0 \times 0]_B \mathcal{N}_{A \rightarrow B}(|1 \times 1\rangle_A)] \quad (\text{A9})$$

$$= \frac{1}{2}Q, \quad (\text{A10})$$

$$p_{XY}(1, 1) := \frac{1}{2} \text{Tr}[[1 \times 1]_B \mathcal{N}_{A \rightarrow B}(|1 \times 1\rangle_A)] \quad (\text{A11})$$

$$= \frac{1}{2}(1 - Q), \quad (\text{A12})$$

which is consistent with the probability distribution $p_{X_2 Y_2}^{\text{6-state|sift}}$ in (109)–(112).

For the BB84 protocol,

$$p_1 = 1 - 2Q + s, \quad (\text{A13})$$

$$p_2 = Q - s, \quad (\text{A14})$$

$$p_3 = Q - s, \quad (\text{A15})$$

$$p_4 = s, \quad (\text{A16})$$

$$Q = \frac{1}{2}(Q_x + Q_z), \quad (\text{A17})$$

$$s = Q - \frac{Q_y}{2}, \quad (\text{A18})$$

where $s \in [0, Q]$ is a parameter to be optimized. Indeed, for these values of p_1, p_2, p_3, p_4 ,

$$p_{XY}(0, 0) := \frac{1}{2} \text{Tr}[[0 \times 0]_B \mathcal{N}_{A \rightarrow B}(|0 \times 0\rangle_A)] \quad (\text{A19})$$

$$= \frac{1}{2}(1 - Q), \quad (\text{A20})$$

$$p_{XY}(0, 1) := \frac{1}{2} \text{Tr} [|1\rangle\langle 1|_B \mathcal{N}_{A \rightarrow B}(|0\rangle\langle 0|_A)] \quad (\text{A21})$$

$$= \frac{1}{2} Q, \quad (\text{A22})$$

$$p_{XY}(1, 0) := \frac{1}{2} \text{Tr} [|0\rangle\langle 0|_B \mathcal{N}_{A \rightarrow B}(|1\rangle\langle 1|_A)] \quad (\text{A23})$$

$$= \frac{1}{2} Q, \quad (\text{A24})$$

$$p_{XY}(1, 1) := \frac{1}{2} \text{Tr} [|1\rangle\langle 1|_B \mathcal{N}_{A \rightarrow B}(|1\rangle\langle 1|_A)] \quad (\text{A25})$$

$$= \frac{1}{2} (1 - Q), \quad (\text{A26})$$

which is consistent with the probability distribution $p_{X_2 Y_2}^{\text{BB84|sift}}$ in (129)–(132).

In general,

$$p_{XY}(0, 0) := \frac{1}{2} \text{Tr} [|0\rangle\langle 0|_B \mathcal{N}_{A \rightarrow B}(|0\rangle\langle 0|_A)] \quad (\text{A27})$$

$$= \frac{1}{2} (p_1 + p_2), \quad (\text{A28})$$

$$p_{XY}(0, 1) := \frac{1}{2} \text{Tr} [|1\rangle\langle 1|_B \mathcal{N}_{A \rightarrow B}(|0\rangle\langle 0|_A)] \quad (\text{A29})$$

$$= \frac{1}{2} (p_3 + p_4), \quad (\text{A30})$$

$$p_{XY}(1, 0) := \frac{1}{2} \text{Tr} [|0\rangle\langle 0|_B \mathcal{N}_{A \rightarrow B}(|1\rangle\langle 1|_A)] \quad (\text{A31})$$

$$= \frac{1}{2} (p_3 + p_4), \quad (\text{A32})$$

$$p_{XY}(1, 1) := \frac{1}{2} \text{Tr} [|1\rangle\langle 1|_B \mathcal{N}_{A \rightarrow B}(|1\rangle\langle 1|_A)] \quad (\text{A33})$$

$$= \frac{1}{2} (p_1 + p_2). \quad (\text{A34})$$

Then,

$$\begin{aligned} \rho_{XY} = & \frac{1}{2} (p_1 + p_2) |0, 0\rangle\langle 0, 0| + \frac{1}{2} (p_3 + p_4) |0, 1\rangle\langle 0, 1| \\ & + \frac{1}{2} (p_3 + p_4) |1, 0\rangle\langle 1, 0| \\ & + \frac{1}{2} (p_1 + p_2) |1, 1\rangle\langle 1, 1|. \end{aligned} \quad (\text{A35})$$

It is then straightforward to show that

$$\begin{aligned} I(X; Y)_\rho = & 1 + (p_1 + p_2) \log_2(p_1 + p_2) \\ & + (p_3 + p_4) \log_2(p_3 + p_4) \end{aligned} \quad (\text{A36})$$

$$= 1 - h_2(p_1 + p_2), \quad (\text{A37})$$

where h_2 is the binary entropy function.

Let us now calculate $V(X; Y)_\rho$. We have

$$V(\rho \| \sigma) := \text{Tr} [\rho (\log_2 \rho - \log_2 \sigma)^2] - D(\rho \| \sigma)^2, \quad (\text{A38})$$

and

$$V(X; Y)_\rho := V(\rho_{XY} \| \rho_X \otimes \rho_Y) \quad (\text{A39})$$

$$= \text{Tr} [\rho_{XY} (\log_2 \rho_{XY} - \log_2 (\rho_X \otimes \rho_Y))^2] - I(X; Y)_\rho^2. \quad (\text{A40})$$

One can show that

$$\begin{aligned} & \text{Tr} [\rho_{XY} (\log_2 \rho_{XY} - \log_2 (\rho_X \otimes \rho_Y))^2] \\ &= (p_1 + p_2) (1 + \log_2(p_1 + p_2))^2 \\ & \quad + (p_3 + p_4) (1 + \log_2(p_3 + p_4))^2, \end{aligned} \quad (\text{A41})$$

from which it follows that

$$V(X; Y)_\rho = (p_1 + p_2)(p_3 + p_4) \left(\log_2 \left(\frac{p_1 + p_2}{p_3 + p_4} \right) \right)^2. \quad (\text{A42})$$

We now calculate $I(X; E)$ and $V(X; E)$. We consider the following purification of the Choi state of the channel in (A1):

$$\begin{aligned} |\psi\rangle_{ABE} := & \sqrt{p_1} |\Phi^+\rangle_{AB} |0, 0\rangle_E + \sqrt{p_2} |\Phi^-\rangle_{AB} |1, 1\rangle_E \\ & + \sqrt{p_3} |\Psi^+\rangle_{AB} |0, 1\rangle_E + \sqrt{p_4} |\Psi^-\rangle_{AB} |1, 0\rangle_E. \end{aligned} \quad (\text{A43})$$

Now,

$$\begin{aligned} & (\langle 0|_A \otimes I_{BE}) |\psi\rangle_{ABE} \\ &= |0\rangle_B \frac{1}{\sqrt{2}} (\sqrt{p_1} |0, 0\rangle_E + \sqrt{p_2} |1, 1\rangle_E) \\ & \quad + |1\rangle_B \frac{1}{\sqrt{2}} (\sqrt{p_3} |0, 1\rangle_E + \sqrt{p_4} |1, 0\rangle_E), \end{aligned} \quad (\text{A44})$$

$$\begin{aligned} & (\langle 1|_A \otimes I_{BE}) |\psi\rangle_{ABE} \\ &= |1\rangle_B \frac{1}{\sqrt{2}} (\sqrt{p_1} |0, 0\rangle_E - \sqrt{p_2} |1, 1\rangle_E) \\ & \quad + |0\rangle_B \frac{1}{\sqrt{2}} (\sqrt{p_3} |0, 1\rangle_E - \sqrt{p_4} |1, 0\rangle_E). \end{aligned} \quad (\text{A45})$$

Using this, we obtain

$$\rho_{XE} = \frac{1}{2} |0\rangle\langle 0|_X \otimes \rho_{E|X=0} + \frac{1}{2} |1\rangle\langle 1|_X \otimes \rho_{E|X=1} \quad (\text{A46})$$

$$= \begin{pmatrix} \frac{p_1}{2} & 0 & 0 & \frac{\sqrt{p_1 p_2}}{2} & 0 & 0 & 0 & 0 \\ 0 & \frac{p_3}{2} & \frac{\sqrt{p_3 p_4}}{2} & 0 & 0 & 0 & 0 & 0 \\ 0 & \frac{\sqrt{p_3 p_4}}{2} & \frac{p_4}{2} & 0 & 0 & 0 & 0 & 0 \\ \frac{\sqrt{p_1 p_2}}{2} & 0 & 0 & \frac{p_2}{2} & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & \frac{p_1}{2} & 0 & 0 & -\frac{\sqrt{p_1 p_2}}{2} \\ 0 & 0 & 0 & 0 & 0 & \frac{p_3}{2} & -\frac{\sqrt{p_3 p_4}}{2} & 0 \\ 0 & 0 & 0 & 0 & 0 & -\frac{\sqrt{p_3 p_4}}{2} & \frac{p_4}{2} & 0 \\ 0 & 0 & 0 & 0 & -\frac{\sqrt{p_1 p_2}}{2} & 0 & 0 & \frac{p_2}{2} \end{pmatrix}. \quad (\text{A47})$$

The state ρ_{XE} can be diagonalized as follows:

$$\begin{aligned} \rho_{XE} = & \left(\frac{p_1 + p_2}{2} \right) |0\rangle\langle 0|_X \otimes |\Phi_{p_1, p_2}^+\rangle\langle \Phi_{p_1, p_2}^+| \\ & + \left(\frac{p_1 + p_2}{2} \right) |1\rangle\langle 1|_X \otimes |\Phi_{p_1, p_2}^-\rangle\langle \Phi_{p_1, p_2}^-| \\ & + \left(\frac{p_3 + p_4}{2} \right) |0\rangle\langle 0|_X \otimes |\Psi_{p_3, p_4}^+\rangle\langle \Psi_{p_3, p_4}^+| \\ & + \left(\frac{p_3 + p_4}{2} \right) |1\rangle\langle 1|_X \otimes |\Psi_{p_3, p_4}^-\rangle\langle \Psi_{p_3, p_4}^-|, \end{aligned} \quad (\text{A48})$$

where

$$|\Phi_{p_1, p_2}^\pm\rangle := \frac{1}{\sqrt{\frac{p_1 + p_2}{2}}} \left(\sqrt{\frac{p_1}{2}} |0, 0\rangle \pm \sqrt{\frac{p_2}{2}} |1, 1\rangle \right), \quad (\text{A49})$$

$$|\Psi_{p_3, p_4}^\pm\rangle := \frac{1}{\sqrt{\frac{p_3 + p_4}{2}}} \left(\sqrt{\frac{p_3}{2}} |0, 1\rangle \pm \sqrt{\frac{p_4}{2}} |1, 0\rangle \right). \quad (\text{A50})$$

Then, by observing that

$$\begin{aligned} \rho_E := \text{Tr}_X[\rho_{XE}] = & p_1 |0, 0\rangle\langle 0, 0| + p_3 |0, 1\rangle\langle 0, 1| \\ & + p_4 |1, 0\rangle\langle 1, 0| + p_2 |1, 1\rangle\langle 1, 1|, \end{aligned} \quad (\text{A51})$$

we find that

$$I(X; E) = H(\vec{p}) - h_2(p_1 + p_2), \quad (\text{A52})$$

where

$$H(\vec{p}) := \sum_{i=1}^4 -p_i \log_2 p_i. \quad (\text{A53})$$

Finally, for $V(X; E)$, it is straightforward to show that

$$\begin{aligned} & \text{Tr}[\rho_{XE}(\log_2 \rho_{XE} - \log_2(\rho_X \otimes \rho_E))^2] \\ &= p_1 \left(\log_2 \left(\frac{p_1}{p_1 + p_2} \right) \right)^2 + p_2 \left(\log_2 \left(\frac{p_2}{p_1 + p_2} \right) \right)^2 \\ &+ p_3 \left(\log_2 \left(\frac{p_3}{p_3 + p_4} \right) \right)^2 + p_4 \left(\log_2 \left(\frac{p_4}{p_3 + p_4} \right) \right)^2, \end{aligned} \quad (\text{A54})$$

from which it follows that

$$\begin{aligned} V(X; E) = & p_1 \left(\log_2 \left(\frac{p_1}{p_1 + p_2} \right) \right)^2 \\ & + p_2 \left(\log_2 \left(\frac{p_2}{p_1 + p_2} \right) \right)^2 + p_3 \left(\log_2 \left(\frac{p_3}{p_3 + p_4} \right) \right)^2 \\ & + p_4 \left(\log_2 \left(\frac{p_4}{p_3 + p_4} \right) \right)^2 - (H(\vec{p}) - h_2(p_1 + p_2))^2. \end{aligned} \quad (\text{A55})$$

For the six-state protocol, by using the formulas above and (A2)–(A4), we obtain

$$I(X; Y)_\rho = 1 - h_2(Q), \quad (\text{A56})$$

$$V(X; Y)_\rho = Q(1 - Q) \left(\log_2 \left(\frac{1 - Q}{Q} \right) \right)^2, \quad (\text{A57})$$

$$\begin{aligned} I(X; E)_\rho = & - \left(1 - \frac{3Q}{2} \right) \log_2 \left(1 - \frac{3Q}{2} \right) \\ & - \frac{3Q}{2} \log_2 \left(\frac{Q}{2} \right) - h_2(Q), \end{aligned} \quad (\text{A58})$$

$$\begin{aligned} V(X; E)_\rho = & Q + \left(1 - \frac{3Q}{2} \right) \left(\log_2 \left(\frac{1 - \frac{3Q}{2}}{1 - Q} \right) \right)^2 \\ & + \frac{Q}{2} \left(\log_2 \left(\frac{\frac{Q}{2}}{1 - Q} \right) \right)^2 - I(X; E)_\rho^2. \end{aligned} \quad (\text{A59})$$

For the BB84 protocol, by using the formulas above and (A13)–(A18), we obtain

$$I(X; Y)_\rho = 1 - h_2(Q), \quad (\text{A60})$$

$$V(X; Y)_\rho = Q(1 - Q) \left(\log_2 \left(\frac{1 - Q}{Q} \right) \right)^2, \quad (\text{A61})$$

$$\begin{aligned} I(X; E)_\rho = & H(\{1 - 2Q + s, Q - s, Q - s, s\}) \\ & - h_2(Q), \end{aligned} \quad (\text{A62})$$

$$\begin{aligned} V(X; E)_\rho = & (1 - 2Q + s) \left(\log_2 \left(\frac{1 - 2Q + s}{1 - Q} \right) \right)^2 \\ & + (Q - s) \left(\log_2 \left(\frac{Q - s}{1 - Q} \right) \right)^2 \\ & + (Q - s) \left(\log_2 \left(\frac{Q - s}{Q} \right) \right)^2 \end{aligned}$$

$$+ s \left(\log_2 \left(\frac{s}{Q} \right) \right)^2 - I(X; E)_\rho^2. \quad (\text{A63})$$

Appendix B: Relation between smooth max-mutual informations

Here we prove the following lemma relating two different variants of smooth max-mutual information:

Lemma 7 *Let ρ_{AE} be a bipartite state acting on a separable Hilbert space $\mathcal{H}_A \otimes \mathcal{H}_E$, and let $\varepsilon, \delta > 0$ be such that $\varepsilon + \delta < 1$. Then*

$$\tilde{I}_{\max}^{\varepsilon+\delta}(E; A)_\rho \leq D_{\max}^\varepsilon(\rho_{AE} \| \rho_A \otimes \rho_E) + \log_2 \left(\frac{8}{\delta^2} \right), \quad (\text{B1})$$

where $\tilde{I}_{\max}^{\varepsilon+\delta}(E; A)_\rho$ is defined in (192) and $D_{\max}^\varepsilon(\rho_{AE} \| \rho_A \otimes \rho_E)$ in (191).

Proof. The proof follows the proof of [ABJT18, Theorem 2], but has some differences because it is not necessary in our case to ensure partial smoothing. Let $\tilde{\rho}_{AE}$ be a state satisfying $P(\tilde{\rho}_{AE}, \rho_{AE}) \leq \varepsilon$. Let $\gamma = \delta^2/8$, and set Π_A^γ to be the projection onto the positive eigenspace of $\frac{1}{\gamma}\tilde{\rho}_A - \rho_A$. Then it follows that

$$\begin{aligned} \Pi_A^\gamma \left(\frac{1}{\gamma}\tilde{\rho}_A - \rho_A \right) \Pi_A^\gamma &\geq 0 \\ \Rightarrow \Pi_A^\gamma \rho_A \Pi_A^\gamma &\leq \frac{1}{\gamma} \Pi_A^\gamma \tilde{\rho}_A \Pi_A^\gamma = \frac{8}{\delta^2} \Pi_A^\gamma \tilde{\rho}_A \Pi_A^\gamma, \end{aligned} \quad (\text{B2})$$

and

$$\begin{aligned} (I - \Pi_A^\gamma) \left(\frac{1}{\gamma}\tilde{\rho}_A - \rho_A \right) (I - \Pi_A^\gamma) &\leq 0 \\ \Rightarrow \text{Tr}[(I - \Pi_A^\gamma) \tilde{\rho}_A] &\leq \gamma \text{Tr}[(I - \Pi_A^\gamma) \rho_A] \leq \gamma = \frac{\delta^2}{8}, \end{aligned} \quad (\text{B3})$$

where the last inequality follows because $\text{Tr}[(I - \Pi_A^\gamma) \rho_A] \leq 1$. The inequality in (B3) can be rewritten as

$$\text{Tr}[\Pi_A^\gamma \tilde{\rho}_A] \geq 1 - \frac{\delta^2}{8}. \quad (\text{B4})$$

Let us define the following states:

$$\begin{aligned} \bar{\rho}_{AEX} &:= \Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma \otimes |0\rangle\langle 0|_X \\ &\quad + (I - \Pi_A^\gamma) \tilde{\rho}_{AE} (I - \Pi_A^\gamma) \otimes |1\rangle\langle 1|_X, \end{aligned} \quad (\text{B5})$$

$$\begin{aligned} \hat{\rho}_{AEX} &:= \\ &\left(\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma + \tilde{\rho}_A^{1/2} (I - \Pi_A^\gamma) \tilde{\rho}_A^{1/2} \otimes \rho_E \right) \otimes |0\rangle\langle 0|_X, \end{aligned} \quad (\text{B6})$$

so that

$$\hat{\rho}_{AE} = \text{Tr}_X[\hat{\rho}_{AEX}] \quad (\text{B7})$$

$$= \Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma + \tilde{\rho}_A^{1/2} (I - \Pi_A^\gamma) \tilde{\rho}_A^{1/2} \otimes \rho_E. \quad (\text{B8})$$

Then, using the inequality $\tilde{\rho}_{AE} \leq \mu \rho_A \otimes \rho_E$, with

$$\mu := 2^{D_{\max}(\tilde{\rho}_{AE} \| \rho_A \otimes \rho_E)}, \quad (\text{B9})$$

and the fact that $\mu \frac{8}{\delta^2} \geq 1$ (which holds because $D_{\max}(\tilde{\rho}_{AE} \| \rho_A \otimes \rho_E) \geq 0$ and $8 \geq \delta^2$), we find that

$$\begin{aligned} \hat{\rho}_{AE} &\leq \mu \Pi_A^\gamma \rho_A \Pi_A^\gamma \otimes \rho_E + \tilde{\rho}_A^{1/2} (I - \Pi_A^\gamma) \tilde{\rho}_A^{1/2} \otimes \rho_E \\ &\leq \mu \frac{8}{\delta^2} \Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma \otimes \rho_E + \tilde{\rho}_A^{1/2} (I - \Pi_A^\gamma) \tilde{\rho}_A^{1/2} \otimes \rho_E \\ &\leq \mu \frac{8}{\delta^2} \left[\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma \otimes \rho_E + \tilde{\rho}_A^{1/2} (I - \Pi_A^\gamma) \tilde{\rho}_A^{1/2} \otimes \rho_E \right] \\ &= \mu \frac{8}{\delta^2} \left[\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma + \tilde{\rho}_A^{1/2} (I - \Pi_A^\gamma) \tilde{\rho}_A^{1/2} \right] \otimes \rho_E \\ &= \mu \frac{8}{\delta^2} \hat{\rho}_{AE} \otimes \rho_E. \end{aligned} \quad (\text{B10})$$

The second inequality above follows from (B2). Applying the definition of $D_{\max}(\hat{\rho}_{AE} \| \hat{\rho}_A \otimes \rho_E)$, we conclude that

$$\begin{aligned} D_{\max}(\hat{\rho}_{AE} \| \hat{\rho}_A \otimes \rho_E) &\leq \\ D_{\max}(\tilde{\rho}_{AE} \| \rho_A \otimes \rho_E) &+ \log_2 \left(\frac{8}{\delta^2} \right). \end{aligned} \quad (\text{B11})$$

We can conclude the statement of the lemma if $P(\hat{\rho}_{AE}, \rho_{AE}) \leq \varepsilon + \delta$, and so it is our aim to show this now. Consider that

$$P(\hat{\rho}_{AEX}, \bar{\rho}_{AEX}) = \sqrt{1 - F(\hat{\rho}_{AEX}, \bar{\rho}_{AEX})}. \quad (\text{B12})$$

The following chain of inequalities holds

$$\begin{aligned} &\sqrt{F(\hat{\rho}_{AEX}, \bar{\rho}_{AEX})} \\ &= \text{Tr} \left[\left(\sqrt{\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma} \hat{\rho}_{AE} \sqrt{\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma} \right)^{1/2} \right] \\ &\geq \text{Tr} \left[\left(\sqrt{\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma} (\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma) \sqrt{\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma} \right)^{1/2} \right] \\ &= \text{Tr} [\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma] \\ &= \text{Tr} [\Pi_A^\gamma \tilde{\rho}_A] \\ &\geq 1 - \frac{\delta^2}{8}, \end{aligned} \quad (\text{B13})$$

where the inequality follows from operator monotonicity of the square root and the fact that

$$\hat{\rho}_{AE} = \Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma + \tilde{\rho}_A^{1/2} (I - \Pi_A^\gamma) \tilde{\rho}_A^{1/2} \otimes \rho_E \quad (\text{B14})$$

$$\geq \Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma \quad (\text{B15})$$

From the above and (B4), we conclude that $F(\hat{\rho}_{AEX}, \bar{\rho}_{AEX}) \geq 1 - \frac{\delta^2}{4}$, which implies that

$$P(\hat{\rho}_{AEX}, \bar{\rho}_{AEX}) \leq \frac{\delta}{2}. \quad (\text{B16})$$

Now consider that

$$\begin{aligned}
& P(\bar{\rho}_{AEX}, \rho_{AE} \otimes |0\rangle\langle 0|_X) \\
& \leq P(\bar{\rho}_{AEX}, \tilde{\rho}_{AE} \otimes |0\rangle\langle 0|_X) \\
& \quad + P(\tilde{\rho}_{AE} \otimes |0\rangle\langle 0|_X, \rho_{AE} \otimes |0\rangle\langle 0|_X) \\
& = \sqrt{1 - F(\bar{\rho}_{AEX}, \tilde{\rho}_{AE} \otimes |0\rangle\langle 0|_X)} + P(\tilde{\rho}_{AE}, \rho_{AE}) \\
& = \sqrt{1 - \left\| \sqrt{\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma} \sqrt{\tilde{\rho}_{AE}} \right\|_1^2} + P(\tilde{\rho}_{AE}, \rho_{AE}) \\
& = \sqrt{1 - \left\| \sqrt{\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma} \sqrt{\Pi_A^\gamma \tilde{\rho}_{AE} \Pi_A^\gamma} \right\|_1^2} + P(\tilde{\rho}_{AE}, \rho_{AE}) \\
& = \sqrt{1 - (\text{Tr}[\Pi_A^\gamma \tilde{\rho}_{AE}])^2} + P(\tilde{\rho}_{AE}, \rho_{AE}) \\
& \leq \frac{\delta}{2} + \varepsilon, \tag{B17}
\end{aligned}$$

where we applied the triangle inequality of the sine distance [Ras02, Ras03, Ras06, GLN05] for the first inequality and the fact that $\left\| \sqrt{\Pi \omega \Pi} \sqrt{\tau} \right\|_1 = \left\| \sqrt{\Pi \omega \Pi} \sqrt{\Pi \tau \Pi} \right\|_1$ for a projector Π and states ω and τ . Combining this with (B16), we find that

$$P(\hat{\rho}_{AE}, \rho_{AE}) = P(\hat{\rho}_{AEX}, \rho_{AE} \otimes |0\rangle\langle 0|_X) \tag{B18}$$

$$\leq P(\hat{\rho}_{AEX}, \bar{\rho}_{AEX}) + P(\bar{\rho}_{AEX}, \rho_{AE} \otimes |0\rangle\langle 0|_X) \tag{B19}$$

$$= \varepsilon + \delta. \tag{B20}$$

Since we have found a state $\hat{\rho}_{AE}$ satisfying $P(\hat{\rho}_{AE}, \rho_{AE}) \leq \varepsilon + \delta$ and (B11), we conclude that

$$\tilde{I}_{\max}^{\varepsilon+\delta}(E; A)_\rho \leq D_{\max}(\tilde{\rho}_{AE} \|\rho_A \otimes \rho_E) + \log_2 \left(\frac{8}{\delta^2} \right). \tag{B21}$$

Since this inequality has been shown for all states $\tilde{\rho}_{AE}$ satisfying $P(\tilde{\rho}_{AE}, \rho_{AE}) \leq \varepsilon$, we conclude the statement of the lemma. ■

Appendix C: Smooth universal convex split lemma for states acting on a separable Hilbert space

Here we prove a smooth universal convex split lemma for states acting on a separable Hilbert space:

Lemma 8 (Smooth universal convex split) *Let \mathcal{S} be a set, and let ρ_{AE}^s be a state acting on a separable Hilbert space $\mathcal{H}_A \otimes \mathcal{H}_E$, such that $\text{Tr}_E[\rho_{AE}^s] = \rho_A$ for all $s \in \mathcal{S}$. Let $\tau_{A_1 \dots A_R E}^s$ denote the following state:*

$$\begin{aligned}
& \tau_{A_1 \dots A_R E}^s := \\
& \frac{1}{R} \sum_{r=1}^R \rho_{A_1} \otimes \dots \otimes \rho_{A_{r-1}} \otimes \rho_{A_r E}^s \otimes \rho_{A_{r+1}} \otimes \dots \otimes \rho_{A_R}.
\end{aligned} \tag{C1}$$

Let $\varepsilon \in (0, 1)$ and $\eta \in (0, \sqrt{\varepsilon})$. If

$$\log_2 R \geq \sup_{s \in \mathcal{S}} \tilde{I}_{\max}^{\sqrt{\varepsilon}-\eta}(E; A)_{\rho^s} + 2 \log_2 \left(\frac{1}{2\eta} \right), \tag{C2}$$

then for all $s \in \mathcal{S}$, there exists a state $\tilde{\rho}_E^s$ satisfying

$$\frac{1}{2} \left\| \tau_{A_1 \dots A_R E}^s - \rho_{A_1} \otimes \dots \otimes \rho_{A_R} \otimes \tilde{\rho}_E^s \right\|_1 \leq \sqrt{\varepsilon}, \tag{C3}$$

and $P(\tilde{\rho}_E^s, \rho_E^s) \leq \sqrt{\varepsilon} - \eta$.

Proof. Fix $s \in \mathcal{S}$. Let $\tilde{\rho}_{AE}^s$ be an arbitrary state satisfying $P(\tilde{\rho}_{AE}^s, \rho_{AE}^s) \leq \sqrt{\varepsilon} - \eta$ and is such that

$$\rho_A^s \otimes \tilde{\rho}_E^s = p \tilde{\rho}_{AE}^s + (1-p) \omega_{AE}^s, \tag{C4}$$

for some $p \in (0, 1)$ and ω_{AE}^s some state. We define the following state, which we think of as an approximation to $\tau_{A_1 \dots A_R E}^s$:

$$\begin{aligned}
& \tilde{\tau}_{A_1 \dots A_R E}^s := \\
& \frac{1}{R} \sum_{r=1}^R \rho_{A_1} \otimes \dots \otimes \rho_{A_{r-1}} \otimes \tilde{\rho}_{A_r E}^s \otimes \rho_{A_{r+1}} \otimes \dots \otimes \rho_{A_R}.
\end{aligned} \tag{C5}$$

It is a good approximation if $\sqrt{\varepsilon} - \eta$ is small, because

$$\begin{aligned}
& \sqrt{F}(\tau_{A_1 \dots A_R E}^s, \tilde{\tau}_{A_1 \dots A_R E}^s) \\
& \geq \frac{1}{R} \sum_{r=1}^R \sqrt{F}(\rho_A^{\otimes r-1} \otimes \rho_{A_r E}^s \otimes \rho_A^{\otimes R-r}, \\
& \quad \rho_A^{\otimes r-1} \otimes \tilde{\rho}_{A_r E}^s \otimes \rho_A^{\otimes R-r})
\end{aligned} \tag{C6}$$

$$= \frac{1}{R} \sum_{r=1}^R \sqrt{F}(\rho_{A_r E}^s, \tilde{\rho}_{A_r E}^s) \tag{C7}$$

$$= \sqrt{F}(\rho_{A_r E}^s, \tilde{\rho}_{A_r E}^s), \tag{C8}$$

which in turn implies that

$$\sqrt{F}(\tau_{A_1 \dots A_R E}^s, \tilde{\tau}_{A_1 \dots A_R E}^s) \geq \sqrt{F}(\rho_{A_r E}^s, \tilde{\rho}_{A_r E}^s). \tag{C9}$$

So the inequality in (C9), the definition of the sine distance, and the fact that $P(\tilde{\rho}_{AE}^s, \rho_{AE}^s) \leq \sqrt{\varepsilon} - \eta$, imply that

$$P(\tau_{A_1 \dots A_R E}^s, \tilde{\tau}_{A_1 \dots A_R E}^s) \leq \sqrt{\varepsilon} - \eta, \tag{C10}$$

and in turn that

$$\frac{1}{2} \left\| \tau_{A_1 \dots A_R E}^s - \tilde{\tau}_{A_1 \dots A_R E}^s \right\|_1 \leq \sqrt{\varepsilon} - \eta. \tag{C11}$$

Now, following [LW19, Appendix A] closely, let us define the following states:

$$\beta_{AE}^s := \rho_A^s \otimes \tilde{\rho}_E^s, \tag{C12}$$

$$\alpha_{AE}^s := \tilde{\rho}_{AE}^s, \tag{C13}$$

$$\tilde{\tau}_{A^R E^R}^s := \frac{1}{R} \sum_{r=1}^R \beta_{A_1 E_1} \otimes \cdots \otimes \beta_{A_{r-1} E_{r-1}} \otimes \alpha_{A_r E_r}^s \otimes \beta_{A_{r+1} E_{r+1}} \otimes \cdots \otimes \beta_{A_R E_R}, \quad (\text{C14})$$

and observe that

$$\text{Tr}_{E_2^R}[(\beta_{AE}^s)^{\otimes R}] = \rho_{A_1} \otimes \cdots \otimes \rho_{A_R} \otimes \tilde{\rho}_E^s, \quad (\text{C15})$$

$$\text{Tr}_{E_2^R}[\tilde{\tau}_{A^R E^R}^s] = \tilde{\tau}_{A_1 \cdots A_R E}^s. \quad (\text{C16})$$

Thus, it follows from data processing of normalized trace distance that

$$\begin{aligned} \frac{1}{2} \|\tilde{\tau}_{A_1 \cdots A_R E}^s - \rho_{A_1} \otimes \cdots \otimes \rho_{A_R} \otimes \tilde{\rho}_E^s\|_1 \\ \leq \frac{1}{2} \|\tilde{\tau}_{A^R E^R}^s - (\beta_{AE}^s)^{\otimes R}\|_1. \end{aligned} \quad (\text{C17})$$

Now applying [LW19, Lemma 15], we find that

$$\frac{1}{2} \|\tilde{\tau}_{A_1 \cdots A_R E}^s - \rho_{A_1} \otimes \cdots \otimes \rho_{A_R} \otimes \tilde{\rho}_E^s\|_1 \leq \eta \quad (\text{C18})$$

if

$$\log_2 R \geq \log_2(1/p) + 2 \log_2 \left(\frac{1}{2\eta} \right). \quad (\text{C19})$$

For the same choice of R , it follows from (C17) that

$$\frac{1}{2} \|\tilde{\tau}_{A_1 \cdots A_R E}^s - \rho_{A_1} \otimes \cdots \otimes \rho_{A_R} \otimes \tilde{\rho}_E^s\|_1 \leq \eta. \quad (\text{C20})$$

Applying the triangle inequality to (C11) and (C20), we find that

$$\frac{1}{2} \|\tau_{A_1 \cdots A_R E}^s - \rho_{A_1} \otimes \cdots \otimes \rho_{A_R} \otimes \tilde{\rho}_E^s\|_1 \leq \sqrt{\varepsilon}. \quad (\text{C21})$$

The whole argument above holds for an arbitrary state $\tilde{\rho}_{AE}^s$ satisfying $P(\tilde{\rho}_{AE}^s, \rho_{AE}^s) \leq \sqrt{\varepsilon} - \eta$ and (C4), and so taking an infimum of $\log_2(1/p)$ over all states satisfying these conditions, and applying the definition in (192), as well as (187), we find that

$$\frac{1}{2} \|\tau_{A_1 \cdots A_R E}^s - \rho_{A_1} \otimes \cdots \otimes \rho_{A_R} \otimes \tilde{\rho}_E^s\|_1 \leq \sqrt{\varepsilon} \quad (\text{C22})$$

if

$$\log_2 R \geq \tilde{I}_{\max}^{\sqrt{\varepsilon}-\eta}(E; A)_{\rho^s} + 2 \log_2 \left(\frac{1}{2\eta} \right). \quad (\text{C23})$$

Now note that the whole argument holds for all $s \in \mathcal{S}$, due to the uniform structure of the convex split method, which consists of bringing in a tensor-power state and performing a random permutation. We then find that

$$\frac{1}{2} \|\tau_{A_1 \cdots A_R E}^s - \rho_{A_1} \otimes \cdots \otimes \rho_{A_R} \otimes \tilde{\rho}_E^s\|_1 \leq \sqrt{\varepsilon} \quad (\text{C24})$$

for all $s \in \mathcal{S}$ if

$$\log_2 R \geq \sup_{s \in \mathcal{S}} \tilde{I}_{\max}^{\sqrt{\varepsilon}-\eta}(E; A)_{\rho^s} + 2 \log_2 \left(\frac{1}{2\eta} \right). \quad (\text{C25})$$

This concludes the proof. ■

Appendix D: Duality of smooth max-relative entropy

This appendix generalizes a duality relation for smooth max-relative entropy from the finite-dimensional case [JN12] to the case of states acting on a separable Hilbert space. Recall that the smooth max-relative entropy is defined as

$$D_{\max}^{\varepsilon}(\rho \|\sigma) = \log_2 \inf_{\tilde{\rho}: P(\tilde{\rho}, \rho) \leq \varepsilon} \inf_{\lambda \geq 0} \{\lambda : \tilde{\rho} \leq \lambda \sigma\}. \quad (\text{D1})$$

We can also define the dual smooth max-relative entropy as

$$\hat{D}_{\max}^{\varepsilon}(\rho \|\sigma) := \log_2 \sup_{M \geq 0} \inf_{\tilde{\rho}: P(\tilde{\rho}, \rho) \leq \varepsilon} \{\text{Tr}[M\tilde{\rho}] : \text{Tr}[M\sigma] \leq 1\}, \quad (\text{D2})$$

where the supremum is with respect to all compact bounded operators $M \geq 0$, as these are dual to the trace-class operators [RS78]. In this section, for both of the above quantities, we expand the definitions to allow for subnormalized states ρ and σ (i.e., such that $\text{Tr}[\rho], \text{Tr}[\sigma] \leq 1$) and the sine distance becomes as follows [Tom15]:

$$P(\tau, \omega) := \sqrt{1 - F(\tau \oplus (1 - \text{Tr}[\tau]), \omega \oplus (1 - \text{Tr}[\omega]))}. \quad (\text{D3})$$

In what follows, we call subnormalized states “substates” for short. Note that for any projection Π and substates τ and ω , the following inequality holds [Tom15]

$$P(\Pi\tau\Pi, \Pi\omega\Pi) \leq P(\tau, \omega). \quad (\text{D4})$$

Lemma 9 *Let ρ be a state and σ a trace-class positive semi-definite operator acting on a separable Hilbert space \mathcal{H} . Let $\varepsilon \in (0, 1)$ and suppose that $D_{\max}^{\varepsilon}(\rho \|\sigma) < \infty$. Then*

$$D_{\max}^{\varepsilon}(\rho \|\sigma) = \hat{D}_{\max}^{\varepsilon}(\rho \|\sigma). \quad (\text{D5})$$

Proof. We prove this in several steps, with the proof bearing some similarities to the approach from [FAR11, Appendix B] (see also [WW18, Appendix A] in this context). First, for a state $\tilde{\rho}$, consider from weak duality that

$$\inf_{\lambda \geq 0} \{\lambda : \tilde{\rho} \leq \lambda \sigma\} \geq \sup_{M \geq 0} \{\text{Tr}[M\tilde{\rho}] : \text{Tr}[M\sigma] \leq 1\}, \quad (\text{D6})$$

where the optimization on the right-hand side is over the compact bounded operators, given that these are dual to the trace-class operators [RS78]. In more detail, let $\lambda \geq 0$ satisfy $\tilde{\rho} \leq \lambda \sigma$, and let M be an arbitrary compact bounded operator satisfying $M \geq 0$ and $\text{Tr}[M\sigma] \leq 1$. Then it follows that $\lambda \geq \text{Tr}[M\tilde{\rho}] / \text{Tr}[M\sigma] \geq \text{Tr}[M\tilde{\rho}]$, where we used $\tilde{\rho} \leq \lambda \sigma$ and $M \geq 0$. Since this inequality holds for all λ and M satisfying the given conditions, we conclude the weak duality inequality in (D6). Then we have that

$$D_{\max}^{\varepsilon}(\rho \|\sigma)$$

$$= \log_2 \inf_{\tilde{\rho}: P(\tilde{\rho}, \rho) \leq \varepsilon} \inf_{\lambda \geq 0} \{\lambda : \tilde{\rho} \leq \lambda \sigma\} \quad (\text{D7})$$

$$\geq \log_2 \inf_{\tilde{\rho}: P(\tilde{\rho}, \rho) \leq \varepsilon} \sup_{M \geq 0} \{\text{Tr}[M\tilde{\rho}] : \text{Tr}[M\sigma] \leq 1\} \quad (\text{D8})$$

$$\geq \log_2 \sup_{M \geq 0} \inf_{\tilde{\rho}: P(\tilde{\rho}, \rho) \leq \varepsilon} \{\text{Tr}[M\tilde{\rho}] : \text{Tr}[M\sigma] \leq 1\} \quad (\text{D9})$$

$$= \widehat{D}_{\max}^{\varepsilon}(\rho \| \sigma). \quad (\text{D10})$$

So the following weak-duality inequality holds

$$D_{\max}^{\varepsilon}(\rho \| \sigma) \geq \widehat{D}_{\max}^{\varepsilon}(\rho \| \sigma). \quad (\text{D11})$$

Let $\{\Pi^k\}_k$ be a sequence of projectors onto finite-dimensional subspaces strongly converging to the identity operator, and suppose that $\Pi^k \leq \Pi^{k'}$ for $k \leq k'$. Then define

$$\rho^k := \Pi^k \rho \Pi^k, \quad \sigma^k := \Pi^k \sigma \Pi^k. \quad (\text{D12})$$

We now prove that

$$\lim_{k \rightarrow \infty} D_{\max}^{\varepsilon}(\rho^k \| \sigma^k) = D_{\max}^{\varepsilon}(\rho \| \sigma). \quad (\text{D13})$$

Let $\tilde{\rho}$ be an arbitrary state satisfying $P(\tilde{\rho}, \rho) \leq \varepsilon$ and let λ satisfy $\tilde{\rho} \leq \lambda \sigma$. Then it follows that

$$\tilde{\rho}^k := \Pi^k \tilde{\rho} \Pi^k \leq \lambda \Pi^k \sigma \Pi^k = \lambda \sigma^k, \quad (\text{D14})$$

$$P(\tilde{\rho}^k, \rho^k) \leq \varepsilon, \quad (\text{D15})$$

so that

$$D_{\max}^{\varepsilon}(\rho^k \| \sigma^k) \leq \log_2 \lambda. \quad (\text{D16})$$

Since λ and $\tilde{\rho}$ are arbitrary, we conclude that

$$D_{\max}^{\varepsilon}(\rho^k \| \sigma^k) \leq D_{\max}^{\varepsilon}(\rho \| \sigma), \quad (\text{D17})$$

and since this inequality holds for all k , the following inequality holds

$$\limsup_{k \rightarrow \infty} D_{\max}^{\varepsilon}(\rho^k \| \sigma^k) \leq D_{\max}^{\varepsilon}(\rho \| \sigma). \quad (\text{D18})$$

To show the opposite inequality, we first prove that $D_{\max}^{\varepsilon}(\rho^k \| \sigma^k)$ is monotone non-decreasing with k . (The proof is in fact similar to what we have just shown.) Fix k and k' such that $k \leq k'$. Let $\tilde{\rho}^{k'}$ be a substate satisfying $P(\tilde{\rho}^{k'}, \rho^{k'}) \leq \varepsilon$ and let $\lambda^{k'}$ be such that $\tilde{\rho}^{k'} \leq \lambda^{k'} \sigma^{k'}$. Then it follows that

$$\tilde{\rho}^{k',k} := \Pi^k \tilde{\rho}^{k'} \Pi^k \leq \lambda^{k'} \Pi^k \sigma^{k'} \Pi^k = \lambda^{k'} \sigma^k, \quad (\text{D19})$$

and

$$P(\tilde{\rho}^{k',k}, \Pi^k \rho^{k'} \Pi^k) = P(\tilde{\rho}^{k',k}, \rho^k) \leq \varepsilon, \quad (\text{D20})$$

so that

$$D_{\max}^{\varepsilon}(\rho^k \| \sigma^k) \leq \log_2 \lambda^{k'}. \quad (\text{D21})$$

Since $\lambda^{k'}$ and $\tilde{\rho}^{k'}$ are arbitrary, it follows that

$$D_{\max}^{\varepsilon}(\rho^k \| \sigma^k) \leq D_{\max}^{\varepsilon}(\rho^{k'} \| \sigma^{k'}). \quad (\text{D22})$$

Now let $\tilde{\rho}^k$ and λ^k be the optimal state and value for $D_{\max}^{\varepsilon}(\rho^k \| \sigma^k)$, so that $\lambda^k = D_{\max}^{\varepsilon}(\rho^k \| \sigma^k)$. By what we have just shown, the sequence λ^k is monotone non-decreasing, and so the limit $\lambda := \lim_{k \rightarrow \infty} \lambda^k$ is well defined. Also, we know from (D18) that $\lambda \leq D_{\max}^{\varepsilon}(\rho \| \sigma) < \infty$. Due to the fact that $\|\tilde{\rho}^k\|_1 = \text{Tr}[\tilde{\rho}^k] \leq \lambda^k \text{Tr}[\sigma^k] \leq \lambda \text{Tr}[\sigma]$, it follows that $\tilde{\rho}^k$ is a bounded sequence in the trace-class operators. Since the trace-class operators form the dual space of the compact bounded operators [RS78], we apply the Banach–Alaoglu theorem [RS78] to find a subsequence $\{\tilde{\rho}^k\}_{k \in S}$ having a weak* limit $\tilde{\rho}$, which means that $\text{Tr}[K\tilde{\rho}^k] \rightarrow \text{Tr}[K\tilde{\rho}]$ for $k \in S$ and for all compact bounded operators K . It holds that $\tilde{\rho}^k$ is positive semi-definite. Then it follows that $\lambda^k \sigma^k - \tilde{\rho}^k$ converges in the weak operator topology to $\lambda \sigma - \tilde{\rho}$. Then we conclude that $\lambda \sigma - \tilde{\rho} \geq 0$, and finally that $D_{\max}^{\varepsilon}(\rho \| \sigma) \leq \lambda$. So we conclude (D13).

By strong duality, and the fact that ρ^k and σ^k are finite-dimensional, it follows from [JN12] that

$$D_{\max}^{\varepsilon}(\rho^k \| \sigma^k) = \widehat{D}_{\max}^{\varepsilon}(\rho^k \| \sigma^k) \quad (\text{D23})$$

for all k . So these equalities and (D13) imply that

$$\lim_{k \rightarrow \infty} \widehat{D}_{\max}^{\varepsilon}(\rho^k \| \sigma^k) = D_{\max}^{\varepsilon}(\rho \| \sigma). \quad (\text{D24})$$

Now our goal is to prove that

$$\lim_{k \rightarrow \infty} \widehat{D}_{\max}^{\varepsilon}(\rho^k \| \sigma^k) \leq \widehat{D}_{\max}^{\varepsilon}(\rho \| \sigma), \quad (\text{D25})$$

and we adopt a similar approach as above for doing so. Let M^k be an arbitrary compact bounded operator satisfying $\text{Tr}[M^k \sigma^k] \leq 1$ and let $\tilde{\rho}$ be an arbitrary substate satisfying $P(\tilde{\rho}, \rho) \leq \varepsilon$. Define $\tilde{\rho}^k = \Pi^k \tilde{\rho} \Pi^k$. Then it follows that

$$\text{Tr}[M^k \sigma^k] = \text{Tr}[\Pi^k M^k \Pi^k \sigma] \leq 1, \quad (\text{D26})$$

$$P(\tilde{\rho}^k, \rho^k) \leq \varepsilon, \quad (\text{D27})$$

and

$$\inf_{\tilde{\rho}^k: P(\tilde{\rho}^k, \rho^k) \leq \varepsilon} \text{Tr}[M^k \tilde{\rho}^k] \leq \text{Tr}[M^k \tilde{\rho}^k] \quad (\text{D28})$$

$$= \text{Tr}[M^k \Pi^k \tilde{\rho} \Pi^k] \quad (\text{D29})$$

$$= \text{Tr}[\Pi^k M^k \Pi^k \tilde{\rho}]. \quad (\text{D30})$$

Since the inequality holds for all $\tilde{\rho}$ satisfying $P(\tilde{\rho}, \rho) \leq \varepsilon$, we conclude that

$$\begin{aligned} & \inf_{\tilde{\rho}^k: P(\tilde{\rho}^k, \rho^k) \leq \varepsilon} \text{Tr}[M^k \tilde{\rho}^k] \\ & \leq \inf_{\tilde{\rho}: P(\tilde{\rho}, \rho) \leq \varepsilon} \text{Tr}[\Pi^k M^k \Pi^k \tilde{\rho}] \end{aligned} \quad (\text{D31})$$

$$\leq \sup_{M \geq 0} \inf_{\tilde{\rho}: P(\tilde{\rho}, \rho) \leq \varepsilon} \{\text{Tr}[M\tilde{\rho}] : \text{Tr}[M\sigma] \leq 1\} \quad (\text{D32})$$

$$= \widehat{D}_{\max}^{\varepsilon}(\rho \| \sigma), \quad (\text{D33})$$

where the second inequality follows because $\Pi^k M^k \Pi^k$ is a particular compact bounded operator satisfying

$\text{Tr}[\Pi^k M^k \Pi^k \sigma] \leq 1$. Since the inequality above has been shown for an arbitrary compact bounded operator M^k satisfying $\text{Tr}[M^k \sigma^k] \leq 1$, we conclude that

$$\begin{aligned} \sup_{M^k \geq 0} \inf_{\hat{\rho}^k: P(\hat{\rho}^k, \rho^k) \leq \varepsilon} \{ \text{Tr}[M^k \hat{\rho}^k] : \text{Tr}[M^k \sigma^k] \leq 1 \} \\ = \hat{D}_{\max}^\varepsilon(\rho^k \| \sigma^k) \leq \hat{D}_{\max}^\varepsilon(\rho \| \sigma). \end{aligned} \quad (\text{D34})$$

Since this inequality has been shown for arbitrary k , we conclude that

$$\limsup_{k \rightarrow \infty} \hat{D}_{\max}^\varepsilon(\rho^k \| \sigma^k) \leq \hat{D}_{\max}^\varepsilon(\rho \| \sigma). \quad (\text{D35})$$

Finally, by combining (D11), (D24), and (D25), we conclude that

$$\hat{D}_{\max}^\varepsilon(\rho \| \sigma) = D_{\max}^\varepsilon(\rho \| \sigma). \quad (\text{D36})$$

This completes the proof. ■

Appendix E: Relation between smooth max-relative entropy and hypothesis testing relative entropy

This appendix establishes inequalities relating the smooth max-relative entropy and the hypothesis testing relative entropy of states acting on a separable Hilbert space.

Lemma 10 *Let ρ be a state and σ a trace-class positive semi-definite operator acting on a separable Hilbert space \mathcal{H} . Let $\varepsilon \in (0, 1)$, and set $\delta \in (0, 1)$ such that $\varepsilon + \delta < 1$. Suppose that $D_{\max}^{\sqrt{\varepsilon}}(\rho \| \sigma) < \infty$. Then the following bounds hold*

$$D_{\max}^{\sqrt{\varepsilon}}(\rho \| \sigma) \leq D_H^{1-\varepsilon}(\rho \| \sigma) + \log_2 \left(\frac{1}{1-\varepsilon} \right), \quad (\text{E1})$$

$$D_H^{1-\varepsilon-\delta}(\rho \| \sigma) \leq D_{\max}^{\sqrt{\varepsilon}}(\rho \| \sigma) + \log_2 \left(\frac{4(1-\varepsilon)}{\delta^2} \right). \quad (\text{E2})$$

Proof. These bounds were established for the finite-dimensional case in [ABJT19, Theorem 4]. Here we check that the arguments presented in the proof of [ABJT19, Theorem 4] hold for the more general case in the statement of the lemma, and we combine with the result from Lemma 9.

We first consider the inequality in (E1). Let $M \geq 0$ be an arbitrary compact bounded operator satisfying $\text{Tr}[M\sigma] \leq 1$. Since M is compact, it has a countable spectral decomposition as $M = \sum_i m_i |\phi_i\rangle\langle\phi_i|$, where $\{m_i\}_i$ is a countable set of non-negative eigenvalues and $\{|\phi_i\rangle\}_i$ is a countable orthonormal basis. We define a measurement (or completely dephasing) channel as

$$\mathcal{M}(\cdot) := \sum_i |\phi_i\rangle\langle\phi_i|(\cdot)|\phi_i\rangle\langle\phi_i|, \quad (\text{E3})$$

and we set the probability distributions P and Q such that

$$\mathcal{M}(\rho) = \sum_i P(i) |\phi_i\rangle\langle\phi_i|, \quad (\text{E4})$$

$$\mathcal{M}(\sigma) = \sum_i Q(i) |\phi_i\rangle\langle\phi_i|. \quad (\text{E5})$$

Then the data processing inequality for the hypothesis testing relative entropy implies that

$$D_H^{1-\varepsilon}(\rho \| \sigma) \geq D_H^{1-\varepsilon}(P \| Q) \geq D_s^{1-\varepsilon}(P \| Q) := K, \quad (\text{E6})$$

where the ε -information spectrum relative entropy of states τ and ω is defined as [TH13]

$$D_s^\varepsilon(\tau \| \omega) := \sup \{ \lambda \in \mathbb{R} : \text{Tr}[\tau \{ \tau \leq 2^\lambda \omega \}] \leq \varepsilon \}, \quad (\text{E7})$$

and $\{ \tau \leq 2^\lambda \omega \}$ denotes the projection onto the positive part of $2^\lambda \omega - \tau$. The second inequality above follows by picking $\Lambda := \{ \tau > 2^\lambda \omega \}$ for $\lambda = D_s^\varepsilon(\tau \| \omega) - \xi$ and $\xi > 0$. Since Λ satisfies $\text{Tr}[\Lambda \tau] \geq 1 - \varepsilon$, and we also have that

$$\text{Tr}[\Lambda \omega] = \text{Tr}[\{ \tau > 2^\lambda \omega \} \omega] \quad (\text{E8})$$

$$\leq 2^{-\lambda} \text{Tr}[\tau \{ \tau > 2^\lambda \omega \}] \quad (\text{E9})$$

$$\leq 2^{-\lambda}, \quad (\text{E10})$$

it follows from definitions that

$$\lambda = D_s^\varepsilon(\tau \| \omega) - \xi \leq D_H^\varepsilon(\tau \| \omega). \quad (\text{E11})$$

Since the inequality has been shown for all $\xi > 0$, it follows that $D_s^\varepsilon(\tau \| \omega) \leq D_H^\varepsilon(\tau \| \omega)$. Now set $\eta > 0$, and define the set

$$I := \{ i : P(i) \leq 2^{K+\eta} Q(i) \}, \quad (\text{E12})$$

which implies that $P(I) := \sum_{i \in I} P(i) > 1 - \varepsilon$ from the definition of $D_s^{1-\varepsilon}(P \| Q)$ (indeed, from the definition of $D_s^{1-\varepsilon}(P \| Q)$, K is the largest possible value such that $\sum_{i: P(i) \leq 2^K Q(i)} P(i) \leq 1 - \varepsilon$, so that if it is increased by $\eta > 0$, then $P(I) > 1 - \varepsilon$). Now define the projection $\Pi := \sum_{i \notin I} |\phi_i\rangle\langle\phi_i|$. Then it follows that

$$\text{Tr}[\Pi \rho] = \text{Tr}[\mathcal{M}(\Pi) \rho] \quad (\text{E13})$$

$$= \text{Tr}[\Pi \mathcal{M}(\rho)] \quad (\text{E14})$$

$$= 1 - P(I) \quad (\text{E15})$$

$$\leq \varepsilon. \quad (\text{E16})$$

Set

$$\tilde{\rho} := \frac{(I - \Pi) \rho (I - \Pi)}{1 - \text{Tr}[\Pi \rho]}. \quad (\text{E17})$$

Then it follows that $P(\rho, \tilde{\rho}) \leq \sqrt{\varepsilon}$ because

$$\begin{aligned} F(\rho, \tilde{\rho}) &= \left\| \sqrt{\rho} \sqrt{\tilde{\rho}} \right\|_1^2 \\ &= \frac{1}{1 - \text{Tr}[\Pi \rho]} \left\| \sqrt{\rho} \sqrt{(I - \Pi) \rho (I - \Pi)} \right\|_1^2 \end{aligned} \quad (\text{E18})$$

$$\begin{aligned} &= \frac{1}{1 - \text{Tr}[\Pi \rho]} \left\| \sqrt{\rho} \sqrt{(I - \Pi) \rho (I - \Pi)} \right\|_1^2 \\ &= \frac{1}{1 - \text{Tr}[\Pi \rho]} \times \end{aligned} \quad (\text{E19})$$

$$\left\| \sqrt{(I - \Pi) \rho (I - \Pi)} \sqrt{(I - \Pi) \rho (I - \Pi)} \right\|_1^2 \quad (\text{E20})$$

$$= \frac{1}{1 - \text{Tr}[\Pi \rho]} \|(I - \Pi) \rho (I - \Pi)\|_1^2 \quad (\text{E21})$$

$$= 1 - \text{Tr}[\Pi \rho]. \quad (\text{E22})$$

Then since $1 - \text{Tr}[\Pi \rho] \geq 1 - \varepsilon$, it follows that

$$\text{Tr}[M \tilde{\rho}] = \frac{1}{1 - \text{Tr}[\Pi \rho]} \text{Tr}[M (I - \Pi) \rho (I - \Pi)] \quad (\text{E23})$$

$$= \frac{1}{1 - \text{Tr}[\Pi \rho]} \sum_{i \in I} m_i P(i) \quad (\text{E24})$$

$$\leq \frac{1}{1 - \varepsilon} 2^{K+\eta} \sum_{i \in I} m_i Q(i) \quad (\text{E25})$$

$$\leq \frac{1}{1 - \varepsilon} 2^{K+\eta} \sum_i m_i Q(i) \quad (\text{E26})$$

$$= \frac{1}{1 - \varepsilon} 2^{K+\eta} \text{Tr}[M \sigma] \quad (\text{E27})$$

$$\leq \frac{1}{1 - \varepsilon} 2^{D_H^{1-\varepsilon}(\rho \parallel \sigma) + \eta}. \quad (\text{E28})$$

Taking a logarithm and an infimum over all states $\tilde{\rho}$ satisfying $P(\rho, \tilde{\rho}) \leq \sqrt{\varepsilon}$, we find that

$$\log_2 \inf_{\tilde{\rho}: P(\rho, \tilde{\rho}) \leq \sqrt{\varepsilon}} \text{Tr}[M \tilde{\rho}] \leq D_H^{1-\varepsilon}(\rho \parallel \sigma) + \eta + \log_2 \left(\frac{1}{1 - \varepsilon} \right). \quad (\text{E29})$$

Since the inequality has been shown for all compact bounded operators $M \geq 0$ satisfying $\text{Tr}[M \sigma] \leq 1$, it follows that

$$\hat{D}_{\max}^{\sqrt{\varepsilon}}(\rho \parallel \sigma) = \log_2 \sup_{M \geq 0, \text{Tr}[M \sigma] \leq 1} \left[\inf_{\tilde{\rho}: P(\rho, \tilde{\rho}) \leq \sqrt{\varepsilon}} \text{Tr}[M \tilde{\rho}] \right] \quad (\text{E30})$$

$$\leq D_H^{1-\varepsilon}(\rho \parallel \sigma) + \eta + \log_2 \left(\frac{1}{1 - \varepsilon} \right). \quad (\text{E31})$$

Since the inequality has been shown for all $\eta > 0$, it follows that

$$\hat{D}_{\max}^{\sqrt{\varepsilon}}(\rho \parallel \sigma) \leq D_H^{1-\varepsilon}(\rho \parallel \sigma) + \log_2 \left(\frac{1}{1 - \varepsilon} \right). \quad (\text{E32})$$

Now applying Lemma 9, we conclude the inequality in (E1).

We now consider the other inequality in (E2). Let $\lambda \geq 0$ and $\tilde{\rho}$ be a state satisfying $P(\tilde{\rho}, \rho) \leq \sqrt{\varepsilon}$ and

$$\tilde{\rho} \leq 2^\lambda \sigma. \quad (\text{E33})$$

Consider an arbitrary operator Λ satisfying $0 \leq \Lambda \leq I$ and $\text{Tr}[(I - \Lambda) \rho] = 1 - \varepsilon - \delta$. Then the data processing inequality for the fidelity, with respect to the measurement $\{\Lambda, I - \Lambda\}$, implies that

$$\sqrt{1 - \varepsilon}$$

$$\leq \sqrt{F(\tilde{\rho}, \rho)}$$

$$\leq \sqrt{\text{Tr}[\Lambda \tilde{\rho}] \text{Tr}[\Lambda \rho]} + \sqrt{\text{Tr}[(I - \Lambda) \tilde{\rho}] \text{Tr}[(I - \Lambda) \rho]}$$

$$\leq \sqrt{2^\lambda \text{Tr}[\Lambda \sigma]} + \sqrt{1 - \varepsilon - \delta}. \quad (\text{E34})$$

Now taking an infimum over all λ such that (E33) holds and all Λ satisfying $0 \leq \Lambda \leq I$ and $\text{Tr}[(I - \Lambda) \rho] = 1 - \varepsilon - \delta$, and applying definitions, we find that

$$\sqrt{1 - \varepsilon} \leq \sqrt{2^{D_{\max}^{\sqrt{\varepsilon}}(\rho \parallel \sigma)} 2^{-D_H^{1-\varepsilon-\delta}(\rho \parallel \sigma)}} + \sqrt{1 - \varepsilon - \delta}. \quad (\text{E35})$$

Rewriting this gives

$$\log_2 \left[\sqrt{1 - \varepsilon} - \sqrt{1 - \varepsilon - \delta} \right]^2 \leq D_{\max}^{\sqrt{\varepsilon}}(\rho \parallel \sigma) - D_H^{1-\varepsilon-\delta}(\rho \parallel \sigma). \quad (\text{E36})$$

Now applying the inequality $\sqrt{1 - \varepsilon} - \sqrt{1 - \varepsilon - \delta} \geq \frac{\delta}{2\sqrt{1 - \varepsilon}}$, we conclude (E2). ■

Appendix F: Second-order asymptotics of smooth max-relative entropy for states acting on a separable Hilbert space

Recall the quantities defined in (247)–(249). We also define

$$\Phi(a) := \frac{1}{\sqrt{2\pi}} \int_{-\infty}^a dx \exp\left(-\frac{x^2}{2}\right), \quad (\text{F1})$$

$$\Phi^{-1}(\varepsilon) := \sup \{a \in \mathbb{R} \mid \Phi(a) \leq \varepsilon\}. \quad (\text{F2})$$

For $\varepsilon \in (0, 1)$, observe that

$$\Phi^{-1}(1 - \varepsilon) = -\Phi^{-1}(\varepsilon). \quad (\text{F3})$$

Let us define the quantity $T(\rho \parallel \sigma)$ [TH13, Li14, KW17] as

$$T(\rho \parallel \sigma) := \sum_{x,y} |\langle \phi_y | \psi_x \rangle|^2 \lambda_x \left| \log_2 \left(\frac{\lambda_x}{\mu_y} \right) - D(\rho \parallel \sigma) \right|^3, \quad (\text{F4})$$

where the eigendecompositions of the state ρ and the trace-class positive semi-definite operator σ are given in (247). Then the following expansion holds for ρ and σ such that $D(\rho \parallel \sigma), V(\rho \parallel \sigma), T(\rho \parallel \sigma) < \infty$ and $V(\rho \parallel \sigma) > 0$:

$$\frac{1}{n} D_H^\varepsilon(\rho^{\otimes n} \parallel \sigma^{\otimes n}) = D(\rho \parallel \sigma) + \sqrt{\frac{1}{n} V(\rho \parallel \sigma)} \Phi^{-1}(\varepsilon) + O\left(\frac{\log n}{n}\right). \quad (\text{F5})$$

The equality in (F5) was shown for the finite-dimensional case in [Li14, TH13]. For a state ρ and positive-semidefinite trace-class σ acting on a separable Hilbert space, the inequality \leq was shown in [DPR16, KW17], while the inequality \geq was established in [Li14, DPR16,

OMW19. The term $O\left(\frac{\log n}{n}\right)$ above hides constants involving $V(\rho\|\sigma)$, $T(\rho\|\sigma)$, and ε .

By combining the equality in (F5) with Lemma 10, we arrive at the following corollary, giving the second-order asymptotics for smooth max-relative entropy of trace-class operators acting on a separable Hilbert space:

Corollary 11 *Let $\varepsilon \in (0, 1)$. Let ρ be a state and σ a trace-class positive semi-definite operator acting on a separable Hilbert space \mathcal{H} , such that $D(\rho\|\sigma), V(\rho\|\sigma), T(\rho\|\sigma) < \infty$ and $V(\rho\|\sigma) > 0$. Then the following second-order expansion holds for sufficiently large n :*

$$\frac{1}{n} D_{\max}^{\sqrt{\varepsilon}}(\rho^{\otimes n} \|\sigma^{\otimes n}) = D(\rho\|\sigma) - \sqrt{\frac{1}{n} V(\rho\|\sigma) \Phi^{-1}(\varepsilon)} + O\left(\frac{\log n}{n}\right). \quad (\text{F6})$$

Proof. Exploiting the inequality in (E1), we find that

$$\begin{aligned} & \frac{1}{n} D_{\max}^{\sqrt{\varepsilon}}(\rho^{\otimes n} \|\sigma^{\otimes n}) \\ & \leq \frac{1}{n} D_H^{1-\varepsilon}(\rho^{\otimes n} \|\sigma^{\otimes n}) + \frac{1}{n} \log_2 \left(\frac{1}{1-\varepsilon} \right) \end{aligned} \quad (\text{F7})$$

$$= D(\rho\|\sigma) + \sqrt{\frac{1}{n} V(\rho\|\sigma) \Phi^{-1}(1-\varepsilon)} + O\left(\frac{\log n}{n}\right) \quad (\text{F8})$$

$$= D(\rho\|\sigma) - \sqrt{\frac{1}{n} V(\rho\|\sigma) \Phi^{-1}(\varepsilon)} + O\left(\frac{\log n}{n}\right). \quad (\text{F9})$$

where the first equality follows from (F5) and the last equality follows from (F3). Now exploiting the inequality in (E2) and choosing $\delta = 1/\sqrt{n}$, we find that

$$\begin{aligned} & \frac{1}{n} D_{\max}^{\sqrt{\varepsilon}}(\rho^{\otimes n} \|\sigma^{\otimes n}) \\ & \geq \frac{1}{n} D_H^{1-\varepsilon-\delta}(\rho^{\otimes n} \|\sigma^{\otimes n}) - \frac{1}{n} \log_2 \left(\frac{4(1-\varepsilon)}{\delta^2} \right) \\ & = D(\rho\|\sigma) + \sqrt{\frac{1}{n} V(\rho\|\sigma) \Phi^{-1}(1-\varepsilon)} + O\left(\frac{\log n}{n}\right) \\ & = D(\rho\|\sigma) - \sqrt{\frac{1}{n} V(\rho\|\sigma) \Phi^{-1}(\varepsilon)} + O\left(\frac{\log n}{n}\right). \end{aligned} \quad (\text{F10})$$

In the first equality, we have invoked a standard step from [TH13, Footnote 6] applied to $\Phi^{-1}(1-\varepsilon-\delta)$, which is an invocation of Taylor's theorem: for f continuously differentiable, c a positive constant, and $n \geq n_0$, the following equality holds

$$\sqrt{n} f(x + c/\sqrt{n}) = \sqrt{n} f(x) + c f'(a) \quad (\text{F11})$$

for some $a \in [x, x + c/\sqrt{n_0}]$. This concludes the proof. ■

Appendix G: Mutual information variance and T quantity of classical–quantum states

Proposition 12 *Given is a classical–quantum state of the following form:*

$$\rho_{XB} := \sum_x p_X(x) |x\rangle\langle x|_X \otimes \rho_B^x. \quad (\text{G1})$$

Suppose that ρ_B^x and $\rho_B := \sum_x p_X(x) \rho_B^x$ have the following spectral decompositions:

$$\rho_B^x = \sum_y p(y|x) |\psi^{x,y}\rangle\langle\psi^{x,y}|_B, \quad (\text{G2})$$

$$\rho_B = \sum_z q(z) |\phi^z\rangle\langle\phi^z|_B, \quad (\text{G3})$$

for $p(y|x)$ a conditional probability distribution, $\{|\psi^{x,y}\rangle_B\}_y$ an orthonormal set of eigenvectors (for fixed x), $q(z)$ a probability distribution, and $\{|\phi^z\rangle_B\}_z$ an orthonormal set of eigenvectors. Then

$$\begin{aligned} & V(X; B)_\rho \\ & = \sum_x p_X(x) \left(V(\rho_B^x \|\rho_B) + [D(\rho_B^x \|\rho_B)]^2 \right) - [I(X; B)]^2 \end{aligned} \quad (\text{G4})$$

$$= \sum_x p(x) \sum_{y,z} |\langle\psi^{x,y}|\phi^z\rangle_B|^2 p(y|x) |f(x, y, z)|^2, \quad (\text{G5})$$

$$\begin{aligned} & T(X; B)_\rho = \\ & \sum_x p(x) \sum_{y,z} |\langle\psi^{x,y}|\phi^z\rangle_B|^2 p(y|x) |f(x, y, z)|^3, \end{aligned} \quad (\text{G6})$$

where

$$f(x, y, z) := \log_2(p(y|x)/q(z)) - I(X; B). \quad (\text{G7})$$

Proof. To see the first expression in (G4), consider that

$$\begin{aligned} & \log_2 \rho_{XB} - \log_2 \rho_X \otimes \rho_B \\ & = \log_2 \left[\sum_x |x\rangle\langle x|_X \otimes p_X(x) \rho_B^x \right] \\ & \quad - \log_2 \left[\sum_x |x\rangle\langle x|_X \otimes p_X(x) \rho_B \right] \\ & = \sum_x |x\rangle\langle x|_X \otimes (\log_2 [p_X(x) \rho_B^x] - \log_2 [p_X(x) \rho_B]) \\ & = \sum_x |x\rangle\langle x|_X \otimes (\log_2 \rho_B^x - \log_2 \rho_B), \end{aligned} \quad (\text{G8})$$

and we find that

$$\begin{aligned} & [\log_2 \rho_{XB} - \log_2 \rho_X \otimes \rho_B - I(X; B)]^2 \\ & = \sum_x |x\rangle\langle x|_X \otimes (\log_2 \rho_B^x - \log_2 \rho_B - I(X; B))^2, \end{aligned} \quad (\text{G9})$$

so that

$$\begin{aligned}
& \text{Tr}[\rho_{XB} (\log_2 \rho_{XB} - \log_2 \rho_X \otimes \rho_B - I(X; B))^2] \\
&= \text{Tr} \left[\left(\sum_{x'} p_X(x') |x'\rangle\langle x'|_X \otimes \rho_B^{x'} \right) \times \right. \\
&\quad \left. \left(\sum_x |x\rangle\langle x|_X \otimes (\log_2 \rho_B^x - \log_2 \rho_B - I(X; B))^2 \right) \right] \\
&= \sum_x p_X(x) \text{Tr}[\rho_B^x (\log_2 \rho_B^x - \log_2 \rho_B - I(X; B))^2] \\
&= \sum_x p_X(x) \text{Tr}[\rho_B^x (\log_2 \rho_B^x - \log_2 \rho_B)^2] - [I(X; B)]^2.
\end{aligned} \tag{G10}$$

Now consider that

$$\begin{aligned}
& \text{Tr}[\rho_B^x (\log_2 \rho_B^x - \log_2 \rho_B)^2] \\
&= \text{Tr}[\rho_B^x (\log_2 \rho_B^x - \log_2 \rho_B)^2] \\
&\quad - [D(\rho_B^x \| \rho_B)]^2 + [D(\rho_B^x \| \rho_B)]^2 \\
&= \text{Tr}[\rho_B^x (\log_2 \rho_B^x - \log_2 \rho_B - D(\rho_B^x \| \rho_B))^2] \\
&\quad + [D(\rho_B^x \| \rho_B)]^2 \\
&= V(\rho_B^x \| \rho_B) + [D(\rho_B^x \| \rho_B)]^2.
\end{aligned} \tag{G11}$$

Substituting the last line back in (G10) gives the formula in (G4).

To see the other expressions, consider that

$$\begin{aligned}
& T(\rho_{XB} \| \rho_X \otimes \rho_B) \\
&= \sum_{x, x', y, z} |(\langle x|_X \otimes \langle \psi^{x, y}|_B) (|x'\rangle_X \otimes |\phi^z\rangle_B)|^2 p(x) p(y|x) \times \\
&\quad |\log_2(p(x) p(y|x) / [p(x') q(z)]) - I(X; B)|^3
\end{aligned} \tag{G12}$$

$$= \sum_{x, y, z} |\langle \psi^{x, y} | \phi^z \rangle_B|^2 p(x) p(y|x) |f(x, y, z)|^3 \tag{G13}$$

$$= \sum_x p(x) \sum_{y, z} |\langle \psi^{x, y} | \phi^z \rangle_B|^2 p(y|x) |f(x, y, z)|^3. \tag{G14}$$

By employing a similar development as above, the formula in (G5) is then clear. ■

Appendix H: Holevo information and Holevo information variance of a Gaussian ensemble of Gaussian states

In what follows, we determine formulas for the Holevo information and Holevo information variance of a Gaussian ensemble of Gaussian states. The first is well known, but the expression we give for it seems to be novel. The latter has not been presented yet to our knowledge. Before presenting the formulas, we provide a brief review of quantum Gaussian states in order to set some notation. We refer to [Ser17] for an in-depth overview of quantum Gaussian states and measurements.

We consider m -mode Gaussian states, where m is some fixed positive integer. Let \hat{r}_j denote each quadrature operator ($2m$ of them for an m -mode state), and let

$$\hat{r} \equiv [\hat{x}_1, \hat{p}_1, \dots, \hat{x}_m, \hat{p}_m] \tag{H1}$$

$$\equiv [\hat{r}_1, \dots, \hat{r}_{2m}] \tag{H2}$$

denote the vector of quadrature operators, so that the odd entries correspond to position-quadrature operators and the even entries to momentum-quadrature operators. The quadrature operators satisfy the following commutation relations:

$$[\hat{r}_j, \hat{r}_k] = i\Omega_{j,k}, \quad \text{where} \quad \Omega := I_m \otimes \begin{bmatrix} 0 & 1 \\ -1 & 0 \end{bmatrix}, \tag{H3}$$

and I_m is the $m \times m$ identity matrix. We also take the annihilation operator $\hat{a} = (\hat{x} + i\hat{p})/\sqrt{2}$.

Let ρ be a Gaussian state, with the mean-vector entries

$$\mu_j := \langle \hat{r}_j \rangle_\rho, \tag{H4}$$

and let μ denote the mean vector. The entries of the covariance matrix V of ρ are given by

$$V_{j,k} \equiv \langle \{\hat{r}_j - \mu_j, \hat{r}_k - \mu_k\} \rangle_\rho, \tag{H5}$$

and they satisfy the uncertainty principle $V + i\Omega \geq 0$. A $2m \times 2m$ matrix S is symplectic if it preserves the symplectic form: $S\Omega S^T = \Omega$. According to Williamson's theorem [Wil36], there is a diagonalization of the covariance matrix V of the form,

$$V = S(D \otimes I_2)S^T, \tag{H6}$$

where S is a symplectic matrix and $D \equiv \text{diag}(\nu_1, \dots, \nu_m)$ is a diagonal matrix of symplectic eigenvalues such that $\nu_i \geq 1$ for all $i \in \{1, \dots, m\}$. We say that a quantum Gaussian state is faithful if all of its symplectic eigenvalues are strictly greater than one (this also means that the state is positive definite). We can write the density operator ρ of a faithful state in the following exponential form [Che05, Kru06, Hol10] (see also [Hol12, Ser17]):

$$\rho = Z^{-1/2} \exp \left[-\frac{1}{2} (\hat{r} - \mu)^T G (\hat{r} - \mu) \right], \tag{H7}$$

$$\text{with } Z := \det([V + i\Omega]/2) \tag{H8}$$

$$\text{and } G := -2\Omega S [\text{arccoth}(D) \otimes I_2] S^T \Omega, \tag{H9}$$

where $\text{arccoth}(x) \equiv \frac{1}{2} \ln \left(\frac{x+1}{x-1} \right)$ with domain $(-\infty, -1) \cup (1, +\infty)$. The matrix G is known as the Hamiltonian matrix [Ser17]. Note that we can also write

$$G = 2i\Omega \text{arccoth}(iV\Omega), \tag{H10}$$

so that G is represented directly in terms of the covariance matrix V . Faithfulness of Gaussian states is required to ensure that G is non-singular. By inspection, the Hamiltonian matrix G and the covariance matrix V are symmetric.

Let $\mu^\rho, V^\rho, G^\rho, Z^\rho$ denote the various quantities above for an m -mode quantum Gaussian state ρ , and let $\mu^\sigma, V^\sigma, G^\sigma, Z^\sigma$ denote the various quantities for an m -mode

quantum Gaussian state σ . Then the relative entropy $D(\rho\|\sigma)$ is given by the following formula:

$$D(\rho\|\sigma) = \frac{1}{2\ln 2} \left[\ln \left(\frac{Z_\sigma}{Z_\rho} \right) + \frac{1}{2} \text{Tr}[V^\rho \Delta] + \delta^T G^\sigma \delta \right]. \quad (\text{H11})$$

The formula in (H11) was established by [Che05] for the zero-mean case, by [Kru06] for the case of non-zero mean but equal covariance matrices, and then extended by [Pir17] to the case of general multi-mode Gaussian states. The relative entropy variance is given by the following formula [WTLB17]:

$$V(\rho\|\sigma) = \frac{1}{8\ln^2 2} \left[\text{Tr}[(\Delta V^\rho)^2] + \text{Tr}[(\Delta \Omega)^2] \right] + \frac{1}{2\ln^2 2} \delta^T G^\sigma V^\rho G^\sigma \delta, \quad (\text{H12})$$

where

$$\delta := \mu^\rho - \mu^\sigma, \quad (\text{H13})$$

$$\Delta := G^\sigma - G^\rho. \quad (\text{H14})$$

Recall from (41) and (42) that the Holevo information and Holevo information variance of a general ensemble $\{p_Y(y), \rho_E^y\}_y$ are given by the following, with sums replaced by integrals:

$$I(Y; E) = \int dy p_Y(y) D(\rho_E^y \| \rho_E), \quad (\text{H15})$$

$$V(Y; E) = \int dy p_Y(y) \left[V(\rho_E^y \| \rho_E) + (D(\rho_E^y \| \rho_E))^2 \right] - [I(Y; E)]^2, \quad (\text{H16})$$

where

$$\rho_E := \int dy p_Y(y) \rho_E^y. \quad (\text{H17})$$

Then the proof of Proposition 3 is as follows:

Proof of Proposition 3. Recall Definition 2 for a Gaussian ensemble of quantum Gaussian states. First, consider that the expected density operator ρ_E in (H17) is a quantum Gaussian state because it is a Gaussian mixture of Gaussian states. Furthermore, the entries μ_E^j of the mean vector μ_E of ρ_E are given by

$$\mu_E^j := \text{Tr}[\hat{r}_j \rho_E] \quad (\text{H18})$$

$$= \int dy p_Y(y) \text{Tr}[\hat{r}_j \rho_E^y] \quad (\text{H19})$$

$$= \int dy p_Y(y) ([Wy]_j + \nu_j) \quad (\text{H20})$$

$$= [W\mu + \nu]_j, \quad (\text{H21})$$

so that

$$\mu_E = W\mu + \nu. \quad (\text{H22})$$

The entries V_E^{jk} of the covariance matrix V_E of ρ_E are given by

$$V_E^{jk} := \text{Tr} \left[\left\{ \hat{r}_j - \mu_E^j, \hat{r}_k - \mu_E^k \right\} \rho_E \right] \quad (\text{H23})$$

$$= \text{Tr} [\{\hat{r}_j, \hat{r}_k\} \rho_E] - 2\mu_E^j \text{Tr} [\hat{r}_k \rho_E] - 2\mu_E^k \text{Tr} [\hat{r}_j \rho_E] + 2\mu_E^j \mu_E^k \text{Tr} [\rho_E] \quad (\text{H24})$$

$$= \text{Tr} [\{\hat{r}_j, \hat{r}_k\} \rho_E] - 2\mu_E^j \mu_E^k. \quad (\text{H25})$$

Let us focus on the first term $\text{Tr} [\{\hat{r}_j, \hat{r}_k\} \rho_E]$. Set

$$y_c := y - \mu, \quad (\text{H26})$$

and consider that

$$\text{Tr} [\{\hat{r}_j, \hat{r}_k\} \rho_E] = \int dy p_Y(y) \text{Tr} [\{\hat{r}_j, \hat{r}_k\} \rho_E^y] \quad (\text{H27})$$

$$= \int dy p_Y(y) \left(V^{jk} + 2[Wy + \nu]_j [Wy + \nu]_k \right) \quad (\text{H28})$$

$$= V^{jk} + 2 \int dy p_Y(y) [Wy + \nu]_j [Wy + \nu]_k \quad (\text{H29})$$

$$= V^{jk} + 2 \int dy p_Y(y) [Wy_c + \mu_E]_j [Wy_c + \mu_E]_k, \quad (\text{H30})$$

where the second equality follows from the definition of the quantum covariance matrix V of ρ_E^y and the fact that $Wy + \nu$ is the mean vector of ρ_E^y . The last equality follows from (H22) and (H26). Focusing on the second term, we find that

$$\begin{aligned} & \int dy p_Y(y) [Wy_c + \mu_E]_j [Wy_c + \mu_E]_k \\ &= \int dy p_Y(y) \left(\mu_E^j + \sum_\ell W_{j\ell} y_c^\ell \right) \left(\mu_E^k + \sum_m W_{km} y_c^m \right) \end{aligned} \quad (\text{H31})$$

$$= \mu_E^j \mu_E^k + \sum_{\ell, m} W_{j\ell} W_{km} \int dy p_Y(y) y_c^\ell y_c^m \quad (\text{H32})$$

$$= \mu_E^j \mu_E^k + \sum_{\ell, m} W_{j\ell} W_{km} \Sigma_{\ell m} \quad (\text{H33})$$

$$= \mu_E^j \mu_E^k + [W \Sigma W^T]_{jk}, \quad (\text{H34})$$

where the second equality follows because

$$\int dy p_Y(y) \sum_\ell W_{j\ell} y_c^\ell \mu_E^k = 0, \quad (\text{H35})$$

with similar reasoning for the other vanishing term. It follows that

$$\text{Tr} [\{\hat{r}_j, \hat{r}_k\} \rho_E] = V^{jk} + 2 \left([\mu_E^j \mu_E^k + W \Sigma W^T]_{jk} \right), \quad (\text{H36})$$

and we find from combining with (H25) that

$$V_E^{jk} = V^{jk} + 2[W \Sigma W^T]_{jk}, \quad (\text{H37})$$

or equivalently,

$$V_E = V + 2W\Sigma W^T. \quad (\text{H38})$$

So the expected density operator ρ_E is a quantum Gaussian state with mean vector given by (H22) and quantum covariance matrix given by (H38). The normalization Z_E of ρ_E is thus given by

$$Z_E := \det([V_E + i\Omega]/2), \quad (\text{H39})$$

and the Hamiltonian matrix G_E of ρ_E is given by

$$G_E := 2i\Omega \operatorname{arccoth}(iV_E\Omega). \quad (\text{H40})$$

Thus, the Holevo information $I(Y; E)$ works out to

$$I(Y; E) \quad (\text{H41})$$

$$= \int dy p_Y(y) D(\rho_E^y \| \rho_E) \quad (\text{H42})$$

$$= \int dy \frac{p_Y(y)}{2 \ln 2} \left[\ln \left(\frac{Z_E}{Z} \right) + \frac{1}{2} \operatorname{Tr}[V\Delta] + \delta^T G_E \delta \right] \quad (\text{H43})$$

$$= \frac{1}{2 \ln 2} \left[\ln \left(\frac{Z_E}{Z} \right) + \frac{1}{2} \operatorname{Tr}[V\Delta] + \int dy p_Y(y) \delta^T G_E \delta \right], \quad (\text{H44})$$

where

$$\delta := Wy + \nu - (W\mu + \nu) = W(y - \mu). \quad (\text{H45})$$

For the equality in (H43), we applied the formula in (H11). To evaluate the last integral, consider that

$$\begin{aligned} & \int dy p_Y(y) \delta^T G_E \delta \\ &= \int dy p_Y(y) \operatorname{Tr}[\delta \delta^T G_E] \end{aligned} \quad (\text{H46})$$

$$= \int dy p_Y(y) \operatorname{Tr}[W(y - \mu)(y - \mu)^T W^T G_E] \quad (\text{H47})$$

$$= \operatorname{Tr}[W\Sigma W^T G_E]. \quad (\text{H48})$$

Then the formula for the Holevo information $I(Y; E)$ reduces to

$$I(Y; E) = \frac{1}{2 \ln 2} \left[\ln \left(\frac{Z_E}{Z} \right) + \frac{1}{2} \operatorname{Tr}[V\Delta] + \operatorname{Tr}[W\Sigma W^T G_E] \right], \quad (\text{H49})$$

as claimed.

We now determine a formula for the Holevo information variance. We first consider the difference

$$\int dy p_Y(y) (D(\rho_E^y \| \rho_E))^2 - [I(Y; E)]^2. \quad (\text{H50})$$

Consider from (H43) that

$$(2 \ln 2)^2 \left[(D(\rho_E^y \| \rho_E))^2 - [I(Y; E)]^2 \right]$$

$$\begin{aligned} &= \left[\ln \left(\frac{Z_E}{Z} \right) + \frac{1}{2} \operatorname{Tr}[V\Delta] + \delta^T G_E \delta \right]^2 \\ &\quad - \left[\ln \left(\frac{Z_E}{Z} \right) + \frac{1}{2} \operatorname{Tr}[V\Delta] + \operatorname{Tr}[W\Sigma W^T G_E] \right]^2 \end{aligned} \quad (\text{H51})$$

$$\begin{aligned} &= 2 \left(\ln \left(\frac{Z_E}{Z} \right) + \frac{1}{2} \operatorname{Tr}[V\Delta] \right) (\delta^T G_E \delta - \operatorname{Tr}[W\Sigma W^T G_E]) \\ &\quad + (\delta^T G_E \delta)^2 - (\operatorname{Tr}[W\Sigma W^T G_E])^2. \end{aligned} \quad (\text{H52})$$

This means that

$$\begin{aligned} &(2 \ln 2)^2 \int dy p_Y(y) (D(\rho_E^y \| \rho_E))^2 - [I(Y; E)]^2 \\ &= \int dy p_Y(y) (\delta^T G_E \delta)^2 - (\operatorname{Tr}[W\Sigma W^T G_E])^2, \end{aligned} \quad (\text{H53})$$

due to (H48). To evaluate the first term, consider that

$$\begin{aligned} &\int dy p_Y(y) (\delta^T G_E \delta)^2 \\ &= \int dy p_Y(y) (y_c^T W^T G_E W y_c)^2. \end{aligned} \quad (\text{H54})$$

Then write the above as

$$\begin{aligned} &\int dy p_Y(y) \sum_{ijk\ell} y_c^i [W^T G_E W]_{ij} y_c^j y_c^k [W^T G_E W]_{k\ell} y_c^\ell \\ &= \sum_{ijk\ell} [W^T G_E W]_{ij} [W^T G_E W]_{k\ell} \int dy p_Y(y) y_c^i y_c^j y_c^k y_c^\ell \end{aligned} \quad (\text{H55})$$

$$\begin{aligned} &= \sum_{ijk\ell} [W^T G_E W]_{ij} [W^T G_E W]_{k\ell} \times \\ &\quad [\Sigma^{ij} \Sigma^{k\ell} + \Sigma^{ik} \Sigma^{j\ell} + \Sigma^{i\ell} \Sigma^{jk}] \end{aligned} \quad (\text{H56})$$

$$= (\operatorname{Tr}[W^T G_E W \Sigma])^2 + 2 \operatorname{Tr}[(W^T G_E W \Sigma)^2] \quad (\text{H57})$$

$$= (\operatorname{Tr}[W\Sigma W^T G_E])^2 + 2 \operatorname{Tr}[(W\Sigma W^T G_E)^2], \quad (\text{H58})$$

where we applied Isserlis' theorem [Iss18] to evaluate the fourth moment and we employed the facts that $W^T G_E W$ and Σ are symmetric matrices. So then by combining with (H53), we find that

$$\begin{aligned} &\int dy p_Y(y) (D(\rho_E^y \| \rho_E))^2 - [I(Y; E)]^2 \\ &= \frac{1}{2 \ln 2} \operatorname{Tr}[(W\Sigma W^T G_E)^2]. \end{aligned} \quad (\text{H59})$$

It remains to evaluate the term

$$\begin{aligned} &\int dy p_Y(y) V(\rho_E^y \| \rho_E) \\ &= \int dy \frac{p_Y(y)}{8 \ln^2 2} \left[\operatorname{Tr}[(\Delta V)^2] + \operatorname{Tr}[(\Delta \Omega)^2] + 4\delta^T G_E V G_E \delta \right] \end{aligned} \quad (\text{H60})$$

$$= \frac{1}{8 \ln^2 2} \left[\text{Tr}[(\Delta V)^2] + \text{Tr}[(\Delta \Omega)^2] \right] + \frac{1}{2 \ln^2 2} \int dy p_Y(y) \delta^T G_E V G_E \delta, \quad (\text{H61})$$

where we applied the formula in (H12). Then it follows that

$$\int dy p_Y(y) \delta^T G_E V G_E \delta = \int dy p_Y(y) \text{Tr}[\delta \delta^T G_E V G_E] \quad (\text{H62})$$

$$= \int dy p_Y(y) \text{Tr}[W(y - \mu)(y - \mu)^T W^T G_E V G_E] \quad (\text{H63})$$

$$= \text{Tr}[W \Sigma W^T G_E V G_E]. \quad (\text{H64})$$

Putting everything together, we find that

$$V(Y; E) = \frac{1}{8 \ln^2 2} \left[\text{Tr}[(\Delta V)^2] + \text{Tr}[(\Delta \Omega)^2] \right] + \frac{1}{2 \ln^2 2} \left[\text{Tr}[W \Sigma W^T G_E V G_E] + \text{Tr}[(W \Sigma W^T G_E)^2] \right], \quad (\text{H65})$$

as claimed. ■

The formulas from Proposition 3 can be applied to the scenario in which some modes of a Gaussian state are measured according to a “general-dyne” Gaussian measurement [GLS16, Ser17], which leaves a Gaussian ensemble of Gaussian states on the remaining modes. To see how this works, let ρ_{AB} denote a bipartite Gaussian state of $m + n$ modes, with m modes for system A and n modes for system B . Suppose that the $2(m + n) \times 1$ mean vector of ρ_{AB} is

$$\begin{bmatrix} \bar{r}_A \\ \bar{r}_B \end{bmatrix}, \quad (\text{H66})$$

and the $2(m + n) \times 2(m + n)$ quantum covariance matrix is

$$\begin{bmatrix} V_A & V_{AB} \\ V_{AB}^T & V_B \end{bmatrix}. \quad (\text{H67})$$

A general-dyne measurement of system B is described by a quantum Gaussian state ω_M with covariance matrix V_M satisfying the uncertainty principle $V_M + i\Omega \geq 0$ [GLS16, Ser17]. The POVM elements of this general-dyne detection are given by

$$\left\{ \frac{1}{(2\pi)^n} \hat{D}_{-y} \omega_M \hat{D}_y \right\}_{y \in \mathbb{R}^{2n}}, \quad (\text{H68})$$

where the displacement operator is defined as $\hat{D}_y := \exp(iy^T \Omega \hat{r})$, and the following completeness relation holds

$$\frac{1}{(2\pi)^n} \int_{\mathbb{R}^{2n}} dy \hat{D}_{-y} \omega_M \hat{D}_y. \quad (\text{H69})$$

(Note that ideal heterodyne detection corresponds to $V_M = I_{2n}$.) If this measurement is performed on system B of the state ρ_{AB} as specified above, then the induced ensemble on system A is $\{p_Y(y), \rho_A^y\}$, where

$$p_Y(y) = \frac{\exp\left(-\frac{1}{2}(y - \bar{r}_B)^T \left(\frac{V_B + V_M}{2}\right)^{-1} (y - \bar{r}_B)\right)}{\sqrt{(2\pi)^{2n} \det\left(\frac{V_B + V_M}{2}\right)}}, \quad (\text{H70})$$

and ρ_A^y is a quantum Gaussian state with mean vector

$$\bar{r}_A + V_{AB} (V_B + V_M)^{-1} (y - \bar{r}_B), \quad (\text{H71})$$

and quantum covariance matrix

$$V_A - V_{AB} (V_B + V_M)^{-1} V_{AB}^T. \quad (\text{H72})$$

Thus, we can use Proposition 3 to calculate both the Holevo information and the Holevo information variance of this ensemble with the following identifications in Definition 2:

$$\mu = \bar{r}_B, \quad (\text{H73})$$

$$\Sigma = \frac{V_B + V_M}{2}, \quad (\text{H74})$$

$$W = V_{AB} (V_B + V_M)^{-1}, \quad (\text{H75})$$

$$\nu = \bar{r}_A - V_{AB} (V_B + V_M)^{-1} \bar{r}_B, \quad (\text{H76})$$

$$V = V_A - V_{AB} (V_B + V_M)^{-1} V_{AB}^T. \quad (\text{H77})$$