

Bandit Linear Control

Asaf Cassel*

Tomer Koren†

October 30, 2021

Abstract

We consider the problem of controlling a known linear dynamical system under stochastic noise, adversarially chosen costs, and bandit feedback. Unlike the full feedback setting where the entire cost function is revealed after each decision, here only the cost incurred by the learner is observed. We present a new and efficient algorithm that, for strongly convex and smooth costs, obtains regret that grows with the square root of the time horizon T . We also give extensions of this result to general convex, possibly non-smooth costs, and to non-stochastic system noise. A key component of our algorithm is a new technique for addressing bandit optimization of loss functions with memory.

1 Introduction

Reinforcement learning studies sequential decision making problems where a learning agent repeatedly interacts with an environment and aims to improve her strategy over time based on the received feedback. One of the most fundamental tradeoffs in reinforcement learning theory is the *exploration vs. exploitation tradeoff*, that arises whenever the learner observes only partial feedback after each of her decisions, thus having to balance between exploring new strategies and exploiting those that are already known to perform well. The most basic and well-studied form of partial feedback is the so-called “bandit” feedback, where the learner only observes the cost of her chosen action on each decision round, while obtaining no information about the performance of other actions.

Traditionally, the environment dynamics in reinforcement learning are modeled as a Markov Decision Process (MDP) with a finite number of possible states and actions. The MDP model has been studied and analyzed in numerous different settings and under various assumptions on the transition parameters, the nature of the reward functions, and the feedback model. Recently, a particular focus has been given to continuous state-action MDPs, and in particular, to a specific family of models in classic control where the state transition function is linear. Concretely, in *linear control* the state evolution follows the linear dynamics:

$$x_{t+1} = A_*x_t + B_*u_t + w_t, \quad (1)$$

where $x_t \in \mathbb{R}^d$, $u_t \in \mathbb{R}^k$, $w_t \in \mathbb{R}^d$ are respectively the system state, action (control), and noise at round t , and $A_* \in \mathbb{R}^{d \times d}$, $B_* \in \mathbb{R}^{d \times k}$ are the system parameters. The goal is to minimize the total control costs with respect to cost function $c_t(x, u) : \mathbb{R}^d \times \mathbb{R}^k \rightarrow \mathbb{R}$ put forward on round t .

However, in contrast to the reinforcement learning literature, existing work on learning in linear control largely assumes the full feedback model, where after each decision round the learning agent observes the entire cost function c_t used to assign costs on the same round. In fact, to the best of our knowledge, thus far linear control has not been studied in the bandit setting, even in the special case where the costs are generated stochastically over time.

*School of Computer Science, Tel Aviv University; acassel@mail.tau.ac.il.

†School of Computer Science, Tel Aviv University; tkoren@tauex.tau.ac.il.

Contributions. In this paper, we introduce and study the *bandit linear control* problem, where a learning agent has to control a known linear dynamical system (as in Eq. (1)) under stochastic noise, adversarially chosen convex cost functions, and bandit feedback. Namely, after each decision round the learner only observes the incurred cost $c_t(x_t, u_t)$ as feedback. (We still assume, however, that the state evolution is fully observable.) For strongly convex and smooth cost functions, we present an efficient bandit algorithm that achieves $\tilde{O}(\sqrt{T})$ regret over T decision rounds, with a polynomial dependence on the natural problem parameters. This result is optimal up to polylogarithmic factors as it matches the optimal regret rate in the easier stationary (i.e., stateless) strongly convex and smooth bandit optimization setting [25, 16].

The starting point of our algorithmic approach is an approximate reparameterization of the online control problem due to [1, 2], called the Disturbance-Action Policy. In this new parameterization, the control problem is cast in terms of bounded memory convex loss functions, under which the cost of the learner on each round depends explicitly only on her last few decisions rather than on the entire history (this is thanks to strong stability conditions of the learned policies [8]).

As a key technical tool, we develop a new reduction technique for addressing bandit convex optimization with bounded memory. While an analogous reduction has been well established in the full feedback model [3, 1, 2], its adaptation to bandit feedback is far from straightforward. Indeed, loss functions with memory in the bandit setting were previously studied by [4], that showed a black-box reduction via a mini-batching approach that, for an algorithm achieving $O(T^{1/2})$ regret in the no-memory bandit setting, achieves $O(T^{2/3})$ regret with memory. While this technique imposes very few restrictions on the adversary, it degrades performance significantly even for adversaries with bounded memory. In contrast, [3] show that the full-feedback setting enjoys nearly no degradation when the adversary’s memory is fixed and bounded. Our new technique establishes a similar lossless reduction for bandit feedback with adversaries restricted to choosing *smooth* cost functions. Combining these ideas with standard techniques in (no-memory) bandit convex optimization [14, 24, 16] gives our main result.

Our techniques readily extend to weakly convex costs with regret scaling as $\tilde{O}(T^{2/3})$ in the smooth case and $\tilde{O}(T^{3/4})$ without smoothness. Moreover, these hold even without the stochastic assumptions on the system noise w_t , which were only required in our analysis for preserving the strong convexity of the costs through the reduction to loss functions with memory. We defer further details on these extensions to later sections and choose to focus first on the more challenging case—demonstrating how both the strong convexity and smoothness of the costs are exploited—and where $\tilde{O}(\sqrt{T})$ rates are possible.

Related work. The study of linear control has seen renewed interest in recent years. Most closely related to our work are [8, 1, 2], that study online linear control in the full-information setting. The latter paper establishes logarithmic regret bounds for the case where the costs are strongly convex and smooth and the noise is i.i.d. stochastic. Subsequently, [15] established a similar result for fixed and known quadratic losses and adversarial disturbances. Thus, we exhibit a gap between the achievable regret rates in the full- and bandit-feedback cases of our problem. (A similar gap exists in standard online optimization with strongly convex and smooth losses [17, 25].)

A related yet crucially different setting of partial observability was recently studied in [27], that considered the case where the state evolution is not revealed in full to the learner and only a low-dimensional projection of the state vector is observed instead. However, this model assumes full observability of the (convex) loss function following each round, and is therefore not directly comparable to ours. When the underlying linear system is initially unknown (this is the so-called adaptive control setting), regret of order \sqrt{T} was recently shown to be optimal for online linear control even with full feedback and quadratic (strongly convex) costs [6, 26]. Optimal and efficient algorithms matching these lower bounds were developed earlier in [9, 21, 1].

In the reinforcement learning literature on finite Markov Decision Processes (MDPs), regret minimization with bandit feedback was studied extensively (e.g., [22, 18, 10, 12, 5, 23, 19]). Our study can thus be viewed as a first step in an analogous treatment of bandit learning in continuous linear control.

2 Preliminaries

2.1 Problem Setup: Bandit Linear Control

We consider the setting of controlling a known linear dynamical system with unknown (strongly) convex losses and bandit feedback. The linear system is an instance of the process described in Eq. (1) where A_\star and B_\star are known, initialized for simplicity and without loss of generality at $x_0 = 0$. (Our assumptions on the nature of the various parameters are specified below.) Our goal is to minimize the total control cost in the following online setting where an *oblivious* adversary chooses cost functions $c_t : \mathbb{R}^d \times \mathbb{R}^k \rightarrow \mathbb{R}$ for $t \geq 1$. At round t :

- (1) The player chooses control u_t ;
- (2) The system transitions to x_{t+1} according to Eq. (1);
- (3) The player observes the new state x_{t+1} and the incurred cost $c_t(x_t, u_t)$.

The overall cost incurred is $J(T) = \sum_{t=1}^T c_t(x_t, u_t)$. We denote by $J_K(T)$ the overall cost of a linear controller $K \in \mathbb{R}^{d \times k}$, which chooses its actions as $u_t = -Kx_t$. For such controllers, it is useful to define the notion of strong stability [8] (and its refinement due to [2]), which is essentially a quantitative version of classic stability notions in linear control.

Definition 1 (strong stability). A controller K for the system (A_\star, B_\star) is (κ, γ) -strongly stable ($\kappa \geq 1$, $0 < \gamma \leq 1$) if there exist matrices Q, L such that $A_\star + B_\star K = QLQ^{-1}$, $\|L\| \leq 1 - \gamma$, and $\|K\|, \|Q\|, \|Q^{-1}\| \leq \kappa$. If additionally L is complex and diagonal and Q is complex, then K is diagonal (κ, γ) -strongly stable.

For fixed κ, γ , we define regret with respect to the class \mathcal{K} of (κ, γ) -diagonal strongly stable policies

$$\mathcal{K} = \{K \in \mathbb{R}^{d \times k} : K \text{ is } (\kappa, \gamma)\text{-diagonal strongly stable w.r.t. } (A_\star, B_\star)\}. \quad (2)$$

Beyond its relative simplicity, this class is interesting as it contains an asymptotic global optimum (with respect to *all* policies) when the costs are constrained to a fixed quadratic function, as in classical control. The regret compared to $K \in \mathcal{K}$ is given by $R(T, K) = J(T) - J_K(T)$. The pseudo regret is then defined as

$$\bar{\mathcal{R}}_{\mathcal{A}}(T) = \max_{K \in \mathcal{K}} \mathbf{E}[R_{\mathcal{A}}(T, K)],$$

where the expectation is taken with respect to the randomness of the algorithm, and the system noise.

Assumptions. Throughout we assume the following. There are known constants $\kappa_B \geq 1$, and $W, G, C, \alpha, \beta, \sigma > 0$ such that:

1. (System bound) $\|B_\star\| \leq \kappa_B$;
2. (Noise bound) $\|w_t\| \leq W \forall t \geq 1$;
3. (Cost bounds) If $\|x\|, \|u\| \leq D$ for large enough D ,¹ then

$$|c_t(x, u)| \leq CD^2, \quad \|\nabla_x c_t(x, u)\|, \|\nabla_u c_t(x, u)\| \leq GD;$$

4. (Curvature bounds) The costs $c_t(x, u)$ are α -strongly convex and β -smooth;
5. (Noise) The disturbances w_t are independent random variables satisfying $\mathbf{E}[w_t w_t^\top] \succeq \sigma^2 I$.

The above assumptions are fairly standard in recent literature (e.g., [1, 2]).

2.2 Online Optimization with Memory

We describe the setting of online optimization with memory [4, 3], which will serve as an intermediate framework for our algorithmic development. In this setting, an oblivious adversary chooses loss functions $f_t : \mathcal{K}_+^H \rightarrow \mathbb{R}$ over a domain $\mathcal{K}_+ \subseteq \mathbb{R}^d$, where $H \geq 1$ is the length of the adversary's memory. The game proceeds in rounds, where in round t , the player chooses $x_t \in \mathcal{K}_+$ and observes some form of feedback \hat{f}_t . Performance is evaluated using the expected *policy regret*,

$$\mathcal{R}_H(T) = \mathbf{E} \left[\sum_{t=H}^T f_t(x_{t+1-H}, \dots, x_t) \right] - \min_{x \in \mathcal{K}} \sum_{t=H}^T f_t(x, \dots, x), \quad (3)$$

¹The precise D for which this holds will be specified later as an explicit polynomial in the problem parameters.

where $\mathcal{K} \subseteq \mathcal{K}_+$ is the comparator set, which may differ from the domain \mathcal{K}_+ where the loss functions are defined (and are well behaved). Notice that for $H = 1$, the quantity $\mathcal{R}_1(T)$ refers to the regret of standard online optimization, with no memory.

We will rely on the following conditions for the loss functions. The first is a coordinate-wise Lipschitz property, while the second is standard smoothness, stated explicitly for an H -coordinate setup.

Definition 2. $f : \mathcal{K}_+^H \rightarrow \mathbb{R}$ is coordinate-wise L -Lipschitz if $\forall i \in [H], x_1, \dots, x_H, y_i \in \mathcal{K}_+$:

$$|f(x_1, \dots, x_i, \dots, x_H) - f(x_1, \dots, y_i, \dots, x_H)| \leq L \|x_i - y_i\|.$$

Definition 3. $f : \mathcal{K}_+^H \rightarrow \mathbb{R}$ is β -smooth if for any $x = (x_1, \dots, x_H), y = (y_1, \dots, y_H) \in \mathcal{K}_+^H$:

$$f(y) - f(x) \leq \sum_{i=1}^H \nabla_i f(x)^\top (y_i - x_i) + \frac{\beta}{2} \|y - x\|^2,$$

where ∇_i is the gradient with respect to x_i . When $x_1 = \dots = x_H = z$, we compress notation to $\nabla_i f(z)$.

2.3 Disturbance-Action Policies

Online linear control may be approximated by certain loss functions with memory, via a reparameterization suggested in [1, 2] named the Disturbance Action Policy (DAP). For completeness, we state the parameterization here even though our technical development will be mostly orthogonal.

Definition 4 (Disturbance-Action Policy). For a fixed linear controller $K_0 \in \mathcal{K}$ and parameters $M = (M^{[1]}, \dots, M^{[H]})$ with $M^{[i]} \in \mathbb{R}^{k \times d}$, a *disturbance-action policy* chooses an action at time t as

$$u_t(M) = -K_0 x_t + \sum_{i=1}^H M^{[i]} w_{t-i},$$

where for notational convenience we say $w_i = 0$ for $i \leq 0$.

This parameterization reduces the decision of the player at time t to choosing $M_t = (M_t^{[1]}, \dots, M_t^{[H]})$. The comparator set is given by $\mathcal{M} = \mathcal{M}^{[1]} \times \dots \times \mathcal{M}^{[H]}$, where

$$\mathcal{M}^{[i]} = \{M \in \mathbb{R}^{k \times d} : \|M\| \leq 2\kappa_B \kappa^3 (1 - \gamma)^i\},$$

however, the player may choose M_t from the slightly larger $\mathcal{M}_+ = \{2M : M \in \mathcal{M}\}$. The following defines the adversary's cost functions, referred to as surrogate or ideal cost functions. It is a summary of Definitions 4.2, 4.4, and 4.5 of [1], as well as 3.4 of [2], and while we do not use it explicitly, we give it here for the sake of concreteness.

Definition 5. Denote by $M_{0:H}$ a sequence of policies $M_0, \dots, M_H \in \mathcal{M}_+$. For a controller K , let $\tilde{A}_K = A_\star + KB_\star$, and define:

- (1) (disturbance-state transfer matrix) $\Psi_i^K(M_{0:H-1}) = \tilde{A}_K^i \mathbb{1}_{i \leq H} + \sum_{j=1}^H \tilde{A}_K^j B_\star M_{H-j}^{[i-j]} \mathbb{1}_{i-j \in [1, H]}$;
- (2) (ideal state) $y_{t+1}^K(M_{0:H-1}) = \sum_{i=0}^{2H} \Psi_i^K(M_{0:H-1}) w_{t-i}$;
- (3) (ideal action) $v_t^K(M_{0:H}) = -K y_t^K(M_{0:H-1}) + \sum_{i=1}^H M_H^{[i]} w_{t-i}$.

The surrogate or ideal costs and their expected value are respectively defined as:

$$f_t(M_{0:H}) = c_t(y_t^K(M_{0:H-1}), v_t^K(M_{0:H})), \quad F_t(M_{0:H}) = \mathbf{E}_w[c_t(y_t^K(M_{0:H-1}), v_t^K(M_{0:H}))].$$

The following are statements of the reduction's key results due to [2]. Denote:

$$H = \gamma^{-1} \log 2\kappa^3 T, \quad D_{x,u} = 8\gamma^{-1} \kappa_B \kappa^3 W(H\kappa_B + 1). \quad (4)$$

The first result relates the costs f_t, F_t and the associated regret to the original losses and regret.

Lemma 6. For any algorithm \mathcal{A} that plays policies $M_1, \dots, M_T \in \mathcal{M}_+$ we have:

- (i) $\|x_t\|, \|u_t\| \leq D_{x,u}$, and thus $|c_t(x_t, u_t)| \leq CD_{x,u}^2$;
- (ii) $|c_t(x_t, u_t) - f_t(M_{t-H:t})| \leq GD_{x,u}^2/T$;
- (iii) $\bar{\mathcal{R}}_{\mathcal{A}}(T) \leq \mathbf{E} \left[\sum_{t=H+1}^T F_t(M_{t-H:t}) - \min_{M_* \in \mathcal{M}} \sum_{t=H+1}^T F_t(M_*, \dots, M_*) \right] + 2D_{x,u}^2(G + HC)$.

The second result establishes certain desirable properties of the cost functions f_t and F_t .

Lemma 7. *Let $\tilde{F}_t : M \mapsto F_t(M, \dots, M)$. Then:*

- (i) f_t, F_t are coordinate-wise L_f -Lipschitz over \mathcal{M}_+ , with $L_f = 2\kappa_B \gamma^{-1} \kappa^3 G D_{x,u} W$;
- (ii) if $c_t(\cdot, \cdot)$ are β -smooth then f_t, F_t, \tilde{F}_t are β_f -smooth over \mathcal{M}_+ with $\beta_f = 25\beta\kappa_B^2\kappa^6 W^2 H/\gamma^2$;
- (iii) If $c_t(\cdot, \cdot)$ are α -strongly convex and $\mathbf{E}[w_t w_t^\top] \succeq \sigma^2 I$ then \tilde{F}_t are α_f -strongly convex over \mathcal{M} with $\alpha_f = \frac{1}{36}\alpha\sigma^2\gamma^2/\kappa^{10}$.

We note that the second claim of Lemma 7 was not previously established. We prove it in Appendix C.3 using similar techniques to those used for the first claim.

3 Algorithm and Main Results

We present a new algorithm for the bandit linear control problem, detailed in Algorithm 1, for which we prove:

Theorem 8. *Let $H, D_{x,u}, \alpha_f, \beta_f$ be as in Eq. (4) and Lemma 7, K_0 be a (κ, γ) -diagonal strongly stable controller, and $n = \min\{d, k\}$. Suppose Algorithm 1 is run with the above parameters, and*

$$\eta = \sqrt{\frac{3n^2 + (15\beta_f/\alpha_f) \log T}{Td^2k^2C^2D_{x,u}^4}}, \quad r_t^{[i]} = [(2\kappa_B\kappa^3(1-\gamma)^i)^{-2} + \frac{1}{2}\alpha_f\eta t]^{-1/2}.$$

Then the expected pseudo-regret is bounded as

$$\bar{\mathcal{R}}_{\mathcal{A}}(T) \leq 4dkCD_{x,u}^2(H+1)^2\sqrt{T(3n^2 + (15\beta_f/\alpha_f) \log T)} + \tilde{O}(T^{1/4}).$$

The big- \tilde{O} notation in the theorem hides polynomial dependence in the problem parameters and poly-log dependence on T . We prove Theorem 8 later in Section 5 after discussing our reduction technique.

There are three main components to the algorithm:

- (1) A randomized schedule to determine the times of parameter updates, which ensures that these are at least $2(H+1)$ apart and $O(H)$ in expectation. This is part of our new reduction scheme, which is presented and discussed in Section 4.
- (2) A standard one-point gradient estimate that gives a (nearly-)unbiased estimate for the gradient of a function based on bandit feedback, by perturbing the policy using uniform samples from the unit Euclidean sphere of $\mathbb{R}^{(d \times k) \times H}$; this is denoted as $U \sim \mathcal{S}^{(k \times d) \times H}$.
- (3) A preconditioned (online) gradient update rule that uses mixed regularization and standard Euclidean projections $\Pi_{\mathcal{M}^{[i]}}[M] = \arg \min_{M' \in \mathcal{M}^{[i]}} \|M - M'\|_F$.

The mixed regularization, inspired by [16], is comprised of two terms (see $r_t^{[i]}$ in Theorem 8): the first exploits the strong convexity of the (expected) loss functions, while the second accounts for the small diameter of $\mathcal{M}^{[i]}$, which might be significantly smaller than the magnitude of the perturbations required for the gradient estimates (this is particularly problematic for large i). To avoid sampling too far away from the “admissible” set, where the cost functions are well-behaved, we cap the perturbations of the one-point estimate according to the radii $\{r_t^{[i]}\}_{i \in [H]}$ and increase the regularization term to account for the higher variance of the resulting gradient estimate.

4 Bandit Convex Optimization with Memory

In this section we give the details of our reduction from BCO with memory to standard BCO, that constitutes a key element of our main algorithm. The application to bandit linear control, however, will require a slightly more general feedback model than the usual notion of bandit feedback.

Algorithm 1 Bandit Linear Control

```
1: input: controller  $K_0$ , memory length  $H$ , step size  $\eta$ , and coordinate-wise sampling radii  $r_t^{[i]}$ 
2: Draw  $U_1 \sim \mathcal{S}^{(k \times d) \times H}$ .
3: Initialize  $\tau = 1$ ,  $\bar{M}_1 = 0$ ,  $M_1^{[i]} = r_1^{[i]} U_1^{[i]}$  ( $\forall i \in [H]$ ).
4: for  $t = 1, \dots, T$  do
5:   Play  $u_t = -K_0 x_t + \sum_{i=1}^H M_t^{[i]} w_{t-i}$ ,
6:   Observe  $x_{t+1}$  and  $c_t(x_t, u_t)$ ; update  $w_t = x_{t+1} - A_* x_t - B_* u_t$ .
7:   Draw  $b_t \sim \text{Bernoulli}(1/(2H+2))$ 
8:   if  $t \geq 2H+2$  and  $b_t \prod_{i=1}^{2H+1} (1 - b_{t-i}) = 1$  then
9:     Update  $\bar{M}_{\tau+1}^{[i]} = \Pi_{\mathcal{M}^{[i]}} [\bar{M}_\tau^{[i]} - \eta dk H c_t(x_t, u_t) r_\tau^{[i]} U_\tau^{[i]}]$  ( $\forall i \in [H]$ ).
10:     $\tau \leftarrow \tau + 1$ 
11:    Draw  $U_\tau \sim \mathcal{S}^{(k \times d) \times H}$ .
12:     $M_{t+1}^{[i]} = \bar{M}_\tau^{[i]} + r_\tau^{[i]} U_\tau^{[i]}$  ( $\forall i \in [H]$ ).
13:   else
14:      $M_{t+1} = M_t$ 
```

4.1 Setup

We consider the online optimization with memory setting described in Section 2.2, with feedback model such that on round t :

- (1) The player chooses $x_t \in \mathcal{K}_+$, and independently, the adversary draws a random ξ_t ;
- (2) The player observes feedback $\hat{f}_t = \hat{f}_t(x_{t+1-H:t}; \xi_{t+1-H:t})$ such that, if $x_{t+1-H:t}$ are jointly independent of $\xi_{t+1-H:t}$, then $|\mathbf{E}_{\xi_{t+1-H:t}}[\hat{f}_t] - f_t(x_{t+1-H:t})| \leq \varepsilon$.

The above expectation is only with respect to the variables $\xi_{t+1-H:t}$, and $\varepsilon \geq 0$ is a fixed parameter (possibly unknown to the player). Our feedback model, which may potentially seem non-standard, encompasses the following ideas, both of which are necessary for the application to linear control:

- In the standard no-memory setting ($H = 1$), standard arguments apply even if the feedback received by the learner is randomized, as long as it is independent of the learner's decision on the same round. In the memory setting, the analogous condition is that the last H decisions do not depend on the adversary's randomness during this time.
- We allow feedback of the form $\hat{f}_t = f_t(x_t) + \varepsilon_t$, where ε_t is a small *adaptive* adversarial disturbance that can depend on all past history (yet is at most ε in absolute value).

4.2 Base BCO Algorithm

The reduction relies on the following properties of the base algorithm $\mathcal{A}(T)$ for BCO with no memory, that can be used against an adversary that chooses loss function from $\mathcal{F} \subseteq \{f : \mathcal{K}_+ \rightarrow \mathbb{R}\}$, and observing feedback satisfying $|\mathbf{E}_{\xi_t}[\hat{f}_t] - f_t(x_t)| \leq \varepsilon$:

- (i) Its regret at times $t \leq T$ is bounded as $\mathcal{R}_1(t) \leq R_{\mathcal{A}}(T)$ where $R_{\mathcal{A}}(T) \geq 0$;
- (ii) Its predictions x_1, \dots, x_T satisfy $\|\bar{x}_{t+1} - \bar{x}_t\| \leq \delta_t$, and $\|x_t - \bar{x}_t\| \leq \vartheta_t$ almost surely, where \bar{x}_t is the expected value of x_t conditioned on all past history up to (not including) the player's decision at time t , and δ_t, ϑ_t are decreasing sequences.

The above properties are satisfied by standard BCO algorithms, often without any modification. In particular, these algorithms are amenable to our randomized and perturbed feedback model and often require only a slight modification in their regret analyses to account for the additive disturbances. (In Appendix B we give an analysis of a concrete BCO algorithm in this setting.)

Notice that, crucially, δ_t bounds the change in the algorithm's *expected* predictions as opposed to their actual movement. This is crucial as typical BCO algorithms add large perturbations to their predictions (as part of their gradient estimation procedure), with magnitude often significantly larger than the change in the underlying expected prediction; i.e., it holds that $\vartheta_t \gg \delta_t$. Our reduction procedure is able to exploit this observation to improve performance for smooth functions.

4.3 The Reduction

We can now present our reduction from BCO with memory to BCO with no memory ($H = 1$); see Algorithm 2. The idea is simple: we use a base algorithm for standard BCO, denoted here by \mathcal{A} , using the observed feedback, but make sure that \mathcal{A} is updated at most once in every H rounds. Since the setup is adversarial, we cannot impose a deterministic update schedule; instead, we employ a randomized schedule in which \mathcal{A} is invoked with probability $1/H$ on each round, but constrained so that this does not happen too frequently. (A similar technique was used in a different context in [11, 7].)

The induced spacing between consecutive updates of \mathcal{A} serves two purposes at once: first, it reduces the H -memory loss functions to functions of a single argument, amenable to optimization using \mathcal{A} ; second, it facilitates (conditional) probabilistic independence between consecutive updates which is crucial for dealing with the extended feedback model as required by the application to linear control. (We note that these conditions are not satisfied by existing techniques [4, 3, 1].)

Algorithm 2 BCO Reduction

```

1: input: memory length  $H$ , BCO algorithm  $\mathcal{A}(T/H)$ .
2: set:  $x_1 \leftarrow \mathcal{A}.\text{initialize}()$ 
3: for  $t = 1, \dots, T$  do
4:   Play  $x_t$  (independently, adversary draws  $\xi_t$ )
5:   Observe feedback  $\hat{f}_t(x_{t+1-H:t}; \xi_{t+1-H:t})$ 
6:   Draw  $b_t \sim \text{Bernoulli}(1/H)$ 
7:   if  $t \geq H$  and  $b_t \prod_{i=1}^{H-1} (1 - b_{t-i}) = 1$  then
8:      $x_{t+1} \leftarrow \mathcal{A}.\text{update}(\hat{f}_t)$ 
9:   else
10:     $x_{t+1} \leftarrow x_t$ 

```

The following is the main result of the reduction.

Theorem 9. *Suppose Algorithm 2 is run using $\mathcal{A}(T/H)$ satisfying the above properties:*

(i) *If $\tilde{f}_t : x \mapsto f_t(x, \dots, x)$ satisfy $\tilde{f}_t \in \mathcal{F}$, and f_t are coordinate-wise L -Lipschitz then*

$$\mathcal{R}_H(T) \leq 3HR_{\mathcal{A}}\left(\frac{T}{H}\right) + \frac{1}{2}LH^2 \sum_{t=1}^{\lfloor T/H \rfloor} (\delta_t + 2\vartheta_t);$$

(ii) *If additionally \tilde{f}_t are convex and f_t are β -smooth, then*

$$\mathcal{R}_H(T) \leq 3HR_{\mathcal{A}}\left(\frac{T}{H}\right) + \frac{1}{2}H^2 \sum_{t=1}^{\lfloor T/H \rfloor + 1} (L\delta_t + \beta\delta_t^2 + 6\beta\vartheta_t^2).$$

4.4 Proof Ideas

We provide some of the main ideas for proving Theorem 9. We start with the following technical lemma that quantifies the duration between updates of the base BCO algorithm.

Lemma 10. *Suppose b_t in Algorithm 2 are drawn in advance for all $t \geq 1$. Let $t_0 = 0$ and for $i \geq 1$ let*

$$t_i = \min\left\{t \geq t_{i-1} + H \mid b_t \prod_{i=1}^{H-1} (1 - b_{t-i}) = 1\right\}.$$

Then denoting $S = \{t_i \mid H \leq t_i < T\}$, the times Algorithm 2 updates \mathcal{A} , we have that (i) $|S| \leq \lfloor T/H \rfloor$, and (ii) $\mathbf{E}[t_i - t_{i-1}] = \mathbf{E}t_1 \leq 3H$ for all i .

See proof in Appendix A.2. The next lemma considers Algorithm 2 as a BCO without memory algorithm that incurs loss $\tilde{f}_t(x_{t+1-H})$ at each round and relates its regret to that of the base algorithm.

Lemma 11. *Suppose Algorithm 2 is run with $\mathcal{A}(T/H)$ as in Theorem 9. If $\tilde{f}_t \in \mathcal{F}$ then we have that*

$$\mathbf{E} \left[\sum_{t=H}^T \tilde{f}_t(x_{t+1-H}) \right] - \sum_{t=H}^T \tilde{f}_t(x) \leq 3HR_{\mathcal{A}} \left(\frac{T}{H} \right), \quad \forall x \in \mathcal{K}.$$

Proof. Let S be the times Algorithm 2 updates \mathcal{A} as defined in Lemma 10. Denote $\tilde{\xi}_t = \xi_{t+1-H:t}$, and notice that $\{\tilde{\xi}_t\}_{t \in S}$ are mutually independent since Algorithm 2 ensures there are at least H rounds between updates of \mathcal{A} . Moreover, this implies that for any $t \in S$, $x_{t+1-H} = \dots = x_t$, and these are also independent of $\tilde{\xi}_t$. Our H -memory feedback model thus implies that

$$|\tilde{f}_t(x_t) - \mathbf{E}_{\tilde{\xi}_t}[\hat{f}_t]| \leq \varepsilon, \quad \forall t \in S,$$

and since $\tilde{f}_t \in \mathcal{F}$, we can use the regret bound of \mathcal{A} to get that for any $x \in \mathcal{K}$

$$\mathbf{E} \left[\sum_{t \in S} \tilde{f}_t(x_t) - \sum_{t \in S} \tilde{f}_t(x) \right] = \mathbf{E} \left[\mathbf{E} \left[\sum_{t \in S} \tilde{f}_t(x_t) - \sum_{t \in S} \tilde{f}_t(x) \mid S \right] \right] = \mathbf{E}[\mathcal{R}_1(|S|)] \leq R_{\mathcal{A}} \left(\frac{T}{H} \right),$$

where the last transition also used the fact that $|S| \leq T/H$ (see Lemma 10). Next, denote $\chi_t = b_t \prod_{i=1}^{H-1} (1 - b_{t-i})$ and notice that $\mathbf{E}\chi_t = \mathbf{E}\chi_H$. Then for any fixed $x \in \mathcal{K}$ we have that

$$\mathbf{E} \left[\sum_{t \in S} \tilde{f}_t(x) \right] = \mathbf{E} \left[\sum_{t=H}^T \tilde{f}_t(x) \chi_t \right] = \sum_{t=H}^T \tilde{f}_t(x) \mathbf{E}[\chi_t] = \mathbf{E}[\chi_H] \sum_{t=H}^T \tilde{f}_t(x).$$

Next, notice that x_{t+1-H} is independent of χ_t and since $\chi_t = 1$ implies that $x_t = x_{t+1-H}$, we get that

$$\mathbf{E} \left[\sum_{t \in S} \tilde{f}_t(x_t) \right] = \mathbf{E} \left[\sum_{t=H}^T \tilde{f}_t(x_t) \chi_t \right] = \sum_{t=H}^T \mathbf{E}[\tilde{f}_t(x_{t+1-H})] \mathbf{E}[\chi_t] = \mathbf{E}[\chi_H] \mathbf{E} \left[\sum_{t=H}^T \tilde{f}_t(x_{t+1-H}) \right].$$

Finally, combining the last three equations we get that

$$\mathbf{E} \left[\sum_{t=H}^T \tilde{f}_t(x_{t+1-H}) \right] - \sum_{t=H}^T \tilde{f}_t(x) \leq (\mathbf{E}[\chi_H])^{-1} R_{\mathcal{A}} \left(\frac{T}{H} \right) \leq 3HR_{\mathcal{A}} \left(\frac{T}{H} \right),$$

where the last transition used the non-negativity of $R_{\mathcal{A}}(T/H)$ and that $\mathbf{E}[\chi_H] \geq 1/3H$. \blacksquare

Given the above, completing the proof of Theorem 9 entails bounding $\mathbf{E} \left[\sum_{t=H}^T f_t(x_{t+1-H}, \dots, x_t) - \tilde{f}_t(x_{t+1-H}) \right]$. While the smooth case requires some delicate care for achieving the squared dependence on ϑ_t , the proof is otherwise quite technical and thus deferred to Appendix A.1.

5 Analysis

We first require the following, mostly standard, analysis of the base procedure of Algorithm 1 for the no-memory setting ($H = 1$). See proof in Appendix C.1.

Lemma 12. *Consider the setting of Section 4 with $H = 1$ and $\varepsilon \in \tilde{O}(1/T)$, against an adversary that chooses $f_t : \mathcal{M}_+ \rightarrow \mathbb{R}$ that are α_f -strongly convex and β_f -smooth. Let $d_{\mathcal{M}} = dkH$ be the dimension of \mathcal{M} , and $\mathcal{R}_1(t)$ be the regret of a procedure that at time t :*

- (i) *Draws $U_t \sim \mathcal{S}^{(k \times d) \times H}$; and plays M_t where $M_t^{[i]} = \bar{M}_t^{[i]} + r_t^{[i]} U_t^{[i]}$ ($\forall i \in [H]$)*
- (ii) *Observes \hat{f}_t ; and sets $\hat{g}_t^{[i]} = (d_{\mathcal{M}}/r_t^{[i]}) \hat{f}_t U_t^{[i]}$ ($\forall i \in [H]$)* (1-point gradient estimate)
- (iii) *Updates $\bar{M}_{t+1}^{[i]} = \Pi_{\mathcal{M}^{[i]}}[\bar{M}_t^{[i]} - \eta(r_t^{[i]})^2 \hat{g}_t^{[i]}]$ ($\forall i \in [H]$).* (preconditioned update)

If $|\hat{f}_t| \leq \hat{C}$, $r_t^{[i]}$, n are as in Theorem 8, and $\eta \in \tilde{O}(T^{-1/2})$ then $\delta_t = d_{\mathcal{M}} \hat{C} \sqrt{2\eta/\alpha_f t}$ and $\vartheta_t^2 = 2/\alpha_f \eta t$ satisfy the assumptions of $\mathcal{A}(T)$ in Theorem 9, and for all $t \leq T$

$$\mathcal{R}_1(t) \leq \frac{1}{\eta} \left(Hn^2 + \frac{2\beta_f}{\alpha_f} (1 + \log T) \right) + \frac{d_{\mathcal{M}}^2 \hat{C}^2}{2} \eta T + \tilde{O}(T^{1/4}).$$

Proof of Theorem 8. Consider f_t, F_t from Definition 5 and notice that f_t depends on the last $H+1$ policies but also the last $2(H+1)$ system noises. This means that the effective memory of the adversary is $2(H+1)$, prompting us to modify the definitions of f_t, F_t to receive $2(H+1)$ policies but ignore the first $H+1$, i.e.,

$$F_t^{\text{new}}(M_{0:2H+1}) = F_t(M_{H+1:2H+1}), \quad f_t^{\text{new}}(M_{0:2H+1}) = f_t(M_{H+1:2H+1}).$$

Henceforth, f_t, F_t refer to $f_t^{\text{new}}, F_t^{\text{new}}$. Notice that Lemmas 6 and 7 are not impacted by this change and hold with the same H as the original functions. We thus have that F_t are L_f -coordinate-wise Lipschitz and β_f -smooth, and \tilde{F}_t are α_f -strongly convex and β_f -smooth. Moreover, $|c_t(x_t, u_t)| \leq CD_{x,u}^2$, and if $M_{t-1-2H:t}$ are independent of $w_{t-1-2H:t}$ then

$$|\mathbf{E}_{w_{t-1-2H:t}}[c_t(x_t, u_t) - f_t(M_{t-1-2H:t})]| = |\mathbf{E}_{w_{t-1-2H:t}}[c_t(x_t, u_t)] - F_t(M_{t-1-2H:t})| \leq \frac{GD_{x,u}^2}{T}.$$

Now, Consider Algorithm 1 in the context of the BCO with memory setting presented in Section 4 with $\varepsilon = GD_{x,u}^2/T$, feedback bounded by $CD_{x,u}^2$, and let $\mathcal{R}_{2(H+1)}(T)$ be its regret against an adversary that chooses functions $h_t : \mathcal{M}_+^{2(H+1)} \rightarrow \mathbb{R}$ satisfying:

- h_t are L_f -coordinate-wise Lipschitz and β_f -smooth;
- $\tilde{h}_t : M \mapsto h_t(M, \dots, M)$ are α_f -strongly convex and β_f -smooth.

Since F_t satisfy these assumptions, and our choice of $r_t^{[i]}$ ensures that $M_t \in \mathcal{M}_+$, Lemma 6 yields that

$$\bar{\mathcal{R}}_{\mathcal{A}}(T) \leq \mathcal{R}_{2(H+1)}(T) + 2D_{x,u}^2(G + HC),$$

and since the second term is at most poly-log in T , it remains to bound $\mathcal{R}_{2(H+1)}(T)$. To that end, notice that Algorithm 1 fits the mold of our reduction procedure given in Algorithm 2 with base procedure as in Lemma 12. Now, invoking Lemma 12 with $\hat{C} = CD_{x,u}^2$ and horizon $T/2(H+1)$, the second term of Theorem 9 satisfies that

$$\sum_{t=1}^{\lfloor T/2(H+1) \rfloor + 1} (L_f \delta_t + \beta_f \delta_t^2 + 6\beta_f \vartheta_t^2) \leq \frac{12\beta_f \log T}{\alpha_f \eta} + \tilde{O}(T^{1/4}),$$

and further using Lemma 12 to bound the first term of Theorem 9, and simplifying, we get that

$$\mathcal{R}_{2(H+1)}(T) \leq 2(H+1)^2 \left[\frac{1}{\eta} \left(3n^2 + \frac{15\beta_f}{\alpha_f} \log T \right) + d^2 k^2 C^2 D_{x,u}^4 \eta T \right] + \tilde{O}(T^{1/4}).$$

Our choice of η yields the final bound. ■

6 Extensions to General Costs and Adversarial Noise

In this section we consider the case where the cost functions chosen by the adversary are general, possibly non-smooth (weakly) convex functions. Importantly, we also allow the system noise to be chosen by an oblivious adversary. Formally, the setup is identical to Section 2.1 but with the following modifications:

1. Only Assumptions 1-3 are assumed throughout;
2. The costs $c_t(x, u)$ are (weakly) convex functions of (x, u) ;
3. The disturbances w_t are chosen by an oblivious adversary, i.e., one that has knowledge of the algorithm but must choose all disturbances before the first round. (Notice that w_t are still bounded as per Assumption 1.)

To ease notation, recall that $n = \min\{d, k\}$, and $D^2 = \max_{M_1, M_2 \in \mathcal{M}} \|M_1 - M_2\|_F^2 \leq 4n^2 \kappa_B^2 \kappa^6 / \gamma$. The following extends our main results, given in Theorem 8, to the setting above.

Theorem 13. *Let $H, D_{x,u}, L_f, \beta_f$ be as in Eq. (4) and Lemma 7, K_0 be a (κ, γ) -strongly stable controller, $d_{\mathcal{M}} = dkH$, $\hat{C} = CD_{x,u}^2$, and $r_0^{[i]} = 2\kappa_B \kappa^3 (1 - \gamma)^i$. Then:*

1. The regret of running Algorithm 1 with $\eta = 2 \left[\frac{(H+1)^3 L_f^2 D^2}{d_{\mathcal{M}}^6 \hat{C}^6 T} \right]^{1/4}$, and $r_t^{[i]} = \left[(r_0^{[i]})^{-2} + \frac{4L_f \sqrt{(H+1)T}}{d_{\mathcal{M}} \hat{C} D} \right]^{-1/2}$ satisfies

$$\mathcal{R}_{\mathcal{A}}(T) \leq 13 \sqrt{2dknCD_{x,u}^2 \kappa_B \kappa^3 \gamma^{-1/2} L_f (H+1)^{7/2} T^{3/4}} + \tilde{O}(T^{1/2});$$

2. if c_t are β -smooth, then the regret of running Algorithm 1 with $r_t^{[i]} = \left[(r_0^{[i]})^{-2} + \left(\frac{4\beta_f^2 T}{(H+1)d_{\mathcal{M}}^2 \hat{C}^2 D^2} \right)^{1/3} \right]^{-1/2}$, and $\eta = \left[\frac{2(H+1)\beta_f D^2}{d_{\mathcal{M}}^4 \hat{C}^4 T} \right]^{1/3}$ satisfies

$$\mathcal{R}_{\mathcal{A}}(T) \leq 12 \left(2dknCD_{x,u}^2 \kappa_B \kappa^3 \sqrt{\beta_f / \gamma} (H+1)^3 T \right)^{2/3} + \tilde{O}(T^{1/2}).$$

The proof of Theorem 13 is given in Appendix D, and follows the same ideas behind Theorem 8 with a few technical adjustments. Notice that Theorem 13 only requires a strongly stable initial controller K_0 , as opposed to the *diagonal* strongly stable controller needed for Theorem 8. Moreover, since the noise is no longer stochastic, our definition of pseudo regret now coincides with the standard definition of regret given by $\mathcal{R}_{\mathcal{A}}(T) = \mathbf{E}[\max_{K \in \mathcal{K}} R_{\mathcal{A}}(T, K)]$.

Acknowledgements

This work was partially supported by the Israeli Science Foundation (ISF) grant 2549/19 and by the Yandex Initiative in Machine Learning.

References

- [1] N. Agarwal, B. Bullins, E. Hazan, S. Kakade, and K. Singh. Online control with adversarial disturbances. In *International Conference on Machine Learning*, pages 111–119, 2019.
- [2] N. Agarwal, E. Hazan, and K. Singh. Logarithmic regret for online control. In *Advances in Neural Information Processing Systems*, pages 10175–10184, 2019.
- [3] O. Anava, E. Hazan, and S. Mannor. Online learning for adversaries with memory: price of past mistakes. In *Advances in Neural Information Processing Systems*, pages 784–792, 2015.
- [4] R. Arora, O. Dekel, and A. Tewari. Online bandit learning against an adaptive adversary: from regret to policy regret. In *Proceedings of the 29th International Conference on Machine Learning*, pages 1747–1754, 2012.
- [5] M. G. Azar, I. Osband, and R. Munos. Minimax regret bounds for reinforcement learning. In *Proceedings of the 34th International Conference on Machine Learning-Volume 70*, pages 263–272. JMLR. org, 2017.
- [6] A. Cassel, A. Cohen, and T. Koren. Logarithmic regret for learning linear quadratic regulators efficiently. *arXiv preprint arXiv:2002.08095*, 2020.
- [7] N. Cesa-Bianchi, C. Gentile, and Y. Mansour. Nonstochastic bandits with composite anonymous feedback. In *Conference On Learning Theory*, pages 750–773, 2018.
- [8] A. Cohen, A. Hasidim, T. Koren, N. Lazic, Y. Mansour, and K. Talwar. Online linear quadratic control. In *International Conference on Machine Learning*, pages 1029–1038, 2018.
- [9] A. Cohen, T. Koren, and Y. Mansour. Learning linear-quadratic regulators efficiently with only \sqrt{T} regret. In *International Conference on Machine Learning*, pages 1300–1309, 2019.
- [10] O. Dekel and E. Hazan. Better rates for any adversarial deterministic MDP. In *International Conference on Machine Learning*, pages 675–683, 2013.

- [11] O. Dekel, E. Hazan, and T. Koren. The blinded bandit: Learning with adaptive feedback. In *Advances in Neural Information Processing Systems*, pages 1610–1618, 2014.
- [12] T. Dick, A. Gyorgy, and C. Szepesvari. Online learning in markov decision processes with changing cost sequences. In *International Conference on Machine Learning*, pages 512–520, 2014.
- [13] J. Duchi, E. Hazan, and Y. Singer. Adaptive subgradient methods for online learning and stochastic optimization. *Journal of machine learning research*, 12(Jul):2121–2159, 2011.
- [14] A. D. Flaxman, A. T. Kalai, and H. B. McMahan. Online convex optimization in the bandit setting: gradient descent without a gradient. In *Proceedings of the sixteenth annual ACM-SIAM symposium on Discrete algorithms*, pages 385–394, 2005.
- [15] D. J. Foster and M. Simchowitz. Logarithmic regret for adversarial online control. *arXiv preprint arXiv:2003.00189*, 2020.
- [16] E. Hazan and K. Levy. Bandit convex optimization: Towards tight bounds. In *Advances in Neural Information Processing Systems*, pages 784–792, 2014.
- [17] E. Hazan, A. Agarwal, and S. Kale. Logarithmic regret algorithms for online convex optimization. *Machine Learning*, 69(2-3):169–192, 2007.
- [18] T. Jaksch, R. Ortner, and P. Auer. Near-optimal regret bounds for reinforcement learning. *Journal of Machine Learning Research*, 11(Apr):1563–1600, 2010.
- [19] T. Jin and H. Luo. Learning adversarial MDPs with bandit feedback and unknown transition. *arXiv preprint arXiv:1912.01192*, 2019.
- [20] D. A. Levin and Y. Peres. *Markov chains and mixing times*. American Mathematical Society, 2017.
- [21] H. Mania, S. Tu, and B. Recht. Certainty equivalence is efficient for linear quadratic control. In *Advances in Neural Information Processing Systems*, pages 10154–10164, 2019.
- [22] G. Neu, A. Antos, A. György, and C. Szepesvári. Online markov decision processes under bandit feedback. In *Advances in Neural Information Processing Systems*, pages 1804–1812, 2010.
- [23] A. Rosenberg and Y. Mansour. Online stochastic shortest path with bandit feedback and unknown transition function. In *Advances in Neural Information Processing Systems*, pages 2209–2218, 2019.
- [24] A. Saha and A. Tewari. Improved regret guarantees for online smooth convex optimization with bandit feedback. In *Proceedings of the Fourteenth International Conference on Artificial Intelligence and Statistics*, pages 636–642, 2011.
- [25] O. Shamir. On the complexity of bandit and derivative-free stochastic convex optimization. In *Conference on Learning Theory*, pages 3–24, 2013.
- [26] M. Simchowitz and D. J. Foster. Naive exploration is optimal for online LQR. *arXiv preprint arXiv:2001.09576*, 2020.
- [27] M. Simchowitz, K. Singh, and E. Hazan. Improper learning for non-stochastic control. *arXiv preprint arXiv:2001.09254*, 2020.

A Reduction to no-Memory BCO Proofs

A.1 Proof of Theorem 9

We first need the following lemma, which bounds the prediction shifts and magnitudes of Algorithm 2.

Lemma 14. *Suppose Algorithm 2 is run with $\mathcal{A}(T/H)$ as in Theorem 9, and let x_1, \dots, x_T be its predictions. Then we have that for $q > 0$:*

- (i) $\sum_{t=H}^T \sum_{i=2}^H \|x_{t+i-H} - x_{t+1-H}\| \leq \sum_{t=1}^{\lfloor T/H \rfloor} (\delta_t + 2\vartheta_t)$;
- (ii) $\sum_{t=H}^T \sum_{i=1}^H \|\bar{x}_{t+i-H} - \bar{x}_{t+1-H}\|^q \leq \frac{1}{2} H^2 \sum_{t=1}^{\lfloor T/H \rfloor} \delta_t^q$;
- (iii) $\mathbf{E}[\sum_{t=H}^T \sum_{i=1}^H \|x_{t+i-H} - \bar{x}_{t+i-H}\|^2] \leq 3H^2 \sum_{t=1}^{\lfloor T/H \rfloor + 1} \vartheta_t^2$.

The proof is mostly technical, and relies on the fact that Algorithm 2 changes its prediction at most once every H rounds. See proof in Appendix A.2. We are now ready to prove Theorem 9.

Proof of Theorem 9. We show that Algorithm 2 achieves the desired regret bound. Given Lemma 11, the proof is concluded by upper bounding $\mathbf{E}[\sum_{t=H}^T f_t(x_{t+1-H}, \dots, x_t) - \tilde{f}_t(x_{t+1-H})]$ under each set of assumptions. First, using the coordinate-wise Lipschitz property we get that

$$\sum_{t=H}^T f_t(x_{t+1-H}, \dots, x_t) - \tilde{f}_t(x_{t+1-H}) \leq L \sum_{t=H}^T \sum_{i=2}^H \|x_{t+i-H} - x_{t+1-H}\| \leq \frac{1}{2} L H^2 \sum_{t=1}^{\lfloor T/H \rfloor} (\delta_t + 2\vartheta_t),$$

where the last transition follows by Lemma 14. Taking expectation concludes the first part of the proof. Now, notice that by its definition, \bar{x}_t is determined given any history up to (not including) the player's decision at time $s \geq t$. Using total expectation we thus get that $\mathbf{E}[\nabla_i f_t(\bar{x}_t)^\top x_s] = \mathbf{E}[\nabla_i f_t(\bar{x}_t)^\top \bar{x}_s]$, and using this equality we get that for all $i \geq 1$,

$$\begin{aligned} \mathbf{E}[\nabla_i f_t(\bar{x}_{t+1-H})^\top (x_{t+i-H} - \bar{x}_{t+1-H})] &= \mathbf{E}[\nabla_i f_t(\bar{x}_{t+1-H})^\top (\bar{x}_{t+i-H} - \bar{x}_{t+1-H})] \\ &\leq \mathbf{E}[\|\nabla_i f_t(\bar{x}_{t+1-H})\| \|\bar{x}_{t+i-H} - \bar{x}_{t+1-H}\|] \quad (\text{Cauchy-Schwarz}) \\ &\leq L \mathbf{E}[\|\bar{x}_{t+i-H} - \bar{x}_{t+1-H}\|], \quad (f_t \text{ Lipschitz}) \end{aligned}$$

where the last transition used the Lipschitz assumption to bound the gradient. Finally, we get that

$$\begin{aligned} &\mathbf{E}\left[\sum_{t=H}^T f_t(x_{t+1-H}, \dots, x_t) - \tilde{f}_t(x_{t+1-H})\right] \\ &\leq \mathbf{E}\left[\sum_{t=H}^T f_t(x_{t+1-H}, \dots, x_t) - \tilde{f}_t(\bar{x}_{t+1-H})\right] \quad (\tilde{f}_t \text{ convex}) \\ &\leq \mathbf{E}\left[\sum_{t=H}^T \sum_{i=1}^H \nabla_i f_t(\bar{x}_{t+1-H})^\top (x_{t+i-H} - \bar{x}_{t+1-H}) + \frac{\beta}{2} \|x_{t+i-H} - \bar{x}_{t+1-H}\|^2\right] \quad (f_t \text{ smooth}) \\ &\leq \mathbf{E}\left[\sum_{t=H}^T \sum_{i=1}^H L \|\bar{x}_{t+i-H} - \bar{x}_{t+1-H}\| + \beta \|\bar{x}_{t+i-H} - \bar{x}_{t+1-H}\|^2 + \beta \|x_{t+i-H} - \bar{x}_{t+i-H}\|^2\right], \end{aligned}$$

where the last transition used the previous equation and the triangle inequality. Plugging in the expressions provided in Lemma 14 concludes the proof. \blacksquare

A.2 Proofs of Lemmas 10 and 14

Proof of Lemma 10. First, notice that by definition $t_i - t_{i-1} \geq H$. Summing over i and recalling $t_0 = 0$ we get that $t_i \geq iH$. By definition of S we then get that $|S|H \leq t_{|S|} < T$, and changing sides concludes the first part of the lemma.

To see the second part of the lemma, consider a Markov chain with states corresponding to H -tuples of bits that captures the evolution of the sequence (b_{t-H+1}, \dots, b_t) as t increases. Notice that our quantity of interest

is the expected return time of the state $s = (0, 0, \dots, 1)$. Since the chain is irreducible it admits a stationary distribution π^* , and by a standard fact about Markov chains (e.g., Proposition 1.14 in [20]), the desired expected return time equals $1/\pi^*(s)$. The latter probability equals $(1/H)(1-1/H)^{H-1} \geq 1/(eH) \geq 1/(3H)$, which gives the claim. \blacksquare

Proof of Lemma 14. For the first claim, noticing that the algorithm only changes predictions at times $t \in S$, we have that

$$\begin{aligned}
\sum_{t=H}^T \sum_{i=2}^H \|x_{t+i-H} - x_{t+1-H}\| &\leq \sum_{i=2}^H \sum_{j=1}^{i-1} \sum_{t=H}^T \|x_{t+j+1-H} - x_{t+j-H}\| && \text{(triangle in Eq)} \\
&\leq \frac{1}{2} H^2 \sum_{t=1}^{T-1} \|x_{t+1} - x_t\| \\
&= \frac{1}{2} H^2 \sum_{t \in S} \|x_{t+1} - x_t\| \\
&\leq \frac{1}{2} H^2 \sum_{t \in S} \|x_{t+1} - \bar{x}_{t+1}\| + \|\bar{x}_{t+1} - \bar{x}_t\| + \|\bar{x}_t - x_t\| && \text{(triangle in Eq)} \\
&\leq \frac{1}{2} H^2 \sum_{t=1}^{|S|} \vartheta_{t+1} + \delta_t + \vartheta_t \\
&\leq \frac{1}{2} H^2 \sum_{t=1}^{\lfloor T/H \rfloor} \delta_t + 2\vartheta_t,
\end{aligned}$$

where the last transition also used the decreasing property of ϑ_t . Next, we have that for any $q > 0$

$$\begin{aligned}
\sum_{t=H}^T \sum_{i=1}^H \|\bar{x}_{t+i-H} - \bar{x}_{t+1-H}\|^q &= \sum_{t=H}^T \sum_{i=2}^H \left\| \sum_{j=1}^{i-1} \bar{x}_{t+j+1-H} - \bar{x}_{t+j-H} \right\|^q \\
&= \sum_{i=2}^H \sum_{j=1}^{i-1} \sum_{t=H}^T \|\bar{x}_{t+j+1-H} - \bar{x}_{t+j-H}\|^q \\
&\leq \frac{1}{2} H^2 \sum_{t=1}^{T-1} \|\bar{x}_{t+1} - \bar{x}_t\|^q \\
&\leq \frac{1}{2} H^2 \sum_{t=1}^{|S|} \delta_t^q \\
&\leq \frac{1}{2} H^2 \sum_{t=1}^{\lfloor T/H \rfloor} \delta_t^q,
\end{aligned}$$

where the second transition follows since predictions change at most once every H rounds and thus there is at most one summand that is non-zero. This concludes the second part of the lemma. Next, recall that t_i from Lemma 10 are the times Algorithm 2 updates the base BCO \mathcal{A} , and subsequently its prediction. Then we get that

$$\begin{aligned}
\mathbf{E} \left[\sum_{t=H}^T \sum_{i=1}^H \|x_{t+i-H} - \bar{x}_{t+i-H}\|^2 \right] &\leq H \mathbf{E} \left[\sum_{t=1}^T \|x_t - \bar{x}_t\|^2 \right] \\
&\leq H \mathbf{E} \left[\sum_{s=1}^{\lfloor |S| \rfloor + 1} \vartheta_s^2 (t_s - t_{s-1}) \right] \\
&\leq H \sum_{s=1}^{\lfloor T/H \rfloor + 1} \vartheta_s^2 \mathbf{E}[t_s - t_{s-1}]
\end{aligned}$$

$$\leq 3H^2 \sum_{t=1}^{\lfloor T/H \rfloor + 1} \vartheta_t^2.$$

where the last two transitions used Lemma 10. ■

B Base BCO Algorithm

We give a general example of a BCO algorithm that may be employed in conjunction with our reduction procedure given in Algorithm 2. For a positive semi-definite matrix $P \in \mathbb{R}^{d \times d}$ define the projection in $\|\cdot\|_P$ distance $\Pi_{\mathcal{K}}^P(x) = \arg \min_{y \in \mathcal{K}} \|x - y\|_P$, where $\|x\|_P^2 = x^\top P x$. We analyze Algorithm 3, a standard BCO procedure that uses a preconditioned gradient update, and a one-point gradient estimate.

Algorithm 3 Base BCO

- 1: **input:** regularization matrices $P_t \succeq 0$, step size η
 - 2: **set:** $\bar{x}_1 \in \mathcal{K}$
 - 3: **for** $t = 1, \dots, T$ **do**
 - 4: Draw $u_t \sim \mathcal{S}^d$
 - 5: Play $x_t = \bar{x}_t + P_t^{-1/2} u_t$
 - 6: Observe \hat{f}_t and set $\hat{g}_t = d\hat{f}_t P_t^{1/2} u_t$
 - 7: Update $\bar{x}_{t+1} = \Pi_{\mathcal{K}}^{P_t}(\bar{x}_t - \eta P_t^{-1} \hat{g}_t)$
-

Since our setting of BCO with (no) memory $H = 1$ uses a non-standard feedback model, we provide a full analysis of the bounds on the regret, and the prediction shifts and magnitudes. To that end, denote

$$D = \max_{x, y \in \mathcal{K}} \|x - y\|, \quad D_P = \max_{x, y \in \mathcal{K}} \|x - y\|_P, \quad \hat{C} = \max_{t \in [T]} |\hat{f}_t|.$$

Lemma 15. *Consider the BCO with no memory ($H = 1$) setting described in Section 4.2 against an adversary that chooses $f_t : \mathcal{K}_+ \rightarrow \mathbb{R}$ that are α -strongly convex over \mathcal{K} ($\alpha = 0$ in the weakly convex case). If Algorithm 3 is run with regularization matrices $P_t = P_0 + \frac{1}{2} \alpha \eta t I$ where $P_0 \succeq 0$, then*

$$\delta_t = d\eta \hat{C} \|P_t^{-1/2}\| \quad \vartheta_t^2 = \|P_t^{-1}\|$$

satisfy the assumptions of $\mathcal{A}(T)$ in Theorem 9. Moreover, for all $t \leq T$ we have that

1. if f_s are L -Lipschitz then $\mathcal{R}_1(t) \leq \frac{D_{P_1}^2}{\eta} + \frac{\eta d^2 \hat{C}^2}{2} t + d\epsilon t D_{P_t} + 2L \sum_{s=1}^t \|P_s^{-1/2}\|$;
2. if f_s are β -smooth then $\mathcal{R}_1(t) \leq \frac{D_{P_1}^2}{\eta} + \frac{\eta d^2 \hat{C}^2}{2} t + d\epsilon t D_{P_t} + \beta \sum_{s=1}^t \|P_s^{-1}\|$.

The proof of Lemma 15 relies on a few standard results. First, we require a standard regret bound for the time-varying preconditioned update rule. This is stated in the next lemma, which is a specialization of bounds found in, e.g., [13], to the case of strongly convex quadratic regularizers.

Lemma 16. *Let $\hat{g}_1, \dots, \hat{g}_t \in \mathbb{R}^d$, and $P_t \succeq \dots \succeq P_1 \succ 0$ be arbitrary. For step size $\eta > 0$ define the update rule: $\bar{x}_{t+1} = \Pi_{\mathcal{K}}^{P_t}(\bar{x}_t - \eta P_t^{-1} \hat{g}_t)$. Then we have that*

$$\sum_{s=1}^t \hat{g}_s^\top (\bar{x}_s - x^*) \leq \frac{1}{\eta} \|\bar{x}_1 - x^*\|_{P_1}^2 + \frac{1}{\eta} \sum_{s=2}^t \|\bar{x}_s - x^*\|_{P_s - P_{s-1}}^2 + \frac{\eta}{2} \sum_{s=1}^t \|\hat{g}_s\|_{P_s^{-1}}^2, \quad \forall x^* \in \mathcal{K}.$$

Next, we need the notion of smoothing and the one point-gradient estimate, which were initially proposed by [14] and later refined in [24, 16]. The following lemma due to [16] encapsulates the relevant results.

Lemma 17 (Lemmas 6 and 7 in [16]). *Let $P \in \mathbb{R}^{d \times d}$ be symmetric and non-singular, $b \sim \mathcal{B}^d$, and $u \sim \mathcal{S}^d$. Define the smoothed version of $f : \mathcal{K}_+ \rightarrow \mathbb{R}$ with respect to P as*

$$\bar{f}(x) = \mathbf{E}[f(x + Pb)].$$

Then we have that:

- (i) $\nabla \bar{f}(x) = \mathbf{E}[df(x + Pu)P^{-1}u]$;
- (ii) if f is α -strongly convex then so is \bar{f} ;
- (iii) if f is convex and β -smooth then $0 \leq \bar{f}(x) - f(x) \leq \frac{\beta}{2}\|P\|^2$, $\forall x \in \mathcal{K}_+$;
- (iv) if f is convex and L -Lipschitz then $0 \leq \bar{f}(x) - f(x) \leq L\|P\|$, $\forall x \in \mathcal{K}_+$.

Among other things, this lemma implies that a regret bound for a sequence \bar{f}_t yields one for f_t . We are now ready to prove Lemma 15.

Proof of Lemma 15. First notice that \bar{x}_t in Algorithm 3 is indeed the expectation of x_t conditioned on all past history up to (not including) the decision at time t (since u_t is a zero mean independent random variable). Using the projection's shrinking property we get that

$$\|\bar{x}_{t+1} - \bar{x}_t\| \leq \|P_t^{-1/2}\| \|\bar{x}_{t+1} - \bar{x}_t\|_{P_t} \leq \|P_t^{-1/2}\| \|\eta d \hat{f}_t P_t^{-1/2} u_t\|_{P_t} = \|P_t^{-1/2}\| \|\eta d\| \|\hat{f}_t\| \leq d\eta \hat{C} \|P_t^{-1/2}\| = \delta_t.$$

Next, we have that $\|x_t - \bar{x}_t\|^2 = \|P_t^{-1/2} u_t\|^2 \leq \|P_t^{-1}\| = \vartheta_t^2$, thus concluding first part of the proof. Moving on to the regret bound, let $x \in \mathcal{K}$ be fixed, and denote $g_s = df_s(\bar{x}_s) P_s^{1/2} u_s$, the desired gradient estimate at time s . Recalling that \bar{x}_s is independent of the adversary's random variable ξ_s , we use total expectation to get that

$$\begin{aligned} \mathbf{E} \left[\sum_{s=1}^t (g_s - \hat{g}_s)^\top (\bar{x}_s - x) \right] &= d \mathbf{E} \left[\sum_{s=1}^t (f_s(\bar{x}_s) - \hat{f}_s) u_s^\top P_s^{1/2} (\bar{x}_s - x) \right] \\ &= d \mathbf{E} \left[\sum_{s=1}^t (f_s(\bar{x}_s) - \mathbf{E}_{\xi_s}[\hat{f}_s]) u_s^\top P_s^{1/2} (\bar{x}_s - x) \right] \\ &\leq d \varepsilon \mathbf{E} \left[\sum_{s=1}^t \|\bar{x}_s - x\|_{P_s} \right] \leq d \varepsilon t D_{P_t}, \end{aligned}$$

where the second to last transition used the Cauchy-Schwarz inequality, and the last transition used the assumption that P_s is increasing. Next, notice that $\bar{x}_s, P_s, \hat{g}_s$ satisfy the conditions of Lemma 16, and since $\|\hat{g}_s\|_{P_s^{-1}}^2 \leq d^2 \hat{C}^2$, we get that

$$\sum_{s=1}^t \hat{g}_s^\top (\bar{x}_s - x) \leq \frac{D_{P_1}^2}{\eta} + \frac{\alpha}{2} \sum_{s=1}^t \|\bar{x}_s - x\|^2 + \frac{\eta d^2 \hat{C}^2}{2} t,$$

and taking expectation, summing the last two equations, and changing sides, we get that

$$\mathbf{E} \left[\sum_{s=1}^t \bar{f}_s(\bar{x}_s) - \sum_{s=1}^t \bar{f}_s(x) \right] \leq \mathbf{E} \left[\sum_{s=1}^t g_s^\top (\bar{x}_s - x) - \frac{\alpha}{2} \sum_{s=1}^t \|\bar{x}_s - x\|^2 \right] \leq \frac{D_{P_1}^2}{\eta} + \frac{\eta d^2 \hat{C}^2}{2} t + d \varepsilon t D_{P_t}, \quad (5)$$

where the first transition also used Lemma 17 to show that g_s is an unbiased estimate of $\nabla \bar{f}_s(\bar{x}_s)$ given \bar{x}_s , and that \bar{f}_s are α strongly convex (with $\alpha = 0$ in the weakly convex case). Now, let \bar{f}_s be smoothed with respect to $P_s^{-1/2}$ as defined in Lemma 17. If f_s are β smooth, we get that

$$\mathbf{E}[f_s(x_s)] \leq \mathbf{E} \left[f_s(\bar{x}_s) + \nabla f_s(\bar{x}_s)^\top P_s^{-1/2} u_s + \frac{\beta}{2} \|P_s^{-1}\| \right] = \mathbf{E}[f_s(\bar{x}_s)] + \frac{\beta}{2} \|P_s^{-1}\| \leq \mathbf{E}[\bar{f}_s(\bar{x}_s)] + \frac{\beta}{2} \|P_s^{-1}\|,$$

where the last transition used Lemma 17, which also gives us that $-f_s(x) \leq -\bar{f}_s(x) + \frac{\beta}{2} \|P_s^{-1}\|$. We thus conclude that

$$\mathcal{R}_1(t) = \max_{x \in \mathcal{K}} \left\{ \mathbf{E} \left[\sum_{s=1}^t f_s(x_s) - \sum_{s=1}^t f_s(x) \right] \right\} \leq \max_{x \in \mathcal{K}} \left\{ \mathbf{E} \left[\sum_{s=1}^t \bar{f}_s(\bar{x}_s) - \sum_{s=1}^t \bar{f}_s(x) \right] \right\} + \beta \sum_{s=1}^t \|P_s^{-1}\|,$$

and plugging in Eq. (5) concludes the smooth case. Finally, if f_s are L Lipschitz then using Lemma 17 we get that

$$\mathbf{E}[f_s(x_s) - f_s(x)] \leq \mathbf{E}[f_s(\bar{x}_s) - f_s(x)] + L \|P_s^{-1/2}\| \leq \mathbf{E}[\bar{f}_s(\bar{x}_s) - \bar{f}_s(x)] + 2L \|P_s^{-1/2}\|,$$

and summing over s and plugging Eq. (5) concludes the non-smooth case. \blacksquare

C Main Result Proofs

C.1 Proof of Lemma 12

This lemma is a direct specification of Lemma 15 with the appropriate choice of parameters. For $M \in \mathcal{M}_+$, denote $[M]_{\text{vec}} \in \mathbb{R}^{dkH}$ the column stacking of M . Next, denote $I \in \mathbb{R}^{dk \times dk}$, the identity matrix, and $\text{diag}(r_t^{[1]}, \dots, r_t^{[H]}) \in \mathbb{R}^{H \times H}$, the diagonal matrix with $r_t \in \mathbb{R}^H$ on its diagonal. Consider Algorithm 3 with $\mathcal{K} = \mathcal{M}$ (column stacked), dimension $d_{\mathcal{M}} = dkH$, and

$$P_t = [\text{diag}(r_t^{[1]}, \dots, r_t^{[H]}) \otimes I]^{-2},$$

where \otimes is the Kronecker product. Then, first, for $M \in \mathcal{M}_+$ we can write the projection as

$$\Pi_{\mathcal{M}}^{P_t}([M]_{\text{vec}}) = \arg \min_{M' \in \mathcal{M}} \|[M]_{\text{vec}} - [M']_{\text{vec}}\|_{P_t}^2 = \arg \min_{M' \in \mathcal{M}} \sum_{i=1}^H (r_t^{[i]})^{-2} \|M^{[i]} - M'^{[i]}\|_F^2,$$

and since $\mathcal{M} = \mathcal{M}^{[1]} \times \dots \times \mathcal{M}^{[H]}$, each term in the sum may be minimized separately, and so we get that

$$\Pi_{\mathcal{M}}^{P_t}([M]_{\text{vec}}) = [\Pi_{\mathcal{M}^{[1]}}(M^{[1]}), \dots, \Pi_{\mathcal{M}^{[H]}}(M^{[H]})]_{\text{vec}},$$

where $\Pi_{\mathcal{M}^{[i]}}(M) = \arg \min_{M' \in \mathcal{M}^{[i]}} \|M - M'\|$. Second, we have that $\hat{g}_t = [\hat{g}_t^{[1]}, \dots, \hat{g}_t^{[H]}]_{\text{vec}}$ and thus the update rule may be rewritten as

$$[\bar{M}_{t+1}]_{\text{vec}} = [\bar{M}_t]_{\text{vec}} - \eta P_t^{-1} \hat{g}_t = [\bar{M}_t^{[1]} - \eta (r_t^{[1]})^2 \hat{g}_t^{[1]}, \dots, \bar{M}_t^{[H]} - \eta (r_t^{[H]})^2 \hat{g}_t^{[H]}]_{\text{vec}}.$$

We conclude that the procedure in Lemma 12 is indeed described by Algorithm 3. We can now conclude the lemma using Lemma 15. A simple calculation shows that

$$D^2 = \max_{M_1, M_2 \in \mathcal{M}} \|M_1 - M_2\|_F^2 \leq 4n^2 \kappa_B^2 \kappa^6 / \gamma;$$

$$D_{P_0}^2 = \max_{M_1, M_2 \in \mathcal{M}} \|M_1 - M_2\|_{P_0}^2 \leq Hn^2.$$

Moreover, $D_{P_t}^2 = D_{P_0}^2 + \frac{1}{2} \alpha \eta t D^2$, and $\|P_t^{-1}\| \leq \frac{2}{\alpha \eta t}$. Plugging this into Lemma 15 we get that for all $t \leq T$

$$\mathcal{R}_1(t) \leq \frac{1}{\eta} \left(Hn^2 + \frac{2\beta_f}{\alpha_f} (1 + \log T) \right) + \frac{d_{\mathcal{M}}^2 \hat{C}^2}{2} \eta T$$

$$+ \underbrace{\frac{2n^2 \kappa_B^2 \kappa^6 \alpha_f}{\gamma} + d_{\mathcal{M}} \varepsilon \left(\sqrt{HnT} + \sqrt{\frac{4\alpha_f \eta n^2 \kappa_B^2 \kappa^6 T^3}{\gamma}} \right)}_{R_{\text{low}}},$$

and for $\varepsilon \in \tilde{O}(T^{-1})$, and $\eta \in \tilde{O}(T^{-1/2})$, we indeed have that $R_{\text{low}} \in \tilde{O}(T^{-1/4})$. Finally, δ_t, ϑ_t translate directly between lemmas, thus concluding the proof.

C.2 Low Order Terms in Theorem 8

We summarize the low order terms that were omitted in the last three equations of the proof of Theorem 8 given in Section 5. The first of the three explicitly states the lower order term

$$R_{\text{low}}^{(1)} = 2D_{x,u}^2 (G + HC),$$

which is later omitted in the last step. The second equation results from invoking Lemma 12 with $\hat{C} = CD_{x,u}^2$ and horizon $T/2(H+1)$, to bound the second term of Theorem 9. Here the terms related to δ_t, δ_t^2 were omitted, and satisfy

$$\sum_{t=1}^{\lceil T/2(H+1) \rceil + 1} (L_f \delta_t + \beta_f \delta_t^2) \leq 2L_f dk CD_{x,u}^2 \sqrt{\frac{\eta HT}{\alpha_f}} + \frac{2\beta_f d^2 k^2 H^2 C^2 D_{x,u}^4 \eta \log T}{\alpha_f} = R_{\text{low}}^{(2)}.$$

The third equation results from plugging in the previous result as well as that of Lemma 12 with horizon $T/(2(H+1))$, and $\varepsilon = GD_{x,u}^2/T$ into Theorem 9. Lemma 12 yields a low order term, which is given at the end of the proof in Appendix C.1. Plugging in the horizon, ε , and \hat{C} this term is given by

$$R_{\text{low}}^{(3)} = \frac{2n^2\kappa_B^2\kappa^6\alpha_f}{\gamma} + d^2k^2H^2GD_{x,u}^2 \left(\sqrt{H}\eta + \sqrt{\frac{2\alpha_f\eta n^2\kappa_B^2\kappa^6T}{\gamma(H+1)}} \right),$$

and thus the final low order term is given by

$$R_{\text{low}} = R_{\text{low}}^{(1)} + 2(H+1)^2R_{\text{low}}^{(2)} + 6(H+1)R_{\text{low}}^{(3)}.$$

Since H is logarithmic in T , and $\eta \in \tilde{O}(T^{-1/2})$, we get that $R_{\text{low}} \in \tilde{O}(T^{1/4})$, as desired.

C.3 Proof of (ii) in Lemma 7

Proof. Recall from Definition 5 that $f_t(M_{0:H}) = c_t(y_t(M_{0:H}), v_t(M_{0:H}))$, and denote

$$z_t(M_{0:H}) = [y_t(M_{0:H})^\top v_t(M_{0:H})^\top]^\top.$$

Since $z_t(\cdot)$ is a linear mapping, its Jacobian is constant, and we denote it as J_{z_t} . Applying the chain rule, we get that for all $M_0, \dots, M_H \in \mathcal{M}_+$

$$\|\nabla^2 f_t(M_{0:H})\| = \|J_{z_t}^\top \nabla^2 c_t(y_t(M_{0:H}), v_t(M_{0:H})) J_{z_t}\| \leq \beta \|J_{z_t}\|^2,$$

and thus bounding $\|J_{z_t}\|$ will show that f_t is smooth. To that end, notice that an intermediate step of Lemma 5.6 of [1] shows that for any $M_0, \dots, M_H, M'_0, \dots, M'_H \in \mathcal{M}_+$, we have that

$$\|z_t(M_{0:H}) - z_t(M_0, \dots, M'_{H-k}, \dots, M_H)\| \leq 5\kappa_B\kappa^3W(1-\gamma)^k \sum_{i=0}^H \|M_{H-k}^{[i]} - M'_{H-k}{}^{[i]}\|. \quad (6)$$

Recalling that $\|\cdot\| \leq \|\cdot\|_F$, and using the triangle and Cauchy-Schwarz inequalities we get that

$$\begin{aligned} \|z_t(M_{0:H}) - z_t(M'_{0:H})\| &\leq 5\kappa_B\kappa^3W \sum_{k=0}^H (1-\gamma)^k \sum_{i=1}^H \|M_{H-k}^{[i]} - M'_{H-k}{}^{[i]}\|_F \\ &\leq 5\kappa_B\kappa^3W\sqrt{H} \sum_{k=0}^H (1-\gamma)^k \|M_{H-k} - M'_{H-k}\|_F \\ &\leq 5\kappa_B\kappa^3W\sqrt{H} \|M_{0:H} - M'_{0:H}\|_F \sqrt{\sum_{k=0}^H (1-\gamma)^{2k}} \\ &\leq 5\kappa_B\kappa^3W \sqrt{\frac{H}{\gamma}} \|M_{0:H} - M'_{0:H}\|_F. \end{aligned}$$

Since \mathcal{M}_+ contains an open set of $\mathbb{R}^{(k \times d) \times (H+1)}$, this Lipschitz property implies that $\|J_{z_t}\| \leq 5\kappa_B\kappa^3W\sqrt{\frac{H}{\gamma}} \leq \sqrt{\beta_f/\beta}$, thus showing that f_t is β_f smooth. Since F_t results from taking expectation of f_t with respect to the random system noise, it is also β_f smooth.

Next, recall that $\tilde{f}_t(M) = f_t(M, \dots, M)$, and thus defining $\tilde{z}_t = z_t(M, \dots, M)$, and repeating the process above, it suffices to show that \tilde{z}_t is $\sqrt{\beta_f/\beta}$ Lipschitz to conclude that \tilde{f}_t, \tilde{F}_t are β_f smooth. Using Eq. (6) we get that for $M, M' \in \mathcal{M}_+$

$$\|\tilde{z}_t(M) - \tilde{z}_t(M')\| \leq 5\kappa_B\kappa^3W \sum_{k=0}^H (1-\gamma)^k \sum_{i=1}^H \|M^{[i]} - M'^{[i]}\|_F$$

$$\begin{aligned}
&\leq 5\kappa_B\kappa^3W\sqrt{H}\|M - M'\|_F \sum_{k=0}^H (1-\gamma)^k \\
&\leq \frac{5\kappa_B\kappa^3W}{\gamma}\sqrt{H}\|M - M'\|_F \\
&= \sqrt{\beta_f/\beta}\|M - M'\|_F,
\end{aligned}$$

thus establishing the Lipschitz property and concluding the proof. \blacksquare

D Extensions Proofs

We first need to extend the base BCO procedure to the weakly convex cases. Similarly to Lemma 12, this is an immediate corollary of Lemma 15 with appropriate choice of parameters.

Lemma 18. *Consider the setting of Section 4 with $H = 1$ and $\varepsilon \in \tilde{O}(1/T)$, against an adversary that chooses $f_t : \mathcal{M}_+ \rightarrow \mathbb{R}$ that are convex. Let $d_{\mathcal{M}}, D, r_0^{[i]}$ be as in Theorem 13, and $\mathcal{R}_1(t)$ be the regret of a procedure that at time t :*

- (i) *Draws $U_t \sim \mathcal{S}^{(k \times d) \times H}$; and plays M_t where $M_t^{[i]} = \bar{M}_t^{[i]} + r_t^{[i]}U_t^{[i]}$ ($\forall i \in [H]$)*
- (ii) *Observes \hat{f}_t ; and sets $\hat{g}_t^{[i]} = (d_{\mathcal{M}}/r_t^{[i]})\hat{f}_tU_t^{[i]}$ ($\forall i \in [H]$)* *(1-point gradient estimate)*
- (iii) *Updates $\bar{M}_{t+1}^{[i]} = \Pi_{\mathcal{M}^{[i]}}[\bar{M}_t^{[i]} - \eta(r_t^{[i]})^2\hat{g}_t^{[i]}]$ ($\forall i \in [H]$).* *(preconditioned update)*

Suppose that $|\hat{f}_t| \leq \hat{C}$ then for all $t \leq T$:

1. *if f_t are L -Lipschitz, $\eta = 2\left[\frac{L^2D^2}{d_{\mathcal{M}}^6D^6T}\right]^{1/4}$, and $r_t^{[i]} = \left[(r_0^{[i]})^{-2} + \frac{4L\sqrt{T}}{d_{\mathcal{M}}CD}\right]^{-1/2}$ then*

$$\mathcal{R}_1(t) \leq 4\sqrt{d_{\mathcal{M}}LD\hat{C}T^{3/4}} + \tilde{O}(T^{1/4}), \quad \delta_t = \frac{D}{\sqrt{T}}, \quad \vartheta_t^2 = \frac{d_{\mathcal{M}}D\hat{C}}{4L\sqrt{T}};$$

2. *if f_t are β_f smooth, $\eta = \left[\frac{2\beta_fD^2}{d_{\mathcal{M}}^4\hat{C}^4T}\right]^{1/3}$, and $r_t^{[i]} = \left[(r_0^{[i]})^{-2} + \left(\frac{4\beta_f^2T}{d_{\mathcal{M}}^2\hat{C}^2D^2}\right)^{1/3}\right]^{-1/2}$ then*

$$\mathcal{R}_1(t) \leq (4\sqrt{\beta_f}d_{\mathcal{M}}\hat{C}DT)^{2/3} + \tilde{O}(T^{1/3}), \quad \delta_t = \frac{D}{\sqrt{T}} \quad \vartheta_t^2 = \left(\frac{d_{\mathcal{M}}^2\hat{C}^2D^2}{4\beta_f^2T}\right)^{1/3}.$$

See proof in Appendix D.1.

Proof of Theorem 13. First, unlike the proof of Theorem 8, here we use f_t as given in Definition 5, without any modification. As before we view Algorithm 1 in the context of the BCO with memory setting presented in Section 4. The adversary's noise ξ_t is now degenerate (w_t are not stochastic), the costs are given by f_t and by Lemma 6, the feedback satisfies

$$|c_t(x_t, u_t) - f_t(M_{t-1-2H:t})| \leq \frac{GD_{x,u}^2}{T},$$

and thus $\varepsilon = GD_{x,u}^2/T$, and the feedback $c_t(x_t, u_t)$ is bounded by $CD_{x,u}^2$. Let $\mathcal{R}_{H+1}(T)$ be the regret of Algorithm 1 against an adversary with memory $H + 1$, and notice that our choice of $r_t^{[i]}$, and in particular $r_0^{[i]}$, ensures that $M_t \in \mathcal{M}_+$. Since the third part of Lemma 6 is, in fact, proven for f_t rather than F_t (the latter is an immediate corollary) and so we have that

$$\mathcal{R}_{\mathcal{A}}(T) \leq \mathcal{R}_{H+1}(T) + 2D_{x,u}^2(G + HC).$$

Since the second term is at most poly-log in T , it remains to bound $\mathcal{R}_{H+1}(T)$ for each set of assumptions and parameter choices. Recall that Algorithm 1 fits the mold of our reduction procedure given in Algorithm 2 with base procedure as in Lemma 18. Moving forward, our analysis is divided in two. Consider the first set of

parameter choices (with no smoothness assumptions). By Lemma 7, f_t are coordinate-wise L_f Lipschitz, and thus $\tilde{f}_t : M \mapsto f_t(M, \dots, M)$ are $(H+1)L_f$ Lipschitz. Invoking Lemma 18 with $\hat{C} = CD_{x,u}^2$, $L = (H+1)L_f$ and horizon $T/(H+1)$, the second term of Theorem 9 (with no smoothness assumption) satisfies that

$$\begin{aligned} \frac{1}{2}L_f(H+1)^2 \sum_{t=1}^{\lfloor T/(H+1) \rfloor} \delta_t + 2\vartheta_t &\leq \frac{1}{2}L_f(H+1)T(\delta_t + 2\vartheta_t) \\ &\leq \frac{1}{2}L_f(H+1)T \left(D\sqrt{\frac{H+1}{T}} + \sqrt{\frac{d_{\mathcal{M}}\hat{C}D}{L_f}} \left(\frac{H+1}{T} \right)^{1/4} \right) \\ &\leq \frac{1}{2}\sqrt{d_{\mathcal{M}}\hat{C}DL_f(H+1)^{5/2}T^{3/4}} + \tilde{O}(T^{1/2}), \end{aligned}$$

and further using Lemma 18 to bound the first term of Theorem 9, and simplifying, we get that

$$\begin{aligned} \mathcal{R}_{H+1}(T) &\leq 13\sqrt{d_{\mathcal{M}}\hat{C}DL_f(H+1)^{5/2}T^{3/4}} + \tilde{O}(T^{1/2}) \\ &\leq 13\sqrt{2dknCD_{x,u}^2\kappa_B\kappa^3\gamma^{-1/2}L_f(H+1)^{7/2}T^{3/4}} + \tilde{O}(T^{1/2}), \end{aligned}$$

where the last step only plugs in the values of $d_{\mathcal{M}}, \hat{C}, D$. This concludes the proof of the non-smooth case. Now suppose that c_t are β smooth and Algorithm 1 is run with our second choice of parameters. Notice that the proof of the smoothness in Lemma 7 (see Appendix C.3) actually shows that both f_t, \tilde{f}_t are β_f smooth, and as before, we invoke Lemma 18 with our parameter choices to bound the second term of Theorem 9 (with the smoothness assumption) by

$$\begin{aligned} \frac{1}{2}(H+1)^2 \sum_{t=1}^{\lfloor T/2(H+1) \rfloor + 1} ((H+1)L_f\delta_t + \beta_f\delta_t^2 + 6\beta_f\vartheta_t^2) &\leq (H+1)T((H+1)L_f\delta_t + \beta_f\delta_t^2 + 6\beta_f\vartheta_t^2) \\ &\leq (H+1)T \left(L_fD\sqrt{\frac{(H+1)^3}{T}} + \beta_fD^2\frac{H+1}{T} + 6\beta_f \left(\frac{d_{\mathcal{M}}^2\hat{C}^2D^2(H+1)}{4\beta_f^2T} \right)^{1/3} \right) \\ &\leq 4 \left(\sqrt{\beta_f}d_{\mathcal{M}}\hat{C}D(H+1)^2T \right)^{2/3} + \tilde{O}(T^{1/2}), \end{aligned}$$

and further using Lemma 18 to bound the first term of Theorem 9, and simplifying, we get that

$$\begin{aligned} \mathcal{R}_{H+1}(T) &\leq 12 \left(\sqrt{\beta_f}d_{\mathcal{M}}\hat{C}D(H+1)^2T \right)^{2/3} + \tilde{O}(T^{1/2}) \\ &\leq 12 \left(2dknCD_{x,u}^2\kappa_B\kappa^3\sqrt{\beta_f/\gamma}(H+1)^3T \right)^{2/3} + \tilde{O}(T^{1/2}), \end{aligned}$$

where the last step only plugs in the values of $d_{\mathcal{M}}, \hat{C}, D$. ■

D.1 Proof of Lemma 18

Recall Appendix C.1, where we show that Lemma 12 is a direct corollary of Lemma 15. As the procedure itself does not change here, the proof is concluded by plugging-in our assumptions and parameter choices into Lemma 15. For the first case, f_t are L Lipschitz, and our choice of parameters gives that

$$\begin{aligned} D_{P_t}^2 = D_{P_1}^2 = D_{P_0}^2 + \frac{4LD\sqrt{T}}{d_{\mathcal{M}}\hat{C}} &= Hn^2 + \frac{4LD\sqrt{T}}{d_{\mathcal{M}}\hat{C}}, \\ \|P_s^{-1/2}\| \leq r_1^{[1]} &\leq \frac{1}{2}\sqrt{\frac{Dd_{\mathcal{M}}\hat{C}}{L\sqrt{T}}}, \end{aligned}$$

and plugging into Lemma 15 we get that

$$\mathcal{R}_1(t) \leq 4\sqrt{d_{\mathcal{M}}LD\hat{C}T^{3/4}} + \underbrace{\frac{Hn^2}{\eta} + d_{\mathcal{M}}\varepsilon TD_{P_1}}_{R_{\text{low}}},$$

and by our assumptions we indeed get that $R_{\text{low}} \in \tilde{O}(T^{1/4})$ as desired. To conclude the non-smooth case, we further apply Lemma 15 to get that

$$\delta_t = \frac{D}{\sqrt{T}} \quad \vartheta_t^2 = \frac{d_{\mathcal{M}}D\hat{C}}{4L\sqrt{T}}.$$

Next, for the second case, f_t are β_f smooth and our choice of parameters gives that

$$\begin{aligned} D_{P_t}^2 = D_{P_1}^2 = D_{P_0}^2 + D^2 \left(\frac{4\beta_f^2 T}{d_{\mathcal{M}}^2 \hat{C}^2 D^2} \right)^{1/3} &\leq Hn^2 + \left(\frac{4\beta_f^2 D^4 T}{d_{\mathcal{M}}^2 \hat{C}^2} \right)^{1/3}, \\ \|P_s^{-1}\| \leq (r_1^{[1]})^2 \leq \left(\frac{d_{\mathcal{M}}^2 \hat{C}^2 D^2}{4\beta_f^2 T} \right)^{1/3}, \end{aligned}$$

and plugging into Lemma 15 we get that

$$\mathcal{R}_1(t) \leq (4\sqrt{\beta_f}d_{\mathcal{M}}\hat{C}DT)^{2/3} + \underbrace{\frac{Hn^2}{\eta} + d_{\mathcal{M}}\varepsilon TD_{P_1}}_{R_{\text{low}}},$$

and by our assumptions we indeed get that $R_{\text{low}} \in \tilde{O}(T^{1/3})$ as desired. To conclude the smooth case, and thus the proof, we further apply Lemma 15 to get that

$$\delta_t = \frac{D}{\sqrt{T}} \quad \vartheta_t^2 = \left(\frac{d_{\mathcal{M}}^2 \hat{C}^2 D^2}{4\beta_f^2 T} \right)^{1/3},$$

as desired.