

Sampling trajectories for the short-time Fourier transform

Michael Speckbacher *

Abstract

We study the problem of stable reconstruction of the short-time Fourier transform from samples taken from trajectories in \mathbb{R}^2 . We first consider the interplay between relative density of the trajectory and the reconstruction property. Later, we consider spiraling curves, a special class of trajectories, and connect sampling and uniqueness properties of these sets. Moreover, we show that for window functions given by a linear combination of Hermite functions, it is indeed possible to stably reconstruct from samples on some particular natural choices of spiraling curves.

MSC2010: 42C15, 42C30, 42C40, 65T60, 94A20

Keywords: Gabor analysis, sampling theory, mobile sampling, polyanalytic functions

1 Introduction

Reconstructing a function from incomplete data is an omnipresent task in fields like signal processing or harmonic analysis. Classically, one aims to reconstruct a function from discrete samples (see e.g. [32, 36]) and the stable version of this problem leads to the notion of frames [11, 13]. For a variety of function spaces, the lower Beurling density [9] (the definition being adapted to the particular geometry of the function space in consideration) of the discrete sampling set needs to exceed a certain threshold in order for the sampling process to form a frame, see for example [1, 22, 29, 31]. This threshold is commonly known as the Nyquist rate.

*Acoustics Research Institute, Austrian Academy of Sciences, Wohllebengasse 12-14, 1040 Vienna, Austria, speckbacher@kfs.oeaw.ac.at

A more abstract form of the sampling problem is to characterize so called *sampling measures* [6, 25, 26], i.e. measures μ on X that satisfy

$$A\|F\|_{L^p(X)}^p \leq \int_X |F|^p d\mu \leq B\|F\|_{L^p(X)}^p,$$

for some $A, B > 0$ and every F in a given subspace of $L^p(X)$. A common situation is that $X = \mathbb{R}^d$ and the measure takes the form $\mu = \chi_\Gamma \mathcal{H}^k$, where $\Gamma \subset X$, and \mathcal{H}^k , $0 \leq k \leq d$, is the k -dimensional Hausdorff measure. The case $k = 0$ corresponds to the classical discrete sampling problem. For the second extreme case $k = d$, it turns out that a weaker notion of density is sufficient to stably reconstruct. For the Paley-Wiener space, this is known as the Logvinenko-Sereda theorem [21, 23] and multiple extensions to other spaces of analytic functions [16, 24, 26] and the range space of the short-time Fourier transform [19] have since been established.

Recently, the study of the intermediate cases $0 < k < d$ on the Paley-Wiener space $PW_2(\Omega)$ has drawn increased attention and became known in the literature as the mobile sampling problem [34, 35]. Mobile sampling has many applications whenever a signal is measured by a moving sensor like in an MRI scan [8, 34]. Adapting Beurling's lower density for $k = 1$, the *lower path density* of a set Γ (measuring the limit average length of the curve Γ in a balls of increasing radii) was studied in [14]. In [20], it is shown that a sufficiently large lower path density yields a stable sampling process. On the other hand, there is no Nyquist rate that the lower path density needs to exceed for stable sampling, see [14]. For particularly structured classes of trajectories Γ however, Nyquist rates were established in terms of certain parameters that characterize the 'separation' of Γ [18, 30].

In this paper, we study the equivalent of the mobile sampling problem for the *short-time Fourier transform*

$$V_g f(z) = \int_{\mathbb{R}} f(t) \overline{g(t-x)} e^{-2\pi i \xi t} dt, \quad z = (x, \xi) \in \mathbb{R}^2.$$

In particular, if $M^p(\mathbb{R})$ denotes the modulation space associated to $L^p(\mathbb{R}^2)$ (see e.g. [13]), we study *Gabor sampling trajectories* for $M^p(\mathbb{R})$, that is, trajectory sets $\Gamma \subset \mathbb{R}^2$ for which

$$A\|f\|_{M^p}^p \leq \int_{\Gamma} |V_g f(z)|^p d\mathcal{H}^1(z) \leq B\|f\|_{M^p}^p, \quad f \in M^p(\mathbb{R}), \quad (1)$$

holds. This is a particular instance of a sampling measure for the short-time Fourier

transform [6].

Just like in classical Gabor analysis, the stable sampling property relies heavily on both the window g and the trajectory set Γ . On the one hand, one can quickly show that for windows in $M^1(\mathbb{R})$, a necessary condition for Γ being a Gabor sampling trajectory is that it is relatively dense [6] (see Section 3.1 for the definition). On the other hand, applying a characterization of sampling measures on the Bargmann-Fock space [26] we show that relative density is also sufficient for Gabor sampling trajectories with Gaussian window (see Section 3.2). It is thus hopeless to search for a Nyquist rate both in terms of a path density as well as certain separation parameters that holds for general windows. However, in Proposition 10 we prove that for certain windows it is a sufficient for Γ being a Gabor sampling trajectory that, for R small enough, $\mathcal{H}^1(\Gamma \cap B_R(z))$ is bounded away from zero.

Later, we change perspective and study particular examples of trajectory sets. First, we characterize sampling and uniqueness properties if Γ is a collection of parallel lines. This will in turn be useful when studying the sampling property of a particular class of trajectories: spiraling curves. Spiraling curves were introduced in [18]. In this article, we work with a slightly more restrictive definition of spiraling curves that nevertheless includes all the examples given in [18]. Loosely speaking, a spiraling curve is a trajectory that (in the limit) in each direction approaches a collection of equispaced parallel lines or equispaced parallel edges. We spare the details for now and refer to Definition 3 and Theorem 17.




Figure 1: Two examples of spiraling curves. *Left:* The set of concentric circles O_η . *Right:* The path $\mathcal{S}_\eta(z_1, \dots, z_4)$ generated by the points $\{(-a, a), (a, a), (a, -a), (-a, -a)\}$.

Beurling's theory of weak limits [9, 10, 32] states an equivalence between sampling sets Γ for the Paley-Wiener space $PW_2(\Omega)$ and the uniqueness property for all weak limits of translates of Γ on the Bernstein space $PW_\infty(\Omega)$. This is a very powerful result as the

uniqueness property is often easier to verify. The price one has to pay is that uniqueness has to be shown on a larger space and for all weak limits of translates of the original set. A similar result for sampling measures for the modulation space $M^p(\mathbb{R})$ was shown by Ascensi [6]. In case of the measure $\chi_\Gamma d\mathcal{H}^1$, this result states that Γ is a Gabor sampling trajectory for $M^p(\mathbb{R})$ if and only if all weak limits of translates of Γ are uniqueness sets for the weighted modulation space $M_{1/\vartheta_s}^p(\mathbb{R})$, for some $s > 2$.

In most applications, Beurling's theory is used to derive necessary conditions on sampling sets. In [18] for example, the authors showed that certain weak limits of translates of spiraling curves cannot be uniqueness sets for $PW_\infty(\Omega)$ if the separation exceeds a certain threshold. Together with a result from [8], this yields a full characterization which sets of concentric circles and which Archimedes spirals are sampling trajectories in terms of their separation parameter [18, Theorem A].

We take a different approach in this paper in that we first characterize the set of weak limits of translates of spiraling curves and then show (Theorem 17) that, for windows taken from the linear span of the Hermite functions, the uniqueness property is automatically satisfied for all weak limits of Γ except for Γ itself (and its finite shifts). It then follows that Γ is a Gabor sampling trajectory for $M^p(\mathbb{R})$ if and only if Γ is a uniqueness set for $M_{1/\vartheta_s}^p(\mathbb{R})$ for some $s > 2$ (Theorem 18). Moreover, we prove that certain spiraling curves are indeed uniqueness sets. In particular, our main result is the following.

Theorem 1 *Let $g \in \text{span}\{h_n : n \in \mathbb{N}_0\}$, $1 \leq p < \infty$, and $\eta > 0$. Moreover, let*

- (a) *P be a star shaped polygon in \mathbb{R}^2 such that $0 \in \text{Ker}(P)$ and no line passing through an edge of the polygon meets the origin,*
- (b) *$z_1, \dots, z_n \in \mathbb{R}^2$, $n \geq 3$, be such that $\arg(z_1), \dots, \arg(z_n), \arg(z_1)$ is strictly increasing or strictly decreasing modulo 2π .*

The following sets are Gabor sampling trajectories for $M^p(\mathbb{R})$:

- (i) *the set of concentric circles $\mathcal{O}_\eta := \{(x, y) \in \mathbb{R}^2 : x^2 + y^2 = \eta^2 k^2, k \in \mathbb{N}\}$,*
- (ii) *the collection of star shaped polygons $\mathcal{P}_\eta := \{(x, y) \in \mathbb{R}^2 : (x, y) \in \eta k P, k \in \mathbb{N}\}$,*
- (iii) *$\mathcal{S}_\eta(z_1, \dots, z_n)$, the path generated by the sequence of vectors*

$$\{\eta z_1, \eta z_2, \dots, \eta z_n, 2\eta z_1, 2\eta z_2, \dots, 2\eta z_n, 3\eta z_1, 3\eta z_2, \dots\}.$$

This paper is organized as follows. After a section dedicated to preliminaries, we study some basic examples of windows and trajectory sets in Section 3 and give necessary and sufficient conditions for Gabor sampling trajectories in that setting. Then in Section 4 we introduce spiraling curves and study their weak limits of translates which then allows us to prove our main result.

2 Preliminaries

2.1 Notation

Throughout this paper we adopt the following conventions. We write \vec{d} for vectors in \mathbb{S}^1 and $\vec{\ell}(\theta) := (\cos(2\pi\theta), \sin(2\pi\theta))$, $\theta \in \mathbb{T} \cong [0, 1)$ as well as \vec{e}_i for the standard basis vectors in \mathbb{R}^2 . For $\vec{d} \in \mathbb{S}^1$ we write \vec{d}_\perp for the vector obtained by rotating \vec{d} by $\pi/2$. The space of continuous, compactly supported functions is denoted by $C_c(\mathbb{R}^d)$, and we write $A \lesssim B$ if there exist $C > 0$ such that $A \leq CB$.

2.2 Hausdorff measure and trajectory sets

Let $E \subset \mathbb{R}^2$. The 1-dimensional Hausdorff measure of E is given by

$$\mathcal{H}^1(E) = \liminf_{\delta \searrow 0} \left\{ 2 \sum_j r_j : E \subset \bigcup_j B(x_j, r_j) \text{ and } r_j \leq \delta \right\}.$$

When restricted to a line, \mathcal{H}^1 equals the 1-dimensional Lebesgue measure.

Let $\varphi : [0, 1) \rightarrow [0, \infty)$ be continuous in 0. A (locally finite Borel) measure μ is called φ -regular if for every $z \in \mathbb{R}^2$ and every $R \in (0, 1)$ one has

$$\mu(B_R(z)) \leq \pi\varphi(R)R.$$

A set $E \subset \mathbb{R}^2$ is called φ -regular if $\mathcal{H}^1|_E$ is φ -regular.

A *trajectory* $\Gamma \subset \mathbb{R}^d$ is the image of a curve $\gamma : \mathbb{R} \rightarrow \mathbb{R}^d$, i.e. $\Gamma = \gamma(\mathbb{R})$, such that each restriction of γ to a finite interval is rectifiable. A *trajectory set* Γ is a countable collection of trajectories.

2.3 The short-time Fourier transform and modulation spaces

Let $z = (x, \xi) \in \mathbb{R}^2$. A *time-frequency shift* of a function g is given by

$$\pi(z)g(t) = M_\xi T_x g(t) = e^{2\pi i \xi t} g(t - x).$$

Given a window $g \in L^2(\mathbb{R})$, the *short-time Fourier transform* of $f \in L^2(\mathbb{R})$ is defined as

$$V_g f(z) = \langle f, \pi(z)g \rangle = \int_{\mathbb{R}} f(t) \overline{g(t - x)} e^{-2\pi i \xi t} dt.$$

The short-time Fourier transform satisfies the following *orthogonality relation*

$$\int_{\mathbb{R}^2} V_{g_1} f_1(z) \overline{V_{g_2} f_2(z)} dz = \langle f_1, f_2 \rangle \langle g_1, g_2 \rangle,$$

which implies that, if $\|g\| = 1$, $V_g : L^2(\mathbb{R}) \rightarrow L^2(\mathbb{R}^2)$ is an isometry.

Let $\vartheta : \mathbb{R}^2 \rightarrow \mathbb{R}^+$ be a *submultiplicative weight function*, i.e. $\vartheta(z + w) \leq \vartheta(z)\vartheta(w)$. The *(weighted) modulation spaces* $M_\vartheta^p(\mathbb{R})$, $1 \leq p \leq \infty$, can be defined by

$$M_\vartheta^p(\mathbb{R}) := \{f \in \mathcal{S}'(\mathbb{R}) : V_{h_0} f \cdot \vartheta \in L^p(\mathbb{R})\},$$

where h_0 denotes the normalized Gaussian and $\mathcal{S}'(\mathbb{R})$ the space of tempered distributions. Modulation spaces are Banach spaces when equipped with the natural norm $\|f\|_{M_\vartheta} = \|V_{h_0} f \cdot \vartheta\|_{L^p}$. See for example [13] for a thorough introduction to modulation spaces. Throughout this paper we only consider *polynomial weight functions*, i.e.,

$$\vartheta_s(z) = (1 + |z|)^s, \quad z \in \mathbb{R}^2, \quad s \geq 0.$$

We note here that $M_{\vartheta_s}^1(\mathbb{R})$ is closed under pointwise multiplication with functions from the *weighted Fourier algebra* $A_{\vartheta_s}(\mathbb{R})$

$$A_{\vartheta_s}(\mathbb{R}) := \left\{ f \in C_0(\mathbb{R}) : \int_{\mathbb{R}} |\widehat{f}(\xi)| \vartheta_s(\xi) d\xi < \infty \right\}.$$

In particular, for $f \in A_{\vartheta_s}(\mathbb{R})$ and $g \in M_{\vartheta_s}^1(\mathbb{R})$ we have

$$\|fg\|_{M_{\vartheta_s}^1} \leq \|f\|_{A_{\vartheta_s}} \|g\|_{M_{\vartheta_s}^1}, \quad (2)$$

see for example the arguments in [17, Proposition 4.13] which can easily be adapted to the weighted case.

Let $g \in M^1(\mathbb{R})$. We call a trajectory set $\Gamma \subset \mathbb{R}^2$ a *Gabor sampling trajectory* for $M^p(\mathbb{R})$ if there exist constants $A, B > 0$ such that

$$A\|f\|_{M^p}^p \leq \int_{\Gamma} |V_g f(z)|^p d\mathcal{H}^1(z) \leq B\|f\|_{M^p}^p, \quad f \in M^p(\mathbb{R}). \quad (3)$$

If only the upper bound is satisfied, then we call Γ a *Gabor Bessel trajectory*. If $p = 2$, then $M^p(\mathbb{R}) = L^2(\mathbb{R})$, and (3) is equivalent to $\{\pi(z)g\}_{z \in \Gamma}$ forming a continuous frame, see [5, 28].

The trajectory set Γ is called a *uniqueness set* for $M^p(\mathbb{R})$, if $V_g f|_{\Gamma} = 0$, $f \in M^p(\mathbb{R})$, implies $f = 0$.

2.4 Hermite windows and polyanalytic functions

A function $F : \mathbb{C} \rightarrow \mathbb{C}$ is called *polyanalytic of order n* if it satisfies the higher order Cauchy-Riemann equation $(\bar{\partial})^{n+1}F = 0$. In that case, F can be written as

$$F(z) = F(z, \bar{z}) = \sum_{k=0}^n F_k(z) \bar{z}^k, \quad z \in \mathbb{C} \quad (4)$$

where $F_0, \dots, F_n : \mathbb{C} \rightarrow \mathbb{C}$ are holomorphic functions.

The *Hermite functions* are given by

$$h_n(t) = \frac{2^{1/4}}{\sqrt{n!}} \left(\frac{-1}{2\sqrt{\pi}} \right)^n e^{\pi t^2} \frac{d^n}{dt^n} \left(e^{-2\pi t^2} \right), \quad n \in \mathbb{N}_0. \quad (5)$$

For $f \in M_{\vartheta_s}^p(\mathbb{R})$, $1 \leq p < \infty$, the function F given by

$$F(z) = V_{h_n} f(\bar{z}) e^{\pi(z^2 - \bar{z}^2)/4} e^{\pi|z|^2/2}, \quad (6)$$

is polyanalytic of order n [2], where we identify $z = (x, \xi) \in \mathbb{R}^2$ with $z = x + i\xi \in \mathbb{C}$. In particular, if $g = \sum_{k=0}^n \alpha_k h_k$, then $V_g f(\bar{z}) e^{\pi(z^2 - \bar{z}^2)/4} e^{\pi|z|^2/2}$ is polyanalytic of order n .

A polyanalytic function F of order n is called *reduced* if it can be written as

$$F(z) = \sum_{k=0}^n F_k(z) |z|^{2k}, \quad F_k \text{ holomorphic.}$$

Reduced polyanalytic functions satisfy the following Cauchy-type formula [7, Section 1.3, (11)]. For a similar Cauchy-type formula for true polyanalytic functions, see [4].

Lemma 2 (Balk) *Let F be a reduced polyanalytic function of order n in $B_R(0)$, $0 < R_0 < R_1 < \dots < R_n < R$, and let $\Gamma_k := \{z : |z| = R_k\}$. For every $z \in B_{R_0}(0)$*

$$F(z) = \frac{1}{2\pi i} \sum_{k=0}^n P_k(|z|^2) \int_{\Gamma_k} \frac{F(t)}{t-z} dt, \quad (7)$$

where $P_k(t) := \prod_{j \neq k} \frac{R_j^2 - t}{R_j^2 - R_k^2}$.

2.5 The metaplectic rotation

Let us denote the rotation matrices in \mathbb{R}^2 by $R(\theta) = \begin{pmatrix} \cos(2\pi\theta) & -\sin(2\pi\theta) \\ \sin(2\pi\theta) & \cos(2\pi\theta) \end{pmatrix}$, $\theta \in \mathbb{T}$. The *metaplectic rotation* of $f \in L^2(\mathbb{R})$ is given in terms of the Hermite basis $\{h_n\}_{n \in \mathbb{N}_0}$

$$\mu(\theta)f := \sum_{n \geq 0} e^{-2\pi i n \theta} \langle f, h_n \rangle h_n.$$

Clearly, $\mu(\theta)$ is a unitary operator on $L^2(\mathbb{R})$ with $\mu(\theta)^* = \mu(-\theta)$, and $\mu(\theta)h_n = e^{-2\pi i n \theta} h_n$. For $f, g \in L^2(\mathbb{R})$, the standard rotation of the argument of the short-time Fourier transform and the metaplectic rotation are connected via the formula

$$V_g f(R(\theta)z) = e^{\pi i(x\omega - x'\omega')} V_{\mu(\theta)g} \mu(\theta)f(z), \quad z = (x, \omega), \text{ and } (x', \omega') = R(\theta)z, \quad (8)$$

or equivalently via $\pi(R(\theta)z) = e^{-\pi i(x\omega - x'\omega')} \mu(-\theta)\pi(z)\mu(\theta)$. This is a special case of the symplectic covariance of the Schrödinger representation, see [12, Chapters 1 & 2], and [13, Chapter 9].

As ϑ_s is radially symmetric, (8) implies that $\|f\|_{M_{\vartheta_s}^1} = \|\mu(\theta)f\|_{M_{\vartheta_s}^1}$, which allows to extend the operator $\mu(\theta)$ to $M_{1/\vartheta_s}^\infty(\mathbb{R}) = M_{\vartheta_s}^1(\mathbb{R})^*$ via

$$\langle \mu(\theta)f, g \rangle_{M_{1/\vartheta_s}^\infty \times M_{\vartheta_s}^1} = \langle f, \mu(-\theta)g \rangle_{M_{1/\vartheta_s}^\infty \times M_{\vartheta_s}^1}, \quad f \in M_{1/\vartheta_s}^\infty(\mathbb{R}), \quad g \in M_{\vartheta_s}^1(\mathbb{R}).$$

Consequently, (8) remains valid for $f \in M_{1/\vartheta_s}^\infty(\mathbb{R})$, and $g \in M_{\vartheta_s}^1(\mathbb{R})$.

3 General trajectory sets

In this section, we present some basic necessary and sufficient conditions for Gabor sampling trajectories. Moreover, we study the particular cases of (i) Gaussian window with general trajectory sets and (ii) sampling on parallel lines for general windows.

3.1 Relative density

We call a trajectory set $\Gamma \subset \mathbb{R}^2$ (m, R) -dense if

$$\inf_{z \in \mathbb{R}^2} \mathcal{H}^1(\Gamma \cap B_R(z)) \geq m > 0,$$

and *relatively dense* if there exist constants $m, R > 0$ such that Γ is (m, R) -dense. It turns out that relative density is a necessary condition for Γ being a Gabor sampling trajectory for M^p , see [6, Theorem 8 & 10]:

Proposition 3 (Ascensi) *Let $g \in M^1(\mathbb{R})$ and $1 \leq p < \infty$. If $\Gamma \subset \mathbb{R}^2$ is a Gabor Bessel trajectory for $M^p(\mathbb{R})$, then there exist $M, R > 0$ such that*

$$\sup_{z \in \mathbb{R}^2} \mathcal{H}^1(\Gamma \cap B_R(z)) \leq M. \tag{9}$$

If Γ is a Gabor sampling trajectory for $M^p(\mathbb{R})$, then Γ is relatively dense.

Note that the proof of (9) can easily be adapted to the case $p = 2$ and general $g \in L^2(\mathbb{R})$ and explicit upper bounds of the Bessel constant can be derived for example from [3, 4].

The question whether relative density is also necessary for general windows and Gabor sampling trajectories for $L^2(\mathbb{R})$ remains open. Drawing comparison to the discrete [29] and planar cases [19] however suggests that relative density should indeed be a necessary requirement.

3.2 Gaussian window

In [26], Ortega-Cerdà fully characterized the sampling measures for the Bargmann-Fock space of entire functions which corresponds to the short-time Fourier transform with Gaussian window. The result goes as follows.

Theorem 4 (Ortega-Cerdà) *Let $1 \leq p < \infty$. The measure μ is a sampling measure for $V_{h_0}(M^p(\mathbb{R}))$ if and only if there exist constants $R, \delta, M > 0$ and $N \in \mathbb{N}$ such that*

$$(i) \sup_{z \in \mathbb{R}^2} \mu(B_R(z)) \leq M, \quad (ii) \inf_{z \in \mathbb{R}^2} \frac{n(R, N, \delta, z)}{R^2} > 1,$$

where $n(R, N, \delta, z)$ is calculated by the following rule: take $S_R(z) := z + [-R/2, R/2]^2$ and cover it with N^2 smaller squares of sidelength R/N . Then $n(R, N, \delta, z)$ denotes the number of smaller squares $s \subset S_R(z)$ for which $\mu(s) \geq \delta$.

When specifying the measure μ to be the 1-dimensional Hausdorff measure on Γ , we subsequently show that, with a minor extra condition on the trajectory set Γ , condition (ii) is equivalent to Γ being relatively dense.

Corollary 5 *Let h_0 be the standard Gaussian window and $\Gamma \subset \mathbb{R}^2$ be a φ -regular trajectory set. Then Γ is a Gabor sampling trajectory for $M^p(\mathbb{R})$, $1 \leq p < \infty$, if and only if there exist $R, m, M > 0$ such that*

$$m \leq \mathcal{H}^1(\Gamma \cap B_R(z)) \leq M, \quad \text{for every } z \in \mathbb{R}^2. \quad (10)$$

Proof: The second inequality of (10) is condition (i) in Theorem 4. Hence, we have to show the equivalence of the left hand side inequality and (ii). If (ii) holds, then

$$\mathcal{H}^1(\Gamma \cap B_R(z)) \geq \mathcal{H}^1(\Gamma \cap S_R(z)) \geq \delta n(R, N, \delta, z) > \delta R^2.$$

Now let Γ be relatively dense and choose N large enough such that $\varphi(\sqrt{2}R/N) \leq \sqrt{2}\varphi(0)$. Then, using the lower bound in (10) and the φ -regularity of Γ , we get

$$\begin{aligned} m &\leq \mathcal{H}^1(\Gamma \cap B_R(z)) \leq \mathcal{H}^1(\Gamma \cap S_{2R}(z)) \\ &\leq n(2R, N, \delta, z) \sup_{w \in S_{2R}(z)} \mathcal{H}^1(\Gamma \cap S_{\frac{2R}{N}}(w)) + (N^2 - n(2R, N, \delta, z))\delta \\ &\leq n(2R, N, \delta, z) 2\pi\varphi(0) \frac{R}{N} + (N^2 - n(2R, N, \delta, z))\delta, \end{aligned}$$

for some constant $C > 0$. Regrouping the terms yields

$$n(2R, N, \delta, z) \geq N \frac{m - N^2\delta}{2\pi R - \delta N}.$$

Choosing $\delta = \frac{1}{N^2} \min\{m/2, \pi R\}$ shows that $n(2R, N, \delta, z)$ can be arbitrarily large as $N \rightarrow \infty$. In particular, there exists, $N \in \mathbb{N}$ such that (ii) is satisfied. \square

Remark 6 In [27] it is shown that φ -regularity with $\varphi(0) = 1$ can be considered as a quantitative strengthening of rectifiability. On the other hand, it is possible to construct fractal sets that are φ -regular if $\varphi(0) > 1$, which shows that φ -regularity for some φ is a rather mild assumption.

3.3 The case of parallel lines

We now study sampling and uniqueness properties of sets of parallel lines which follow from simple arguments. The results however will be useful later when we study spiraling curves.

Proposition 7 Let $g \in L^2(\mathbb{R})$, $\Lambda \subset \mathbb{R}$ be countable, and $\vec{d} = R(\theta)\vec{e}_2$. The collection of parallel lines $L_{\vec{d}, \Lambda}$, where

$$L_{\vec{d}, \Lambda} := \{t\vec{d} + \lambda\vec{d}_\perp : t \in \mathbb{R}, \lambda \in \Lambda\},$$

is a Gabor sampling trajectory for $L^2(\mathbb{R})$ with sampling bounds $A, B > 0$ if and only if

$$A \leq \sum_{\lambda \in \Lambda} |\mu(\theta)g(t - \lambda)|^2 \leq B, \quad \text{for a.e. } t \in \mathbb{R}. \quad (11)$$

Proof: First, by (8) we can rotate the problem and assume $\vec{d} = \vec{e}_2$. Writing the short-time Fourier transform as $V_g f(x, \xi) = \mathcal{F}(f\overline{T_x g})(\xi)$ and using Parseval's identity yields

$$\begin{aligned} \int_{L_{\vec{e}_2, \Lambda}} |V_g f(z)|^2 d\mathcal{H}^1(z) &= \sum_{\lambda \in \Lambda} \int_{\mathbb{R}} |V_g f(\lambda, \xi)|^2 d\xi = \sum_{\lambda \in \Lambda} \int_{\mathbb{R}} |f(t)\overline{g(t - \lambda)}|^2 dt \\ &= \int_{\mathbb{R}} |f(t)|^2 \left(\sum_{\lambda \in \Lambda} |g(t - \lambda)|^2 \right) dt, \end{aligned}$$

where changing the order of integration and summation is allowed by either (11) or the existence of the upper sampling bound. \square

The uniqueness property of parallel lines on the distribution space $M_{1/\vartheta_s}^\infty(\mathbb{R})$ can be characterized in a similar fashion.

Proposition 8 *Let $g \in M_{\vartheta_s}^1(\mathbb{R}) \cap A_{\vartheta_s}(\mathbb{R})$, $s \geq 0$, $\Lambda \subset \mathbb{R}$ be countable and $\vec{d} = R(\theta)\vec{e}_2$. The collection of parallel lines $L_{\vec{d},\Lambda}$ is a uniqueness set for $M_{1/\vartheta_s}^\infty(\mathbb{R})$ if and only if*

$$\bigcup_{\lambda \in \Lambda} \widetilde{\text{supp}}(T_\lambda \mu(\theta)g) = \mathbb{R},$$

where $\widetilde{\text{supp}}(g) := \{t \in \mathbb{R} : g(t) \neq 0\}$ denotes the effective support of g .

Remark 9 *In [6, Lemma 27], a similar result was shown for planar uniqueness sets. Since some technical details are left out there, we decided to include the proof here.*

Proof: For $f \in M_{1/\vartheta_s}^\infty(\mathbb{R})$, $g \in M_{\vartheta_s}^1(\mathbb{R}) \cap A_{\vartheta_s}(\mathbb{R})$ and $h \in M_{\vartheta_s}^1(\mathbb{R})$, we define fg via $\langle fg, h \rangle_{M_{1/\vartheta_s}^\infty \times M_{\vartheta_s}^1} = \langle f, gh \rangle_{M_{1/\vartheta_s}^\infty \times M_{\vartheta_s}^1}$. By (2), it then follows that $fg \in M_{1/\vartheta_s}^\infty(\mathbb{R})$ as

$$|\langle fg, h \rangle_{M_{1/\vartheta_s}^\infty \times M_{\vartheta_s}^1}| = |\langle f, gh \rangle_{M_{1/\vartheta_s}^\infty \times M_{\vartheta_s}^1}| \leq \|f\|_{M_{1/\vartheta_s}^\infty} \|gh\|_{M_{\vartheta_s}^1} \leq \|f\|_{M_{1/\vartheta_s}^\infty} \|g\|_{A_{\vartheta_s}} \|h\|_{M_{\vartheta_s}^1}.$$

Moreover, since $A_{\vartheta_s}(\mathbb{R})$ is invariant under translations it follows that $f\overline{T_x g} \in M_{1/\vartheta_s}^\infty \subset \mathcal{S}'(\mathbb{R})$ and consequently, $\mathcal{F}(f\overline{T_x g}) \in \mathcal{S}'(\mathbb{R})$ is a well defined tempered distribution.

Since $M_{\vartheta_s}^1(\mathbb{R})$ is weak-* dense in $M_{1/\vartheta_s}^\infty(\mathbb{R})$, and since the short-time Fourier transform of a distribution in $M_{1/\vartheta_s}^\infty(\mathbb{R})$ is continuous in \mathbb{R}^2 , it follows that $V_g f(x, \xi) = \mathcal{F}(f\overline{T_x g})(\xi)$.

As before we may rotate the problem and assume $\vec{d} = \vec{e}_2$. Now, $V_g f|_{L_{\vec{e}_2, \Lambda}} = 0$ if and only if the distributions $f\overline{T_\lambda g}$, $\lambda \in \Lambda$, are zero. This in turn is equivalent to the support of f and the effective support of $T_\lambda g$ being disjoint for every $\lambda \in \Lambda$. \square

3.4 Connection to discrete sampling

Proposition 7 shows that Γ being relatively dense is not sufficient for Γ to be a Gabor sampling trajectory. A natural question is therefore whether for every $g \in L^2(\mathbb{R}) \setminus \{0\}$ there exists $R^* > 0$ such that every (γ, R) -dense trajectory set Γ is a Gabor sampling trajectory if $R \leq R^*$. We follow the approach of [19] to show that such R^* does in fact exist for a certain class of window functions.

Let us write $Q_R(z) := Rz + [-R/2, R/2]^2$ and recall the definition of the Sobolev space $H^1(\mathbb{R}) := \left\{ f \in L^2(\mathbb{R}) : \int_{\mathbb{R}} (1 + |\xi|^2) |\hat{f}(\xi)|^2 d\xi < \infty \right\}$.

Proposition 10 *Let $g, tg \in H^1(\mathbb{R})$, $R > 0$ be chosen such that*

$$\Delta := \frac{2R}{\pi} \left(\|g'\|_2 + \|tg\|_2 + \frac{2R}{\pi} \|tg'\|_2 \right) < \|g\|_2, \quad (12)$$

and $\Gamma \subset \mathbb{R}^2$ be a trajectory set. If

$$0 < m \leq \mathcal{H}^1(\Gamma \cap Q_R(z)) \leq M < \infty, \quad \text{for every } z \in \mathbb{R}^2,$$

then

$$m(\|g\|_2 - \Delta)^2 \|f\|^2 \leq \int_{\Gamma} |V_g f(z)|^2 d\mathcal{H}^1(z) \leq M(\|g\|_2 + \Delta)^2 \|f\|^2.$$

Proof: It is shown in [33] that for the particular choice of g and R , taking arbitrary points $z_n \in Q_R(n)$, $n \in \mathbb{Z}^2$, yields a discrete frame $\{\pi(z_n)g\}_{n \in \mathbb{Z}^2}$ for $L^2(\mathbb{R})$ with uniform frame bounds $A = (\|g\|_2 - \Delta)^2$ and $B = (\|g\|_2 + \Delta)^2$.

For every $n \in \mathbb{Z}^2$ there exists $z_n \in \Gamma \cap Q_R(n)$ such that

$$|V_g f(z_n)|^2 \geq \frac{1}{\mathcal{H}^1(\Gamma \cap Q_R(n))} \int_{\Gamma \cap Q_R(n)} |V_g f(z)|^2 d\mathcal{H}^1(z).$$

Then, as every choice of points $z_n \in Q_R(n)$ generates a Gabor frame with uniform upper bound B , we have

$$\begin{aligned} \int_{\Gamma} |V_g f(z)|^2 d\mathcal{H}^1(z) &= \sum_{n \in \mathbb{Z}^2} \int_{\Gamma \cap Q_R(n)} |V_g f(z)|^2 d\mathcal{H}^1(z) \\ &\leq \sum_{n \in \mathbb{Z}^2} \mathcal{H}^1(\Gamma \cap Q_R(n)) |V_g f(z_n)|^2 \leq MB \|f\|^2. \end{aligned}$$

The lower sampling bound follows with a similar argument. □

Remark 11 *This construction works for general measures and gives a characterization of sampling measures for this class of window functions.*

4 Spiraling curves

4.1 Weak limits

There are multiple ways of defining weak limits of trajectory sets. The definition in [18] for example adapts the initial definition by Beurling [10] which is given in terms of a geometric condition. Here, it will be convenient to work with a stronger notion that was introduced to define weak limits of measures, see [6].

Definition 1 Let $\Gamma, \Gamma', \Gamma_n$ be trajectory sets in \mathbb{R}^2 . We say that $\{\Gamma_n\}_{n \in \mathbb{N}}$ converges weakly to Γ if

$$\int_{\Gamma_n} \phi(z) d\mathcal{H}^1(z) \rightarrow \int_{\Gamma} \phi(z) d\mathcal{H}^1(z),$$

for every nonnegative function $\phi \in C_c(\mathbb{R}^2)$. In that case we write $\Gamma_n \xrightarrow{w} \Gamma$.

We say that Γ' is a weak limit of translates of Γ if there exists a sequence $\{z_n\}_{n \in \mathbb{N}}$ such that $z_n + \Gamma \xrightarrow{w} \Gamma'$ and define \mathcal{W}_Γ as the set of all weak limits of translates of Γ .

The following characterization of Gabor sampling trajectories is an immediate consequence of a characterization of sampling measures for the short-time Fourier transform given by Ascensi [6, Theorem 14]. One can think of this result as a time-frequency analog of the classical result by Beurling [10, Theorem 3, pg. 345] where the Gabor sampling property on $M^p(\mathbb{R})$ is connected to the uniqueness property of all weak limits of translates on the larger space $M^p_{1/\vartheta_s}(\mathbb{R})$. Note that Ascensi's result requires a special class of windows which we define in a simplified version tailored to polynomial weights.

Definition 2 We say that $1/\vartheta_s$ controls $V_g g$ if there exist a function $d : \mathbb{R}^+ \rightarrow \mathbb{R}^+$ which is decreasing with $d(r) \rightarrow 0$, as $r \rightarrow \infty$, and satisfies $|V_g g(z)| \leq d(|z|)/\vartheta_s(z)$. The class $\mathcal{M}_s^1(\mathbb{R})$, $s > 2$, is then given by

$$\mathcal{M}_s^1(\mathbb{R}) := \{g \in L^2(\mathbb{R}) : 1/\vartheta_s \text{ controls } V_g g\}.$$

Theorem 12 (Ascensi) Let $g \in \mathcal{M}_s^1(\mathbb{R})$, for some $s > 2$, and $1 \leq p < \infty$. Then Γ is a Gabor sampling trajectory for $M^p(\mathbb{R})$ if and only if every $\Gamma' \in \mathcal{W}_\Gamma$ is a set of uniqueness for $M^p_{1/\vartheta_s}(\mathbb{R})$.

4.2 Spiraling curves and their weak limits

The notion of a spiraling curve was introduced in [18]. This class of trajectory sets includes a wide range of natural examples such as the concentric circles or the Archimedes spiral. In this paper, we use a slightly more restrictive notion of spiraling curves that still includes the main examples from [18] and that allows a full characterization of the set of weak limits of translates.

Definition 3 (Spiraling curve) Let $\mathcal{I}_\Gamma \subset \mathbb{T}$ be a finite set. A trajectory set Γ is called spiraling if the following list of conditions is satisfied:

If $\beta \in \mathbb{T} \setminus \mathcal{I}_\Gamma$, then

(A.i) (Escape Cone) for $\alpha := \min\{\text{dist}(\beta, \mathcal{I}_\Gamma), 1/8\}$ the intersection of Γ with the cone

$$\mathcal{C}_{\alpha,\beta} := \{(r \cos 2\pi\theta, r \sin 2\pi\theta) : r \geq 0, \beta - \alpha \leq \theta \leq \beta + \alpha\}$$

can be parametrized in polar coordinates as

$$\gamma_\beta(\theta) = (r_\beta(\theta) \cos 2\pi\theta, r_\beta(\theta) \sin 2\pi\theta)$$

with $\theta \in \bigcup_{k \in \mathbb{N}} [k + \beta - \alpha, k + \beta + \alpha]$ and r_β a nonnegative C^2 -function on each interval whose C^2 -norm is globally bounded.

(A.ii) (Asymptotic radial monotonicity) there exist $K \in \mathbb{N}$ such that for any $\theta \in [-\alpha, \alpha]$ fixed, the sequence $r_\beta(k + \beta + \theta)$ is strictly increasing for $k \geq K$.

(A.iii) (Asymptotic flatness) the curvature of γ_β , denoted by κ_β , tends to 0 as its input goes to infinity. To be more precise, we assume

$$\sup_{\theta \in (-\alpha, \alpha)} \kappa_\beta(k + \beta + \theta) \rightarrow 0, \quad k \rightarrow \infty. \quad (13)$$

(A.iv) (Asymptotic equispacing) there exist continuous functions $\eta_\beta : [-\alpha, \alpha] \rightarrow \mathbb{R}^+$, $\rho_\beta : [-\alpha, \alpha] \rightarrow \mathbb{R}$ such that

$$\sup_{\theta \in [-\alpha, \alpha]} |r_\beta(k + \beta + \theta) - \eta_\beta(\theta)k - \rho_\beta(\theta)| \rightarrow 0, \quad k \rightarrow \infty.$$

(A.v) (Asymptotic velocity) there exists a continuous function $\vec{d}_\beta : [-\alpha, \alpha] \rightarrow \mathbb{S}^1$ such that $\vec{d}_\beta(\theta)$ is non-collinear with $\vec{\ell}(\theta)$ and

$$\sup_{\theta \in [-\alpha, \alpha]} \left\| \frac{\gamma'_\beta(k + \beta + \theta)}{\|\gamma'_\beta(k + \beta + \theta)\|} - \vec{d}_\beta(\theta) \right\| \rightarrow 0, \quad k \rightarrow \infty. \quad (14)$$

If $\beta \in \mathcal{I}_\Gamma$, then (A.i) – (A.v) hold with the following modifications

(B.i) for $\alpha := \min\{\text{dist}(\beta, \mathcal{I}_\Gamma \setminus \{\beta\}), 1/8\}$, the parametrization $\gamma_\beta|_{[k + \beta - \alpha, k + \beta + \alpha]}$ is continuous and the restrictions of γ_β to $(k + \beta, k + \beta + \alpha]$ and $[k + \beta - \alpha, k + \beta)$ are C^2 -functions with bounded C^2 -norms.

(B.iii) The supremum in (13) is replaced by an supremum over $(-\alpha, \alpha) \setminus \{0\}$.

(B.v) The velocity vector \vec{d}_β is continuous on $[-\alpha, \alpha] \setminus \{0\}$. Moreover, $\lim_{\theta \nearrow 0} \vec{d}_\beta(\theta)$ and $\lim_{\theta \searrow 0} \vec{d}_\beta(\theta)$ exist, and the supremum in (14) is taken over $[-\alpha, \alpha] \setminus \{0\}$.

Remark 13 (i) The original definition of spiraling curves [18, Section 3.3] only assumed that there exist at least one angle such that the conditions (A.i)-(A.v) are satisfied. Let us mention here, that our additional assumptions are also met by the examples mentioned in [18]. In particular, the set of concentric circles is also a spiraling curve in the sense of this paper.

(ii) Since the collection of star shaped polygons and paths generated by a set of points consist of line segments (mostly parallel and equispaces within escape cones), it is a straightforward task to show that these trajectory sets are indeed spiraling curves. The only escape cone that needs more attention is the one that contains the line segments $s(kz_n, (k+1)z_1)$. In the limit however, these are parallel and equispaced line segments.

Subsequently, we give a full characterization of the set of all weak limits of translates of spiraling curves. To do so, we establish two technical lemmas that describe the weak limits of $z_k + \Gamma$ according to a certain geometric condition on the sequence $\{z_k\}_{k \in \mathbb{N}}$.

Lemma 14 Let $z_k = -r_k \vec{\ell}(\theta_k)$, $k \in \mathbb{N}$, be an unbounded sequence. If there exist no pair (\mathcal{N}, γ) , $\mathcal{N} \subset \mathbb{N}$, $\gamma \in \mathbb{T}$, such that

$$(i) \{z_k\}_{k \in \mathcal{N}} \text{ is unbounded} \quad \text{and} \quad (ii) \{r_k \sin(2\pi(\theta_k - \gamma))\}_{k \in \mathcal{N}} \text{ is bounded},$$

then there exist a subsequence $\{z_{k_n}\}_{n \in \mathbb{N}}$, an angle $\beta \in \mathbb{T} \setminus \mathcal{I}_\Gamma$, and a constant $\tau \in \mathbb{R}$, such that (a) $-z_{k_n} \in (\mathcal{C}_{\alpha, \beta})^\circ$, for every $n \in \mathbb{N}$, (b) $\theta_{k_n} \rightarrow \theta^*$, $n \rightarrow \infty$, and

$$(c) \ z_{k_n} + \Gamma \xrightarrow{w} \tau \vec{d}_\perp + L_{\vec{d}, \lambda \mathbb{Z}},$$

where $\vec{d} = \lim_{n \rightarrow \infty} \vec{d}_\beta(\theta_{k_n} - \beta)$ and $\lambda = \eta_\beta(\theta^* - \beta) \sin(\arccos(\vec{\ell}(\theta^*) \cdot \vec{d}))$.

Moreover, for every $\tau \in \mathbb{R}$, $\beta \in \mathbb{T} \setminus \mathcal{I}_\Gamma$ and for $\vec{d} = \lim_{\theta \searrow 0} \vec{d}_\beta(\theta)$ as well as for $\vec{d} = \lim_{\theta \nearrow 0} \vec{d}_\beta(\theta)$, there exist a sequence $\{z_k\}_{k \in \mathbb{N}}$ such that

$$z_k + \Gamma \xrightarrow{w} \tau \vec{d}_\perp + L_{\vec{d}, \lambda \mathbb{Z}},$$

with $\lambda = \eta_\beta(0) \sin(\arccos(\vec{\ell}(\beta) \cdot \vec{d}))$.

Remark 15 *The distinction of the two directions (which coincide for $\beta \in \mathbb{T} \setminus \mathcal{I}_\Gamma$) in Lemma 14 is necessary as, for $\beta \in \mathcal{I}_\Gamma$, the sets of parallel lines with the left and right limits of the asymptotic velocity as directions are both included in \mathcal{W}_Γ .*

Proof: *Step 1:* Since $r_k \sin(2\pi(\theta_k - \gamma))$ is unbounded for every $\gamma \in \mathcal{I}_\Gamma$ and since \mathbb{T} is compact we can, after passing to a subsequence, assume that $\{-z_k\}_{k \in \mathbb{N}}$ is contained in the interior of an escape cone $\mathcal{C}_{\alpha, \beta}$ for some $\beta \in \mathbb{T} \setminus \mathcal{I}_\Gamma$ and that $\theta_k \rightarrow \theta^* \in [-\alpha + \beta, \alpha + \beta]$.

As the problem is rotation invariant, we may for simplicity assume that $\beta = 0$. In the following we therefore omit the subscripts in η_β, r_β , etc.. As $\|z_k\|$ is unbounded, we can, after passing to yet another subsequence, write z_k as

$$z_k = -(\eta(\theta^*)(n_k + v_k) + \rho(\theta^*))\vec{\ell}(\theta_k),$$

where $n_k \in \mathbb{N}$ is strictly increasing, $v_k \in [0, 1]$ converges to v^* , and η, ρ are the functions given by (A.iv). If $z_k + \Gamma$ converges weakly to Γ' , then $z_k + v_k \eta(\theta^*)\vec{\ell}(\theta_k) + \Gamma$ converges weakly to $v^* \eta(\theta^*)\vec{\ell}(\theta^*) + \Gamma'$. As $z_k + v_k \eta(\theta^*)\vec{\ell}(\theta_k)$ still satisfies the assumption of this lemma, we may further simplify notation and assume

$$z_k = -(\eta(\theta^*)k + \rho(\theta^*))\vec{\ell}(\theta_k).$$

Step 2: We will later show that the following property is always satisfied: For every compact set $K \subset \mathbb{R}^2$ there exists $k^* \in \mathbb{N}$ such that

$$K \subset z_k + \mathcal{C}_{\alpha - |\theta_k|, \theta_k}, \quad k \geq k^*.$$

For $h \in C_c(\mathbb{R}^2)$, there exist $T_\theta, S_\theta > 0$ and $t_\theta \in \mathbb{R}$ such that the parallelogram

$$\tilde{P}_\theta = \{(t_\theta + t)\vec{\ell}(\theta) + s\vec{d}(\theta) : s \in [-S_\theta, S_\theta], t \in [0, T_\theta]\}$$

satisfies $\text{supp}(h) \subset \tilde{P}_\theta$. Note that T_θ, S_θ can be chosen to depend continuously on $\theta \in [-\alpha, \alpha]$. In order to simplify the argument, we define a slightly larger parallelogram P_θ containing \tilde{P}_θ . To this end, let $m_\theta, M_\theta \in \mathbb{Z}$ be the largest (respectively smallest) integer such that $m_\theta \eta(\theta) \leq t_\theta$, and $M_\theta \eta(\theta) \geq t_\theta + T_\theta$ and define

$$P_\theta = \{(m_\theta - 1/2 + t)\eta(\theta)\vec{\ell}(\theta) + s\vec{d}(\theta) : s \in [-S_\theta, S_\theta], t \in [0, M_\theta - m_\theta + 1]\},$$

as well as the smaller parallelograms

$$P_{\theta,m} = \left\{ (m - 1/2 + t)\eta(\theta)\vec{\ell}(\theta) + s\vec{d}(\theta) : s \in [-S_\theta, S_\theta], t \in [0, 1] \right\}, \quad m_\theta \leq m \leq M_\theta.$$

Since all parameters defining P_θ are continuously depending on θ , it first follows that the number of smaller parallelograms is bounded by $\max_{\theta \in [-\alpha, \alpha]} T_\theta / \eta(\theta) + 2$. Secondly, there exists a compact set K such that $P_\theta \subset K$ for ever $\theta \in [-\alpha, \alpha]$. Consequently, by our previous assumption, for k large enough we have that $P_{\theta_k} \subset K \subset z_k + C_{\alpha-|\theta_k|, \theta_k}$.

Step 3: For each k, m , let $\psi_{k,m} : I_{k,m} \rightarrow \mathbb{R}^2$ be a re-parametrization by arc-length of the segment $\{z_k + \gamma(k + m + \theta)\}_{\theta \in [-\alpha, \alpha]}$ such that

$$\psi_{k,m}(0) = z_k + \gamma(k + m + \theta_k) = (r(k + m + \theta_k) - k\eta(\theta^*) - \rho(\theta^*))\vec{\ell}(\theta_k).$$

For large values of k , $\psi_{k,m}(0)$ approximates $m\eta(\theta^*)\vec{\ell}(\theta^*)$. Applying a first order Taylor approximation yields

$$\|\psi_{k,m}(t) - (r(k + m + \theta_k) - k\eta(\theta^*) - \rho(\theta^*))\vec{\ell}(\theta_k) - t\psi'_{k,m}(0)\| \leq \frac{t^2}{2} \sup_{s \in I_{k,m}} \|\psi''_{k,m}(s)\|. \quad (15)$$

Let us define $S_{\max} := \max_{\theta \in [-\alpha, \alpha]} S_\theta$ (and S_{\min} analogously). By conditions (A.iii)-(A.v) of Definition 3 and

$$\sup_{s \in I_{k,m}} \|\psi''_{k,m}(s)\| = \sup_{\theta \in [-\alpha, \alpha]} |\kappa(k + m + \theta)| \rightarrow 0, \quad \text{as } k \rightarrow \infty,$$

we have that for every $\delta > 0$ there exists $k^* \in \mathbb{N}$ such that

- (i) $|\kappa(k + m + \theta)| < \delta/8S_{\max}^2$,
- (ii) $\|\psi'_{k,m}(0) - \vec{d}(\theta_k)\| = \left\| \frac{\gamma'(k+m+\theta_k)}{\|\gamma'(k+m+\theta_k)\|} - \vec{d}(\theta_k) \right\| < \delta/8S_{\max}$,
- (iii) $|r(k + m + \theta^*) - \eta(\theta^*)(k + m) - \rho(\theta^*)| < \delta/4$,
- (iv) $|r(k + m + \theta_k) - r(k + m + \theta^*)| < \delta/4$,

whenever $k \geq k^*$. Note that we have used that the C^2 -norm of r is globally bounded to ensure the last estimate. Now, if $t \in [-2S_{\max}, 2S_{\max}]$ and $k \geq k^*$, then, using (15) and triangle inequality, we get

$$\|\psi_{k,m}(t) - \eta(\theta^*)m\vec{\ell}(\theta_k) - t\vec{d}(\theta_k)\|$$

$$\begin{aligned}
&\leq |r(k+m+\theta^*) - r(k+m+\theta_k)| + |r(k+m+\theta^*) - \eta(\theta^*)(k+m) - \rho(\theta^*)| \times \\
&\quad + |t| \|\psi'_{k,m}(0) - \vec{d}(\theta_k)\| + \frac{t^2}{2} \sup_{s \in I_{k,m}} \|\psi''_{k,m}(s)\| \\
&< \delta/4 + \delta/4 + \delta/4 + \delta/4 = \delta.
\end{aligned}$$

Hence, if $\delta < \min\{S_{\min}, \eta\}$, then $\psi_{k,m} \cap P_{\theta_k} \subset P_{\theta_k,m}$, and $\psi_{k,m}(t) \notin P_{\theta_k,m}$ for every $|t| \geq 2S_{\max}$.

As h is uniformly continuous we may choose δ according to ε such that $\|x - y\| < \delta$ implies $|h(x) - h(y)| < \varepsilon$. Let $\lambda_k = \eta(\theta_k) \sin(\arccos(\vec{\ell}(\theta_k) \cdot \vec{d}(\theta_k)))$. Then, for $k \geq k^*$

$$\begin{aligned}
&\left| \int_{z_k + \Gamma} h(x) \, d\mathcal{H}^1(x) - \int_{L_{\vec{d}(\theta_k), \lambda_k \mathbb{Z}}} h(x) \, d\mathcal{H}^1(x) \right| \\
&= \sum_{m=m_1, \theta_k}^{m_2, \theta_k} \left| \int_{(z_k + \Gamma) \cap P_{\theta_k, m}} h(x) \, d\mathcal{H}^1(x) - \int_{L_{\vec{d}(\theta_k), \lambda_k \mathbb{Z}} \cap P_{\theta_k, m}} h(x) \, d\mathcal{H}^1(x) \right| \\
&\leq \sum_{m=m_1, \theta_k}^{m_2, \theta_k} \int_{-2S_{\max}}^{2S_{\max}} \left| h(\psi_{k,m}(t)) - h(\eta(\theta_k)m\vec{\ell}(\theta_k) + \vec{d}(\theta_k)t) \right| dt \\
&\leq 4S_{\max} \sum_{m=m_1, \theta_k}^{m_2, \theta_k} \sup_{t \in [-2S_{\max}, 2S_{\max}]} \left| h(\psi_{k,m}(t)) - h(\eta(\theta_k)m\vec{\ell}(\theta_k) + \vec{d}(\theta_k)t) \right| \\
&\leq 4S_{\max}(m_2, \theta_k - m_1, \theta_k)\varepsilon \leq 4S_{\max} \left(\max_{\theta \in [-\alpha, \alpha]} T_\theta / \eta(\theta) + 2 \right) \varepsilon.
\end{aligned}$$

As $\theta_k \rightarrow \theta^*$ and consequently $\lambda_k \rightarrow \lambda^*$, it is clearly possible to find k^* such that

$$\left| \int_{L_{\vec{d}(\theta^*), \lambda^* \mathbb{Z}}} h(x) \, d\mathcal{H}^1(x) - \int_{L_{\vec{d}(\theta_k), \lambda_k \mathbb{Z}}} h(x) \, d\mathcal{H}^1(x) \right| \leq \varepsilon,$$

whenever $k \geq k^*$. Therefore, by triangle inequality, the convergence $z_k + \Gamma \xrightarrow{w} L_{\vec{d}(\theta^*), \lambda^* \mathbb{Z}}$ follows.

Step 4: It remains to show that the assumption $K \subset z_k + \mathcal{C}_{\alpha - |\theta_k|, \theta_k}$ can always be satisfied for k large enough. To this end, we distinguish the cases $|\theta^*| < \alpha$ and $|\theta^*| = \alpha$. In the former case, we set $\alpha^* = (\alpha - |\theta^*|)/2$ and observe that for k large enough $-\frac{1}{2}\|z_k\|\vec{\ell}(\theta^*) + \mathcal{C}_{\alpha^*, \theta^*} \subset z_k + \mathcal{C}_{\alpha - |\theta_k|, \theta_k}$ and the left side of the inclusion relation will eventually cover any compactum.

If $|\theta^*| = \alpha$ and $\theta^* \notin \mathcal{I}_\Gamma$, then it is possible to apply a rotation with a small angle such that α is still the opening angle for the escape cone of $\beta = 0$ and $|\theta^*| < \alpha$.

If $|\theta^*| = \alpha$ and $\theta^* \in \mathcal{I}_\Gamma$, then one can rotate the problem so that $\theta^* = 0$. Moreover, we can without loss of generality assume that $\theta_k > 0$. Let us consider the cone $\mathcal{C}_{\theta_k, \theta_k}$. A simple geometric argument shows that

$$\{(x, y) \in \mathbb{R}^2 : x \geq -a_k, |y| \leq b_k, \text{ and } 2b_k x + a_k b_k \geq a_k y\} \subset z_k + \mathcal{C}_{\theta_k, \theta_k}, \quad (16)$$

where $a_k = r_k \cos(2\pi\theta_k)$ and $b_k = r_k \sin(2\pi\theta_k)$, see Figure 2 for an illustration. The




Figure 2: The set from the left hand side of (16) (gray shaded area) and the cone $z_k + \mathcal{C}_{\theta_k, \theta_k}$.

assumptions that there is no unbounded subsequence of $\{z_k\}_k$ such that $r_{k_n} \sin(2\pi\theta_{k_n})$ is bounded and $|\theta_k| \leq \alpha \leq 1/8$ then shows, after possibly passing to yet another subsequence, that $z_k + \mathcal{C}_{\theta_k, \theta_k}$ eventually covers any compactum.

Step 5: To see that every such collection of parallel lines is in fact a weak limit, we may assume that $\vec{d} = \lim_{\theta \searrow 0} \vec{d}_\beta(\theta)$ ($\vec{d} = \lim_{\theta \nearrow 0} \vec{d}_\beta(\theta)$ works exactly the same) and choose

$$z_k = \tau \vec{d}_\perp - (\eta_\beta(0)k + \rho_\beta(0))\vec{\ell}(\beta + 1/\sqrt{k}), \quad \beta \in \mathbb{T} \setminus \mathcal{I}_\Gamma.$$

For this choice, the assumptions of the first part of this lemma are satisfied and one may repeat the arguments to show that $z_k + \Gamma \xrightarrow{w} \tau \vec{d}_\perp + L_{\vec{d}, \eta} \mathbb{Z}$. \square

Lemma 16 *Let $z_k = -r_k \vec{\ell}(\theta_k)$, $k \in \mathbb{N}$, be an unbounded sequence. If there exists a pair (\mathcal{N}, γ) , $\mathcal{N} \subset \mathbb{N}$, $\gamma \in \mathcal{I}_\Gamma$, such that*

$$(i) \{z_k\}_{k \in \mathcal{N}} \text{ is unbounded} \quad \text{and} \quad (ii) \{r_k \sin(2\pi(\theta_k - \gamma))\}_{k \in \mathcal{N}} \text{ is bounded,}$$

then there exist a subsequence $\{z_{k_n}\}_{n \in \mathbb{N}}$, and $z \in \mathbb{R}^2$, such that

$$z_{k_n} + \Gamma \xrightarrow{w} z + E_\gamma,$$

where the set of parallel edges E_γ is given by

$$E_\gamma := \left\{ \eta_\gamma k \vec{\ell}(\gamma) - t \vec{d}_\gamma^- : k \in \mathbb{Z}, t \in [0, \infty) \right\} \cup \left\{ \eta_\gamma k \vec{\ell}(\gamma) + t \vec{d}_\gamma^+ : k \in \mathbb{Z}, t \in [0, \infty) \right\},$$

and $\eta_\gamma = \eta_\gamma(0)$, $\vec{d}_\gamma^- = \lim_{\theta \nearrow 0} \vec{d}_\gamma(\theta)$, and $\vec{d}_\gamma^+ = \lim_{\theta \searrow 0} \vec{d}_\gamma(\theta)$.

Moreover, for every $\gamma \in \mathcal{I}_\Gamma$ and every $z \in \mathbb{R}^2$ there exist a sequence $\{z_k\}_{k \in \mathbb{N}}$ such that $z_k + \Gamma \xrightarrow{w} z + E_\gamma$.

Proof: After potentially passing to a subsequence, one can assume that $\mathcal{N} = \mathbb{N}$, and that r_k is an increasing unbounded sequence. Moreover, by rotation invariance we may assume that $\gamma = 0$. By assumption, the sequence $r_k \sin(2\pi\theta_k)$ is bounded which shows that there exists a subsequence converging to y^* . Therefore, after passing to this subsequence, we see that if $z_k + \Gamma$ converges to Γ' , then $(-r_k \cos \theta_k, 0) + \Gamma$ converges to $(0, -y^*) + \Gamma'$. Therefore, we further simplify the problem and assume that $z_k = (-\tilde{r}_k, 0)$. From here we can basically proceed as in the proof of Lemma 14 with some minor adjustments.

Let us shortly point out where caution is needed. For $h \in C_c(\mathbb{R}^2)$ the parallelograms need to be replaced by arrow shaped objects defined as follows: let $t^* \in \mathbb{R}$ and $S, T > 0$ be chosen such that the set

$$\tilde{A}_h := \left\{ (t^* + t) \vec{e}_1 - s \vec{d}_0^- : t \in [0, T], s \in [0, S] \right\} \cup \left\{ (t^* + t) \vec{e}_1 + s \vec{d}_0^+ : t \in [0, T], s \in [0, S] \right\}$$

contains $\text{supp}(h)$. Then one can proceed almost exactly as before by replacing P_h by A_h , using the assumptions (B.iii)-(B.v) of Definition 3 and applying two Taylor expansions for the right and left limits.

Again, we are left with showing that each such set of parallel edges is indeed a weak limit of translates. Setting $z_k = z - (\eta_\gamma(0)k + \rho_\gamma(0))\vec{\ell}(\gamma)$, $\gamma \in \mathcal{I}_\Gamma$, however yields that $z_k + \Gamma \xrightarrow{w} z + E_\gamma$. \square

Theorem 17 *The set of weak limits of translates of a spiraling curve Γ is given by*

$$\mathcal{W}_\Gamma = \mathcal{S}_\Gamma \cup \mathcal{L}_\Gamma \cup \mathcal{E}_\Gamma, \tag{17}$$

where $\mathcal{S}_\Gamma = \{z + \Gamma : z \in \mathbb{R}^2\}$, $\mathcal{E}_\Gamma = \{z + E_\beta : \beta \in \mathcal{I}_\Gamma, z \in \mathbb{R}^2\}$, and

$$\mathcal{L}_\Gamma = \left\{ \tau \vec{d}_\perp + L_{\vec{d}, \lambda \mathbb{Z}} : \tau \in \mathbb{R}, \vec{d} = \lim_{\theta \searrow 0} \vec{d}_\beta(\theta), \text{ or } \vec{d} = \lim_{\theta \nearrow 0} \vec{d}_\beta(\theta), \beta \in \mathbb{T} \right\},$$

where λ is defined as in Lemma 14.

Proof: It follows from Lemma 14 and Lemma 16 that $\mathcal{S}_\Gamma \cup \mathcal{L}_\Gamma \cup \mathcal{E}_\Gamma \subseteq \mathcal{W}_\Gamma$.

Now let $z_k + \Gamma \xrightarrow{w} \Gamma'$. If $\|z_k\| \leq C$, then there exist a converging subsequence $z_{k_n} \rightarrow z^*$ and it follows that $\Gamma' = z^* + \Gamma \in \mathcal{S}_\Gamma$. If $\{z_k\}_{k \in \mathbb{N}}$ is unbounded, then either there exist $\mathcal{N} \subset \mathbb{N}$ and $\gamma \in \mathcal{I}_\Gamma$ such that $\{z_k\}_{k \in \mathcal{N}}$ is unbounded and $\{r_k \sin(2\pi(\theta_k - \gamma))\}_{k \in \mathcal{N}}$ is bounded, or not. Hence, the assumption of either Lemma 14 or Lemma 16 are satisfied which leaves us with the limit Γ' being either a set of parallel lines or a set of parallel edges, i.e. $\mathcal{W}_\Gamma \subseteq \mathcal{S}_\Gamma \cup \mathcal{L}_\Gamma \cup \mathcal{E}_\Gamma$. \square

4.3 Spiraling curves as Gabor sampling trajectories

After characterizing the set of all weak limits of translates we can now prove our main results. We first show that, for a certain class of windows, spiraling curves are Gabor sampling trajectories if and only if they are uniqueness sets for the weighted modulation space $M_{1/\vartheta_s}^p(\mathbb{R})$. Later, we then verify that certain spiraling curves are indeed such uniqueness sets.

Theorem 18 *Let $\Gamma \in \mathbb{R}^2$ be a spiraling curve, $g \in \text{span}\{h_n : n \in \mathbb{N}_0\}$, and $1 \leq p < \infty$. Then Γ is a Gabor sampling trajectory for $M^p(\mathbb{R})$ if and only if Γ is a uniqueness set for $M_{1/\vartheta_s}^p(\mathbb{R})$ for some $s > 2$.*

To show this theorem we first need to state two auxiliary lemmas. The first one is a consequence of [15, Corollary 3.9(c) & Proposition 2.2].

Lemma 19 *If there exist $\alpha > 0$ such that $|g(t)| \lesssim e^{-\alpha|t|}$ and $|\widehat{g}(\xi)| \lesssim e^{-\alpha|\xi|}$, then $|V_g g(z)| \lesssim 1/\vartheta_s(z)$, for every $s > 0$.*

The following lemma is a simple consequence of [6, Corollary 26].

Lemma 20 *Let $g \in \text{span}\{h_n : n \in \mathbb{N}_0\}$. For every $f \in M_{1/\vartheta_s}^p(\mathbb{R})$, $1 \leq p < \infty$, $z \in \mathbb{R}^2$, and $\beta \in \mathbb{T}$, it holds that $V_g f(z + t\vec{\ell}(\beta))$ is a real analytic function in $t \in \mathbb{R}$.*

Proof: First, observe that $V_g f(z + t\vec{\ell}(\beta))$ is real analytic if and only if

$$V_g f(R(\beta)R(-\beta)(z + t\vec{\ell}(\beta))) = V_{\mu(\beta)g}(\mu(\beta)f)(R(-\beta)z + t\vec{e}_1)$$

is real analytic. For $\beta \in \mathbb{T}$ one has that $\mu(\beta)g \in \mathcal{M}_s^1(\mathbb{R})$ by Lemma 19 and $|\mu(\beta)g(t)| \lesssim e^{-\alpha|t|}$. Since the metaplectic rotation leaves $M_{1/\vartheta_s}^p(\mathbb{R})$ invariant, it follows by [6, Corollary 26] that $V_{\mu(\beta)g}(\mu(\beta)f)(R(-\beta)z + t\vec{e}_1)$ is real analytic. \square

Proof of Theorem 18: First, observe that $g \in \mathcal{M}_s^1(\mathbb{R})$ by Lemma 19. We may therefore apply Theorem 12. By Theorem 17, the set of weak limits of translates consists of finite shifts of Γ and the sets of parallel lines and edges. As $V_g f(z - w) = e^{2\pi i \xi y} V_g \pi(w) f(z)$, and $M_{1/\vartheta_s}^p(\mathbb{R})$ is invariant under time-frequency shifts, it follows that $z + \Gamma$ is a uniqueness set for $M_{1/\vartheta_s}^p(\mathbb{R})$ if and only if Γ is a uniqueness set for $M_{1/\vartheta_s}^p(\mathbb{R})$.

We now show that every set of parallel lines (resp. parallel edges) is a uniqueness set. To show the two cases at once, we prove that any collection of parallel half lines $\{\eta k \vec{d}_1 + t \vec{d}_2 : t \geq 0\}$, \vec{d}_1, \vec{d}_2 not colinear, and $\eta > 0$, is a uniqueness set for $M_{1/\vartheta_s}^p(\mathbb{R})$. Since $V_g f$ restricted to a line in \mathbb{R}^2 is real analytic by Lemma 20, it follows that $V_g f|_{\{\eta k \vec{d}_1 + t \vec{d}_2 : t \geq 0, k \in \mathbb{Z}\}} = 0$ implies $V_g f|_{\{\eta k \vec{d}_1 + t \vec{d}_2 : t \in \mathbb{R}, k \in \mathbb{Z}\}} = 0$.

The function $\mu(\theta)g$ is also a linear combination of Hermite functions and thus has only finitely many zeros. Therefore, it follows that $\bigcup_{k \in \mathbb{Z}} \widetilde{\text{supp}}(T_{\delta k} \mu(\theta)g) = \mathbb{R}$ for every $\delta > 0$. Finally, as $g \in A_{\vartheta_s}(\mathbb{R})$, we may apply Proposition 8 to see that $V_g f|_{\{\eta k \vec{d}_1 + t \vec{d}_2 : t \in \mathbb{R}, k \in \mathbb{Z}\}} = 0$ implies $f = 0$. \square

Corollary 21 *Let $g \in \text{span}\{h_n : n \in \mathbb{N}_0\}$, $1 \leq p < \infty$, $\eta > 0$. Moreover, let $P \subset \mathbb{R}^2$ and $\{z_1, \dots, z_n\} \subset \mathbb{R}^2$ be such that the assumptions (a) – (b) in Theorem 1 are satisfied. The collection of star shaped polygons P_η and $\mathcal{S}(z_1, \dots, z_n)$ are Gabor sampling trajectory for $M^p(\mathbb{R})$.*

Proof: Take a line $\ell \subset \mathbb{R}^2$ that contains one of the edges of P (resp. that contains the line segment $s(z_1, z_2)$) and consider the collection $\{\eta k \ell\}_{k \in \mathbb{N}}$. If $V_g f|_{P_\eta} = 0$ (resp. $V_g f|_{\mathcal{S}(z_1, \dots, z_n)} = 0$), then, as $V_g f$ is real analytic on any line $\eta k \ell$ and zero on a subset of nonzero measure, it follows that $V_g f|_{\{\eta k \ell\}_{k \in \mathbb{N}}} = 0$. Arguing as before, we get $\bigcup_{k \in \mathbb{N}} \widetilde{\text{supp}}(T_{k\eta} \mu(\beta)g) = \mathbb{R}$. Therefore, it follows that $f = 0$. \square

Corollary 22 *Let $g \in \text{span}\{h_n : n \in \mathbb{N}_0\}$, $\eta > 0$, and $1 \leq p < \infty$. The collection of concentric circles O_η is a Gabor sampling trajectory for $M^p(\mathbb{R})$.*

Proof: For $g = \sum_{k=0}^n \alpha_k h_k$, we denote by F the polyanalytic function of order n given by $F := \sum_{k=0}^n \alpha_k F_k$, where the functions F_0, \dots, F_n are given in (6). Then $V_g f(\bar{z}) = 0$ exactly when $F(z) = 0$. Multiplying F by z^n changes the zero set of F at most in the origin, and results in a reduced polyanalytic function. By assumption, and since $\overline{O_\eta} = O_\eta$ we hence have that $z^n F|_{O_\eta} = 0$. By Lemma 7, it thus follows that $F(z) = 0$ for every $z \in B_{R_0}(0)$, where R_0 can be chosen arbitrarily large. Consequently, $F(z) = 0$ for every $z \in \mathbb{C}$ which implies that $f = 0$ and O_η is a uniqueness set for $M_{1/\vartheta_s}^p(\mathbb{R})$. \square

Acknowledgement

The author would like to thank Felipe Negrera and José-Luis Romero for valuable discussions and suggesting some of the references. The author also acknowledges the support of the Austrian Science Fund (FWF) through the Erwin Schrödinger Fellowship J-4254.

- [1] L. D. Abreu and A. S. Bandeira. Landau's necessary density conditions for the Hankel transform. *J. Funct. Anal.*, 162:1845–1866, 2012.
- [2] L. D. Abreu and K. Gröchenig. Banach Gabor frames with Hermite functions: polyanalytic spaces from the Heisenberg group. *Appl. Anal.*, 91:1981–1997, 2012.
- [3] L. D. Abreu and M. Speckbacher. A planar large sieve and sparsity of time-frequency representations. In *Proceedings of SampTA*, 2017.
- [4] L. D. Abreu and M. Speckbacher. Donoho-Logan large sieve principles for modulation and polyanalytic Fock spaces. *Bull. Sci. Math.*, 2021.
- [5] S. T. Ali, J-P. Antoine, and J-P. Gazeau. Continuous frames in Hilbert spaces. *Ann. Phys.*, 222:1–37, 1993.
- [6] G. Ascensi. Sampling measures for the Gabor transform. *J. Approx. Theory*, 200:40–67, 2015.
- [7] M. B. Balk. *Complex Analysis I*, chapter Polyanalytic Functions and Their Generalizations, pages 197–253. Springer Berlin, 1997.

- [8] J. J. Benedetto and H.-C. Wu. Nonuniform sampling and spiral MRI reconstruction. *Proc. SPIE Symp. Wavelets Applications in Signal and Image Processing VIII*, 2000.
- [9] A. Beurling. Local harmonic analysis with some applications to differential operators. In *Some Recent Advances in the Basic Sciences, Proc. Annual Sci. Conf., Belfer Grad. School Sci., Yeshiva Univ., New York*, 1962.
- [10] A. Beurling. On functions with a spectral gap. Seminar on Harmonic Analysis, Univ. of Uppsala, 1942. In *Collected works of Arne Beurling: Volume II Harmonic Analysis*. Birkhäuser, Boston, 1989.
- [11] O. Christensen. *An Introduction to Frames and Riesz Bases*. Applied and Numerical Harmonic Analysis. Birkhäuser, 2003.
- [12] G. B. Folland. *Harmonic Analysis in Phase Space*. Princeton University Press, Princeton, 1989.
- [13] K. Gröchenig. *Foundations of Time-Frequency Analysis*. Appl. Numer. Harmon. Anal. Birkhäuser Boston, 2001.
- [14] K. Gröchenig, J. L. Romero, J. Unnikrishnan, and M. Vetterli. On minimal trajectories for mobile sampling of bandlimited fields. *Appl. Comp. Harmonic Anal.*, 39:487–510, 2015.
- [15] K. Gröchenig and G. Zimmermann. Spaces of testfunctions via the STFT. *J. Funct. Spaces Appl.*, 2(1):25–53, 2004.
- [16] A. Hartmann, D. Kamissoko, S. Konate, and M A. Orsoni. Dominating sets in Bergman spaces and sampling constants. *J. Math. Anal. Appl.*, 495(2):124755, 2021.
- [17] M. S. Jakobsen. On a (no longer) new Segal algebra: A review of the Feichtinger algebra. *J. Fourier Anal. Appl.*, 24:1579–1660, 2018.
- [18] P. Jaming, F. Negreira, and J. L. Romero. The Nyquist sampling rate for spiraling curves. *Appl. Comp. Harmonic Anal.*, 52:198–230, 2020.
- [19] P. Jaming and M. Speckbacher. Planar sampling sets for the short-time Fourier transform. *Constr. Approx.*, 2020.

- [20] B. Jaye and M. Mitkowski. A sufficient condition for mobile sampling in terms of surface density. *arXiv:2103.06340v1*, 2021.
- [21] O. Kovrijkine. Some results related to the Logvinenko-Sereda theorem. *Proc. Amer. Math. Soc.*, 129(10):3037–3047, 2001.
- [22] H. J. Landau. Necessary density conditions for sampling and interpolation of certain entire functions. *Acta Math.*, 37–52(117), 1967.
- [23] V. N. Logvinenko and Y. F. Sereda. Equivalent norms in spaces of entire functions of exponential type. *Teor. Funktsii, Funktsional. Anal. i Prilozhen*, 19:234–246, 1973.
- [24] D. H. Luecking. Inequalities on Bergman spaces. *Illinois J. Math.*, 25(1):1–11, 1981.
- [25] D. H. Luecking. Sampling measures for the Bergman space on the unit disc. *Math. Annalen*, 316(4):659–679, 2000.
- [26] J. Ortega-Cerdá. Sampling measures. *Publ. Mat.*, 42:559–566, 1998.
- [27] D. Preiss. Geometry of measures in \mathbb{R}^n : distribution, rectifiability, and densities. *Ann. Math.*, 125:537–643, 1987.
- [28] A. Rahimi, A. Najati, and Y. N. Dehghan. Continuous frames in Hilbert spaces. *Methods Funct. Anal. Topol.*, 12(2):170–182, 2006.
- [29] J. Ramanathan and T. Steger. Incompleteness of sparse coherent states. *Appl. Comp. Harmon. Anal.*, 2(2):148–153, 1995.
- [30] A. Rashkovskii, A. Ulanovskii, and I. Zlotnikov. On 2-dimensional mobile sampling. *arXiv: 2005.11193v1*, 2020.
- [31] K. Seip. Beurling type density theorems in the unit disk. *Invent. Math.*, 113:21–39, 1993.
- [32] K. Seip. *Interpolation and Sampling in Spaces of Analytic Functions*, volume 33 of *University Lecture Series*. American Mathematical Society, Providence, 2004.
- [33] W. Sun and X. Zhou. Irregular Gabor frames and their stability. *Proc. Amer. Math. Soc.*, 131(9):2883–2893, 2002.

- [34] J. Unnikrishnan and M. Vetterli. Sampling and reconstruction on spatial fields using mobile sensors. *IEEE Trans. Signal Process.*, 61(9):2338–2340, 2013.
- [35] J. Unnikrishnan and M. Vetterli. Sampling high-dimensional band-limited fields on low dimensional manifolds. *IEEE Trans. Inform. Theory*, 59(4):2103–2127, 2013.
- [36] A. I. Zayed. *Advances in Shannon’s Sampling Theory*. CRC Press, 1993.