

Error-free approximation of explicit linear MPC through lattice piecewise affine expression [★]

Jun Xu ^{a,b}, Yunjiang Lou ^a, Bart De Schutter ^c, Zhenhua Xiong ^d

^a*School of Mechanical Engineering and Automation, Harbin Institute of Technology, Shenzhen*

^b*Key Laboratory of System Control and Information Processing, Ministry of Education, Shanghai*

^c*Delft Center for Systems and Control, Delft University of Technology, The Netherlands*

^d*State Key Laboratory of Mechanical Systems and Vibration, Shanghai Jiao Tong University, Shanghai, China*

Abstract

In this paper, the disjunctive and conjunctive lattice piecewise affine (PWA) approximations of explicit linear model predictive control (MPC) are proposed. The training data are generated uniformly in the domain of interest, consisting of the state samples and corresponding affine control laws, based on which the lattice PWA approximations are constructed. Re-sampling of data is also proposed to guarantee that the lattice PWA approximations are identical to the explicit MPC control law in the unique order (UO) regions containing the sample points as interior points. Additionally, if all the distinct affine functions have been sampled, the disjunctive lattice PWA approximation constitutes a lower bound while the conjunctive lattice PWA approximation formulates an upper bound of the original optimal control law. The equivalence of the two lattice PWA approximations then guarantees that the approximations are error-free in the domain of interest, which is tested through a statistical guarantee. The complexity of the entire procedure is analyzed, which is polynomial with respect to the number of samples. The performance of the proposed approximation strategy is tested through two simulation examples, and the results show that with a moderate number of sample points, we can construct lattice PWA approximations that are equivalent to the optimal control law of the explicit linear MPC.

Key words: linear MPC; lattice piecewise affine; error-free approximation.

1 Introduction

Model predictive control (MPC) is currently the most popular control methodology employed in process control and its impact on industry has been recognized widely [1]. In MPC, the control action is calculated through solving a finite-horizon open-loop optimal control problem at each sampling instant, which is compu-

tationally expensive and only suitable for systems with slow dynamics. Therefore, for fast dynamical systems, in order to use MPC, the complexity of the online optimization should be reduced. A natural thought is to move the online optimization offline, which is the idea of explicit MPC. Explicit MPC was first introduced in [2], in which the linear MPC problem is formulated as a multi-parametric quadratic programming (mpQP) problem and solved offline. The optimal control law is proved to be continuous piecewise affine (PWA) with respect to the state. The subregions as well as the corresponding affine functions defined on them are recorded. For online implementation, given the current state, one must only find the subregion in which the state lies, and the function evaluation of the corresponding affine function gives rise to the optimal control law.

However, the offline construction of such subregions, the memory required to store them, and the online search for the right subregion are the main limitations of explicit MPC [3]. Much work has been done to solve these three

[★] This work was supported in part by the National Natural Science Foundation of China under Grant U1813224, 62173113, and in part by the Science and Technology Innovation Committee of Shenzhen Municipality under Grant GXWD20201230155427003-20200821173613001, JCYJ20200109113412326. The material in this paper was partially presented at the 60th IEEE Conference on Decision and Control, December 13-17, 2021, Austin, Texas, USA.

Email addresses: xujungy@gmail.com (Jun Xu), louyj@hit.edu.cn (Yunjiang Lou), b.deschutter@tudelft.nl (Bart De Schutter), mexiong@sjtu.edu.cn (Zhenhua Xiong).

problems. To overcome the complex offline geometric computations, combinatorial approaches are proposed that are based on implicitly enumerating all possible combinations of active constraints [4,5]. To reduce the memory required to store the subregions as well as the control laws, region-free explicit MPC is proposed [3,6]. Moreover, the online search complexity can be reduced by storing additional information [7,8], introducing an improved binary search tree (orthogonal truncated binary search tree) [9], or resorting to the method of convex lifting [10,11]. The lattice PWA representation has also been used to exactly express the explicit MPC control law, resulting in a much lower storage requirement [12,13]. As the complexity of solving the explicit MPC problem increases exponentially with the size of the optimization problem, all these methods can only alleviate the computational burden to some extent.

Another idea is to formulate the approximate MPC controller [14,15] or semi-explicit MPC controller [16]. In these methods, training data containing the values of states and corresponding optimal control laws of the MPC problem are generated, and the approximated controller is constructed using these data. In general, the samples are required to be distributed sufficiently evenly over the domain [17]. Different approaches have been used to generate the approximation, such as the canonical piecewise linear function [18], radial basis functions [19], wavelets [20], and so on. In addition, reinforcement learning has also been used to derive a data-driven MPC control law in [21]. In the work of [15], [20], and [22], the approximations are based on particular partitions of the domain of interest, and the interpolation based algorithm can be developed [23]. In fact, the partitions of the domain of interest employed in these works are different from the domain partitions in the explicit linear MPC law, e.g., the continuous PWA solution of the linear MPC problem has not been fully explored in the approximation.

To resemble explicit MPC control law to a larger extent, the information of the local affine functions of the linear explicit MPC is utilized to derive the lattice PWA approximation. In our previous work, the lattice PWA *representation* of the explicit MPC control law was derived, which however also scales poorly with the dimension of the parameters. In this paper, in order to handle more complex problems, we present an *error-free approximation* that consists of disjunctive and conjunctive lattice PWA approximations, which coincide with the explicit MPC control in a statistical sense. Moreover, the offline calculation complexity depends mainly on the number of sample points, which scales well with the state dimension. A preliminary thought of the disjunctive lattice PWA approximation of explicit linear MPC was presented in [24], in which the approximated control law is not guaranteed to be error-free. However, in this work, under mild assumptions, the equivalence of the disjunctive and conjunctive approximations guarantees that the

two approximations are identical to the optimal control law in the domain of interest. The approximation can also be simplified to further lower the storage requirements and online computational complexity.

The rest of this paper is organized as follows. Section 2 gives the preliminaries about the explicit linear MPC problem and the lattice PWA expression. The offline approximations of the explicit linear MPC control law through the lattice PWA expression are given in detail in Section 3, in which the sampling and re-sampling procedures, as well as the simplification of the approximation are provided. In Section 4, the approximation error and the complexity of the proposed procedure are analyzed. Section 5 provides the simulation results and the paper ends with conclusions and plans for future work in Section 6.

2 Preliminaries

2.1 Explicit linear MPC problem

In particular, MPC for a discrete-time linear time-invariant system can be cast as the following optimization problem at time step t :

$$\min_U \left\{ J(U, \mathbf{x}_0) = v_{N_p}(\mathbf{x}_{N_p}) + \sum_{k=0}^{N_p-1} v(\mathbf{x}_k, \mathbf{u}_k) \right\} \quad (1a)$$

$$\text{s.t. } \mathbf{x}_{k+1} = A\mathbf{x}_k + B\mathbf{u}_k, k = 0, \dots, N_p - 1 \quad (1b)$$

$$(\mathbf{x}_k, \mathbf{u}_k) \in \mathcal{G}, k = 0, \dots, N_p - 1 \quad (1c)$$

$$\mathbf{x}_{N_p} \in \mathcal{F} \quad (1d)$$

in which the optimized variable is $U = [\mathbf{u}_0^T, \dots, \mathbf{u}_{N_p-1}^T]^T$, N_p is the prediction horizon, the variables $\mathbf{x}_k \in \mathbb{R}^{n_x}$ and $\mathbf{u}_k \in \mathbb{R}^{n_u}$ denote the predicted state and input at time step k , respectively, using (1b). The terminal penalty is denoted as v_N and $v(\cdot, \cdot)$ is the stage cost; \mathcal{G} and \mathcal{F} are full-dimensional polyhedral sets of appropriate dimensions. In this paper, we assume a strictly convex cost, i.e., $v_N = \mathbf{x}_N^T Q_N \mathbf{x}_N$, $v(\mathbf{x}_k, \mathbf{u}_k) = \mathbf{x}_k^T Q_k \mathbf{x}_k + \mathbf{u}_k^T Q_u \mathbf{u}_k$, in which $Q_u \succ 0$, $Q_k, Q_N \succeq 0$. After solving the optimization problem (1), the optimal $U^* = [(\mathbf{u}_0^*)^T, \dots, (\mathbf{u}_{N_p-1}^*)^T]^T$ is obtained, and only \mathbf{u}_0^* is applied to the system. The optimization problem is subsequently reformulated and solved at the next time steps $t = 1, 2, \dots$ by updating the given state vector \mathbf{x}_0 .

It has been proved in [2] that the solution U^* is a *continuous PWA function* of the state \mathbf{x}_0 , and we use \mathbf{x} instead hereafter in this paper. In fact, this conclusion is

obtained through solving an mpQP problem of the form

$$\begin{aligned} \min_U \quad & \frac{1}{2}U^T H U + \mathbf{x}^T F U \\ \text{s.t.} \quad & G U \leq \mathbf{w} + E \mathbf{x} \end{aligned} \quad (2)$$

where $U \in \mathbb{R}^{N_p \cdot n_u}$ is the vector of optimization variables, the parameter vector is $\mathbf{x} \in \mathbb{R}^{n_x}$, and the matrices H, F, G , and E are calculated through the optimization problem (1) [2]. Under the assumption that $Q_k, Q_N \succeq 0, Q_u \succ 0$, we have $H \succ 0$.

The definition of a continuous PWA function as well as the lemma concerning the continuous PWA property of the solution to the mpQP problem is presented as follows.

Definition 1 [25] *A function $f : \Omega \rightarrow \mathbb{R}^m$, where $\Omega \subset \mathbb{R}^{n_x}$ is convex, is said to be continuous PWA if it is continuous on the domain Ω and the following conditions are satisfied:*

- (1) *The domain space Ω is divided into a finite number of nonempty convex polyhedra, i.e., $\Omega = \cup_{i=1}^{\hat{N}} \Omega_i$, $\Omega_i \neq \emptyset$, the polyhedra are closed and have non-overlapping interiors, $\text{int}(\Omega_i) \cap \text{int}(\Omega_j) = \emptyset$, $\forall i, j \in \{1, \dots, \hat{N}\}, i \neq j$. These polyhedra are also called local regions. The boundaries of the polyhedra are nonempty sets in $(n-1)$ -dimensional space.*
- (2) *In each local region Ω_i , f equals a local affine function $u_{\text{loc}(i)}$:*

$$f(\mathbf{x}) = u_{\text{loc}(i)}(\mathbf{x}), \quad \forall \mathbf{x} \in \Omega_i.$$

Lemma 2 [2] *Considering the mpQP problem (2) and assuming that $H \succ 0$, then the set of feasible parameters $\Omega \subset \mathbb{R}^{n_x}$ is convex, the optimizer $U^* : \Omega \rightarrow \mathbb{R}^{N_p \cdot n_u}$ is continuous PWA, and the value function $J^* : \Omega \rightarrow \mathbb{R}$ is continuous convex and piecewise quadratic.*

The details of constructing such continuous PWA function are given as follows.

First, the mpQP problem can be rewritten in the form

$$\begin{aligned} \min_{\mathbf{z}} \quad & \frac{1}{2} \mathbf{z}^T H \mathbf{z} \\ \text{s.t.} \quad & G \mathbf{z} \leq \mathbf{w} + S \mathbf{x} \end{aligned} \quad (3)$$

by letting $\mathbf{z} = U + H^{-1} F^T \mathbf{x}$ and $S = E + G H^{-1} F^T$. Once the optimal solution \mathbf{z}^* of the optimization problem (3) is available, we can easily obtain the optimal U^* as

$$U^* = \mathbf{z}^* - H^{-1} F^T \mathbf{x}.$$

The optimal solution \mathbf{z}^* for a fixed \mathbf{x} is fully characterized by the Karush-Kuhn-Tucker (KKT) conditions:

$$H \mathbf{z}^* + G_{\mathcal{A}^*}^T \boldsymbol{\lambda}^* + G_{\mathcal{N}^*}^T \boldsymbol{\mu}^* = 0 \quad (4a)$$

$$G_{\mathcal{A}^*} \mathbf{z}^* = \mathbf{w}_{\mathcal{A}^*} + S_{\mathcal{A}^*} \mathbf{x} \quad (4b)$$

$$G_{\mathcal{N}^*} \mathbf{z}^* < \mathbf{w}_{\mathcal{N}^*} + S_{\mathcal{N}^*} \mathbf{x} \quad (4c)$$

$$\boldsymbol{\lambda}^* \geq 0 \quad (4d)$$

$$\boldsymbol{\mu}^* \geq 0 \quad (4e)$$

$$\boldsymbol{\lambda}^{*T} (G_{\mathcal{A}^*} \mathbf{z}^* - \mathbf{w}_{\mathcal{A}^*} - S_{\mathcal{A}^*} \mathbf{x}) = 0 \quad (4f)$$

$$\boldsymbol{\mu}^{*T} (G_{\mathcal{N}^*} \mathbf{z}^* - \mathbf{w}_{\mathcal{N}^*} - S_{\mathcal{N}^*} \mathbf{x}) = 0 \quad (4g)$$

in which (4b) and (4c) are the active and inactive constraints at \mathbf{z}^* , respectively. Assuming that $G \in \mathbb{R}^{p \times N_p \cdot n_u}$, $\mathbf{w} \in \mathbb{R}^p$, $S \in \mathbb{R}^{p \times n_x}$, and G_i, w_i , and S_i denote the i -th row of G, w , and S , respectively, the active as well as inactive index sets can be written as

$$\mathcal{A}^* = \{j \in \{1, \dots, p\} | G_j \mathbf{z}^* = w_j + S_j \mathbf{x}\}$$

and

$$\mathcal{N}^* = \{j \in \{1, \dots, p\} | G_j \mathbf{z}^* < w_j + S_j \mathbf{x}\},$$

respectively. It is apparent that $\mathcal{A}^* = \{1, \dots, p\} \setminus \mathcal{N}^*$. For an inactive constraint j , we have $\boldsymbol{\mu}_j^* = 0$. For a particular \mathcal{A}^* , and assume $G_{\mathcal{A}^*}$ is full row rank, we have

$$\boldsymbol{\lambda}^* = -(G_{\mathcal{A}^*} H^{-1} G_{\mathcal{A}^*}^T)^{-1} (\mathbf{w}_{\mathcal{A}^*} + S_{\mathcal{A}^*} \mathbf{x}), \quad (5)$$

as well as

$$\mathbf{z}^* = H^{-1} G_{\mathcal{A}^*}^T (G_{\mathcal{A}^*} H^{-1} G_{\mathcal{A}^*}^T)^{-1} (\mathbf{w}_{\mathcal{A}^*} + S_{\mathcal{A}^*} \mathbf{x}). \quad (6)$$

The local region for which the local affine function (6) is defined is called *critical region*, and it can be constructed by the constraints of primal feasibility (4c) and dual feasibility (4d).

Remark 3 *For the case in which $G_{\mathcal{A}^*}$ is not full row rank, i.e., the rows of $G_{\mathcal{A}^*}$ are linearly dependent, the linear independence constraints qualification (LICQ) is violated according to [26], and this is referred to as primary degeneracy [2] (dual degeneracy cannot occur as $H \succ 0$). Assuming that the rank of $G_{\mathcal{A}^*}$ is r , we can then arbitrarily select r independent constraints, and proceed with the new reduced active index set [27].*

To search for all the local affine functions and critical regions, one must enumerate all possible active index sets \mathcal{A}^* , apply the KKT conditions accordingly, and then the continuous PWA control law can be obtained. In the next subsection, the lattice PWA representation is presented, which is used to express the resulting continuous PWA control law in our previous work [13].

2.2 Lattice PWA representation

It is stated in [13] that any continuous PWA function can be represented by the lattice PWA representation.

Lemma 4 [13] *Letting f be a continuous PWA function defined in Definition 1, then f can be represented as*

$$f(\mathbf{x}) = f_{L,d}(\mathbf{x}) = \max_{i=1,\dots,N} \min_{j \in I_{\geq,i}} u_j(\mathbf{x}), \quad \forall \mathbf{x} \in \Gamma, \quad (7)$$

or

$$f(\mathbf{x}) = f_{L,c}(\mathbf{x}) = \min_{i=1,\dots,N} \max_{j \in I_{\leq,i}} u_j(\mathbf{x}), \quad \forall \mathbf{x} \in \Gamma, \quad (8)$$

in which $I_{\geq,i} = \{j | u_j(\mathbf{x}) \geq u_i(\mathbf{x}), \forall \mathbf{x} \in \Gamma_i\}$, $I_{\leq,i} = \{j | u_j(\mathbf{x}) \leq u_i(\mathbf{x}), \forall \mathbf{x} \in \Gamma_i\}$, and the expressions $\min_{j \in I_{\geq,i}} u_j(\mathbf{x})$ and $\max_{j \in I_{\leq,i}} u_j(\mathbf{x})$ are called terms of $f_{L,d}$ and $f_{L,c}$, respectively. The affine function $u_j(\mathbf{x})$ is called a literal. The region Γ_i is a **unique order (UO) region** that is subset of the local region and the order of the affine functions

$$u_1(\mathbf{x}), \dots, u_N(\mathbf{x}), \quad (9)$$

remains unchanged in the interior of Γ_i . The expressions (7) and (8) are called full disjunctive and conjunctive lattice PWA representations, respectively, in which the names “disjunctive” and “conjunctive” come from the terminology in Boolean algebra.

Considering a two-dimensional continuous PWA function (10) with four affine pieces, Fig. 1 illustrates the UO region and corresponding PWA function.

Example 5

$$f = \begin{cases} \ell_1(\mathbf{x}) = -x_2 + 1 & \text{if } \mathbf{x} \in \Gamma_1, \\ \ell_2(\mathbf{x}) = -x_1 + 1 & \text{if } \mathbf{x} \in \Gamma_2, \\ \ell_3(\mathbf{x}) = x_2 + 1 & \text{if } \mathbf{x} \in \Gamma_3, \\ \ell_4(\mathbf{x}) = x_1 + 1 & \text{if } \mathbf{x} \in \Gamma_4. \end{cases} \quad (10)$$


The polyhedral regions $\Gamma_1, \Gamma_2, \Gamma_3, \Gamma_4$, and the two-dimensional function f are shown in Fig. 1.

The regions $\Gamma_1, \Gamma_2, \Gamma_3$, and Γ_4 are local affine regions, and can be divided into UO regions $\Gamma_{11}, \Gamma_{12}, \dots, \Gamma_{41}$, and Γ_{42} . Taking the UO region Γ_{31} as an example, the order of affine functions is


$$\ell_3 < \ell_2 < \ell_1 < \ell_4.$$

For this continuous PWA function, as it is concave, both the disjunctive and conjunctive lattice PWA representations are

$$f = \min\{\ell_1, \ell_2, \ell_3, \ell_4\}.$$



(a) Function.



(b) Regions.

Fig. 1. Continuous PWA function in Example 5.

According to Lemma 4, we can represent a continuous PWA control law using a lattice PWA function (either disjunctive or conjunctive). The disjunctive lattice PWA representation of explicit linear MPC was investigated in [12] and [13], in which the continuous PWA control law was obtained through the MPT3 toolbox [28] in advance. However, as explained in Section 2.1, for problems with a large number of constraints and a high-dimensional state, the number of possible combinations of active constraints increases exponentially and the derivation of the explicit MPC solution is extremely computationally expensive. Hence, in this paper, we propose an approximated continuous PWA control law by sampling only a set of states in the domain of interest. We show that this approximation utilizes the local affine property of the original explicit MPC control law and is identical to the original control law at the sample points and in the UO regions the sample points lie. In addition, under mild assumptions, the lattice PWA approximations are identical to the explicit MPC control law in the domain of interest.

3 Lattice PWA approximation of explicit linear MPC control law

3.1 Generation of sample points in the interior of UO regions

As indicated in Lemma 2, the explicit linear MPC control law U^* is a continuous PWA function with respect to the state \mathbf{x} . Then the first element of U^* , which is \mathbf{u}_0^* , is also a continuous PWA function of \mathbf{x} , i.e., \mathbf{u}_0^* is affine in the local regions that \mathbf{x} lies in. For simplicity, we omit the subscript in \mathbf{u}_0^* hereafter in the paper, and use \mathbf{u}^* instead. The sample points $(\mathbf{x}_i, \mathbf{u}_i(\mathbf{x}_i)) \in \mathcal{X}_1 \times \mathcal{U}_1$ are generated in the domain of feasible parameters, in which $\mathbf{u}_i(\mathbf{x})$ is the affine function at \mathbf{x}_i such that

$$\mathbf{u}_i(\mathbf{x}_i) = \mathbf{u}^*(\mathbf{x}_i).$$

For simplicity, we consider the case $n_u = 1$; note however that the proposed methodology can be easily extended to the case when $n_u > 1$. Moreover, the domain of interest is assumed to be a hyperbox.

In this subsection, the training points $\mathbf{x}_i \in \mathcal{X}_1$ are required to be in the interior of UO regions, i.e., $\mathbf{x}_i \in \text{int}(\Gamma(\mathbf{x}_i))$, in which $\Gamma(\mathbf{x}_i)$ is the corresponding UO region. This means that if $u_{j_1}(\mathbf{x}_i) > u_{j_2}(\mathbf{x}_i)$ holds, then we have

$$u_{j_1}(\mathbf{x}) > u_{j_2}(\mathbf{x}), \forall \mathbf{x} \in \Gamma(\mathbf{x}_i).$$

As a matter of fact, if there are no affine functions $u_{j_1}(\mathbf{x})$ and $u_{j_2}(\mathbf{x})$ such that $u_{j_1}(\mathbf{x}_i) = u_{j_2}(\mathbf{x}_i)$, then $\mathbf{x}_i \in \text{int}(\Gamma(\mathbf{x}_i))$. If there is a point \mathbf{x}_i that is not in the interior of the corresponding UO region, i.e., there exist j_1, j_2 , such that $u_{j_1}(\mathbf{x}_i) = u_{j_2}(\mathbf{x}_i)$, then a perturbation should be applied, i.e., $\mathbf{x}_i = \mathbf{x}_i + \delta$, such that \mathbf{x}_i is in the interior of the UO region. This will be shown in Example 12 in Section 3.3. It will be shown in Lemma 7 that the condition that \mathbf{x}_i is in the interior of UO regions is required for the equivalence of lattice PWA approximations and the original optimal control law in UO regions.

It should be noted that for the checking of UO regions, only the information of sampled affine functions is needed, and the global information of the PWA function is unknown, e.g., whether there is some u_j that has not been sampled or how these sampled affine functions are connected.

Algorithm 1 describes the sampling of training points.

Algorithm 1 *Sampling of training points in explicit linear MPC control law.*

Input: Linear MPC problem, the number of sample points N_1 , sample domain Ω .

Output: Sample data set $\mathcal{X}_1 \times \mathcal{U}_1$.

- 1: $\mathcal{X}_1 = \emptyset, \mathcal{U}_1 = \emptyset$.
 - 2: **for** $i = 1$ to N_1 **do**
 - 3: Generate a grid point \mathbf{x}_i in Ω .
 - 4: **if** \mathbf{x}_i is not an interior point of some UO region **then**
 - 5: Apply a perturbation until \mathbf{x}_i is an interior point of $\Gamma(\mathbf{x}_i)$.
 - 6: **end if**
 - 7: Solve corresponding QP problem (3) by letting $\mathbf{x} = \mathbf{x}_i$.
 - 8: Determine active and inactive index sets \mathcal{A}^* and \mathcal{N}^* , respectively.
 - 9: Solve KKT conditions (4) to obtain the affine function \mathbf{z}_i^* through (6).
 - 10: Obtain optimal input, i.e., $U_i(\mathbf{x}_i)$ and $u_i(\mathbf{x}_i)$.
 - 11: **end for**
-

For a feasible state \mathbf{x}_i , line 7 in Algorithm 1 states that the optimal $\mathbf{z}_i^* = U_i^* + H^{-1}F^T \mathbf{x}_i$ can be obtained through the QP problem (3), which, together with the information of \mathbf{x}_i , determines the active and inactive constraints (4b) and (4c), respectively. Therefore, the index set \mathcal{A}_i^* as well as \mathcal{N}_i^* is fixed, and if the matrix $G_{\mathcal{A}_i^*}$ is full row rank, the affine function $\mathbf{z}_i(\mathbf{x}_i)$ can be calculated through (6) (the rank-deficient case can be handled as indicated in Remark 3). Then we have

$$U_i(\mathbf{x}_i) = \mathbf{z}_i^*(\mathbf{x}_i) - H^{-1}F^T \mathbf{x}_i, \quad (11)$$

and

$$u_i(\mathbf{x}_i) = \left[\mathbf{I}_{n_u \times n_u} \ \mathbf{0} \ \cdots \ \mathbf{0} \right] U_i(\mathbf{x}_i) \quad (12)$$

in which $\mathbf{I}_{n_u \times n_u}$ is the identity matrix with size $n_u \times n_u$.

After evaluating Algorithm 1, we can obtain the sample dataset $\mathcal{X}_1 \times \mathcal{U}_1$, in which \mathcal{U}_1 is a set of affine functions $u_i(\mathbf{x}_i)$. It is noted that compared with ordinary sampling, in which only the evaluation of $u_i^*(\mathbf{x}_i)$ is available, here the corresponding affine function is also recorded, which can be used for the lattice PWA approximation in Section 3.2.

3.2 Lattice PWA approximation based on sample points

We now derive both the disjunctive and conjunctive lattice PWA approximations based on the sample dataset $\mathcal{X}_1 \times \mathcal{U}_1$.

The disjunctive lattice PWA approximation is constructed via the sample points and can be expressed as follows:

$$\hat{f}_{L,d}(\mathbf{x}) = \max_{i=1,\dots,N_1} \min_{j \in J_{\geq,i}} u_j(\mathbf{x}), \quad (13)$$

in which the index set $J_{\geq,i}$ is described as

$$J_{\geq,i} = \{j | u_j(\mathbf{x}_i) \geq u_i(\mathbf{x}_i)\}. \quad (14)$$

Similarly, the conjunctive lattice PWA approximation can be described as follows:

$$\hat{f}_{L,c}(\mathbf{x}) = \min_{i=1,\dots,N_1} \max_{j \in J_{\leq,i}} u_j(\mathbf{x}), \quad (15)$$

in which the index set $J_{\leq,i}$ is described as

$$J_{\leq,i} = \{j | u_j(\mathbf{x}_i) \leq u_i(\mathbf{x}_i)\}. \quad (16)$$

Compared with the full disjunctive and conjunctive lattice PWA representations (7) and (8), respectively, we can see that the lattice PWA approximations (13) and (15) only consider the order of local affine control laws at each sample point. Under certain conditions as shown in Assumption 6, the lattice PWA approximations (13) and (15) coincide with the explicit linear MPC control law at the sample points.

Assumption 6 *The terms in both disjunctive and conjunctive lattice PWA approximations satisfy,*

$$\min_{j \in J_{\geq,i}} u_j(\mathbf{x}_k) \leq u_k(\mathbf{x}_k), \forall i, k \in \{1, \dots, N_1\} \quad (17)$$

and

$$\max_{j \in J_{\leq,i}} u_j(\mathbf{x}_k) \geq u_k(\mathbf{x}_k), \forall i, k \in \{1, \dots, N_1\} \quad (18)$$

Lemma 7 *Assume that the disjunctive and conjunctive lattice PWA approximations are constructed through (13) and (15), respectively. Supposing that Assumption 6 holds, then we have*

$$\hat{f}_{L,d}(\mathbf{x}) = u^*(\mathbf{x}), \forall \mathbf{x} \in \Gamma(\mathbf{x}_i), \forall \mathbf{x}_i \in \mathcal{X}_1 \quad (19)$$

and

$$\hat{f}_{L,c}(\mathbf{x}) = u^*(\mathbf{x}), \forall \mathbf{x} \in \Gamma(\mathbf{x}_i), \forall \mathbf{x}_i \in \mathcal{X}_1. \quad (20)$$

PROOF.

We first prove (19) for the disjunctive case.

As all the sample points \mathbf{x}_i are interior points for some UO regions, according to (17), we have

$$\min_{j \in J_{\geq,k}} u_j(\mathbf{x}) \leq u_i(\mathbf{x}), \forall i, k \in \{1, \dots, N_1\}, \forall \mathbf{x} \in \Gamma(\mathbf{x}_i)$$

Besides, the equality holds for $i = k$, i.e.,

$$\min_{j \in J_{\geq,i}} u_j(\mathbf{x}) = u_i(\mathbf{x}), \forall i \in \{1, \dots, N_1\}, \forall \mathbf{x} \in \Gamma(\mathbf{x}_i).$$

Combining with the disjunctive lattice PWA approximation (13), we have

$$\hat{f}_{L,d}(\mathbf{x}) = u_i(\mathbf{x}), \forall k \in \{1, \dots, N_1\}, \forall \mathbf{x} \in \Gamma(\mathbf{x}_i).$$

As $u^*(\mathbf{x}) = u_i(\mathbf{x}), \forall i \in \{1, \dots, N_1\}, \forall \mathbf{x} \in \Gamma(\mathbf{x}_i)$, we then have (19).

The conjunctive case can be proved similarly.

Remark 8 *It is noted that the lattice PWA approximation differs from the other approximations in that the lattice PWA approximation equals the original control law not only at the sample points, but also in the UO regions containing the sample points as interior points, as (19) and (20) show. To achieve this, for each sample point, not only is the value of the corresponding control law recorded, but the specific affine expression is as well, as Algorithm 1 shows.*

3.3 Re-sampling

In general, when we generate a moderate number of sample points, (17) and (18) hold. However, there are situations when the two inequalities are not valid, the following gives the resampling method such that both (17) and (18) hold.

3.3.1 Guaranteeing the validity of Assumption 6

Taking the disjunctive lattice PWA approximation as an example, if (17) is violated for some $\mathbf{x}_\alpha, \mathbf{x}_\beta \in \mathcal{X}_1$, i.e.,

$$\min_{j \in J_{\geq,\alpha}} u_j(\mathbf{x}_\beta) > u^*(\mathbf{x}_\beta) = u_\beta(\mathbf{x}_\beta), \quad (21)$$

we can add sample points in the line segment

$$\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta) = \lambda \mathbf{x}_\alpha + (1 - \lambda) \mathbf{x}_\beta, \lambda \in (0, 1) \quad (22)$$

such that (17) is satisfied for α and \mathbf{x}_β , which is shown in Lemma 9.

Lemma 9 *Assuming that there are two points \mathbf{x}_α and \mathbf{x}_β such that (21) holds, then there must be some point $\mathbf{x}_\gamma \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$, which is defined in (22), and the corresponding control solution u_γ , such that the inequality*

$$u_\gamma(\mathbf{x}_\alpha) \geq u_\alpha(\mathbf{x}_\alpha), u_\gamma(\mathbf{x}_\beta) \leq u_\beta(\mathbf{x}_\beta), \quad (23)$$

holds.

Furthermore, by adding \mathbf{x}_γ to the sample dataset, we have

$$\min_{j \in J_{\geq,\alpha}} u_j(\mathbf{x}_\beta) \leq u_\beta(\mathbf{x}_\beta). \quad (24)$$

PROOF. As the optimal control solution u^* is continuous PWA, it is still continuous PWA when restricted to the line segment $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$.

Defining an index set $\text{aff}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$ as

$$\text{aff}(\mathbf{x}_\alpha, \mathbf{x}_\beta) = \{j | \exists \mathbf{x} \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta) \text{ such that } u^*(\mathbf{x}) = u_j(\mathbf{x})\},$$

i.e., the index set $\text{aff}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$ includes all the indices of affine functions in $u^*(x)$ when restricted to $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$.

According to [13], we have

$$\min_{j \in S_{\geq, \alpha}} u_j(\mathbf{x}) \leq u_\beta(\mathbf{x}_\beta), \forall \mathbf{x} \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta),$$

in which $S_{\geq, \alpha}$ is the index set such that

$$S_{\geq, \alpha} = \{j \in \text{aff}(\mathbf{x}_\alpha, \mathbf{x}_\beta) | u_j(\mathbf{x}_\alpha) \geq u_\alpha(\mathbf{x}_\alpha)\}.$$

Apparently, there should be some $\gamma \in S_{\geq, \alpha}$, such that (23) is valid.

Therefore, if we add one of these \mathbf{x}_γ to the sample point set, we have

$$\gamma \in S_{\geq, \alpha} \subset J_{\geq, \alpha}.$$

Hence (24) is valid.

It is noted that for the case when (18) is violated, we have similar results.

Corollary 10 *Assuming that there are two points \mathbf{x}_α and \mathbf{x}_β such that the following inequality holds:*

$$\max_{j \in J_{\leq, \alpha}} u_j(\mathbf{x}_\beta) < u^*(\mathbf{x}_\beta) = u_\beta(\mathbf{x}_\beta), \quad (25)$$

then there must be some point $\mathbf{x}_\gamma \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$, and the corresponding control solution u_γ satisfies the following inequality:

$$u_\gamma(\mathbf{x}_\alpha) \leq u_\alpha(\mathbf{x}_\alpha), u_\gamma(\mathbf{x}_\beta) \geq u_\beta(\mathbf{x}_\beta). \quad (26)$$

Additionally, by adding \mathbf{x}_γ to the sample dataset, we have

$$\max_{j \in J_{\leq, \alpha}} u_j(\mathbf{x}_\beta) \geq u_\beta(\mathbf{x}_\beta). \quad (27)$$

When (21) or (25) holds, in order to construct a continuous PWA function and to ensure the validity of (17) and (18) for every *sample point* in the line segment $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$, the line segment is recursively partitioned to generate new sample points, as Algorithm 2 shows.

Algorithm 2 *Recursive partitioning of line segment $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$ in case that (21) or (25) holds.*

Input: Linear MPC problem, initial sample dataset $\mathcal{X}_1 \times \mathcal{U}_1$, the line segment $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$.
Output: Additional sample dataset $\mathcal{X}_2 \times \mathcal{U}_2$.
1: Initialize flag = 1, $\mathcal{X}_2 = \emptyset$, $\mathcal{U}_2 = \emptyset$.
2: **while** flag **do**
3: $N_a = 0$;
4: **for** $\mathbf{x}_i \in \mathcal{X}_1 \cup \mathcal{X}_2$ **do**
5: Select corresponding $u_i(\mathbf{x}_i) \in \mathcal{U}_1 \cup \mathcal{U}_2$.
6: **if** $\text{sign}(u_i(\mathbf{x}_i) - u_{i+1}(\mathbf{x}_i)) = \text{sign}(u_i(\mathbf{x}_{i+1}) - u_{i+1}(\mathbf{x}_{i+1}))$ **then**
7: $N_a = N_a + 1$.
8: Add a point $\mathbf{x}_{\text{new}} = 0.5(\mathbf{x}_i + \mathbf{x}_{i+1})$ to \mathcal{X}_2 .
9: Calculate corresponding affine function $u^*(\mathbf{x}_{\text{new}})$ through lines 7-9 of Algorithm 1, add to \mathcal{U}_2 .
10: **end if**
11: **end for**
12: **if** $N_a = 0$ **then**
13: flag = 0.
14: **end if**
15: **end while**

Lemma 11 shows that, if we add points according to Algorithm 2, (17) and (18) are satisfied for all the sample points in $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$.

Lemma 11 *Given the line segment $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$ such that (21) or (25) holds, if we add points according to Algorithm 2, then we have*

$$\min_{j \in J_{\geq, i}} u_j(\mathbf{x}_k) \leq u_k(\mathbf{x}_k), \forall \mathbf{x}_i, \mathbf{x}_k \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta) \cap (\mathcal{X}_1 \cup \mathcal{X}_2) \quad (28)$$

and

$$\max_{j \in J_{\leq, i}} u_j(\mathbf{x}_k) \geq u_k(\mathbf{x}_k), \forall \mathbf{x}_i, \mathbf{x}_k \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta) \cap (\mathcal{X}_1 \cup \mathcal{X}_2). \quad (29)$$

PROOF. After evaluating Algorithm 2, the condition

$$(u_i(\mathbf{x}_i) - u_{i+1}(\mathbf{x}_i)) \cdot (u_i(\mathbf{x}_{i+1}) - u_{i+1}(\mathbf{x}_{i+1})) \leq 0 \quad (30)$$

is satisfied for all points $\mathbf{x}_i \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$, which corresponds to two cases as shown in Fig. 2. To generalize, here we only consider the case when $u_i \neq u_{i+1}$; for the case $u_i = u_{i+1}$, the affine function u_i can connect the two points. Then, we can construct a continuous PWA function connecting the two points \mathbf{x}_i and \mathbf{x}_{i+1} , i.e., $\min\{u_i, u_{i+1}\}$ for case 1 and $\max\{u_i, u_{i+1}\}$ for case 2.

Supposing that the constructed disjunctive and conjunctive continuous PWA functions connecting \mathbf{x}_α and \mathbf{x}_β




Fig. 2. Two cases satisfying (30).

are \hat{f}_1 and \hat{f}_2 , respectively, then we have

$$\hat{f}_1(\mathbf{x}_k) = \hat{f}_2(\mathbf{x}_k) = u_k(\mathbf{x}_k), \forall \mathbf{x}_k \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta) \cap (\mathcal{X}_1 \cup \mathcal{X}_2).$$

Defining the index sets $\text{aff}_1(\mathbf{x}_\alpha, \mathbf{x}_\beta)$ and $\text{aff}_2(\mathbf{x}_\alpha, \mathbf{x}_\beta)$ as

$$\text{aff}_1(\mathbf{x}_\alpha, \mathbf{x}_\beta) = \{j | \exists \mathbf{x} \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta) \text{ such that } \hat{f}_1(\mathbf{x}) = u_j(\mathbf{x})\},$$

and

$$\text{aff}_2(\mathbf{x}_\alpha, \mathbf{x}_\beta) = \{j | \exists \mathbf{x} \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta) \text{ such that } \hat{f}_2(\mathbf{x}) = u_j(\mathbf{x})\},$$

we then have

$$\min_{j \in J_{\geq, i} \cap \text{aff}_1(\mathbf{x}_\alpha, \mathbf{x}_\beta)} u_j(\mathbf{x}_k) \leq u_k(\mathbf{x}_k) \quad \forall \mathbf{x}_i, \mathbf{x}_k \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta) \cap (\mathcal{X}_1 \cup \mathcal{X}_2)$$

and

$$\max_{j \in J_{\leq, i} \cap \text{aff}_2(\mathbf{x}_\alpha, \mathbf{x}_\beta)} u_j(\mathbf{x}_k) \geq u_k(\mathbf{x}_k) \quad \forall \mathbf{x}_i, \mathbf{x}_k \in \mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta) \cap (\mathcal{X}_1 \cup \mathcal{X}_2).$$

According to the above inequalities, we have (28) and (29).

Algorithm 2 can be run repeatedly until, for all the sample points $(\mathbf{x}_i, u_i) \in (\mathcal{X}_1 \cup \mathcal{X}_2) \times (\mathcal{U}_1 \cup \mathcal{U}_2)$, we have (17) and (18); thus Assumption 6 is satisfied and the resulting lattice PWA approximation equals the original control solution at all sample points and in the UO containing the sample points as interior points, as Lemma 7 shows.

A simple one-dimensional example is used to illustrate the process of constructing the disjunctive and conjunctive lattice PWA approximations and the re-sampling procedure.

Example 12 Considering a one-dimensional continu-

ous PWA function as in [13],

$$u(x) = \begin{cases} \ell_1(x) = 0.5x + 0.5 & x \in [0, 1], \\ \ell_2(x) = 2x - 1 & x \in [1, 1.5], \\ \ell_3(x) = 2 & x \in [1.5, 3.5], \\ \ell_4(x) = -2x + 9 & x \in [3.5, 4], \\ \ell_5(x) = -0.5x + 3 & x \in [4, 5], \end{cases}$$

the plot of which is shown in Fig. 3.




Fig. 3. One-dimensional continuous PWA function.

Supposing that we choose sample points as $(x_1, u(x_1)) = (0.5, 0.75)$, $(x_2, u(x_2)) = (2.5, 2)$, $(x_3, u(x_3)) = (3.75, 1.5)$, and $(x_4, u(x_4)) = (4.5, 0.75)$. Apparently, $(x_2, u(x_2)) = (2.5, 2)$ is on the boundary of some UO region, as $\ell_1(2.5) = \ell_5(2.5)$, hence we apply a perturbation and move x_2 to 2.4, i.e., we have $(x_2, u(x_2)) = (2.4, 2)$.

then the disjunctive lattice PWA approximation is

$$\hat{f}_{L,d} = \max\{\min\{\ell_1, \ell_3, \ell_4, \ell_5\}, \min\{\ell_3, \ell_4\}, \min\{\ell_1, \ell_3, \ell_4\}, \min\{\ell_1, \ell_3, \ell_5\}\}.$$

The conjunctive lattice PWA approximation is constructed as

$$\hat{f}_{L,c} = \min\{\ell_1, \max\{\ell_3, \ell_5\}, \max\{\ell_4, \ell_5\}, \max\{\ell_4, \ell_5\}\}.$$

It is apparent that the affine function ℓ_2 has not been sampled, and we check whether (17), (18) are satisfied and find that

$$\min_{j \in J_{\geq, 2}} u_j(x_1) = \min\{\ell_3(x_1), \ell_4(x_1)\} > \ell_1(x_1),$$

and

$$\max_{j \in J_{\leq, 1}} u_j(x_3) = \ell_1(x_3) < \ell_3(x_3).$$

Hence more sample points should be added between x_1 and x_3 .

Applying Algorithm 2, we obtain the newly sampled points $x_5 = 1.2$ and $u(x_5) = 2 \times 1.2 - 1 = 1.4$ and now Assumption 6 is satisfied.

Until now, all of the distinct affine functions ℓ_1, \dots, ℓ_5 have been sampled, and we obtain the following lattice PWA approximations:

$$\hat{f}_{L,d} = \max\{\min\{\ell_1, \ell_3, \ell_4, \ell_5\}, \min\{\ell_2, \ell_3, \ell_4, \ell_5\}, \min\{\ell_2, \ell_3, \ell_4\}, \min\{\ell_1, \ell_2, \ell_3, \ell_4\}, \min\{\ell_1, \ell_2, \ell_3, \ell_5\}\}$$

and

$$\hat{f}_{L,c} = \min\{\max\{\ell_1, \ell_2\}, \max\{\ell_1, \ell_2\}, \max\{\ell_1, \ell_3, \ell_5\}, \max\{\ell_4, \ell_5\}, \max\{\ell_4, \ell_5\}\}.$$

For all x , as $\min\{\ell_2, \ell_3, \ell_4\} \geq \min\{\ell_2, \ell_3, \ell_4, \ell_5\}$ and $\min\{\ell_2, \ell_3, \ell_4\} \geq \min\{\ell_1, \ell_2, \ell_3, \ell_4\}$, the disjunctive approximation $\hat{f}_{L,d}$ can be further expressed as

$$\hat{f}_{L,d} = \max\{\min\{\ell_1, \ell_3, \ell_4, \ell_5\}, \min\{\ell_2, \ell_3, \ell_4\}, \min\{\ell_1, \ell_2, \ell_3, \ell_5\}\}.$$

Similarly, the conjunctive approximation can be rewritten as

$$\hat{f}_{L,c} = \min\{\max\{\ell_1, \ell_2\}, \max\{\ell_1, \ell_3, \ell_5\}, \max\{\ell_4, \ell_5\}\}.$$

Fig. 4 and 5 give the plots of $\hat{f}_{L,d}$ and $\hat{f}_{L,c}$, respectively. It is apparent that for this simple example, after re-sampling, the disjunctive approximation $\hat{f}_{L,d}$ equals $u(x)$, and there is **deviation** between the conjunctive approximation $\hat{f}_{L,c}$ and $u(x)$. However, both $\hat{f}_{L,d}$ and $\hat{f}_{L,c}$ are identical to $u(x)$ at the sample points x_1, \dots, x_6 and in $\Gamma(x_1), \dots, \Gamma(x_6)$, confirming Lemma 7.

3.4 Simplification of lattice PWA approximation

In Example 12, duplicated or redundant terms have been removed from the lattice PWA approximation, which simplifies the approximation. When the number of sample points N_s is large, the evaluation of (13) and (15) are not easy, and hence the simplification is considered in this section.

The simplification of a disjunctive lattice PWA function was addressed in [13], for which the detailed subregions of the PWA function are known. In this paper, the information of the subregions of the PWA function is unknown. It is also difficult to derive the expression of




Fig. 4. Disjunctive lattice PWA approximation.




Fig. 5. Conjunctive lattice PWA approximation.

the subregion polyhedra through lattice PWA approximation. Hence, in this section, the disjunctive and conjunctive lattice PWA approximations are simplified according to the following rule. Assuming that the set C denotes the codomain of affine functions u_1, u_2, \dots , the operations \vee and \wedge are defined as follows,

$$u_i \vee u_j = \max\{u_i, u_j\}, u_i \wedge u_j = \min\{u_i, u_j\}.$$

It has been shown in [29] that the set C , together with the operations \vee and \wedge , constitutes a distributive lattice, and the following property holds for all $u_i, u_j \in C$:

$$R1: \begin{aligned} u_i \vee (u_i \wedge u_j) &= u_i \\ u_i \wedge (u_i \vee u_j) &= u_i. \end{aligned} \quad (31)$$

Actually, the above rule has been used in the simplification of lattice PWA approximations $\hat{f}_{L,d}$ and $\hat{f}_{L,c}$ in Example 12. After simplification, we get lattice PWA approximations with far less terms, which are equivalent to the lattice PWA approximations constructed through (13) and (15).

The process of obtaining disjunctive and conjunctive lattice PWA approximations and simplifying them can be summarized in Algorithm 3.

Algorithm 3 Construction and simplification of disjunctive and conjunctive lattice PWA approximations.

Input: Linear MPC problem.

Output: Simplified disjunctive and conjunctive lattice PWA approximations.

- 1: Generate sample dataset $\mathcal{X}_1 \times \mathcal{U}_1$ according to Algorithm 1.
 - 2: Generate additional sample dataset $\mathcal{X}_2 \times \mathcal{U}_2$ according to Algorithm 2.
 - 3: **for** $\mathbf{x}_i \in \mathcal{X}_1 \cup \mathcal{X}_2$ **do**
 - 4: Calculate the index sets $J_{\geq, i}$ and $J_{\leq, i}$ at the point \mathbf{x}_i according to Equation (14) and (16), respectively.
 - 5: **end for**
 - 6: Construct the disjunctive and conjunctive lattice PWA approximations according to Equation (13) and (15).
 - 7: Simplify the lattice PWA approximations according to the rule R1 (31).
-

The disjunctive and conjunctive lattice PWA approximations of explicit MPC control law are illustrated using a small example of a linear discrete-time system.

Example 13 Considering the discrete-time double integrator example introduced in [30], the system dynamics can be written as

$$\mathbf{x}_{k+1} = \begin{bmatrix} 1 & T_s \\ 0 & 1 \end{bmatrix} \mathbf{x}_k + \begin{bmatrix} T_s^2 \\ T_s \end{bmatrix} u_k$$

where the sampling interval T_s is 0.3. Considering the MPC problem with $Q = \text{diag}(1, 0)$, $R = 1$, and P is the solution of the discrete-time algebraic Riccati equation. The system constraints are $-1 \leq u_k \leq 1$ and $-0.5 \leq x_{k,2} \leq 0.5$. The region is set to be $[-2.8, 2.8] \times [-0.8, 0.8]$.

To derive the lattice PWA approximation, 441 points (21×21) are uniformly generated in the region $[-1, 1]^2$. For all 441 points, 68 points reach the boundary of some subregions, and we apply perturbations to move the points to the interior of some UO regions. There are five distinct affine functions, which are

$$\begin{aligned} u_1 &= -0.8082x_1 - 1.1559x_2; \\ u_2 &= -3.3333x_2 - 2.6667; \\ u_3 &= -3.3333x_2 + 2.6667; \\ u_4 &= -1; u_5 = 1. \end{aligned}$$

We generate 441 terms, and after the simplification of terms, the following lattice PWA approximations are ob-

tained:

$$\hat{f}_{L,d}(\mathbf{x}) = \max\{u_2(\mathbf{x}), u_4(\mathbf{x}), \min(u_1(\mathbf{x}), u_3(\mathbf{x}), u_5(\mathbf{x}))\}$$

and

$$\hat{f}_{L,c}(\mathbf{x}) = \min\{\max(u_1(\mathbf{x}), u_2(\mathbf{x}), u_4(\mathbf{x})), u_3(\mathbf{x}), u_5(\mathbf{x})\}.$$

Readers can verify that the disjunctive and conjunctive approximations are equivalent in $[-2.8, 2.8] \times [-0.8, 0.8]$. Fig. 6(a) gives the optimal MPC controller generated by the MPT3 Toolbox [28], and the linear subregions are also shown, see Fig. 6(b). For this example, the lattice PWA approximations are identical to explicit MPC. In the next section, we demonstrate that if all the affine functions have been sampled and the two lattice PWA approximations are identical, then both of them equal the optimal MPC control law.




Fig. 6. Explicit MPC controller in Example 13.

4 Approximation error and computational complexity

4.1 Deviations between the disjunctive and conjunctive approximations

After evaluating Algorithm 1-2, we obtain the sample point set $(\mathcal{X}_1 \cup \mathcal{X}_2) \times (\mathcal{U}_1 \cup \mathcal{U}_2)$, and use $\mathcal{X} = \mathcal{X}_1 \cup \mathcal{X}_2$ and $\mathcal{U} = \mathcal{U}_1 \cup \mathcal{U}_2$ to denote the sample point set. Assuming that $\mathcal{X} = \{\mathbf{x}_1, \dots, \mathbf{x}_{N_s}\}$, given both the disjunctive and conjunctive lattice PWA approximations, under the following assumption, the deviation between the approximations and the optimal control law can be derived.

Assumption 14 We assume that all the distinct affine functions have been sampled.

All the distinct affine functions for a PWA MPC optimal controller can be obtained by collecting all critical regions and corresponding local affine functions $u_{loc}(x)$ as defined in Definition 1 and selecting the distinct ones.

Assumption 14 can be explained as follows. Suppose we have 3 regions $\Omega_1, \Omega_2, \Omega_3$ and the local affine functions $u_{loc,1}(\mathbf{x}) = \ell_1(\mathbf{x}), u_{loc,2}(\mathbf{x}) = \ell_1(\mathbf{x}), u_{loc,3}(\mathbf{x}) = \ell_2(\mathbf{x})$, then the distinct affine functions are $\ell_1(\mathbf{x})$ and $\ell_2(\mathbf{x})$,

and by sampling points in Ω_1 and Ω_3 , we have sampled all the distinct affine functions.

Theorem 15 bounds the error between the lattice PWA approximations and the original optimal control law.

Theorem 15 *Supposing that*

$$\hat{f}_{L,d}(\mathbf{x}) = \max_{i \in \{1, \dots, N_s\}} \min_{j \in J_{\geq, i}} u_j(\mathbf{x})$$

and

$$\hat{f}_{L,c}(\mathbf{x}) = \min_{i \in \{1, \dots, N_s\}} \max_{j \in J_{\leq, i}} u_j(\mathbf{x})$$

are the disjunctive and conjunctive approximations of the optimal control law $u^*(\mathbf{x})$ over the domain Ω , assuming that Assumption 14 holds, and defining

$$\varepsilon = \max_{\mathbf{x}} \left(\hat{f}_{L,c}(\mathbf{x}) - \hat{f}_{L,d}(\mathbf{x}) \right), \quad (32)$$

we then have

$$-\varepsilon \leq \hat{f}_{L,d}(\mathbf{x}) - u^*(\mathbf{x}) \leq 0 \quad (33)$$

and

$$0 \leq \hat{f}_{L,c}(\mathbf{x}) - u^*(\mathbf{x}) \leq \varepsilon. \quad (34)$$

Furthermore, if $\varepsilon = 0$, we have

$$\hat{f}_{L,d}(\mathbf{x}) = \hat{f}_{L,c}(\mathbf{x}) = u^*(\mathbf{x}), \forall \mathbf{x} \in \Omega. \quad (35)$$

PROOF. Assume \mathcal{N} is the index of all UO regions, according to the conclusion in [13], we have

$$u^*(\mathbf{x}) = \max_{i \in \mathcal{N}} \min_{j \in I_{\geq, i}} u_j(\mathbf{x}), \forall \mathbf{x} \in \Omega, \quad (36)$$

$$u^*(\mathbf{x}) = \min_{i \in \mathcal{N}} \max_{j \in I_{\leq, i}} u_j(\mathbf{x}), \forall \mathbf{x} \in \Omega. \quad (37)$$

in which the index sets $I_{\geq, i}$ and $I_{\leq, i}$ are defined as,

$$I_{\geq, i} = \{j | u_j(\mathbf{x}) \geq u_i(\mathbf{x}), \forall \mathbf{x} \in \Gamma(\mathbf{x}_i)\},$$

$$I_{\leq, i} = \{j | u_j(\mathbf{x}) \leq u_i(\mathbf{x}), \forall \mathbf{x} \in \Gamma(\mathbf{x}_i)\}.$$

If Assumption 14 holds, i.e., all the distinct affine functions have been sampled, then for a UO region $\Gamma(\mathbf{x}_i)$, as the order of affine functions remains unchanged in the UO region, the set $I_{\geq, i}$ is identical to $J_{\geq, i}$ defined in (14). Similarly, the sets $I_{\leq, i}$ and $J_{\leq, i}$ defined in (16) are equivalent. Therefore, for all $\mathbf{x} \in \Omega$ and all $i \in \mathcal{N}$, the following inequalities hold:

$$\min_{j \in J_{\geq, i}} u_j(\mathbf{x}) \leq u^*(\mathbf{x}), \quad (38)$$

and

$$\max_{j \in J_{\leq, i}} u_j(\mathbf{x}) \geq u^*(\mathbf{x}). \quad (39)$$

As the sampled UO regions are only a subset of all UO regions, i.e.,

$$\{1, \dots, N_s\} \subset \mathcal{N},$$

we have inequalities (38) and (39) for all $\mathbf{x} \in \Omega$ and all $i \in \{1, \dots, N_s\}$.

Then the following is valid:

$$\hat{f}_{L,d}(\mathbf{x}) \leq u^*(\mathbf{x}) \leq \hat{f}_{L,c}(\mathbf{x}), \forall \mathbf{x} \in \Omega.$$

According to (32), we have (33) and (34).

Furthermore, if $\varepsilon = 0$, then both approximations are identical to the optimal control law in the region Ω , i.e., (35) holds.

As Theorem 15 indicates, in order to guarantee that the lattice PWA approximations are error-free, two conditions should be satisfied, the first is the validity of Assumption 14, and the second is that ε as defined in (32) is zero.

Remark 16 *As a necessary condition for the validity of (35), i.e., the lattice PWA approximations are error-free, Assumption 14 requires that all the distinct affine functions have been sampled. It is noted that this is not the same as the condition that all the critical regions should be identified. As [13] shows, the number of distinct affine functions in explicit MPC is generally far more less than the number of critical regions, as some critical regions can share the same affine function.*

4.1.1 A necessary condition for the validity of Assumption 14

In general, it is not easy to check whether Assumption 14 is satisfied, which is vital for the validity of (38) and (39) for all $\mathbf{x} \in \Omega$ and $i \in \{1, \dots, N_s\}$. Hence we check whether the relaxed condition

$$\min_{j \in J_{\geq, i}} u_j(\mathbf{x}) \leq \max_{j \in J_{\leq, i}} u_j(\mathbf{x}), \forall i \in \{1, \dots, N_s\}, \forall \mathbf{x} \in \Omega \quad (40)$$

holds, which is a direct result of (38) and (39).

To check whether (40) is satisfied, for any $i, k \in \{1, \dots, N_s\}$, the following optimization problem is solved:

$$\begin{aligned} \min_{\mathbf{x}} \max_{j \in J_{\leq, i}} u_j(\mathbf{x}) - \min_{j \in J_{\geq, k}} u_j(\mathbf{x}) \\ \text{s.t. } \mathbf{x} \in \Omega. \end{aligned} \quad (41)$$

If the optimal value for all $i, k \in \{1, \dots, N_s\}$ is nonnegative, then (40) holds.

The optimization problem (41) can be transformed into an equivalent linear programming (LP) problem:

$$\begin{aligned}
& \min_{\mathbf{x}, y_1, y_2} y_1 + y_2 \\
& \text{s.t. } \mathbf{x} \in \Omega, \\
& u_j(\mathbf{x}) \leq y_1, \forall j \in J_{\leq, i}, \forall i \in \{1, \dots, N_s\} \\
& u_j(\mathbf{x}) \geq -y_2, \forall j \in J_{\geq, k}, \forall k \in \{1, \dots, N_s\}
\end{aligned} \tag{42}$$

which is easy to solve as Ω is a polyhedron. If we find a point \mathbf{x} and an index pair i, k , such that the cost in (42) is negative, which means that (40) is violated, we can generate more sample points and get more distinct affine functions, as Lemma 17 shows.

Lemma 17 *Suppose there are some \mathbf{x}_γ and indices α, β such that $y_1(\mathbf{x}_\gamma) + y_2(\mathbf{x}_\gamma) < 0$, then more sample points can be generated in the line segment $\mathcal{L}(\mathbf{x}_i, \mathbf{x}_\gamma)$ or $\mathcal{L}(\mathbf{x}_\gamma, \mathbf{x}_k)$ according to Algorithm 2, and more distinct affine functions can be sampled.*

PROOF. As $y_1(\mathbf{x}_\gamma) + y_2(\mathbf{x}_\gamma) < 0$ for some α, β , we have

$$\max_{j \in J_{\leq, \alpha}} u_j(\mathbf{x}_\gamma) < \min_{j \in J_{\geq, \beta}} u_k(\mathbf{x}_\gamma). \tag{43}$$

Then at least one of the inequalities

$$\min_{j \in J_{\geq, \alpha}} u_j(\mathbf{x}_\gamma) > u^*(\mathbf{x}_\gamma) \tag{44}$$

and

$$\max_{j \in J_{\leq, \beta}} u_j(\mathbf{x}_\gamma) < u^*(\mathbf{x}_\gamma) \tag{45}$$

is valid. This is apparent, since, if both (44) and (45) do not hold, we have

$$\min_{j \in J_{\geq, \alpha}} u_j(\mathbf{x}_\gamma) \leq \max_{j \in J_{\leq, \beta}} u_j(\mathbf{x}_\gamma),$$

which contradicts (43).

The checking of (44) and (45) is very simple, as \mathbf{x}_γ and $u^*(\mathbf{x}_\gamma)$ are both known, and computing $\min_{j \in J_{\geq, \alpha}} u_j(\mathbf{x}_\gamma)$ only needs arithmetic operations, i.e., comparing the functions values of several affine functions at the point \mathbf{x}_γ . If (44) holds, then according to Lemma 11, sample points can be added to the line segment $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\gamma)$ as in Section 3.3.1 to ensure that

$$\min_{j \in J_{\geq, i}} u_j(\mathbf{x}_k) \leq u_k(\mathbf{x}_k)$$

for all the sample points in $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\gamma)$. In this process, more distinct affine functions have been identified.

For the conjunctive case, if (45) is valid, we can also add sample points in the line segment $\mathcal{L}(\mathbf{x}_\beta, \mathbf{x}_\gamma)$ according to Lemma 11 such that

$$\max_{j \in J_{\leq, i}} u_j(\mathbf{x}_k) \geq u_k(\mathbf{x}_k)$$

for all the sample points in $\mathcal{L}(\mathbf{x}_\beta, \mathbf{x}_\gamma)$.

By doing so, more sample points as well as more distinct affine functions have been sampled, which is necessary for the validity of Assumption 14.

Remark 18 *It is noted that although the relaxed condition (40) is only a necessary condition for the validity of Assumption 14, the checking of (40) is with respect to the entire domain Ω , not only the sample points. And we discovered in our numerical experiments that in most cases, if (40) holds in the domain of interest, all the distinct affine functions active in that region have been identified.*

4.1.2 Checking whether the 2 approximations are identical

Both the disjunctive approximation $\hat{f}_{L,d}$ and conjunctive approximation $\hat{f}_{L,c}$ are continuous PWA functions, so whether $\hat{f}_{L,d} = \hat{f}_{L,c}$ can be checked in each linear subregion of both $\hat{f}_{L,d}$ and $\hat{f}_{L,c}$. When the number of literals and terms in the lattice PWA approximations are large, it is not easy to identify all the linear subregions. So here we resort to a statistical method, i.e., generating a huge number of i.i.d. sample points, which constitute a validation dataset $\mathcal{X}_{\text{validate}} = \{\mathbf{x}_i, i = 1, \dots, N_v\}$. For each sample point, we define an indicator function as

$$I(\mathbf{x}_i) := \begin{cases} 1 & \text{if } \hat{f}_{L,d}(\mathbf{x}_i) = \hat{f}_{L,c}(\mathbf{x}_i) \\ 0 & \text{if } \hat{f}_{L,d}(\mathbf{x}_i) \neq \hat{f}_{L,c}(\mathbf{x}_i), \end{cases}$$

and then the random variables $I(\mathbf{x}_i), i = 1, \dots, N_v$ are also i.i.d. Denoting the probability for $I(\mathbf{x}_i = 1)$ as μ , i.e., $\mathbb{P}[I(\mathbf{x}_i) = 1] = \mu$, then according to Hoeffding's inequality [31], we have

$$\mathbb{P}[|\mu - \bar{I}| \geq \epsilon] \leq 2 \exp(-2N_v \epsilon^2),$$

in which $\bar{I} = \frac{1}{N_v} \sum_{k=1}^{N_v} I(\mathbf{x}_k)$. Therefore, we have

$$\mathbb{P}[\mu \geq \bar{I} - \epsilon] > 1 - 2 \exp(-2N_v \epsilon^2),$$

meaning that with confidence $1 - 2 \exp(-2N_v \epsilon^2)$, the probability that the lattice PWA approximations $\hat{f}_{L,d}$ and $\hat{f}_{L,c}$ are identical is larger than $\bar{I} - \epsilon$. If $\bar{I} = 1$, then by setting a small enough threshold ϵ , we can say that with confidence $1 - 2 \exp(-2N_v \epsilon^2)$, the lattice PWA

approximations $\hat{f}_{L,d}$ and $\hat{f}_{L,c}$ are almost identical, and thus both equal the optimal control law. For example, if $\epsilon = 10^{-3}$, then $N_v \geq 5 \times 10^6$ can ensure that the confidence is almost 1.

4.2 Complexity analysis

4.2.1 Online evaluation

Assuming that there are \tilde{N} terms in the final approximation, according to [12], the worst-case online evaluation complexity is $O(\tilde{N}^2)$. In general, we have $\tilde{N} \ll N_s$, and hence the online evaluation is very fast.

4.2.2 Storage requirements

Assuming that the disjunctive lattice PWA approximation has \tilde{N} terms and M literals (i.e. the number of distinct affine functions is M), we must store $(n_x+1) \cdot M$ real numbers and $\sum_{i=1}^{\tilde{N}} |J_{\geq,i}|$ integer numbers, in which $|J_{\geq,i}|$ is the number of elements in the set $J_{\geq,i}$. As $|J_{\geq,i}| \leq M$, in total $(n_x + 1) \cdot M$ real numbers and $M \cdot \tilde{N}$ integer numbers must be stored.

In many cases, we have $\tilde{N} \ll N_s$, and hence the storage requirement for the disjunctive lattice PWA approximation is very small.

For the conjunctive lattice PWA approximation, we achieve the same result.

4.2.3 Offline complexity

The offline time complexity for deriving equivalent disjunctive and conjunctive lattice PWA approximations can be summarized as follows.

The time complexity consists of two parts. One concerns the training points sampling and re-sampling in order to obtain lattice PWA approximations and the other is the complexity of checking whether the lattice PWA approximations are error-free. Lemma 19 describes the worst-case offline time complexity.

Lemma 19 *Assuming that the sample domain is a hyperbox, then the worst-case complexity of deriving the disjunctive and conjunctive lattice PWA approximations is $O(N_v \cdot N_s^2)$, in which N_s and N_v are the numbers of sample points in \mathcal{X} and $\mathcal{X}_{\text{validate}}$, respectively.*

PROOF. *As indicated previously, the offline complexity comes from evaluating Algorithm 3 and checking whether the two lattice PWA approximations are equivalent.*

For Algorithm 3, the evaluation of Algorithm 1 and 2, and the simplification of lattice PWA approximations account for the major part of the computational complexity.

The number of sample points in Algorithm 1 can be calculated as $N_1 = \prod_{i=1}^n \frac{b_i - a_i}{\delta_i}$, in which $[a_i, b_i]$ is the sample range for the i -th component, and correspondingly, δ_i is the length of the sample interval. The complexity of evaluating Algorithm 1 includes solving N_1 convex quadratic programming problems and corresponding KKT conditions, which are basically solving linear equations. The time complexity of solving N_1 convex quadratic programming problems with $N_p \cdot n_u$ decision variables is approximately $O(N_1 \cdot L^2 (N_p \cdot n_u)^4)$ by using an interior-point algorithm [32], in which L is the bit length of the quadratic programming problem. The dominant algorithmic operation in solving the KKT conditions is solving N_1 matrix inversion problems, the worst-case complexity of which is $O(N_1 |\mathcal{A}^|^3)$ using the Gauss-Jordan elimination algorithm, in which $|\mathcal{A}^*|$ is the number of active constraints. As $|\mathcal{A}^*| \leq p$, where p is the number of constraints in QP (3), the worst-case complexity for solving the KKT conditions is $O(N_1 p^3)$.*

We now discuss the worst-case complexity of evaluating Algorithm 2. For two points \mathbf{x}_α and \mathbf{x}_β , if (38) is violated, the evaluation of Algorithm 2 is basically a binary search method for identifying omitted subregions in the line segment $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$ as well as calculating affine functions for newly generated points. Assume the maximum number of subregions appearing in $\mathcal{L}(\mathbf{x}_\alpha, \mathbf{x}_\beta)$ is $M_{\alpha,\beta}$, and generally $M_{\alpha,\beta} < N_1$. The binary searching of the subregions then yields a worst-case complexity of $O(\log_2 N_1)$ and the affine function calculation yields a worst-case complexity of $O(p^3 \log_2 N_1)$, in which p is the number of constraints in QP (3). Supposing that there are N_t point pairs such that (38) is violated, then the worst-case complexity is $O(N_t \cdot p^3 \log_2 N_1)$. In general, the number N_t is closely related to the sample grid size δ_i , which then depends on the number of sample points N_1 in Algorithm 1. A larger N_1 will result in a smaller number of N_t ; hence, the complexity of Algorithm 2 can be decreased by increasing the complexity of Algorithm 1.

After evaluating Algorithm 1-2, there are N_s sample points. The simplification procedure requires the comparison of the sets $J_{\geq,i}$ ($J_{\leq,i}$) for $i = 1, \dots, N_s$, which at most yields $\binom{N_s}{2} = \frac{N_s(N_s-1)}{2}$ times comparisons. For each comparison, at most M^2 literals need to be compared. Hence the worst-case complexity for the simplification is $O(M^2 N_s^2)$.

After simplification, we have only \tilde{N} terms, which is generally much less than N_s , i.e., $\tilde{N} \ll N_s$, then for the process of checking whether the lattice PWA approximations are error-free, one has to solve at most \tilde{N} LP problems and generate N_v validation points. Assuming

that L is the bit length of the LP problem (42), then the worst-case complexity for solving \tilde{N}^2 LP problems is $O(\tilde{N}^2 \cdot n_x^{3.5} \cdot L)$. For the sampling of N_v points in the lattice PWA approximations, as indicated in Section 4.2.1, the function evaluation process of lattice PWA approximations has a worst-case complexity of $O(\tilde{N}^2)$, in which $\tilde{N} < N_s$, hence the worst-case complexity of generating validation points is $O(N_v \cdot \tilde{N}^2)$. As N_v is large, we have $O(\tilde{N}^2 \cdot n_x^{3.5} \cdot L) \ll O(N_v \cdot \tilde{N}^2)$; hence the worst-case complexity of validation is $O(N_v \cdot \tilde{N}^2)$.

In general, $N_1 < N_s$, $p \ll N_1$, $N_t \ll N_1$, $M \ll N_v$, and $\tilde{N} \ll N_s$, and then the total worst-case complexity is $O(N_v \cdot N_s^2)$.

It is noted that $O(N_v \cdot N_s^2)$ is the worst-case complexity. In the simulation results, we can see that the offline calculation is actually not time consuming.

5 Simulation results

Example 20 Consider an example taken from [18], which is the inverted pendulum on a cart. The state consists of the angle and the angle speed of the pole, i.e., Φ , $\dot{\Phi}$, respectively, and the position and speed of the cart, i.e., s and \dot{s} , respectively. The constraints for the state are $\|\mathbf{x}\|_\infty^T \leq [1, 1.5, 0.35, 1.0]^T$. The input is the force, the constraint of which is $|u| \leq 1$. The discrete-time dynamic is given by

$$A = \begin{bmatrix} 1 & 0.1 & 0 & 0 \\ 0 & 0.9818 & 0.2673 & 0 \\ 0 & 0 & 1 & 0.1 \\ 0 & -0.0455 & 3.1182 & 1 \end{bmatrix}, B = \begin{bmatrix} 0 \\ 0.1818 \\ 0 \\ 0.4546 \end{bmatrix}.$$

The prediction horizon is taken to be $N = 10$. The value of matrices in the cost function is $Q = \text{diag}\{2, 2, 2, 2\}$, $R = 1$, and $P = 0$. According to the MPT3 toolbox, the optimal control solution is a PWA function of the state \mathbf{x} , with 2,271 polyhedral regions.

In [18], 88,341 samples were generated to train an approximated controller, which is basically a deep PWL neural network. Here, in order to construct the disjunctive and conjunctive lattice PWA approximations, only $8^4 = 4096$ samples are generated uniformly in the region $\Omega = [-0.6, 0.6] \times [-0.9, 0.9] \times [-0.21, 0.21] \times [-0.6, 0.6]$. In this case, there are only 13 distinct affine functions, which is due to the choice of the region. For a larger region, say $\Omega_2 = [-0.9, 0.9] \times [-1.2, 1.2] \times [-0.25, 0.25] \times [-0.9, 0.9]$, there are 47 distinct affine functions. However, there are a significant number of infeasible state points in Ω_2 , and according to the state trajectory in [18], the region Ω is enough.

The evaluation of Algorithm 1-2 results in the disjunctive and conjunctive lattice PWA approximations, both with six terms. All the computations in this paper are implemented through MatLab 2016b (MathWorks, USA) on an Apple M1 Max computer.

The entire offline calculation time is 41.25s, i.e., Algorithm 1, 2, 3 takes 40.25s, 0.66s and 0.33s, respectively. The number of parameters for both approximations is 143, while the number of parameters stored in the MPT3 solution is 104,535. The average online evaluation time for the MPT solution, the disjunctive as well as conjunctive lattice PWA approximations are 0.0052s, 8.96×10^{-5} s, and 8.33×10^{-5} s, respectively. It is apparent that the approximation results in a much lower online computational burden.

It has been tested through 5×10^6 test data points that the two lattice PWA approximations are identical in the region Ω . By setting $\epsilon = 10^{-3}$, it can be concluded that with confidence $\delta = 0.9999$ the probability that the approximated lattice PWA control laws equal the optimal control is larger than 0.999. For the 5×10^6 points, the optimal explicit linear MPC control law is also calculated and it is found that the lattice PWA approximations are error-free in Ω .

Fig. 7 shows one exemplary closed-loop simulation of the example, and we can see from the figure that the optimal state trajectory and the trajectory with the lattice PWA approximations as inputs are identical.

Example 21 Consider an example taken from [5], which is an mpQP problem constructed from the typical MPC setup of the form

$$\min_{u_0, \dots, u_{N-1}} \mathbf{x}_N^T P \mathbf{x}_N + \sum_{k=0}^{N-1} \mathbf{x}_k^T Q \mathbf{x}_k + u_k^T R u_k \quad (46a)$$


$$\text{s.t. } \mathbf{x}_{k+1} = A \mathbf{x}_k + B u_k \quad (46b)$$

$$\mathbf{x} \in \mathcal{X}, u \in \mathcal{U} \quad (46c)$$


with $\mathbf{x} \in \mathbb{R}^{10}$, $u \in \mathbb{R}$, $P = Q = I_{10}$, $R = 1$, $\mathcal{X} = \{x | -10 \leq x_i \leq 10, i = 1, \dots, n_x\}$, $\mathcal{U} = \{-1 \leq u \leq 1\}$. The prediction model is obtained by discretizing the model $1/(s+1)^{10}$ with sampling time of 1 s and then converting the discretized model into state space form. The prediction horizon is taken to be $N = 10$.

Apparently this problem is more complex than Example 20, as the dimension is much higher. As [5] shows, the `mpt_solve` function in MPT3 Toolbox failed to solve this problem offline, i.e., MATLAB ran out of memory.

Here, in order to construct the disjunctive and conjunctive lattice PWA approximations, we have to generate sample points in the 10-dimensional domain, which may suffer from the curse-of-dimensionality if the sample



(a)



(b)

Fig. 7. One exemplary closed-loop simulation of Example 20.

points are generated uniformly in the domain. Instead, we generate sample points on several trajectories, which reflect the most possible states of the dynamic system under optimal MPC control law. Specifically, 300 initial points are generated in the domain $[-2, 2]^{10}$, then for the 300 trajectories we have 7802 sample points.

In this case, there are 16 distinct affine functions. The evaluation of Algorithm 1-2 results in the disjunctive and conjunctive lattice PWA approximations, the number of terms is 9 and 8, respectively. The offline as well as online complexity of lattice PWA approximations when the prediction horizon N is 10 are shown in Table 1.

The entire offline calculation time for generating the disjunctive and conjunctive lattice PWA approximations is 84.65s, i.e., Algorithm 1,2,3 accounts for 80.3016s, 2.8734s, 1.4776s, respectively. The number of parameters for the disjunctive and conjunctive approximations are 320 and 304, respectively. The average online evaluation times (over 10^4 trials) for the online QP, disjunctive as well as conjunctive lattice PWA approximations are 0.0077, 1.69×10^{-4} s, and 1.40×10^{-4} s, respectively. It is apparent that the approximations result in a very low online computational burden.

It has been tested through 5×10^6 test data points that the

Table 1

Performance of lattice PWA approximations on Example 21, in which N_s and #para are the number of sample points and parameters, and t_{off} and t_{on} denote offline and online computation time.

Method	N	N_s	#para	t_{off} [s]	t_{on} [s]
Disjunctive	10	7808	320	84.65	1.69×10^{-4}
Conjunctive		7808	304	84.65	1.40×10^{-4}
Online MPC					0.0077
Method in [5]				72.85	
Disjunctive	20	10188	418	229.24	2.71×10^{-4}
Conjunctive		10188	418	229.24	2.53×10^{-4}
Online MPC					0.015
Method in [5]					

two lattice PWA approximations are identical in the region Ω . By setting $\epsilon = 10^{-3}$, it can be concluded that with confidence $\delta = 0.9999$ the probability that the approximated lattice PWA control laws equal the optimal control law is larger than 0.999. For the 5×10^6 points, the optimal linear MPC control law is also calculated and it is found that the lattice PWA approximations are error-free in Ω .

Fig. 8 shows one exemplary closed-loop simulation of the example, and we can see from the figure that the optimal state trajectory and the trajectory with the lattice PWA approximations as inputs are identical.

As indicated in [5], the MPT3 Toolbox failed to solve the problem. Moreover the combinatorial approach proposed in [5] successfully enumerating all optimal active sets and creating corresponding critical regions, takes 72.85s. It is noticed that although the calculation time for our procedure is slightly longer, we obtain the final continuous PWA expression of the optimal control law in a simplified form, which is easier to be implement online.

To demonstrate more clearly the efficacy of the lattice PWA approximations, the prediction horizon N is extended to 20, and the complexity of lattice PWA approximations is also listed in Table 1. Besides, we also generate 5×10^6 validation points to show that with confidence $\delta = 0.9999$ the probability that the approximated lattice PWA control laws equal the optimal control law is larger than 0.999. When $N = 20$, [5] did not provide a result either. The lattice PWA approximations in this case takes 229.2417s to get error-free approximations in $\Omega = [-2, 2]^{10}$, showing that the lattice PWA approximations scale well with the problem size for this example.

6 Conclusions and Future work

In this paper, we have presented disjunctive and conjunctive lattice PWA approximations of the explicit linear MPC control law by sampling and resampling in the




Fig. 8. One exemplary closed-loop simulation of Example 21.

state domain. The lattice PWA approximated and exact control laws are identical for sample points and in UO regions that contain the sample points as interior points. Furthermore, under the assumption that all the affine functions have been identified in the domain of interest, the disjunctive lattice PWA approximation is always smaller than the original optimal control law, while the conjunctive lattice PWA approximation is always larger. Then if the disjunctive and conjunctive lattice PWA approximations are identical, both are equivalent to the optimal control law. The two kinds of lattice PWA approximations have been simplified to further reduce the storage and online evaluation complexity. The complexity of the online and offline approximation as well as the storage requirements, have been analyzed. Simulation results show that with a moderate number of sample points we can obtain statistically error-free lattice PWA approximations that are calculated with relatively small computational cost.

In the future, apart from the information of local affine functions, the information of critical regions will also be used to construct the lattice PWA approximation. Moreover, for more general domain of interest, the approximation error will be considered, which can be used to derive corresponding feasibility and stability analysis. Besides, practical applications will also be considered.

References

- [1] T. Samad. A survey on industry impact and challenges thereof. *IEEE Control Systems Magazine*, 37(1):17–18, 2017.
- [2] A. Bemporad, M. Morari, V. Dua, and E. N. Pistikopoulos. The explicit linear quadratic regulator for constrained systems. *Automatica*, 38(1):3–20, 2002.
- [3] M. Kvasnica, B. Takács, J. Holaza, and S. Di Cairano. On region-free explicit model predictive control. In *Proceedings of the 2015 IEEE 54th Conference on Decision and Control (CDC)*, pages 3669–3674, Osaka, Japan, 2015.
- [4] A. Gupta, S. Bhartiya, and P. Nataraj. A novel approach to multiparametric quadratic programming. *Automatica*, 47(9):2112–2117, 2011.
- [5] P. Ahmadi-Moshkenani, T. A. Johansen, and S. Oлару. Combinatorial approach toward multiparametric quadratic programming based on characterizing adjacent critical regions. *IEEE Transactions on Automatic Control*, 63(10):3221–3231, 2018.
- [6] F. Borrelli, M. Baotić, J. Pekar, and G. Stewart. On the computation of linear model predictive control laws. *Automatica*, 46(6):1035–1041, 2010.
- [7] M. Herceg, S. Mariétoz, and M. Morari. Evaluation of piecewise affine control law via graph traversal. In *Proceedings of the European Control Conference*, pages 3083–3088, 2013.
- [8] F. J. Christophersen, M. Kvasnica, C. N. Jones, and M. Morari. Efficient evaluation of piecewise control laws defined over a large number of polyhedra. In *Proceedings of the European Control Conference*, pages 2360–2367, 2007.
- [9] F. Bayat, T. A. Johansen, and A. Jalali. Flexible piecewise function evaluation methods based on truncated binary search trees and lattice representation in explicit MPC. *IEEE Transactions on Control Systems Technology*, 20(3):632–640, 2012.
- [10] N. A. Nguyen, M. Gulán, S. Oлару, and P. Rodríguez-Ayerbe. Convex lifting: Theory and control applications. *IEEE Transactions on Automatic Control*, 63(5):1243–1258, 2017.
- [11] M. Gulán, G. Takács, N. A. Nguyen, S. Oлару, P. Rodríguez-Ayerbe, and Rohal’-Ilkiv B. Efficient embedded model predictive vibration control via convex lifting. *IEEE Transactions on Control Systems Technology*, 27(1):48–62, 2019.
- [12] C. Wen, X. Ma, and B. E. Ydstie. Analytical expression of explicit MPC solution via lattice piecewise-affine function. *Automatica*, 45(4):910–917, 2009.
- [13] J. Xu, T. J. J. van den Boom, B. De Schutter, and S. Wang. Irredundant lattice representations of continuous piecewise affine functions. *Automatica*, 70:109–120, 2016.
- [14] A. Bemporad and C. Filippi. Suboptimal explicit MPC via approximated multiparametric quadratic programming. In *Proceedings of the 40th IEEE Conference on Decision and Control, 2001*, volume 5, pages 4851–4856. IEEE, 2001.
- [15] A. Bemporad, A. Oliveri, T. Poggi, and M. Storaice. Ultra-fast stabilizing model predictive control via canonical piecewise affine approximations. *IEEE Transactions on Automatic Control*, 56(12):2883–2897, 2011.
- [16] G. Goebel and F. Allgöwer. Semi-explicit MPC based on subspace clustering. *Automatica*, 83:309–316, 2017.
- [17] A. Chakrabarty, V. Dinh, M. J. Corless, A. E. Rundell, S. H. Žak, and G. T. Buzzard. Support vector machine

- informed explicit nonlinear model predictive control using low-discrepancy sequences. *IEEE Transactions on Automatic Control*, 62(1):135–148, 2016.
- [18] B. Karg and S. Lucia. Efficient representation and approximation of model predictive control laws via deep learning. *IEEE Transactions on Cybernetics*, 50(9):3866–3878, 2020.
- [19] L. Csekő, M. Kvasnica, and B. Lantos. Explicit MPC-based RBF neural network controller design with discrete-time actual Kalman filter for semiactive suspension. *IEEE Transactions on Control Systems Technology*, 23(5):1736–1753, 2015.
- [20] S. Summers, C. N. Jones, J. Lygeros, and M. Morari. A multiresolution approximation method for fast explicit model predictive control. *IEEE Transactions on Automatic Control*, 56(11):2530–2541, 2011.
- [21] S. Gros and M. Zanon. Data-driven economic NMPC using reinforcement learning. *IEEE Transactions on Automatic Control*, 65(2):636–648, 2020.
- [22] F. Scibilia, S. Oлару, and M. Hovd. Approximate explicit linear MPC via Delaunay tessellation. In *2009 European Control Conference (ECC)*, pages 2833–2838, 2009.
- [23] A. Pavlov, I. Shames, and C. Manzie. Minimax strategy in approximate model predictive control. *Automatica*, 111:108649, 2020.
- [24] J. Xu. Lattice piecewise affine approximation of explicit linear model predictive control. In *Proceedings of the 60th IEEE Conference on Decision and Control*, 2021.
- [25] L. O. Chua and A. C. Deng. Canonical piecewise-linear representation. *IEEE Transactions on Circuits and Systems*, 35(1):101–111, 1988.
- [26] J. Nocedal and S. Wright. *Numerical Optimization*. Springer-Verlag, New York, NY, USA, 2006.
- [27] F. Borrelli. *Constrained Optimal Control of Linear and Hybrid Systems*, volume 290. New York: Springer, 2003.
- [28] M. Hecceg, M. Kvasnica, C. N. Jones, and M. Morari. Multi-parametric toolbox 3.0. In *Proceedings of the European Control Conference*, pages 502–510, 2013. <http://control.ee.ethz.ch/~mpt>.
- [29] J. M. Tarela, J. M. Perez, and V. Aleixandre. Minimization of lattice polynomials on piecewise linear functions (Part I). *Mathematics and Computers in Simulation*, 17(2):79–85, 1975.
- [30] M. Johansson. *Piecewise linear control systems: A computational approach*. Springer-Verlag New York, Inc. Secaucus, NJ, USA, 2003.
- [31] W. Hoeffding. Probability inequalities for sums of bounded random variables. In 409-426, editor, *The Collected Works of Wassily Hoeffding*. Springer, 1994.
- [32] Y. Ye and E. TSE. An extension of Karmarkar’s projective algorithm for convex quadratic programming. *Mathematical Programming*, 44(1):157–159, 1989.