Information between quantum systems via POVMs

Lev B. Levitin and Tom maso To oli ECE Dept., Boston University, Boston, MA 02215

A bstract

The concepts of conditional entropy and inform ation between subsystems of a composite quantum system are generalized to include arbitrary indirect measurements (POVMs). Some properties of those quantities dier from those of their classical counterparts; certain equalities and inequalities of classical information theory may be violated.

K eyw ords: Q uantum inform ation; quantum conditional entropy; POVM; quantum relative entropy; entropy defect. PACS 03.67.-a.

In [Levitin 1998, Levitin 1999], concepts of conditional entropy and information were introduced for quantum systems with respect to direct (von Neumann) measurements performed over subsystems of a composite quantum system. In this paper the concepts are generalized to include arbitrary indirect measurements (POVMs). The concepts of conditional entropy and information retain their validity for quantum systems, but their properties dier somewhat from those of their classical counterparts; specically, some equalities and inequalities of classical information theory are in general violated.

Consider a composite quantum system consisting of two subsystems A and B, the Hilbert space H of the system being the tensor product, H $_{\rm A}$ H $_{\rm B}$, of the Hilbert spaces of its two subsystems. The state of the system and the states of its subsystems are described, respectively, by the joint density matrix (A;B) and the marginal density matrices (A) and (B). The joint entropy of the system and the marginal entropies of the two subsystems are, respectively, H (A;B), H (A), and H (B).

Now, let M $_{\rm A}$ = fM $_{\rm a}$ (A)g be a countable set of self-adjoint nonnegative de nite operators that form a resolution of the identity (in general, non-orthogonal) in H $_{\rm A}$, and M $_{\rm B}$ = fM $_{\rm b}$ (B)g a similar set of operators in H $_{\rm B}$. The sets M $_{\rm A}$ and M $_{\rm B}$ correspond to indirect measurements (POVMs) performed respectively over the systems A and B . By Naimark's theorem [Naimark 1940], any POVM is equivalent to a direct (von Neumann) measurement performed in an extended Hilbert space. Henceforth we will consider POVMs that correspond to measurements of a complete set of variables (represented by a complete set of orthogonal one-dimensional projectors) in the extended Hilbert space. Henceforth we will consider POVMs

Denote by and the two random variables that are the results of measurements M $_{\rm A}$ and M $_{\rm B}$. The probability distributions of and are

$$Prf = ag = Trf (A)M_{a}(A)g;$$

$$Prf = bg = Trf (B)M_{b}(B)g;$$

$$Prf = a; = bg = Trf (A;B)M_{a}(A) M_{b}(b)g;$$
(1)

Lemma 1. For any choice of M $_{\rm A}$ and M $_{\rm B}$,

Proof. Inequalities (2) follow from Klein's lemma[Klein 1931] by use of Naimark's theorem. ■

The conditional density matrix of subsystem A given the result of a measurement performed over subsystem B can be de ned for POVMs in a sim - ilar way as it is de ned for von Neumann measurements, namely, following Balian 1991],

$$(A j = b) = \frac{Tr_B f (A;B)[I(A) M_b(B)]g}{Trf (A;B)[I(A) M_b(B)]g};$$
 (3)

where I(A) is the identity operator in H $_{\rm A}$. Note that the denominator in (3) is just the probability Prf = bg for to take on value b.

 $^{^1\}text{T}$ he expression \com plete set of variables" is used here in exactly the samem eming as \com plete set of physical quantities" in [Lifshitz 1977, p.5], namely, as a maximum set of simultaneously measurable quantum variables (observables). \Com plete set of projectors" means that they form a resolution of the identity. Also, since sets M $_{\rm A}$ and M $_{\rm B}$ are countable, they correspond to measurements of variables with discrete spectrum.

Then the conditional entropy of system A, given m easurement M $_{\rm B}\,$ performed on B, is

By K lein's lem m a, for any $\;$ and $\;$ (i.e., for any m easurements M $_{\rm A}$ and M $_{\rm B}$ performed on A and B),

$$H(Aj) H(j);$$
 (5)

where equality holds i all (A j = b) commute and M $_A$ is a von Neumann measurement in the basis where all (A j = b) are diagonal.

Since conditional entropy is meant to express the uncertainty of the state of subsystem A under the constraints imposed on it by the \best" measurement performed on subsystem B, we propose the following

Definition 1. The conditional entropy of subsystem A, conditioned by subsystem B, is

$$H (A \beta) = \inf_{M_B} H (A j)$$
: (6)

The following theorem states that, just as in the classical case, conditioning can only decrease the entropy of a system:

Theorem 1.

Proof.

and

$$\begin{array}{c} X \\ \text{H } (A \not B) = \inf_{\substack{M \in B \\ M \in A}} \text{Prf} = \bigoplus_{\substack{M \in A \\ M \in A}} \inf_{\substack{M \in A \\ M \in A}} \text{H } (j) \quad \inf_{\substack{M \in A \\ M \in A}} \text{H } () \\ = \text{H } (A) : \quad \blacksquare \end{array}$$

It has been pointed out [Yang 2004] that inequality (7) follows from the nonnegativity of the entropy defect [LeviLin 1969, Holevo 1973]. Indeed,

$$H(A) H(A\beta) = X$$

$$= \inf_{M_B} [Tr(A) \log (A) + Prf = \log Trf(Aj = b) \log (Aj = b)g];$$

where the expression in brackets is a special case of the entropy defect.

Note that in classical information theory H(;) = H() + H(j). However, this equality turns into an inequality for quantum systems:

Theorem 2.

$$H (A;B) H (B) + H (A;B)$$
: (8)

Proof. By de nition (6), it su ces to prove that, for any choice of M $_{\rm B}$,

$$H (A;B) H (B) + H (A;B)$$
: (9)

It follows from Naimark's theorem that it is su cient to prove (9) for the case when M $_{\rm B}$ corresponds to a complete set of orthogonal projectors (a von Neumann measurement).

Let $fu_{ib}g$ be the set of orthonorm aleigenvectors of the conditional density matrix (A j = b), and fv_bg the set of orthonorm alvectors corresponding to projectors M $_b$ (B). Consider a basis in H = H $_A$ H $_B$ form ed by vectors $u_{i;b}$ v_b . The joint density matrix (A;B) = $jj_{ib;i}v_b$ jj in this basis has the property that $_{ib;i}v_b = _{ib}v_b$.

Let us introduce a density matrix ⁰(A;B) obtained from (A;B) by deleting the o -diagonal elements in the basis described above, namely,

$${}^{0}(A;B) = jj_{ib;i^{0}p^{0}} jj = jj_{ib}_{ib}_{ib} jj = jj_{ib}_{ib} jj$$
(10)

For each b, the conditional density matrix is

$$(A j = b) = \frac{P^{ib \ ii^0}}{i \ ib}$$
:

Also, denote

0
(B) = Tr_A 0 (A;B) = 1 ibb 0 1 ib 1 i

It is readily seen that, since matrices (A;B) and (B) are diagonal,

$$H (Aj) = Tr^{0}(A;B) ln^{0}(A;B) + Tr^{0}(B) ln^{0}(B)$$

$$= Tr (A;B) ln^{0}(A;B) + Tr (B) ln^{0}(B);$$
(11)

Consider now the quantum relative entropy (cf. [Schum acher 2000, Vedral 2001]) between states (A;B) and 0 (A;B),

H ((A;B)) (A;B)) = Tr (A;B) (A;B) Tr (A;B) (A;B) (A;B); (12) and sim ilarly that between (B) and (B),

$$H ((B)_{1}^{1})^{0}(B) = Tr (B) \ln (B) Tr (B) \ln (B)$$
: (13)

It is well known [Vedral 2001, p.13,F2] that partial tracing reduces relative entropy; therefore

H (
$$(A;B)$$
 $)$ $)$ $(A;B)$ H T r_A $(A;B)$ $)$ $)$ $(A;B)$ = H ((B) $)$ (B) $)$ (B) which, by (11), (12), and (13), yields inequality (9).

According to classical information theory, the information between the outcomes and of two POVMsM $_{\rm A}$ and M $_{\rm B}$ performed on subsystems A and B is

$$I(;) = H() H(;):$$
 (14)

In the spirit of Shannon's inform ation theory, we de ne the mutual inform ation between two quantum systems as follows:

Definition 2. The information in subsystem B about subsystem A (and vice versa) is

$$I(A;B) = \sup_{M_A;M_B} I(;):$$
 (15)

The classical equality (14) then turns into an inequality:

Theorem 3.

Proof. From the entropy defect bound [Levitin 1969, Holevo 1973] it follows that for any M $_{\rm B}$

$$I(A;) = \sup_{M_A} I(;) H(A) H(Aj);$$
 (17)

where equality holds i all (A j = b) commute and M_A is a von Neumann measurement in the basis where all (A j = b) are diagonal.

From (17),

$$I(A;B) = \sup_{M_A;M_B} I(;)$$

$$\sup_{M_B} [H(A) H(Aj)] = H(a) \inf_{M_B} H(Aj)$$

$$= H(A) H(A;B): \blacksquare$$

The proposed measures of information and conditional entropy turn out to be useful in the analysis of correlated (in particular, entangled) quantum systems, in place of their classical counterparts.

A cknow ledgm ent

We would like to thank Dr.D. Yang (University of Science and Technology of China) for his thoughtful remarks [Yang 2004].

R eferences

- Balian 1991] Balian, Roger, From Microphisics to Macrophysics: Methods and applications of statistical physics, Vol. 1, Springer (Verlag 1991.
- Holevo 1973] Holevo, Alexander S., \Som e estimates of the information transmitted over a quantum communication channel," Probl. of Information Transmission 9:3 (1973), 3{11.
- [K lein 1931] K lein, Otto, Zeitschr. f. Phys. 72 (1931), 767.
- Levitin 1998] Levitin, Lev B., \Conditional entropy and information in quantum system s," Proc. 1998 IEEE Int. Sym p. Information Theory, Cambridge M A, Aug. 1998, 88.
- [Levitin 1999] Levitin, Lev B., \Conditional entropy and information in quantum systems," Chaos, Solitons, and Fractals 10 (1999), 1651 [56.
- [Levitin 1969] Levitin, Lev B., \On the quantum measure of information," Proc. 4th Conf. on Information Theory, Tashkent, 1969, 111{116. English translation in Annales de la Fondation Louis de Broglie 21:3 (1996), 345{348.
- [Lifshitz 1977] Lifshitz, Evgeny M, Lev D Landau, Quantum Mechanics: Non-Relativistic Theory, vol. 3, 3rd rev.ed., Elsevier Science 1977.
- Naim ark 1940] Naimark, Mark A., \Spectral functions of a symmetric operator, Izv. Akad. Nauk SSSS, Ser. Mat. 4 (1940), 277{318.
- [Schum acher 2000] Schum acher, Ben, and M. D. Westmore-land, Relative entropy in quantum information theory," arxiv.org/archive/quantum-ph/0004045 (10 Apr. 2000).

[Vedral2001] Vedral, V., \The role of relative entropy in quantum information theory," arxiv.org/archive/quantum-ph/0102094 (19 Feb. 2001).

[Yang 2004] Yang, D., private communication (Sep. 2004).