

## Combinatorial Computation of Clebsch-Gordan Coefficients

Klaus Schertler and Markus H. Thoma

Institut für Theoretische Physik, Universität Gießen, 35392 Gießen, Germany  
(January 9, 2022)

The addition of angular momenta can be reduced to elementary coupling processes of spin- $\frac{1}{2}$ -particles. In this way, a method is developed which allows for a non-recursive, simultaneous computation of all Clebsch-Gordan coefficients concerning the addition of two angular momenta. The relevant equations can be interpreted easily, analogously to simple probabilistic considerations. They provide an improved understanding of the addition of angular momenta as well as a practicable evaluation of Clebsch-Gordan coefficients in an easier way than within the well-known methods.

PACS number(s): 03.65Ca

## I. INTRODUCTION

## A. Definition and properties of Clebsch-Gordan coefficients

A system of two quantum mechanical angular momenta is characterized by the angular momentum operators of the total angular momentum  $\hat{J}^2, \hat{J}_z$  and the operators of the individual angular momenta  $\hat{J}_1^2, \hat{J}_{1z}, \hat{J}_2^2, \hat{J}_{2z}$ . These operators can be classified into two groups in which the corresponding operators commute [1]:

$$\hat{J}_1^2, \hat{J}_2^2, \hat{J}^2, \hat{J}_z,$$

$$\hat{J}_1^2, \hat{J}_2^2, \hat{J}_{1z}, \hat{J}_{2z}.$$

Hence the basis states can be chosen as

coupled eigenstates, denoted by  $|j; J_2; J; M\rangle$  or  $|j; M\rangle$ ,

uncoupled eigenstates, denoted by  $|j_1; J_2; M_1; M_2\rangle$  or  $|M_1; M_2\rangle$ .

These complete basis systems are related to each other via an unitary transformation:

$$|j; M\rangle = \sum_{M_1, M_2} |M_1; M_2\rangle \langle M_1; M_2 | j; M \rangle \quad (1)$$

The amplitudes  $\langle M_1; M_2 | j; M \rangle$  in (1) are called Clebsch-Gordan (CG) coefficients. General properties of the CG-coefficients are given e.g. in Ref. [1]. Here only a few are listed:

CG-coefficients vanish if  $M \notin M_1 + M_2$ .

The total angular momentum  $J$  satisfies  $|J - J_2| \leq J \leq J_1 + J_2$ .

CG-coefficients can be chosen as real.

## B. Conventional methods

A standard method for calculating CG-coefficients (see e.g. [2]) is based on the iterative application of the operator  $\hat{J} = \hat{J}_x + i\hat{J}_y$  on the maximum state

$$|j; M\rangle = |M_1 = J_1; M_2 = J_2\rangle;$$

where  $J = J_1 + J_2$  and  $M = M_1 + M_2$ . The effect of the lowering operator on  $|j; M\rangle$  is given by

$$\hat{J}^- |j; M\rangle = \sqrt{(J + M)(J - M + 1)} |j; M - 1\rangle;$$

The CG-coefficients are obtained by projecting the resulting states onto the uncoupled product state  $\langle M_1; M_2 |$ .

Furthermore, Racah gave an elaborate but explicit formula for the CG-coefficients (see e.g. [2]). Both the methods are very formal and render the evaluation even in the case of "small" angular momentum cumbersome. Thus CG-coefficients have been listed in tables (see e.g. [3]).

Here we propose an intuitive way allowing for an immediate computation of CG-coefficients. First we will consider the special case of coupling of two angular momenta to their maximum angular momentum, before we will turn to the general case in section III. Based on these investigations we will provide a very simple way of calculating CG-coefficients in section IV. In the appendix we will prove the equivalence of our method with the Racah formula.

## II. ADDITION OF TWO ANGULAR MOMENTA TO THEIR MAXIMUM ANGULAR MOMENTUM

By speaking of a spin- $J$ -particle in the following we denote any object with angular momentum  $J$ , e.g. also orbital angular momenta, in order to avoid the inconvenient expression "objects with angular momentum  $J$ ".

### A. Decomposition of a particle into spin- $\frac{1}{2}$ -particles

According to Schwinger's oscillator model of angular momentum [1,4] every spin- $J$ -particle can be considered as a composition of  $2J$  spin- $\frac{1}{2}$ -particles. Then a particle described by the state  $|j;M\rangle$  with angular momentum  $J$  and  $z$ -component  $M$  consists of

$$\begin{aligned} j(J) &= 2J \text{ spin-}\frac{1}{2}\text{-particles,} \\ u(J;M) &= J+M \text{ spin-up particles } \uparrow, \\ d(J;M) &= J-M \text{ spin-down particles } \downarrow. \end{aligned}$$

This idea relies on the fact that the  $2J$  spin- $\frac{1}{2}$ -particles satisfy the same transformation relations under rotation as a spin- $J$ -particle. Thus, if we are interested in the angular momentum of a spin- $J$ -particle, i.e. its transformation properties under rotation, we might consider  $j = 2J$  spin- $\frac{1}{2}$ -particles as well. Only in this sense we might speak of a spin- $J$ -particle consisting of spin- $\frac{1}{2}$ -particles. In order to distinguish real spin- $\frac{1}{2}$ -particles from the constituent spin- $\frac{1}{2}$ -particles we will call the latter imaginary spin- $\frac{1}{2}$ -particles.

In the following the question, how many possibilities of decomposing a particle described by the state  $|j;M\rangle$  into imaginary spin- $\frac{1}{2}$ -particles exist (see table I), will play a crucial role. We know that there are  $u = J+M$  imaginary particles of the  $j$  particles after the decomposition in the state  $\uparrow$ . Then the number of possibilities is given by

$$s(j;u) = \frac{j!}{u!} \quad (2)$$

We say, the state  $|j;M\rangle$  consists of  $s$  imaginary states. As we will see later on, the CG-coefficients depend on the number of the imaginary states belonging to the particles under consideration. This number is given by the  $2J$ th row of the binomial expansion (Pascal's triangle) (see table II) for all (for the spin- $J$ -particle) possible  $M$ -values.

### B. Computation of the CG-coefficients for $J = J_1 + J_2$

The matrix

We will now investigate the special case of the coupling of two particles with angular momenta  $J_1$  and  $J_2$  to a system with the maximum angular momentum

$$J = J_1 + J_2; j = j_1 + j_2:$$

As we have seen in (1), the coupled state  $|j;M\rangle$  is composed of all uncoupled states  $|j_1;M_1; j_2;M_2\rangle$  for which  $M = M_1 + M_2$  holds. Since there must be no interference between the uncoupled states { this would lead to  $J < J_1 + J_2$  }, we expect real and positive CG-coefficients (according to the usual phase convention). This enables us to determine the CG-coefficients from square roots of probabilities. The square of the CG-coefficient  $\langle j_1;M_1; j_2;M_2 | j;M \rangle$  corresponds to the probability of finding the individual particles in the state  $|j_1;M_1; j_2;M_2\rangle$  at the instance of measuring the total angular momentum. This probability follows by decomposing the coupled and uncoupled states according to section IIA into

their imaginary spin- $\frac{1}{2}$ -particles and counting the number of imaginary states generated in this way. We denote the number of imaginary states of the coupled system by  $s_c$  and the one of the uncoupled system by  $s_{uc}$ , respectively.

$$s_c(j;u) = \binom{j}{u};$$

$$s_{uc}(j_1;u_1;j_2;u_2) = \binom{j_1}{u_1} \binom{j_2}{u_2};$$

The quantity  $s_{uc}$  is given by the product of the number of the imaginary states of the individual particles, because each of the  $\binom{j_1}{u_1}$  states of particle 1 can generate a new state with each of the  $\binom{j_2}{u_2}$  states of particle 2. The fact that the coupled state and the sum of all uncoupled states with  $M = M_1 + M_2$  describe the same physical system suggests that both should have the same number of imaginary states, leading to

$$s_c(j;u) = \sum_{u_1, u_2} s_{uc}(j_1;u_1;j_2;u_2); \quad (3)$$

where the sum  $s$  extends over all  $u_1, u_2$  with  $u_1 + u_2 = u$ , corresponding to  $M_1 + M_2 = M$ . Eq. (3) is known as the addition theorem for binomial coefficients (see e.g. [5]).

The desired probabilities, i.e. the squares of the CG-coefficients, will be obtained by the simple assumption that the combined system is found in each of the  $\binom{j}{u}$  imaginary states with equal probability.

If we could determine the imaginary state of the system, we would obtain a state after  $\binom{j_1}{u_1} \binom{j_2}{u_2}$  of  $\binom{j}{u}$  measurements in the average, which according to (3) originates uniquely from the decomposition of the uncoupled state  $j(M_1;M_2)i$ . Hence the desired probability of finding the system in the state  $j(M_1;M_2)i$  is given by  $\binom{j_1}{u_1} \binom{j_2}{u_2} \binom{j}{u}^{-1}$ . In this way we obtain an expression for the CG-coefficient in the case  $J = J_1 + J_2$ :

$$\begin{aligned} h(M_1;M_2)jJ;M i &= \frac{\binom{j_1}{u_1} \binom{j_2}{u_2} \binom{j}{u}^{-1}}{\sum s} \\ &= \frac{s_{uc}(j_1;u_1;j_2;u_2)}{s_c(j;u)}; \end{aligned} \quad (4)$$

Therefore, in this special case the CG-coefficients can be understood in an elementary way. Nature chooses the simplest way, not distinguishing any of the  $s_c$  imaginary states. The  $u = u_1 + u_2$   $s$ -states and the  $d = d_1 + d_2$   $s$ -states are coupled with equal probabilities to all possible imaginary states. Some of these states ( $s_{uc}$ ), however, are interpreted as an uncoupled state. Thus the coupled system consists according to the ratio  $\frac{s_{uc}}{s_c}$  of this uncoupled state.

Expressing (4) by  $J_1;M_1$  and using the definition of the binomial coefficients, we recover the Racah formula for  $J = J_1 + J_2$ ,

$$\begin{aligned} h(M_1;M_2)jJ;M i &= \frac{\sum \frac{(2J_1)!(2J_2)!}{(2J)!}}{\sum \frac{(J+M)!(J-M)!}{(J_1+M_1)!(J_1-M_1)!(J_2+M_2)!(J_2-M_2)!}}; \end{aligned} \quad (5)$$

as it can be found e.g. in Ref. [2].

In order to simplify the explicit calculation of CG-coefficients and the generalization to arbitrary total angular momenta, we define a matrix  ${}_0$  containing all essential information of the r.h.s. of (4) for all  $u_1, u_2$ . The crucial quantities are the values of  $s_{uc}$ . The values of  $s_c$  only take care for the correct normalization of the CG-coefficients and depend according to (3) on  $s_{uc}$ . We define the matrix  ${}_0$  via their components

$${}_0 \binom{j_1}{u_1} \binom{j_2}{u_2} s_{uc}(j_1;u_1;j_2;u_2) = \binom{j_1}{u_1} \binom{j_2}{u_2}; \quad (6)$$

Here  $u_1$  extends from 0 (1st row) to  $j_1$  and  $u_2$  from 0 (1st column) to  $j_2$ , respectively.  ${}_0$  is a  $2J_1 + 1 \times 2J_2 + 1$ -matrix. Sometimes we will use the angular momenta  $J_1;J_2$  as the arguments of  ${}_0 = {}_0(J_1;J_2)$ .

### Example: Addition of two spin-1-particles to spin 2

One of the essential advantages of (4) compared with the Racah formula (5) consists in the possibility of extracting all results of (4) easily by means of the matrix  ${}^0_0$ . As a first example we will calculate all CG-coefficients corresponding to the coupling of two spin-1-particles to a spin-2-state according to (4).  ${}^0_0$  follows according to (6) by multiplying two  $J = 1$ -rows of Pascal's triangle, denoted in the following way

$${}^0_0(1;1) = \begin{array}{c|ccc} 0 & 1 & 2 & 1 \\ \hline 1 & 1 & 2 & 1 \\ 2 & 2 & 4 & 2 \\ 1 & 1 & 2 & 1 \end{array} \begin{array}{c} 1 \\ C \\ A \end{array} = \begin{array}{c|ccc} 0 & 1 & 2 & 1 \\ \hline 2 & 2 & 4 & 2 \\ 1 & 1 & 2 & 1 \end{array} \begin{array}{c} 1 \\ C \\ A \end{array} :$$

Each of the  $3 \times 3$  components of this matrix reproduces the number of the imaginary states of the state  $j(M_1; M_2)i$ . The connection between the position in the matrix and the corresponding  $M$ -value is shown in table III. The maximum state  $j(1;1)i$  is found down-right. The diagonals (raising from left to right) correspond to a given  $M_1 + M_2 = M$ . The  $M$ -values of the diagonals increase from  $M = J_1 - J_2$  (up-left) to  $M = J_1 + J_2$  (down-right). The quantity  ${}^j_u$  appearing in (4) is extracted according to (3) by summing up the diagonalelements. In our example these sums give  $1;4;6;4;1g$ , corresponding to the  $J = 2$ -row of Pascal's triangle, as expected from (3). The CG-coefficients are read off from  ${}^0_0$  by dividing the components  ${}^{j_1}_{u_1} {}^{j_2}_{u_2}$  by the sum of the diagonalelements  ${}^j_u$  and extracting the square root. This procedure yields the following CG-coefficients, as can also be found in Ref. [3]

$$\begin{aligned} \mathcal{P}; 2i &= {}^j(1;1)i; \\ \mathcal{P}; 1i &= \sqrt{\frac{2}{4}} {}^j(1;0)i + \sqrt{\frac{2}{4}} {}^j(0;1)i; \\ \mathcal{P}; 0i &= \sqrt{\frac{1}{6}} {}^j(1;-1)i + \sqrt{\frac{4}{6}} {}^j(0;0)i + \sqrt{\frac{1}{6}} {}^j(-1;1)i; \\ \mathcal{P}; -1i &= \sqrt{\frac{2}{4}} {}^j(0;-1)i + \sqrt{\frac{2}{4}} {}^j(-1;0)i; \\ \mathcal{P}; -2i &= {}^j(-1;-1)i; \end{aligned}$$

Utilizing the  ${}^0_0$ -matrices we are able to determine all non-vanishing CG-coefficients with  $J = J_1 + J_2$  immediately. As a further example we present the coupling of a  $J_1 = \frac{3}{2}$ -particle with a  $J_2 = 1$ -particle to the  $J = \frac{5}{2}$ -state:

$${}^0_{\frac{3}{2}}(\frac{3}{2};1) = \begin{array}{c|ccc} 0 & 1 & 2 & 1 \\ \hline 1 & 1 & 2 & 1 \\ 3 & 3 & 6 & 3 \\ 3 & 3 & 6 & 3 \\ 1 & 1 & 2 & 1 \end{array} \begin{array}{c} 1 \\ C \\ A \end{array} = \begin{array}{c|ccc} 0 & 1 & 2 & 1 \\ \hline 3 & 3 & 6 & 3 \\ 3 & 3 & 6 & 3 \\ 1 & 1 & 2 & 1 \end{array} \begin{array}{c} 1 \\ C \\ A \end{array} :$$

### III. GENERAL ADDITION OF TWO ANGULAR MOMENTA

Next we will consider the general case in which two particles with  $J_1$  and  $J_2$  may couple to a total angular momentum  $J < J_1 + J_2$ . This problem can also be treated by means of imaginary spin- $\frac{1}{2}$ -particles. Assuming that two of these imaginary particles couple to spin 0, they do not contribute to the total angular momentum  $J$  anymore. If there are  $n$  spin-0-particles in a system of imaginary spin- $\frac{1}{2}$ -particles, the total angular momentum is reduced to  $J = J_1 + J_2 - n$ . In this way the general addition of two angular momenta can be described by two elementary processes of imaginary spin- $\frac{1}{2}$ -particles, namely the coupling of some imaginary particles to spin 0 and the coupling of the remaining particles to their maximum angular momentum according to section II. First we will consider the coupling of two spin- $\frac{1}{2}$ -particles to spin 0, before we will combine both processes.

## Coupling of two imaginary spin $\frac{1}{2}$ -particles to spin 0

From

$${}_0\left(\frac{1}{2}; \frac{1}{2}\right) = {}_0 \begin{array}{c|cc} & 1 & 1 \\ \hline 1 & 1 & 1 \\ 1 & 1 & 1 \end{array} A = \begin{array}{cc} 1 & 1 \\ 1 & 1 \end{array}$$

we obtain

$$j_1; 0i = \sqrt{\frac{1}{2}} j\left(\frac{1}{2}; \frac{1}{2}\right)i + \sqrt{\frac{1}{2}} j\left(\frac{1}{2}; \frac{1}{2}\right)i:$$

From the requirement  $h(0;0)j(1;0)i = 0$  we find

$$j_0; 0i = \sqrt{\frac{1}{2}} j\left(\frac{1}{2}; \frac{1}{2}\right)i - \sqrt{\frac{1}{2}} j\left(\frac{1}{2}; \frac{1}{2}\right)i:$$

We indicate the state  $j_0; 0i$  as

$$\% \& \quad \& \% : \tag{7}$$

A. The matrix  ${}_n$  of the coupling to  $J = J_1 + J_2$  is

As we will see, the general case  $J = J_1 + J_2$  can also be constructed from a matrix, called  ${}_n$  from which we can read off the CG-coefficient, similar to  ${}_0$ , directly. However, we cannot demand positiveness of the CG-coefficients any longer. Negative CG-coefficients will be identified from  ${}_n$  simply by a minus sign in front of the corresponding component.

In order to exemplify this prescription we will show  ${}_1\left(\frac{3}{2}; 1\right)$  here. The details of its calculation are given below. It describes the coupling of a spin- $\frac{3}{2}$ -particle with a spin-1-particle to spin  $\frac{3}{2}$ :

$${}_1\left(\frac{3}{2}; 1\right) = {}_1 \begin{array}{ccc|ccc} & 0 & 0 & 3 & 6 & 1 \\ \hline 2 & 2 & 1 & 8 & 2 & 8 \\ 8 & 1 & 2 & 6 & 3 & 0 \end{array} A :$$

From this we can read off the CG-coefficients (from down-left to up-right), e.g. from the 4th diagonal corresponding to  $M = \frac{1}{2}$ :

$$j_{\frac{3}{2}}; \frac{1}{2}i = \sqrt{\frac{6}{15}} j\left(\frac{3}{2}; 1\right)i + \sqrt{\frac{1}{15}} j\left(\frac{1}{2}; 0\right)i - \sqrt{\frac{8}{15}} j\left(\frac{1}{2}; 1\right)i:$$

The minus signs in  ${}_1$  just indicate that the corresponding CG-coefficient is negative. Calculating the normalization, these signs must not be considered in the sum of the diagonal elements, here 15.

We will regard two  ${}_n$  matrices as equivalent, if they differ only by a factor, denoted by  ${}_n \cong {}_n$ . Also two matrices are equivalent, if their diagonals, raising from left to right, deviate only by a factor. In both cases we find the same CG-coefficients.

The matrix  ${}_n$  follows from the requirements that

1. among the imaginary spin- $\frac{1}{2}$ -particles  $n$  Spin-0-particles arise

and

2. the remaining imaginary spin- $\frac{1}{2}$ -particles couple to their maximum spin.

Spin-0-particles arise according to (7), if the imaginary spin- $\frac{1}{2}$ -particles generate

$$\% \& - \quad \text{or} \quad \& \% \text{-states.}$$

The components of  $\rho_n$  play the role of non-normalized probabilities, analogously to the interpretation of  $\rho_0$ . They are composed from the probabilities of the processes 1. and 2. Defining

$U$  as the matrix describing the probabilities for the state  $\epsilon_1 \epsilon_2$ ,

$V$  as the matrix describing the probabilities for the state  $\epsilon_1 \epsilon_2$ , and

$\tilde{\rho}_n$  as the matrix describing the probabilities for the coupling of the remaining imaginary particles to their maximum spin,

the above requirement translates directly to the matrix equation

$$\rho_n = (U - V)^{[n]} \tilde{\rho}_n; \quad (8)$$

where the products (and) and the subtractions (or) between the matrices have to be performed for each single component. When we talk of probabilities in the following, we may not refer to normalized probabilities, as the product by components in (8) allows for arbitrary factors (normalization) in  $U$  and  $\tilde{\rho}_n$ .

#### B. The matrix $(U - V)^{[n]}$ of $n$ spin-0-particles

For calculating  $(U - V)^{[n]}$  we need the probabilities of creating  $\epsilon_1$ - or  $\epsilon_2$ -states from imaginary spin- $\frac{1}{2}$ -particles. The probability of creating  $\epsilon_1$  is proportional to the probability of finding  $\epsilon_1$  at particle 1 and  $\epsilon_2$  at particle 2 at the same time. This in turn is proportional to the product of the number of the imaginary particles in the corresponding states. An analogous statement holds for  $\epsilon_2$ . Therefore we define

$$\begin{aligned} U_{j_1 j_2} &= u_1 (j_2 - u_2); \\ V_{j_1 j_2} &= d_1 u_2 = (j_1 - u_1) u_2; \end{aligned} \quad (9)$$

leading to

$$(U - V)_{j_1 j_2} = u_1 d_2 - d_1 u_2;$$

The expression  $u_1 d_2 - d_1 u_2$  can be interpreted (if it is positive) as the surplus of  $\epsilon_1 \epsilon_2$ -states of an uncoupled state. If it is negative it yields the (negative) excess of  $\epsilon_1 \epsilon_2$ -states. This pays attention to the fact that according to (1) interference can occur only between uncoupled states but not within an uncoupled state itself.

Performing the exponentiation  $^{[n]}$  one has to take into account that the probabilities  $U$  depend on the number of the spin-0-particles already generated. If e.g. already one  $\epsilon_1 \epsilon_2$ -state has been built, there are only  $u_1 - 1$  and  $d_2 - 1$  particles available. Therefore the exponentiation means

$$(U - V)^{[n]}_{j_1 j_2} = \sum_{k=0}^n \binom{n}{k} (u_1 d_2)^{[n-k]} (d_1 u_2)^{[k]}; \quad (10)$$

where

$$\begin{aligned} (u_1 d_2)^{[n-k]} &= \prod_{i=0}^{n-k-1} (u_1 - i) (d_2 - i); \\ (d_1 u_2)^{[k]} &= \prod_{i=0}^{k-1} (d_1 - i) (u_2 - i); \end{aligned} \quad (11)$$

Example:  $(U - V)^{[n]}$  for  $J_1 = \frac{3}{2}$  and  $J_2 = 1$

As an example we will calculate  $U$  and  $(U - V)^{[2]}$  for the coupling of  $J_1 = \frac{3}{2}$  and  $J_2 = 1$ , already mentioned above. The  $U$  and  $V$  matrices in this case read

$$= \begin{array}{c|ccc} 0 & 2 & 1 & 0 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 0 \\ 1 \\ 2 \\ 3 \end{array} & \begin{array}{c} 0 \\ 2 \\ 4 \\ 6 \end{array} & \begin{array}{c} 0 \\ 0 \\ 0 \\ 3 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ C \\ A \end{array}, V = \begin{array}{c|ccc} 0 & 0 & 1 & 2 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 3 \\ 2 \\ 1 \\ 0 \end{array} & \begin{array}{c} 0 \\ 3 \\ 2 \\ 0 \end{array} & \begin{array}{c} 6 \\ 4 \\ 2 \\ 0 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ C \\ A \end{array};$$

leading to

$$V = \begin{array}{c|ccc} 0 & 0 & 3 & 6 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 2 \\ 4 \\ 6 \end{array} & \begin{array}{c} 1 \\ 1 \\ 3 \end{array} & \begin{array}{c} 4 \\ 2 \\ 0 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ A \end{array} :$$

The matrix  $(V)^{[2]}$  is given according to (10) and (11) by

$$(V)^{[2]} = \begin{array}{c|ccc} 0 & 2 & V & V V^0; \end{array}$$

where

$$V_{j_1, j_2}^0 = (u_1 - 1)(d_2 - 1)$$

and

$$V_{j_1, j_2}^0 = (d_1 - 1)(u_2 - 1)$$

read

$$= \begin{array}{c|ccc} 0 & 1 & 0 & 0 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 0 \\ 0 \\ 1 \\ 2 \end{array} & \begin{array}{c} 0 \\ 0 \\ 0 \\ 2 \end{array} & \begin{array}{c} 0 \\ 0 \\ 0 \\ 0 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ C \\ A \end{array}, V^0 = \begin{array}{c|ccc} 0 & 0 & 0 & 1 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 2 \\ 1 \\ 0 \\ 0 \end{array} & \begin{array}{c} 0 \\ 0 \\ 0 \\ 0 \end{array} & \begin{array}{c} 2 \\ 1 \\ 0 \\ 0 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ C \\ A \end{array} :$$

From this we get

$$(V)^{[2]} = \begin{array}{c|ccc} 0 & 0 & 0 & 0 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 0 \\ 4 \\ 12 \end{array} & \begin{array}{c} 0 \\ 0 \\ 0 \end{array} & \begin{array}{c} 0 \\ 0 \\ 0 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ A \end{array} + \begin{array}{c|ccc} 0 & 0 & 0 & 0 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 0 \\ 2 \\ 0 \end{array} & \begin{array}{c} 0 \\ 2 \\ 0 \end{array} & \begin{array}{c} 0 \\ 0 \\ 0 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ A \end{array} + \begin{array}{c|ccc} 0 & 0 & 0 & 12 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 0 \\ 0 \\ 0 \end{array} & \begin{array}{c} 0 \\ 0 \\ 0 \end{array} & \begin{array}{c} 4 \\ 0 \\ 0 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ A \end{array}$$

$$= \begin{array}{c|ccc} 0 & 0 & 4 & 4 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 0 \\ 4 \\ 12 \end{array} & \begin{array}{c} 4 \\ 4 \\ 0 \end{array} & \begin{array}{c} 4 \\ 0 \\ 0 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ A \end{array} \neq \begin{array}{c|ccc} 0 & 0 & 1 & 1 \\ \hline \begin{array}{c} B \\ C \\ A \end{array} & \begin{array}{c} 0 \\ 1 \\ 3 \end{array} & \begin{array}{c} 1 \\ 1 \\ 0 \end{array} & \begin{array}{c} 1 \\ 0 \\ 0 \end{array} \end{array} \begin{array}{c} 1 \\ C \\ A \end{array} :$$

All higher exponents ( $n = 3; 4; \dots$ ) of  $V$  vanish in accordance with the rule  $[j_1 - j_2] = j_1 + j_2$ . In order to calculate the CG-coefficients of the above example, we need the matrices  $\tilde{\sim}_1$  and  $\tilde{\sim}_2$  of the remaining system in addition. Their computation is the topic of the next section.

### C. The matrix $\tilde{\sim}_n$ of the remaining system

The matrix  $\tilde{\sim}_n$  follows directly from  $\tilde{\sim}_0$  by removing the imaginary spin- $\frac{1}{2}$ -particles, contained in  $(V)^{[n]}$ . Here removing a  $\frac{1}{2}$  from the particle means that the total number of imaginary spin- $\frac{1}{2}$ -particles and the number of  $\frac{1}{2}$  is reduced by one; i.e., we replace

$$j_i \rightarrow j_i - 1; \\ u_i \rightarrow u_i - 1;$$

Analogously a  $\frac{1}{2}$  is removed by

$$\begin{aligned} j_i &= j_i - 1; \\ d_i &= d_i - 1; \end{aligned}$$

For constructing  $\sim_1$  a spin-0-particle has to be removed from  $\sim_0$ ; i.e., according to (7) a  $\begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix}$  will be removed from particle 1 and a  $\begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix}$  from particle 2 at the same time or a  $\begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix}$  from particle 1 and a  $\begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix}$  from particle 2. Together with

$$\sim_0 \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} = \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix}$$

we get

$$\sim_1 \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} = \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} - \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} - \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} ;$$

where the removing of a  $\begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix}$  has been performed via

$$\begin{smallmatrix} j_1 \\ u_1 \end{smallmatrix} = \begin{smallmatrix} j_1 \\ d_1 \end{smallmatrix} - \begin{smallmatrix} j_1 \\ d_1 - 1 \end{smallmatrix} = \begin{smallmatrix} j_1 \\ u_1 \end{smallmatrix} :$$

The binomial coefficients vanish for all unphysical values, e.g. if  $j_1 - 1 < u_1$  or  $u_1 - 1 < 0$ . This corresponds to the fact that there is no state with  $u_1 < 0$  or  $d_1 < 0$ . The matrix  $\sim_2$  is obtained from  $\sim_1$  by removing an additional spin-0-particle:

$$\begin{aligned} \sim_2 \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} &= \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} - \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} \\ &+ \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} : \end{aligned}$$

In general  $\sim_n$  is given by

$$\sim_n \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} = \sum_{k=0}^n (-1)^k \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} - \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} + \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} - \begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix} + \dots : \quad (12)$$

The matrices  $\sim_n$  can be calculated easily, as they consist essentially out of  $\sim_0(J_1 - \frac{n}{2}; J_2 - \frac{n}{2})$ . This reflects the fact that a system with  $J = J_1 + J_2 - n$  can be imagined as originated from coupling of spin  $J_1 - \frac{n}{2}$  and spin  $J_2 - \frac{n}{2}$  to their maximum spin. This will be illustrated in the following example.

**Example:**  $\sim_n$  for  $J_1 = \frac{3}{2}$  and  $J_2 = 1$

We compute  $\sim_1$  and  $\sim_2$  in the case of the coupling of  $J_1 = \frac{3}{2}$  and  $J_2 = 1$  from (12). First, however, we will repeat  $\sim_0$ :

$$\sim_0 \left( \frac{3}{2}; 1 \right) = \begin{pmatrix} \begin{smallmatrix} 0 & 1 & 2 & 1 \\ 1 & 2 & 1 \end{smallmatrix} \\ \begin{smallmatrix} 3 & 6 & 3 \\ 3 & 6 & 3 \end{smallmatrix} \end{pmatrix} :$$

For physical values of  $u_1$  and  $u_2$  the expression  $\begin{smallmatrix} j_1 & j_2 \\ u_1 & u_2 \end{smallmatrix}$  in (12) leads to the smaller matrix  $\sim_0(J_1 - \frac{n}{2}; J_2 - \frac{n}{2})$ , in our example

$$\sim_0 \left( 1; \frac{1}{2} \right) = \begin{pmatrix} \begin{smallmatrix} 0 & 1 \\ 1 & 1 \end{smallmatrix} \\ \begin{smallmatrix} 2 & 2 \\ 1 & 1 \end{smallmatrix} \end{pmatrix}$$

if  $n = 1$  and



$${}_0\left(\frac{1}{2};0\right) = \begin{matrix} 1 \\ 1 \end{matrix}$$

if  $n = 2$ . For all other values of  $u_1$  and  $u_2$  the expression is identical to zero. The value of  $k$  fixes the position of these matrices:  $k=0$  corresponds to down-left,  $k=n$  to up-right. The matrices  $\sim_1$  and  $\sim_2$  thus are found easily:

$$\sim_1 = \begin{matrix} & 0 & 0 & 0 & 1 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 1 & 1 & 0 \\ 2 & 2 & 0 \\ 1 & 1 & 0 \end{matrix} \end{matrix} \begin{matrix} & 0 & 0 & 1 & 1 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 0 & 2 & 2 \\ 0 & 1 & 1 \\ 0 & 0 & 0 \end{matrix} \end{matrix} = \begin{matrix} & 0 & 1 & 1 & 1 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 1 & 1 & 2 \\ 2 & 1 & 1 \\ 1 & 1 & 0 \end{matrix} \end{matrix} \begin{matrix} C \\ A \end{matrix};$$

$$\begin{aligned} \sim_2 &= \begin{matrix} & 0 & 0 & 0 & 1 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 0 & 0 & 0 \\ 1 & 0 & 0 \\ 1 & 0 & 0 \end{matrix} \end{matrix} \begin{matrix} & 0 & 0 & 0 & 1 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 0 & 1 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 0 \end{matrix} \end{matrix} \begin{matrix} & 0 & 0 & 1 & 1 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 0 & 0 & 1 \\ 0 & 0 & 1 \\ 0 & 0 & 0 \end{matrix} \end{matrix} \begin{matrix} C \\ A \end{matrix} \\ &= \begin{matrix} & 0 & 0 & 1 & 1 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 0 & 2 & 1 \\ 1 & 2 & 0 \\ 1 & 0 & 0 \end{matrix} \end{matrix} \begin{matrix} C \\ A \end{matrix} : \end{aligned}$$

D. Results of the example  $J_1 = \frac{3}{2}$  and  $J_2 = 1$

We are now able to give all CG-coefficients in form of the matrices  ${}_0$  to  ${}_2$ , producing the well-known results [3].

Coupling of  $J_1 = \frac{3}{2}$  and  $J_2 = 1$  to  $J = \frac{5}{2}$ :

$${}_0\left(\frac{3}{2};1\right) = \begin{matrix} & 0 & 1 & 2 & 1 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 3 & 6 & 3 \\ 3 & 6 & 3 \\ 1 & 2 & 1 \end{matrix} \end{matrix} \begin{matrix} C \\ A \end{matrix} :$$

Coupling of  $J_1 = \frac{3}{2}$  and  $J_2 = 1$  to  $J = \frac{3}{2}$ :

From (8) together with the results of the sections IIIB and IIIC we end up with

$$\begin{aligned} {}_1 &= \begin{matrix} & (V) \sim_1 \\ 0 & 0 & 3 & 6 & 1 & 0 \end{matrix} \begin{matrix} & 0 & 1 & 1 & 1 & 0 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 2 & 1 & 4 \\ 4 & 1 & 2 \\ 6 & 3 & 0 \end{matrix} \end{matrix} \begin{matrix} & 0 & 1 & 1 & 2 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 1 & 1 & 2 \\ 2 & 1 & 1 \\ 1 & 1 & 0 \end{matrix} \end{matrix} \begin{matrix} & 0 & 0 & 3 & 6 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 2 & 1 & 8 \\ 8 & 1 & 2 \\ 6 & 3 & 0 \end{matrix} \end{matrix} \begin{matrix} C \\ A \end{matrix} : \end{aligned}$$

It should be noticed once more that a minus sign in front of a component only indicates that the corresponding CG-coefficient is negative. Thus a minus sign is transferred to the product matrix, although if both the components which are multiplied are negative. (As we will see in the next section (13), the components which are multiplied have the same sign.) The matrix  ${}_1$  has been discussed already in section IIIA, where the extraction of the CG-coefficients from it has been demonstrated.

Coupling of  $J_1 = \frac{3}{2}$  and  $J_2 = 1$  to  $J = \frac{1}{2}$ :

$$\begin{aligned} {}_2 &= \begin{matrix} & (V) \sim_2 \\ 0 & 0 & 0 & 3 & 1 & 0 \end{matrix} \begin{matrix} & 0 & 0 & 1 & 1 & 0 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 0 & 1 & 1 \\ 1 & 1 & 0 \\ 3 & 0 & 0 \end{matrix} \end{matrix} \begin{matrix} & 0 & 2 & 1 & 1 & 0 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 0 & 2 & 1 \\ 1 & 2 & 0 \\ 1 & 0 & 0 \end{matrix} \end{matrix} \begin{matrix} & 0 & 0 & 3 & 1 \\ \begin{matrix} B \\ C \\ A \end{matrix} & \begin{matrix} 0 & 2 & 1 \\ 1 & 2 & 0 \\ 3 & 0 & 0 \end{matrix} \end{matrix} \begin{matrix} C \\ A \end{matrix} : \end{aligned}$$

#### IV . A L T E R N A T I V E F O R M U L A T I O N

So far we are able to compute all CG-coefficients from (8)

$$n = (V)^{[n]} \sim_n :$$

Comparing the definition (10) of  $(V)^{[n]}$  with the definition (12) of  $\sim_n$ , the following relation between both the matrices can be recognized:

$$\sim_n \triangleq (V)^{[n]} \cdot 0 : \quad (13)$$

This relation offers the possibility of finding an alternative formulation that requires only the knowledge of one of the both matrices and  $0$ . It can be shown directly by multiplying  $(V)^{[n]}$  with  $0$ . For this purpose the terms (11) in (10) are written as

$$(u_1 d_2)^{[n-k]} = \frac{u_1! d_2!}{(u_1 - (n-k))! (d_2 - (n-k))!};$$

$$(d_1 u_2)^{[k]} = \frac{d_1! u_2!}{(d_1 - k)! (u_2 - k)!};$$

Multiplying these terms with the components of  $0$

$$\frac{j_1}{u_1} \frac{j_2}{u_2} = \frac{j_1! j_2!}{u_1! d_1! u_2! d_2!}$$

yields

$$(u_1 d_2)^{[n-k]} (d_1 u_2)^{[k]} \frac{j_1}{u_1} \frac{j_2}{u_2}$$

$$= \frac{j_1!}{(u_1 - (n-k))! (d_1 - k)!} \frac{j_2!}{(u_2 - k)! (d_2 - (n-k))!};$$

This expression is proportional to

$$\frac{j_1 - n}{u_1 - (n-k)} \frac{j_2 - n}{u_2 - k}$$

$$= \frac{(j_1 - n)!}{(u_1 - (n-k))! (d_1 - k)!} \frac{(j_2 - n)!}{(u_2 - k)! (d_2 - (n-k))!};$$

showing up in (12). Thus (13) is proven, from which the following equations, equivalent to (8), result:

$$n \triangleq \sim_n^2 \cdot 0^{-1}; \quad (14)$$

$$n \triangleq (V)^{[n]} \cdot 0^2 : \quad (15)$$

Here again we have to take care of the signs when squaring a matrix. The matrix  $0^{-1}$  contains the inverse components of  $0$  (or a multiple of them).

As we will show in the appendix, (14) and therefore also (8) are equivalent to the Racah formula.

#### Example

We check (14) using the example  $2 \left( \frac{3}{2}; 1 \right)$ . In section IIIC we found

$$\sim_2 = \begin{pmatrix} \begin{matrix} 0 & 0 & 0 & 1 \\ 0 & 2 & 1 \\ 1 & 2 & 0 \\ 1 & 0 & 0 \end{matrix} & \begin{matrix} 1 \\ C \\ A \end{matrix} \end{pmatrix} \quad \sim_2^2 = \begin{pmatrix} \begin{matrix} 0 & 0 & 0 & 1 \\ 0 & 4 & 1 \\ 1 & 4 & 0 \\ 1 & 0 & 0 \end{matrix} & \begin{matrix} 1 \\ C \\ A \end{matrix} \end{pmatrix} :$$

Furthermore,

$$_0 = \begin{pmatrix} 0 & 1 & 2 & 1 \\ B & 3 & 6 & 3 \\ C & 3 & 6 & 3 \\ 1 & 2 & 1 \end{pmatrix} \quad {}_0^1 = \begin{pmatrix} 0 & 6 & 3 & 6 \\ B & 2 & 1 & 2 \\ C & 2 & 1 & 2 \\ 6 & 3 & 6 \end{pmatrix} :$$

The final result reads

$$\begin{aligned} {}_2 &\triangleq \begin{pmatrix} \sim^2 & 1 \\ 2 & 0 \end{pmatrix} \\ &= \begin{pmatrix} B & 0 & 4 & 1 \\ C & 1 & 4 & 0 \\ 1 & 0 & 0 \end{pmatrix} \begin{pmatrix} C & B & 2 & 1 & 2 \\ A & C & 2 & 1 & 2 \\ 6 & 3 & 6 \end{pmatrix} = \begin{pmatrix} B & 0 & 4 & 2 \\ C & 2 & 4 & 0 \\ 6 & 0 & 0 \end{pmatrix} \begin{pmatrix} C \\ A \end{pmatrix} ; \end{aligned}$$

which is equivalent to the result of section IIID up to a factor. In conclusion, (14) provides a very simple method for a practicable computation of CG-coefficients. For obtaining  $\sim_n^2$  and  $_0^1$  only the matrices  $_0(J_1; J_2)$  and  $_0(J_1 - \frac{n}{2}; J_2 - \frac{n}{2})$  are needed. Actually, the calculation can be simplified further by considering the reflection symmetry of  $_0$  and  $_n$  at their center, if  $n$  is even. If  $n$  is odd, the signs of the reflected components have to be changed. This property of  $_0$  and  $_n$  corresponds to the relation  $h(M_1; M_2)j; M_i = (-1)^{J_1+J_2-J} h(M_1; M_2)j; M_i [2]$ . Because of the component-like multiplication and subtraction of the matrices yielding  $_n$ , only half of the components of  $_0(J_1; J_2)$  and  $_0(J_1 - \frac{n}{2}; J_2 - \frac{n}{2})$  has to be computed.

## V. CONCLUSIONS

In this paper we have demonstrated how the coupling of two angular momenta,  $J_1$  and  $J_2$ , can be understood easily by decomposing each of the angular momenta into imaginary spin- $\frac{1}{2}$ -particles. Counting the possibilities of decomposing the angular momenta  $J_1$  into these imaginary particles by simple combinatorial manipulations (binomial coefficients), leads to the CG-coefficients in the case of coupling to maximum angular momentum  $J = J_1 + J_2$ . Here the basic assumption of equally distributed probabilities for each of the decompositions has been adopted. For extracting the CG-coefficients, it is convenient to introduce the matrix  $_0$ , defined in (6). The CG-coefficients can be read off directly from the components of this matrix divided by the sum of the diagonal elements and extracting the square root.

The general case,  $J = J_1 + J_2 - n$ , can be considered as the coupling of  $2n$  imaginary spin- $\frac{1}{2}$ -particles to spin 0 and the coupling of the remaining imaginary particles to maximum spin. In this way the matrix  $_n$ , defined in (8), results, from which the CG-coefficients can be read off in the same way as from  $_0$ , apart from the fact that minus signs in front of the components simply indicate negative CG-coefficients. Utilizing a relation between the matrix describing the coupling of the imaginary particles to spin 0 and the one describing the coupling of the remaining system to maximum spin, the matrix  $_n$  can be found easily by (14). This method, shown to be equivalent to the Racah formula, requires much less computational effort than the latter one.

The new, probabilistic interpretation of the addition of angular momenta, presented here, provides an elegant and practicable way of computing all CG-coefficients for the coupling of two arbitrary angular momenta.

## APPENDIX: EQUIVALENCE TO THE RACAH FORMULA

Here (14),  $_n \triangleq \sim_n^2 {}_0^1$ , shall be derived from the Racah formula (see e.g. [2])

$$h(M_1; M_2)j; M_i = \sum_{k_s} \sum_{k_p} \frac{(-1)^{k_p} \frac{s}{(2J+1)} \frac{(J_1+J_2-J)!(J_1-J_2+J)!(J_2-J_1+J)!}{(J_1+J_2+J+1)!(J_1-M_1-k)^2!(J_2+M_2-k)^2 k!}}{\frac{(J_1+M_1)!(J_2+M_2)!(J+M)!}{(J-J_2+M_1+k)^2 (J-J_1-M_2+k)^2 (J_1+J_2-J-k)^2}} : \quad (A1)$$

For this purpose we express the angular momenta showing up in the Racah formula by the number of imaginary particles, substituting

$$\begin{aligned}
J_i &= j_i = 2; \\
J &= J_1 + J_2 \quad n = j_1 = 2 + j_2 = 2 \quad n; \\
M_i &= u_i \quad j_i = 2; \\
M &= M_1 + M_2 = u_1 + u_2 \quad j_1 = 2 \quad j_2 = 2;
\end{aligned}$$

Then we find

$$\begin{aligned}
h(M_1; M_2) j j; M_i = & \sum_k \binom{n}{k} \frac{(-1)^k \frac{(j+1)u!}{(j+1+n)!}}{\frac{(j_1-n)!(j_2-n)!u_1!u_2!}{(d_1-k)! (u_1-n+k)! (d_2-n+k)! (u_2-k)!}}; \quad (A2)
\end{aligned}$$

where

$$\begin{aligned}
u &= u_1 + u_2 \quad n; \\
d &= d_1 + d_2 \quad n; \\
j &= j_1 + j_2 \quad 2n;
\end{aligned}$$

The components  $h_{n, j_1, j_2}$  of the matrix  $h$  follow by squaring the CG-coefficients, taking care of their sign (indicated by the exponent  $2j$ ). The first square root in (A2) can be omitted, because it is constant within the diagonals of the matrix. Thus we get

$$h_{n, j_1, j_2} = \sum_k \binom{n}{k} \frac{(-1)^k \frac{(j_1-n)!(j_2-n)!u_1!u_2!}{(d_1-k)! (u_1-n+k)! (d_2-n+k)! (u_2-k)!}}{1} : \quad (A3)$$

Multiplying (A3) with the components

$$h_{0, j_1, j_2} = \frac{j_1!}{u_1!} \frac{j_2!}{u_2!} = \frac{j_1!}{u_1!} \frac{j_2!}{u_2!}$$

of the matrix  $h_0$  leads to (neglecting the constant factor  $j_1!j_2!$ )

$$h_{n, j_1, j_2} h_{0, j_1, j_2} = \sum_k \binom{n}{k} \frac{j_1-n}{u_1-n+k} \frac{j_2-n}{u_2-k} \frac{(-1)^k}{1} :$$

The r.h.s is identical with the square of the components of  $\tilde{h}_n$  in (12). Hence  $h_n \approx \tilde{h}_n^2$  has been derived from the Racah formula.

- [1] J.J. Sakurai, Modern Quantum Mechanics (Addison-Wesley, Reading, 1994).
- [2] A. Messiah, Quantum mechanics, Volume II (North Holland, Amsterdam, 1963).
- [3] Particle data group, Phys. Rev. D 50, 1287 (1994).
- [4] J. Schwinger, in: Quantum Theory of Angular Momentum, edited by L.C. Biedenharn and H. Van Dam (Academic Press, New York, 1965), p.229.
- [5] M. Abramowitz and I.A. Stegun, Handbook of Mathematical Functions (National Bureau of Standards, Washington, 1964).

	M =				
	1	$\frac{1}{2}$	0	$\frac{1}{2}$	1
$J = \frac{1}{2}$		1			
$J = 1$	1		1		
$\vdots$					

TABLE I. Imaginary states of a particle described by the state  $|J;M\rangle$

$s(J;M)$	M =							
	2	$\frac{3}{2}$	1	$\frac{1}{2}$	0	$\frac{1}{2}$	1	$\frac{3}{2}$
$J = \frac{1}{2}$				1		1		
$J = 1$			1		2		1	
$J = \frac{3}{2}$		1		3		3		1
$J = 2$	1		4		6		4	
$\vdots$								

TABLE II. Number of the imaginary states of a particle described by the state  $|J;M\rangle$

	M <sub>2</sub>	1	0	1
M <sub>1</sub>	$u_1 u_2$	0	1	2
1	0	1	2	1
0	1	2	4	2
1	2	1	2	1

TABLE III. M and u-values of  $\phi_0$