

The Zero-Difference Properties of Functions and Their Applications

Zongxiang Yi^{a,b,*}, Dingyi Pei^{a,b}, Chunming Tang^{a,b}

^aSchool of Mathematics and Information Science, Guangzhou University, Guangzhou, 510006, P.R. China.

^bGuangdong Provincial Key Laboratory of Information Security, Guangzhou University, Guangzhou, 510006, P.R. China.

Abstract

A function f from an Abelian group $(A, +)$ to an Abelian group $(B, +)$ is (n, m, S) zero-difference (ZD), if $S = \{\lambda_\alpha \mid \alpha \in A \setminus \{0\}\}$ where $n = |A|$, $m = |f(A)|$ and $\lambda_\alpha = |\{x \in A \mid f(x+\alpha) = f(x)\}|$. A function is called zero-difference balanced (ZDB) if $S = \{\lambda\}$ where λ is a constant number. ZDB functions have many good applications. However it is point out that many known zero-difference balanced functions are already given in the language of partitioned difference family (PDF). The problem that whether zero-difference "not balanced" functions still have good applications as ZDB functions, is investigated in this paper. By using the change point technic, zero-difference functions with good applications are constructed from known ZDB function. Then optimal difference systems of sets (DSS) and optimal frequency-hopping sequences (FHS) are obtained with new parameters. Furthermore the sufficient and necessary conditions of these being optimal, are given.

Keywords: Zero-Difference, Zero-Difference Balanced, Constant Weight Code, Difference System of Sets, Frequency-Hopping Sequence

1. Introduction

Let $(A, +)$ and $(B, +)$ be two finite Abelian groups. Denote $A^* = A \setminus \{0\}$. A function from A to B is an (n, m, λ) zero-difference balanced (ZDB) function, if there exists a constant number λ such that for any nonzero element $a \in A^*$,

$$|\{x \in A \mid f(x+a) - f(x) = 0\}| = \lambda,$$

where $n = |A|$ and $m = |f(A)|$. Carlet and Ding first proposed the concept of ZDB function in 2004 [7]. Some optimal objects can be obtained by ZDB functions, such as constant composition codes (CCC), constant weight codes (CWC), difference systems of sets (DSS) and frequency-hopping sequences (FHS). Hence many researchers have been working on this topic (see [5–7, 14, 15, 18, 34, 40, 43, 45, 47–49] and the references therein).

A difference family (DF) is collection \mathcal{F} of some nonempty subsets (blocks) \mathcal{F}_i of a group $(G, +)$ such that for any nonzero elements α of G , there has exactly λ representations of $\alpha = x - y$ where $x \neq y$ and $x, y \in \mathcal{F}_i$. If \mathcal{F} is a partition of G , then \mathcal{F} is called a partitioned difference family (PDF). It is well known that a ZDB function is equivalent to a PDF. Many PDFs were constructed since 1970 (see [4, 22, 24, 30, 41] and the references therein). Thus before a ZDB function is claimed to be new, the authors should check carefully whether the ZDB function is equivalent to an already known PDF. For example, Buratti and Jungnickel recently point out that many recent results on ZDB function reproduced the earlier results on PDF [3]. In the view of definition, ZDB function has more constraints and PDF is more cleaner. As a result, ZDB function has more useful properties and can be applied to complicated applications. For example, when the underlying group is cyclic, frequency-hopping sequences can be obtained from the blocks of a PDF. But it is impossible to consider the linear complexity of FHSs without equipping an binary operation over blocks. That is why we use the terminology of ZDB function rather than the terminology of PDF when considering further applications.

*Corresponding author at: School of Mathematics and Information Science, Guangzhou University, Guangzhou, 510006, P.R. China.

Email addresses: tpu01yzx@gmail.com (Zongxiang Yi), dypei4188@163.com (Dingyi Pei), ctang@gzhu.edu.cn (Chunming Tang)

To construction more optimal objects, we turn to study the generalization of ZDB function, i.e., relaxing the "balanced" condition on "zero-difference". There are some work on the generalization of ZDB function. In 2014, Carlet et al. proposed an concept called differentially δ -vanishing [8]. A function from A to B is differentially δ -vanishing, if for any nonzero element $a \in A^*$,

$$1 \leq |\{x \in A \mid f(x+a) - f(x) = 0\}| \leq \delta.$$

Any (n, m, λ) ZDB function is differentially λ -vanishing (λ -DV). But there had been little research on this concept, until Jiang and Liao proposed a related concept called generalized zero-difference balanced (G-ZDB) function in 2016 [26]. A function from A onto B is an (n, m, S) generalized zero-difference balanced function, if there exists a constant set $S \subset \mathbb{N}$ such that for any nonzero element $a \in A^*$,

$$|\{x \in A \mid f(x+a) - f(x) = 0\}| \in S,$$

where $n = |A|$ and $m = |f(A)|$. Then some objects can be obtained by G-ZDB functions [25, 26, 33], but they are not optimal. The main reason is that the size of S is too large, which implies they are not really zero-difference balanced. Therefore, in 2018, Xu et al. gave another concept called near zero-difference balanced (N-ZDB) function [42]. A function from A to B is an (n, m, λ, t) near zero-difference balanced function, if there exist a constant number λ and a t -subset T of A^* such that for any nonzero element $a \in A^*$,

$$|\{x \in A \mid f(x+a) - f(x) = 0\}| = \begin{cases} \lambda, & a \in T \\ \lambda + 1, & a \notin T \end{cases},$$

where $n = |A|$ and $m = |f(A)|$.

The four concepts ZDB, λ -DV, G-ZDB and N-ZDB, are close related to each other. Among them, G-ZDB captures most useful information. However the concept of G-ZDB would lead to the misunderstanding that such G-ZDB functions are really "balanced". Thus the concept of zero-difference (ZD) is used instead of G-ZDB.

Definition 1. A function f from an Abelian group $(A, +)$ to an Abelian group $(B, +)$ is (n, m, S) zero-difference (ZD), if $S = \{\lambda_\alpha \mid \alpha \in A \setminus \{0\}\}$ where $n = |A|$, $m = |f(B)|$ and $\lambda_\alpha = |\{x \in A \mid f(x + \alpha) = f(x)\}|$. A function is called an (n, m, S) ZD function if it is (n, m, S) ZD.

Recently Xu et al. and Li et al. shown that optimal DSSs and FHSs can be obtained via ZD functions in 2018, respectively [31, 42]. Thus we will study the ZD property of cryptographic functions with good applications. Specifically, our contributions are as follows:

- We propose a framework to construct ZD functions from some type of ZDB functions, namely the change point technic;
- We obtain optimal CWCs, DSSs and FHSs from ZD functions and generalize the work in [42];
- We give the sufficient and necessary conditions of ZD functions having good applications;

The rest of this paper is organized as follows. In Section 2, some properties of ZD functions are given and many ZD functions are constructed from some known ZDB functions. In Section 3, the conditions of the constructed ZD functions having good applications are studied and many optimal objects are obtained. Section 4 conclusions this paper.

2. A Framework to Construct Zero-Difference Functions

2.1. Notations

Let $(R, +, \times)$ be a ring with an identity. R^\times denote the set of all invertible elements in monoid (R, \times) . For a set A , define $A^* = A \setminus \{0\}$ if A is a subset of an additive group.

Operations on sets are defined as usual. For any two set A, B , $A + B = \{a + b \mid a \in A, b \in B\}$ if $a + b$ is well defined. For any element x and any set A , $x + A = \{x + a \mid a \in A\}$, $xA = \{xa \mid a \in A\}$. Similarly, $A - B$, $x - A$, Ax , $A - x$ and $A + x$ can be defined in this manner.

To resolve the ambiguity, several notions are defined. The size of a set S is denoted by $|S|$. Let f be a function from A to B . The set of all images is denoted by $f(A) = \{f(x) \mid x \in A\}$. The preimage of an element $b \in B$ is denoted by $f^{-1}(b) = \{x \in A \mid f(x) = b\}$. The set of all preimages is denoted by $\text{PI}(f) = \{f^{-1}(b) \mid b \in B\}$. The multi-set of sizes of all preimage is denoted by $\text{SP}(f) = \{|S| \mid S \in \text{PI}(f)\}$. Using the language of combinatorics, a multi-set can be represented as $\{r_1^{e_1}, r_2^{e_2}, \dots, r_k^{e_k}\}$ which means that r_i appears exactly e_i times. If $e_i = 1$, then e_i can be omitted.

2.2. Some Properties of Zero-Difference functions

In this subsection, let f be an (n, m, S) ZD function from $(A, +)$ onto $(B, +)$. Define $r_b = |f^{-1}(b)|$, for every $b \in B$. Define $\lambda_\alpha = |\{x \in A \mid f(x + \alpha) = f(x)\}|$, for every nonzero element $\alpha \in A^*$. Denote $\lambda = \max_{i \in S} i$ and $\mu = \min_{i \in S} i$.

The following lemma follows directly from the definition of ZD property.

Lemma 1. *Notations are as above. Then*

$$\sum_{b \in B} r_b(r_b - 1) = \sum_{\alpha \in A^*} \lambda_\alpha,$$

Proof. Consider the following set

$$\{(x, \alpha) \in A \times A^* \mid f(x + \alpha) - f(x) = 0\}.$$

On one hand, given $\alpha \in A^*$, the number of x satisfying the equation is λ_α . It equals the right hand side when α runs over A^* . On the other hand, given $b \in B$, the number of x satisfying $f(x) = b$ is r_b and the number of α satisfying the equation is $r_b - 1$ for each x . It leads to the left hand side when b runs over B . \square

Let $\bar{\lambda}$ be the arithmetic average of the multi-set $\{\lambda_\alpha \mid \alpha \in A^*\}$, i.e.,

$$\bar{\lambda} = \frac{1}{n-1} \sum_{\alpha \in A^*} \lambda_\alpha. \quad (1)$$

Based on Lemma 1, we have the following lower bound on λ .

Lemma 2. *Notations are as above. Then*

$$\lambda \geq \lceil \frac{(n-\epsilon)(n+\epsilon-m)}{m(n-1)} + \lambda - \bar{\lambda} \rceil, \quad (2)$$

where $n = km + \epsilon$ with $0 \leq \epsilon < m$. In particular,

$$\lambda = \frac{(n-\epsilon)(n+\epsilon-m)}{m(n-1)} + \lambda - \bar{\lambda},$$

if and only if, for $b \in B$, $r_b = k$ for $m - \epsilon$ times and $r_b = k + 1$ for the other ϵ times.

Proof. According to Lemma 1, we have

$$\sum_{b \in B} r_b^2 - n = \sum_{\alpha \in A^*} \lambda_\alpha = (n-1)\bar{\lambda} = (n-1)(\lambda - \lambda + \bar{\lambda}).$$

Moreover, we have

$$\sum_{b \in B} r_b^2 - n \geq \min_{r_b, b \in B} \sum_{b \in B} r_b^2 - n$$

Note that $\sum_{b \in B} r_b = n$. By integral programming, $\{r_b \mid b \in B\}$ attains the minimum value, if and only if, f is as balanced as possible. Note that $n = km + \epsilon$. We have

$$\min_{r_b, b \in B} \sum_{b \in B} r_b^2 - n = (m - \epsilon)k^2 + \epsilon(k + 1)^2 - n = \frac{(n - \epsilon)(n + \epsilon - m)}{m}.$$

It completes the proof by some simple calculations. \square

Using Lemma 1, we can also obtain the bounds on the size of preimage sets. The sizes of all preimage sets are important in some applications, such as construct constant composition codes and difference systems of sets.

Lemma 3. *Notations are as above. Then for each $b \in B$,*

$$\frac{n - \sqrt{\Delta}}{m} \leq r_b \leq \frac{n + \sqrt{\Delta}}{m},$$

where $\Delta = (n + \lambda n - \lambda)m^2 - (n^2 + n + \mu n - \mu)m + n^2$.

Proof. For any $b \in B$, we have

$$\begin{aligned} 0 &\leq \sum_{b_1, b_2 \in B \setminus \{b\}, b_1 \neq b_2} (r_{b_1} - r_{b_2})^2 \\ &= \sum_{b_1, b_2 \in B \setminus \{b\}, b_1 \neq b_2} r_{b_1}^2 + r_{b_2}^2 - 2r_{b_1}r_{b_2} \\ &= 2(m-2) \sum_{b_0 \in B \setminus \{b\}} r_{b_0}^2 - 2 \sum_{b_1, b_2 \in B \setminus \{b\}, b_1 \neq b_2} r_{b_1}r_{b_2}. \end{aligned}$$

It then follows that

$$(m-2) \sum_{b_0 \in B \setminus \{b\}} r_{b_0}^2 \geq \sum_{b_1, b_2 \in B \setminus \{b\}, b_1 \neq b_2} r_{b_1}r_{b_2}.$$

By Lemma 1, we have

$$\begin{aligned} n + (n-1)\mu &\leq \sum_{b_0 \in B} r_{b_0}^2 \\ &= \left(\sum_{b_0 \in B \setminus \{b\}} r_{b_0}^2 \right) + r_b^2 \\ &= \left(\sum_{b_0 \in B \setminus \{b\}} r_{b_0}^2 \right) + (n - \sum_{b_0 \in B \setminus \{b\}} r_{b_0})^2 \\ &= 2 \left(\sum_{b_0 \in B \setminus \{b\}} r_{b_0}^2 \right) + n^2 - 2n(n - r_b) + \sum_{b_1, b_2 \in B \setminus \{b\}, b_1 \neq b_2} r_{b_1}r_{b_2} \\ &\leq m \left(\sum_{b_0 \in B} r_{b_0}^2 \right) + mr_b^2 + n^2 - 2n(n - r_b) \\ &\leq m(n + (n-1)\lambda) + mr_b^2 + n^2 - 2n(n - r_b). \end{aligned}$$

Finally, solving the above inequality of r_b completes the proof. \square

In a similar way, it also has the following lemmas.

Lemma 4. *Notations are as above. Then*

$$\sum_{b \in B} r_b^2 = (n-1)\bar{\lambda} + n.$$

Lemma 5. *Notations are as above. Then*

$$\bar{\lambda} \geq \frac{(n-\epsilon)(n+\epsilon-m)}{m(n-1)},$$

where $n = km + \epsilon$ with $0 \leq \epsilon < m$. In particular,

$$\bar{\lambda} = \frac{(n-\epsilon)(n+\epsilon-m)}{m(n-1)},$$

if and only if, for $b \in B$, $r_b = k$ for $m - \epsilon$ times and $r_b = k + 1$ for the other ϵ times.

Lemma 6. Notations are as above. Then for each $b \in B$,

$$\frac{n - \sqrt{\Delta}}{m} \leq r_b \leq \frac{n + \sqrt{\Delta}}{m},$$

where $\Delta = (n + \bar{\lambda}n - \bar{\lambda})m^2 - (n^2 + n + \bar{\lambda}n - \bar{\lambda})m + n^2$.

Remark 1. As a comparison, the properties of ZD functions in Lemmas 1, 2 and 3, are generalizations of those properties of ZDB functions in [40] and generalization of those properties of N-ZDB functions in [42].

2.3. Zero-Difference Functions from Zero-Difference Balanced Functions

Firstly, a generic class of ZDB function proposed by Yi et al. is recalled.

Proposition 7. [43, Theorem 1] Let $(R, +, \times)$ be a ring of order n , and let G be a subgroup of (R, \times) . Denote $D_G = \{rG \mid r \in R\}$, where $rG = \{rg \mid g \in G\}$. Define a function from R to $\mathbb{Z}_{|D_G|}$, $f_G(x) = h_G(g_G(x))$ where $g_G(x) = rG$ if $x \in rG$ and h_G is a bijection from D_G to $\mathbb{Z}_{|D_G|}$. If G satisfies the condition

$$(G - 1) \setminus \{0\} \subset R^\times, \quad (3)$$

then $f_G(x)$ is an $(n, \frac{n-1}{k} + 1, k - 1)$ ZDB function from $(R, +)$ to $(\mathbb{Z}_m, +)$, where $m = \frac{n-1}{k} + 1$ and $k = |G|$.

Remark 2. Let R be a residual class ring \mathbb{Z}_n or a product of finite fields \mathbb{F}_q , then these ZDB functions are studied in [5, 18, 47].

So far as we know, there only two subclasses of such ZDB functions, namely Proposition 8 and Proposition 9. The main difference between them is that ZDB functions in Proposition 8 are cyclic and thus have more applications and ZDB functions in Proposition 9 have more feasible parameters.

Proposition 8. [47, Theorem 1] Let $n = p_1^{r_1} p_2^{r_2} \cdots p_k^{r_k}$, where $p_1 < p_2 < \cdots < p_k$ are odd prime numbers, and r_1, r_2, \dots, r_k are positive integers. Then for any positive integers e such that $e \mid \gcd(p_1 - 1, p_2 - 1, \dots, p_k - 1)$, there exists an $(n, \frac{n-1}{e} + 1, e - 1)$ ZDB function from $(\mathbb{Z}_n, +)$ to $(\mathbb{Z}_{\frac{n-1}{e} + 1}, +)$.

Proposition 9. [18, Theorem 1] Let $n = p_1^{r_1} p_2^{r_2} \cdots p_k^{r_k}$, where $p_1 < p_2 < \cdots < p_k$ are prime numbers, and r_1, r_2, \dots, r_k are positive integers. Then for any positive integers e such that $e \mid \gcd(p_1^{r_1} - 1, p_2^{r_2} - 1, \dots, p_k^{r_k} - 1)$, there exists an $(n, \frac{n-1}{e} + 1, e - 1)$ ZDB function from $(\prod_{i=1}^k \mathbb{F}_{p_i^{r_i}}, +)$ to $(\mathbb{Z}_{\frac{n-1}{e} + 1}, +)$.

If the ZDB function f_G is modified a little bit, then a ZD function f_G^0 can be obtained. Comparing with the original ZDB functions, these ZD functions are better in balance, namely they are almost balanced.

Theorem 1. Using the notations in Proposition 7, define a function

$$f_G^0(x) = \begin{cases} f_G(x), & x \neq 0, \\ f_G(1), & x = 0. \end{cases}$$

Then f_G^0 is an $(n, \frac{n-1}{k}, S)$ ZD function, where

$$S = \begin{cases} \{n\}, & \frac{n-1}{k} = 1, \\ \{k\}, & \frac{n-1}{k} = 2 \text{ and } -1 \notin G, \\ \{k-1, k\}, & \frac{n-1}{k} > 2 \text{ and } -1 \notin G, \\ \{k-1, k+1\}, & \frac{n-1}{k} \geq 2 \text{ and } -1 \in G. \end{cases}$$

Proof. Obviously $|f_G^0(R)| = |f_G(R)| - 1 = \frac{n-1}{k}$, since there does not exist $x \in R$ such that $f_G^0(x) = f_G(0)$. If $\frac{n-1}{k} = 1$, then f_G^0 must be a constant function. In the following, assume that $\frac{n-1}{k} \geq 2$. To solve the equation $f_G^0(x+a) = f_G^0(x)$, consider two special cases.

- Case $a \in G$: We assert that $x = 0$ is a solution of the equation $f_G^0(x+a) = f_G^0(x)$. Since

$$f_G^0(0+a) = f_G^0(a) = f_G(a) = h_G(G),$$

and

$$f_G^0(0) = f_G(1) = h_G(G),$$

we have $f_G^0(0+a) = f_G^0(0)$, where h_G is the bijection in Proposition 7.

- Case $a \in -G$: We assert that $x = -a$ is a solution of the equation $f_G^0(x+a) = f_G^0(x)$. Since

$$f_G^0(-a+a) = f_G^0(0) = f_G(1) = h_G(G),$$

and

$$f_G^0(-a) = f_G(-a) = h_G(G),$$

we have $f_G^0(-a+a) = f_G^0(-a)$.

Note that neither $x = 0$ nor $x = -a$ can be a solution of the equation $f_G(x+a) = f_G(x)$ and that $-G = G$ if and only if $-1 \in G$. Now for any nonzero element $a \in R^*$, we have the following different cases.

- If $\frac{n-1}{k} \geq 2$ and $-1 \in G$, then we have

$$\begin{aligned} & \{x \in R \mid f_G^0(x+a) = f_G^0(x)\} \\ &= \begin{cases} \{x \in R^* \mid f_G(x+a) = f_G(x)\} \cup \{0, -a\}, & a \in G, \\ \{x \in R^* \mid f_G(x+a) = f_G(x)\}, & \text{otherwise.} \end{cases} \end{aligned}$$

Therefore, we have

$$|\{x \in R \mid f_G^0(x+a) = f_G^0(x)\}| = \begin{cases} k+1, & a \in G, \\ k-1, & \text{otherwise.} \end{cases}$$

- If $\frac{n-1}{k} > 2$ and $-1 \notin G$, then we have

$$\begin{aligned} & \{x \in R \mid f_G^0(x+a) = f_G^0(x)\} \\ &= \begin{cases} \{x \in R^* \mid f_G(x+a) = f_G(x)\} \cup \{0\}, & a \in G, \\ \{x \in R^* \mid f_G(x+a) = f_G(x)\} \cup \{-a\}, & a \in -G, \\ \{x \in R^* \mid f_G(x+a) = f_G(x)\}, & \text{otherwise,} \end{cases} \end{aligned}$$

and

$$|\{x \in R \mid f_G^0(x+a) = f_G^0(x)\}| = \begin{cases} k, & a \in -G \cup G, \\ k-1, & \text{otherwise.} \end{cases}$$

- If $\frac{n-1}{k} = 2$ and $-1 \notin G$, we have

$$\begin{aligned} & \{x \in R \mid f_G^0(x+a) = f_G^0(x)\} \\ &= \begin{cases} \{x \in R^* \mid f_G(x+a) = f_G(x)\} \cup \{0\}, & a \in G, \\ \{x \in R^* \mid f_G(x+a) = f_G(x)\} \cup \{-a\}, & a \in -G, \end{cases} \end{aligned}$$

and

$$|\{x \in R \mid f_G^0(x+a) = f_G^0(x)\}| = k, a \in -G \cup G.$$

It completes the proof. □

To investigate when $-1 \in G$, we have the following lemma.

Lemma 10. *Let $(R, +, \times)$ be a ring and G be a subgroup of (R, \times) . Denote $k = |G|$. If G satisfies $(G - 1) \setminus \{0\} \subset R^\times$, then $-1 \in G$ if and only if $2 \mid k$ or the characteristic p of R is 2.*

Proof. If $2 \mid k$, then by Cauchy's Theorem [1] there exists an element $\alpha \in G$ with order 2, i.e., $\alpha^2 = 1$. Then

$$(\alpha - 1)^2 = \alpha^2 - 2\alpha + 1 = 2(1 - \alpha).$$

Since $(G - 1) \setminus \{0\} \subset R^\times$, we have $\alpha - 1 \in R^\times$. Hence

$$(\alpha - 1) = -2.$$

So $-1 = \alpha \in G$.

If $p = 2$, then $-1 = 1 \in G$.

Conversely, suppose that $-1 \in G$. If $p \neq 2$, then $-1 \neq 1$. The multiplicative order of -1 must be 2 since $(-1)^2 = 1$. By Lagrange's Theorem [1] we have $2 \mid k$. □

Remark 3. *Note that the results in [42, Section 4] are also the main results in [5] and Theorem 1 is a generalization of them. Hence f_G^0 is a generalization of the exact N -ZDB function in [42, Theorem 4.1]. The technic used in Theorem 1 is called change point technic.*

Using the same technic, we can generalize Theorem 1 a bit.

Theorem 2. *Let f be an $(n, \frac{n-1}{k}, \lambda)$ ZDB function from $(A, +)$ to $(B, +)$ such that for any $b \in B$,*

$$|\{x \in A \mid f(x) = b\}| = \begin{cases} k, & b \neq b_0, \\ 1, & b = b_0, \end{cases}$$

where $k \geq 2$ and $b_0 \in B$. Suppose $f(a_0) = b_0$. For any $a \in A$, define $I(a) = \{x \in A \mid f(x) = f(a)\}$ and define a function

$$g_a(x) = \begin{cases} f(x), & x \neq a_0, \\ f(a), & x = a_0. \end{cases}$$

If $a_0 \notin I(a)$ then g_a is an $(n, \frac{n-1}{k}, S)$ ZD function where

$$S = \begin{cases} \{n\}, & \frac{n-1}{k} = 1, \\ \{k\}, & \frac{n-1}{k} = 2 \text{ and } D = \emptyset, \\ \{k-1, k\}, & \frac{n-1}{k} > 2 \text{ and } D = \emptyset, \\ \{k-1, k+1\}, & \frac{n-1}{k} \geq 2 \text{ and } D = I(a) - a_0, \\ \{k-1, k, k+1\}, & \frac{n-1}{k} \geq 2 \text{ and } \emptyset \subsetneq D \subsetneq I(a) - a_0, \end{cases}$$

and $D = (I(a) - a_0) \cap (a_0 - I(a))$. Moreover, $\lambda = k - 1$.

Proof. The proof is similar with that of Theorem 1. For any nonzero element $\alpha \in A^*$, if α belongs to either $I(a) - a_0$ or $a_0 - I(a)$, then it will append one more solution for $g_a(x + \alpha) = g_a(x)$, either $x = a_0$ or $x = a_0 - \alpha$. If α belongs to both $I(a) - a_0$ and $a_0 - I(a)$, then it will append two more solutions for $g_a(x + \alpha) = g_a(x)$, $x = a_0$ and $x = a_0 - \alpha$. For the rest, the solutions for $g_a(x + \alpha) = g_a(x)$ remain the same.

Define $\lambda_\alpha = |\{x \in A \mid g_a(x + \alpha) = g_a(x)\}|$ for every nonzero element $\alpha \in A^*$. Denote $E = (I(a) - a_0) \cup (a_0 - I(a))$. Assume that $\frac{n-1}{k} \geq 2$. Then we have the following four cases.

- If $\frac{n-1}{k} = 2$ and $D = \emptyset$, then $E = A^*$, $a_0 = 0$ and we have

$$\lambda_\alpha = \lambda + 1, \alpha \in E.$$

- If $\frac{n-1}{k} > 2$ and $D = \emptyset$, then we have

$$\lambda_\alpha = \begin{cases} \lambda + 1, & \alpha \in I(a) - a_0, \\ \lambda + 1, & \alpha \in a_0 - I(a), \\ \lambda, & \text{otherwise.} \end{cases}$$

- If $\frac{n-1}{k} \geq 2$ and $D = I(a) - a_0$, then $D = I(a) - a_0 = a_0 - I(a)$ and we have

$$\lambda_\alpha = \begin{cases} \lambda + 2, & \alpha \in D, \\ \lambda, & \text{otherwise.} \end{cases}$$

- If $\frac{n-1}{k} \geq 2$ and $\emptyset \subsetneq D \subsetneq I(a) - a_0$, then we have

$$\lambda_\alpha = \begin{cases} \lambda + 1, & \alpha \in E \setminus D, \\ \lambda + 2, & \alpha \in D, \\ \lambda, & \text{otherwise.} \end{cases}$$

To finish the proof, we assert that $\lambda = k - 1$. On one hand, since g_a satisfies the condition in Lemma 5, we have

$$\bar{\lambda} = \frac{(n - \epsilon)(n + \epsilon - m)}{m(n - 1)} = k - 1 + \frac{2k}{n - 1},$$

where $m = \frac{n-1}{k}$ and $\epsilon = 1$. On the other hand, note that $|I(a) - a_0| = |a_0 - I(a)| = k$ and $|E| = 2k - |D|$. Hence according to the definition of $\bar{\lambda}$, i.e., Equation (1), we have

$$\begin{aligned} \bar{\lambda} &= \frac{|D|(\lambda + 2) + (|E| - |D|)(\lambda + 1) + (n - 1 - |E|)\lambda}{n - 1} \\ &= \lambda + \frac{2k}{n - 1}. \end{aligned}$$

Consequently $\lambda = k - 1$. □

Remark 4. Let $a_0 = 0$ and $a = 1$. Then the ZDB functions in Proposition 7 satisfy the conditions in Theorem 2. A survey of such ZDB functions is in [45].

Definition 2. Let f be a function A to B . f is Type-A if $\text{SP}(f) = \{1, e^{m-1}\}$, and is Type-B if $\text{SP}(f) = \{e + 1, e^{m-1}\}$ where $m = |f(A)|$ and e is a positive integer.

Proposition 11. [45, Corollary 1] Let $n = p_1^{r_1} p_2^{r_2} \cdots p_k^{r_k}$, where $p_1 < p_2 < \cdots < p_k$ are odd prime numbers, and r_1, r_2, \dots, r_k are positive integers. Then for any positive integers e such that $e(e - 1) \mid \text{gcd}(p_1 - 1, p_2 - 1, \dots, p_k - 1)$, there exist $(en, \frac{en-1}{e-1} + 1, e - 2)$ ZDB functions from $(\mathbb{Z}_{en}, +)$ to $(\mathbb{Z}_{\frac{en-1}{e-1}+1}, +)$.

Proposition 12. [45, Corollary 2] Let $n = p_1^{r_1} p_2^{r_2} \cdots p_k^{r_k}$, where $p_1 < p_2 < \cdots < p_k$ are prime numbers, and r_1, r_2, \dots, r_k are positive integers. Denote $R = \prod_{i=1}^k \mathbb{F}_{p_i^{r_i}}$. Then for any positive integer e such that $e(e - 1) \mid \text{gcd}(p_1^{r_1} - 1, p_2^{r_2} - 1, \dots, p_k^{r_k} - 1)$, there exist $(en, \frac{en-1}{e-1} + 1, e - 2)$ ZDB functions from $(R \times \mathbb{Z}_e, +)$ to $(\mathbb{Z}_{\frac{en-1}{e-1}+1}, +)$.

It is interesting that Theorem 2 gives many ZD functions from ZDB functions without caring how these ZDB functions are constructed. In particular, it converts a ZDB function of Type-A into a ZD function of Type-B. In [45], many ZDB functions of Type-A are summarized, namely Proposition 8, Proposition 9, Proposition 11 and Proposition 12. Although not all the generated ZD functions have good applications, we will show what kind of ZD functions would lead to optimal objects, such as constant weight codes, difference systems of sets and frequency-hopping sequences.

3. Applications of Zero-Difference Functions

We remark that the frameworks of applications using ZDB functions are still valid if ZDB functions are replaced by ZD functions. Thus many objects can be obtained by ZD functions. In this section, we will give the conditions of these objects being optimal.

3.1. Constant Composition Codes

An $(n, M, d, [w_0, w_1, \dots, w_{q-1}]_q)$ constant composition code (CCC) is a code over an Abelian group G with length n , size M and minimum Hamming distance d such that in every codeword the element b_i appears exactly w_i times for every i , where $b_i \in G$. Let $A_q(n, d, [w_0, w_1, \dots, w_{q-1}])$ be the maximum size of an $(n, M, d, [w_0, w_1, \dots, w_{q-1}]_q)$ CCC. A CCC is optimal if the bound in Lemma 13 is met.

Lemma 13. [35] *If $nd - n^2 + \sum_{i=0}^{q-1} w_i^2 > 0$, then*

$$A_q(n, d, [w_0, w_1, \dots, w_{q-1}]) \leq \frac{nd}{nd - n^2 + \sum_{i=0}^{q-1} w_i^2}.$$

Obviously ZD functions can be used to construct CCCs and these CCCs in Proposition 14 is optimal only if the ZD function is a ZDB function.

Proposition 14. [14] *Denote*

$$A = \{a_0, a_1, \dots, a_{n-1}\}, B = \{b_0, b_1, \dots, b_{m-1}\}.$$

Let f be a function from A to B . If f is an (n, m, S) ZD function, then

$$C_f = \{(f(a_0 + a_i), \dots, f(a_{n-1} + a_i)) \mid 0 \leq i \leq n-1\} \quad (4)$$

is an $(n, n, n - \lambda, [w_0, w_1, \dots, w_{m-1}]_m)$ CCC over B , where $w_i = |\{x \in A \mid f(x) = b_i\}|$ and $\lambda = \max_{x \in S} x$.

Proposition 15. *In Proposition 14, if C_f is optimal, then $S = \{\lambda\}$, i.e., f is a ZDB function.*

Proof. If C_f is optimal, then

$$n = \frac{nd}{nd - n^2 + \sum_{i=0}^{q-1} w_i^2},$$

where $d = n - \lambda$ and $q = m$. We have

$$\sum_{i=0}^{m-1} w_i^2 = n\lambda + n - \lambda.$$

It follows from Lemma 1 that

$$n\lambda - \lambda = \sum_{\alpha \in A^*} \lambda_\alpha,$$

where $\lambda_\alpha = |\{x \in A \mid f(x + \alpha) = f(x)\}|$ for every $\alpha \in A^*$. It implies

$$n - 1 = \sum_{\alpha \in A^*} \frac{\lambda_\alpha}{\lambda}.$$

We have $0 \leq \frac{\lambda_\alpha}{\lambda} \leq 1$, since $\lambda_\alpha \in S$ and $\lambda = \max_{x \in S} x$. Therefore, $\frac{\lambda_\alpha}{\lambda} = 1$, for every $\alpha \in A^*$. It implies that $S = \{\lambda\}$, i.e., f is a ZDB function. \square

3.2. Constant Weight Codes

An $(n, M, d, w)_q$ constant weight code (CWC) is a code over an Abelian group $\{b_0, b_1, \dots, b_{q-1}\}$ with length n , size M and minimum Hamming distance d such that the Hamming weight of each codeword is w . Let $A_q(n, d, w)$ be the maximum size of an $(n, M, d, w)_q$ CWC.

Note that CCCs are special CWCs. They have many applications such as determining the zero error decision feedback capacity of discrete memoryless channels [38], multiple-access communications [19], spherical codes for modulation [20], DNA codes [27, 36], powerline communications [10, 13] and frequency hopping [11].

A CWC is optimal if the bound in Lemma 16 is met. Theorem 3 gives many optimal CWCs from ZD functions.

Lemma 16. [21] *If $nd - 2nw + \frac{q}{q-1}w^2 > 0$, then*

$$A_q(n, d, w) \leq \frac{nd}{nd - 2nw + \frac{q}{q-1}w^2}.$$

Theorem 3. *Let f be an (n, m, S) ZD function. Then C_f in (4) is an $(n, n, n - \lambda, n - b_0)_m$ CWC, where $\lambda = \max_{x \in S} x$ and $b_0 = |f^{-1}(0)|$. Furthermore, C_f is optimal if and only if $\lambda(n - 1)(m - 1) = b_0^2 m - 2b_0 n + n(n - m + 1)$.*

We have several results for the ZDB functions of Type-A in Proposition 7 and the ZD functions of Type-B in Theorem 2. Comparing with Theorem 6 in [43], Theorem 4 is generic since it does not depend on the construction method.

Theorem 4. *Let f be an $(n, \frac{n-1}{k} + 1, k - 1)$ ZDB function of Type-A such that $|f^{-1}(0)| = 1$. Then C_f in (4) is an optimal $(n, n, n - k + 1, n - 1)_{\frac{n-1}{k} + 1}$ CWC.*

Theorem 5. *Let f be an $(n, 2, k)$ ZDB function of Type-B in Theorem 2. Define $b_0 = |f^{-1}(0)|$. Then C_f in (4) is an optimal $(n, n, n - k, n - b_0)_2$ CWC where $b_0 = k$ or $b_0 = k + 1$.*

Note that the construction of code in Proposition 14 does not require the function should be defined over a cyclic group. Since Proposition 9 and Proposition 12 give more parameters than Proposition 8 and Proposition 11. Only Proposition 9 and Proposition 12 are considered when applying Theorem 4 and Theorem 5. Consequently, we obtain many optimal CWCs. Some optimal CWCs are listed in Table 1. For more optimal CWCs, please see [2].

Corollary 17. *Let $n = p_1^{r_1} p_2^{r_2} \cdots p_k^{r_k}$, where $p_1 < p_2 < \cdots < p_k$ are odd prime numbers, and r_1, r_2, \dots, r_k are positive integers. Then for any positive integers e such that $e \mid \gcd(p_1^{r_1} - 1, p_2^{r_2} - 1, \dots, p_k^{r_k} - 1)$, there exists an optimal $(n, n, n - e + 1, n - 1)_{\frac{n-1}{e} + 1}$ CWC.*

Example 1. *Let $n = 11$ and $e = 5$. Then an optimal $(11, 11, 7, 10)_3$ CWC C_1 is obtained from an $(11, 3, 4)$ ZDB function by Corollary 17, namely,*

$$C_1 = \{12221212101, 21222120111, 22210111122, 22102211211, 12021121212, 21121112220, 12112122021, 20111222112, 11122201122, 01211221221, 11212012212\}.$$

Corollary 18. *Let $n = p_1^{r_1} p_2^{r_2} \cdots p_k^{r_k}$, where $p_1 < p_2 < \cdots < p_k$ are prime numbers, and r_1, r_2, \dots, r_k are positive integers. Denote $R = \prod_{i=1}^k \mathbb{F}_{p_i^{r_i}}$. Then for any positive integer e such that $e(e - 1) \mid \gcd(p_1^{r_1} - 1, p_2^{r_2} - 1, \dots, p_k^{r_k} - 1)$, there exists an optimal $(en, en, en - e + 2, en - 1)_{\frac{en-1}{e-1} + 1}$ CWC.*

Example 2. *Let $n = 7$ and $e = 3$. Then an optimal $(21, 21, 20, 20)_{11}$ CWC C_2 is obtained from an $(21, 11, 1)$ ZDB function by Corollary 18, namely,*

$$C_2 = \{2304467A876319A158952, 3443078759A26895611A2, 042235A89193856A76714, 43232A91158456779A860, 40324859A8727116A5693, 675A89801449736232A51, 78A95814530192A342766, A7819047386545291A326, 8591A15362468274039A7, 7915843825760A316942A, 6A9874064711382A95235, 323429156610AA8987574, 16857794803AA45223619, 985613252A8A494671037, A96716A27328548430195, 15A7623941A9264857308, 5679A34106982735A8241, 816A522A3957310786449, 91786A73942560132458A, 5A169562A237139044878, 224031667A54975819A83\}.$$

Corollary 19. Let $n = p_1^{r_1} p_2^{r_2} \cdots p_k^{r_k}$, where $p_1 < p_2 < \cdots < p_k$ are odd prime numbers, and r_1, r_2, \dots, r_k are positive integers. Then for any odd and positive integers e such that $e \mid \gcd(p_1^{r_1} - 1, p_2^{r_2} - 1, \dots, p_k^{r_k} - 1)$, there exists an optimal $(n, n, \frac{n+1}{2}, \frac{n-1}{2})_2$ CWC and an optimal $(n, n, \frac{n+1}{2}, \frac{n+1}{2})_2$ CWC.

Example 3. Let $n = 11$ and $e = 5$. Then an optimal $(11, 11, 6, 5)_2$ CWC C_3 and an optimal $(11, 11, 6, 6)_2$ CWC C_4 are obtained from an $(11, 2, 5)$ ZDB function by Corollary 19, namely,

$$C_3 = \{01110101000, 10111010000, 11100000011, 11001100100, 01010010101, 10010001110, 01001011010, 10000111001, 00011100011, 00100110110, 00101001101\},$$

$$C_4 = \{01110101010, 10111011000, 11101000011, 11011100100, 01110010101, 10010001111, 01001011110, 11000111001, 00011110011, 10100110110, 00101101101\}.$$

Table 1: Some Optimal $(n, n, d, w)_2$ Constant Weight Codes

n	d	w	$A_2(n, d, w)$	n	d	w	$A_2(n, d, w)$
5	4	4	5	5	4	5	5
7	4	4	7	7	4	5	7
7	6	6	7	7	6	7	7
9	8	8	9	9	8	9	9
11	6	6	11	11	6	7	11
11	10	10	11	11	10	11	11
13	10	10	13	13	10	11	13
13	12	12	13	13	12	13	13
15	14	14	15	15	14	15	15
17	16	16	17	17	16	17	17
19	10	10	19	19	10	11	19
19	16	16	19	19	16	17	19
19	18	18	19	19	18	19	19
23	12	12	23	23	12	13	23
27	14	14	27	27	14	15	27
31	16	16	31	31	16	17	31

3.3. Difference Systems of Sets

Difference systems of sets (DSS) are related with comma-free codes, authentication codes and secret sharing schemes [23, 37]. Let $\{D_0, D_1, \dots, D_{q-1}\}$ be disjoint subsets of an Abelian group $(G, +)$. Denote $|G| = n$ and $|D_i| = w_i$ for every i . Then $\{D_0, D_1, \dots, D_{q-1}\}$ is said to be an $(n, \{w_0, w_1, \dots, w_{q-1}\}, \lambda)$ DSS if the multi-set

$$\{x - y \mid x \in D_i, y \in D_j, 0 \leq i \neq j \leq q - 1\}$$

contains every nonzero element $g \in G$ at least λ times. Moreover, a DSS is perfect if every non-zero element g appears exactly λ times in the multi-set just mentioned above. It is required that

$$\tau_q(n, \lambda) = \sum_{i=0}^{q-1} |D_i|$$

as small as possible. A DSS is called optimal if the bound in Lemma 20 is met.

Lemma 20. [39] For an $(n, [w_0, w_1, \dots, w_{q-1}], \lambda)$ DSS, we have

$$\tau_q(n, \lambda) \geq \sqrt{SQUARE(\lambda(n-1) + \lceil \frac{\lambda(n-1)}{q-1} \rceil)},$$

where $SQUARE(x)$ denotes the smallest square number that is no less than x and $\lceil x \rceil$ denotes the smallest integer that no less than x .

Remark 5. DSSs on non-cyclic groups are related to authentication codes and secret sharing schemes [23, 37].

In 2009, Ding gave a method to construct optimal DSSs from a ZDB function.

Proposition 21. [15] If f is an (n, m, λ) ZDB function from A to B . Denote $f(A) = \{b_0, b_1, \dots, b_{m-1}\}$. Then

$$\mathcal{D} = \{D_i \mid 0 \leq i \leq q-1\} \quad (5)$$

is an $(n, [w_0, w_1, \dots, w_{m-1}], n-\lambda)$ DSS if $n \geq m\lambda$, where $D_i = \{x \in A \mid f(x) = b_i\}$, $w_i = |D_i|$.

To obtain optimal DSSs, we need the following lemmas to prove Theorem 6.

Lemma 22. Let a be a positive integer, and let b be a real number. $\lceil x \rceil$ denotes the ceiling function. Then $a < \lceil b \rceil$, if and only if, $a < b$.

Proof. For some $0 \leq \varepsilon < 1$, we have

$$\begin{aligned} a < \lceil b \rceil &\Leftrightarrow a \leq \lceil b \rceil - 1 \Leftrightarrow a \leq b + \varepsilon - 1 \\ &\Leftrightarrow a \leq b - (1 - \varepsilon) \Leftrightarrow a < b. \end{aligned}$$

□

Lemma 23. Let a be a positive integer, and let b be a real number. $\lceil x \rceil$ denotes the ceiling function. Then $a \geq \lceil b \rceil$, if and only if, $a \geq b$.

Theorem 6. In Proposition 21, the DSS \mathcal{D} is optimal, if and only if $n \geq m\lambda - m + 2$.

Proof. Note that $m \geq 2$. If $n \geq m\lambda - m + 2$, then $n - 1 > m(\lambda - 1)$. That is $\frac{n-1}{m-1} > \lambda - 1$. Hence, we have

$$\begin{aligned} &\rho(n-1) + \lceil \frac{\rho(n-1)}{q-1} \rceil \\ &\geq (n-\lambda)(n-1) + \frac{(n-\lambda)(n-1)}{m-1} \\ &= (n-1)(n-\lambda + \frac{(n-\lambda)(n-1)}{m-1}) \\ &> (n-1)(n-\lambda + \lambda - 1) \\ &= (n-1)^2, \end{aligned}$$

where $q = m$ and $\rho = n - \lambda$. Since $\tau_q(n, \rho) = n$, it follows from Lemma 20 that

$$\sqrt{SQ\text{UARE}(\rho(n-1) + \lceil \frac{\rho(n-1)}{q-1} \rceil)} = n.$$

Therefore, D meets the bound in Lemma 20.

Conversely, if D is optimal, then we have

$$\sqrt{SQ\text{UARE}((n-\lambda)(n-1) + \lceil \frac{(n-\lambda)(n-1)}{m-1} \rceil)} = n.$$

That is

$$(n-\lambda)(n-1) + \lceil \frac{(n-\lambda)(n-1)}{m-1} \rceil > (n-1)^2.$$

According to Lemma 22, we can get

$$(n-\lambda)(n-1) + \frac{(n-\lambda)(n-1)}{m-1} > (n-1)^2,$$

which leads to $n - 1 > m(\lambda - 1)$. Finally we have $n \geq m\lambda - m + 2$.

□

Remark 6. Since N -ZDB function is a special case of ZD function, Theorem 6 is a generalization of Theorem 5.12 in [42].

Remark 7. When the ZD function f is also a ZDB function, the condition of the constructed DSSs being optimal in this paper, is weaker than that in Proposition 21 [15] (see also [49, Lemma 6]). If $m \geq 2$, then $n \geq m\lambda - m + 2$ which implies $n \geq m\lambda$.

As a result, it improves Theorem 7 in [43] a bit. Moreover, Theorem 7 does not depend on the construction method and will give more optimal DSSs.

Lemma 24. [43, Theorem 7] Let f be an $(n, \frac{n-1}{k} + 1, k - 1)$ ZDB function of Theorem 3 in [43]. Then the DSS constructed by the method in Proposition 21 is optimal if $n \geq (k - 1)^2$.

Theorem 7. Let f be an $(n, \frac{n-1}{k} + 1, k - 1)$ ZDB function. Then the DSS constructed by the method in Proposition 21 is optimal if $n \geq \frac{k(k-1)}{2} + 1$.

Example 4. Using the notations in Proposition 7, put $R = \mathbb{Z}_{11}$ and $G = \langle 4 \rangle$. Then the group G of order 5 satisfies Condition (3). Hence there is an $(11, 3, 4)$ ZDB function f which lead to an $(11, [1, 5, 5], 7)$ DSS. Obviously this DSS is optimal. It is easy to check that f satisfies the condition in Theorem 7, but not the condition in Lemma 24.

No matter it is Type-A or Type-B, a ZD function may be used to construct an optimal DSS. Several classes of optimal DSSs are obtained by ZD functions in Theorem 2.

Theorem 8. Let f be an $(n, \frac{n-1}{k}, S)$ ZD function in Theorem 2 such that $k = \max_{x \in S} x$. Then the DSS \mathcal{D} in Proposition 21 is optimal. Moreover, it is perfect if f is a ZDB function.

Corollary 25. [42, Theorem 5.13] Let n be an positive integer with the following factorization $n = \prod_{i=1}^r p_i^{e_i}$, where p_i are odd prime numbers, e_i are positive integers ($i = 1, 2, \dots, r$). Let $e \geq 2$ be an odd integer such that $e \mid p_i - 1$ for every i . Then there exists an optimal $(n, \underbrace{[e, e, \dots, e, e + 1]}_{\frac{n-1}{e} - 1 \text{ times}}, n - e)$ DSS over $(\mathbb{Z}_n, +)$.

Corollary 26. Let n be an positive integer with the following factorization $n = \prod_{i=1}^r p_i^{e_i}$, where p_i are prime numbers, e_i are positive integers ($i = 1, 2, \dots, r$). Let $e \geq 2$ be an odd integer such that $e \mid p_i^{e_i} - 1$ for every i . Then there exists an optimal $(n, \underbrace{[e, e, \dots, e, e + 1]}_{\frac{n-1}{e} - 1 \text{ times}}, n - e)$ DSS over $(\prod_{i=1}^r \mathbb{F}_{p_i^{e_i}}, +)$.

Corollary 27. Let n be an positive integer with the following factorization $n = \prod_{i=1}^r p_i^{e_i}$, where p_i are odd prime numbers, e_i are positive integers ($i = 1, 2, \dots, r$). Let $e \geq 2$ be an odd integer such that $e(e - 1) \mid p_i - 1$ for every i . Then there exists an optimal $(en, \underbrace{[e - 1, e - 1, \dots, e - 1, e]}_{\frac{en-1}{e-1} - 1 \text{ times}}, en - e + 1)$ DSS over $(\mathbb{Z}_{en}, +)$.

Corollary 28. Let n be an positive integer with the following factorization $n = \prod_{i=1}^r p_i^{e_i}$, where p_i are prime numbers, e_i are positive integers ($i = 1, 2, \dots, r$). Let $e \geq 2$ be an odd integer such that $e(e - 1) \mid p_i^{e_i} - 1$ for every i . Then there exists an optimal $(en, \underbrace{[e - 1, e - 1, \dots, e - 1, e]}_{\frac{en-1}{e-1} - 1 \text{ times}}, en - e + 1)$ DSSs over $(\mathbb{Z}_e \times \prod_{i=1}^r \mathbb{F}_{p_i^{e_i}}, +)$.

Remark 8. Corollary 26 is a generalizations of Theorem 5.13 in [42] and provide more optimal DSSs with new parameters. In the following, Example 5 can not be obtained by Theorem 5.13 in [42].

Example 5. In Theorem 8, put $n = 3^2 \times 5 = 45$ and $e = 4$. Then we obtain an optimal $(45, \underbrace{[4, 4, \dots, 4, 5]}_{10 \text{ times}}, 41)$ DSS.

We summarize some known optimal DSSs in Table 2 where p and q denote a prime number and a prime power, respectively.

Table 2: Some known optimal DSSs with parameters $(n, [w_0, w_1, \dots, w_{M-1}], \rho)$

n	w_0, w_1, \dots, w_{M-1}	ρ	Constraints	Reference.
$q^2 + 1$	w_0, w_1, \dots, w_{q-1}	$q^2 - q$	$m \in \mathbb{Z}^+$ and $q = 2^m$	[14, Proposition 10]
q	w_0, w_1, \dots, w_{d-1}	$q - \frac{q-d}{d}$	$d \mid q$	[14, Proposition 7]
p^2	$2p - 1, p - 1, \dots, p - 1$	$p^2 - p$	-	[15, Corollary 8]
$\frac{q^m-1}{N}$	w_0, w_1, \dots, w_{q-1}	$\frac{q^{m-1}(q-1)}{N}$	$N \mid q - 1$ and $\gcd(N, m) = 1$	[15, Theorem 9]
q^m	$w_0, w_1, \dots, w_{\frac{q^m-1}{d}}$	$q^m - d + 1$	$d \mid q - 1$	[16, Proposition 14]
$q^2 + q + 1$	w_0, w_1, \dots, w_{q-1}	$q^2 + 2$	-	[16, Proposition 22]
$q^m - 1$	$w_0, w_1, \dots, w_{q^s-1}$	$q^m - q^{m-s}$	$1 \leq s \leq m$	[49, Corollary 1]
$t \frac{q^m-1}{N}$	$w_0, w_1, \dots, w_{q^s-1}$	$t \frac{q^m - q^{m-s}}{N}$	$N \mid q - 1, \gcd(N, m) = 1,$ $1 \leq t \leq N$ and $1 \leq s \leq m$	[49, Theorem 6]
n	$1, e, e, \dots, e$	$n - e + 1$	$n = \prod_{i=1}^k p_i^{e_i} > 3, p_i$ is odd prime and $e \mid (p_i - 1)$ for all i	[5, Theorem 1]
ev	$1, e - 1, e - 1, \dots, e - 1$	$ev - e + 2$	$v = \prod_{i=1}^k p_i^{e_i}, p_i$ is odd prime and $e(e - 1) \mid (p_i - 1)$ for all i	[6, Theorem 1]
n	$1, e, e, \dots, e$	$n - e + 1$	$n = \prod_{i=1}^k p_i^{e_i}, n \geq (m - 1)^2$ and $e \mid (p_i^{e_i} - 1)$ for all i	[43, Theorem 7]
n	$e + 1, e, e, \dots, e$	$n - e$	$n = \prod_{i=1}^k p_i^{e_i}, p_i$ is odd prime, e is odd and $e \mid (p_i - 1)$ for all i	[42, Theorem 5.13]
ev	$1, e - 1, e - 1, \dots, e - 1,$ $e - 2, e - 2, \dots, e - 2$	$ev - e + 2$	$v = \prod_{i=1}^k p_i^{e_i}, p_i$ is odd prime, $e \geq 3,$ $(e - 2) \mid (p_i - 1)$ and $e \mid (p_i - 1)$ for all i	[42, Theorem 5.14]
ev	$e - 1, e - 1, \dots, e - 1,$ $e - 2, e - 2, \dots, e - 2$	$ev - e + 2$	$v = \prod_{i=1}^k p_i^{e_i}, p_i$ is odd prime, e is odd with $e \geq 3,$ $(e - 2) \mid (p_i - 1)$ and $e \mid (p_i - 1)$ for all i	[42, Theorem 5.15]
n	$e + 1, e, e, \dots, e$	$n - e$	$n = \prod_{i=1}^k p_i^{e_i}, p_i$ is odd prime, e is odd and $e \mid (p_i^{e_i} - 1)$ for all i	Corollary 25
ev	$e, e - 1, e - 1, \dots, e - 1$	$ev - e + 1$	$v = \prod_{i=1}^k p_i^{e_i}, p_i$ is odd prime, e is odd and $e(e - 1) \mid (p_i - 1)$ for all i	Corollary 26 *
ev	$e, e - 1, e - 1, \dots, e - 1$	$ev - e + 1$	$v = \prod_{i=1}^k p_i^{e_i}, p_i$ is odd prime, e is odd and $e(e - 1) \mid (p_i^{e_i} - 1)$ for all i	Corollary 27 *

3.4. Frequency-hopping Sequences

For any two sequences X, Y of length n over an alphabet B . The Hamming correlation $H_{X,Y}$ is defined as

$$H_{X,Y}(t) = \sum_{i=0}^{n-1} h[x_i, y_{(i+t) \pmod{n}}], 0 \leq t < n$$

where $h[a, b] = 1$ if $a = b$, and 0 otherwise. Frequency-hopping sequences (FHS) are the sequences such that the hamming autocorrelation is as small as possible. Lempel and Greenberger gave a lower bound in 1974 [29]. Let (n, m, λ) denote an FHS X of length n over an alphabet of size m with $\lambda = H(X)$. An FHS is optimal if the bound in Lemma 29 is met.

Lemma 29. [29] For any FHS X of length n over an alphabet of size m , define

$$H(X) = \max_{1 \leq t < n} \{H_{X,X}(t)\},$$

then

$$H(X) \geq \lceil \frac{(n - \epsilon)(n + \epsilon - m)}{m(n - 1)} \rceil, \quad (6)$$

where ϵ is the least nonnegative residue of n modulo m and $\lceil x \rceil$ denotes the smallest integer that no less than x .

In 2014, Wang and Zhou gave a method to construct FHSs by a ZDB function.

Proposition 30. [40, Lemma 5.3] Let f be an (n, m, S) ZDB function from a cyclic group $(A, +)$ to a group $(B, +)$. Then $\mathcal{T} = \{f(i\alpha)\}_{i=0}^{n-1}$ is an (n, m, λ) FHS, where α is a generator of A and $\lambda = \max_{x \in S} x$.

Remark 9. The criteria of optimality in this subsection is different from that in [33]. In this subsection, we call an FHS is optimal with respect to the bound in Lemma 29. In [33], they call an FHS is optimal with respect to a set of FHSs (see Lemma 12 in [33]).

Theorem 5.5, Theorem 5.6 and Theorem 5.7 in [42] imply that, a ZD function f is not necessary ZDB to obtain optimal FHS. In order to characterize such ZD functions, we will give the conditions of the constructed FHSs being optimal is given as follows.

Theorem 9. In proposition 30, the FHS \mathcal{T} is optimal, if and only if, $0 \leq \lambda - C < 1$, where $C = \frac{(n-\epsilon)(n+\epsilon-m)}{m(n-1)}$ and $n = km + \epsilon$ with $0 \leq \epsilon < m$.

Proof. If the FHS T is optimal, then we have

$$\lambda = \lceil C \rceil.$$

Thus

$$\lambda < \lceil C \rceil + \delta.$$

where $0 < \delta = C + 1 - \lceil C \rceil \leq 1$. Note that $\lceil C \rceil = C + 1 - \delta$. Hence

$$\lambda < C + 1.$$

It follows from Lemma 2 that $\lambda \geq C$. Therefore, $0 \leq \lambda - C < 1$.

Conversely, if $0 \leq \lambda - C < 1$, then we have

$$\lambda < C + 1.$$

Denote $0 < \delta = C + 1 - \lceil C \rceil \leq 1$. Note that $C = \lceil C \rceil - 1 + \delta$. Hence

$$\lambda < C + 1 = \lceil C \rceil - 1 + \delta + 1 = \lceil C \rceil + \delta.$$

Thus

$$\lambda \leq \lceil C \rceil.$$

It follows from Lemma 29 that $\lambda \geq \lceil C \rceil$. Therefore, $\lambda = \lceil C \rceil$, i.e., the FHS T is optimal. \square

Remark 10. Since N -ZDB function is a special case of ZD function, Theorem 9 is a generalization of Lemma 5.4, Theorem 5.5, Theorem 5.6 and Theorem 5.7 in [42].

Note that $0 \leq \lambda - C = \delta_1 + \delta_2 < 1$, where $\delta_1 = \lambda - \bar{\lambda}$ and $\delta_2 = \bar{\lambda} - C$. For an (n, m, S) ZD function with $\lambda - C < 1$, it implies that the deviation δ_1 of the zero-difference distribution S should be not too great, and that the distance δ_2 between the preimage distribution $\bar{\lambda} = \frac{(\sum_{b \in B} r_b^2) - n}{n-1}$ of function f and the idea balanced preimage distribution $C = \frac{\min_{r_b, b \in B} \sum_{b \in B} r_b^2 - n}{n-1}$ should be not too great. Furthermore, the upper bound of the sum of $\delta_1 + \delta_2$ is 1. Therefore, $\bar{\lambda}$ is a bridge connecting the zero-difference property and the preimage distribution.

According to Lemma 5, $C = \bar{\lambda}$ if f is almost balanced. Thus we only consider a special class of ZD functions which are almost balanced, namely, Type-B. For a ZD function of Type-B, $\lambda - C < 1$ is equivalent to $\lambda - \bar{\lambda} < 1$.

Definition 3. A function f from A onto B is almost balanced (AB) if for $b \in B$, $w_b = k$ for $m - \epsilon$ times and $w_b = k + 1$ for the other ϵ times, where $w_b = |\{x \in A \mid f(x) = b\}|$, $n = |A|$, $m = |B|$ and $n = km + \epsilon$ with $0 \leq \epsilon < m$.

Theorem 10. Let f be an (n, m, S) ZD and AB function. Then the FHS \mathcal{T} in Proposition 30 is optimal if and only if $\lambda - \bar{\lambda} < 1$ where $\lambda = \max_{x \in S} x$ and $\bar{\lambda}$ is defined in (1).

Theorem 11. Let f be an $(n, \frac{n-1}{k}, S)$ ZD functions in Theorem 2 such that $k = \max_{x \in S} x$. Then the FHS \mathcal{T} in Proposition 30 is optimal.

Proof. Obviously, f is Type-B and thus AB. From the proof of Theorem 2, we have

$$\bar{\lambda} = k - 1 + \frac{2k}{n-1}.$$

As $\frac{n-1}{k} \geq 2$, it is easy to see that $0 < \frac{2k}{n-1} \leq 1$ and $0 \leq 1 - \frac{2k}{n-1} < 1$. It follows that

$$0 \leq \lambda - \bar{\lambda} = k - (k - 1 + \frac{2k}{n-1}) = 1 - \frac{2k}{n-1} < 1.$$

It completes the proof by Theorem 10. □

Remark 11. From the conclusion of Theorem 2, if $k = \max_{x \in S} x$, then it must be $D = \emptyset$. According to Lemma 10, it requires that k must be odd if the characteristic of the underlying ring is not 2.

Using the above theorems, it is easy to obtain optimal FHSs from ZD functions.

Corollary 31. [42, Theorem 5.5] Let n be an positive integer with the following factorization

$$n = \prod_{i=1}^r p_i^{e_i},$$

where p_i are prime numbers, e_i are positive integers ($i = 1, 2, \dots, r$). Let $e \geq 2$ be an odd integer such that $e \mid p_i - 1$ for every i . Then there exist optimal $(n, \frac{n-1}{e}, e-1)$ FHSs over $(\mathbb{Z}_n, +)$.

Corollary 32. Let n be an positive integer with the following factorization

$$n = \prod_{i=1}^r p_i^{e_i},$$

where p_i are prime numbers, e_i are positive integers ($i = 1, 2, \dots, r$). Let $e \geq 2$ be an even integer such that $e \mid p_i - 1$ for every i . Then there exist optimal $(en, \frac{en-1}{e-1}, e-2)$ FHSs over $(\mathbb{Z}_{en}, +)$.

Example 6. Let $n = 13$ and $e = 4$. Then an optimal $(52, 17, 3)$ FHS \mathcal{T}_1 is obtained from an $(52, 17, \{2, 3\})$ ZD function by Corollary 32, namely,

$$\mathcal{T}_1 = \{1, 0, 0, 0, 1, 6, 7, 8, 4, 9, 10, 11, 1, 10, 11, 12, 2, 13, 14, 15, 4, 5, 6, 7, 4, 14, 15, 16, 3, 16, 13, 14, 3, 7, 8, 5, 1, 15, 16, 13, 2, 12, 9, 10, 3, 11, 12, 9, 2, 8, 5, 6\}.$$

To end this subsection, we summarize some known optimal FHSs in Table 3.

4. Conclusion

In this paper, we have proposed a concept called zero-difference (ZD) as a generalization of zero-difference balanced (ZDB) by eliminating the "balanced" requirement on "zero-difference". Then we discussed some properties of ZD functions and construct ZD functions of Type-B from ZDB functions of Type-A by change point technic. Finally we show that these ZD functions can be used to construction optimal objects such as optimal CWCs, optimal DSSs and FHSs.

Using ZDB functions, many authors gave the conditions of the constructed CWCs, DSSs and FHSs being optimal. It is interesting that by our change point technic, the ZD functions obtained by those ZDB function can construct optimal CWCs, DSSs and FHSs without any conditions. The main reason is that these ZD functions are Type-B and hence almost balanced while those ZDB functions are Type-A and not balanced enough. Moreover, according to the "philosophy" proposed by Buratti and Jungnickel [3], our ZD functions have no blocks of size 1 or 2 and possess relatively small difference between the smallest and largest block sizes. Thus these ZD functions can be viewed as the suboptimal function if no balanced ZDB functions with the same parameter exists.

In the future work, we are expected to construct more optimal CWC, DSS and FHS. For further applications in these areas, we have to investigate other requirements for these objects. They would impose other restrictions on the underlying functions. For example, there are bounds for a set of FHSs while only one bound of a FHS is considered in the paper.

Table 3: Some known optimal FHSs with parameters (n, m, λ)

n	m	λ	Constraints	Reference.
p	e	f	$p = ef + 1$ is prime, e is even and f is odd	[9, Corollary 2]
p	$e + 1$	$f - 1$	$p = ef + 1$ is prime and $2 \leq f \leq e + 2$	[9, Corollary 3]
p	L	$2g$	$p = 2Lg + 1$ is an odd prime number and $p \equiv 3 \pmod{4}$	[12, Theorem 7]
p	$L + 1$	$2g - 1$	$p = 2Lg + 1$ is an odd prime number, $p \equiv 3 \pmod{4}$, g is odd and $3 \leq g \leq \frac{L+3}{2}$	[12, Theorem 9]
p^2	p	p	p is prime	[28, Theorem 2]
$p^t - 1$	p^k	$p^{t-k} - 1$	p is prime and $1 \leq k \leq t$	[29, Theorem 2]
p^r	$\frac{p^r-1}{f}$	f	$p = ef + 1$ is an odd prime number and f is odd	[32, Theorem 3.1]
p^r	$\frac{p^r-1}{f} + 1$	$f - 1$	$p = ef + 1$ is an odd prime number	[32, Theorem 3.2]
$q - 1$	e	f	$q = ef + 1$ is a prime power and f is even	[17, Theorem 4]
$q - 1$	$e + 1$	$f - 1$	$q = ef + 1$ is a prime power	[17, Theorem 5]
$\frac{q^r-1}{l}$	q	$\frac{q^{r-1}-1}{l}$	q is a prime power, $l \mid (q - 1)$ and $\gcd(l, \frac{q^r-1}{q-1}) = 1$	[17, Theorem 5]
n	$\frac{n-1}{e} + 1$	$e - 1$	$n = \prod_{i=1}^k p_i^{e_i}$, p_i is odd and prime, $e \mid p_i - 1$, for $1 \leq i \leq k$. $k > 1$ or $k = 1$ with $\frac{n-1}{e} \geq e$	[46, Corollary 2]
n	$\frac{n-1}{e}$	e	$n = \prod_{i=1}^k p_i^{e_i}$, p_i are odd and prime, e is odd and $e \mid (p_i - 1)$, for $1 \leq i \leq k$.	[42, Theorem 5.5]
ev	$\frac{ev-1}{e-1} + 1$	$e - 2$	$v = \prod_{i=1}^k p_i^{e_i}$, p_i are odd and prime, $e \geq 3$ and $e(e-1) \mid (p_i - 1)$, $1 \leq i \leq k$	[46, Theorem 3]
ev	$\frac{(e-1)v-1}{e-2} + 1$	$e - 2$	$v = \prod_{i=1}^k p_i^{e_i}$, p_i are odd and prime, $e \geq 3$, $e \mid (p_i - 1)$ and $(e-2) \mid (p_i - 1)$, for $1 \leq i \leq k$	[42, Theorem 5.6]
ev	$\frac{(e-1)v-1}{e-2}$	$e - 2$	$v = \prod_{i=1}^k p_i^{e_i}$, p_i are odd and prime, e is odd, $e \geq 3$, $e \mid (p_i - 1)$ and $(e-2) \mid (p_i - 1)$, for $1 \leq i \leq k$	[42, Theorem 5.7]
ev	$\frac{ev-1}{e-1}$	$e - 2$	$v = \prod_{i=1}^k p_i^{e_i}$, p_i are odd and prime, e is even and $e(e-1) \mid (p_i - 1)$, $1 \leq i \leq k$	Corollary 32

Acknowledgment

The work was partially supported by the National Natural Science Foundation of China (Grant No. 61502113 and 61702124) and Tang's research was supported in part by the Foundation of National Natural Science of China (No. 61772147), Guangdong Province Natural Science Foundation of major basic research and Cultivation project (No. 2015A030308016), Project of Ordinary University Innovation Team Construction of Guangdong Province (No. 2015KCXTD014), Collaborative Innovation Major Projects of Bureau of Education of Guangzhou City (No. 1201610005) and National Cryptography Development Fund (No. MMJJ20170117).

Thanks to reviewers for their detailed comments and suggestions that improved the quality of this article.

References

- [1] Phani Bhushan Bhattacharya, Surender Kumar Jain, and SR Nagpaul. *Basic abstract algebra*. Cambridge University Press, 1994.
- [2] Andries E Brouwer. Bounds for binary constant weight codes. <http://www.win.tue.nl/~aeb/codes/Andw.html>, 2019. Accessed June 11, 2019.
- [3] Marco Buratti and Dieter Jungnickel. Partitioned difference families versus zero-difference balanced functions. *Designs, Codes and Cryptography*, 2019. doi: 10.1007/s10623-019-00616-x.
- [4] Marco Buratti, Jie Yan, and Chengmin Wang. From a 1-rotational rbibd to a partitioned difference family. *the electronic journal of combinatorics*, 17(1):139, 2010.
- [5] Han Cai, Xiangyong Zeng, Tor Helleseht, Xiaohu Tang, and Yang Yang. A new construction of zero-difference balanced functions and its applications. *IEEE Transactions on Information Theory*, 59(8):5008–5015, 2013.
- [6] Han Cai, Zhengchun Zhou, Xiaohu Tang, and Ying Miao. Zero-difference balanced functions with new parameters and their applications. *IEEE Transactions on Information Theory*, 63(7):4379–4387, 2017.
- [7] Claude Carlet and Cunsheng Ding. Highly nonlinear mappings. *Journal of complexity*, 20(2):205–244, 2004.

- [8] Claude Carlet, Guang Gong, and Yin Tan. Quadratic zero-difference balanced functions, apn functions and strongly regular graphs. *Designs, Codes and Cryptography*, pages 1–26, 2014.
- [9] Wensong Chu and Charles J Colbourn. Optimal frequency-hopping sequences via cyclotomy. *IEEE Transactions on Information Theory*, 51(3):1139–1141, 2005.
- [10] Wensong Chu, Charles J Colbourn, and Peter Dukes. Constructions for permutation codes in powerline communications. *Designs, Codes and Cryptography*, 32(1-3):51–64, 2004.
- [11] Wensong Chu, Charles J Colbourn, and Peter Dukes. On constant composition codes. *Discrete Applied Mathematics*, 154(6):912–929, 2006.
- [12] Jin-Ho Chung and Kyeongcheol Yang. Optimal frequency-hopping sequences with new parameters. *IEEE Transactions on Information Theory*, 56(4):1685–1693, 2010.
- [13] Charles J Colbourn, Torleiv Klove, and Alan CH Ling. Permutation arrays for powerline communication and mutually orthogonal latin squares. *IEEE Transactions on Information Theory*, 50(6):1289–1291, 2004.
- [14] Cunsheng Ding. Optimal constant composition codes from zero-difference balanced functions. *IEEE Transactions on Information Theory*, 54(12):5766–5770, 2008.
- [15] Cunsheng Ding. Optimal and perfect difference systems of sets. *Journal of Combinatorial Theory, Series A*, 116(1):109–119, 2009.
- [16] Cunsheng Ding and Yin Tan. Zero-difference balanced functions with applications. *Journal of Statistical Theory and Practice*, 6(1):3–19, 2012.
- [17] Cunsheng Ding and Jianxing Yin. Sets of optimal frequency-hopping sequences. *IEEE Transactions on Information Theory*, 54(8):3741–3745, 2008.
- [18] Cunsheng Ding, Qi Wang, and Maosheng Xiong. Three new families of zero-difference balanced functions with applications. *IEEE Transactions on Information Theory*, 60(4):2407–2413, 2014.
- [19] AG Dyachkov. Random constant composition codes for multiple access channels. *Probl. of Control and Inform. Theory*, 13:357–369, 1984.
- [20] Thomas Ericson and Victor Zinoviev. Spherical codes generated by binary partitions of symmetric pointsets. *IEEE transactions on information theory*, 41(1):107–129, 1995.
- [21] Fang-Wei Fu, AJ Han Vinck, and Shi-Yi Shen. On the constructions of constant-weight codes. *IEEE Transactions on Information Theory*, 44(1):328–333, 1998.
- [22] R Fuji-Hara, Y Miao, and S Shinohara. Complete sets of disjoint difference families and their applications. *Journal of statistical planning and inference*, 106(1-2):87–103, 2002.
- [23] Ryoh Fuji-Hara, Koji Momihara, and Mieko Yamada. Perfect difference systems of sets and Jacobi sums. *Discrete Mathematics*, 309(12):3954–3961, 2009.
- [24] Steven Furino. Difference families from rings. *Discrete Mathematics*, 97(1-3):177–190, 1991.
- [25] Lin Jiang and Qunying Liao. A new class of generalized zero-difference balanced functions and applications. *Chinese Annals of Mathematics*, 37(3):243–260, 2016. doi: 10.16205/j.cnki.cama.2016.0021.
- [26] Lin Jiang and Qunying Liao. On generalized zero-difference balanced functions. *Communications of the Korean Mathematical Society*, 31(1):41–52, 2016.
- [27] Oliver D King. Bounds for dna codes with constant gc-content. *the electronic journal of combinatorics*, 10(1):33, 2003.
- [28] P Vijay Kumar. Frequency-hopping code sequence designs having large linear span. *IEEE Transactions on Information Theory*, 34(1):146–151, 1988.
- [29] Abraham Lempel and Haim Greenberger. Families of sequences with optimal hamming-correlation properties. *IEEE Transactions on Information Theory*, 20(1):90–94, 1974.
- [30] Shuxing Li, Hengjia Wei, and Gennian Ge. Generic constructions for partitioned difference families with applications: a unified combinatorial approach. *Designs, Codes and Cryptography*, 82(3):583–599, 2017.
- [31] Zhengqian Li, Pinhui Ke, and Shengyuan Zhang. New classes of generalized zero-difference balanced functions and their applications. *Journal of the Chinese Institute of Engineers*, 42(1):2–8, 2019.
- [32] Fang Liu, Daiyuan Peng, Zhengchun Zhou, and Xiaohu Tang. New constructions of optimal frequency hopping sequences with new parameters. *Advances in Mathematics of Communications*, 7(1), 2013.
- [33] Haibo Liu and Qunying Liao. Some new constructions for generalized zero-difference balanced functions. *International Journal of Foundations of Computer Science*, 27(08):897–908, 2016.
- [34] Junying Liu, Yupeng Jiang, Qunxiong Zheng, and Dongdai Lin. A new construction of zero-difference balanced functions and two applications. *Designs, Codes and Cryptography*, 2019. doi: 10.1007/s10623-019-00632-x.
- [35] Yuan Luo, Fang-Wei Fu, AJ Han Vinck, and Wende Chen. On constant-composition codes over \mathbb{Z}_q . *IEEE Transactions on Information Theory*, 49(11):3010–3016, 2003.
- [36] Olgica Milenkovic and Navin Kashyap. On the design of codes for dna computing. In *International Workshop on Coding and Cryptography*, pages 100–119. Springer, 2005.
- [37] Wakaha Ogata, Kaoru Kurosawa, Douglas R. Stinson, and Hajime Saido. New combinatorial designs and their applications to authentication codes and secret sharing schemes. *Discrete Mathematics*, 279(1-3):383–405, 2004.
- [38] I. Emre Telatar and Robert G. Gallager. Zero error decision feedback capacity of discrete memoryless channels. In *Communication, Control, and Signal Processing: Proceedings of the 1990 Bilkent International Conference on New Trends in Communication, Control, and Signal Processing*, pages 228–233. Bilkent University, Ankara, Turkey, July 1990. Elsevier.
- [39] H Wang. A new bound for difference systems of sets. *Journal of Combinatorial Mathematics and Combinatorial Computing*, 58:161, 2006.
- [40] Qi Wang and Yue Zhou. Sets of zero-difference balanced functions and their applications. *Advances in Mathematics of Communications*, 8(1):83–101, 2014.
- [41] Richard M Wilson. Cyclotomy and difference families in elementary abelian groups. *Journal of Number Theory*, 4(1):17–47, 1972.
- [42] Shanding Xu, Xiwang Cao, Guangkui Xu, and Chunming Tang. Optimal fhss and dsss via near zero-difference balanced functions. *Discrete Applied Mathematics*, 247:433–447, 2018.
- [43] Zongxiang Yi, Zhiqiang Lin, and Lishan Ke. A generic method to construct zero-difference balanced functions. *Cryptography and Commu-*

- nications*, 10(4):591–609, 2018.
- [44] Zongxiang Yi, Dingyi Pei, and Chunming Tang. The Zero-Difference Properties of Functions and Their Applications. *arXiv e-prints*, art. arXiv:1811.08132, Nov 2018.
 - [45] Zongxiang Yi, Yuyin Yu, Chunming Tang, and Yanbin Zheng. A note on two constructions of zero-difference balanced functions. *IEICE TRANSACTIONS on Fundamentals of Electronics, Communications and Computer Sciences*, 102(4):680–684, 2019.
 - [46] Xiangyong Zeng, Han Cai, Xiaohu Tang, and Yang Yang. Optimal frequency hopping sequences of odd length. *IEEE Transactions on information theory*, 59(5):3237–3248, 2013.
 - [47] Zhengbang Zha and Lei Hu. Cyclotomic constructions of zero-difference balanced functions with applications. *IEEE Transactions on Information Theory*, 61(3):1491–1495, 2015.
 - [48] YE Zhifan, KE Pinhui, Shengyuan Zhang, and Zuling Chang. Zero-difference balanced function derived from fermat quotients and its applications. *IEICE Transactions on Fundamentals of Electronics, Communications and Computer Sciences*, 98(11):2336–2340, 2015.
 - [49] Zhengchun Zhou, Xiaohu Tang, Dianhua Wu, and Yang Yang. Some new classes of zero-difference balanced functions. *IEEE Transactions on Information Theory*, 58(1):139–145, 2012.