

On the discretization of Darboux Integrable Systems

Kostyantyn Zheltukhin¹

Department of Mathematics, Middle East Technical University, Ankara, Turkey

Natalya Zheltukhina²

Department of Mathematics, Faculty of Science, Bilkent University, Ankara, Turkey

Abstract *We study the discretization of Darboux integrable systems. The discretization is done using x -, y -integrals of the considered continuous systems. New examples of semi-discrete Darboux integrable systems are obtained.*

Keywords: semi-discrete system, Darboux integrability, x -integral, n -integral.

1 Introduction

The classification problem of Darboux integrable equations has attracted a considerable interest in the recent time, see the survey paper [1] and references there in. There are many classification results in the continuous case. The case of semi-discrete and discrete equations is not that well studied. Discrete models play a big role in many areas of physics and discretization of existing integrable continuous models is an important problem. There is a currently discussed conjecture saying that for each continuous Darboux integrable system it is possible to find a semi-discrete Darboux integrable system that admits the same set of x -integrals. To better understand properties of semi-discrete and discrete Darboux integrable systems it is important to have enough examples of such systems. We can test the conjecture and obtain new semi-discrete Darboux integrable systems, corresponding to given continuous ones, following an approach proposed by Habibullin et al., see [2]. In this case we take a Darboux integrable continuous equation and look for a semi-discrete equation admitting the same integrals. The method was successfully applied to many Darboux integrable continuous equations, see [2]-[4]. In almost all considered cases such semi-discrete equations exist and they are Darboux integrable.

In the present paper we apply this method of discretization to Darboux integrable systems to obtain new Darboux integrable semi-discrete systems. Let us give necessary definitions and formulate the main results of our work.

¹e-mail: zheltukh@metu.edu.tr

²e-mail: natalya@fen.bilkent.edu.tr

Consider a hyperbolic continuous system

$$p_{xy} = \mathcal{A}(p, p_x, p_y) \quad (p_{xy}^i = \mathcal{A}^i(p^1 \dots p^N, p_x^1 \dots p_x^N, p_y^1 \dots p_y^N) \quad i = 1, \dots, N), \quad (1)$$

where $p^i(x, y)$, $i = 1, \dots, N$, are functions of continuous variables $x, y \in \mathbb{R}$. We say that a function $F(x, y, p, p_y, p_{yy}, \dots)$ is an x -integral of the system (1) if

$$D_x F(x, y, p, p_y, p_{yy}, \dots) = 0 \quad \text{on all the solutions of the system (1).}$$

The operator D_x represents the total derivative with respect to x . The y -integral of the system (1) is defined in a similar way. The system (1) is called Darboux integrable if it admits N functionally independent non-trivial x -integrals and N functionally independent non-trivial y -integrals.

Consider a hyperbolic semi-discrete system

$$q_{x1} = \mathcal{B}(q, q_x, q_1), \quad (q_{x1}^i = \mathcal{B}^i(q^1 \dots q^N, q_x^1 \dots q_x^N, q_1^1 \dots q_1^N) \quad i = 1, \dots, N), \quad (2)$$

where $q^i(x, n)$, $i = 1, \dots, N$, are functions of a continuous variable $x \in \mathbb{R}$ and a discrete variable $n \in \mathbb{N}$. Note that we use notation $q_1(x, n) = Dq(x, n) = q(x, n+1)$ and $q_k(x, n) = D^k q(x, n) = q(x, n+k)$, where D is the shift operator. To state the Darboux integrability of a semi-discrete system we need to define x - and n -integrals for such systems, see [5]. An x -integral is defined in the same way as in continuous case and a function $I(x, n, q, q_x, q_{xx}, \dots)$ is an n -integral of system (2) if

$$DI(x, n, q, q_x, q_{xx}, \dots) = I(x, n, q, q_x, q_{xx}, \dots) \quad \text{on all the solutions of the system (2).}$$

The system (2) is called Darboux integrable if it admits N functionally independent non-trivial x -integrals and N functionally independent non-trivial n -integrals.

To find new Darboux integrable semi-discrete systems we applied the discretization method proposed in [2] to one of the continuous systems derived by Zhiber, Kostrigina in [6] and continuous systems derived by Shabat, Yamilov in [7]. In [6] the authors considered the classification problem for Darboux integrable continuous systems that admit the x - and y -integrals of the first and second order. In [7] the authors considered the exponential type system

$$\mu_{xy}^i = e^{\sum a_{ij} \mu^j}, \quad i, j = 1, 2, \dots, N.$$

It was shown that such a system is Darboux integrable if and only if the matrix $A = (a_{ij})$ is a Cartan matrix of a semi-simple Lie algebra. Such systems are closely related to the classical Toda field theories, see [8]-[10] and references there in. In this case we obtain the Darboux integrable semi-discrete systems that were already described in [11].

First we consider the following system (see [6])

$$\begin{cases} u_{xy} = \frac{u_x u_y}{u+v+c} + \left(\frac{1}{u+v+c} + \frac{1}{u+v-c} \right) u_x v_y \\ v_{xy} = \frac{v_x v_y}{u+v-c} + \left(\frac{1}{u+v+c} + \frac{1}{u+v-c} \right) u_x v_y, \end{cases} \quad (3)$$

where c is an arbitrary constant. This system is Darboux integrable and admits the following y -integrals

$$I_1 = 2v - \frac{v_x(u+v+c)}{u_x} + 2c \ln \frac{u_x}{u+v+c} \quad (4)$$

and

$$I_2 = \frac{u_{xx}}{u_x} - \frac{2u_x + v_x}{u+v+c}. \quad (5)$$

The x -integrals have the same form in u, v, u_y, v_y, \dots variables.

Now we look for semi-discrete systems admitting these functions as n -integrals. The obtained results are given in Theorems 1 and 2 below.

Theorem 1 *The system*

$$\begin{cases} u_{1x} = f(x, n, u, v, u_1, v_1, u_x, v_x) \\ v_{1x} = g(x, n, u, v, u_1, v_1, u_x, v_x) \end{cases} \quad (6)$$

possessing n -integrals (4) and (5), where c is a function of n satisfying $c(n) \neq c(n+1)$ for all $n \in \mathbb{Z}$, has the form

$$\begin{cases} u_{1x} = \frac{(u_1 + v_1 + c_1)u_x}{u + v + c} \\ v_{1x} = \frac{2(v_1 - v)u_x}{u + v + c} + \frac{2(c_1 - c)u_x}{u + v + c} \ln \frac{u_x}{u + v + c} + v_x. \end{cases} \quad (7)$$

Moreover, the system above also possesses x -integrals

$$F_1 = \frac{(c - c_1)(v_2 - v) - (c - c_2)(v_1 - v)}{(c - c_2)(v_3 - v) - (c - c_3)(v_2 - v)} \quad (8)$$

and

$$F_2 = \frac{(c_1 - c_2)u + (c_2 - c)u_1 + (c - c_1)u_2}{\sqrt{(c_1 - c_2)v + (c_2 - c)v_1 + (c - c_1)v_2}} - \sqrt{(c_1 - c_2)v + (c_2 - c)v_1 + (c - c_1)v_2}. \quad (9)$$

Hence, semi-discrete system (7) is Darboux integrable.

Theorem 2 *The system (6) possessing n -integrals (4) and (5), where c is a constant, is either*

$$\begin{cases} u_{1x} = \frac{(u_1 + v_1 + c)u_x}{u + v + c} \\ v_{1x} = \frac{2(v_1 - v)u_x}{u + v + c} + v_x \end{cases} \quad (10)$$

with x -integrals $F_1 = \frac{v_1 - v}{v_2 - v_1}$ and $F_2 = \frac{u_2 - u + v - v_2}{\sqrt{v_1 - v}}$, or

$$\begin{cases} u_{1x} = \frac{(u_1 + v_1 + c)Bu_x}{u + v + c} \\ v_{1x} = \frac{2B(v_1 - v + c \ln B)}{u + v + c}u_x + Bv_x, \end{cases} \quad (11)$$

where B is defined by equality $H(K_1, K_2) = 0$ with

$$K_1 = \frac{v_1 - vB + B(1 - B)u + c \ln B}{(B - 1)^2} + c \ln(B - 1) - c \ln B$$

and

$$K_2 = \frac{u_1 + cB - c - c \ln B}{B - 1} + \frac{B^2v - Bv_1 - cB \ln B}{(B - 1)^2} + c \ln(B - 1) - c \ln B,$$

and H being any smooth function.

Remark 1 We considered some special cases of the system (11) and get Darboux integrable systems.

(I) System (11) with $B = \frac{u - v + (-1)^n \sqrt{(u - v)^2 + 4uv_1}}{2u}$ is Darboux Integrable. (The expression for B is found from $K_1 = 0$, with $c = 0$.)

(II) System (11) with $B = \frac{v_1 - u_1 + (-1)^n \sqrt{(v_1 - u_1)^2 + 4u_1v}}{2v}$ is Darboux Integrable. (The expression for B is found from $K_2 = 0$, with $c = 0$.)

Remark 2 Expansion of the function $B(u, v, v_1)$, given implicitly by $(B - 1)^2 K_1 = 0$, into a series of the form

$$B(u, v, v_1) = \sum_{n=0}^{\infty} a_n (v_1 - v)^n, \quad (12)$$

where coefficients a_n depend on variables u and v , yields $a_0 = 1$ and $a_1 = \frac{1}{u + v - c}$. So B can be written as

$$B(u, v, v_1) = 1 + \frac{1}{u + v - c}(v_1 - v) + \sum_{n=2}^{\infty} a_n (v_1 - v)^n. \quad (13)$$

By letting $u_1 = u + \epsilon u_y$ and $v = v + \epsilon v_y$ and taking $\epsilon \rightarrow 0$ one can see that the system (11) has a continuum limit (3).

Let us discuss the exponential type systems. We consider the discretization of such systems corresponding to 2×2 matrices, namely,

$$\begin{aligned} \mu_{xy} &= e^{2\mu - \nu}, \\ \nu_{xy} &= e^{-c\mu - 2\nu}, \end{aligned} \quad (14)$$

where $c = 1, 2, 3$. The obtained results are given in Theorem 3 below. The discretization of such systems was also considered in [11], where the form of the corresponding semi-discrete system was directly postulated and then the Darboux integrability proved. In our approach we do not make any specific assumptions about the form of the corresponding semi-discrete system. Note that the integrals corresponding to Darboux integrable exponential systems are given in the statement of Theorem 3.

Theorem 3 (1) *The system*

$$\begin{cases} u_{1x} = \tilde{f}(u, v, u_1, v_1, u_x, v_x) \\ v_{1x} = \tilde{g}(u, v, u_1, v_1, u_x, v_x), \end{cases} \quad (15)$$

possessing n -integrals

$$I_1 = u_{xx} + v_{xx} - u_x^2 + u_x v_x - v_x^2 \quad (16)$$

and

$$I_1^* = u_{xxx} + u_x(v_{xx} - 2u_{xx}) + u_x^2 v_x - u_x v_x^2 \quad (17)$$

has the form

$$\begin{cases} u_{1x} = u_x + Ae^{u_1+u-v_1} \\ v_{1x} = v_x + Be^{-u+v+v_1}, \end{cases} \quad (18)$$

or

$$\begin{cases} u_{1x} = u_x + Ae^{u_1+u-v} \\ v_{1x} = v_x + Be^{-u_1+v+v_1}, \end{cases} \quad (19)$$

where A and B are arbitrary constants.

(2) *The system (15) possessing n -integrals*

$$I_2 = 2u_{xx} + v_{xx} - 2u_x^2 + 2u_x v_x - v_x^2 \quad (20)$$

and

$$\begin{aligned} I_2^* = & u_{xxxx} + u_x(v_{xxx} - 2u_{xxx}) + u_{xx}(4u_x v_x - 2u_x^2 - v_x^2) \\ & + u_{xx}(v_{xx} - u_{xx}) + v_{xx}u_x(u_x - 2v_x) + u_x^4 + u_x^2 v_x^2 - 2u_x^3 v_x \end{aligned} \quad (21)$$

has the form

$$\begin{cases} u_{1x} = u_x + Ae^{u+u_1-v_1} \\ v_{1x} = v_x + Be^{-2u+v+v_1}, \end{cases} \quad (22)$$

where A and B are arbitrary constants.

(3) The system (15) possessing n -integrals

$$I_3 = u_{xx} + \frac{1}{3}v_{xx} - u_x^2 + u_x v_x - \frac{1}{3}v_x^2 \quad (23)$$

and

$$\begin{aligned} I_3^* = & u_{(6)} - 2u_{(5)}u_x + v_{(5)}u_x + u_{(4)}(32(u_x)^2 - 30u_x v_x + 11(v_x)^2 - 40u_{xx} - 11v_{xx}) \\ & + v_{(4)}(14(u_x)^2 - 15u_x v_x + (13/3)(v_x)^2 - 10u_{xx} - (13/3)v_{xx}) + 19(u_{(3)})^2 + (13/6)(v_{(3)})^2 + 16u_{(3)}v_{(3)} \\ & + u_{(3)}(-36u_{xx}u_x + 18u_{xx}v_x + 80v_{xx}u_x - 45v_{xx}v_x) + v_{(3)}(-52u_{xx}u_x + 33u_{xx}v_x - 5v_{xx}u_x) \\ & + u_{(3)}(-64(u_x)^3 + 102(u_x)^2v_x - 62u_x(v_x)^2 + 13(v_x)^3) + v_{(3)}(32(u_x)^3 - 58(u_x)^2v_x \\ & + 38u_x(v_x)^2 - (26/3)(v_x)^3) + 66(u_{xx})^3 + (26/3)(v_{xx})^3 - 35(u_{xx})^2(v_{xx}) - 5u_{xx}(v_{xx})^2 \\ & + (u_{xx})^2(30(u_x)^2 - 18u_x v_x - (11/2)(v_x)^2) + u_{xx}v_{xx}(-34(u_x)^2 + 32u_x v_x - 2(v_x)^2) - 2(v_{xx})^2u_x v_x \\ & + u_{xx}(6(u_x)^4 - 24(u_x)^3v_x + 25(u_x)^2(v_x)^2 - 9u_x(v_x)^3 + (v_x)^4) + v_{xx}(-(u_x)^4 + 8(u_x)^3v_x - 8(u_x)^2(v_x)^2 \\ & + 2u_x(v_x)^3) + (-2(u_x)^6 + 6(u_x)^5v_x - (13/2)(u_x)^4(v_x)^2 + 3(u_x)^3(v_x)^3 - (1/2)(u_x)^2(v_x)^4) \quad (24) \end{aligned}$$

has the form

$$\begin{cases} u_{1x} = u_x + Ae^{u+u_1-v_1} \\ v_{1x} = v_x + Be^{-3u+v+v_1}, \end{cases} \quad (25)$$

where A and B are arbitrary constants.

Remark 3 We note that while considering systems with integrals (20) and (21) we also obtain two degenerate systems

$$\begin{cases} u_{1x} = u_x \\ v_{1x} = v_x + Be^{-(2+c)u+cu_1+v+v_1}, \end{cases} \quad (26)$$

and

$$\begin{cases} u_{1x} = u_x + Ae^{u+u_1+2cv-(2c+1)v_1} \\ v_{1x} = v_x, \end{cases} \quad (27)$$

where A , B and c are arbitrary constants, which are equivalent to a Darboux integrable equation.

Remark 4 By letting $u = \mu^1$, $u_1 = \mu^1 + \epsilon\mu_y^1$, $v = \mu^2$, $v_1 = \mu^2 + \epsilon\mu_y^2$ and $A = \epsilon$, $B = \epsilon$ in equations (18), (22), (25) and taking $\epsilon \rightarrow 0$ one can see that the considered systems have corresponding continuum limit given by (14).

2 Proof of Theorems 1.1 and 1.2

Let us find a semi-discrete system (6) possessing n -integrals (4) and (5), where c is an arbitrary constant, possibly dependent on n . Let $Dc = c_1$. It follows from $DI_2 = I_2$ that

$$\frac{u_{1xx}}{u_{1x}} - \frac{2u_{1x} + v_{1x}}{u_1 + v_1 + c_1} = \frac{u_{xx}}{u_x} - \frac{2u_x + v_x}{u + v + c},$$

that is

$$\frac{f_x + f_u u_x + f_v v_x + f_{u_1} f + f_{v_1} g + f_{u_x} u_{xx} + f_{v_x} v_{xx}}{f} - \frac{2f + g}{u_1 + v_1 + c_1} = \frac{u_{xx}}{u_x} - \frac{2u_x + v_x}{u + v + c}. \quad (28)$$

Compare the coefficients by v_{xx} and u_{xx} , we get $f_{v_x} = 0$ and $\frac{f_{u_x}}{f} = \frac{1}{u_x}$. Hence

$$f(x, n, u, v, u_1, v_1, u_x, v_x) = A(x, n, u, v, u_1, v_1) u_x. \quad (29)$$

It follows from $DI_1 = I_1$ that

$$2v_1 - \frac{(u_1 + v_1 + c_1)g}{f} + 2c_1 \ln \frac{f}{u_1 + v_1 + c_1} = 2v - \frac{v_x(u + v + c)}{u_x} + 2c \ln \frac{u_x}{u + v + c}. \quad (30)$$

Using (29) we obtain

$$2v_1 - \frac{(u_1 + v_1 + c_1)g}{Au_x} + 2c_1 \ln \frac{Au_x}{u_1 + v_1 + c_1} = 2v - \frac{v_x(u + v + c)}{u_x} + 2c \ln \frac{u_x}{u + v + c}$$

and find g as

$$g = \left(\frac{2(v_1 - v)A}{(u_1 + v_1 + c_1)} + \frac{2Ac_1}{(u_1 + v_1 + c_1)} \ln \frac{(u + v + c)A}{(u_1 + v_1 + c_1)} \right) u_x + \frac{2(c_1 - c)A}{(u_1 + v_1 + c_1)} u_x \ln \frac{u_x}{u + v + c} + \frac{(u + v + c)A}{(u_1 + v_1 + c_1)} v_x. \quad (31)$$

Substituting the expressions (29) and (31) into equality (28) and comparing coefficients by u_x , v_x , $u_x \ln \frac{u_x}{u + v + c}$ and free term we get the following equalities

$$\frac{A_x}{A} = 0 \quad (32)$$

$$\frac{2(c_1 - c)A_{v_1}}{(u_1 + v_1 + c_1)} - \frac{2(c_1 - c)A}{(u_1 + v_1 + c_1)^2} = 0 \quad (33)$$

$$\begin{aligned} \frac{A_u}{A} + A_{u_1} + \left(\frac{A_{v_1}}{A} - \frac{1}{(u_1 + v_1 + c_1)} \right) \left(\frac{2(v_1 - v)A}{(u_1 + v_1 + c_1)} + \frac{2c_1 A}{(u_1 + v_1 + c_1)} \ln \frac{(u + v + c)A}{(u_1 + v_1 + c_1)} \right) \\ - \frac{2A}{(u_1 + v_1 + c_1)} + \frac{2}{(u + v + c)} = 0 \end{aligned} \quad (34)$$

$$\frac{A_v}{A} + \frac{(u + v + c)A_{v_1}}{(u_1 + v_1 + c_1)} - \frac{(u + v + c)A}{(u_1 + v_1 + c_1)^2} + \frac{1}{(u + v + c)} = 0. \quad (35)$$

We have two possibilities: $c_1 \neq c$ and $c_1 = c$.

2.1 c depends on n

First we consider the case $c_1 \neq c$, that is c depends on n and satisfies $c(n) \neq c(n+1)$ for all n .

Then equations (33)-(35) are transformed into

$$\frac{A_{v_1}}{A} - \frac{1}{(u_1 + v_1 + c_1)} = 0 \quad (36)$$

$$\frac{A_u}{A} + A_{u_1} - \frac{2A}{(u_1 + v_1 + c_1)} + \frac{2}{(u + v + c)} = 0 \quad (37)$$

$$\frac{A_v}{A} + \frac{1}{(u + v + c)} = 0. \quad (38)$$

Equations (36) and (38) imply that

$$A = \frac{(u_1 + v_1 + c_1)}{(u + v + c)} M(n, u, u_1). \quad (39)$$

Substituting the above A into (37) we get that M satisfies

$$(u + v + c) \frac{M_u}{M} + (u_1 + v_1 + c_1) M_{u_1} + (1 - M) = 0. \quad (40)$$

Differentiating equation (40) with respect to v and v_1 we get that $M_u = 0$ and $M_{u_1} = 0$ respectively.

Thus, equation (40) implies that $M = 1$. So in the case $c_1 \neq c$ we arrive to the system of equations (7). We note that the system (7) is Darboux integrable. It admits two n -integrals (4) and (5) and two x -integrals (8) and (9). The x -integrals can be found by considering the characteristic x -ring for system (7).

2.2 c does not depend on n

Now we consider the case $c = c_1$, that is c is a constant independent of n . Then we have equations

(34) and (35). Introducing new variable $B = \frac{(u + v + c)}{(u_1 + v_1 + c)} A$ we can rewrite the equations as

$$\frac{B_u}{B} + \frac{(u_1 + v_1 + c)}{(u + v + c)} B_{u_1} + 2 \frac{(v_1 - v + c \ln B)}{(u + v + c)} B_{v_1} + \frac{1 - B}{(u + v + c)} = 0 \quad (41)$$

$$\frac{B_v}{B} + B_{v_1} = 0. \quad (42)$$

The set of solutions of the above system is not empty, for example it admits a solution $B = 1$.

Setting $B = 1$ we arrive to the system of equations (10). We note that the system (10) is Darboux integrable. It admits two n -integrals (4) and (5) and two x -integrals

$$F_1 = \frac{v_1 - v}{v_2 - v_1}, \quad F_2 = \frac{u_2 - u + v - v_2}{\sqrt{v_1 - v}}.$$

The x -integrals are calculated by considering the characteristic x -ring for system (10).

Now let us consider case when $B \neq 1$ identically. For function $W = W(u, v, u_1, v_1, B)$ equations (41) and (42) become

$$\frac{W_u}{B} + \frac{(u_1 + v_1 + c)}{(u + v + c)}W_{u_1} + 2\frac{(v_1 - v + c \ln B)}{(u + v + c)}W_{v_1} + \frac{B - 1}{(u + v + c)}W_B = 0 \quad (43)$$

$$\frac{W_v}{B} + W_{v_1} = 0. \quad (44)$$

After the change of variables $\tilde{v} = v + c$, $\tilde{v}_1 = v_1 + c - (v + c)B$, $\tilde{u} = u$, $\tilde{u}_1 = u_1$, $\tilde{B} = B$ equations (44) and (43) become $W_{\tilde{v}} = 0$ and

$$\frac{\tilde{u} + \tilde{v}}{\tilde{B}}W_{\tilde{u}} + (\tilde{u}_1 + \tilde{v}_1 + \tilde{v}\tilde{B})W_{\tilde{u}_1} + (2\tilde{v}_1 + 2c \ln \tilde{B} + \tilde{v}(\tilde{B} - 1))W_{\tilde{v}_1} + (\tilde{B} - 1)W_{\tilde{B}} = 0.$$

We differentiate the last equality with respect to \tilde{v} , use $W_{\tilde{v}} = 0$, and find that W satisfies the following equations

$$\begin{aligned} \frac{W_{\tilde{u}}}{\tilde{B}} + \tilde{B}W_{\tilde{u}_1} + (\tilde{B} - 1)W_{\tilde{v}_1} &= 0 \\ \frac{\tilde{u}}{\tilde{B}}W_{\tilde{u}} + (\tilde{u}_1 + \tilde{v}_1)W_{\tilde{u}_1} + (2\tilde{v}_1 + 2c \ln \tilde{B})W_{\tilde{v}_1} + (\tilde{B} - 1)W_{\tilde{B}} &= 0. \end{aligned}$$

After doing another change of variables $u_1^* = \tilde{u}_1 - \tilde{B}^2\tilde{u}$, $v_1^* = \tilde{v}_1 + \tilde{B}(1 - \tilde{B})\tilde{u}$, $u^* = \tilde{u}$, $B^* = \tilde{B}$, we obtain that $W_{u^*} = 0$ and

$$(u_1^* + v_1^*)W_{u_1^*} + (2v_1^* + 2c \ln B^*)W_{v_1^*} + (B^* - 1)W_{B^*} = 0.$$

The first integrals of the last equation are

$$K_1 = \frac{v_1^*}{(B^* - 1)^2} + \frac{c \ln B^*}{(B^* - 1)^2} - c \ln B^* + c \ln(B^* - 1) + \frac{c}{B^* - 1}$$

and

$$K_2 = \frac{u_1^* - c - c \ln B^*}{B^* - 1} - \frac{B^*v_1^*}{(B^* - 1)^2} - \frac{cB^* \ln B^*}{(B^* - 1)^2} + c \ln(B^* - 1) - c \ln B^*.$$

They can be rewritten in the original variables as

$$K_1 = \frac{v_1 - vB + B(1 - B)u + c \ln B}{(B - 1)^2} + c \ln(B - 1) - c \ln B$$

and

$$K_2 = \frac{u_1 + cB - c - c \ln B}{B - 1} + \frac{B^2v - Bv_1 - cB \ln B}{(B - 1)^2} + c \ln(B - 1) - c \ln B.$$

Therefore, system (6) becomes (11) due to (29) and (31).

2.3 Proof of Remark 1.1

Function B is any function satisfying the equality $H(K_1, K_2) = 0$, where H is any smooth function.

(I) By taking function H as $H(K_1, K_2) = K_1$ we obtain one possible function B . It satisfies the equality $-uB^2 + (u - v)B + v_1 = 0$ and can be taken as $B = \frac{u - v + (-1)^n \sqrt{(u - v)^2 + 4uv_1}}{2u}$

(II) By taking function H as $H(K_1, K_2) = K_2$ we obtain another possible function B . It satisfies the equality $vB^2 + (u_1 - v_1)B - u_1 = 0$ and can be taken as $B = \frac{v_1 - u_1 + (-1)^n \sqrt{(v_1 - u_1)^2 + 4u_1v}}{2v}$.

In both cases ((I) and (II)) let us consider the corresponding x -rings. Denote by $X = D_x$, $Y_1 = \frac{\partial}{\partial u_x}$, $Y_2 = \frac{\partial}{\partial v_x}$, $E_1 = \frac{u + v}{B}[Y_1, X]$, $E_2 = \frac{1}{B}[Y_2, X]$, $E_3 = [E_1, E_2]$. Note that $X = u_x E_1 + v_x E_2$. We have,

$[E_i, E_j]$	E_1	E_2	E_3
E_1	0	E_3	$\alpha_1 E_2 + \alpha_2 E_3$
E_2	$-E_3$	0	0
E_3	$-(\alpha_1 E_2 + \alpha_2 E_3)$	0	0

where

$$\alpha_1 = \frac{2v_1(u - v) + 2(uv - v^2 + 2uv_1)B}{v_1(u - v) + ((u - v)^2 + 2uv_1)B}, \quad \alpha_2 = -3 + \frac{2}{B}$$

in case (I) and

$$\alpha_1 = \frac{2u_1^2 + 4u_1v - 2u_1v_1 + 2(-(u_1 - v_1)^2 + vv_1 - 3vu_1)B}{u_1(v_1 - u_1) + ((u_1 - v_1)^2 + 2u_1v)B}, \quad \alpha_2 = -3 + \frac{2}{B}$$

in case (II).

3 Proof of Theorem 1.3

3.1 Case (1)

Let us find a system

$$\begin{cases} u_{1x} = \tilde{f}(x, n, u, v, u_1, v_1, u_x, v_x) \\ v_{1x} = \tilde{g}(x, n, u, v, u_1, v_1, u_x, v_x) \end{cases} \quad (45)$$

possessing n -integrals (16) and (17). The equality $DI = I$ implies

$$u_{1xx} + v_{1xx} - u_{1x}^2 + u_{1x}v_{1x} - v_{1x}^2 = u_{xx} + v_{xx} - u_x^2 + u_xv_x - v_x^2, \quad (46)$$

or the same

$$\begin{aligned} & \tilde{f}_x + \tilde{f}_u u_x + \tilde{f}_v v_x + \tilde{f}_{u_1} \tilde{f} + \tilde{f}_{v_1} \tilde{g} + \tilde{f}_{u_x} u_{xx} + \tilde{f}_{v_x} v_{xx} + \tilde{g}_x + \tilde{g}_u u_x + \tilde{g}_v v_x \\ & + \tilde{g}_{u_1} \tilde{f} + \tilde{g}_{v_1} \tilde{g} + \tilde{g}_{u_x} u_{xx} + \tilde{g}_{v_x} v_{xx} - \tilde{f}^2 + \tilde{f}\tilde{g} - \tilde{g}^2 = u_{xx} + v_{xx} - u_x^2 + u_xv_x - v_x^2. \end{aligned} \quad (47)$$

We consider the coefficients by u_{xx} and u_{xx} in (47) to get

$$\tilde{f}_{u_x} + \tilde{g}_{u_x} = 1 \quad (48)$$

$$\tilde{f}_{v_x} + \tilde{g}_{v_x} = 1. \quad (49)$$

The equality $DI_1^* = I_1^*$ implies

$$u_{1xxx} + u_{1x}(v_{1xx} - 2u_{1xx}) + u_{1x}^2 v_{1x} - u_{1x} v_{1x}^2 = u_{xxx} + u_x(v_{xx} - 2u_{xx}) + u_x^2 v_x - u_x v_x^2. \quad (50)$$

Since $DI_1^* = u_{1xxx} + \dots = \tilde{f}_{u_x} u_{xxx} + \dots$, where the remaining terms do not depend on u_{xxx} , the equality (50) implies

$$\tilde{f}_{u_x} = 1. \quad (51)$$

Note that $J = D_x I_1 - I_1^* = v_{xxx} + v_x(u_{xx} - 2v_{xx}) + v_x^2 u_x - u_x^2 v_x$ is an n -integral as well. Since $DJ = J$ and $DJ = v_{1xxx} + \dots = \tilde{g}_{v_x} v_{xxx} + \dots$, where the remaining terms do not depend on v_{xxx} , then

$$\tilde{g}_{v_x} = 1. \quad (52)$$

It follows from equalities (48), (49), (51) and (52) that $\tilde{f}_{v_x} = 0$ and $\tilde{g}_{u_x} = 0$. Therefore the system (45) and equality (47) become

$$\begin{cases} u_{1x} = u_x + f(x, n, u, v, u_1, v_1) \\ v_{1x} = v_x + g(x, n, u, v, u_1, v_1) \end{cases} \quad (53)$$

and

$$\begin{aligned} f_x + f_u u_x + f_v v_x + f_{u_1}(u_x + f) + f_{v_1}(v_x + g) + g_x + g_u u_x + g_v v_x + g_{u_1}(u_x + f) \\ + g_{v_1}(v_x + g) - 2u_x f - f^2 + u_x g + v_x f + fg - 2v_x g - g^2 = 0 \end{aligned} \quad (54)$$

By considering coefficients by u_x , v_x and $u_x^0 v_x^0$ in the last equality, we get

$$(f + g)_u + (f + g)_{u_1} + (f + g) - 3f = 0 \quad (55)$$

$$(f + g)_v + (f + g)_{v_1} + (f + g) - 3g = 0 \quad (56)$$

$$f(f + g)_{u_1} + g(f + g)_{v_1} + (f + g)_x - (f + g)^2 + 3fg = 0. \quad (57)$$

Now let us rewrite inequality (50) for the system (53)

$$\begin{aligned} D_x(f_x + f_u u_x + f_v v_x + f_{u_1}(u_x + f) + f_{v_1}(v_x + g)) \\ + (u_x + f)(g_x + g_u u_x + g_v v_x + g_{u_1}(u_x + f) + g_{v_1}(v_x + g) + v_{xx}) \\ + (u_x + f)(-2f_x - 2f_u u_x - 2f_v v_x - 2f_{u_1}(u_x + f) - 2f_{v_1}(v_x + g) - 2u_{xx}) \\ + (u_x^2 + 2u_x f + f^2)(v_x + g) - (v_x^2 + 2v_x g + g^2)(u_x + f) = u_x(v_{xx} - 2u_{xx}) + u_x^2 v_x - u_x v_x^2. \end{aligned} \quad (58)$$

By comparing the coefficients by u_{xx} and v_{xx} in the last equality, we get

$$\begin{aligned} f_u + f_{u_1} &= 2f \\ f_v + f_{v_1} &= -f. \end{aligned} \quad (59)$$

It follows from equality $DJ = J$ that

$$\begin{aligned} &D_x(g_x + g_u u_x + g_v v_x + g_{u_1}(u_x + f) + g_{v_1}(v_x + g)) \\ &\quad + (v_x + g)(f_x + f_u u_x + f_v v_x + f_{u_1}(u_x + f) + f_{v_1}(v_x + g) + u_{xx}) \\ &\quad - 2(v_x + g)(g_x + g_u u_x + g_v v_x + g_{u_1}(u_x + f) + g_{v_1}(v_x + g) + v_{xx}) \\ &\quad + (u_x + f)(v_x^2 + 2v_x g + g^2) - (v_x + g)(u_x^2 + 2u_x f + f^2) = v_x(u_{xx} - 2v_{xx}) + v_x^2 u_x - u_x^2 v_x. \end{aligned} \quad (60)$$

By comparing the coefficients by u_{xx} and v_{xx} in the last equality, we get

$$\begin{aligned} g_u + g_{u_1} &= -g \\ g_v + g_{v_1} &= 2g. \end{aligned} \quad (61)$$

Note that the equalities (55) and (56) follow from equalities (59) and (61). Let us use equalities (59) and (61) to rewrite equality (58)

$$\begin{aligned} &D_x(f_x + 2f u_x - f v_x + f_{u_1} f + f_{v_1} g) + (u_x + f)(g_x + g_{u_1} f + g_{v_1} g + v_{xx} - 4f u_x - 2f_x) \\ &\quad + (u_x + f)(2f v_x - 2f_{u_1} f - 2f_{v_1} g - 2u_{xx} + u_x v_x + f v_x + f g - v_x^2 - g^2) \\ &\quad = u_x(v_{xx} - 2u_{xx}) + u_x^2 v_x - u_x v_x^2. \end{aligned}$$

We note that the consideration of the coefficients by u_{xx} , v_{xx} , u_x^2 , v_x^2 , $u_x v_x$ in the above equality give us equations that follow immediately from (59) and (61). Considering coefficient by u_x we get

$$\begin{aligned} &f_{xu} + f_{xu_1} + 2f_x + 2f f_{u_1} + 2f_{v_1} g + f f_{u_1 u} + f_{u_1} f_u + f_{u_1}^2 + g f_{v_1 u} \\ &\quad + g f_{u_1 v_1} + f_{v_1} g_u + f_{v_1} g_{u_1} + f_{u_1 u_1} f + g_x + g_{u_1} f + g_{v_1} g - 2f_x - 2f_{u_1} f - 2f_{v_1} g + f g - g^2 - 4f^2 = 0. \end{aligned}$$

Using equations (59) and (61) we get

$$2f_x + g_x + 4f f_{u_1} + f_{v_1} g + g_{u_1} f + g_{v_1} g + f g - g^2 - 4f^2 = 0,$$

or using equation (57) ,

$$f_x + 3f(f_{u_1} - f) = 0. \quad (62)$$

Considering coefficient by v_x we get

$$f_{xv} + f_{xv_1} - f_x - ff_{u_1} - f_{v_1}g + ff_{u_1v} + ff_{u_1v_1} + f_{u_1}f_v + f_{u_1}f_{v_1} \\ + gf_{v_1v} + gf_{v_1v_1} + f_{v_1}g_v + f_{v_1}g_{v_1} + 3f^2 = 0.$$

Using equations (59) and (61) we get

$$2f_x + 3f(f_{u_1} - f) = 0. \quad (63)$$

It follows from equations (62) and (63) that $f_x = 0$ and $f(f_{u_1} - f) = 0$. Thus either $f = 0$ or

$$\begin{cases} f = f_{u_1} \\ f = f_u. \end{cases} \quad (64)$$

Now we consider the coefficient by $u_x^0v_x^0$ in (58) we get

$$f^2f_{u_1u_1} + fgf_{u_1v_1} + ff_{u_1}^2 + f_{u_1}f_{v_1}g + fgf_{u_1v_1} + g^2f_{v_1v_1} + f_{v_1}g_x + ff_{v_1}g_{u_1} \\ + gf_{v_1}g_{v_1} + fg_x + f^2g_{u_1} + fgg_{v_1} - 2f^2f_{u_1} - 2fgf_{v_1} + f^2g - fg^2 = 0.$$

First assume that $f \neq 0$ then using (64) we can rewrite the above equality as

$$fgf_{v_1} + g^2f_{v_1v_1} + f_{v_1}g_x + f_{v_1}g_{u_1}f + f_{v_1}g_{v_1}g + fg_x + f^2g_{u_1} + fgg_{v_1} + f^2g - fg^2 = 0. \quad (65)$$

Also we can rewrite equality (60), using equations (59), (61) and (57) then considering coefficients by u_x and v_x we obtain

$$2g_x + 3g(g_{v_1} - g) = 0 \\ g_x + 3g(g_{v_1} - g) = 0.$$

From above equalities and (61) it follows that $g_x = 0$, $g_{v_1} = g$ and $g_v = g$ (we assume that $g \neq 0$).

We have

$$\begin{aligned} f_{u_1} = f, \quad f_u = f, \quad f_v + f_{v_1} = -f \\ g_{v_1} = g, \quad g_v = g, \quad g_u + g_{u_1} = -g \\ f_{v_1}g + g_{u_1}f = -fg. \end{aligned} \quad (66)$$

Using (66), the equality (65) takes form $g_{u_1}f_{v_1}(-g + f) = 0$. This equality implies that under assumptions that $f \neq 0$ and $g \neq 0$ we have three possibilities: (I) $g_{u_1} = 0$, (II) $f_{v_1} = 0$ and (III) $g = f$. Let us consider these possibilities.

Case (I) From $g_{u_1} = 0$, using (66), we get that $g_u = -g$, $g_{v_1} = g$, $g_v = g$. Thus $g = Be^{-u+v+v_1}$, where B is a constant. We also get that $f_u = f$, $f_{u_1} = f$, $f_v = 0$ and $f_{v_1} = -f$. Thus $f = Ae^{u_1+u-v_1}$, where A is a constant. So the system (53) takes form (18).

Case (II) From $f_{v_1} = 0$, using (66), we get that $f_u = f$, $f_{u_1} = f$, $f_v = -f$. Thus $f = Ae^{u_1+u-v}$, where A is a constant. We also get that $g_u = 0$, $g_{u_1} = -g$, $g_v = g$ and $g_{v_1} = g$. Thus $g = Be^{-u_1+v_1+v}$, where B is a constant. So the system (53) takes form (19).

Case (III) From $g = f$, using (66), we get that $f = 0$ and $g = 0$. So the system (53) takes form

$$\begin{cases} u_{1x} &= u_x \\ v_{1x} &= v_x. \end{cases}$$

3.2 Case (2)

Let us find system (15) possessing n -integrals (20) and (21). We compare the coefficients in $DI_2 = I_2$ by u_{xx} and v_{xx} and get

$$\begin{aligned} 2\tilde{f}_{u_x} + \tilde{g}_{u_x} &= 2 \\ 2\tilde{f}_{v_x} + \tilde{g}_{v_x} &= 1. \end{aligned} \tag{67}$$

We also compare the coefficients in $DI_2^* = I_2^*$ and

$D(D_x^2 I_2 - 2I_2^*) = (D_x^2 I_2 - 2I_2^*)$ by u_{xxxx} and v_{xxxx} respectively and get $\tilde{f}_{u_x} = 1$ and $\tilde{g}_{v_x} = 1$. It follows from (67) that $\tilde{f}_{v_x} = 0$ and $\tilde{g}_{u_x} = 0$. Therefore, our system (15) becomes

$$\begin{cases} u_{1x} &= u_x + f(u, v, u_1, v_1) \\ v_{1x} &= v_x + g(u, v, u_1, v_1). \end{cases}$$

We write equality $DI_2 = I_2$ and get

$$\begin{aligned} 2u_{xx} + 2f_u u_x + 2f_v v_x + 2f_{u_1}(u_x + f) + 2f_{v_1}(v_x + g) + v_{xx} + g_u u_x + g_v v_x + g_{u_1}(u_x + f) \\ + g_{v_1}(v_x + g) - 2(u_x + f)^2 + 2(u_x + f)(v_x + g) - (v_x + g)^2 = 2u_{xx} + v_{xx} - 2u_x^2 + 2u_x v_x - v_x^2. \end{aligned}$$

By comparing the coefficients by u_x , v_x and $u_x^0 v_x^0$ in the last equality we obtain the system of equations

$$\begin{aligned} 2f_u + f_{u_1} + g_u + g_{u_1} - 4f + 2g &= 0 \\ 2f_v + 2f_{v_1} + g_v + g_{v_1} + 2f - 2g &= 0 \\ 2ff_{u_1} + 2gf_{v_1} + fg_{u_1} + gg_{v_1} - 2f^2 + 2fg - g^2 &= 0. \end{aligned}$$

That suggests the following change of variables

$$u = P, \quad u_1 - u = Q, \quad v = S, \quad v_1 - v = T$$

to be made. In new variables the system (15) becomes

$$\begin{cases} Q_x &= F(P, Q, S, T) \\ T_x &= G(P, Q, S, T). \end{cases} \tag{68}$$

The comparison of coefficients in $DI_2 = I_2$ by P_x , S_x and $P_x^0 S_x^0$ gives

$$\begin{aligned} -4F + 2G + 2F_P + G_P &= 0 \\ 2F - 2G + 2F_S + G_S &= 0 \\ -2F^2 + G(-G + 2F_T + G_T) + F(2G + 2F_Q + G_Q) &= 0. \end{aligned} \tag{69}$$

The coefficients in $DI_2^* = I_2^*$ by S_{xxx} and P_{xxx} are compared and we obtain the following equalities

$$\begin{aligned} F + F_S &= 0 \\ -2F + F_P &= 0. \end{aligned} \tag{70}$$

It follows from (69) and (70) that $G_S = 2G$, $G_P = -2G$, $F_S = -F$ and $F_P = 2F$. Therefore, system (68) can be written as

$$\begin{cases} Q_x = A(Q, T)e^{-S+2P} \\ T_x = B(Q, T)e^{2S-2P}. \end{cases}$$

We compare the coefficient in $DI_2^* = I_2^*$ by S_{xx} and get

$$3e^{4P-2S}A^2 - 3e^{4P-2S}AA_Q = 0,$$

that is $A = A_Q$. Hence, $A(Q, T) = e^Q \tilde{A}(T)$. Now we compare the coefficient in $DI_2 = I_2$ by $P_x^0 S_x^0$ and get

$$\tilde{A} + \tilde{A}_T = \frac{1}{2}e^{-4P+3S-Q}(B - B_T) - \frac{\tilde{A}}{2B}B_Q. \tag{71}$$

Since functions $\tilde{A}(T)$ and $B(Q, T)$ do not depend on variable P , then it follows from (71) that $B = B_T$, that is $B = \tilde{B}(Q)e^T$. Now (71) becomes

$$-2\frac{\tilde{A} + \tilde{A}_T}{\tilde{A}} = \frac{\tilde{B}_Q}{\tilde{B}}.$$

Note that the right side of the last equality depends on Q only, while the left side depends on T only. Hence, $-2\frac{\tilde{A} + \tilde{A}_T}{\tilde{A}} = c$ and $\frac{\tilde{B}_Q}{\tilde{B}} = c$, where c is some constant. One can see that $\tilde{A} = c_1 e^{-(2c+1)T}$ and $\tilde{B} = c_2 e^{cQ}$ and therefore system (68) becomes

$$\begin{cases} Q_x = c_1 e^{-S+2P+Q-(2c+1)T} \\ T_x = c_2 e^{2S-2P+T+cQ}, \end{cases}$$

where c , c_1 and c_2 are some constants. Equality $DI_2 - I_2 = 0$ becomes $-3cc_1c_2e^{s+(c+1)Q-2cT} = 0$, which implies that either $c = 0$, or $c_1 = 0$, or $c_2 = 0$. Note that the $DI_2^* = I_2^*$ is also satisfied if either $c = 0$ or $c_1 = 0$ or $c_2 = 0$. So we have three cases:

when $c = 0$ the system (15) becomes (22) with $c_1 = A$ and $c_2 = B$.

when $c_1 = 0$ the system (15) becomes (26) with $c_2 = B$.

when $c_2 = 0$ the system (15) becomes (27) with $c_1 = A$.

3.3 Case (3)

Let us find system (15) possessing n -integrals (23) and (24). We compare the coefficients in $DI_3 = I_3$ by u_{xx} and v_{xx} and get

$$\begin{aligned}\tilde{f}_{u_x} + \frac{1}{3}\tilde{g}_{u_x} &= 1 \\ \tilde{f}_{v_x} + \frac{1}{3}\tilde{g}_{v_x} &= 1.\end{aligned}\tag{72}$$

We also compare the coefficients in $DI_3^* = I_3^*$ and $D(D_x^4 I_3 - I_3^*) = (D_x^4 I_3 - I_3^*)$ by $u_{(6)}$ and $v_{(6)}$ respectively and get $\tilde{f}_{u_x} = 1$ and $\tilde{g}_{v_x} = 1$. It follows from (72) that $\tilde{f}_{v_x} = 0$ and $\tilde{g}_{u_x} = 0$. Therefore, our system (15) becomes

$$\begin{cases} u_{1x} = u_x + f(u, v, u_1, v_1) \\ v_{1x} = v_x + g(u, v, u_1, v_1). \end{cases}$$

By comparing the coefficients by u_x , v_x and $u_x^0 v_x^0$ in $DI_3 = I_3$ we obtain the system of equations

$$\begin{aligned}f_u + f_{u_1} + \frac{1}{3}g_u + \frac{1}{3}g_{u_1} - 2f + g &= 0 \\ f_v + f_{v_1} + \frac{1}{3}g_v + \frac{1}{3}g_{v_1} + f - \frac{2}{3}g &= 0 \\ ff_{u_1} + gf_{v_1} + \frac{1}{3}fg_{u_1} + \frac{1}{3}gg_{v_1} - f^2 + fg - \frac{1}{3}g^2 &= 0.\end{aligned}$$

That suggests the following change of variables

$$u = P, \quad u_1 - u = Q, \quad v = S, \quad v_1 - v = T$$

to be made. In new variables the system (15) becomes

$$\begin{cases} Q_x = F(P, Q, S, T) \\ T_x = G(P, Q, S, T). \end{cases}\tag{73}$$

The comparison of coefficients in $DI_3 = I_3$ by P_x , S_x and $P_x^0 S_x^0$ gives

$$\begin{aligned}6F - 3G - 3F_P - G_P &= 0 \\ -3F + 2G - 3F_S - G_S &= 0 \\ F^2 - FG + \frac{1}{3}G^2 - 2GF_T - \frac{1}{3}GG_T - FF_Q - \frac{1}{3}FG_Q &= 0.\end{aligned}\tag{74}$$

The comparison of coefficients in $DI_3^* = I_3^*$ by $S_{(5)}$ and $P_{(5)}$ gives

$$\begin{aligned}F + F_S &= 0 \\ -2F + F_P &= 0.\end{aligned}\tag{75}$$

Using equations (74) and (75) we get $G_S = 2G$, $G_P = -3G$, $F_S = -F$, and $F_P = 2F$. Therefore, system (73) can be written as

$$\begin{cases} Q_x = A(Q, T)e^{-S+2P} \\ T_x = B(Q, T)e^{2S-3P}, \end{cases}$$

where A and B are some functions depending on Q and T only. We compare the coefficients in $DI_3 - I_3 = 0$ by $S_x^0 P_x^0$ and the coefficients in $DI_3^* - I_3^* = 0$ by $P_{(4)}$, $S_{(4)}$ and $P_{(3)}P_x$ respectively and get

$$\begin{aligned}
a_{11}A_T + a_{12}B_T + a_{13}A_Q + a_{14}B_Q + b_1 &= 0 \\
a_{21}A_T + a_{22}B_T + a_{23}A_Q + a_{24}B_Q + b_2 &= 0 \\
a_{31}A_T + a_{32}B_T + a_{33}A_Q + a_{34}B_Q + b_3 &= 0 \\
a_{41}A_T + a_{42}B_T + a_{43}A_Q + a_{44}B_Q + b_4 &= 0,
\end{aligned} \tag{76}$$

where

$$\begin{aligned}
a_{11} &= -e^{-P+S}B, & a_{12} &= -\frac{1}{3}e^{-6P+4S}B, & a_{13} &= -e^{4P-2S}A, & a_{14} &= -\frac{1}{3}e^{-P+S}A, \\
a_{21} &= -33e^{-P+S}B, & a_{22} &= -11e^{-6P+4S}B, & a_{23} &= -28e^{4P-2S}A, & a_{24} &= -11e^{-P+S}A, \\
a_{31} &= -13e^{-P+S}B, & a_{32} &= -\frac{13}{3}e^{-6P+4S}B, & a_{33} &= -16e^{4P-2S}A, & a_{34} &= -\frac{13}{3}e^{-P+S}A, \\
a_{41} &= 18e^{-P+S}B, & a_{42} &= -79e^{-6P+4S}B, & a_{43} &= 328e^{4P-2S}A, & a_{44} &= 6e^{-P+S}A,
\end{aligned}$$

and

$$\begin{aligned}
b_1 &= e^{4P-2S}A^2 - e^{-P+S}AB + \frac{1}{3}e^{-6P+4S}B^2 \\
b_2 &= 28e^{4P-2S}A^2 - 33e^{-P+S}AB + 11e^{-6P+4S}B^2 \\
b_3 &= 16e^{4P-2S}A^2 - 13e^{-P+S}AB + \frac{13}{3}e^{-6P+4S}B^2 \\
b_4 &= -328e^{4P-2S}A^2 + 18e^{-P+S}AB + 79e^{-6P+4S}B^2.
\end{aligned}$$

We solve the linear system of equations (76) with respect to A_T , A_Q , B_T and B_Q and get the following system of differential equations $A_T = -A$, $A_Q = A$, $B_T = B$ and $B_Q = 0$. Thus the system (73) is written as

$$\begin{cases} Q_x &= c_1 e^{2P+Q-S-T} \\ T_x &= c_2 e^{-3P+2S+T}, \end{cases}$$

where c_1 and c_2 are arbitrary constants. It is equivalent to system (25) with $A = c_1$ and $B = c_2$.

References

- [1] A.V. Zhiber, R.D. Murtazina, I.T. Habibullin, and A.B. Shabat, Characteristic Lie rings and integrable models in mathematical physics, *Ufa Math. J.* **4** (3)(2012) 17–85.
- [2] I.T. Habibullin, N. Zheltukhina, and A. Sakieva, Discretization of hyperbolic type Darboux integrable equations preserving integrability, *J. Math. Phys.* **52** (2011) 093507–093519.
- [3] I.T. Habibullin and N. Zheltukhina, Discretization of Liouville type nonautonomous equations *J. Nonlinear Math. Phys.* **23** (2016) 620–642.

- [4] K. Zheltukhin and N. Zheltukhina, On the discretization of Laine equations, *J. Nonlinear Math. Phys.* **25** (2018) 166–177 .
- [5] I.T. Habibullin, A. Pekcan, Characteristic Lie algebra and the classification of semi-discrete models, *Theoret. and Math. Phys.* **151** (2007) 781790.
- [6] O.S. Kostrigina and A.V. Zhiber, Darboux-integrable two-component nonlinear hyperbolic systems of equations, *J. Math. Phys.* **52** (2011) 033503–033535.
- [7] A.B. Shabat and R.I. Yamilov Exponential Systems of Type I and the Cartan Matrices (Russian) *Preprint BBAS USSR Ufa* (1981).
- [8] N.H. Ibragimov, A.V. Aksenov, V.A. Baikov, V.A. Chugunov, R.K. Gazizov and A.G. Meshkov CRC Handbook of Lie Group Analysis of Differential Equations Vol. 2. Applications in Engineering and Physical Science, edited by Ibragimov *Boca Raton, FL: CRC Press* (1995).
- [9] E.I. Ganzha and S.P. Tsarev, Integration of Classical Series A_n , B_n , C_n , of Exponential Systems *Krasnoyarsk: Krasnoyarsk State Pedagogical University Press* (2001).
- [10] A.N. Leznov and M.V. Savelev, Group Methods of Integration of Nonlinear Dynamical Systems, *Progress in Physics* **15** *Birkhuser Verlag, Basel* (1992).
- [11] I.T. Habibullin, K. Zheltukhin, and M. Yangubaeva, Cartan matrices and integrable lattice Toda field equations, *J. Phys. A* **44** (2011) 465202–465222.