

System of Lane-Emden equations as IVPs BVPs and Four Point BVPs & Computation with Haar Wavelets

Amit K. Verma^{a*}, Narendra Kumar^b, Diksha Tiwari^c

^{a,b}Department of Mathematics

Indian Institute of Technology Patna,

Bihta, Patna 801103, (BR) India.

^cFaculty of Mathematics, University of Vienna, Austria.

January 3, 2022

Abstract

In this work we present Haar wavelet collocation method and solve the following class of system of Lane-Emden equation defined as

$$\begin{aligned} -(t^{k_1} y'(t))' &= t^{-\omega_1} f_1(t, y(t), z(t)), \\ -(t^{k_2} z'(t))' &= t^{-\omega_2} f_2(t, y(t), z(t)), \end{aligned}$$

where $t > 0$, subject to initial values, boundary values and four point boundary values:

$$\begin{aligned} \text{Initial Condition:} \quad & y(0) = \gamma_1, \quad y'(0) = 0, \quad z(0) = \gamma_2, \quad z'(0) = 0, \\ \text{Boundary Condition:} \quad & y'(0) = 0, \quad y(1) = \delta_1, \quad z'(0) = 0, \quad z(1) = \delta_2, \\ \text{Four point Boundary Condition:} \quad & y(0) = 0, \quad y(1) = n_1 z(v_1), \quad z(0) = 0, \quad z(1) = n_2 y(v_2), \end{aligned}$$

where $n_1, n_2, v_1, v_2 \in (0, 1)$ and $k_1 \geq 0, k_2 \geq 0, \omega_1 < 1, \omega_2 < 1$ are real constants. Results are compared with exact solutions in the case of IVP and BVP. In case of four point BVP we compare the result with other methods. Convergence of these methods is also established and found to be of second order. We observe that as resolution is increased to $J = 4$ we get the exact values for IVPs and BVPs. For four point BVPs also at $J = 4$, we get highly accurate solutions, e.g., the L^∞ error is of order 10^{-16} or 10^{-17} .

Keywords: Haar Wavelet; Coupled Lane-Emden Equations; IVPs; BVPs; Four Point BVPs;

AMS Subject Classification: 65T60; 65L05; 34B16; 34B15; 34B10

1 Introduction

Lane-Emden type of equations in one dependent variable occur in several branches of sciences and engineering [6, 5, 8, 7, 3]. Excellent treatment of existence uniqueness of such a generalised class of Lane-Emden type equations can be found in [20, 22, 21, 32, 19, 23, 31, 36] and the references cited there in. Existence of solutions for three point BVPs can be found in [26, 33, 35, 28, 34, 27] and for numerical solution one may refer [29]. In a recent work [40] existence is proved for a class of four point BVPs. Recently Haar wavelets are used efficiently to solve Lane-Emden equations for example please refer the papers [39, 30, 25]. Other wavelets are also utilised to solve Lane-Emden equations [37, 38].

Ma [13] considered the following set of differential and boundary equations:

$$\begin{aligned} u''(t) + \lambda a(t)f(u(t), v(t)) &= 0, \quad t \in (0, 1), & (1) \\ v''(t) + \lambda b(t)g(u(t), v(t)) &= 0, \quad t \in (0, 1), & (2) \\ u(0) = v(0) = u(1) = v(1) &= 0. & (3) \end{aligned}$$

Under suitable conditions on $a(t), b(t), f, g$ and using theory of cones existence of multiple positive solutions is proved in [13].

*Corresponding author email: akverma@iitp.ac.in

For 4-point BVP the work of Zhang et al. [44] may be referred, in which singularity was allowed at both end points of the BVP. They considered

$$-u''(t) = f(t, v(t)), \quad t \in (0, 1), \quad (4)$$

$$-v''(t) = g(t, u(t)), \quad t \in (0, 1), \quad (5)$$

$$u(0) = au(\xi), \quad u(1) = bu(c), \quad (6)$$

$$v(0) = av(\xi), \quad v(1) = bv(c), \quad (7)$$

where $0 < \xi < c < 1$, $0 \leq a < \frac{1}{1-\xi}$, $0 \leq b < \frac{1}{c}$, $a\xi(1-b) + (1-a)(1-bc) > 0$; $f(t, v)$ and $g(t, u)$ may be singular at $t = 0$ and/or $t = 1$. Based on functional expansion-compression fixed point theorem existence of positive solution is achieved.

Wang et al. [41] by using the fixed point theory of cone expansion and compression with norm type, studied the existence of positive solutions for a class of second-order nonlinear m -point boundary value problems of differential system.

Hao et al. [9] considered the following set of equations

$$-u''(x) + \frac{r}{x}u'(x) = f_1(x, u(x), v(x)), \quad x \in (0, 1), \quad (8)$$

$$-v''(x) + \frac{r}{x}v'(x) = f_2(x, u(x), v(x)), \quad x \in (0, 1), \quad (9)$$

subject to conditions

$$u'(0) = 0, \quad u(1) = \beta_1, \quad (10)$$

$$v'(0) = 0, \quad v(1) = \beta_2, \quad (11)$$

where r is a real constant and $f_1(u(x), v(x))$ and $f_2(u(x), v(x))$ are arbitrary functions of u and v . They used series representation to approximate the solution of coupled Lane-Emden boundary value problems. Xie et al. [43] also solved similar type of Lane-Emden problems by using differential transform method coupled with Adomian polynomials.

Yalcin [18] proposed an efficient numerical method for solving system of Lane-Emden type equations using Chebyshev operational matrix method. He et al. [10] used Taylor series method to solve system of Lane-Emden equations of second order.

Madduri et al. [14] presented a fast-converging iterative scheme to approximate the solution of a system of Lane-Emden equations arising in catalytic diffusion reactions. Mahalakshmi et al. [15] presented an efficient wavelet-based method for the numerical solutions of nonlinear coupled reaction-diffusion equations which occurs in biochemical engineering.

Very recently, Barnwal et al. [2] considered the following nonlinear four point BVP,

$$-(p(x)u'(x))' = q(x)f_1(x, u(x), v(x)), \quad x \in (0, 1), \quad (12)$$

$$-(p(x)v'(x))' = q(x)f_2(x, u(x), v(x)), \quad x \in (0, 1), \quad (13)$$

subject to conditions

$$u(0) = v(0) = 0, \quad u(1) = \mu_1 z(v_1), \quad u(1) = \mu_2 z(v_2). \quad (14)$$

Here $p(0) = 0$, $\int_0^\infty (1/p)dt < \infty$ and $q(x) > 0$ such that $q \in L^1[0, 1]$. Such BVPs are also referred as doubly singular BVPs. They used monotonic iterative technique without the presence of upper-lower solutions.

In the present work we use Haar wavelet collocation approach together with Newton Raphson method to solve system of nonlinear Lane-Emden equations

$$-(t^{k_1}y'(t))' = t^{-\omega_1}f_1(t, y(t), z(t)), \quad (15)$$

$$-(t^{k_2}z'(t))' = t^{-\omega_2}f_2(t, y(t), z(t)), \quad (16)$$

where $t > 0$, subject to initial values, boundary values and four point boundary values:

$$\text{Initial Condition:} \quad y(0) = \gamma_1, \quad y'(0) = 0, \quad z(0) = \gamma_2, \quad z'(0) = 0,$$

$$\text{Boundary Condition:} \quad y'(0) = 0, \quad y(1) = \delta_1, \quad z'(0) = 0, \quad z(1) = \delta_2,$$

$$\text{Four point Boundary Condition:} \quad y(0) = 0, \quad y(1) = n_1 z(v_1), \quad z(0) = 0, \quad z(1) = n_2 y(v_2),$$

where $n_1, n_2, v_1, v_2 \in (0, 1)$ and $k_1 \geq 0, k_2 \geq 0, \omega_1 < 1, \omega_2 < 1$ are real constants. We developed three methods referred as Haar wavelet collocation approach for IVPs (HWCAIVP), Haar wavelet collocation approach for BVPs

(HWCABVP) and Haar wavelet collocation approach for four point BVPs (HWCA4PTBVP). For each case we have considered two test examples. Convergence of the proposed methods are also proved. Results obtained in this paper are new and does not exist in literature. Calculations and plotting are performed on Mathematica 11.3 and Origin 8.

The paper is arranged in several sections. In section 2 we introduce about wavelets and Haar wavelets. Section 3 is devoted to nonlinear singular coupled system of IVPs. Section 4 is devoted to nonlinear singular coupled system of IVPs. Section 5 is devoted to nonlinear singular coupled system of four point BVPs. Lastly in section 6 we conclude the paper with some important remarks.

2 Preliminary

Wavelet word is used in the name of French geophysicist Jean Morlet (1931–2007). Morlet and Croatian-French physicist Alex Grossman developed the modern wavelet theory [24, p. 222]. Wavelets are multi-indexed and it has parameters which is used to shift or dilate/contract the functions giving us basis functions. The following properties of wavelets enable us to choose them over other methods [24, 4, 16, 1].

(H1) Orthogonality.

(H2) Compact Support.

(H3) Density.

(H4) Localization Property: Haar basis is localized, i.e., the vector is zero except for a few entries.

(H5) Multiresolution Analysis (MRA).

MRA

An orthogonal multiresolution analysis (MRA) is a collection of closed subspaces of $L^2(\mathbb{R})$ which are nested, having trivial intersection, they exhaust the space, the subspaces are connected to each other by scaling property and finally there is a special function, the scaling function φ , whose integer translates form an orthonormal basis for one of the subspaces. We give formal statement of MRA as defined in [24].

Definition 2.1. An MRA with scaling function φ is a collection of closed subspaces $V_j, j = \dots, -2, -1, 0, 1, 2, \dots$ of $L^2(\mathbb{R})$ such that

1. $V_j \subset V_{j+1}$.
2. $\overline{\bigcup V_j} = L^2(\mathbb{R})$.
3. $\bigcap V_j = 0$.
4. The function $f(x)$ belongs to V_j if and only if the function $f(2x) \in V_{j+1}$.
5. The function φ belongs to V_0 , the set $\{\varphi(x - k), k \in \mathbb{Z}\}$ is orthonormal basis for V_0 .

The sequence of wavelet subspaces W_j of $L^2(\mathbb{R})$, are such that $V_j \perp W_j$, for all j and $V_{j+1} = V_j \oplus W_j$. Closure of $\bigoplus_{j \in \mathbb{Z}} W_j$ is dense in $L^2(\mathbb{R})$ with respect to L^2 norm.

Mallat's theorem [16] guarantees that in presence of an orthogonal MRA, an orthonormal basis for $L^2(\mathbb{R})$ exists.

Theorem 2.1. (Mallat's Theorem). Given an orthogonal MRA with scaling function φ , there is a wavelet $\psi \in L^2(\mathbb{R})$ such that for each $j \in \mathbb{Z}$, the family $\{\psi_{j,k}\}_{k \in \mathbb{Z}}$ is an orthonormal basis for W_j . Hence the family $\{\psi_{j,k}\}_{k \in \mathbb{Z}}$ is an orthonormal basis for $L^2(\mathbb{R})$.

2.1 Haar Matrices

Excellent treatment is given on applications of Haar Wavelets in [12] by Lepik. Let us consider the interval $0 \leq x \leq 1$. Let us define $M = 2^J$, where J is maximum level of resolution. Let us divide $[0, 1]$ into $2M$ subintervals of equal length $\Delta x = \frac{1}{2M}$. The wavelet number i is calculated by $i = m + k + 1$, here $j = 0, 1, \dots, J$ and $k = 0, 1, \dots, m - 1$ (here $m = 2^j$). The Haar wavelet's mother wavelet function is defined as [12, pp.7-10],

$$h_i(x) = \begin{cases} 1, & \eta_1(i) \leq x < \eta_2(i), \\ -1, & \eta_2(i) \leq x < \eta_3(i), \\ 0, & \text{else,} \end{cases} \quad (17)$$

where,

$$\eta_1(i) = 2k\mu\Delta x, \quad \eta_2(i) = (2k+1)\mu\Delta x, \quad \eta_3(i) = 2(k+1)\mu\Delta x, \quad \mu = \frac{M}{m}, \quad (18)$$

if $i > 2$. For $i = 1$, it is defined as,

$$h_1(x) = \begin{cases} 1, & 0 \leq x \leq 1, \\ 0, & \text{else.} \end{cases} \quad (19)$$

For $i = 2$,

$$\eta_1(2) = 0, \quad \eta_2(2) = 0.5, \quad \eta_3(2) = 1. \quad (20)$$

The width of the i^{th} wavelet is,

$$\eta_3(i) - \eta_1(i) = 2\mu\Delta x = 2^{-j}.$$

The integral $P_{v,i}(x)$ is defined as,

$$P_{v,i}(x) = \int_0^x \int_0^x \cdots \int_0^x h_i(t) dt^v = \frac{1}{(v-1)!} \int_0^x (x-t)^{v-1} h_i(t) dt, \quad (21)$$

here v is the order of integration.

Using (17), we will calculate these integrals analytically and by doing it we obtain,

$$P_{v,i}(x) = \begin{cases} 0, & x < \eta_1(i), \\ \frac{1}{v!} [x - \eta_1(i)]^v, & \eta_1(i) \leq x \leq \eta_2(i), \\ \frac{1}{v!} [x - \eta_1(i)]^v - 2[x - \eta_2(i)]^v, & \eta_2(i) \leq x \leq \eta_3(i), \\ \frac{1}{v!} [x - \eta_1(i)]^v - 2[x - \eta_2(i)]^v + [x - \eta_3(i)]^v, & x > \eta_3(i), \end{cases} \quad (22)$$

for $i > 1$. For $i = 1$ we have $\eta_1 = 0, \eta_2 = \eta_3 = 1$ and,

$$P_{v,1}(x) = \frac{x^v}{v!}. \quad (23)$$

For computation by using Haar wavelet, we make use of the method of collocation. Here, the grid points are defined by,

$$\tilde{x}_c = c\Delta x, \quad c = 0, 1, \dots, 2M, \quad (24)$$

and collocation points are defined by,

$$x_c = 0.5(\tilde{x}_{c-1} + \tilde{x}_c), \quad c = 1, \dots, 2M, \quad (25)$$

and replace $x \rightarrow x_c$ in (17), (22), (23).

For computational point of view, we introduce the Haar matrices H, P_1, P_2, \dots, P_v . The order of these matrices are $2M \times 2M$. These matrices are defined by,

$$H(i, c) = h_i(x_c), \quad P_v(i, c) = p_{v,i}(x_c) \quad v = 1, 2, \dots.$$

For $J = 1$, the matrices H, P_1 and P_2 are defined by,

$$H = \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & 1 & -1 & -1 \\ 1 & -1 & 0 & 0 \\ 0 & 0 & 1 & -1 \end{bmatrix}, \quad P_1 = \frac{1}{8} \begin{bmatrix} 1 & 3 & 5 & 7 \\ 1 & 3 & 3 & 1 \\ 1 & 1 & 0 & 0 \\ 0 & 0 & 1 & 1 \end{bmatrix}, \quad P_2 = \frac{1}{128} \begin{bmatrix} 1 & 9 & 25 & 49 \\ 1 & 9 & 23 & 31 \\ 1 & 7 & 8 & 8 \\ 0 & 0 & 1 & 7 \end{bmatrix}.$$

3 System of Nonlinear Singular Two Point IVP

In this section we develop the solution method for system of nonlinear singular two point initial value problems. We will study some examples based on it.

3.1 Method 1: HWCAIVP

Consider the following singular nonlinear system of differential equations (15)-(16) subject to the initial conditions,

$$y(0) = \gamma_1, \quad y'(0) = 0, \quad (26)$$

$$z(0) = \gamma_2, \quad z'(0) = 0, \quad (27)$$

where $t > 0$ and where $k_1 \geq 0, k_2 \geq 0, \omega_1 < 1, \omega_2 < 1, \gamma_1, \gamma_2$ are real constants. .

Theorem 3.1. Consider the differential equations (15)-(16) with initial conditions (26)-(27). Let us assume $f_1(t, y, z), f_2(t, y, z)$ be continuous functions in t . Let $y(t)$ and $z(t)$ be the solutions of the differential equations (15)-(16) subject to the initial conditions (26)-(27). Then the numerical solutions $y(t)$ and $z(t)$ for differential equations (15)-(16) using Haar wavelet method are given as follows,

$$y(t) = \gamma_1 + \sum_{i=1}^{2M} a_i P_{2,i}(t),$$

$$z(t) = \gamma_2 + \sum_{i=1}^{2M} b_i P_{2,i}(t).$$

Proof. Assume ([11]),

$$y''(t) = \sum_{i=1}^{2M} a_i h_i(t), \quad (28)$$

$$z''(t) = \sum_{i=1}^{2M} b_i h_i(t), \quad (29)$$

where a_i, b_i are wavelet coefficients. Now integrate above equations from 0 to t twice we get,

$$y'(t) = \sum_{i=1}^{2M} a_i P_{1,i}(t) + y'(0), \quad (30)$$

$$y(t) = \sum_{i=1}^{2M} a_i P_{2,i}(t) + ty'(0) + y(0). \quad (31)$$

$$z'(t) = \sum_{i=1}^{2M} b_i P_{1,i}(t) + z'(0), \quad (32)$$

$$z(t) = \sum_{i=1}^{2M} b_i P_{2,i}(t) + tz'(0) + z(0). \quad (33)$$

Now apply initial conditions (26)-(27) in (30)-(33) and we get,

$$y'(t) = \sum_{i=1}^{2M} a_i P_{1,i}(t), \quad (34)$$

$$y(t) = \gamma_1 + \sum_{i=1}^{2M} a_i P_{2,i}(t), \quad (35)$$

$$z'(t) = \sum_{i=1}^{2M} b_i P_{1,i}(t), \quad (36)$$

$$z(t) = \gamma_2 + \sum_{i=1}^{2M} b_i P_{2,i}(t). \quad (37)$$

□

Now substitute these equations (28)-(37) in (15)-(16) after discretizing by collocation method, we get the system of nonlinear equations given as,

$$\Phi_c^{IVP}(a_1, a_2, \dots, a_{2M}) = 0, \quad c = 1, 2, \dots, 2M, \quad (38)$$

$$\Psi_c^{IVP}(b_1, b_2, \dots, b_{2M}) = 0, \quad c = 1, 2, \dots, 2M. \quad (39)$$

The above system of nonlinear equations is solved by applying Newton-Raphson method to get the wavelet coefficients a_i and b_i for numerical solution. Finally substituting the values of a_i, b_i in equations (35) and (37), we get the approximate solution obtained by HWCAIVP.

3.2 Convergence Analysis for HWCAIVP

Consider the following singular nonlinear system of differential equations, (15)-(16) subject to the initial conditions (26)-(27). Here we define $M = 2^J$, where J is maximum level of resolution. Let us write the approximate solutions as follows so that we have a clear distinction between exact and computed solution.

$$\begin{aligned} y^M &= \gamma_1 + \sum_0^{2M} a_i p_{2,i}(t), \\ |E_{M1}| &= \left| \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} a_{2^j+k+1} p_{2,2^j+k+1}(t) \right|, \\ z^M &= \gamma_2 + \sum_0^{2M} a_i (p_{2,i}(t)), \\ |E_{M2}| &= \left| \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} b_{2^j+k+1} p_{2,2^j+k+1}(t) \right|, \end{aligned}$$

where $|E_{M1}| = |y^M - y|$ and $|E_{M2}| = |z^M - z|$. Now, let us define

$$\|E_M\|_2 = \|E_{M1}\|_2 + \|E_{M2}\|_2. \quad (40)$$

Theorem 3.2. Consider the differential equation (15)-(16) subject to the initial conditions (26)-(27). Let us assume that $y'''(t), z'''(t) \in L^2(\mathbb{R})$ are continuous functions on $[0, 1]$. Consider $y'''_{r+1}(t), z'''_{r+1}(t)$ are bounded such that $|y'''_{r+1}(t)| \leq \xi_1$ and $|z'''_{r+1}(t)| \leq \xi_2 \quad \forall t \in [0, 1]$. Let $\epsilon > 0$ be arbitrary small positive number, and if $J > \log_2 \left(\sqrt{\frac{\xi_1}{3\epsilon}} \right) - 1$, then $\|E_M\|_2 < \epsilon$.

Proof. We will do calculation for E_{M1} , for E_{M2} it will follow accordingly. Expanding quadrate of L^2 norm of error function, we obtain

$$\|E_{M1}\|_2^2 = \int_0^1 \left(\sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} a_{2^j+k+1} p_{2,2^j+k+1}(t) \right)^2 dt.$$

Then we have

$$\|E_{M1}\|_2^2 = \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \sum_{s=0}^{2^r-1} a_{2^j+k+1} a_{2^r+s+1} \int_0^1 (p_{2,2^j+k+1}(t) p_{2,2^r+s+1}(t)) dt. \quad (41)$$

By the use of definition of Haar wavelet function we can evaluate coefficients a_i as

$$\begin{aligned} a_i &= 2^j \int_0^1 y''(t) h_i(t) dt, \\ a_i &= 2^j \left[\int_{\eta_1}^{\eta_2} y''(\zeta) d\zeta - \int_{\eta_2}^{\eta_3} y''(\zeta) d\zeta \right], \\ a_i &= 2^j [(\eta_2 - \eta_1) y''(\zeta_1) - (\eta_3 - \eta_2) y''(\zeta_2)], \end{aligned}$$

where $\zeta_1 \in (\eta_1, \eta_2)$ and $\zeta_2 \in (\eta_2, \eta_3)$. It follows from Eq. (18) that $(\eta_2 - \eta_1) = (\eta_3 - \eta_2) = 1/(2m) = 1/(2^{j+1})$, then the above expression of a_i reduces to

$$a_i = \frac{1}{2}[y''(\zeta_1) - y''(\zeta_2)] = \frac{1}{2}(\zeta_1 - \zeta_2) \frac{dy''}{dt}(\zeta), \quad \zeta \in (\zeta_1, \zeta_2).$$

Let us consider that $\left(\frac{dy''}{dt}\right)$ is bounded such that $\left|\frac{dy''}{dt}\right| \leq \xi_1$, so we have

$$a_i \leq \xi_1 \left(\frac{1}{2^{j+1}}\right). \quad (42)$$

Here we will solve for upper bound of a function $p_{2,i}$ in all subintervals. Since $p_{2,i}(t) = 0$ for $t \in [0, \eta_1(i)]$. The function $p_{2,i}(t)$ increases monotonically in the interval $t \in [\eta_1(i), \eta_2(i)]$. Thus $p_{2,i}(t)$ achieves its upper bound at $t = \eta_2(i)$ as follows

$$p_{2,i} = p_{2,2^j+k+1} \leq \frac{[\eta_2(i) - \eta_1(i)]^2}{2} = \frac{1}{2} \left(\frac{1}{2^{j+1}}\right)^2, \quad t \in [\eta_1(i), \eta_2(i)].$$

In the interval $t \in [\eta_2(i), \eta_3(i)]$ the function $p_{2,i}$ is monotonically increasing if

$$t \leq \eta_3, \quad (43)$$

which is obviously true.

This inequality (43) can be derived from formulas (18) and (22) and condition $\frac{dp_{2,i}(t)}{dt} > 0$. Hence maximum value of $p_{2,i}(t)$ can be obtained by substituting $t = \eta_3(i)$ in eq. (22) as

$$p_{2,i}(t) = p_{2,2^j+k+1} \leq \left(\frac{1}{2^{j+1}}\right)^2, \quad t \in [\eta_2(i), \eta_3(i)].$$

When $t \in [\eta_3, 1]$ the function $p_{2,i}(t)$ can be expanded as (by eq. (22) (see [17])

$$p_{2,i}(t) = \left(\frac{1}{2^{j+1}}\right)^2.$$

The function $p_{2,i}(t)$ increases monotonically in $[0, 1]$, since it increases monotonically in every sub interval of $[0, 1]$. So upper bound of $p_{2,i}(t)$ in $[0, 1]$ is given by

$$p_{2,i}(t) \leq \left(\frac{1}{2^{j+1}}\right)^2 \quad \forall t \in [0, 1]. \quad (44)$$

Now inserting eq. (42) in eq. (41) we get

$$\|E_{M1}\|_2^2 \leq \xi_1^2 \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \sum_{s=0}^{2^r-1} \frac{1}{2^{r+j+2}} \int_0^1 (p_{2,2^j+k+1}(t)) (p_{2,2^r+s+1}(t)) dt. \quad (45)$$

Here we have

$$p_{2,2^j+k+1}(t) \leq \left(\frac{1}{2^{j+1}}\right)^2, \quad p_{2,2^r+s+1}(t) \leq \left(\frac{1}{2^{r+1}}\right)^2 \quad \forall t \in [0, 1]. \quad (46)$$

Inserting eq. (46) in eq. (45) we get

$$\begin{aligned} \|E_{M1}\|_2^2 &\leq \xi_1^2 \sum_{j=J+1}^{\infty} \sum_{r=J+1}^{\infty} \left(\frac{1}{2^{j+1}}\right)^3 \left(\frac{1}{2^{r+1}}\right)^3 2^j 2^r (1 - \eta_1), \\ \|E_{M1}\|_2^2 &\leq \frac{1}{36} \xi_1^2 \left(\frac{1}{2^{J+1}}\right)^4. \end{aligned}$$

Hence

$$\|E_{M1}\|_2 \leq \frac{1}{6} \xi_1 \left(\frac{1}{2^{J+1}}\right)^2.$$

Let $\epsilon > 0$ be arbitrary small positive number and if we choose

$$J > \log_2 \sqrt{\frac{\xi_1}{3\epsilon}} - 1,$$

then

$$\|E_{M1}\|_2 \leq \frac{\epsilon}{2}.$$

Similarly following the same process for z^M , we can prove that

$$\|E_{M2}\|_2 < \frac{\epsilon}{2}.$$

Hence,

$$\|E_M\|_2 < \epsilon$$

whenever resolution $J > \log_2 \sqrt{\frac{\xi_1}{3\epsilon}} - 1$. □

3.3 Numerical Illustration for HWCAIVP

In this section we will discuss two numerical problems based on system of nonlinear singular two point initial value problem considered by Wazwaz et al. [42].

3.3.1 Example 1 ([42])

Consider (15)-(16) subject to initial conditions (26)-(27) with $\gamma_1 = 1$, $\gamma_2 = 1$, $k_1 = 3$, $k_2 = 2$, $\omega_1 = -3$, $\omega_2 = -2$, $f_1(t, y(t), z(t)) = -4(y + z)$ and $f_2(t, y(t), z(t)) = 3(y + z)$. Now applying solution method (subsection 3.1) to solve this problem, we get system of non-linear equations. Thus we arrive at (38)-(39). To solve the non-linear equations we use Newton Raphson method to calculate wavelet coefficients (a_i) and (b_i). After calculating wavelet coefficients (a_i) and (b_i) we get our required solution from equations (35) and (37). The exact solution $\tilde{y}(t)$ and $\tilde{z}(t)$ of this problem are $1 + t^2$ and $1 - t^2$, respectively.

Here we are computing absolute error. Absolute error is defined as the difference of exact value and approximated value. Maximum error is defined as,

$$L^\infty = \max_i |\tilde{y}(t_i) - y(t_i)|,$$


where $\tilde{y}(t)$ is the exact solution and $y(t_i)$ is HWCAIVP solution.

For initial guess $[1, 1, \dots, 1]$ computed solutions for $y^M(t)$ and $z^M(t)$ is given in Table 1 and Table 2, respectively for $J = 3$ and $J = 4$. Graph for $y^M(t)$ and $z^M(t)$ with exact solution is given in figure 1a and figure 1b respectively for $J = 4$. Graph of absolute errors in computation of $y^M(t)$ and $z^M(t)$ is given in figure 2a and figure 2b respectively for $J = 1$, $J = 2$, $J = 3$ and $J = 4$.


For slight modification in initial guesses, say, $[1.01, 1.01, \dots, 1.01]$ and $[1.1, 1.1, \dots, 1.1]$ final solution is not affected at all, which shows the stability of the method.

t	$J = 3$	$J = 4$	Exact Solution
0	1	1	1
0.1	1.01	1.01	1.01
0.2	1.04	1.04	1.04
0.3	1.09	1.09	1.09
0.4	1.16	1.16	1.16
0.5	1.25	1.25	1.25
0.6	1.36	1.36	1.36
0.7	1.49	1.49	1.49
0.8	1.64	1.64	1.64
0.9	1.81	1.81	1.81
1	2	2	2
L^∞	0	0	

Table 1: Solutions $y^M(t)$ for $J = 3$ and $J = 4$ for example 3.3.1.




(a) Graph of $y^M(t)$ for $J = 4$ for example 3.3.1.




(b) Graph of $z^M(t)$ for $J = 4$ for example 3.3.1.

Figure 1



(a) Graph of absolute errors in $y^M(t)$ for example 3.3.1.



(b) Graph of absolute errors in $z^M(t)$ for example 3.3.1.

Figure 2

t	$J = 3$	$J = 4$	Exact Solution
0	1	1	1
0.1	0.99	0.99	0.99
0.2	0.96	0.96	0.96
0.3	0.91	0.91	0.91
0.4	0.84	0.84	0.84
0.5	0.75	0.75	0.75
0.6	0.64	0.64	0.64
0.7	0.51	0.51	0.51
0.8	0.36	0.36	0.36
0.9	0.19	0.19	0.19
1	0	0	0
L^∞	0	0	

Table 2: Solutions $z^M(t)$ for $J = 3$ and $J = 4$ for example 3.3.1.

3.3.2 Example 2 ([42])

Consider the system of differential equations (15)-(16) subject to initial conditions (26)-(27) with $\gamma_1 = 1$, $\gamma_2 = 1$, $k_1 = 1$, $k_2 = 3$, $\omega_1 = -1$, $\omega_2 = -3$, $f_1(t, y(t), z(t)) = -z^3(y^2 + 1)$ and $f_2(t, y(t), z(t)) = z^5(y^2 + 3)$. The exact solution $\tilde{y}(t)$ and $\tilde{z}(t)$ of this problem are $\sqrt{1+t^2}$ and $\frac{1}{\sqrt{1+t^2}}$ respectively.

Since this problem is same as subsection 3.3.1. Computed solutions for $y^M(t)$ and $z^M(t)$ is given in Table 3 and Table 4, respectively for $J = 3$ and $J = 4$ taking initial guess $[0, 0, \dots, 0]$. Graph for $y^M(t)$ and $z^M(t)$ with exact solution is given in figure 3a and figure 3b respectively for $J = 4$. Graph of absolute errors in computation of $y^M(t)$ and $z^M(t)$ is given in figure 4a and figure 4b respectively for $J = 1$, $J = 2$, $J = 3$ and $J = 4$.

For slight modification in initial guesses, say, $[0.01, 0.01, \dots, 0.01]$ and $[0.1, 0.1, \dots, 0.1]$ final solution is not affected at all, which shows the stability of the method.

t	$J = 3$	$J = 4$	Exact Solution
0	1	1	1
0.1	1.00499	1.00499	1.00499
0.2	1.0198	1.0198	1.0198
0.3	1.04403	1.04403	1.04403
0.4	1.07703	1.07703	1.07703
0.5	1.11803	1.11803	1.11803
0.6	1.16619	1.16619	1.16619
0.7	1.22065	1.22065	1.22066
0.8	1.28061	1.28062	1.28062
0.9	1.34535	1.34536	1.34536
1	1.41419	1.41421	1.41421
L^∞	2.76016E-05	6.87997E-06	

Table 3: Solution $y^M(t)$ for $J = 3$ and $J = 4$ for example 3.3.2.

t	$J = 3$	$J = 4$	Exact Solution
0	1	1	1
0.1	0.995035	0.995036	0.995037
0.2	0.980564	0.980577	0.980581
0.3	0.9578	0.957819	0.957826
0.4	0.928424	0.928465	0.928477
0.5	0.894355	0.894409	0.894427
0.6	0.857402	0.85747	0.857493
0.7	0.819121	0.819205	0.819232
0.8	0.780748	0.780839	0.780869
0.9	0.743164	0.743262	0.743294
1	0.706975	0.707074	0.707107
L^∞	0.000131757	3.28838E-05	

Table 4: Solutions $z^M(t)$ for $J = 3$ and $J = 4$ for example 3.3.2.

4 System of Two Point Nonlinear Singular BVP

In this section we will develop the solution technique for solving system of nonlinear singular two point boundary value problem. We will also discuss some numerical examples based on it.


4.1 Method 2 : HWCABVP

Consider (15)-(16) with the following boundary conditions,


$$y'(0) = 0, y(1) = \delta_1, \quad (47)$$

$$z'(0) = 0, z(1) = \delta_2, \quad (48)$$

where $t \in (0, 1)$ and $\delta_1, \delta_2, k_1 \geq 1, k_2 \geq 1, \omega_1 < 1, \omega_2 < 1$ are real constants.




(a) Graph of $y^M(t)$ for $J = 4$ for example 3.3.2.




(b) Graph of $z^M(t)$ for $J = 4$ for example 3.3.2.

Figure 3



(a) Graph of absolute errors in $y^M(t)$ for example 3.3.2.



(b) Graph of absolute errors in $z^M(t)$ for example 3.3.2.

Figure 4

Theorem 4.1. Consider the system of differential equations (15)-(16) with boundary conditions (47)-(48). Let us assume $f_1(t, y, z)$, $f_2(t, y, z)$ be continuous functions in t . Let $y(t)$ and $z(t)$ be the solutions of the differential equations (15)-(16) subject to the initial conditions (47)-(48). Then the numerical solutions $y(t)$ and $z(t)$ for differential equations (15)-(16) using Haar wavelet method are defined as follows,

$$y(t) = \delta_1 + \sum_{i=1}^{2M} a_i (P_{2,i}(t) - P_{2,i}(1)),$$

$$z(t) = \delta_2 + \sum_{i=1}^{2M} b_i (P_{2,i}(t) - P_{2,i}(1)).$$

Proof. Let (28), (29) be the solutions of (15)-(16) where a_i , b_i are wavelet coefficients. Now integrate (28), (29) two times from 0 to t we will get (30)-(33) then apply boundary conditions (47) and (48) and we get,

$$y'(t) = \sum_{i=1}^{2M} a_i P_{1,i}(t), \quad (49)$$

$$y(t) = \delta_1 + \sum_{i=1}^{2M} a_i (P_{2,i}(t) - P_{2,i}(1)), \quad (50)$$

$$z'(t) = \sum_{i=1}^{2M} b_i P_{1,i}(t), \quad (51)$$

$$z(t) = \delta_2 + \sum_{i=1}^{2M} b_i (P_{2,i}(t) - P_{2,i}(1)). \quad (52)$$

□

Now substituting equations (28)-(29) and (49)-(52) in (15)-(16) after discretizing by collocation method, we will get the system of nonlinear equations given as,

$$\Phi_c^{BVP}(a_1, a_2, \dots, a_{2M}) = 0, \quad c = 1, 2, \dots, 2M, \quad (53)$$

$$\Psi_c^{BVP}(b_1, b_2, \dots, b_{2M}) = 0, \quad c = 1, 2, \dots, 2M, \quad (54)$$

which we solve by Newton-Raphson method to get the wavelet coefficients a_i and b_i . Finally substituting the values of a_i, b_i in equations (50) and (52), we get the approximate solution obtained by HWCABVP.

4.2 Convergence Analysis of HWCABVP

Let us consider y and z are the exact solutions of differential equation (15)-(16) with boundary conditions (47)-(48) and y^M, z^M are the solutions obtained after truncation of the wavelet series. Then

$$y^M = \delta_1 + \sum_0^{2M} a_i (p_{2,i}(t) - p_{2,i}(1)),$$

$$|\tilde{E}_{M1}| = \left| \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} a_{2^j+k+1} (p_{2,2^j+k+1}(t) - p_{2,2^r+s+1}(1)) \right|,$$

$$z^M = \delta_2 + \sum_0^{2M} a_i (p_{2,i}(t) - p_{2,i}(1)),$$

$$|\tilde{E}_{M2}| = \left| \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} b_{2^j+k+1} (p_{2,2^j+k+1}(t) - p_{2,2^r+s+1}(1)) \right|,$$

where $|\tilde{E}_{M1}| = |y^M - y|$ and $|\tilde{E}_{M2}| = |z^M - z|$. Similar to case of HWCAIVP, Now we define

$$\|\tilde{E}_M\|_2 = \|\tilde{E}_{M1}\|_2 + \|\tilde{E}_{M2}\|_2. \quad (55)$$

Theorem 4.2. Consider the system of differential equations (15)-(16) subject to boundary conditions (47)-(48). Let us assume that $y'''(t), z'''(t) \in L^2(\mathbb{R})$ are continuous functions on $[0, 1]$. Consider $y'''_{r+1}(t), z'''_{r+1}(t)$ are bounded such that $|y'''_{r+1}(t)| \leq \xi_1$ and $|z'''_{r+1}(t)| \leq \xi_2 \quad \forall t \in [0, 1]$. Let $\epsilon > 0$ be arbitrary small positive number, and if $J > \log_2 \left(\sqrt{\frac{2\xi_1}{3\epsilon}} \right) - 1$, then $\|\tilde{E}_M\|_2 < \epsilon$.

Proof. We will do calculation for \tilde{E}_{M1} , for \tilde{E}_{M2} it will follow accordingly. Expanding quadrate of L^2 norm of error function, we obtain

$$\|\tilde{E}_{M1}\|_2^2 = \int_0^1 \left(\sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} a_{2^j+k+1} (p_{2,2^j+k+1}(t) - p_{2,2^j+k+1}(1)) \right)^2 dt.$$

Then we have

$$\|\tilde{E}_{M1}\|_2^2 = \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \sum_{s=0}^{2^r-1} a_{2^j+k+1} a_{2^r+s+1} \int_0^1 (p_{2,2^j+k+1}(t) - p_{2,2^j+k+1}(1))(p_{2,2^r+s+1}(t) - p_{2,2^r+s+1}(1)) dt. \quad (56)$$

By the use of definition of Haar wavelet function we can evaluate coefficients a_i as

$$\begin{aligned} a_i &= 2^j \int_0^1 y''(t) h_i(t) dt, \\ a_i &= 2^j \left[\int_{\eta_1}^{\eta_2} y''(\zeta) d\zeta - \int_{\eta_2}^{\eta_3} y''(\zeta) d\zeta \right], \\ a_i &= 2^j [(\eta_2 - \eta_1) y''(\zeta_1) - (\eta_3 - \eta_2) y''(\zeta_2)], \end{aligned}$$

where $\zeta_1 \in (\eta_1, \eta_2)$ and $\zeta_2 \in (\eta_2, \eta_3)$. It follows from Eq. (18) that $(\eta_2 - \eta_1) = (\eta_3 - \eta_2) = 1/(2m) = 1/(2^{j+1})$, then the above expression of a_i reduces to

$$a_i = \frac{1}{2} [y''(\zeta_1) - y''(\zeta_2)] = \frac{1}{2} (\zeta_1 - \zeta_2) \frac{dy''}{dt}(\zeta), \quad \zeta \in (\zeta_1, \zeta_2).$$

Let us consider that $\left(\frac{dy''}{dt} \right)$ is bounded such that $\left| \frac{dy''}{dt} \right| \leq \xi_1$, so we have

$$a_i \leq \xi_1 \left(\frac{1}{2^{j+1}} \right). \quad (57)$$

Here we will solve for upper bound of a function $p_{2,i}$ in all subintervals. Since $p_{2,i}(t) = 0$ for $t \in [0, \eta_1(i)]$. The function $p_{2,i}(t)$ increases monotonically in the interval $t \in [\eta_1(i), \eta_2(i)]$. Thus $p_{2,i}(t)$ achieves its upper bound at $t = \eta_2(i)$ as follows

$$p_{2,i} = p_{2,2^j+k+1} \leq \frac{[\eta_2(i) - \eta_1(i)]^2}{2} = \frac{1}{2} \left(\frac{1}{2^{j+1}} \right)^2, \quad t \in [\eta_1(i), \eta_2(i)].$$

In the interval $t \in [\eta_2(i), \eta_3(i)]$ the function $p_{2,i}$ is monotonically increasing if

$$t \leq \eta_3, \quad (58)$$

which is obviously true.

This inequality (58) can be derived from formulas (18) and (22) and condition $\frac{dp_{2,i}(t)}{dt} > 0$. Hence maximum value of $p_{2,i}(t)$ can be obtained by substituting $t = \eta_3(i)$ in eq. (22) as

$$p_{2,i}(t) = p_{2,2^j+k+1} \leq \left(\frac{1}{2^{j+1}} \right)^2, \quad t \in [\eta_2(i), \eta_3(i)].$$

When $t \in [\eta_3, 1]$ the function $p_{2,i}(t)$ can be expanded as (by eq. (22)) (see [17])

$$p_{2,i}(t) = \left(\frac{1}{2^{j+1}} \right)^2.$$

The function $p_{2,i}(t)$ increases monotonically in $[0, 1]$, since it increases monotonically in every sub interval of $[0, 1]$. So upper bound of $p_{2,i}(t)$ in $[0, 1]$ is given by

$$p_{2,i}(t) \leq \left(\frac{1}{2^{j+1}}\right)^2 \quad \forall t \in [0, 1]. \quad (59)$$

Now inserting eq. (57) in equation (56) we get

$$\|\tilde{E}_{M1}\|_2^2 \leq \xi_1^2 \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \sum_{s=0}^{2^r-1} \frac{1}{2^{r+j+2}} \int_0^1 (p_{2,2^j+k+1}(t) - p_{2,2^j+k+1}(1))(p_{2,2^r+s+1}(t) - p_{2,2^r+s+1}(1)) dt. \quad (60)$$

Now since

$$(p_{2,2^j+k+1}(t) - p_{2,2^j+k+1}(1)) \leq |p_{2,2^j+k+1}(t)| + |p_{2,2^j+k+1}(1)|. \quad (61)$$

Here we have

$$p_{2,2^j+k+1}(t) \leq \left(\frac{1}{2^{j+1}}\right)^2, \quad p_{2,2^r+s+1}(t) \leq \left(\frac{1}{2^{r+1}}\right)^2 \quad \forall t \in [0, 1]. \quad (62)$$

Using eq. (62) in equation (61) we get

$$(p_{2,2^j+k+1}(t) - p_{2,2^j+k+1}(1)) \leq 2 \left(\frac{1}{2^{j+1}}\right)^2. \quad (63)$$

Similarly,

$$(p_{2,2^r+s+1}(t) - p_{2,2^r+s+1}(1)) \leq 2 \left(\frac{1}{2^{r+1}}\right)^2. \quad (64)$$

Inserting eq. (63), (64) in equation (60) we get

$$\begin{aligned} \|\tilde{E}_{M1}\|_2^2 &\leq 4\xi_1^2 \sum_{j=J+1}^{\infty} \sum_{r=J+1}^{\infty} \left(\frac{1}{2^{j+1}}\right)^3 \left(\frac{1}{2^{r+1}}\right)^3 2^j 2^r (1 - \eta_1), \\ \|\tilde{E}_{M1}\|_2^2 &\leq \frac{1}{9} \xi_1^2 \left(\frac{1}{2^{J+1}}\right)^4. \end{aligned}$$

Hence,

$$\|\tilde{E}_{M1}\|_2 \leq \frac{1}{3} \xi_1 \left(\frac{1}{2^{J+1}}\right)^2.$$

Hence the proof is completed as per arguments given in proof of theorem 3.2. \square

4.3 Numerical Illustration for HWCABVP

In this section we will discuss two numerical problems based on nonlinear singular two point boundary value problem (Wazwaz et al. [42]).

4.3.1 Example 3 ([42])

Consider system of differential equation (15)-(16) with boundary conditions (47)-(48) with $\delta_1 = 1 - 2 \log_e 2$, $\delta_2 = 1 + 2 \log_e 2$, $k_1 = 5$, $k_2 = 3$, $\omega_1 = -5$, $\omega_2 = -3$, $f_1(t, y(t), z(t)) = 8 \left(\exp(y-1) + 2 \exp\left(-\frac{z-1}{2}\right) \right)$ and $f_2(t, y(t), z(t)) = -8 \left(\exp(-(z-1)) + \exp\left(\frac{y-1}{2}\right) \right)$. Applying solution method (subsection 4.1) to solve this problem, we get system of non-linear equations. Thus we arrive at (53)-(54). To solve the non-linear equations we use Newton Raphson method to calculate wavelet coefficients (a_i) and (b_i). After calculating wavelet coefficients (a_i) and (b_i) we get our required solution. Here we are computing absolute error described in subsection 3.3.1. The exact solution $\tilde{y}(t)$ and $\tilde{z}(t)$ of this problem are $1 - 2 \log_e(1 + t^2)$ and $1 + 2 \log_e(1 + t^2)$, respectively.

For initial guess $[0.8, 0.8, \dots, 0.8]$ computed solutions for $y^M(t)$ and $z^M(t)$ is given in Table 5 and Table 6 respectively for $J = 3$ and $J = 4$. Graph for $y^M(t)$ and $z^M(t)$ with exact solution is given in figure 5a and figure 5b respectively for $J = 4$. Graph of absolute errors in computation of $y^M(t)$ and $z^M(t)$ is given in figure 6a and figure 6b respectively for $J = 1, J = 2, J = 3$ and $J = 4$.

Small perturbations in initial guesses, say, $[0.82, 0.82, \dots, 0.82]$ and $[0.78, 0.78, \dots, 0.78]$ does affected the final solution, which shows the stability of the method.

t	$J = 3$	$J = 4$	Exact Solution
0	1.00147	1.00037	1
0.1	0.981545	0.980458	0.980099
0.2	0.922895	0.921893	0.921559
0.3	0.828852	0.827944	0.827645
0.4	0.704169	0.703414	0.70316
0.5	0.554528	0.553916	0.553713
0.6	0.38565	0.385183	0.385031
0.7	0.202866	0.202554	0.202448
0.8	0.0108728	0.0106725	0.0106075
0.9	-0.186541	-0.186624	-0.186654
1	-0.386294	-0.386294	-0.386294
L^∞	0.00147404	0.000367459	

Table 5: Solutions $y^M(t)$ for $J = 3$ and $J = 4$ for example 4.3.1.

t	$J = 3$	$J = 4$	Exact Solution
0	0.998354	0.99959	1
0.1	1.01828	1.0195	1.0199
0.2	1.07693	1.07806	1.07844
0.3	1.17098	1.17201	1.17236
0.4	1.29567	1.29655	1.29684
0.5	1.44532	1.44605	1.44629
0.6	1.61422	1.61478	1.61497
0.7	1.79703	1.79742	1.79755
0.8	1.98905	1.98931	1.98939
0.9	2.1865	2.18661	2.18665
1	2.38629	2.38629	2.38629
L^∞	0.00164587	0.000410165	


Table 6: Solutions $z^M(t)$ for $J = 3$ and $J = 4$ for example 4.3.1.

4.3.2 Example 4 ([42])


Consider the system of differential equations (15)-(16) with boundary conditions (47)-(48) with $\delta_1 = \frac{1}{e}$, $\delta_2 = e$, $k_1 = 8$, $k_2 = 4$, $\omega_1 = -8$, $\omega_2 = -4$, $f_1(t, y(t), z(t)) = 18y - 4y \log_e z$ and $f_2(t, y(t), z(t)) = 4z \log_e y - 10z$. This problem is same as subsubsection 4.3.1. Here we are computing absolute error described in subsubsection 3.3.1. The exact solution $\tilde{y}(t)$ and $\tilde{z}(t)$ of this problem are $\exp(-t^2)$ and $\exp(t^2)$, respectively.

For initial guess $[0.3, 0.3, \dots, 0.3]$ computed solutions for $y^M(t)$ and $z^M(t)$ is given in Table 7 and Table 8 respectively for $J = 3$ and $J = 4$. Graph for $y^M(t)$ and $z^M(t)$ with exact solution is given in figure 7a and figure 7b respectively for $J = 4$. Graph of absolute errors in computation of $y^M(t)$ and $z^M(t)$ is given in figure 8a and figure 8b respectively for $J = 1, J = 2, J = 3$ and $J = 4$.

Varying initial guesses to $[0.35, 0.35, \dots, 0.35]$ and $[0.28, 0.28, \dots, 0.28]$, does not change the computed, significantly. This shows that the method is stable.




(a) Graph of $y^M(t)$ for $J = 4$ for example 4.3.1.




(b) Graph of $z^M(t)$ for $J = 4$ for example 4.3.1

Figure 5




(a) Graph of absolute errors in $y^M(t)$ for example 4.3.1.




(b) Graph of absolute errors in $z^M(t)$ for example 4.3.1.

Figure 6



(a) Graph of $y^M(t)$ for $J = 4$ for example 4.3.2.



(b) Graph of $z^M(t)$ for $J = 4$ for example 4.3.2.

Figure 7

t	$J = 3$	$J = 4$	Exact Solution
0	1.00075	1.00019	1
0.1	0.990793	0.990235	0.99005
0.2	0.961486	0.960964	0.960789
0.3	0.914573	0.91409	0.913931
0.4	0.852692	0.852283	0.852144
0.5	0.779256	0.778915	0.778801
0.6	0.698032	0.697763	0.697676
0.7	0.612869	0.612688	0.612626
0.8	0.527451	0.527331	0.527292
0.9	0.444924	0.444876	0.444858
1	0.367879	0.367879	0.367879
L^∞	0.000754755	0.00018869	


Table 7: Solutions $y^M(t)$ for $J = 3$ and $J = 4$ for example 4.3.2.

t	$J = 3$	$J = 4$	Exact Solution
0	1.00051	1.00013	1
0.1	1.01055	1.01018	1.01005
0.2	1.0413	1.04093	1.04081
0.3	1.09465	1.09429	1.09417
0.4	1.17395	1.17362	1.17351
0.5	1.28442	1.28412	1.28403
0.6	1.43369	1.43341	1.43333
0.7	1.63256	1.63238	1.63232
0.8	1.89673	1.89653	1.89648
0.9	2.24798	2.24794	2.24791
1	2.71828	2.71828	2.71828
L^∞	0.000505366	0.00012642	


Table 8: Solutions for $z^M(t)$ for $J = 3$ and $J = 4$ for example 4.3.2.

5 System of Nonlinear Singular Four Point BVP

In this section we will develop the method for solving system of nonlinear singular four point boundary value problem. We also study some numerical examples based on it. These test examples are also considered by Barnwal et al. [2]. We also compare our results with the result of Barnwal et al. [2].



(a) Graph of absolute errors in $y^M(t)$ for example 4.3.2.



(b) Graph of absolute errors in $z^M(t)$ for example 4.3.2.

Figure 8

5.1 Method 3 : HWCA4PTBVP

Consider the system of differential equations (15)-(16) subject to four-point boundary conditions,

$$y(0) = 0, \quad y(1) = n_1 z(v_1), \quad (65)$$

$$z(0) = 0, \quad z(1) = n_2 y(v_2), \quad (66)$$

where $t \in (0, 1)$, $n_1, n_2, v_1, v_2 \in (0, 1)$ and $0 \leq k_1 < 1$, $0 \leq k_2$, $\omega_1 < 1$, $\omega_2 < 1$ are real constants.

Theorem 5.1. Consider the system of differential equations (15)-(16) with boundary conditions (65)-(66). Let us assume $f_1(t, y, z)$, $f_2(t, y, z)$ be continuous functions in t, y, z . Let $y(t)$ and $z(t)$ be the solutions of the differential equations (15)-(16) subject to the four point boundary conditions (65)-(66). Then the numerical solutions $y(t)$ and $z(t)$ for differential equations (15)-(16) using HWCA4PTBVP are defined as follows,

$$y(t) = \frac{n_1 t}{1 - n_1 n_2 v_1 v_2} \left[n_2 v_1 \sum_{i=1}^{2M} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + \sum_{i=1}^{2M} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{2M} a_i [P_{2,i}(t) - t P_{2,i}(1)],$$

$$z(t) = \frac{n_2 t}{1 - n_1 n_2 v_1 v_2} \left[\sum_{i=1}^{2M} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + v_2 n_1 \sum_{i=1}^{2M} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{2M} b_i [P_{2,i}(t) - t P_{2,i}(1)].$$

Proof. Let (28), (29) be the solutions of (15)-(16) where a_i, b_i are wavelet coefficients. Now integrate (28)-(29) two times from 0 to t we will get (30)-(33) then apply boundary conditions (65)-(66) and we get,

$$y'(t) = \frac{n_1}{1 - n_1 n_2 v_1 v_2} \left[n_2 v_1 \sum_{i=1}^{2M} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + \sum_{i=1}^{2M} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{2M} a_i [P_{1,i}(t) - P_{2,i}(1)], \quad (67)$$

$$y(t) = \frac{n_1 t}{1 - n_1 n_2 v_1 v_2} \left[n_2 v_1 \sum_{i=1}^{2M} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + \sum_{i=1}^{2M} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{2M} a_i [P_{2,i}(t) - t P_{2,i}(1)], \quad (68)$$

$$z'(t) = \frac{n_2}{1 - n_1 n_2 v_1 v_2} \left[\sum_{i=1}^{2M} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + v_2 n_1 \sum_{i=1}^{2M} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{2M} b_i [P_{1,i}(t) - P_{2,i}(1)], \quad (69)$$

$$z(t) = \frac{n_2 t}{1 - n_1 n_2 v_1 v_2} \left[\sum_{i=1}^{2M} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + v_2 n_1 \sum_{i=1}^{2M} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{2M} b_i [P_{2,i}(t) - t P_{2,i}(1)]. \quad (70)$$

□

Now substituting these equations (28)-(29) and (67)-(70) in (15)-(16) after discretizing by collocation method, we will get the system of nonlinear equations given as,

$$\Phi_c^{4PtBVP}(a_1, a_2, \dots, a_{2M}) = 0, \quad c = 1, 2, \dots, 2M, \quad (71)$$

$$\Psi_c^{4PtBVP}(b_1, b_2, \dots, b_{2M}) = 0, \quad c = 1, 2, \dots, 2M, \quad (72)$$

which we solve by Newton Raphson method to get the wavelet coefficients a_i and b_i and substitute them in (68) and (70) to get approximate HWCA4PTBVP solutions.

5.2 Convergence Analysis of HWCA4PBVP

Define

$$y(t) = \frac{n_1 t}{1 - n_1 n_2 v_1 v_2} \left[n_2 v_1 \sum_{i=1}^{\infty} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + \sum_{i=1}^{\infty} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{\infty} a_i [P_{2,i}(t) - t P_{2,i}(1)], \quad (73)$$

$$z(t) = \frac{n_2 t}{1 - n_1 n_2 v_1 v_2} \left[\sum_{i=1}^{\infty} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + v_2 n_1 \sum_{i=1}^{\infty} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{\infty} b_i [P_{2,i}(t) - t P_{2,i}(1)]. \quad (74)$$

$$y^M(t) = \frac{n_1 t}{1 - n_1 n_2 v_1 v_2} \left[n_2 v_1 \sum_{i=1}^{2M} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + \sum_{i=1}^{2M} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{2M} a_i [P_{2,i}(t) - t P_{2,i}(1)], \quad (75)$$

$$z^M(t) = \frac{n_2 t}{1 - n_1 n_2 v_1 v_2} \left[\sum_{i=1}^{2M} a_i [P_{2,i}(v_2) - v_2 P_{2,i}(1)] + v_2 n_1 \sum_{i=1}^{2M} b_i [P_{2,i}(v_1) - v_1 P_{2,i}(1)] \right] + \sum_{i=1}^{2M} b_i [P_{2,i}(t) - t P_{2,i}(1)]. \quad (76)$$

Then,

$$\begin{aligned} |\bar{E}_{M1}| = & \left| \frac{n_1 t}{1 - n_1 n_2 v_1 v_2} \left[n_2 v_1 \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} a_{2^j+k+1} [P_{2,2^j+k+1}(v_2) - v_2 P_{2,2^j+k+1}(1)] \right. \right. \\ & \left. \left. + \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} b_{2^j+k+1} [P_{2,2^j+k+1}(v_1) - v_1 P_{2,2^j+k+1}(1)] \right] \right. \\ & \left. + \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} a_{2^j+k+1} [P_{2,2^j+k+1}(t) - t P_{2,2^j+k+1}(1)] \right|, \end{aligned}$$

$$\begin{aligned} |\bar{E}_{M2}| = & \left| \frac{n_2 t}{1 - n_1 n_2 v_1 v_2} \left[\sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} a_{2^j+k+1} [P_{2,2^j+k+1}(v_2) - v_2 P_{2,2^j+k+1}(1)] \right. \right. \\ & \left. \left. + v_2 n_1 \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} b_{2^j+k+1} [P_{2,2^j+k+1}(v_1) - v_1 P_{2,2^j+k+1}(1)] \right] \right. \\ & \left. + \sum_{i=1}^{2M} b_{2^j+k+1} [P_{2,2^j+k+1}(t) - t P_{2,2^j+k+1}(1)] \right|. \end{aligned}$$

where $|\bar{E}_{M1}| = |y^M - y|$ and $|\bar{E}_{M2}| = |z^M - z|$. Here again we define total error as

$$\|\bar{E}_M\|_2 = \|\bar{E}_{M1}\|_2 + \|\bar{E}_{M2}\|_2. \quad (77)$$

Theorem 5.2. Consider the system of differential equation (15)-(16) with four point boundary conditions (65)-(66). Let us assume that $y'''(t), z'''(t) \in L^2(\mathbb{R})$ are continuous functions on $[0, 1]$. Consider $y''_{r+1}(t), z''_{r+1}(t)$ are bounded such that $|y''_{r+1}(t)| \leq \xi_1$ and $|z''_{r+1}(t)| \leq \xi_2 \quad \forall t \in [0, 1]$. Let $\epsilon > 0$ be arbitrary small positive number and if $J > \log_2 \sqrt{\frac{2\tilde{C}}{\epsilon}} - 1$, then $\|\bar{E}_M\|_2 < \epsilon$, where \tilde{C} is real number which depends on $n_1, n_2, v_2, v_2, \xi_1, \xi_2$.

Proof. We perform the calculation for \overline{E}_{M1} , for \overline{E}_{M2} it will follow accordingly. Now, by the use of definition of Haar wavelet function we can evaluate coefficients a_i as

$$\begin{aligned} a_i &= 2^j \int_0^1 y''(t) h_i(t) dt, \\ a_i &= 2^j \left[\int_{\eta_1}^{\eta_2} y''(\zeta) d\zeta - \int_{\eta_2}^{\eta_3} y''(\zeta) d\zeta \right], \\ a_i &= 2^j [(\eta_2 - \eta_1) y''(\zeta_1) - (\eta_3 - \eta_2) y''(\zeta_2)], \end{aligned}$$

similarly coefficients b_i as

$$b_i = 2^j [(\eta_2 - \eta_1) z''(\zeta_1) - (\eta_3 - \eta_2) z''(\zeta_2)],$$

where $\zeta_1 \in (\eta_1, \eta_2)$ and $\zeta_2 \in (\eta_2, \eta_3)$. It follows from Eq. (18) that $(\eta_2 - \eta_1) = (\eta_3 - \eta_2) = 1/(2m) = 1/(2^{j+1})$, then the above expression of a_i, b_i reduces to

$$\begin{aligned} a_i &= \frac{1}{2} [y''(\zeta_1) - y''(\zeta_2)] = \frac{1}{2} (\zeta_1 - \zeta_2) \frac{dy''}{dt}(\zeta), \quad \zeta \in (\zeta_1, \zeta_2), \\ b_i &= \frac{1}{2} (\zeta_1 - \zeta_2) \frac{dz''}{dt}(\zeta), \quad \zeta \in (\zeta_1, \zeta_2). \end{aligned}$$

Let us consider that $\left(\frac{dy''}{dt}\right)$ is bounded such that $\left|\frac{dy''}{dt}\right| \leq \xi_1$, so we have

$$a_i \leq \xi_1 \left(\frac{1}{2^{j+1}}\right). \quad (78)$$

similarly let us consider that $\left(\frac{dz''}{dt}\right)$ is bounded such that $\left|\frac{dz''}{dt}\right| \leq \xi_2$, so we have

$$b_i \leq \xi_2 \left(\frac{1}{2^{j+1}}\right). \quad (79)$$

Here we will solve for upper bound of a function $p_{2,i}$ in all subintervals. Since $p_{2,i}(t) = 0$ for $t \in [0, \eta_1(i)]$. The function $p_{2,i}(t)$ increases monotonically in the interval $t \in [\eta_1(i), \eta_2(i)]$. Thus $p_{2,i}(t)$ achieves its upper bound at $t = \eta_2(i)$ as follows

$$p_{2,i} = p_{2,2^j+k+1} \leq \frac{[\eta_2(i) - \eta_1(i)]^2}{2} = \frac{1}{2} \left(\frac{1}{2^{j+1}}\right)^2, \quad t \in [\eta_1(i), \eta_2(i)].$$

In the interval $t \in [\eta_2(i), \eta_3(i)]$ the function $p_{2,i}$ is monotonically increasing if

$$t \leq \eta_3, \quad (80)$$

which is obviously true.

This inequality (80) can be derived from formulas (18) and (22) and condition $\frac{dp_{2,i}(t)}{dt} > 0$. Hence maximum value of $p_{2,i}(t)$ can be obtained by substituting $t = \eta_3(i)$ in eq. (22) as

$$p_{2,i}(t) = p_{2,2^j+k+1} \leq \left(\frac{1}{2^{j+1}}\right)^2, \quad t \in [\eta_2(i), \eta_3(i)].$$

When $t \in [\eta_3, 1]$ the function $p_{2,i}(t)$ can be expanded as (by eq. (22)) (see [17])

$$p_{2,i}(t) = \left(\frac{1}{2^{j+1}}\right)^2.$$

The function $p_{2,i}(t)$ increases monotonically in $[0, 1]$, since it increases monotonically in every sub interval of $[0, 1]$. So upper bound of $p_{2,i}(t)$ in $[0, 1]$ is given by

$$p_{2,i}(t) \leq \left(\frac{1}{2^{j+1}}\right)^2 \quad \forall t \in [0, 1]. \quad (81)$$

Expanding quadrate of L^2 norm of error function, we obtain

$$\begin{aligned} \|\bar{E}_{M1}\|_2^2 = & \int_0^1 \left(\frac{n_1 t}{1 - n_1 n_2 v_1 v_2} \left[n_2 v_1 \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} a_{2^j+k+1} [P_{2,2^j+k+1}(v_2) - v_2 P_{2,2^j+k+1}(1)] + \right. \right. \\ & \left. \left. \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} b_{2^j+k+1} [P_{2,2^j+k+1}(v_1) - v_1 P_{2,2^j+k+1}(1)] \right] \right. \\ & \left. + \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} a_{2^j+k+1} a_i [P_{2,2^j+k+1}(t) - t P_{2,2^j+k+1}(1)] \right)^2 dt. \quad (82) \end{aligned}$$

Expanding and calculating the integral we have

$$\begin{aligned} \|\bar{E}_{M1}\|_2^2 = & \frac{n_1^2 n_2^2 v_1^2}{3(1 - n_1 n_2 v_1 v_2)^2} \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \sum_{s=0}^{2^r-1} a_{2^j+k+1} a_{2^r+s+1} (p_{2,2^j+k+1}(v_2) - v_2 p_{2,2^j+k+1}(1)) \\ & (p_{2,2^r+s+1}(v_2) - v_2 p_{2,2^r+s+1}(1)) \\ & + \frac{n_1^2}{3(1 - n_1 n_2 v_1 v_2)^2} \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \sum_{s=0}^{2^r-1} b_{2^j+k+1} b_{2^r+s+1} \\ & (p_{2,2^j+k+1}(v_1) - v_1 p_{2,2^j+k+1}(1)) (p_{2,2^r+s+1}(v_1) - v_1 p_{2,2^r+s+1}(1)) \\ & + \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \sum_{s=0}^{2^r-1} a_{2^r+s+1} a_{2^j+k+1} \\ & \int_0^1 (p_{2,2^j+k+1}(t) - t p_{2,2^r+s+1}(1)) (p_{2,2^r+s+1}(t) - t p_{2,2^r+s+1}(1)) dt \\ & + \frac{2n_1^2 n_2 v_1}{3(1 - n_1 n_2 v_1 v_2)^2} \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \\ & \sum_{s=0}^{2^r-1} a_{2^j+k+1} b_{2^r+s+1} (p_{2,2^j+k+1}(v_2) - v_2 p_{2,2^j+k+1}(1)) (p_{2,2^r+s+1}(v_1) - v_1 p_{2,2^r+s+1}(1)) \\ & + \frac{2n_1}{1 - n_1 n_2 v_1 v_2} \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \\ & \sum_{s=0}^{2^r-1} b_{2^j+k+1} a_{2^r+s+1} (p_{2,2^j+k+1}(v_1) - v_1 p_{2,2^j+k+1}(1)) \left(\frac{1}{2} p_{2,2^r+s+1}(t) - \frac{1}{3} p_{2,2^r+s+1}(1) \right) \\ & + \frac{2n_1 n_2 v_1}{1 - n_1 n_2 v_1 v_2} \sum_{j=J+1}^{\infty} \sum_{k=0}^{2^j-1} \sum_{r=J+1}^{\infty} \sum_{s=0}^{2^r-1} b_{2^j+k+1} a_{2^r+s+1} (p_{2,2^r+s+1}(v_2) - v_2 p_{2,2^r+s+1}(1)) \\ & \left(\frac{1}{2} p_{2,2^j+k+1}(t) - \frac{1}{3} p_{2,2^j+k+1}(1) \right). \quad (83) \end{aligned}$$

Now inserting equation (78), (79) and (81) in equation (83) and following the calculation similar to the proof of theorem 4.2, we get

$$\|\bar{E}_{M1}\|_2 \leq \tilde{C} \left(\frac{1}{2^{J+1}} \right)^2$$

where \tilde{C} is a constant which depends on $n_1, n_2, v_1, v_2, \xi_1, \xi_2$. Rest of the proof can be completed as we did for theorem 3.2. \square

5.3 Numerical Illustration for HWCA4PTBVP

In this section we will discuss two numerical problems based on system of nonlinear singular four point boundary value problem ([2]).

5.3.1 Example 5 ([2])

Consider the system of singular nonlinear differential equations (15)-(16) with four point boundary conditions (65)-(66) with $n_1 = 1$, $n_2 = 1$, $v_1 = \frac{1}{2}$, $v_2 = \frac{1}{3}$, $k_1 = \frac{1}{2}$, $k_2 = \frac{1}{2}$, $\omega_1 = -\frac{1}{2}$, $\omega_2 = -\frac{1}{2}$, $f_1(t, y(t), z(t)) = \left(\frac{99}{35}t - \frac{1}{2} + \left(t^2 - \frac{66}{35}t^3 + \frac{1089}{1225}t^4\right)z - y^2z\right)$ and $f_2(t, y(t), z(t)) = \left(-\frac{24}{35t} + \frac{64}{1225}t^5 - \frac{2112}{42875}t^6 - yz^2\right)$. Applying solution method (subsection 5.1) to solve this problem, we get system of non-linear equations. Thus we arrive at (71)-(72). To solve the non-linear equations we use Newton Raphson method to calculate wavelet coefficients (a_i) and (b_i). After calculating wavelet coefficients (a_i) and (b_i) we get our required solution by substituting a_i and b_i in (68) and (70). For computation of absolute error see subsection 3.3.1. The exact solution $\tilde{y}(t)$ and $\tilde{z}(t)$ of this problem are $-\frac{33}{35}t^2 + t$ and $\frac{8}{35}t^2$ respectively.

For initial guess $[1.25, 1.25, \dots, 1.25]$ computed solutions for $y^M(t)$ and $z^M(t)$ is given in Table 9 and Table 10, respectively for $J = 3$ and $J = 4$. Graph for $y^M(t)$ and $z^M(t)$ with exact solution is given in figure 9a and figure 9b, respectively for $J = 4$. Graph of absolute errors in computation of $y^M(t)$ and $z^M(t)$ is given in figure 10a and figure 10b, respectively for $J = 1$, $J = 2$, $J = 3$ and $J = 4$.

If we change initial guesses to $[1.29, 1.29, \dots, 1.29]$ and $[1.21, 1.21, \dots, 1.21]$ we observe that solution does not change significantly.

t	$J = 3$	$J = 4$	Exact Solution	Successive Iter. Tech. [2]
0	0	0	0	0
0.1	0.0905714	0.0905714	0.0905714	0.09057158
0.2	0.162286	0.162286	0.162286	0.16228593
0.3	0.215143	0.215143	0.215143	0.21514312
0.4	0.249143	0.249143	0.249143	0.24914315
0.5	0.264286	0.264286	0.264286	0.26428604
0.6	0.260571	0.260571	0.260571	0.26057177
0.7	0.238	0.238	0.238	0.23800035
0.8	0.196571	0.196571	0.196571	0.19657177
0.9	0.136286	0.136286	0.136286	0.13628605
1	0.0571429	0.0571429	0.0571429	0.05714317
L^∞	5.55112E-17	8.32667E-17		3.4978 E-7


Table 9: Solutions $y^M(t)$ for $J = 3$ and $J = 4$ for example 5.3.1.

t	$J = 3$	$J = 4$	Exact Solution	Successive Iter. Tech. [2]
0	0	0	0	0
0.1	0.00228571	0.00228571	0.00228571	0.00228586
0.2	0.00914286	0.00914286	0.00914286	0.00914306
0.3	0.0205714	0.0205714	0.0205714	0.02057168
0.4	0.0365714	0.0365714	0.0365714	0.03657172
0.5	0.0571429	0.0571429	0.0571429	0.05714317
0.6	0.0822857	0.0822857	0.0822857	0.08228604
0.7	0.112	0.112	0.112	0.11200033
0.8	0.146286	0.146286	0.146286	0.14628604
0.9	0.185143	0.185143	0.185143	0.18514316
1	0.228571	0.228571	0.228571	0.2285717
L^∞	5.55112E-17	5.55112E-17		3.3431E-7


Table 10: Solutions $z^M(t)$ for $J = 3$, $J = 4$ for example 5.3.1.

5.3.2 Example 6 ([2])

Consider the system of singular differential equations (15)-(16) with four point boundary conditions (65)-(66) with $n_1 = \frac{2}{3}$, $n_2 = \frac{1}{3}$, $v_1 = \frac{1}{2}$, $v_2 = \frac{1}{4}$, $k_1 = \frac{1}{2}$, $k_2 = \frac{1}{2}$, $\omega_1 = -\frac{1}{2}$, $\omega_2 = -\frac{1}{2}$, $f_1(t, y(t), z(t)) = \left(-\frac{283}{216} + \frac{67}{9}t + \left(\frac{80089}{16} - \frac{18961}{2}t + 4489t^2\right)\frac{t^2z^2}{729} - y^2z^2\right)$ and $f_2(t, y(t), z(t)) = \left(-\frac{1}{3} + \frac{3}{2}t + \left(-67t + \frac{283}{4}\right)^2\left(\frac{1}{4}t^2 - \frac{2}{3}t + \frac{4}{9}\right)\frac{t^4}{729} - y^2z^2\right)$. Here we are computing absolute error described in subsection 3.3.1. The exact solution $\tilde{y}(t)$ and $\tilde{z}(t)$ of this problem are $-\frac{67}{27}t^2 + \frac{283}{108}t$ and $-\frac{1}{2}t^2 + \frac{2}{3}t$, respectively.




(a) Graph of $y^M(t)$ for $J = 4$ for example 5.3.1.




(b) Graph of $z^M(t)$ for $J = 4$ for example 5.3.1.

Figure 9




(a) Graph of absolute errors in $y^M(t)$ for example 5.3.1.




(b) Graph of absolute errors in $z^M(t)$ for example 5.3.1.

Figure 10



(a) Graph of $y^M(t)$ for $J = 4$ for example 5.3.2.



(b) Graph of $z^M(t)$ for $J = 4$ for example 5.3.2.

Figure 11

For initial guess $[1.75, 1.75, \dots, 1.75]$ computed solutions for $y^M(t)$ and $z^M(t)$ is given in Table 11 and Table 12, respectively for $J = 3$ and $J = 4$. Graph for $y^M(t)$ and $z^M(t)$ with exact solution is given in figure 11a and figure 11b, respectively for $J = 4$. Graph of absolute errors in computation of $y^M(t)$ and $z^M(t)$ is given in figure 12a and figure 12b, respectively for $J = 1, J = 2, J = 3$ and $J = 4$.


If the initial guesses are changed to $[1.79, 1.79, \dots, 1.79]$ and $[1.71, 1.71, \dots, 1.71]$ we observe that solution does not vary which proves that method is stable.

t	$J = 3$	$J = 4$	Exact Solution	Successive Iter. Tech. [2]
0	0	0	0	0
0.1	0.237222	0.237222	0.237222	0.237222
0.2	0.424815	0.424815	0.424815	0.42481451
0.3	0.562778	0.562778	0.562778	0.5627774
0.4	0.651111	0.651111	0.651111	0.65111068
0.5	0.689815	0.689815	0.689815	0.68981435
0.6	0.678889	0.678889	0.678889	0.67888841
0.7	0.618333	0.618333	0.618333	0.61833284
0.8	0.508148	0.508148	0.508148	0.50814765
0.9	0.348333	0.348333	0.348333	0.34833284
1	0.138889	0.138889	0.138889	0.13888839
L^∞	1.11022E-16	1.11022E-16		4.9806E-7


Table 11: Solutions $y^M(t)$ for $J = 3$ and $J = 4$ for example 5.3.2.

t	$J = 3$	$J = 4$	Exact Solution	Successive Iter. Tech. [2]
0	0	0	0	0
0.1	0.0616667	0.0616667	0.0616667	0.06166623
0.2	0.113333	0.113333	0.113333	0.11333273
0.3	0.155	0.155	0.155	0.15499929
0.4	0.186667	0.186667	0.186667	0.18666591
0.5	0.208333	0.208333	0.208333	0.20833259
0.6	0.22	0.22	0.22	0.21999934
0.7	0.221667	0.221667	0.221667	0.22166612
0.8	0.213333	0.213333	0.213333	0.21333293
0.9	0.195	0.195	0.195	0.19499974
1	0.166667	0.166667	0.166667	0.16666655
L^∞	5.55112E-17	5.55112E-17		7.5635E-7

Table 12: Solutions $z^M(t)$ for $J = 3$ and $J = 4$ for example 5.3.2.



(a) Graph of absolute errors in $y^M(t)$ for example 5.3.2.



(b) Graph of absolute errors in $z^M(t)$ for example 5.3.2.

Figure 12

6 Remark

In this work we have used Haar collocation method followed by Newton Raphson method to solve system of Lane-Emden equations subject to IVPs, BVPs and Four Point BVPs. For IVP we have given tables 1, 2, 3, 4, and figures 1, 2, 3, 4. It is visible from the table that at $J = 3, 4$, that is 16, 32 divisions 100% accuracy is achieved. Figures 1, 2, 3, 4 show the nature as well as accuracy of the computed solution.

For BVP we have given tables 5, 6, 7, 8, and figures 5, 6, 7, 8. It is visible from the table that at $J = 3, 4$, that is 16, 32 divisions absolute L^∞ error is almost tending to zero. Figures 5, 6, 7, 8 show the nature as well as accuracy of the computed solution.

For the 4 point BVP we have given tables 9, 10, 11, 12, and figures 9, 10, 11, 12. It is visible from the table that at $J = 3, 4$, that is 16, 32 divisions absolute L^∞ error is almost tending to zero. Figures 9, 10, 11, 12 show the nature as well as accuracy of the computed solution. We have compared our result with a recently published work by Barnwal et al. (Successive Iteration Technique [2]). In our case error is almost zero while incase of [2] error is of order 10^{-6} or 10^{-7} .

Our method takes minimum number of spatial division and only finite number of iterations (of Newton Raphson) to obtain exact solution. We observe that our solution approaches to exact solution as the value of J is increased to 3, 4 or so. We also observed that if we makes small perturbation in initial guess then our solution does not vary significantly. Moreover our proposed method takes less time and computational work as compared to other numerical methods like Monotonic iterative technique. The computed results shows the accuracy and stability of proposed method. Hence this method is more reliable and robust.

References

- [1] George Bachman, Lawrence Narici, and Edward Beckenstein. Fourier and wavelet analysis. *Springer-Verlag New York Berlin Heidelberg*, 2000.
- [2] Amit K. Barnwal and Priti Pathak. Successive iteration technique for singular nonlinear system with four-point boundary conditions. *Journal of Applied Mathematics and Computing*, 2019.
- [3] John V. Baxley and Stephen B. Robinson. Nonlinear boundary value problems for shallow membrane caps, ii. *Journal of Computational and Applied Mathematics*, 88:203 – 224, 1998.
- [4] Albert Boggess and Francis J. Narcowich. A first course in wavelets with fourier analysis. *John Wiley and Sons*, 2009.
- [5] P. L. Chambre. On the solution of the poisson boltzmann equation with application to the theory of thermal explosions. *The Journal of Chemical Physics*, 20:1795–1797, 1952.
- [6] S. Chandrasekhar. Introduction to the study of stellar structure. *Dover publications*, 1967.

- [7] R. W. Dickey. Rotationally symmetric solutions for shallow membrane caps. *Quarterly of Applied Mathematics*, 47:571–581, 1989.
- [8] R. C. Duggan and A. M. Goodman. Pointwise bounds for a nonlinear heat conduction model of the human head. *Bulletin of Mathematical Biology*, 48:229 – 236, 1986.
- [9] Tian-Chu Hao, Fu-Zhong Cong, and Yu-Feng Shang. An efficient method for solving coupled lane-emen boundary value problems in catalytic diffusion reactions and error estimate. *Journal of Mathematical Chemistry*, 56(9):2691–2706, Oct 2018.
- [10] Ji-Huan He and Fei-Yu Ji. Taylor series solution for lane-emen equation. *Journal of Mathematical Chemistry*, 57(8):1932–1934, Sep 2019.
- [11] Ulo Lepik. Haar wavelet method for solving higher order differential equations. *Int. J. Math. Comput*, 1:84–94, 2008.
- [12] Ulo Lepik and Helle Hein. *Haar Wavelets With Applications*. Springer, Cham, 2014.
- [13] Ruyun Ma. Multiple nonnegative solutions of second-order systems of boundary value problems. *Nonlinear Analysis: Theory, Methods & Applications*, 42(6):1003 – 1010, 2000.
- [14] Harshita Madduri and Pradip Roul. A fast-converging iterative scheme for solving a system of lane-emen equations arising in catalytic diffusion reactions. *Journal of Mathematical Chemistry*, 57(2):570–582, Feb 2019.
- [15] M. Mahalakshmi and G. Hariharan. An efficient wavelet-based method for the numerical solutions of nonlinear coupled reaction-diffusion equations in biochemical engineering. *Journal of Mathematical Chemistry*, 57(4):1154–1168, Apr 2019.
- [16] Stephane G. Mallat. Multiresolution approximations and wavelet orthonormal bases of $l^2(\mathbf{r})$. *Trans. Amer. Math. Soc.*, 315:69–87, 1989.
- [17] V. B. Mandelzweig and F. Tabakin. Quasilinearization approach to nonlinear problems in physics with application to nonlinear odes. *Computer Physics Communications*, 141:268–281, 2001.
- [18] Yalcin Ozturk. An efficient numerical algorithm for solving system of lane-emen type equations arising in engineering” nonlinear engineering. *Nonlinear Engineerin*, 8(1):429–437, 2018.
- [19] R. K. Pandey and Amit K. Verma. On solvability of derivative dependent doubly singular boundary value problems. *Journal of Applied Mathematics and Computing*, 33(1):489–511, Jun 2010.
- [20] R.K. Pandey and A.K. Verma. Existence-uniqueness results for a class of singular boundary value problems arising in physiology. *Nonlinear Analysis: Real World Applications*, 9(1):40 – 52, 2008.
- [21] R.K. Pandey and A.K. Verma. Existence-uniqueness results for a class of singular boundary value problems-ii. *Journal of Mathematical Analysis and Applications*, 338(2):1387 – 1396, 2008.
- [22] R.K. Pandey and A.K. Verma. A note on existence-uniqueness results for a class of doubly singular boundary value problems. *Nonlinear Analysis: Theory, Methods & Applications*, 71(7):3477– 3487, 2009.
- [23] R.K. Pandey and Amit K. Verma. Monotone method for singular bvp in the presence of upper and lower solutions. *Applied Mathematics and Computation*, 215(11):3860 – 3867, 2010.
- [24] Mara Cristina Pereyra and Lesley A. Ward. *Harmonic Analysis: From Fourier to Wavelets*. American Mathematical Society, 2012.
- [25] Himanshu Garg Randhir Singh and Vandana Guleria. Haar wavelet collocation method for lane-emen equations with dirichlet, neumann and neumann-robin boundary conditions. *J. Comput. Appl. Math.*, 346:150–161, 2019.
- [26] Mandeep Singh and Amit K. Verma. Picard type iterative scheme with initial iterates in reverse order for a class of nonlinear three point bvps. *International Journal of Differential Equations*, 2013:6, 2013.
- [27] Mandeep Singh and Amit K. Verma. Nonlinear three point singular bvps: A classification. *Communications in Applied Analysis*, 21(4):513–532, 2017.
- [28] Mandeep Singh, Amit K. Verma, and Ravi P. Agarwal. Maximum and anti-maximum principles for three point sbvps and nonlinear three point sbvps. *Journal of Applied Mathematics and Computing*, 47(1):249–263, Feb 2015.

- [29] Mandeep Singh, Amit K Verma, and Ravi P Agarwal. On an iterative method for a class of 2 point & 3 point nonlinear sbvps. *Journal of Applied Analysis and Computation*, 9(4):1242–1260, 2019.
- [30] Randhir Singh, Julee Shahni, Himanshu Garg, and Apoorv Garg. Haar wavelet collocation approach for lane-emen equations arising in mathematical physics and astrophysics. *he European Physical Journal Plus*, 134(11):548, 2019.
- [31] A. K. Verma. *Analytical Results for a Class of Nonlinear Singular Boundary Value Problems*. PhD thesis, IIT Kharagpur, 2009.
- [32] Amit K. Verma. The monotone iterative method and zeros of bessel functions for nonlinear singular derivative dependent bvp in the presence of upper and lower solutions. *Nonlinear Analysis: Theory, Methods & Applications*, 74(14):4709–4717, 2011.
- [33] Amit K. Verma and Mandeep Singh. Existence of solutions for three-point bvps arising in bridge design. *Electronic Journal of Differential Equations*, 2014(173):1–11, 2014.
- [34] Amit K. Verma and Mandeep Singh. A note on existence results for a class of three-point nonlinear bvps. *Mathematical Modelling and Analysis*, 20(4):457–470, 2015.
- [35] Amit K. Verma and Mandeep Singh. Singular nonlinear three point bvps arising in thermal explosion in a cylindrical reactor. *Journal of Mathematical Chemistry*, 53(2):670–684, Feb 2015.
- [36] Amit K. Verma, Mandeep Singh, and Ravi P. Agarwal. Regions of existence for a class of nonlinear diffusion type problems. *Applicable Analysis and Discrete Mathematics*, 2019.
- [37] Amit K. Verma and Diksha Tiwari. Higher resolution methods based on quasilinearization and haar wavelets on lane-emen equations. *International Journal of Wavelets, Multiresolution and Information Processing*, 17(03), 2019.
- [38] Amit K. Verma and Diksha Tiwari. A note on legendre, hermite, chebyshev, laguerre and gegenbauer wavelets with an application on sbvps arising in real life. *arXiv*, 2019.
- [39] Amit K. Verma and Diksha Tiwari. On some computational aspects of hermite wavelets on a class of sbvps arising in exothermic reactions. *arXiv*, 2019.
- [40] Amit K. Verma, Nazia Urus, and Mandeep Singh. Monotone iterative technique for a class of four point bvps with reversed ordered upper and lower solutions. *International Journal of Computational Methods*, 0(0):1950066, 0.
- [41] Haihua Wang and Haibo Chen. Existence of positive solutions for a system of second-order m-point bvps with variable parameters. *Journal of Applied Mathematics and Computing*, 31(1):517–531, Sep 2009.
- [42] Abdul-Majid Wazwaz, Randolph Rach, and Jun-Sheng Duan. Adomian decomposition method for solving the volterra integral form of the lane-emen equations with initial values and boundary conditions. *Appl. Math. Comput.*, 219(10):5004–5019, 2013.
- [43] Lie-jun Xie, Cai-lian Zhou, and Song Xu. Solving the systems of equations of lane-emen type by differential transform method coupled with adomian polynomials. *Mathematics*, 7(4), 2019.
- [44] Hai-E Zhang and Jian-Ping Sun. Existence of positive solution to singular systems of second-order four-point bvps. *Journal of Applied Mathematics and Computing*, 29(1):325–339, Jan 2009.