

Exact Tests for Offline Changepoint Detection in Multichannel Binary and Count Data with Application to Networks

Shyamal K. De*

School of Mathematical Sciences
NISER, HBNI
OD 752050, India
shyamalkd@gmail.com

Soumendu Sundar Mukherjee†

Interdisciplinary Statistical Research Unit
Indian Statistical Institute, Kolkata
WB 700108, India
soumendu041@gmail.com

Abstract

We consider offline detection of a single changepoint in binary and count time-series. We compare exact tests based on the cumulative sum (CUSUM) and the likelihood ratio (LR) statistics, and a new proposal that combines exact two-sample conditional tests with multiplicity correction, against standard asymptotic tests based on the Brownian bridge approximation to the CUSUM statistic. We see empirically that the exact tests are much more powerful in situations where normal approximations driving asymptotic tests are not trustworthy: (i) small sample settings; (ii) sparse parametric settings; (iii) time-series with changepoint near the boundary.

We also consider a multichannel version of the problem, where channels can have different changepoints. Controlling the False Discovery Rate (FDR), we simultaneously detect changes in multiple channels. This “local” approach is shown to be more advantageous than multivariate global testing approaches when the number of channels with changepoints is much smaller than the total number of channels.

As a natural application, we consider network-valued time-series and use our approach with (a) edges as binary channels and (b) node-degrees or other local subgraph statistics as count channels. The local testing approach is seen to be much more informative than global network changepoint algorithms.

Keywords: Conditional tests; CUSUM statistic; global vs. local testing; multiple testing.

*De’s research is supported in part by the Science and Engineering Research Board grant MTR/2017/000503 under the MATRICS scheme.

†Mukherjee’s research is supported in by an INSPIRE Faculty Fellowship from the Department of Science and Technology, Government of India.

1 Introduction

Changeoint analysis is an important problem in statistics with roots in statistical quality control (Page, 1954, 1957; Girshick and Rubin, 1952). The goal of changeoint analysis is to decide if there are distributional changes in a given time-series (the detection part), and estimate the change if any (the estimation part). There is a huge body of literature on the univariate changeoint problem. An excellent treatment can be found in the book Brodsky and Darkhovsky (2013).

Some notable works on the multivariate version of the problem are Zhang et al. (2010); Siegmund et al. (2011); Srivastava and Worsley (1986); James et al. (1992) in parametric settings, and Harchaoui et al. (2009); Lung-Yut-Fong et al. (2011); Chen and Zhang (2015) in non-parametric settings.

We should mention that there are two types of changeoint problems: (a) offline, where the whole time-series is available to the statistician; (b) online, where data is still arriving at the time of analysis. We will be concerned with the offline problem in this article.

Although a lot of work has been done on changeoint detection for continuous time-series data, results for discrete data are lacking, especially in “small sample” settings where the length of the time-series is relatively small. In this article, our main goal is to develop methods for offline changeoint detection for binary and count data that have good performance in small sample settings.

We adapt well-known conditional two-sample tests for binary and count data to the changeoint setup using a multiple testing approach. We also consider exact tests based on natural statistics such as the CUSUM statistic and the LR statistic. We conduct a comprehensive small-sample power analysis of these tests and compare them against the large sample CUSUM test based on a Brownian bridge approximation (Brodsky and Darkhovsky, 2013). We find that, in small sample scenarios, and in cases where the true changeoint lies near the boundary, the exact tests are significantly more powerful than large sample tests.

Although these methods are developed for single changeoint problems, they seem to work well when multiple changeoints are present, especially if there is one strong change. We report some empirical findings in this direction in the appendix.

We then consider multichannel binary or count time-series. Using a False Discovery Rate (FDR) controlling mechanism, we simultaneously test for change-points in all the channels. This “local” approach vastly outperforms the “global” approach of using some statistic of all channels together (e.g., a vector CUSUM statistic), when the number of channels with change-points is much smaller than the total number of channels.

As an application of this approach, we consider local vs. global testing in network-valued time-series. Although there has been a recent surge of interest in network change-points ([Peel and Clauset, 2015](#); [Roy et al., 2017](#); [Mukherjee, 2018](#); [Wang et al., 2018](#); [Padilla et al., 2019](#); [Zhao et al., 2019](#); [Bhattacharjee et al., 2020](#); [Bhattacharyya et al., 2020](#)), we note that the existing works are focused on large sample asymptotics and use global statistics for detection or estimation. If we use edges (resp. node degrees or some other local subgraph statistics such as local triangle counts) as separate channels, then we have multichannel binary (resp. count) data. We compare the proposed local approach against a standard CUSUM-based global approach in real-world networks. We see that, in addition to picking up strong global changes, the local approach can identify relatively weak and rare changes.

The rest of the paper is organised as follows. In Section 2, we describe the problem set-up precisely and detail our methodology. In Section 3, we discuss our multiple testing based local approach for multichannel change-point detection. In Section 4, we report our simulations: In Section 4.1, we perform a comprehensive power analysis of the various proposed methods against existing approaches. In Section 4.2, we compare the local testing approach vs. multivariate CUSUM-based global testing approaches in multichannel problems. More detailed results are provided in the appendix. Then, in Section 5, we apply our methodology on two real-life examples: a time-series of US senate voting pattern networks, and another time-series of phone-call networks. We conclude the paper with a discussion in Section 6.

2 Set-up and methodology

Suppose that we have time-indexed independent variables X_1, \dots, X_T , with $\mathbb{E}(X_i) = \pi_i$. We want to test if the π_i have changed over time. The single changepoint testing problem is:

$$H_0 : \pi_i = \pi \text{ for all } 1 \leq i \leq T \text{ (no change)}$$

vs.

$$H_1 : \exists 1 \leq \tau \leq T - 1 \text{ such that } \pi_i = \pi_1 \mathbb{I}_{\{i \leq \tau\}} + \pi_2 \mathbb{I}_{\{i > \tau\}} \text{ (at least one change)}. \quad (1)$$

We are interested in the situation where the X_i 's are binary or counts. The binary case is obviously modelled by a independent Bernoulli time-series, whereas we model count data using the Poisson distribution. Keeping that in mind, let us now discuss some natural test statistics for the testing problem (1). We begin by deriving the likelihood ratio statistic.

The Likelihood Ratio (LR) statistic.

Binary data: Note that under H_1 , the likelihood of the data is

$$L(\pi_1, \pi_2, \tau) = \pi_1^{S_\tau} (1 - \pi_1)^{T - S_\tau} \times \pi_2^{S_T - S_\tau} (1 - \pi_2)^{T - \tau - (S_T - S_\tau)}.$$

The maximizers of L for a fixed τ are $\hat{\pi}_1 = \frac{S_\tau}{\tau}$ and $\hat{\pi}_2 = \frac{S_T - S_\tau}{T - \tau}$. Thus the profile log-likelihood for τ is

$$\ell_{\text{PL}}(\tau) = -\tau H(\hat{\pi}_1) - (T - \tau) H(\hat{\pi}_2),$$

where $H(x) = -x \log x - (1 - x) \log(1 - x)$ is the entropy of a $\text{Ber}(x)$ variable. Define

$$\mathcal{T}_b = \min_{1 \leq t \leq T-1} \left[t H\left(\frac{S_t}{t}\right) + (T - t) H\left(\frac{S_T - S_t}{T - t}\right) \right].$$

Then the LR statistic is

$$\mathcal{T}_{\text{LR}}^{(b)} = -2(\ell_0 - \ell_1) = -2(-TH(S_T/T) + \mathcal{T}_b). \quad (2)$$

We would reject H_0 for large values of this statistic.

Count data: Recall that we are modeling counts using the Poisson distribution. Under H_1 , the likelihood of the data is

$$L(\pi_1, \pi_2, \tau) \propto e^{-\tau \pi_1} \pi_1^{S_\tau} e^{-(T - \tau) \pi_2} \pi_2^{S_T - S_\tau}.$$

The maximizers of L for a fixed τ are $\hat{\pi}_1 = \frac{S_\tau}{\tau}$ and $\hat{\pi}_2 = \frac{S_T - S_\tau}{T - \tau}$. Therefore the profile log-likelihood for τ is

$$\ell_{\text{PL}}(\tau) = -\tau G(\hat{\pi}_1) - (T - \tau)G(\hat{\pi}_2),$$

where $G(x) = x(1 - \log x)$. Define

$$\mathcal{T}_c = \min_{1 \leq t \leq T-1} \left[tG\left(\frac{S_t}{t}\right) + (T - t)G\left(\frac{S_T - S_t}{T - t}\right) \right].$$

Then the LR statistic is

$$\mathcal{T}_{\text{LR}}^{(c)} = -2(\ell_0 - \ell_1) = -2(-TG(S_T/T) + \mathcal{T}_L). \quad (3)$$

We would reject H_0 for large values of this statistic.

CUSUM statistic.

A well-known and often-used statistic in change-point problems is the so-called CUSUM statistic. For $0 < a < b < 1$, suppose aT and bT are known upper and lower bounds on the locations of the potential change-points. For $0 \leq \delta \leq 1$, the CUSUM statistic is defined as

$$\mathcal{T}_{\text{CUSUM}}^{(\delta)} = \max_{aT \leq t \leq bT} \left[\frac{t}{T} \left(1 - \frac{t}{T} \right) \right]^\delta \left| \frac{S_t}{t} - \frac{S_T - S_t}{T - t} \right|. \quad (4)$$

This can be used with both binary and count data.

2.1 Asymptotic tests

First, we will consider an asymptotic test based on the CUSUM statistic (4). The asymptotic null distribution can be calculated using a Brownian bridge approximation. For details see, e.g., [Brodsky and Darkhovsky \(2013\)](#).

Proposition 1. Let $B^0(t)$ denote a standard Brownian bridge. Under H_0 , $\pi_i = \pi$ for all i , and

$$\frac{\sqrt{T} \mathcal{T}_{\text{CUSUM}}^{(\delta)}}{\sqrt{\pi(1 - \pi)}} \xrightarrow[T \rightarrow \infty]{\mathcal{L}} M_{ab}^{(\delta)},$$

where $M_{ab}^{(\delta)} = \max_{a \leq t \leq b} \frac{|B^0(t)|}{(t(1-t))^{1-\delta}}$.

Corollary 1. Let $\hat{\pi} = \frac{1}{T} \sum_{s=1}^T X_s \xrightarrow[H_0, T \rightarrow \infty]{a.s.} \pi$. Then, under H_0 ,

$$\frac{\sqrt{T} \mathcal{T}_{\text{CUSUM}}^{(\delta)}}{\sqrt{\hat{\pi}(1 - \hat{\pi})}} \xrightarrow[T \rightarrow \infty]{\mathcal{L}} M_{ab}^{(\delta)}.$$

Using this result we can perform an asymptotic test for H_0 in the “large sample” regime where T is large. This test would be good when π is not too small (so that the underlying normal approximations to the partial sums $\sum_{s=1}^t X_s$ go through). It is well-known that in this asymptotic framework the choice $\delta = 1/2$ is the best for estimation (See, e.g., [Brodsky and Darkhovsky \(2013\)](#), Chapter 3), while $\delta = 1$ is the best for minimizing type-1 error, $\delta = 0$ for minimizing type-2 error. However, in the small sample situations explored in this paper we do not see such a clear-cut distinction (see Section 4).

2.2 Conditional tests

Our exact tests are based on the following simple lemma.

Lemma 1. *Suppose X_1, \dots, X_T are independent $\text{Bin}(n_i, \pi)$ (or $\text{Poisson}(\pi)$). Let $S_i = \sum_{j=1}^i X_j$. Then the joint distribution of (S_1, \dots, S_{T-1}) given S_T does not depend on π .*

Proof. Since S_T is sufficient for π , the distribution of (X_1, \dots, X_T) given S_T does not depend on π . Hence the same holds for (S_1, \dots, S_{T-1}) . \square

Approach 1.

By Lemma 1, $\mathcal{T}_{LR} \mid S_T$ does not depend on π under H_0 . So we can do an exact conditional test. In fact, we can use the statistics \mathcal{T}_b (or \mathcal{T}_c) which is equivalent to $\mathcal{T}_{LR}^{(b)}$ for conditional testing. Similarly, we can do a CUSUM based exact test, since the CUSUM statistic $\mathcal{T}_{\text{CUSUM}}^{(\delta)}$ is a function of the partial sums $S_t, t < T$.

Approach 2.

Note that we can decompose H_1 as a disjoint union of the following $(T - 1)$ hypotheses:

$$H_{1i} : \tau = i, 1 \leq i \leq T - 1,$$

and test these separately against H_0 , and, finally, rejecting H_0 if one of these $T - 1$ hypotheses gets rejected.

Binary data: Suppose $X_i \sim \text{Ber}(\pi_i)$. Note that if we use $S_i = \sum_{j=1}^i X_j$ as a test statistic for testing H_0 against H_{1i} , then, under H_0 ,

$$S_i \mid S_T \sim \text{Hypergeometric}(i, S_T, T).$$

Therefore, we get a p -value p_i from this conditional distribution as

$$p_i = \sum_{q: f(q; i, S_T, T) \leq f(S_i; i, S_T, T)} f(q; i, S_T, T),$$

where $f(q; i, S_T, T)$ is the PMF of the Hypergeometric(i, S_T, T) distribution.

Count data: For count data $X_i \sim \text{Poisson}(\pi_i)$, we can use the same procedure as above using the observation that, under H_0 ,

$$S_i | S_T \sim \text{Binomial}\left(S_T, \frac{i}{T}\right).$$

In this case, we get a p -value p_i from the above conditional distribution as

$$p_i = \sum_{q: g(q; S_T, i/T) \leq g(S_i; S_T, i/T)} g(q; S_T, i/T),$$

where $g(q; S_T, i/T)$ is the PMF of the Binomial($S_T, i/T$) distribution.

Multiplicity correction: Once we get hold of the individual p -values, we can try to control the *familywise error rate* (FWER). It follows from Lemma 1 that (p_1, \dots, p_{T-1}) given S_T does not depend on π under H_0 . Thus we can exactly simulate the distribution of $p_{(1)}$ using Monte Carlo. Denoting by $r_{\alpha, T}$ the lower α -th quantile of $p_{(1)}$, we reject H_0 , if $p_{(1)} \leq r_{\alpha, T}$.

2.3 Changepoint estimation

While we are interested in changepoint detection, the testing methods give bona-fide estimators of the underlying changepoint. For example, the likelihood ratio statistics are based on maximizing the profile log-likelihood $\ell_{\text{PL}}(\tau)$ and the maximizer gives an estimate of τ . Similarly, for the CUSUM statistic, the maximizer in the definition gives one estimate. As for the conditional testing approach, the minimizing index of the individual p -values gives an estimate of the changepoint. One can show that, under a single changepoint model, these estimates are consistent, because all these objective functions are based on the cumulative average S_t/t , and one can use the fact that a properly rescaled version of this process converges to a Brownian motion under the null hypothesis of no changepoints. For example, an analysis of the CUSUM estimator along these lines can be found in [Brodsky and Darkhovsky \(2013\)](#). In Section 5, we

obtain channel-specific estimates of changepoints in this way and plot their histograms (see Figures 5, 7, and 8).

A statistically valid procedure for simultaneous detection and estimation may be obtained by using an even-odd sample splitting: separate out the observations with even and odd time indexes, use the even ones for testing, and based on the decision, use the odd one for further estimation. However, as with any sample splitting method, this method will suffer a loss in power in small sample scenarios.

3 The multichannel case: global vs. local testing

Suppose we observe an m -variate ($m > 1$) independent time-series

$$\mathbf{X}_1, \dots, \mathbf{X}_\tau \stackrel{\text{i.i.d.}}{\sim} F_1, \mathbf{X}_{\tau+1}, \dots, \mathbf{X}_T \stackrel{\text{i.i.d.}}{\sim} F_2,$$

where F_1 and F_2 are m -variate distributions. We would like to test the global null H_0 : “no change in the m -variate time-series”, i.e., $H_0 : \tau = T$. Since permutations of $\mathbf{X}_1, \dots, \mathbf{X}_T$ are equally likely under H_0 , a natural approach for testing H_0 is to adopt a permutation test using the global CUSUM statistic

$$C^{(\delta)} = \max_{1 \leq t \leq T-1} \left[\frac{t}{T} \left(1 - \frac{t}{T} \right) \right]^\delta \left\| \frac{1}{t} \sum_{i=1}^t \mathbf{x}_i - \frac{1}{T-t} \sum_{i=t+1}^T \mathbf{x}_i \right\| \text{ for } \delta \in [0, 1],$$

where $\|\cdot\|$ denote any suitable norm in \mathbb{R}^m . Permuting the time-series multiple times, we construct a randomized size- α test that rejects H_0 for a large value of observed $C^{(\delta)}$. However, this test cannot determine which channels were responsible for the global change.

Now suppose that $\mathbf{X}_i = (X_{i,1}, \dots, X_{i,m})$ for $i = 1, \dots, T$, and the time-series for the j -th channel is

$$X_{j,1}, \dots, X_{j,\tau} \stackrel{\text{i.i.d.}}{\sim} F_{j,1}, X_{j,\tau+1}, \dots, X_{j,T} \stackrel{\text{i.i.d.}}{\sim} F_{j,2} \text{ for } j = 1, 2, \dots, m.$$

In this article, $F_{j,1} \equiv \text{Ber}(p_{j,1})$ or $\text{Pois}(\lambda_{j,1})$ and $F_{j,2} \equiv \text{Ber}(p_{j,2})$ or $\text{Pois}(\lambda_{j,2})$ depending on whether we deal with binary or count data. The global null H_0 is equivalent to $\cap_{j=1}^m H_{0,j}$ where $H_{0,j}$: “no change in the j -th channel”. A local approach for testing H_0 would be to compute p -values corresponding to $H_{0,j}$ for $j = 1, \dots, m$, and apply some suitable multiple testing procedure controlling FWER or FDR. Note that FDR equals FWER under $\cap_{j=1}^m H_{0,j}$. Since FDR controlling

methods are known to be more powerful than traditional FWER controlling methods such as Bonferroni and Holm's methods (Holm (1979)) when m is large, we use some popular methods for FDR control.

In this article, we consider the celebrated Benjamini-Hochberg (BH) step-up procedure proposed by Benjamini and Hochberg (1995). Benjamini and Yekutieli (2001) proved that the BH method controls FDR at a pre-fixed level when p -values are mutually independent or they have certain positive dependence.

Let $\mathcal{R} = \{1 \leq j \leq m : H_{0,j} \text{ is rejected}\}$ be the rejection set obtained from some FDR controlling procedure. The global null H_0 is rejected if and only if \mathcal{R} is nonempty. This test for H_0 is referred as a local test $\phi := \mathbb{I}_{\{\mathcal{R} \neq \emptyset\}}$.

Remark 1. *If FDR is controlled at level α , then ϕ is a valid level- α test for the global null H_0 since $P_{H_0}(H_0 \text{ rejected}) = P_{H_0}(\mathcal{R} \neq \emptyset) = P_{H_0}(\cup_{j=1}^m H_{0,j} \text{ rejected}) = \text{FWER} = \text{FDR} \leq \alpha$.*


Remark 2. *The local testing approach enjoys a few advantages over the global testing approach. First, local testing is much more informative in the sense that channels responsible for the global change, if any, are also determined. Second, under the rare signal regime where signals are available only in a few out of a large number of channels, global tests may fail to detect a change whereas local tests are more likely to detect the change as they scrutinize all channels. These points are empirically demonstrated in the simulations of Section 4.2.*

Remark 3. *Although we have formulated the local testing approach for a single global changepoint so as to compare it to the global testing approach, it is clear that the former applies to situations where individual channels have different changepoints. This advantage of the local testing approach over the global testing approach will be clear in Section 5, where we plot histograms of detected local changepoints.*


4 Simulations

4.1 Exact vs. asymptotic tests in a single channel


We first compare the proposed exact level- α tests against the asymptotic level- α tests in a single channel. Exact conditional tests using the $\min_{1 \leq i \leq T-1} p_i$ statistic, as discussed in Section 2.2,




(a) $T = 50, \tau = 25, \pi_1 = 0.4$



(b) $T = 50, \tau = 40, \pi_1 = 0.46$




(c) $T = 200, \tau = 100, \pi_1 = 0.08$




(d) $T = 200, \tau = 160, \pi_1 = 0.148$

Figure 1: Comparison of change detection probabilities of exact tests, asymptotic tests and the cptmean test with $\alpha = 0.1$ in the time-series $X_1, \dots, X_\tau \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_1), X_{\tau+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_2)$.


are referred to as “minP” tests, conditional tests based on $\mathcal{T}_{\text{LR}}^{(b)}$ and $\mathcal{T}_{\text{LR}}^{(c)}$ are referred to as “LR” tests, and conditional tests based on the CUSUM statistics $\mathcal{T}_{\text{CUSUM}}^{(0.5)}$ and $\mathcal{T}_{\text{CUSUM}}^{(1)}$ are referred to as the “CU.5” test and the “CU1” test respectively. For these exact tests, α -th quantiles of the respective test statistics under null are estimated from 50,000 Monte Carlo samples.




(a) $T = 10, \tau = 5, \lambda_1 = 2$



(b) $T = 10, \tau = 2, \lambda_1 = 1$



(c) $T = 50, \tau = 25, \lambda_1 = 0.15$



(d) $T = 50, \tau = 10, \lambda_1 = 0.15$

Figure 2: Comparison of change detection probabilities of exact tests, asymptotic tests and the cptmeanvar test with $\alpha = 0.1$ in the time-series: $X_1, \dots, X_\tau \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_1), X_{\tau+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_2)$.

Asymptotic tests based on Brownian bridge approximations (see Corollary 1) are considered for $\delta = 0.5$ and $\delta = 1$, and are referred to as the “BB.5” test and the “BB1” test respectively.

Additionally, we consider two tests based on the functions `cpt.mean` and `cpt.meanvar` in the **R** package `changept`, which estimate the number of changepoints in univariate time-series.

These are referred to as the “cptmean” test and the “cptmeanvar” test respectively. These tests¹ detect a change if the number of estimated changepoints is at least one.

Figure 1 considers the Bernoulli case. We see that the exact conditional tests perform well in both sparse and dense situations and always outperform the cptmean test. The asymptotic tests (especially BB1) also provide reasonable power if the sample size T is large and the changepoint τ is near the middle (Figures 1(a) and 1(c)). However, if the changepoint is closer to the boundary (Figures 1(b) and 1(d)), then the exact conditional tests minP and LR perform significantly better than the asymptotic tests.

Figure 2 considers the Poisson case. The proposed exact tests perform well even when the sample size is as small as $T = 10$, and, in this case, they uniformly outperform the asymptotic tests and the cptmeanvar test. If the changepoint is close to the boundary, then the exact tests (especially minP and LR) yield much higher power than their competitors (see Figures 2(b) and 2(d)). For large sample sizes (e.g., $T = 50$), when the Brownian bridge approximations kick in, asymptotic tests become comparable to the exact tests in terms of performance.

4.2 Global vs. local testing in multiple channels

Global testing of H_0 is done by permutation tests using $C^{(\delta)}$ with Euclidean norm as discussed in Section 3. The m -variate time-series $\mathbf{X}_1, \dots, \mathbf{X}_T$ is permuted $B = 1000$ times to obtain a randomized size- α test. For power comparisons, two tests “gCU.5” and “gCU1” are considered that are obtained using the global CUSUM statistics $C^{(0.5)}$ and $C^{(1)}$ respectively.

To test each channel for possible changepoints, we consider three exact conditional tests, namely minP, LR and CU1. After computing p -values from these tests, we employ the BH procedure to obtain $\mathcal{R} = \{1 \leq j \leq m : H_{0,j} \text{ is rejected}\}$. Henceforth, we refer to these local tests as minP-BH, LR-BH and CU1-BH respectively. Figures 3 and 4 compare probabilities of global change detection (gCD), i.e. probabilities of rejecting H_0 (this is $P(\mathcal{R} \neq \emptyset)$ for local tests) for global and local tests. Figure 3 considers Bernoulli channels while Figure 4 deals with Poisson channels. We find that the local tests are significantly more powerful than the global

¹The “cptmean” test in Figure 1 applies the `cpt.mean` function with the “BinSeg” method and the CUSUM statistic. The “cptmeanvar” test in Figure 2 applies the `cpt.meanvar` function with the “BinSeg” method and the “Poisson” statistic.

tests in the rare signal regime where n_{cp} is small or moderate. Also, the power advantage is more and continues over a longer range of n_{cp} when the changepoint is near the boundary. The local and global tests have comparable power for large n_{cp} , as expected.




Figure 3: Comparison of $P(gCD)$ of global and local tests in $m = 1000$ independent Bernoulli series: $X_{j,1}, \dots, X_{j,\tau} \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_1 = 0.05)$, $X_{j,\tau+1}, \dots, X_{j,T} \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_2 = 0.25)$ where $T = 200$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels undergo change at time-point τ .

In a simulation study presented in the appendix, we consider two additional FDR controlling methods, namely the adaptive Benjamini-Hocheberg (ABH) and the adaptive Storey-Taylor-Siegmund (STS) methods. Performances of these methods are comparable to that of the vanilla BH method as the simulation study is done under the rare signal regime. Both the ABH and the STS methods are implemented using the **R** package `mutoss` (Team et al., 2017).

5 Real data

Now we analyse two datasets that can be naturally summarised by networks. These give real examples of multichannel binary and count data with potential changepoints.




Figure 4: Comparison of $P(\text{gCD})$ of global and local tests in $m = 200$ independent Poisson series: $X_{j,1}, \dots, X_{j,\tau} \stackrel{\text{i.i.d.}}{\sim} \text{Pois}(\lambda_1 = 0.25)$, $X_{j,\tau+1}, \dots, X_{j,T} \stackrel{\text{i.i.d.}}{\sim} \text{Pois}(\lambda_2 = 1.5)$ where $T = 20$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels undergo change at time-point τ .

5.1 US senate rollcall data

From the US senate rollcall dataset (Lewis et al., 2020), we construct networks where nodes represent US senate seats. Each epoch represents a proposed bill on which votes were taken. An edge between two seats is formed if they voted similarly on that bill. We have $n = 100$ nodes. We consider $T = 50$ time-points between August 10, 1994 and January 24, 1995.

There are $m = \binom{n}{2} = 4950$ channels (i.e. edges). Of these, 622 channels are ignored while analyzing this data since those channels contain too many zeros or ones (more than 45). We applied the BH procedure to simultaneously test the remaining 4328 channels controlling FDR at level $\alpha = 0.05$. For each significant channel, the corresponding changepoint location is also reported (see the discussion in Section 2.3).

In Figure 5, we plot the histograms of the changepoint locations of the significant channels. Note particularly the peak near time-point 24 (which corresponds to December 1, 1994). There is a historically well-documented change near December 1994, which saw the end of the conservative coalition (see, e.g., Moody and Mucha (2013)). Interestingly, the global method also

detected a changepoint at $t = 24$. Changepoints at nearly the same location were found earlier in Roy et al. (2017) and Mukherjee (2018). However, the local methods have the advantage of identifying the channels that underwent a change. The number of significant channels, n_s , is reported below each histogram. A number of channels had extremely small p -values. For example, Figure 6(a) depicts the time-series of edges (4, 5) and (4, 6). Changes are visible to the naked eye. Seats 5 and 6 are in Arizona, while seat 4 is in Arkansas. Clearly, seat 4 went from agreeing with seats 5 and 6 to disagreeing. On the other hand, seat 3 is also from Arkansas, and no changepoints were found in the channels (3, 5) and (3, 6) (see Figure 6(b)).




Figure 5: Distribution of detected changepoint locations in the US senate rollcall data. All three methods report a mode at $t = 24$.

5.2 MIT reality mining data

We use the MIT reality mining data (Eagle and Pentland, 2006) to construct a series of networks involving $n = 90$ individuals (staff and students at the university). The data consists of call logs between these individuals from 20th July 2004 to 14th June 2005. We construct $T = 48$ weekly networks, where a weighted edge between nodes u and v reports the number of phone calls between them during the corresponding week. There are $m = \binom{n}{2} = 4005$ channels (i.e. edges). 3945 channels are ignored while analyzing this data since those channels contain too many zeros (more than 44). The remaining 60 channels are tested for possible changepoints.

We model the weighted edges as Poisson variables and apply the exact tests minP, LR or CU1 on each channel. Then we apply the BH method to simultaneously test the 60 chan-




Figure 6: (a) Edges (4, 5) and (4, 6). Seats 5 and 6 are in Arizona, while seat 4 is in Arkansas. Clearly, seat 4 went from agreeing with seats 5 and 6 to disagreeing. (b) Edges (3, 5) and (3, 6). Seat 3 is also in Arkansas. No changepoints are detected in these channels.

nels controlling FDR at level $\alpha = 0.05$. Figure 7 contains the histograms of the detected changepoint locations. Note particularly the peaks near $t = 20$ and $t = 33$. For comparison, a changepoint at $t = 24$ was found by a global algorithm in Mukherjee (2018). The graph-based multivariate (global) change detection methods of Chen and Zhang (2015) found changepoints at approximately $t = 22$ and $t = 25$ (their analyses were on daily networks). The global algorithms consider global characteristics, and thus it is not surprising that they find changepoints somewhat in the middle of the predominant local changepoints near $t = 20$ and $t = 33$. It turns out that $t = 20$ is just before the start of the Winter break, and $t = 33$ is just before the start of the Spring break.

We also perform changepoint analysis with node-degrees as channels, modeled as a Poisson series. Figure 8 shows the histograms of the detected changepoint locations. Analyses of edge and degree time-series detect 44 and 46 common nodes (i.e. detected by all three tests: minP-BH, LR-BH and CU1-BH) respectively. Among these, 40 nodes are declared significant by both analyses.

Finally, in Figure 9, we show the average networks before and after time-point 20. The 46 channels (i.e. nodes) declared to have changepoints by all three tests under the degree-based analysis are shown as green circles. A structural change is clearly visible.




Figure 7: Change-point locations from edge-based analysis of the MIT reality mining data.




Figure 8: Change-point locations from degree-based analysis of the MIT reality mining data.

6 Discussion

In this article, we have considered the problem of change-point detection for binary and count data, and proposed exact tests that perform significantly better than Brownian-bridge based asymptotic tests in small samples. We have also considered multichannel data and used a multiple testing approach to test for changes in all channels simultaneously. This local approach outperforms the global approach of treating all channels together as a single object quite significantly in case of rare signals (i.e. when the number of channels with a change-point is much smaller than the total number of channels).

Although the methods we propose are technically for single changes, they work quite well for multiple change-points, especially when there is one large change. This is empirically demon-




Figure 9: Average networks (a) before and (b) after time-point 20 in the MIT reality mining data. Green nodes represent significant channels.

strated in the appendix.

References

- Benjamini, Y. and Hochberg, Y. (1995). 'Controlling the False Discovery Rate: A Practical and Powerful Approach to Multiple Testing'. *Journal of the Royal Statistical Society. Series B.*, pages 289–300.
- Benjamini, Y. and Yekutieli, D. (2001). The control of the false discovery rate in multiple testing under dependency. *Annals of Statistics*, 29:1165–1188.
- Bhattacharjee, M., Banerjee, M., and Michailidis, G. (2020). Change point estimation in a dynamic stochastic block model. *Journal of machine learning research*, 21(107):1–59.
- Bhattacharyya, S., Chatterjee, S., and Mukherjee, S. S. (2020). Consistent detection and optimal localization of all detectable change-points in piecewise stationary arbitrarily sparse network-sequences. *In preparation*.

- Brodsky, E. and Darkhovsky, B. S. (2013). *Nonparametric methods in change point problems*, volume 243. Springer Science & Business Media.
- Chen, H. and Zhang, N. (2015). Graph-based change-point detection. *Ann. Statist.*, 43(1):139–176.
- Eagle, N. and Pentland, A. S. (2006). Reality mining: sensing complex social systems. *Personal and ubiquitous computing*, 10(4):255–268.
- Girshick, M. A. and Rubin, H. (1952). A bayes approach to a quality control model. *The Annals of mathematical statistics*, pages 114–125.
- Harchaoui, Z., Moulines, E., and Bach, F. R. (2009). Kernel change-point analysis. In *Advances in neural information processing systems*, pages 609–616.
- Hochberg, Y. and Benjamini, Y. (1990). More powerful procedures for multiple significance testing. *Statistics in medicine*, 9(7):811–818.
- Holm, S. (1979). A simple sequentially rejective multiple test procedure. *Scandinavian journal of statistics*, pages 65–70.
- James, B., James, K. L., and Siegmund, D. (1992). Asymptotic approximations for likelihood ratio tests and confidence regions for a change-point in the mean of a multivariate normal distribution. *Statistica Sinica*, pages 69–90.
- Lewis, J. B., Poole, K., Rosenthal, H., Boche, A., Rudkin, A., and Sonnet, L. (2020). *Voteview: Congressional Roll-Call Votes Database*. <https://voteview.com/>.
- Lung-Yut-Fong, A., Lévy-Leduc, C., and Cappé, O. (2011). Homogeneity and change-point detection tests for multivariate data using rank statistics. *arXiv preprint arXiv:1107.1971*.
- Moody, J. and Mucha, P. J. (2013). Portrait of political party polarization. *Network Science*, 1(1):119–121.
- Mukherjee, S. S. (2018). *On Some Inference Problems for Networks*. PhD thesis, University of California, Berkeley.

- Padilla, O. H. M., Yu, Y., and Priebe, C. E. (2019). Change point localization in dependent dynamic nonparametric random dot product graphs. *arXiv preprint arXiv:1911.07494*.
- Page, E. S. (1954). Continuous inspection schemes. *Biometrika*, 41(1/2):100–115.
- Page, E. S. (1957). On problems in which a change in a parameter occurs at an unknown point. *Biometrika*, 44(1/2):248–252.
- Peel, L. and Clauset, A. (2015). Detecting change points in the large-scale structure of evolving networks. In *AAAI*, pages 2914–2920.
- Roy, S., Atchadé, Y., and Michailidis, G. (2017). Change point estimation in high dimensional markov random-field models. *Journal of the Royal Statistical Society: Series B (Statistical Methodology)*, 79(4):1187–1206.
- Siegmund, D., Yakir, B., and Zhang, N. R. (2011). Detecting simultaneous variant intervals in aligned sequences. *The Annals of Applied Statistics*, pages 645–668.
- Srivastava, M. and Worsley, K. J. (1986). Likelihood ratio tests for a change in the multivariate normal mean. *Journal of the American Statistical Association*, 81(393):199–204.
- Storey, J. D., Taylor, J. E., and Siegmund, D. (2004). Strong control, conservative point estimation and simultaneous conservative consistency of false discovery rates: a unified approach. *Journal of the Royal Statistical Society: Series B (Statistical Methodology)*, 66(1):187–205.
- Team, M. C., Blanchard, G., Dickhaus, T., Hack, N., Konietschke, F., Rohmeyer, K., Rosenblatt, J., Scheer, M., and Werft, W. (2017). *mutoss: Unified Multiple Testing Procedures*. R package version 0.1-12.
- Wang, D., Yu, Y., and Rinaldo, A. (2018). Optimal change point detection and localization in sparse dynamic networks. *arXiv preprint arXiv:1809.09602*.
- Zhang, N. R., Siegmund, D. O., Ji, H., and Li, J. Z. (2010). Detecting simultaneous change-points in multiple sequences. *Biometrika*, 97(3):631–645.
- Zhao, Z., Chen, L., and Lin, L. (2019). Change-point detection in dynamic networks via graphon estimation. *arXiv preprint arXiv:1908.01823*.

A Appendix

In this appendix, we evaluate the performances of the global and local tests conducted at level $\alpha = 0.1$ for binary and count data. To construct the local tests, we implement the BH procedure and two more powerful adaptive methods for FDR control. The first one is the adaptive Benjamini-Hochberg (ABH) method where the number of true null hypotheses m_0 is estimated as \hat{m}_0 using the proposal of Hochberg and Benjamini (1990), and this estimate is used in the BH method with $\alpha^* = \alpha m / \hat{m}_0$. This approach gives better power than the BH method provided m / \hat{m}_0 is significantly bigger than 1. The other method we use is the adaptive Storey-Taylor-Siegmund (STS) method proposed by Storey et al. (2004).

We consider m independent Bernoulli (Tables 1-4) and Poisson (Tables 5-8) time-series of size T . Among these m channels, n_{cp} channels contain changepoints. We compare the probabilities of global change detection ($P(gCD)$) of the global and local tests. For any local test, one of the tests among minP, LR and CU1 is used in each channel, and then one of the procedures among BH, ABH, and STS is applied to control FDR at level $\alpha = 0.1$. Once channels are detected with changepoints by a local test, we provide a measure of the power of that local test in terms of its True Positive Rate (TPR) defined as $E[TP] / \max(1, n_{cp})$ where TP is the number of channels with correctly detected changepoints. $P(gCD)$, TPR and FDR , presented in Tables 1-8, are estimated based on 1000 Monte Carlo samples.

A.1 Studies with a single changepoint

Tables 1-3 deal with Bernoulli time-series having a single changepoint at location τ in n_{cp} channels. We make the following observations.

1. Power $P(gCD)$ of the local tests are significantly higher than the global tests in setups where n_{cp} is not large enough. This supports our claim that, compared to the global tests, local tests are more sensitive towards detecting a global change when signal is rare. If enough signal is present (n_{cp} large), then global tests tend to produce similar power as the local tests.
2. Under the sparse signal regime ($\pi_1 = 0.01, \pi_2 = 0.1$), if the changepoint is closer to the

boundary ($T = 200, \tau = 175$), then global tests fail miserably to detect a global change (Table 2) whereas local tests are able to detect such a change with high probability even for small to moderate signal ($n_{cp} = 10, 20$ for $m = 200$, and $n_{cp} = 20, 40$ for $m = 1000$).

3. Performances of the three FDR controlling procedures are similar, although STS seems to yield slightly more power in most of the cases.
4. gCU1 performs much better than gCU.5 when the changepoint occurs in the middle of the time-series, and gCU.5 significantly outperforms gCU1 when the changepoint is near the boundary.
5. Both $P(gCD)$ and TPR increase as n_{cp} increases or m decreases (see Tables 1, 2 or Tables 1, 3).
6. The CU1 local tests perform better than the minP and the LR local tests in most of the cases except for a few cases in Table 2 where the changepoint is near the boundary.

Tables 5-7 deal with Poisson time-series of small ($T = 10$) and moderate ($T = 50$) sizes having a single changepoint at τ in n_{cp} channels. We observe the same phenomena mentioned in points 1, 3 and 4 above. If the channels have strong signal (e.g., $\lambda_1 = 0.3, \lambda_2 = 3$), then the local tests perform well even for small sample sizes (e.g., $T = 10$) and very small n_{cp} (e.g., $n_{cp} = 2, 6$). For cases with moderate sample size (e.g., $T = 50$), global changes are detected with high probability even with weak signal (e.g., $\lambda_1 = 0.25, \lambda_2 = 0.75$). For settings with $T = 50$, the global and local tests return higher values of $P(gCD)$ and TPR when the changepoint occurs near the middle of the time-series. This simulation study also indicates that there is no uniformly best conditional exact test among minP, LR and CU1.

A.2 Studies with multiple changepoints

For a binary or count time-series with multiple changepoints, the exact conditional tests minP, LR and CU1 are theoretically valid level- α tests. We conduct comparative power analyses of these tests under the scenarios described in Tables 4 and 8.

Table 4 deals with m independent Bernoulli time-series of the form: $X_1, \dots, X_{\tau_1} \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_1)$, $X_{\tau_1+1}, \dots, X_{\tau_2} \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_2)$, $X_{\tau_2+1}, \dots, X_{\tau_3} \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_3)$, $X_{\tau_3+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_4)$ with $T =$

200, $m = 200$. n_{cp} channels contain changepoints at $\tau_1 = 50, \tau_2 = 100$ and $\tau_3 = 150$. Interestingly, the LR test performs better than the minP and CU1 tests in all the scenarios considered here. Under the rare signal regime, the local tests produce much higher $P(gCD)$ than the global tests which supports the claims of Section 6. In the first setting ($\pi_1 = 0.01, \pi_2 = 0.1, \pi_3 = 0.2, \pi_4 = 0.3$) in Table 4, the Bernoulli probabilities increase steadily over time and strong signals are present in channels with changepoints. Thus TPR and $P(gCD)$ are significantly high even for quite small n_{cp} . In the second setup ($\pi_1 = 0.01, \pi_2 = 0.2, \pi_3 = 0.1, \pi_4 = 0.3$), the Bernoulli probabilities increase and decrease alternatively as time progresses. The local and the global tests experience in this setting a loss of power compared to the first setting. However, the local tests continue to uniformly (and significantly) dominate over the global tests. Note also that the CU1 local tests suffer the most whereas the LR local tests work the best.

In Table 8, we consider m independent Poisson time-series of the form: $X_1, \dots, X_{\tau_1} \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_1), X_{\tau_1+1}, \dots, X_{\tau_2} \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_2), X_{\tau_2+1}, \dots, X_{\tau_3} \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_3), X_{\tau_3+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_4)$ where $T = 50, m = 200$ and n_{cp} channels contain changepoints at $\tau_1 = 10, \tau_2 = 20$ and $\tau_3 = 35$. Interestingly, the CU1 local tests outperform all other local tests for both the settings presented in Table 8. The local and the global tests produce less power in the second setting ($\lambda_1 = 0.2, \lambda_2 = 0.8, \lambda_3 = 0.5, \lambda_4 = 1.4$) compared to the first setting ($\lambda_1 = 0.2, \lambda_2 = 0.5, \lambda_3 = 0.8, \lambda_4 = 1.4$). However, under both the settings, the local tests produce much higher power than the global tests when very few channels ($n_{cp} = 2, 4, 8$) undergo changes, which again corroborates the claims of Section 6.

Table 1: Comparison of gCU.5 and gCU1 with local tests obtained by combining the FDR controlling procedures BH, ABH and STS with minP, LR, and CU1 in m independent Bernoulli series of the form:

$X_1, \dots, X_\tau \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_1), X_{\tau+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_2)$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels (among m) contain a change at τ .

$m = 200, T = 50, \tau = 25, \pi_1 = 0.01, \pi_2 = 0.30$												
n_{cp}		gCU.5	gCU1	minP BH	LR BH	CU1 BH	minP ABH	LR ABH	CU1 ABH	minP STS	LR STS	CU1 STS
0	$P(gCD)$	0.114	0.082	0.086	0.108	0.09	0.086	0.108	0.09	0.09	0.11	0.092
5	$P(gCD)$	0.276	0.432	0.430	0.506	0.540	0.430	0.506	0.540	0.436	0.508	0.546
	TPR			0.122	0.168	0.182	0.122	0.168	0.182	0.124	0.169	0.186
	FDR			0.091	0.092	0.088	0.091	0.094	0.089	0.091	0.094	0.089
10	$P(gCD)$	0.636	0.806	0.704	0.784	0.812	0.710	0.786	0.816	0.726	0.788	0.830
	TPR			0.182	0.238	0.265	0.185	0.239	0.270	0.191	0.242	0.280
	FDR			0.081	0.074	0.076	0.084	0.076	0.080	0.086	0.078	0.082
15	$P(gCD)$	0.912	0.974	0.854	0.914	0.924	0.856	0.916	0.928	0.868	0.920	0.930
	TPR			0.241	0.302	0.340	0.249	0.310	0.359	0.253	0.311	0.360
	FDR			0.089	0.090	0.091	0.093	0.093	0.096	0.095	0.094	0.094
$m = 200, T = 50, \tau = 40, \pi_1 = 0.01, \pi_2 = 0.30$												
5	$P(gCD)$	0.182	0.148	0.616	0.614	0.624	0.616	0.614	0.624	0.622	0.616	0.628
	TPR			0.193	0.194	0.219	0.193	0.194	0.220	0.195	0.195	0.221
	FDR			0.098	0.093	0.090	0.098	0.094	0.091	0.100	0.097	0.091
10	$P(gCD)$	0.458	0.178	0.832	0.828	0.852	0.834	0.828	0.852	0.838	0.832	0.854
	TPR			0.234	0.240	0.266	0.234	0.241	0.267	0.238	0.243	0.268
	FDR			0.084	0.083	0.080	0.088	0.084	0.081	0.088	0.086	0.082
15	$P(gCD)$	0.754	0.304	0.936	0.936	0.950	0.936	0.936	0.952	0.936	0.936	0.954
	TPR			0.308	0.311	0.329	0.309	0.312	0.333	0.312	0.314	0.337
	FDR			0.090	0.091	0.087	0.092	0.094	0.089	0.095	0.096	0.091
$m = 200, T = 200, \tau = 100, \pi_1 = 0.01, \pi_2 = 0.10$												
0	$P(gCD)$	0.084	0.096	0.104	0.098	0.090	0.104	0.098	0.090	0.106	0.102	0.092
10	$P(gCD)$	0.232	0.320	0.726	0.828	0.854	0.728	0.830	0.858	0.744	0.838	0.864
	TPR			0.189	0.258	0.287	0.192	0.260	0.293	0.199	0.266	0.300
	FDR			0.097	0.097	0.088	0.097	0.097	0.091	0.099	0.100	0.089
20	$P(gCD)$	0.454	0.676	0.964	0.984	0.992	0.964	0.984	0.992	0.966	0.986	0.992
	TPR			0.303	0.378	0.431	0.314	0.388	0.446	0.323	0.393	0.452
	FDR			0.093	0.091	0.083	0.097	0.095	0.090	0.101	0.099	0.094
30	$P(gCD)$	0.794	0.928	1	1	1	1	1	1	1	1	1
	TPR			0.365	0.433	0.517	0.383	0.452	0.546	0.395	0.459	0.557
	FDR			0.083	0.083	0.082	0.090	0.091	0.093	0.094	0.095	0.096

Table 2: (Cont'd) Comparison of gCU.5 and gCU1 with local tests obtained by combining the FDR controlling procedures BH, ABH and STS with minP, LR, and CU1 in m independent Bernoulli series of the form: $X_1, \dots, X_\tau \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_1)$, $X_{\tau+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_2)$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels (among m) contain a change at τ .

$m = 200, T = 200, \tau = 175, \pi_1 = 0.01, \pi_2 = 0.10$												
n_{cp}		gCU.5	gCU1	minP BH	LR BH	CU1 BH	minP ABH	LR ABH	CU1 ABH	minP STS	LR STS	CU1 STS
10	$P(gCD)$	0.148	0.120	0.720	0.684	0.610	0.722	0.684	0.610	0.722	0.688	0.620
	TPR			0.137	0.119	0.104	0.139	0.120	0.104	0.141	0.121	0.106
	FDR			0.104	0.102	0.098	0.104	0.104	0.099	0.107	0.105	0.102
20	$P(gCD)$	0.190	0.130	0.926	0.894	0.866	0.926	0.894	0.866	0.926	0.898	0.870
	TPR			0.176	0.157	0.138	0.180	0.159	0.140	0.184	0.164	0.144
	FDR			0.093	0.090	0.103	0.095	0.092	0.103	0.097	0.098	0.105
30	$P(gCD)$	0.445	0.142	0.976	0.966	0.960	0.976	0.966	0.960	0.976	0.966	0.960
	TPR			0.199	0.178	0.156	0.208	0.184	0.159	0.217	0.189	0.166
	FDR			0.081	0.080	0.083	0.084	0.085	0.088	0.089	0.088	0.092
$m = 1000, T = 200, \tau = 100, \pi_1 = 0.01, \pi_2 = 0.10$												
0	$P(gCD)$	0.110	0.095	0.122	0.122	0.106	0.122	0.122	0.106	0.122	0.122	0.106
20	$P(gCD)$	0.192	0.330	0.674	0.782	0.794	0.674	0.782	0.794	0.674	0.782	0.794
	TPR			0.073	0.118	0.121	0.073	0.118	0.121	0.073	0.118	0.122
	FDR			0.109	0.110	0.101	0.109	0.110	0.101	0.109	0.110	0.101
40	$P(gCD)$	0.370	0.650	0.882	0.966	0.968	0.882	0.966	0.968	0.886	0.968	0.968
	TPR			0.110	0.179	0.198	0.111	0.180	0.200	0.114	0.184	0.205
	FDR			0.102	0.096	0.098	0.102	0.096	0.098	0.103	0.099	0.101
60	$P(gCD)$	0.700	0.925	0.970	0.996	0.992	0.970	0.996	0.992	0.970	0.996	0.994
	TPR			0.171	0.252	0.286	0.174	0.257	0.292	0.180	0.261	0.300
	FDR			0.091	0.090	0.091	0.093	0.092	0.093	0.097	0.094	0.096
$m = 1000, T = 200, \tau = 175, \pi_1 = 0.01, \pi_2 = 0.10$												
20	$P(gCD)$	0.148	0.125	0.682	0.682	0.656	0.682	0.682	0.656	0.682	0.682	0.656
	TPR			0.074	0.072	0.062	0.074	0.072	0.062	0.074	0.072	0.062
	FDR			0.113	0.115	0.109	0.113	0.115	0.109	0.115	0.115	0.109
40	$P(gCD)$	0.256	0.160	0.912	0.900	0.872	0.912	0.900	0.872	0.912	0.900	0.872
	TPR			0.100	0.088	0.075	0.100	0.088	0.075	0.101	0.089	0.075
	FDR			0.106	0.100	0.094	0.106	0.100	0.094	0.107	0.102	0.096
60	$P(gCD)$	0.354	0.185	0.990	0.982	0.974	0.990	0.982	0.974	0.990	0.982	0.976
	TPR			0.129	0.112	0.091	0.130	0.112	0.091	0.132	0.113	0.093
	FDR			0.096	0.092	0.093	0.097	0.092	0.093	0.099	0.094	0.094

Table 3: (Cont'd) Comparison of gCU.5 and gCU1 with local tests obtained by combining the FDR controlling procedures BH, ABH and STS with minP, LR, and CU1 in m independent Bernoulli series of the form: $X_1, \dots, X_\tau \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_1), X_{\tau+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_2)$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels (among m) contain a change at τ .

$m = 1000, T = 50, \tau = 25, \pi_1 = 0.01, \pi_2 = 0.30$												
n_{cp}		gCU.5	gCU1	minP BH	LR BH	CU1 BH	minP ABH	LR ABH	CU1 ABH	minP STS	LR STS	CU1 STS
0	$P(gCD)$	0.096	0.11	0.086	0.086	0.080	0.086	0.086	0.080	0.086	0.086	0.080
10	$P(gCD)$	0.258	0.404	0.356	0.402	0.428	0.356	0.402	0.428	0.356	0.404	0.428
	TPR			0.046	0.055	0.065	0.046	0.055	0.065	0.046	0.055	0.065
	FDR			0.091	0.109	0.095	0.091	0.109	0.095	0.091	0.110	0.095
20	$P(gCD)$	0.566	0.792	0.590	0.650	0.722	0.590	0.650	0.722	0.590	0.650	0.722
	TPR			0.065	0.085	0.099	0.065	0.085	0.099	0.065	0.085	0.100
	FDR			0.098	0.094	0.089	0.098	0.094	0.089	0.098	0.094	0.088
30	$P(gCD)$	0.850	0.966	0.744	0.810	0.822	0.744	0.810	0.822	0.744	0.810	0.822
	TPR			0.081	0.108	0.122	0.081	0.109	0.122	0.081	0.108	0.124
	FDR			0.085	0.082	0.078	0.085	0.083	0.078	0.085	0.083	0.079
$m = 1000, T = 50, \tau = 40, \pi_1 = 0.01, \pi_2 = 0.30$												
10	$P(gCD)$	0.182	0.132	0.494	0.474	0.614	0.494	0.474	0.614	0.494	0.474	0.614
	TPR			0.084	0.071	0.103	0.084	0.071	0.103	0.084	0.071	0.103
	FDR			0.090	0.109	0.098	0.090	0.109	0.098	0.090	0.109	0.098
20	$P(gCD)$	0.418	0.166	0.782	0.754	0.862	0.782	0.754	0.862	0.782	0.754	0.862
	TPR			0.125	0.119	0.145	0.125	0.119	0.145	0.125	0.120	0.146
	FDR			0.098	0.092	0.102	0.098	0.092	0.102	0.098	0.092	0.102
30	$P(gCD)$	0.670	0.242	0.898	0.894	0.936	0.898	0.894	0.936	0.898	0.894	0.936
	TPR			0.147	0.140	0.172	0.147	0.140	0.172	0.148	0.140	0.173
	FDR			0.079	0.076	0.078	0.079	0.076	0.078	0.079	0.076	0.078

Table 4: [Multiple changepoints] Comparison of gCU.5 and gCU1 with local tests obtained by combining the FDR controlling procedures BH, ABH and STS with minP, LR, and CU1 in m independent Bernoulli series of the form: $X_1, \dots, X_{\tau_1} \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_1)$, $X_{\tau_1+1}, \dots, X_{\tau_2} \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_2)$, $X_{\tau_2+1}, \dots, X_{\tau_3} \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_3)$ and $X_{\tau_3+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Ber}(\pi_4)$, where $T = 200$ and $m = 200$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels (among m) contain 3 changes at locations $\tau_1 = 50$, $\tau_2 = 100$ and $\tau_3 = 150$.

$\pi_1 = 0.01, \pi_2 = 0.1, \pi_3 = 0.2, \pi_4 = 0.3$												
n_{cp}		gCU.5	gCU1	minP BH	LR BH	CU1 BH	minP ABH	LR ABH	CU1 ABH	minP STS	LR STS	CU1 STS
0	$P(gCD)$	0.084	0.096	0.104	0.098	0.090	0.104	0.098	0.090	0.106	0.102	0.092
2	$P(gCD)$	0.227	0.328	0.930	0.954	0.922	0.930	0.954	0.922	0.930	0.954	0.930
	TPR			0.761	0.811	0.764	0.761	0.811	0.764	0.763	0.812	0.776
	FDR			0.092	0.087	0.101	0.092	0.087	0.101	0.094	0.089	0.105
4	$P(gCD)$	0.556	0.660	1	1	0.992	1	1	0.992	1	1	0.992
	TPR			0.832	0.861	0.832	0.832	0.863	0.833	0.836	0.865	0.837
	FDR			0.110	0.104	0.100	0.110	0.106	0.102	0.112	0.105	0.104
6	$P(gCD)$	0.826	0.892	1	1	1	1	1	1	1	1	1
	TPR			0.866	0.889	0.869	0.867	0.890	0.871	0.870	0.891	0.872
	FDR			0.102	0.096	0.099	0.103	0.098	0.103	0.104	0.098	0.104
$\pi_1 = 0.01, \pi_2 = 0.2, \pi_3 = 0.1, \pi_4 = 0.3$												
2	$P(gCD)$	0.188	0.156	0.692	0.806	0.476	0.692	0.808	0.476	0.692	0.808	0.484
	TPR			0.475	0.602	0.281	0.475	0.605	0.282	0.479	0.605	0.288
	FDR			0.090	0.086	0.086	0.090	0.085	0.086	0.091	0.088	0.089
4	$P(gCD)$	0.402	0.254	0.910	0.978	0.692	0.910	0.978	0.692	0.910	0.978	0.698
	TPR			0.570	0.689	0.321	0.571	0.693	0.322	0.576	0.692	0.327
	FDR			0.109	0.104	0.099	0.109	0.104	0.103	0.110	0.104	0.102
6	$P(gCD)$	0.632	0.352	0.982	0.994	0.866	0.982	0.996	0.866	0.984	0.994	0.872
	TPR			0.650	0.751	0.384	0.651	0.754	0.387	0.655	0.756	0.391
	FDR			0.102	0.100	0.100	0.105	0.102	0.101	0.106	0.103	0.105

Table 5: Comparison of gCU.5 and gCU1 with local tests obtained by combining the FDR controlling procedures BH, ABH and STS with minP, LR, and CU1 in m independent Poisson series of the form: $X_1, \dots, X_\tau \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_1)$, $X_{\tau+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_2)$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels (among m) contain a change at τ .

$m = 1000, T = 50, \tau = 25, \lambda_1 = 0.15, \lambda_2 = 0.75$												
n_{cp}		gCU.5	gCU1	minP BH	LR BH	CU1 BH	minP ABH	LR ABH	CU1 ABH	minP STS	LR STS	CU1 STS
0	$P(gCD)$	0.095	0.115	0.11	0.115	0.135	0.11	0.115	0.135	0.11	0.115	0.135
10	$P(gCD)$	0.225	0.325	0.830	0.900	0.890	0.830	0.900	0.890	0.835	0.900	0.890
	TPR			0.197	0.242	0.283	0.197	0.242	0.283	0.199	0.242	0.283
	FDR			0.113	0.102	0.099	0.113	0.102	0.099	0.114	0.102	0.099
20	$P(gCD)$	0.395	0.670	0.980	0.985	0.995	0.980	0.985	0.995	0.980	0.985	0.995
	TPR			0.260	0.277	0.350	0.261	0.277	0.350	0.262	0.278	0.352
	FDR			0.095	0.101	0.098	0.095	0.101	0.098	0.095	0.101	0.099
30	$P(gCD)$	0.655	0.905	0.995	0.995	0.995	0.995	0.9995	0.995	0.995	0.9995	0.995
	TPR			0.298	0.320	0.400	0.298	0.321	0.401	0.303	0.322	0.402
	FDR			0.085	0.095	0.093	0.086	0.095	0.094	0.091	0.099	0.095
$m = 1000, T = 50, \tau = 40, \lambda_1 = 0.15, \lambda_2 = 0.75$												
10	$P(gCD)$	0.175	0.125	0.710	0.635	0.695	0.710	0.635	0.695	0.710	0.635	0.700
	TPR			0.147	0.113	0.132	0.147	0.113	0.132	0.147	0.113	0.134
	FDR			0.100	0.117	0.113	0.100	0.117	0.113	0.100	0.117	0.113
20	$P(gCD)$	0.250	0.165	0.920	0.900	0.920	0.920	0.900	0.920	0.920	0.900	0.920
	TPR			0.192	0.158	0.173	0.192	0.158	0.173	0.193	0.158	0.173
	FDR			0.078	0.090	0.095	0.080	0.090	0.095	0.080	0.090	0.095
30	$P(gCD)$	0.425	0.220	0.995	0.980	0.980	0.995	0.980	0.980	0.995	0.980	0.980
	TPR			0.234	0.184	0.216	0.234	0.184	0.216	0.236	0.185	0.217
	FDR			0.091	0.098	0.097	0.092	0.098	0.097	0.091	0.097	0.098
$m = 200, T = 50, \tau = 25, \lambda_1 = 0.25, \lambda_2 = 0.75$												
0	$P(gCD)$	0.070	0.120	0.100	0.100	0.100	0.100	0.100	0.100	0.100	0.100	0.100
5	$P(gCD)$	0.150	0.250	0.420	0.460	0.540	0.420	0.460	0.540	0.430	0.460	0.540
	TPR			0.112	0.122	0.152	0.112	0.122	0.152	0.114	0.122	0.154
	FDR			0.059	0.063	0.095	0.059	0.063	0.095	0.064	0.063	0.095
10	$P(gCD)$	0.260	0.640	0.680	0.690	0.790	0.680	0.690	0.790	0.690	0.690	0.800
	TPR			0.133	0.148	0.198	0.133	0.149	0.199	0.140	0.150	0.206
	FDR			0.092	0.100	0.094	0.092	0.095	0.096	0.099	0.100	0.106
20	$P(gCD)$	0.780	0.940	0.940	0.940	0.980	0.940	0.940	0.980	0.940	0.940	0.980
	TPR			0.187	0.190	0.261	0.189	0.192	0.270	0.196	0.196	0.276
	FDR			0.107	0.105	0.097	0.109	0.106	0.101	0.119	0.112	0.102

Table 6: (Cont'd) Comparison of gCU.5 and gCU1 with local tests obtained by combining the FDR controlling procedures BH, ABH and STS with minP, LR, and CU1 in m independent Poisson series of the form: $X_1, \dots, X_\tau \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_1)$, $X_{\tau+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_2)$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels (among m) contain a change at τ .

$m = 200, T = 50, \tau = 40, \lambda_1 = 0.25, \lambda_2 = 0.75$												
n_{cp}		gCU.5	gCU1	minP BH	LR BH	CU1 BH	minP ABH	LR ABH	CU1 ABH	minP STS	LR STS	CU1 STS
10	$P(gCD)$	0.200	0.190	0.510	0.450	0.440	0.510	0.470	0.440	0.520	0.460	0.450
	TPR			0.082	0.063	0.067	0.082	0.065	0.067	0.087	0.064	0.069
	FDR			0.089	0.083	0.087	0.089	0.089	0.087	0.096	0.089	0.097
20	$P(gCD)$	0.400	0.210	0.810	0.700	0.760	0.810	0.700	0.760	0.820	0.710	0.790
	TPR			0.128	0.094	0.101	0.133	0.096	0.103	0.136	0.096	0.110
	FDR			0.117	0.083	0.121	0.114	0.086	0.121	0.122	0.087	0.131
30	$P(gCD)$	0.720	0.290	0.910	0.880	0.910	0.910	0.880	0.910	0.920	0.880	0.920
	TPR			0.147	0.109	0.123	0.151	0.111	0.124	0.158	0.117	0.131
	FDR			0.076	0.068	0.078	0.076	0.068	0.077	0.082	0.079	0.087
$m = 1000, T = 10, \tau = 5, \lambda_1 = 0.30, \lambda_2 = 3.5$												
0	$P(gCD)$	0.090	0.040	0.070	0.060	0.090	0.070	0.060	0.090	0.070	0.060	0.090
2	$P(gCD)$	0.210	0.380	0.630	0.600	0.630	0.630	0.600	0.630	0.630	0.600	0.630
	TPR			0.410	0.395	0.420	0.410	0.395	0.420	0.410	0.395	0.420
	FDR			0.047	0.032	0.071	0.047	0.032	0.071	0.047	0.032	0.071
4	$P(gCD)$	0.450	0.700	0.800	0.780	0.820	0.800	0.780	0.820	0.800	0.780	0.820
	TPR			0.400	0.405	0.428	0.400	0.405	0.428	0.400	0.405	0.428
	FDR			0.049	0.038	0.045	0.049	0.038	0.045	0.049	0.038	0.045
10	$P(gCD)$	0.940	0.990	0.990	0.980	0.990	0.990	0.980	0.990	0.990	0.980	0.990
	TPR			0.474	0.533	0.560	0.474	0.533	0.560	0.474	0.533	0.560
	FDR			0.078	0.040	0.077	0.078	0.040	0.077	0.078	0.040	0.077
$m = 1000, T = 10, \tau = 7, \lambda_1 = 0.30, \lambda_2 = 3.5$												
2	$P(gCD)$	0.160	0.170	0.670	0.600	0.690	0.670	0.600	0.690	0.670	0.600	0.690
	TPR			0.440	0.370	0.475	0.440	0.370	0.475	0.440	0.370	0.475
	FDR			0.072	0.027	0.065	0.072	0.027	0.065	0.072	0.027	0.065
4	$P(gCD)$	0.490	0.310	0.840	0.760	0.870	0.840	0.760	0.870	0.840	0.760	0.870
	TPR			0.463	0.375	0.515	0.463	0.375	0.515	0.463	0.375	0.515
	FDR			0.047	0.034	0.050	0.047	0.034	0.050	0.047	0.034	0.050
10	$P(gCD)$	0.940	0.510	1	1	1	1	1	1	1	1	1
	TPR			0.557	0.511	0.603	0.557	0.511	0.603	0.557	0.511	0.603
	FDR			0.073	0.042	0.078	0.073	0.042	0.078	0.073	0.042	0.078

Table 7: (Cont'd) Comparison of gCU.5 and gCU1 with local tests obtained by combining the FDR controlling procedures BH, ABH and STS with minP, LR, and CU1 in m independent Poisson series of the form: $X_1, \dots, X_\tau \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_1)$, $X_{\tau+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_2)$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels (among m) contain a change at τ .

$m = 200, T = 10, \tau = 5, \lambda_1 = 0.3, \lambda_2 = 3$												
n_{cp}		gCU.5	gCU1	minP BH	LR BH	CU1 BH	minP ABH	LR ABH	CU1 ABH	minP STS	LR STS	CU1 STS
0	$P(gCD)$	0.096	0.101	0.073	0.067	0.083	0.073	0.067	0.083	0.074	0.067	0.083
1	$P(gCD)$	0.140	0.220	0.340	0.410	0.380	0.340	0.410	0.380	0.340	0.410	0.380
	TPR			0.290	0.400	0.350	0.290	0.400	0.350	0.290	0.400	0.350
	FDR			0.088	0.037	0.055	0.088	0.037	0.055	0.088	0.037	0.055
2	$P(gCD)$	0.360	0.500	0.520	0.590	0.580	0.520	0.590	0.580	0.520	0.590	0.580
	TPR			0.325	0.370	0.360	0.325	0.370	0.360	0.330	0.370	0.360
	FDR			0.045	0.032	0.032	0.045	0.032	0.033	0.045	0.032	0.032
6	$P(gCD)$	0.900	0.975	0.860	0.970	0.960	0.860	0.970	0.960	0.860	0.970	0.960
	TPR			0.407	0.492	0.473	0.407	0.500	0.473	0.407	0.492	0.473
	FDR			0.053	0.068	0.062	0.055	0.068	0.062	0.053	0.068	0.062
$m = 200, T = 10, \tau = 7, \lambda_1 = 0.3, \lambda_2 = 3$												
1	$P(gCD)$	0.110	0.120	0.440	0.430	0.480	0.440	0.430	0.480	0.440	0.430	0.480
	TPR			0.390	0.400	0.430	0.390	0.400	0.430	0.390	0.400	0.430
	FDR			0.103	0.052	0.070	0.103	0.052	0.070	0.103	0.052	0.070
2	$P(gCD)$	0.350	0.210	0.590	0.540	0.710	0.590	0.540	0.710	0.590	0.540	0.710
	TPR			0.395	0.320	0.460	0.395	0.320	0.460	0.395	0.320	0.460
	FDR			0.068	0.033	0.042	0.068	0.033	0.043	0.068	0.033	0.042
6	$P(gCD)$	0.760	0.570	0.950	0.960	0.980	0.950	0.960	0.980	0.950	0.960	0.980
	TPR			0.517	0.470	0.538	0.517	0.472	0.538	0.517	0.470	0.538
	FDR			0.061	0.067	0.067	0.061	0.069	0.067	0.061	0.067	0.067

Table 8: [Multiple changepoints] Comparison of gCU.5 and gCU1 with local tests obtained by combining the FDR controlling procedures BH, ABH and STS with minP, LR, and CU1 in m independent Poisson series of the form: $X_1, \dots, X_{\tau_1} \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_1)$, $X_{\tau_1+1}, \dots, X_{\tau_2} \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_2)$, $X_{\tau_2+1}, \dots, X_{\tau_3} \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_3)$ and $X_{\tau_3+1}, \dots, X_T \stackrel{i.i.d.}{\sim} \text{Pois}(\lambda_4)$ where $T = 50$ and $m = 200$. Tests are conducted at level $\alpha = 0.1$ and n_{cp} channels (among m) contain 3 changes at locations $\tau_1 = 10, \tau_2 = 20$ and $\tau_3 = 35$.

$\lambda_1 = 0.2, \lambda_2 = 0.5, \lambda_3 = 0.8, \lambda_4 = 1.4$												
n_{cp}		gCU.5	gCU1	minP BH	LR BH	CU1 BH	minP ABH	LR ABH	CU1 ABH	minP STS	LR STS	CU1 STS
0	$P(gCD)$	0.102	0.098	0.118	0.116	0.114	0.118	0.116	0.114	0.122	0.116	0.114
2	$P(gCD)$	0.210	0.266	0.598	0.594	0.614	0.598	0.594	0.614	0.602	0.596	0.614
	TPR			0.364	0.369	0.382	0.364	0.369	0.382	0.365	0.371	0.383
	FDR			0.100	0.095	0.095	0.100	0.095	0.095	0.105	0.097	0.097
4	$P(gCD)$	0.344	0.502	0.816	0.826	0.838	0.816	0.826	0.838	0.818	0.830	0.846
	TPR			0.429	0.435	0.460	0.430	0.435	0.460	0.431	0.439	0.468
	FDR			0.092	0.099	0.087	0.092	0.099	0.088	0.097	0.099	0.088
8	$P(gCD)$	0.782	0.856	0.968	0.972	0.984	0.968	0.974	0.984	0.970	0.976	0.984
	TPR			0.495	0.511	0.547	0.500	0.515	0.549	0.499	0.516	0.553
	FDR			0.098	0.097	0.092	0.098	0.100	0.094	0.100	0.101	0.095
$\lambda_1 = 0.2, \lambda_2 = 0.8, \lambda_3 = 0.5, \lambda_4 = 1.4$												
2	$P(gCD)$	0.182	0.186	0.468	0.464	0.500	0.468	0.464	0.502	0.474	0.466	0.504
	TPR			0.263	0.258	0.292	0.263	0.258	0.292	0.268	0.259	0.296
	FDR			0.099	0.097	0.098	0.099	0.097	0.100	0.101	0.098	0.098
4	$P(gCD)$	0.320	0.288	0.710	0.690	0.752	0.710	0.690	0.754	0.712	0.694	0.760
	TPR			0.295	0.289	0.336	0.295	0.289	0.337	0.300	0.292	0.340
	FDR			0.096	0.100	0.084	0.097	0.101	0.085	0.100	0.101	0.090
8	$P(gCD)$	0.738	0.640	0.908	0.890	0.934	0.910	0.890	0.934	0.912	0.890	0.940
	TPR			0.373	0.377	0.406	0.376	0.380	0.408	0.379	0.379	0.412
	FDR			0.096	0.098	0.095	0.096	0.098	0.097	0.098	0.099	0.099