

CONTROLLING THE FALSE DISCOVERY RATE IN STRUCTURAL SPARSITY: SPLIT KNOCKOFFS

BY YANG CAO^{1,*}, XINWEI SUN^{2,‡} AND YUAN YAO^{1,†}

¹ *Hong Kong University of Science and Technology*, *ycaoau@connect.ust.hk; †yuany@ust.hk

² *Microsoft Research Asia*, ‡xinsun@microsoft.com

Controlling the False Discovery Rate (FDR) in a variable selection procedure is critical for reproducible discoveries, which receives an extensive study in sparse linear models. However, in many scenarios, the sparsity constraint is not directly imposed on the parameters, but on a linear transformation of the parameters to be estimated. Examples can be found in total variations, wavelet transforms, fused LASSO, and trend filtering, etc. In this paper, we proposed a data adaptive FDR control in this structural sparsity setting, the *Split Knockoff* method. The proposed scheme relaxes the linear subspace constraint to its neighborhood, often known as variable splitting in optimization, that enjoys new statistical benefits. It yields orthogonal design and split knockoff matrices, that exhibit desired FDR control empirically in structural sparsity discovery, and improve the power of strong feature selection by enhancing the incoherence condition for model selection consistency. Yet, the split knockoff statistics fail to satisfy the exchangeability, a crucial property in the classical knockoff method for provable FDR control. To address this challenge, we introduce an almost supermartingale construction under a perturbation of exchangeability, that enables us to establish FDR control up to an arbitrarily small inflation that vanishes as the relaxed neighborhood enlarges. Simulation experiments show the effectiveness of split knockoffs with possible improvements over knockoffs in both FDR control and Power. An application to Alzheimer’s Disease study with MRI data demonstrates that the split knockoff method can disclose important lesion regions in brains associated with the disease and connections between neighboring regions of high contrast variations during disease progression.

CONTENTS

1	Introduction	2
1.1	Structural Sparsity and the False Discovery Rate	3
1.2	Generalized LASSO and Knockoffs	4
1.3	The Split Knockoff Method	4
1.3.1	An Example	4
1.3.2	Split LASSO and Orthogonal Knockoffs	5
1.3.3	Feature and Knockoff Significance Statistics	6
1.3.4	Calculation of Split Knockoff Statistics	6
1.4	FDR Control and Power	6
1.5	Organization of the paper	9
2	Split Knockoffs and Challenges for FDR Control	9
2.1	The Split Knockoffs	9
2.2	Failure of Exchangeability	10
3	FDR Control via Almost Supermartingale	11

MSC2020 subject classifications: Primary 62J05; Secondary 62F03.

Keywords and phrases: Split Knockoffs, Structural Sparsity, False Discovery Rate, Almost Supermartingale.

3.1	W^s and Its Properties	11
3.2	Almost Supermartingale Construction	12
4	Power and Path Consistency for Split LASSO	13
4.1	ν -Incoherence Condition	14
4.2	Path Consistency and Power	14
5	Simulation Experiments	15
5.1	Experimental Setting	15
5.2	Comparison of Split Knockoffs vs. Knockoffs in $D_1 = I_p$	15
5.3	Comparison of Split Knockoffs vs. Knockoffs in 1-D Fused LASSO D_2	15
5.4	Split Knockoffs in Mixed D_3	16
5.5	A Validation Choice of ν	16
5.6	Effects of Other Parameters	17
5.6.1	Effect of Feature Correlation	17
5.6.2	Effect of Signal-to-Noise Ratio	18
5.6.3	Effect of Sparsity Level	18
6	Application: Alzheimer's Disease	19
6.1	Dataset	19
6.2	Region Selection	20
6.3	Connection Selection	20
7	Conclusion and Future Directions	21
	References	21
A	Supplementary Material for Section 2	24
A.1	Construction of Split Knockoff Matrices	24
A.2	Failure of Exchangeability	25
B	Proof for Theorem 3.4	25
B.1	Transfer of FDR Bound	25
B.2	Almost Supermartingale Bound of Dominant Part	27
B.3	Estimate of Gaussian Tail Bound	27
B.4	FDR Bounds for Split Knockoffs	28
B.4.1	Split Knockoff	28
B.4.2	Split Knockoff+	28
C	Proof for Theorem 4.1	29
C.1	Primal-Dual Witness Property	30
C.2	Incoherence Condition and Path Consistency	31
D	Proof of Lemmas	32
D.1	Some Basic Lemmas	32
D.2	Proof for Lemma 3.1 (a)	36
D.3	Proof for Lemma 3.1 (b)	37
D.4	Proof for Lemma 3.2	37
D.5	Optional Stopping Lemma	40
D.6	Proof for Lemma 3.3	41
E	Matlab Package	42

1. Introduction. Variable selection or sparse model selection is a fundamental problem in statistical research. Equipped with the wide spread of modern data acquisition facilities, one can simultaneously measure a large number of covariates or features and it is desired to discover a relatively small amount of dominant factors governing the variations. In many scenarios, such a sparsity constraint does not always rely on a small number of measured covariates or features, but is about some transformations, often linear, of parameters. For instance, in signal processing such as images, sparsity of edges or jumps lies in wavelet transforms

(Donoho and Johnstone, 1995) or total variations (Rudin, Osher and Fatemi, 1992; Cai et al., 2012); in genomic studies of human cancer, sparsity in 1-D fused LASSO (Tibshirani et al., 2005) is associated with abnormality of copy numbers of genome orders in comparative genomic hybridization (CGH) data, a valuable way of understanding human cancer; in trend filtering (Kim et al., 2009), sparsity lies in the change point detection of piece-wise linear time series. In this paper, the sparsity associated with a linear transformation of parameters is called the *structural sparsity* and we study a data adaptive recovery of such structural sparsity in linear regression together with its accuracy in favor of reproducibility of discovery.

1.1. *Structural Sparsity and the False Discovery Rate.* The structural sparsity problem in linear regression is formulated in the following way:

$$(1a) \quad y = X\beta^* + \varepsilon,$$

$$(1b) \quad \gamma^* = D\beta^*,$$

where $y \in \mathbb{R}^n$ is the response vector, $X \in \mathbb{R}^{n \times p}$ is the design matrix, $\beta^* \in \mathbb{R}^p$ is the unknown coefficient vector, $\varepsilon \sim \mathcal{N}(0, \sigma^2 I_n)$ is Gaussian noise; $D \in \mathbb{R}^{m \times p}$ is the linear transformer, and $\gamma^* \in \mathbb{R}^m$ is the sparse vector. And the target for this model is to recover the support set of γ^* . For simplicity of notations, we define the nonnull set $S_1 = \text{supp}(\gamma^*) = \{i : \gamma_i^* \neq 0\}$, and the null set $S_0 = \{i : \gamma_i^* = 0\}$. Note that if we take $m = p$ and $D = I_p$, this model is degenerated into the standard sparse linear regression, therefore, this model can be viewed as an extension for the traditional sparse regression problem. To evaluate the accuracy of an empirically discovered set \hat{S} , the false discovery rate (FDR) is the goal of this paper in favor of the reproducibility of discoveries. Formally speaking, FDR of a selection set \hat{S} is defined as

$$\text{FDR} = \mathbb{E} \left[\frac{|\{i : i \in \hat{S} \cap S_0\}|}{|\hat{S}| \vee 1} \right].$$

The problem of controlling FDR has been widely studied since Benjamini and Hochberg (1995). In particular, Barber et al. (2015) recently proposed the knockoff method for sparse linear regression when $D = I_p$ in Equation (1b) with a theoretical guarantee of the upper bound of FDR.

The idea is to first make a knockoff copy of design matrix, \tilde{X} , that mimics the covariance of original features, but is much less correlated with the original features, i.e.

$$\tilde{X}^T \tilde{X} = X^T X, \quad X^T \tilde{X} = X^T X - \text{diag}(s),$$

where s is some proper non-negative vector. Take $[X, \tilde{X}]$ as a new design matrix, and compute a LASSO path for this joint optimize problem. Ideally, for nonnull features, the original feature coefficients shall appear earlier on the path or bigger in magnitudes than the knockoff feature coefficients; while for null features, the original coefficients and the knockoff coefficients have the same probability to be selected on the path. Such an exchangeability symmetry on null features and knockoffs leads to a beautiful supermartingale structure on knockoff filters that provably controls FDR. This work can be further applied to group sparse model, multi-task regression model (Dai and Barber, 2016), Huber's robust regression (Xu et al., 2016), and high dimensional setting (Barber et al., 2019). In particular, Candès et al. (2018) proposed Model-X knockoff for random design and showed in (Barber et al., 2020) that Model-X knockoff is robust to estimation error of random design parameters. Combined with generative adversarial networks, deep knockoff (Romano, Sesia and Candès, 2019) is developed for nonparametric random designs.

However, due to the constraint in Equation (1b), it is not clear how to apply such knockoff methods to structural sparsity except for some special cases which can be reduced to sparse linear regression. Below we first revisit the generalized LASSO with such special cases.

1.2. *Generalized LASSO and Knockoffs.* Within the large literature dealing with the structural sparsity problem, generalized LASSO (Tibshirani et al., 2011) is the most popular way to handle this structural sparsity problem. In some special cases, it can be converted to sparse linear regression where one can design knockoffs; yet in general, it is open how to do so.

Recall that the generalized LASSO solves the optimization problem below with $\lambda > 0$,

$$(2) \quad \min_{\beta} \frac{1}{2n} \|y - X\beta\|_2^2 + \lambda \|D\beta\|_1.$$

Particularly, if $\text{rank } D = m \leq p$, this problem can be equivalently represented by the following LASSO procedure with respect to $\lambda > 0$,

$$\min_{\gamma} \frac{1}{2n} \|y - XD^\dagger\gamma - XD_0\gamma_0\|_2^2 + \lambda \|\gamma\|_1,$$

where $D^\dagger \in \mathbb{R}^{p \times m}$ is the pseudo inverse for D , $D_0 \in \mathbb{R}^{p \times (p - \text{rank } D)}$ is a matrix whose columns spans the $\ker(D)$, and $\gamma_0 \in \mathbb{R}^{p - \text{rank } D}$ is the representation coefficient for the null space $\ker(D)$ without sparsity. Note that we can write $\beta^* = D^\dagger\gamma^* + D_0\gamma_0^*$ for some $\gamma_0^* \in \mathbb{R}^{p - \text{rank } D}$, and Equation (1) becomes simply

$$y = XD^\dagger\gamma^* + XD_0\gamma_0^* + \varepsilon.$$

In this special case of $\text{rank } D = m \leq p$, one can construct knockoffs like standard sparse linear regression (Xu et al., 2016). To see this, Take $U \in \mathbb{R}^{n \times (n - p + \text{rank } D)}$ as an orthogonal complement for the column space of $XD_0 \in \mathbb{R}^{n \times (p - \text{rank } D)}$, we have

$$(3) \quad U^T y = U^T XD^\dagger\gamma^* + U^T \varepsilon.$$

We can treat $U^T XD^\dagger$ as a new design matrix, $U^T y$ as the response vector and $U^T \varepsilon \sim \mathcal{N}(0, I_{n - p + \text{rank } D})$ as the Gaussian noise. Then the problem is transferred to a sparse linear regression problem and we can apply the standard knockoff method with FDR control.

However, this simple scheme can not be directly applied to the setting $m > p$. If $m > p$, design matrix $U^T XD^\dagger \in \mathbb{R}^{(n - p + \text{rank } D) \times m}$ can not be of full column rank as $D^\dagger \in \mathbb{R}^{p \times m}$ is of maximum rank $p < m$, which causes the identifiable issue of the model. Moreover, the incoherence requirements for sparse recovery or model selection consistency (Donoho and Huo, 2001; Tropp, 2004; Zhao and Yu, 2006; Wainwright, 2009; Osher et al., 2016; Huang et al., 2020) may fail for the design matrix $U^T XD^\dagger$, especially when D is nontrivial and/or X is highly co-related, which may lead to poor power.

To the best of our knowledge, it is still an open problem how to design the knockoffs for the general structural sparsity scenario yet. Below, we are going to present a method based on variable splitting idea that relaxes the linear subspace constraint (1b) to its neighborhood.

1.3. *The Split Knockoff Method.* First of all, we present an example of our Split Knockoff method applied to some typical structural sparsity problems, competitive or better than the standard Knockoff method (Barber et al., 2015) when applicable.

1.3.1. *An Example.* Take $n = 350$, $p = 100$, we generate $X \in \mathbb{R}^{n \times p}$ i.i.d. from $\mathcal{N}(0_p, \Sigma)$, where $\Sigma_{i,j} = c^{|i-j|}$ with feature correlation $c = 0.5$. We take $\beta^* \in \mathbb{R}^p$, where

$$\beta_i := \begin{cases} -A & i \leq k, i \equiv 1 \pmod{3} \\ A & i \leq k, i \equiv 0, -1 \pmod{3} \\ 0 & i > k \end{cases}.$$

Here we take $A = 1$, $k = 20$, and $\varepsilon \in \mathbb{R}^n$ is generated i.i.d. from $\mathcal{N}(0, 1)$. Then we calculate the response vector $y = X\beta^* + \varepsilon \in \mathbb{R}^n$.

In comparison of Split Knockoff and Knockoff, as discussed in Section 1.2, we will consider the special case $m \leq p$ here. For $m > p$ case, we only show the results for Split Knockoff. Now consider the following three types of structural sparsity.

1. Define $D_1 = I_p \in \mathbb{R}^{p \times p}$, where in this case the structural sparsity problem has degenerated to normal sparsity problems for regression.
2. Define $D_2 \in \mathbb{R}^{(p-1) \times p}$ as the graph difference operator for a line: $D_2(i, i) = 1$, $D_2(i, i + 1) = -1$ for $1 \leq i \leq p - 1$; and $D_2(i, j) = 0$ for other pairs of (i, j) .
3. Define $D_3 = [I_p, D_2^T]^T \in \mathbb{R}^{(2p-1) \times p}$, where in this case $m = 2p - 1 > p$.

Then we conduct the simulation experiments 20 times for D_1 , D_2 and D_3 respectively. The result is shown in Table 1, whose details will be discussed in Section 5.

TABLE 1
Results for Knockoff and Split Knockoff: Power and FDR for $q = 0.2$.

	$\gamma^* = D_1\beta^*$		$\gamma^* = D_2\beta^*$		$\gamma^* = D_3\beta^*$
	Knockoff	Split Knockoff	Knockoff	Split Knockoff	Split Knockoff
FDR	0.2011 (0.1075)	0.0266 (0.0636)	0.3510 (0.3206)	0.0401 (0.0788)	0.0248 (0.0326)
Power	1.0000 (0.0000)	1.0000 (0.0000)	0.4179 (0.4237)	1.0000 (0.0000)	0.9956 (0.0108)

As we can see from the table, Split Knockoff can always achieve desired result in this setting, in both $m > p$ and $m \leq p$ cases. What's more, it has lower FDR and higher power compared with the Knockoff method in $m \leq p$ case.

How do we design this Split Knockoff method and why does it work well in FDR control and power, even better than Knockoffs? Below we are going to explain this.

1.3.2. *Split LASSO and Orthogonal Knockoffs.* Our departure from generalized LASSO lies in the relaxation of linear constraint in (1b) to an unconstrained optimization, called as *Split LASSO* in this paper,

$$(4) \quad \min_{\beta, \gamma} \frac{1}{2n} \|y - X\beta\|_2^2 + \frac{1}{2\nu} \|D\beta - \gamma\|_2^2 + \lambda \|\gamma\|_1, \quad \lambda > 0,$$

where $\nu > 0$ is a parameter to control the Euclidean gap between $D\beta$ and γ . In other words, we shall allow model parameters varied in the neighborhood of the linear subspace $D\beta = \gamma$, where the larger is ν , the larger is the relaxation neighborhood. Such a ν -relaxation helps decouple γ and $D\beta$, leading to an orthogonal design (identity matrix) for γ . As a result, it enhances the power in finding strong features by improving the incoherence condition, at a possible cost of losing weak features (see Section 4 for details). In particular, it leads to *orthogonal Split Knockoff* features.

To construct split knockoff features, we rewrite the structural sparsity model (1) as the following linear regression in joint parameter (β^*, γ^*) space with heterogeneous noise:

$$(5) \quad \tilde{y} = A_\beta \beta^* + A_\gamma \gamma^* + \tilde{\varepsilon},$$

where

$$\tilde{y} = \begin{pmatrix} y \\ \frac{y}{\sqrt{n}} \\ 0_m \end{pmatrix}, A_\beta = \begin{pmatrix} X \\ \frac{X}{\sqrt{n}} \\ \frac{D}{\sqrt{\nu}} \end{pmatrix}, A_\gamma = \begin{pmatrix} 0_{n \times m} \\ -\frac{I_m}{\sqrt{\nu}} \\ 0_m \end{pmatrix}, \tilde{\varepsilon} = \begin{pmatrix} \varepsilon \\ \frac{\varepsilon}{\sqrt{n}} \\ 0_m \end{pmatrix}.$$

For linear regression (5), the only sparse parameter is γ^* , therefore we only construct the knockoff copy for its design matrix A_γ . Specifically, a *Split Knockoff* matrix, \tilde{A}_γ , must satisfy

$$(6a) \quad \tilde{A}_\gamma^T \tilde{A}_\gamma = A_\gamma^T A_\gamma = \frac{I_m}{\nu},$$

$$(6b) \quad A_\gamma^T \tilde{A}_\gamma = A_\gamma^T A_\gamma - \text{diag}(\mathbf{s}) = \frac{I_m}{\nu} - \text{diag}(\mathbf{s}),$$

$$(6c) \quad A_\beta^T \tilde{A}_\gamma = A_\beta^T A_\gamma = -\frac{D^T}{\nu},$$

where $\mathbf{s} \in \mathbb{R}^m$ is some non-negative vector. The Split Knockoff matrix, \tilde{A}_γ , is thus an *orthogonal matrix*, that imitates the covariance of original features A_γ , but are decorrelated with the original features as much as possible. In particular, the existence of the nonsparse intercept features further require in Equation (6c) that \tilde{A}_γ imitates the covariance structure between A_γ and A_β . Explicit solutions of Equation (6) will be characterized in Section 2. We denote $\tilde{A}_\gamma^T = [\tilde{A}_{\gamma,1}^T, \tilde{A}_{\gamma,2}^T]^{m \times (n+m)}$ as a partition into two blocks of column size n and m , respectively.

1.3.3. Feature and Knockoff Significance Statistics. The most important construction in our method lies in the following definition of feature significance and knockoff significance (Z_i, \tilde{Z}_i) . We departure from the standard Knockoff method (Barber et al., 2015) by splitting these statistics into three stages as shown in Table 2. For simplicity, we use LASSO regularization path to illustrate our idea. This approach can be also applied to other methods such as elastic net (Zou and Hastie, 2005) and dynamic regularization paths (Osher et al., 2016; Huang et al., 2020; Yao, Rosasco and Caponnetto, 2007).

1.3.4. Calculation of Split Knockoff Statistics. Once we have the new definitions of these crucial statistics Z and \tilde{Z} , the remaining will be the same as the standard knockoff method.

- Define

$$(9) \quad W_i := \text{sign}(Z_i - \tilde{Z}_i)(Z_i \vee \tilde{Z}_i).$$

- (Split Knockoff/Split Knockoff+) As we wish to select i when W_i is large and positive. Let q be our target FDR, the data-dependent threshold based on a pre-set nominal level q is defined as

$$\text{(Split Knockoff)} \quad T_q = \min \left\{ \lambda : \frac{|\{i : W_i \leq -\lambda\}|}{1 \vee |\{i : W_i \geq \lambda\}|} \leq q \right\},$$

or

$$\text{(Split Knockoff+)} \quad T_q = \min \left\{ \lambda : \frac{1 + |\{i : W_i \leq -\lambda\}|}{1 \vee |\{i : W_i \geq \lambda\}|} \leq q \right\},$$

or $T_q = +\infty$ if this set is empty. And in both cases, the selector is defined as

$$\hat{S} = \{i : W_i \geq T_q\}.$$

1.4. FDR Control and Power. The main challenge in establishing the FDR control of Split Knockoffs lies in the failure of exchangeability here. In fact, a rigorous formalization for exchangeability requires the following pairwise exchangeability for responses Barber et al. (2015),

$$[A_\beta, [A_\gamma, \tilde{A}_\gamma]_{\text{swap}\{S_0\}}]^T \tilde{\mathbf{y}} \stackrel{d}{=} [A_\beta, A_\gamma, \tilde{A}_\gamma]^T \tilde{\mathbf{y}}.$$

TABLE 2
Feature and Knockoff Significance statistics (Z, \tilde{Z}) for Split Knockoffs

Stage 0: Intercept Assignment ($\beta(\lambda)$).

The choice should make $\beta_\nu(\lambda)$ a continuous function with respect to $\lambda > 0$ and a sufficient statistics as

$$\beta_\nu(\lambda) = f(X^T y, X, D).$$

A natural choice is the solution path $\beta_\nu(\lambda)$ of Split LASSO (4). Abusing the notation, in the sequel we simply denote $\beta(\lambda)$ while keeping in mind that it may implicitly depend on ν , similarly for $\gamma(\lambda)$ and $\tilde{\gamma}(\lambda)$ below.

Stage 1: Feature Significance (Z).

1. Compute the Split LASSO regularization path for γ ,

$$(7) \quad \gamma(\lambda) := \arg \min_{\gamma} \frac{1}{2} \|\tilde{y} - A_\beta \beta(\lambda) - A_\gamma \gamma\|_2^2 + \lambda \|\gamma\|_1, \quad \lambda > 0.$$

2. Define the feature significance as the maximal $\lambda > 0$ on the regularization path $\gamma(\lambda)$ such that $\gamma_i(\lambda)$ is nonzero and record the sign of $\gamma_i(\lambda)$ upon being nonzero:

$$Z_i = \sup \{\lambda : \gamma_i(\lambda) \neq 0\}, \quad r_i = \lim_{\lambda \rightarrow Z_i^-} \text{sign} \gamma_i(\lambda).$$

Stage 2: Knockoff Significance (\tilde{Z}).

1. Compute the Split LASSO regularization path for $\tilde{\gamma}$,

$$(8) \quad \tilde{\gamma}(\lambda) := \arg \min_{\tilde{\gamma}} \frac{1}{2} \|\tilde{y} - A_\beta \beta(\lambda) - \tilde{A}_\gamma \tilde{\gamma}\|_2^2 + \lambda \|\tilde{\gamma}\|_1, \quad \lambda > 0.$$

2. Define the knockoff significance as the maximal $\lambda > 0$ on the regularization path $\tilde{\gamma}(\lambda)$ such that $\tilde{\gamma}_i(\lambda)$ is nonzero and record the sign of $\tilde{\gamma}_i(\lambda)$ upon being nonzero:

$$Z'_i = \sup \{\lambda : \tilde{\gamma}_i(\lambda) \neq 0\}, \quad r'_i = \lim_{\lambda \rightarrow Z'_i^-} \text{sign} \tilde{\gamma}_i(\lambda).$$

3. To get \tilde{Z} we do a truncation on Z' , i.e.

$$\tilde{Z} = Z' \cdot 1_{\{r_i = r'_i\}}.$$

In other words, we only consider a knockoff significant if its emerging sign on path meets that of the corresponding feature.

However, note that in our case

$$A_\gamma^T \tilde{y} = 0, \quad \tilde{A}_\gamma^T \tilde{y} = \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}} X \beta^* + \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}} \varepsilon,$$

where $A_\gamma^T \tilde{y} = 0$ does not equal to the noise $\zeta := \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}} \varepsilon$, therefore for any $i \in S_0$, swapping the i -th element in the second block with the i -th one in the third block results in different distributions. The perturbation of noise ζ thus breaks the exchangeability, a crucial property in classical knockoffs (Barber et al., 2015) that enables us a supermartingale argument for FDR control. Without it, one has to look for a new approach to the FDR control.

In this paper, the Split Knockoffs exploit the orthogonal designs in A_γ and \tilde{A}_γ , leading to some new statistics with approximate exchangeability as ν grows, resulting in an *almost*

supermartingale construction. This enables us to establish an inflated FDR control whose inflation can be arbitrarily small provided that the parameter ν is properly chosen. To be specific, the following informal statement of FDR control theorem (see details in Theorem 3.4) is established for the selectors above. For Split Knockoff, we control a “modified” FDR that adds q^{-1} in the denominator, which should have little effect if a large number of features are selected; for Split Knockoff+, we get the exact FDR control.

THEOREM 1.1 (FDR Control of Split Knockoffs). *For any $\alpha > 0$, there exists $\nu > 0$, s.t.*

(a) (*Modified FDR of Split Knockoff*)

$$\mathbb{E} \left[\frac{|\{i : i \in \hat{S} \cap S_0\}|}{|\hat{S}| + q^{-1}} \right] \leq q(1 + \alpha).$$

(b) (*FDR of Split Knockoff+*)

$$\mathbb{E} \left[\frac{|\{i : i \in \hat{S} \cap S_0\}|}{|\hat{S}| \vee 1} \right] \leq q(1 + \alpha).$$

REMARK. In Section 3 we present the formal theorem with characterization of α and ν .

To illustrate the intuition behind these results, we select a simulation instance of D_1 in the example above, where we compare Knockoff and Split Knockoff in their feature selections. We plot (Z_i, \tilde{Z}_i) for each feature in Figure 1 for a comparison, where the case of Knockoff is shown in (a), and (b) exhibits that of Split Knockoff.




FIG 1. Comparison between Knockoff and Split Knockoff ($D = D_1$)

Recall that W_i is positive if $Z_i > \tilde{Z}_i$; W_i is negative if $\tilde{Z}_i > Z_i$. For Knockoff, we can see from Figure 1(a) that the points (Z_i, \tilde{Z}_i) of null i are nearly symmetrically distributed w.r.t. the line $Z = \tilde{Z}$, which implies for any threshold t

$$|\{i : \gamma_i = 0, W_i \geq t\}| \stackrel{d}{=} |\{i : \gamma_i = 0, W_i \leq -t\}|.$$

However, for Split Knockoff, we can see from Figure 1(b) that although for null i , the signs of W_i are nearly symmetrically distributed, the magnitudes of W_i are not symmetric around the diagonal. That is, $|W_i|$ tends to be larger when $W_i < 0$ compared with $W_i > 0$, which implies for sufficiently large threshold T_q that matters for small q

$$|\{i : \gamma_i = 0, W_i \geq T_q\}| \ll |\{i : \gamma_i = 0, W_i \leq -T_q\}|.$$

Therefore informally we have

$$\frac{|\{i : \gamma_i = 0, W_i \geq T_q\}|}{|\{i : W_i \geq T_q\}| \vee 1} \llcorner \frac{|\{i : \gamma_i = 0, W_i \leq -T_q\}|}{|\{i : W_i \geq T_q\}| \vee 1} \leq \frac{|\{i : W_i \leq -T_q\}|}{|\{i : W_i \geq T_q\}| \vee 1} =: \widehat{\text{FDR}},$$

where the last step is our empirical FDR estimate. Here the rise of \tilde{Z}_i in Split Knockoff increases the possibility of $W_i < -t$ for a given threshold $t > 0$, that gives a tighter control on the FDR of Split Knockoff. This phenomenon gives us an intuitive explanation of why Split Knockoff tends to work better than the classical Knockoff in practice.

However a rigorous treatment of FDR control for Knockoff requires a martingale structural, which no longer exists for Split Knockoff due to the failure of exchangeability. To overcome this hurdle, we construct an *almost supermartingale* structure to achieve an inflated FDR control, whose details will be introduced in Section 3.

The influence of ν has two aspects, one on the FDR control as shown above, the other on the power to be discussed below. The influence of ν on power is of two folds. On one hand, increasing ν may increase the power of discovering strong nonnull features whose magnitudes are large. It is because that enlarging ν will improve the incoherence condition of the Split LASSO (4) such that strong nonnull features will appear earlier on the path than the weak ones and nulls. On the other hand, increasing ν may lose the power of discovering weak nonnull features whose magnitudes are small. So a proper choice of ν depends on a trade-off and empirically cross-validation provides us a good answer. This will be discussed in details in the study of path consistency in Section 4 and experiments in Section 5.

1.5. Organization of the paper.

- In Section 2, we show the explicit construction of Split Knockoff copies, and demonstrate the main challenge for provable FDR control, the failure of exchangeability.
- In Section 3, we provide a guideline on achieving theoretical FDR control for Split Knockoffs, using an almost supermartingale construction.
- In Section 4, we discuss the influence of ν on the power of Split Knockoffs, through the path consistency property for Split LASSO regularization paths.
- In Section 5, we present results for simulation experiments and compare the performance of Split Knockoffs against Knockoffs.
- In Section 6, we apply Split Knockoffs to an application problem in discovering the lesion regions in brains for Alzheimer's Disease.

Details for proofs and experimental codes are provided in supplementary material sections.

2. Split Knockoffs and Challenges for FDR Control. In this section, we will provide some preliminaries on the FDR control of Split Knockoffs. In Section 2.1, we show the explicit construction of the Split Knockoff copy satisfying Equation (6). In Section 2.2, we demonstrate the main challenge that we are faced to achieve provable FDR control, the failure of exchangeability, a crucial property for theoretical FDR control in classical Knockoffs.

2.1. *The Split Knockoffs.* We will first discuss the existence and an explicit form of the split knockoff matrix \tilde{A}_γ , shown in the following proposition.

PROPOSITION 2.1 (Split Knockoff Matrix). *For any vector s in Equation (6) satisfying*

$$(10a) \quad \text{diag}(s) \succeq 0,$$

$$(10b) \quad 2C_\nu - \text{diag}(s) \succeq 0,$$

where $C_\nu := \Sigma_{\gamma,\gamma} - \Sigma_{\gamma,\beta} \Sigma_{\beta,\beta}^\dagger \Sigma_{\beta,\gamma}$, $\Sigma_{\beta,\beta} := A_\beta^T A_\beta$, $\Sigma_{\beta,\gamma} = \Sigma_{\gamma,\beta}^T := A_\beta^T A_\gamma$, and $\Sigma_{\gamma,\gamma} := A_\gamma^T A_\gamma$, there is a valid Split Knockoff matrix for $n \geq m + p$,

$$(10c) \quad \tilde{A}_\gamma = A_\gamma(I_m - C_\nu^{-1} \text{diag}(\mathbf{s})) + A_\beta \Sigma_{\beta,\beta}^{-1} \Sigma_{\beta,\gamma} C_\nu^{-1} \text{diag}(\mathbf{s}) + \tilde{U} K,$$

where $\tilde{U} \in \mathbb{R}^{(n+m) \times m}$ is the orthogonal complement of $[A_\beta, A_\gamma]$ and $K \in \mathbb{R}^{m \times m}$ satisfies $K^T K = 2\text{diag}(\mathbf{s}) - \text{diag}(\mathbf{s}) C_\nu^{-1} \text{diag}(\mathbf{s})$.

One way to construct such a split knockoff matrix is to take $s_i = (2 - \eta) \lambda_{\min}(C_\nu) \wedge \frac{1}{\nu} := s$ for all $i \in \{1, 2, \dots, m\}$, where $\eta > 0$ is a suitable parameter. Since $\tilde{U} \in \mathbb{R}^{(n+m) \times m}$ here is an orthogonal complement of $[A_\beta, A_\gamma] \in \mathbb{R}^{(n+m) \times (m+p)}$, it requires $n \geq m + p$. Proof for Proposition 2.1 and other constructions of split knockoffs are shown in Section A.1.

2.2. Failure of Exchangeability. Now we introduce the main challenge we are faced with: the exchangeability property of classical Knockoffs fails in Split Knockoffs. Firstly, the split knockoff statistics W shall satisfy the following sufficiency property similarly with the classical knockoff method.

DEFINITION 2.1 (Sufficiency Property). The split knockoff statistics $W \in \mathbb{R}^m$ is said to obey the sufficiency property if W can be written as

$$W = f([A_\beta, A_\gamma, \tilde{A}_\gamma]^T [A_\beta, A_\gamma, \tilde{A}_\gamma], [A_\beta, A_\gamma, \tilde{A}_\gamma]^T \tilde{y}),$$

for some $f: (\mathbf{S}_{p+2m}^+, \mathbb{R}^{p+2m}) \rightarrow \mathbb{R}^m$, where \mathbf{S}_{p+2m}^+ is the cone of $(p+2m) \times (p+2m)$ positive semidefinite matrices.

In addition to the sufficiency property, the classical Knockoff also satisfies an important property called exchangeability with formal definition stated below.

DEFINITION 2.2. Let $\epsilon_i = 1$ for nonnull i , and $\epsilon_i \stackrel{\text{i.i.d.}}{\sim} \{\pm 1\}$ for null i . W is said to obey exchangeability if and only if

$$(11) \quad (W_1, \dots, W_m) \stackrel{d}{=} (W_1 \epsilon_1, \dots, W_m \epsilon_m).$$

In order to achieve this exchangeability property, Barber et al. (2015) (Lemma 2-3) established pairwise exchangeability for both features and responses, the latter of which however fails in Split Knockoffs.

PROPOSITION 2.2 (Failure of Pairwise Exchangeability). For any $S \subseteq S_0$, there holds

$$(12a) \quad [A_\beta, [A_\gamma, \tilde{A}_\gamma]_{\text{swap}\{S\}}]^T [A_\beta, [A_\gamma, \tilde{A}_\gamma]_{\text{swap}\{S\}}] = [A_\beta, A_\gamma, \tilde{A}_\gamma]^T [A_\beta, A_\gamma, \tilde{A}_\gamma],$$

$$(12b) \quad [A_\beta, [A_\gamma, \tilde{A}_\gamma]_{\text{swap}\{S\}}]^T \tilde{y} \stackrel{d}{\neq} [A_\beta, A_\gamma, \tilde{A}_\gamma]^T \tilde{y},$$

where $[A_\gamma, \tilde{A}_\gamma]_{\text{swap}\{S\}}$ denotes a swap of the j -th column of A_γ and \tilde{A}_γ in $[A_\gamma, \tilde{A}_\gamma]$ for $j \in S$.

In other words, for Split Knockoffs, while pairwise exchangeability for features holds in (12a), that for responses fails in (12b). This is due to that in Split Knockoffs

$$A_\gamma^T \tilde{y} = 0, \quad \tilde{A}_\gamma^T \tilde{y} = -\text{diag}(\mathbf{s}) \gamma^* + \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}} \varepsilon,$$

where swapping 0 with noise $\zeta = \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}}\varepsilon$ changes distributions. See Section A.2 for details.

The failure of exchangeability can be a huge theoretical challenge for knockoffs. Without exchangeability, we will not have the beautiful symmetry results on split knockoff statistics. For random design, Barber et al. (2020) exploits KL divergence to measure the “distance” to exchangeability, and then gives approximate but not exact FDR control based on the “distance”. It is also worth to mention that this method no longer relies on the martingale arguments and use direct analysis. However, to the best of our knowledge, no provable results have been provided for fixed design.

Below, we introduce a new way to deal with this challenge in the structural sparsity setting. Our approach exploits the orthogonal design of γ and makes an effort to decouple the magnitudes and signs of W_i , that leads to an almost supermartingale structure for the FDR bound.

3. FDR Control via Almost Supermartingale. In this section, we will introduce our way to achieve provable FDR control via an almost supermartingale construction. First of all, following the standard steps in knockoffs (see Section B.1), we can transfer the upper bound of FDR into the upper bound of $\mathbb{E}[\mathcal{M}_{T_q}(W)]$ where

$$(13) \quad \mathcal{M}_T(W) = \frac{\sum_{i \in S_0} 1\{W_i \geq T\}}{1 + \sum_{i \in S_0} 1\{W_i \leq -T\}}.$$

However due to the failure of exchangeability, $\mathcal{M}_{T_q}(W)$ is no longer a supermartingale with stopping time T_q . To address this challenge, we are going to find some alternative statistics that give an upper bound and behave like a supermartingale at the same time. In the below, we give a new statistics W^s such that

- (a) $\mathcal{M}_{T_q}(W^s)$ provides an upper bound $\mathcal{M}_{T_q}(W) \leq \mathcal{M}_{T_q}(W^s)$, where the length of W_i^s is decoupled with its sign, approximately a Bernoulli random variable of about 1/2 probability;
- (b) $\mathcal{M}_{T_q}(W^s)$ leads to an almost supermartingale construction with stopping time T_q , where the optional stopping theorem leads to an upper bound for the FDR control up to an arbitrarily small inflation factor.

3.1. *W^s and Its Properties.* To establish upper bounds for (13), define W^s as follows,

$$(14) \quad W_i^s := \text{sign}(Z_i - \tilde{Z}_i) \cdot Z_i,$$

for $i \in \{1, 2, \dots, m\}$. Comparing the definition of W (9) and the definition of W^s (14), we have for $W_i > 0$, $W_i = Z_i = W_i^s$, and for $W_i < 0$, $W_i = -\tilde{Z}_i \leq -Z_i = W_i^s$, while W_i shares the same sign with W_i^s . Therefore,

$$(15) \quad \mathcal{M}_{T_q}(W) = \frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 + \sum_{i \in S_0} 1\{W_i \leq -T_q\}} \leq \frac{\sum_{i \in S_0} 1\{W_i^s \geq T_q\}}{1 + \sum_{i \in S_0} 1\{W_i^s \leq -T_q\}} =: \mathcal{M}_{T_q}(W^s).$$

Below we are going to show that the right hand side above, $\mathcal{M}_{T_q}(W^s)$ leads to an *almost supermartingale* with respect to stopping time T_q that enables us to establish an upper bound for FDR up to an inflation factor. Before presenting this, we first visit some key properties of W^s .

Note that Z_i are statistics determined by $[A_\beta^T \tilde{y}, A_\gamma^T \tilde{y}]$ with $A_\gamma^T \tilde{y} = 0$ in our construction. Therefore conditional on $A_\beta^T \tilde{y}$, the sign of W_i is decoupled from the magnitude $|W_i|$, determined by the sign of $\zeta_i r_i$ shown in Lemma 3.1(a); moreover, $\zeta_i r_i$ is almost symmetric at the origin, such that $\mathbb{P}(\zeta_i r_i > 0) \approx \mathbb{P}(\zeta_i r_i < 0)$ whose deviation is bounded by a factor $g(\kappa, \nu)$ which vanishes as ν grows, shown in Lemma 3.1(b).

LEMMA 3.1. Denote $\xi := A_\beta^T \tilde{y} = \frac{X^T y}{n}$ and $\zeta := \frac{\tilde{A}_{\gamma_{i+1}}^T}{\sqrt{n}} \varepsilon$. For any $\kappa > 0$, let

$$(16) \quad \Lambda_{\nu, \kappa} := \left\{ \left\| -[\text{diag}(\mathbf{s})D][\Sigma_X]^{-1}(\xi - \Sigma_X \beta^*) \right\|_\infty < \kappa s \sigma \frac{1}{\sqrt{n}}, \left\| \zeta \right\|_\infty < \kappa \sqrt{s} \sigma \frac{1}{\sqrt{n}} \right\}.$$

- (a) For all $i \in S_0$, $\text{sign}(W_i) = \text{sign}(\zeta_i r_i)$.
(b) For all i , there holds

$$(17) \quad \left| \mathbb{P}(\zeta_i r_i < 0 | \zeta_{-i}, \xi) - \frac{1}{2} \right| \leq g(\kappa, \nu),$$

conditional on $\Lambda_{\nu, \kappa}$, where $g(\kappa, \nu)$ is a function that satisfies $g(\kappa, \nu) \rightarrow 0$ when $\nu \rightarrow \infty$.

REMARK. Details on definition of $g(\kappa, \nu)$ will be given in Section D.3, Equation (46). Note that ξ and ζ are both multivariate Gaussian random vectors, such that $\mathbb{E}[\xi] = \Sigma_X \beta^*$, $\mathbb{E}[\zeta] = 0$, $\text{var}[\xi] = \frac{\sigma^2 \Sigma_X}{n}$ and $\text{var}[\zeta] = \frac{\sigma^2 (2s - \nu s^2)}{n} I_m$. The conditional distribution of $\zeta | \xi$ is also Gaussian, such that

$$\begin{aligned} \mathbb{E}(\zeta | \xi) &= -\text{diag}(\mathbf{s}) D \Sigma_X^{-1} (\xi - \mathbb{E}[\xi]), \\ \text{var}(\zeta | \xi) &= \frac{\sigma^2}{n} ((2s - s^2 \nu) I_m - s^2 D \Sigma_X^{-1} D^T). \end{aligned}$$

The constraint (16) on ξ and ζ is to rule out a Gaussian tail whose width is controlled by κ to avoid extreme cases, such that (17) holds except for an exponentially small probability. For example, it suffices to take $\kappa \sim \ln \nu$ in our case.

3.2. *Almost Supermartingale Construction.* The properties of W^s lead to the following construction that

$$(19) \quad \mathcal{M}_T(W^s) = \frac{\sum_{i \in S_0} 1\{W_i^s \geq T\}}{1 + \sum_{i \in S_0} 1\{W_i^s \leq -T\}},$$

is an *almost supermartingale* with respect to T , whose inflation or growth factor w.r.t. a supermartingale is bounded by $g(\kappa, \nu)$, that vanishes as ν grows.

LEMMA 3.2 (Almost Supermartingale Construction). Define T_k^s to be random variable takes the value of the k -th largest $|W_i^s|$ for $i \in S_0$. For $1 \leq k \leq |S_0|$, define

$$x_{|S_0|+1-k}^s = \frac{\sum_{i \in S_0} 1\{W_i^s \geq T_k^s\}}{1 + \sum_{i \in S_0} 1\{W_i^s \leq -T_k^s\}},$$

with filtration $F_{|S_0|+1-k}^s$ defined as the σ -field of:

1. all W_i for $i \in S_1$.
2. all W_i for $i \in S_0$, s.t. $|W_i^s| < T_k^s$.
3. $V_s^+(k) = \sum_{i \in S_0} 1\{W_i^s \geq T_k^s\}$ and $V_s^-(k) = \sum_{i \in S_0} 1\{W_i^s \leq -T_k^s\}$.

Conditional on $\Lambda_{\nu, \kappa}$ in (16), for $1 \leq k \leq |S_0|$,

$$\mathbb{E}[x_{k+1}^s | F_k^s] \leq (1 + g(\kappa, \nu)) x_k^s,$$

where $g(\kappa, \nu)$ is a function that satisfies $g(\kappa, \nu) \rightarrow 0$ when $\nu \rightarrow \infty$.

REMARK. The order of increasing the index k of x_k^s is equivalent to the order of increasing T of $\mathcal{M}_T(W^s)$. This construction can be viewed as a discrete version of (19). Specially, T_q corresponds with $\hat{k}_q^s = |S_0| + 1 - \text{argmax}_i \{T_i^s \geq T_q\}$ in this case. Here, W_i and W_i^s are determined by (ξ, ζ_i) , and $|W_i^s| = Z_i$ is determined by ξ .

The filtration of almost supermartingale in (19) at T contains information of those W_i of all nonnulls ($\{W_i : i \in S_1\}$) and weak nulls whose $|W_i^s|$ are below T ($\{W_i : i \in S_0, |W_i^s| < T\}$), as well as the total counts of different signs of W_i^s whose magnitudes are above T ($V_s^\pm = \#\{\text{sign}(W_i^s) = \pm 1 : i \in S_0, |W_i^s| \geq T\}$).

Such a filtration makes T_q a stopping time for almost supermartingale (19). Therefore, by optional stopping theorem (see Lemma D.4, e.g.), the expectation of the right hand side of Equation (15) can be bounded by pushing T_q to 0,

$$(20) \quad \mathbb{E}[\mathcal{M}_{T_q}(W^s)] \leq (1 + g(\kappa, \nu))^{|S_0|-1} \mathbb{E}[\mathcal{M}_0(W^s)].$$

It remains to bound the right hand side of (20), $\mathbb{E}[\mathcal{M}_0(W^s)]$. The following lemma characterizes such a bound as a result from the fact that $\sum_{i \in S_0} 1\{W_i^s > 0\}$ approximately follows Binomial distribution $\mathcal{B}(|S_0|, \frac{1}{2})$, shown in Lemma 3.1 (b).

LEMMA 3.3. *Conditional on $\Lambda_{\nu, \kappa}$ in (16), there holds*

$$\mathbb{E}[\mathcal{M}_0(W^s)] = \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i^s > 0\}}{1 + \sum_{i \in S_0} 1\{W_i^s < 0\}} \right] \leq (1 + g(\kappa, \nu))^{2|S_0|}.$$

Now is an opportune time to establish our main theorem on upper bounds of FDR, by combining the Lemma 3.3 together with the tail distribution of event $\Lambda_{\nu, \kappa}$.

THEOREM 3.4 (FDR Control of Split Knockoff). *For any $\alpha > 0$, there exists $\nu > 0$, s.t. the following holds:*

(a) (Knockoff) the modified FDR

$$\mathbb{E} \left[\frac{|\{i : i \in \hat{S} \cap S_0\}|}{|\hat{S}| + q^{-1}} \right] \leq q(1 + \alpha),$$

(b) (Knockoff+) the FDR

$$\mathbb{E} \left[\frac{|\{i : i \in \hat{S} \cap S_0\}|}{|\hat{S}| \vee 1} \right] \leq q(1 + \alpha),$$

where ν satisfies $q(1 + g(\kappa, \nu))^{3|S_0|-1} + p \left[2 - 2\Phi\left(\frac{\kappa}{M_{X,D}}\right) \right] + m(2 - 2\Phi(\kappa)) - 1 \leq \alpha$. Here $\Phi(x)$ is the distribution function for standard normal distribution $\mathcal{N}(0, 1)$ and $M_{X,D} := \|D[\Sigma_X]^{-\frac{1}{2}}\|_\infty$.

The full proof of this theorem will be given in Section B. All the lemmas will be proved in Section D.

4. Power and Path Consistency for Split LASSO. In this section, we discuss the influence of ν on the power of Split Knockoffs. There are two folds of such influences. On one hand, enlarging ν increases the power of discovering strong nonnull features whose magnitudes are large, through improving the incoherence condition of Split LASSO in (4); on the other hand, doing so may lose the power of discovering weak nonnull features of small magnitudes.

To see this, considering the construction in Equation (4), (7) and (8), ideally, a nonnull feature i will appear earlier (of larger $|W_i|$) on the Split LASSO path such that $Z_i > \tilde{Z}_i$, while a null feature j will appear later (of smaller $|W_j|$) on the path such that $Z_j < \tilde{Z}_j$. Since Z_i is determined by the Split LASSO path of (4), it is natural to ask under what conditions

that an early stage of the path has no false positive and the existence of a point on the path with model selection consistency. We approach the model selection consistency following the same treatment in the traditional LASSO problem (Wainwright, 2009) and Split Linearized Bregman Iterations (Huang et al., 2016, 2020). Below we are going to see the incoherence condition that is favoured by a sufficiently large ν will provide the guarantee to find the strong nonnull features, at a possible cost of losing weak nonnulls.

Define $H_\nu := I_m - \frac{D[\Sigma_X + L_D]^{-1}D^T}{\nu}$, and further denote H_ν^{11} to be the covariance matrix for S_1 , H_ν^{00} to be the covariance matrix for S_0 , and H_ν^{10} , H_ν^{01} to be the covariance matrix between S_1 and S_0 . First of all, H_ν^{11} has to be reversible, without which *identifiability* shall be impossible. For this purpose, we assume that the Split LASSO is strongly convex when being restricted on the nonnull features.

Restricted-Strongly-Convex Condition. There exists some $C_{\min} > 0$, such that the smallest eigenvalue of H_ν^{11} is bounded below, *i.e.*

$$(21) \quad \lambda_{\min}(H_\nu^{11}) > C_{\min}.$$

4.1. *ν -Incoherence Condition.* The following incoherence condition is critical for path consistency and influenced by parameter ν .

ν -Incoherence Condition. There exists a parameter $\chi_\nu \in (0, 1]$, such that

$$(22) \quad \|H_\nu^{01}[H_\nu^{11}]^{-1}\|_\infty \leq 1 - \chi_\nu.$$

The influence of ν on this incoherence condition is as follows. As $\nu \rightarrow \infty$, $H_\nu = I_m - \frac{1}{\nu}D[\Sigma_X + L_D]^{-1}D^T \succeq I_m - \frac{1}{\nu}D[\Sigma_X]^{-1}D^T \rightarrow I_m$, therefore $H_\nu^{01} \rightarrow 0_{|S_0| \times |S_1|}$, while $H_\nu^{11} \rightarrow I_{|S_1|}$. In this situation, the left hand side of inequality (22) drops to zero, and it satisfies the incoherence condition with arbitrarily large $\chi_\nu \rightarrow 1$. In a contrast, for generalized LASSO, the incoherence condition of the induced LASSO problem (3) is: there exists some incoherence parameter $\chi \in (0, 1]$, such that for $X(D) := U^T X D^\dagger$

$$\|X(D)_{S_0}^T X(D)_{S_1} (X(D)_{S_1}^T X(D)_{S_1})^{-1}\|_\infty \leq 1 - \chi,$$

which may not be satisfied when the Gram matrix of X or D has heavy off-diagonal elements. In summary, increasing ν helps meet the incoherence condition above.

4.2. *Path Consistency and Power.* Now we are ready to state our main theorem on the Split LASSO path consistency under the restricted strongly convex and ν -incoherence conditions.

THEOREM 4.1. *Assume that the design matrix X and D satisfy the Restricted-Strongly-Convex condition (21) and ν -Incoherence condition (22). Let the columns of X be normalized as $\max_{i \in [1:p]} \frac{\|x_i\|_2}{\sqrt{n}} \leq 1$. Suppose the sequence of $\{\lambda_n\}$ satisfies*

$$(23) \quad \lambda_n > \frac{1}{\chi_\nu} \sqrt{\frac{8\sigma^2 \log m}{n}}.$$

Then for some $c > 0$, the following properties hold with probability $1 - 4e^{-cn\lambda_n^2}$.

1. (No-false-positive) Split LASSO has a unique solution $(\hat{\beta}, \hat{\gamma}) \in \mathbb{R}^p \times \mathbb{R}^m$ without false positives w.r.t. γ .
2. (Sign-consistency) If there holds

$$\min_{i \in S_1} \gamma_i^* > \lambda_n \nu \left[\frac{4\sigma}{\sqrt{C_{\min}}} + \|[H_\nu^{11}]^{-1}\|_\infty \right],$$

in addition, $\hat{\gamma}$ recovers the sign of γ^ .*

The influence of ν on the power can be understood from this theorem as follows: (a) for the early stage of the Split LASSO path characterized by (23), there is no false positive and only nonnull features are selected here; (b) all the strong nonnull features whose magnitudes are larger than $O(\nu\sigma\chi_\nu^{-1}\sqrt{\log m/n})$ could be selected on the path with sign consistency. Hence a sufficiently large ν will ensure the incoherence condition for path consistency such that strong nonnull features will be selected earlier on the Split LASSO path than the nulls, at the cost of possibly losing weak nonnull features below $O(\nu\sigma\chi_\nu^{-1}\sqrt{\log m/n})$. Therefore, a good power must rely on a proper choice of ν for the trade-off.

The formal proof of this theorem will be provided in Section C.

5. Simulation Experiments. In this section, we show by several simulation experiments that our proposed Split Knockoff method performs well in FDR control with structural sparsity, which, at a proper choice of ν , often exhibits better results than the classical knockoff method when both methods can be applied.

5.1. Experimental Setting. In this section, we consider the simulation example in Section 1.3.1. In comparative experiments, we use `glmnet` package (Friedman, Hastie and Tibshirani, 2010; Simon et al., 2011) to compute regularization paths for Split LASSO, etc. For each simulation, we show plots of FDRs and Powers with respect to $\log \nu$. Throughout this section, unless otherwise specified, we take $\log \nu$ from a grid between -1 and 3 with a step size $h_\nu = 0.2$, and take $\log \lambda$ from a grid in $[0, -6]$ with a step size $h_\lambda = 0.01$. Each line in the figures represents the mean values of FDR or Power in 20 experiments.

5.2. Comparison of Split Knockoffs vs. Knockoffs in $D_1 = I_p$. The comparison between Knockoffs and Split Knockoffs is shown in Figure 2(a), 2(b).

FDR. As we can see from the figures, for sufficiently large ν , Split Knockoffs will perform better in FDR control compared with standard Knockoffs, where (Split) Knockoff+ improves FDR over (Split) Knockoff in both methods. Such a result supports Theorem 3.4 which shows upper bounds of FDR for Split Knockoffs becomes tighter as ν increases. Moreover, there is an critical area that Split Knockoffs perform better than Knockoffs in both FDR control and Power. In practice, one way to detect such an area is to use cross validation, whose details will be discussed in Section 5.5.

Power. For a range of proper choice on ν , Split Knockoffs exhibit the same high power compared with standard Knockoffs, where Split Knockoff+ sacrifices a little bit power for improving FDR control compared with Split Knockoff. For Split Knockoffs, increasing ν when it is small will improve the power as the incoherence condition gets improved with better path consistency; however, overshooting ν to be too large will drop the power by losing weak nonnull features, as shown in Theorem 4.1.

5.3. Comparison of Split Knockoffs vs. Knockoffs in 1-D Fused LASSO D_2 . The comparison between Split Knockoffs and Knockoffs is shown in Figure 2(d), 2(e).

FDR. In this case, the 1-D Fused LASSO with correlated X and D_2 destroys the incoherence condition such that null features often show up early in LASSO regularization paths, that hurts the FDR control in practice for standard Knockoffs. However, Split Knockoffs exploits ν to improve the incoherence condition and hence the FDR control, that leads to the advantage in FDR control when ν is sufficiently large.

TABLE 3
Validation Procedure for Split Knockoffs

Validation Procedure

- (1) Divide the data (X, Y) into two parts: (X_0, Y_0) as the training set and (X_1, Y_1) as the validation set.
- (2) Conduct Split Knockoff on (X_0, Y_0) and get \hat{S}_1 as the estimated support set of γ .
- (3) Calculate solution β for the constrained optimization problem

$$\min_{\text{supp}(D\beta) \subseteq \hat{S}_1} \frac{1}{2} \|y - X_1\beta\|^2.$$

- (4) Calculate the square validation loss for the linear regression on (X_1) .
- (5) Select the ν^* with the minimal validation loss.

Power. There is a range of the proper choice of ν for good power of Split Knockoffs. In this case, the correlated X and D_2 destroys the incoherence condition of induced LASSO problem (3), that hurts the power for standard Knockoffs. Meanwhile, for Split Knockoffs, increasing ν when it is small will improve the power as the incoherence condition gets improved with better path consistency. However, for Split Knockoffs, too large ν will lose power due to loss of weak signals and a satisfied power is provided by a good trade-off between improving the incoherence condition and securing weak nonnull features as discussed in Theorem 4.1.

5.4. *Split Knockoffs in Mixed D_3 .* The performance of Split Knockoffs for D_3 is shown in Figure 2(g), 2(h). Only the Split Knockoff method is applicable in this scenario.

FDR. In this case, Split Knockoffs provides a satisfied FDR control for all range of ν in the experiment, where the Split Knockoff+ selector shows better FDR than the Split Knockoff selector. The increase of variable dimension in this case shall help increase the ‘‘sample size’’ for Split Knockoffs, which lead to a better performance. Moreover, as Theorem 3.4 suggests, increasing ν helps FDR control.

Power. A good power of Split Knockoffs lies in a proper range of ν , not being too large or too small. This meets the trade-off between the incoherence condition and weak nonnull feature detection as suggested in Theorem 4.1. Similarly, Split Knockoff+ selector sacrifice power for improving FDR control compared with Split Knockoff selector.

5.5. *A Validation Choice of ν .* From the simulation results, we can see that we need to choose a proper ν to get better performance on both FDR and Power. Although Theorem 3.4 prefer to choose larger ν , Theorem 4.1 requires a trade-off on ν instead of being too large – otherwise the minimal signal condition will not be satisfied and weak nonnull features might be lost. In practice, we find that validation can help select a suitable ν to prevent us from losing too much power. The validation procedure is stated in Table 3.

Such a (cross) validation procedure indeed gives a proper choice of ν^* with satisfactory FDR and Power control in our simulation experiments. We take examples from the simulation experiments to illustrate this. Specially, we take the examples of Split Knockoff for D_1 , D_2 and D_3 in Section 5.3. Means of cross validation loss on selected models at different ν in 20 simulation experiments are shown in Figure 2(c), 2(f) and 2(i). One can observe that the regions of ν with small cross validation loss match the regions with a satisfactory FDR and power performance in Figure 2 respectively.

Therefore, in practice we can use cross-validation to help us decide the choice of ν . In Table 1, we report the performance of Split Knockoff by cross-validation optimal ν^* , where the step size for $\log \nu$ is $h_\nu = 0.4$.




FIG 2. Performances of Split Knockoffs and Knockoffs: Power, FDR and CV loss for $q = 0.2$.

5.6. Effects of Other Parameters. In this section, we will use simulation experiments to illustrate how different parameters (Feature Correlation, Signal-to-Noise Ratio, and Sparsity Level) affect FDR and Power for Split Knockoffs. The settings for simulation experiments are in general the same as Section 5.1, except for the change of respective parameters. Here, we will consider the case where $D = D_2 \in \mathbb{R}^{(p-1) \times p}$ is a 1-D graph difference operator. For Split Knockoff, we will show the curves of FDR and Power with respect to ν under different cases. For simplicity, we only show the comparative results for Knockoff and Split Knockoff in the figures. Similarly like before, all the curves in this part will be the mean curves over 20 random experiments.

5.6.1. Effect of Feature Correlation. We consider two extreme cases: feature correlation parameter c takes 0 and 0.9. The comparison between Knockoff and Split Knockoff on FDR and Power is shown in Figure 3.

From Figure 3, both Split Knockoff and Knockoff show a better performance in FDR control and Power at low feature correlations, as the incoherence condition can be satisfied better in the this case. When the feature correlation is extremely high at 0.9, the power of Split Knockoff drop quickly, though still consistently better than Knockoff. This is due to the improvement on the incoherence condition shown in Theorem 4.1. It is worth to mention




FIG 3. Effect of Feature Correlation: Power and FDR for $q = 0.2$




FIG 4. Effect of SNR: Power and FDR for $q = 0.2$

that for Split Knockoff, there is a critical region of ν with both good FDR control and good power, even when the correlation is very high.

5.6.2. *Effect of Signal-to-Noise Ratio.* Signal-to-Noise Ratio (SNR) in this section is defined as

$$\text{SNR} = \frac{\min_i \{|\gamma_i^*| : i \in S_1\}}{\sigma}$$

where γ^* is the true signal and σ is the noise level. In our experiment, it is the parameter A that determines SNR, and we consider two extreme cases where A takes the value of 0.25 and 4. The comparison between Knockoff and Split Knockoff on FDR and Power is shown in Figure 4.

From Figure 4, Split Knockoff and Knockoff perform well when SNR is large at 4 and ν is reasonably large; yet, both methods suffer from significant power drop when SNR is extremely low at 0.25, suggesting a great loss in weak signals. Due to the improved incoherence condition as discussed in Theorem 4.1, Split Knockoffs still maintain a better power for a proper range of ν ($\log \nu$ is between 0 and 1) when $A = 0.25$.

5.6.3. *Effect of Sparsity Level.* We consider two extreme cases that the sparsity level parameter k takes 10 or 100. The comparison between Knockoffs and Split Knockoffs on FDR and Power is shown in Figure 5.




FIG 5. *Effect of Sparsity Level: Power and FDR for $q = 0.2$*

From Figure 5, Split Knockoff in a proper range of ν has a better and more stable performance in power than Knockoff in both extreme cases. For FDR control, when the signal is less sparse with $k = 100$, Split Knockoff behaves similarly for a wide range of ν compared with Knockoff. This is because as discussed in Section 1.4, one main advantage of our method in FDR control relies on asymmetry of the amplification of nulls in \tilde{Z} , whence as $k = 100$, Split Knockoff has a less advantage than Knockoff on FDR control when the size of null set is reduced. In this scenario, increasing ν has a less influence on improving FDR than sparse cases, yet likely causing a rapid loss of weak nonnull features.

6. Application: Alzheimer’s Disease. In this experiment, we apply the Split Knockoff method to study lesion regions of brains and their connections in Alzheimer’s Disease (AD), which is the major cause of dementia and attracts increasing attention in recent years.

6.1. *Dataset.* The data is obtained from ADNI (<http://adni.loni.ucla.edu>) dataset, acquired by structural Magnetic Resonance Imaging (MRI) scan. In total, the dataset contains $n = 752$ samples, with 126 AD, 433 Mild Cognitive Impairment (MCI) and 193 Normal Controls (NC). For each image, we implement the Dartel VBM (Ashburner, 2007) for pre-processing, followed by the toolbox *Statistical Parametric Mapping* (SPM) for segmentation of gray matter (GM), white matter (WM) and cerebral spinal fluid (CSF). Then we use Automatic Anatomical Labeling (AAL) atlas (Tzourio-Mazoyer et al., 2002) to partition the whole brain into 90 Cerebrum brain anatomical regions, with the volume of each region (summation of all GMs in the region) provided.

We use $X \in \mathbb{R}^{752 \times 90}$ to denote the design matrix, with each element $X_{i,j}$ representing the column-wise normalized volume of region j in the subject i ’s brain. The response variable vector $y \in \mathbb{R}^n$ denotes the Alzheimer’s Disease Assessment Scale (ADAS), which was originally designed to assess the severity of cognitive dysfunction (Rosen, Mohs and Davis, 1984) and was later found to be able to clinically distinguish the diagnosed AD from normal controls (Zec et al., 1992). We test two types of structural sparsity:

- (a) $D = I_p$, the identity matrix, for selecting the regions that account for the Alzheimer’s disease;
- (b) D is the graph difference operator matrix, for selecting the connections of regions with large activation change accounting for the disease.

In both cases with such X, y, D , the condition $n \geq m + p$ is satisfied. In the analysis below, we take $\log \nu$ from an arithmetic sequence from -1 to 1 with step size $h_\nu = 0.1$, and take $\log \lambda$ from an arithmetic sequence from 0 to -6 with step size $h_\lambda = 0.01$.

6.2. *Region Selection.* In this experiment, we consider the selection of lesion regions, with $D = I_p$. We set our target FDR to be $q = 0.2$. The standard knockoffs (Barber et al., 2015) is also implemented as a comparison. For Split Knockoffs, the selection result and the cross validation loss of each ν is reported.

TABLE 4
Comparison for Knockoff and Split Knockoff on Alzheimer’s Disease ($q = 0.2$)

Region	Knockoff	Split Knockoff with $\log \nu$													
		$[-0.8, -0.6]$	$[-1, -0.9]$	$[-0.5, -0.3]$	-0.2	-0.1	$[0, 0.1]$	0.2	0.3	0.4	0.5	$[0.6, 0.8]$	0.9	1	
Superior Frontal gyrus, orbital part (L)					✓	✓	✓	✓	✓	✓	✓	✓	✓		
Hippocampus (L)	✓	✓		✓	✓	✓	✓	✓	✓	✓	✓	✓	✓		
Hippocampus (R)	✓	✓		✓	✓	✓	✓	✓	✓	✓	✓	✓	✓		
Amygdala (L)		✓		✓											
Amygdala (R)				✓											
Rolandic Operculum (L)					✓										
Rolandic Operculum (R)					✓										
Posterior Cingulate gyrus (L)								✓							
Posterior Cingulate gyrus (R)								✓							
Middle Temporal gyrus (L)	✓	✓		✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Middle Temporal gyrus (R)		✓		✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Inferior Temporal gyrus (L)		✓		✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Model CV loss (5 folds)	0.5778	0.5792	0.5828	0.5744	0.5711	0.5666	0.5648	0.5734	0.5693	0.5731	0.5778	0.6739	0.9973		

We can see from Table. 4 that for Split Knockoff, the number of selected regions exhibits a trend of “first increases and then decreases”, as ν grows. Such a trend is similar with the trend of power vs. ν in simulation results; and may be explained by the trade-off effect of ν between weaker incoherence condition and missing weak signals, as stated in Theorem 4.1. Besides, note that as long as $\nu \leq 0.8$, both Split Knockoff and knockoff can select two-side Hippocampus and Middle Temporal Gyrus (L), which are also detected by Knockoff and have been found in large literature to suffer from significant gray matter degeneration for AD patients (Vemuri and Jack, 2010; Schuff et al., 2009). Moreover, at $\nu = 0.2$ corresponding to the minimal CV loss, Split Knockoff can additionally select “Superior Frontal gyrus, orbit part”, “Rolandic Operculum”, and “Inferior Temporal gyrus” in the left brain, as well as the “Posterior Cingulate gyrus” and the “Middle Temporal gyrus” in the right brain. These regions have also been found to be correlated with Alzheimer’s Disease in literature (Bakkour et al., 2013; Roquet et al., 2017; Cajanus et al., 2019). Specifically, it was reported in (Karas et al., 2004; Whitwell et al., 2007; Blanc et al., 2015; Baron et al., 2001) that the temporal lobe, posterior cingulate and rolandic operculum can suffer from degeneration for AD. Bakkour et al. (2013) found that the Superior Frontal gyrus was more atrophied among AD patients than normal agings. Further, Cajanus et al. (2019) investigated the effect of Superior Frontal gyrus on disinhibition and aberrant motor behavior. These results show that Split Knockoff has more power than classical Knockoff in this experiment. This is due to that a proper ν can make incoherence condition easier to satisfy and at the same time do not miss important strong signals, as stated in Theorem 4.1 and illustrated by the simulation results.

6.3. *Connection Selection.* In this experiment, we consider the connection or edge detection, in which each connection is associated with two adjacent brain regions. Formally speaking, we set D as the graph gradient (difference) operator on the graph $G = (V, E)$ where V denotes the vertex set of lesion regions and E denotes the (oriented) edge set of region pairs in neighbor, such that $D(\beta)(i, j) = \beta_i - \beta_j$ for $(i, j) \in E$. Since we take D to be the graph gradient operator that measures the difference in the impacts of Alzheimer’s Disease between adjacent regions in brains, we shall expect a properly selected edge will connect regions of high contrast variations in the degree of atrophy during the disease progression. For example, a selected edge may connect an atrophy region in the brain significantly impaired by Alzheimer’s Disease to another region which is less influenced by the disease.

Here we set the target FDR level as $q = 0.2$ as before and the result is shown in Table 5. As we can see from Table 5, all the edges selected are connected to Hippocampus, which are

TABLE 5
Connection Selection for Split Knockoff on Alzheimer’s Disease ($q = 0.2$)

Connection		Split Knockoff with $\log \nu$						
Region 1	Region 2	$[-1, -0.3]$	$[-0.2, 0]$	$[0.1, 0.2]$	$[0.3, 0.4]$	$[0.5, 0.6]$	0.7	$[0.8, 1]$
Hippocampus (L)	Lingual gyrus (L)			✓	✓	✓		
Hippocampus (L)	Precuneus (L)		✓	✓	✓			
Hippocampus (R)	Lingual gyrus (R)			✓	✓	✓	✓	
Hippocampus (R)	Precuneus (R)			✓				
Hippocampus (R)	Putamen (R)			✓				

supported by existing studies (Juottonen et al., 1999) as one of the most important atrophy regions for Alzheimer’s Disease. The connected regions in the column of Region 2 that are not previously selected in Table 4, indicate that they are relatively stable or undergo possible GM degeneration of different degrees or stages to Hippocampus during disease progression.

7. Conclusion and Future Directions. In this paper, we propose Split Knockoffs as a data adaptive FDR control method for the structural sparsity recovery in linear regression where a linear transformation of parameters is sparse. By relaxing the linear subspace constraint to its neighborhood in a lifted parameter space, our method gains both FDR control and power in improving the model selection consistency conditions on Split LASSO regularization paths. The simulation experiments demonstrate the effective FDR control and good power for Split Knockoffs, even better than classical Knockoffs in the scenarios where both are applicable. In a real world application to Alzheimer’s Disease study with MRI data, Split Knockoffs discover important atrophy lesion regions in brain and neighboring region connections of high contrast in atrophy variations during disease progression.

The key departure of Split Knockoff statistics from classical Knockoffs is that we use two separate regularization paths instead of joint optimizations, namely the feature significance stage and the knockoff significance stage. Intuitively, such a treatment has a benefit of decoupling the magnitudes and the signs of Split Knockoff statistics when exchangeability fails, that enables us an almost supermartingale construction for FDR control. This approach will also have computational benefits since the dimension for each optimization is cut by half from joint optimizations in Knockoffs. This interesting treatment deserves further explorations in the future.

The main theoretical contribution of this paper is that we construct an almost supermartingale structure to give a theoretical FDR control for fixed design when exchangeability is broken by the heterogeneous noise. The key idea for this achievement is to exploit the orthogonal designs of Split Knockoff matrices, together with the separate stages of Split Knockoff statistics above. The orthogonal designs are also crucial in the improved incoherence condition for path consistency of Split LASSO.

In practice, Split Knockoffs benefit from an asymmetric property that the negative knock-off statistics for nulls tend to have greater magnitudes compared with positive ones, which leads to a better FDR control in experiments. However, this may lose some power in discovering weak nonnull features and there is an inflation on our current theoretical guarantee on FDR control. Filling in such a gap is one future direction.

Finally, Split Knockoffs presented in this paper assume $n \geq p + m$ for simplicity, where n is the sample size, m is the number of linear constraints, and p is the number of parameters. In many applications, however, we are in scenarios where $n < p + m$. Therefore, it is desired to extend this method with screening into the latter high-dimensional scenarios, which is left to future studies.

REFERENCES

ASHBURNER, J. (2007). A fast diffeomorphic image registration algorithm. *Neuroimage* **38** 95–113.

- BAKKOUR, A., MORRIS, J. C., WOLK, D. A. and DICKERSON, B. C. (2013). The effects of aging and Alzheimer’s disease on cerebral cortical anatomy: specificity and differential relationships with cognition. *Neuroimage* **76** 332–344.
- BARBER, R. F., CANDÈS, E. J. et al. (2015). Controlling the false discovery rate via knockoffs. *The Annals of Statistics* **43** 2055–2085.
- BARBER, R. F., CANDÈS, E. J. et al. (2019). A knockoff filter for high-dimensional selective inference. *The Annals of Statistics* **47** 2504–2537.
- BARBER, R. F., CANDÈS, E. J., SAMWORTH, R. J. et al. (2020). Robust inference with knockoffs. *Annals of Statistics* **48** 1409–1431.
- BARON, J., CHETELAT, G., DESGRANGES, B., PERCHEY, G., LANDEAU, B., DE LA SAYETTE, V. and EUSTACHE, F. (2001). In vivo mapping of gray matter loss with voxel-based morphometry in mild Alzheimer’s disease. *Neuroimage* **14** 298–309.
- BENJAMINI, Y. and HOCHBERG, Y. (1995). Controlling the false discovery rate: a practical and powerful approach to multiple testing. *Journal of the Royal Statistical Society: series B (Methodological)* **57** 289–300.
- BLANC, F., COLLOBY, S. J., PHILIPPI, N., DE PÉTIGNY, X., JUNG, B., DEMUYNCK, C., PHILLIPPS, C., ANTHONY, P., THOMAS, A., BING, F. et al. (2015). Cortical thickness in dementia with Lewy bodies and Alzheimer’s disease: a comparison of prodromal and dementia stages. *PLoS One* **10** e0127396.
- CAI, J.-F., DONG, B., OSHER, S. and SHEN, Z. (2012). Image restoration: Total variation, wavelet frames, and beyond. *J. Amer. Math. Soc.* **25** 1033–1089.
- CAJANUS, A., SOLJE, E., KOIKKALAINEN, J., LÖTJÖNEN, J., SUHONEN, N.-M., HALLIKAINEN, I., VANNINEN, R., HARTIKAINEN, P., DE MARCO, M., VENNERI, A. et al. (2019). The association between distinct frontal brain volumes and behavioral symptoms in mild cognitive impairment, Alzheimer’s disease, and frontotemporal dementia. *Frontiers in neurology* **10** 1059.
- CANDÈS, E., FAN, Y., JANSON, L. and LV, J. (2018). Panning for gold: Model-X knockoffs for high-dimensional controlled variable selection. *Journal of the Royal Statistical Society: series B (Statistical Methodology)* **80** 551–577.
- DAI, R. and BARBER, R. F. (2016). The knockoff filter for FDR control in group-sparse and multitask regression. In *Proceedings of The 33rd International Conference on Machine Learning (ICML)*. PMLR 48:1851–1859. arXiv:1602.03589.
- DONOHO, D. L. and HUO, X. (2001). Uncertainty Principles and Ideal Atomic Decomposition. *IEEE Transactions on Information Theory* **47** 2845–2862.
- DONOHO, D. L. and JOHNSTONE, I. M. (1995). Adapting to unknown smoothness via wavelet shrinkage. *Journal of the American Statistical Association* **90** 1200–1224.
- FRIEDMAN, J., HASTIE, T. and TIBSHIRANI, R. (2010). Regularization paths for generalized linear models via coordinate descent. *Journal of statistical software* **33** 1.
- HUANG, C., SUN, X., XIONG, J. and YAO, Y. (2016). Split LBI: An Iterative Regularization Path with Structural Sparsity. In *Advances in Neural Information Processing Systems (NIPS)* **29** 3369–3377.
- HUANG, C., SUN, X., XIONG, J. and YAO, Y. (2020). Boosting with structural sparsity: A differential inclusion approach. *Applied and Computational Harmonic Analysis* **48** 1–45.
- JUOTTONEN, K., LAAKSO, M. P., PARTANEN, K. and SOININEN, H. (1999). Comparative MR analysis of the entorhinal cortex and hippocampus in diagnosing Alzheimer disease. *American Journal of Neuroradiology* **20** 139–144.
- KARAS, G., SCHELTENS, P., ROMBOUTS, S., VISSER, P., VAN SCHIJNDEL, R., FOX, N. and BARKHOF, F. (2004). Global and local gray matter loss in mild cognitive impairment and Alzheimer’s disease. *Neuroimage* **23** 708–716.
- KIM, S.-J., KOH, K., BOYD, S. and GORINEVSKY, D. (2009). ℓ_1 trend filtering. *SIAM review* **51** 339–360.
- OSHER, S., RUAN, F., XIONG, J., YAO, Y. and YIN, W. (2016). Sparse Recovery via Differential Inclusions. *Applied and Computational Harmonic Analysis* **41** 436–469.
- ROMANO, Y., SESIA, M. and CANDÈS, E. (2019). Deep knockoffs. *Journal of the American Statistical Association* 1–12.
- ROQUET, D., NOBLET, V., ANTHONY, P., PHILIPPI, N., DEMUYNCK, C., CRETIN, B., MARTIN-HUNYADI, C., DE SOUSA, P. L. and BLANC, F. (2017). Insular atrophy at the prodromal stage of dementia with Lewy bodies: a VBM DARTEL study. *Scientific reports* **7** 1–10.
- ROSEN, W. G., MOHS, R. C. and DAVIS, K. L. (1984). A new rating scale for Alzheimer’s disease. *Am J Psychiatry* **141** 1356–64.
- RUDIN, L. I., OSHER, S. and FATEMI, E. (1992). Nonlinear Total Variation Based Noise Removal Algorithms. *Physica D: Nonlinear Phenomena* **60** 259–268.
- SCHUFF, N., WOERNER, N., BORETA, L., KORNFELD, T., SHAW, L., TROJANOWSKI, J., THOMPSON, P., JACK JR, C., WEINER, M. and INITIATIVE, A. D. N. (2009). MRI of hippocampal volume loss in early Alzheimer’s disease in relation to ApoE genotype and biomarkers. *Brain* **132** 1067–1077.

- SIMON, N., FRIEDMAN, J., HASTIE, T. and TIBSHIRANI, R. (2011). Regularization paths for Cox's proportional hazards model via coordinate descent. *Journal of statistical software* **39** 1.
- TIBSHIRANI, R. J., TAYLOR, J. et al. (2011). The solution path of the generalized lasso. *The Annals of Statistics* **39** 1335–1371.
- TIBSHIRANI, R., SAUNDERS, M., ROSSET, S., ZHU, J. and KNIGHT, K. (2005). Sparsity and smoothness via the fused lasso. *Journal of the Royal Statistical Society: Series B (Statistical Methodology)* **67** 91–108.
- TROPP, J. A. (2004). Greed is good: Algorithmic results for sparse approximation. *IEEE Trans. Inform. Theory* **50** 2231–2242.
- TZOURIO-MAZOYER, N., LANDEAU, B., PAPATHANASSIOU, D., CRIVELLO, F., ETARD, O., DELCROIX, N., MAZOYER, B. and JOLIOT, M. (2002). Automated anatomical labeling of activations in SPM using a macroscopic anatomical parcellation of the MNI MRI single-subject brain. *Neuroimage* **15** 273–289.
- VEMURI, P. and JACK, C. R. (2010). Role of structural MRI in Alzheimer's disease. *Alzheimer's research & therapy* **2** 1–10.
- WAINWRIGHT, M. J. (2009). Sharp Thresholds for High-Dimensional and Noisy Sparsity Recovery Using l_1 -Constrained Quadratic Programming (LASSO). *IEEE Transactions on Information Theory* **55** 2183–2202.
- WHITWELL, J. L., WEIGAND, S. D., SHIUNG, M. M., BOEVE, B. F., FERMAN, T. J., SMITH, G. E., KNOPMAN, D. S., PETERSEN, R. C., BENARROCH, E. E., JOSEPHS, K. A. et al. (2007). Focal atrophy in dementia with Lewy bodies on MRI: a distinct pattern from Alzheimer's disease. *Brain* **130** 708–719.
- XU, Q., XIONG, J., CAO, X. and YAO, Y. (2016). False discovery rate control and statistical quality assessment of annotators in crowdsourced ranking. In *International Conference on Machine Learning* 1282–1291.
- YAO, Y., ROSASCO, L. and CAPONNETTO, A. (2007). On Early Stopping in Gradient Descent Learning. *Constructive Approximation* **26** 289–315.
- ZEC, R. F., LANDRETH, E. S., VICARI, S. K., FELDMAN, E., BELMAN, J., ANDRISE, A., ROBBS, R., KUMAR, V. and BECKER, R. (1992). Alzheimer disease assessment scale: useful for both early detection and staging of dementia of the Alzheimer type. *Alzheimer Disease and Associated Disorders*.
- ZHAO, P. and YU, B. (2006). On model selection consistency of Lasso. *Journal of Machine learning research* **7** 2541–2563.
- ZOU, H. and HASTIE, T. (2005). Regularization and Variable Selection via the Elastic Net. *Journal of the Royal Statistical Society, Series B.* **67** 301–320.

Supplementary Material of “Controlling the False Discovery Rate in Structural Sparsity: Split Knockoffs”

APPENDIX A: SUPPLEMENTARY MATERIAL FOR SECTION 2

In this section, we provide more details on Proposition 2.1, construction of split knockoff copy and Proposition 2.2, failure of exchangeability.

A.1. Construction of Split Knockoff Matrices. We will first show the details for Proposition 2.1. Note that a necessary and sufficient condition for the existence of \tilde{A}_γ satisfying Equation (6) is

$$G := \begin{bmatrix} \Sigma_{\beta,\beta} & \Sigma_{\beta,\gamma} & \Sigma_{\beta,\gamma} \\ \Sigma_{\beta,\gamma} & \Sigma_{\gamma,\gamma} & \Sigma_{\gamma,\gamma} - \text{diag}(\mathbf{s}) \\ \Sigma_{\beta,\gamma} & \Sigma_{\gamma,\gamma} - \text{diag}(\mathbf{s}) & \Sigma_{\gamma,\gamma} \end{bmatrix} \succeq 0.$$

This holds if and only if the Schur complement of $\Sigma_{\beta,\beta}$ is positive semi-definite, i.e.

$$\begin{bmatrix} C_\nu & C_\nu - \text{diag}(\mathbf{s}) \\ C_\nu - \text{diag}(\mathbf{s}) & C_\nu \end{bmatrix} \succeq 0, \quad C_\nu := \Sigma_{\gamma,\gamma} - \Sigma_{\gamma,\beta} \Sigma_{\beta,\beta}^\dagger \Sigma_{\beta,\gamma},$$

which holds if and only if C_ν and its Schur complement are positive semi-definite, i.e.

$$C_\nu \succeq 0,$$

$$C_\nu - (C_\nu - \text{diag}(\mathbf{s}))C_\nu^{-1}(C_\nu - \text{diag}(\mathbf{s})) = 2\text{diag}(\mathbf{s}) - \text{diag}(\mathbf{s})C_\nu^{-1}\text{diag}(\mathbf{s}) \succeq 0.$$

It is equivalent to Equation (10).

There are various choices for $\mathbf{s} = (s_i)$ satisfying (10) for Split Knockoffs. Below we give two typical examples.

(a) (SDP for discrepancy maximization) One can maximize the discrepancy between Knockoffs and its corresponding features by solving the following SDP

$$\begin{aligned} & \text{maximize} \quad \sum_i s_i, \\ & \text{subject to} \quad 0 \leq s_i \leq \frac{1}{\nu}, \\ & \quad \quad \quad \frac{\text{diag}(\mathbf{s})}{2 - \eta} \preceq A_\gamma^T (I - H) A_\gamma, \quad \eta > 0, \end{aligned}$$

where

$$H = A_\beta (A_\beta^T A_\beta)^{-1} A_\beta^T = \begin{bmatrix} \frac{X}{\sqrt{n}} \\ \frac{D}{\sqrt{\nu}} \end{bmatrix} \left[\frac{X^T X}{n} + \frac{D^T D}{\nu} \right]^{-1} \begin{bmatrix} X^T \\ \frac{D^T}{\sqrt{\nu}} \end{bmatrix},$$

and

$$A_\gamma^T (I - H) A_\gamma = A_\gamma^T A_\gamma - A_\gamma^T H A_\gamma = \frac{I}{\nu} - \frac{D}{\nu} \left[\frac{X^T X}{n} + \frac{D^T D}{\nu} \right]^{-1} \frac{D^T}{\nu} = C_\nu.$$

(b) (Equi-correlation) Take $s_i = (2 - \eta)\lambda_{\min}(C_\nu) \wedge \frac{1}{\nu}$ for all $i \in \{1, 2, \dots, m\}$, where $\eta > 0$ is a suitable parameter. Then we have,

$$A_\gamma^T \tilde{A}_\gamma = \left[\frac{1}{\nu} - (2 - \eta)\lambda_{\min}(C_\nu) \wedge \frac{1}{\nu} \right] I_m.$$

One can verify that the construction in Proposition 2.1 satisfies Equation (6).

A.2. Failure of Exchangeability. In this section, we provide the details on how exchangeability fails for Split Knockoffs. To see the details for Proposition 2.2, we first calculate that

$$(25) \quad [A_\beta, A_\gamma, \tilde{A}_\gamma]^T \tilde{y} = \begin{bmatrix} \frac{1}{n}(X^T X \beta^* + X^T \varepsilon) \\ 0 \\ \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}} X \beta^* + \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}} \varepsilon \end{bmatrix},$$

where $\tilde{A}_\gamma = [\tilde{A}_{\gamma,1}^T, \tilde{A}_{\gamma,2}^T]^T$ with $\tilde{A}_{\gamma,1}^T \in \mathbb{R}^{n \times m}$ and $\tilde{A}_{\gamma,2}^T \in \mathbb{R}^{m \times m}$. Recall that from (6), there holds

$$\begin{aligned} \tilde{A}_{\gamma,1}^T \frac{X}{\sqrt{n}} + \tilde{A}_{\gamma,2}^T \frac{D}{\sqrt{\nu}} &= -\frac{D}{\nu}, \\ -\frac{\tilde{A}_{\gamma,2}^T}{\sqrt{\nu}} &= \frac{I}{\nu} - \text{diag}\{\mathbf{s}\}. \end{aligned}$$

Then there holds $\tilde{A}_{\gamma,1}^T \frac{X}{\sqrt{n}} = \text{diag}\{\mathbf{s}\} D$. Combining it with Equation (25), there holds

$$[A_\beta, A_\gamma, \tilde{A}_\gamma]^T \tilde{y} = \begin{bmatrix} \frac{1}{n}(X^T X \beta^* + X^T \varepsilon) \\ 0 \\ -\text{diag}\{\mathbf{s}\} \gamma^* + \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}} \varepsilon \end{bmatrix}.$$

Define $\Sigma_X = \frac{X^T X}{n}$. Then the distribution of $[A_\beta, A_\gamma, \tilde{A}_\gamma]^T \tilde{y}$ is normal

$$\mathcal{N} \left(\begin{bmatrix} \Sigma_X \beta^* \\ 0 \\ -\text{diag}\{\mathbf{s}\} \gamma^* \end{bmatrix}, \begin{bmatrix} \frac{\sigma^2 \Sigma_X}{n} & 0 & -\frac{\sigma^2 s D^T}{n} \\ 0 & 0 & 0 \\ -\frac{\sigma^2 s D}{n} & 0 & \frac{\sigma^2 (2s - \nu s^2)}{n} I_m \end{bmatrix} \right),$$

where swapping any $i \in S_0$ in the second and the third block will lead to different Normal distributions of different covariance matrices, since $\frac{\sigma^2 (2s - \nu s^2)}{n} I_m \neq 0$ in general.

APPENDIX B: PROOF FOR THEOREM 3.4

In this section, we give the formal proof of Theorem 3.4 based on the outline introduced in Section 3. We divide the whole proof into four steps:

Step 1: we transfer the upper bound of FDR into the upper bound of $\mathbb{E}[\mathcal{M}_{T_q}(W^s)]$, i.e.

$$\text{“FDR”} \leq q \mathbb{E}[\mathcal{M}_{T_q}(W)] \leq q \mathbb{E}[\mathcal{M}_{T_q}(W^s)];$$

Step 2: conditional on the major event $\Lambda_{\nu, \kappa}$ (16), $\mathcal{M}_{T_q}(W^s)$ is an almost supermartingale

$$\text{and satisfies } \mathbb{E}[\mathcal{M}_{T_q}(W^s) | \Lambda_{\nu, \kappa}] \leq (1 + g(\kappa, \nu))^{|S_0| - 1} \mathcal{M}_0(W^s | \Lambda_{\nu, \kappa});$$

Step 3: we provide an upper bound for the Gaussian tail probability $\mathbb{P}(\Lambda_{\nu, \kappa}^c)$;

Step 4: final FDR upper bounds are obtained by combining the dominant almost supermartingale upper bound conditional on $\Lambda_{\nu, \kappa}$ and the Gaussian tail bound on $\Lambda_{\nu, \kappa}^c$.

The proof of Lemmas are left to Section D.

B.1. Transfer of FDR Bound. In this section, we first show the details of how to transfer the upper bound of FDR into the upper bound of $\mathbb{E}[\mathcal{M}_{T_q}(W)]$ in (13), then we show the details of Inequality (15) to further transfer the upper bound to $\mathbb{E}[\mathcal{M}_{T_q}(W^s)]$. The first step is of the same procedure as in classical Knockoffs. To see this, we deal with Split Knockoff and Split Knockoff+ separately in the following cases.

(a) (Split Knockoff) The modified FDR can be decoupled into two parts:

$$(27) \quad \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_i 1\{W_i \geq T_q\} + q^{-1}} \right] \leq \mathbb{E} \left[\frac{1 + \sum_i 1\{W_i \leq -T_q\}}{\sum_i 1\{W_i \geq T_q\} + q^{-1}} \frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 + \sum_{i \in S_0} 1\{W_i \leq -T_q\}} \right].$$

By definition of Split Knockoff thresholds, there holds

$$\frac{\sum_i 1\{W_i \leq -T_q\}}{1 \vee \sum_i 1\{W_i \geq T_q\}} \leq q < 1,$$

which implies

$$\sum_i 1\{W_i \leq -T_q\} \leq q \sum_i 1\{W_i \geq T_q\}.$$

Consequently, there holds

$$\frac{1 + \sum_i 1\{W_i \leq -T_q\}}{\sum_i 1\{W_i \geq T_q\} + q^{-1}} \leq \frac{1 + q[\sum_i 1\{W_i \geq T_q\}]}{\sum_i 1\{W_i \geq T_q\} + q^{-1}} = q.$$

Combined with the decoupling in Equation (27), there holds

$$\mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_i 1\{W_i \geq T_q\} + q^{-1}} \right] \leq q \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 + \sum_{i \in S_0} 1\{W_i \leq -T_q\}} \right] = q \mathbb{E}[\mathcal{M}_{T_q}(W)].$$

(b) (Split Knockoff+) The following lines established the result,

$$\begin{aligned} \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 \vee \sum_i 1\{W_i \geq T_q\}} \right] &\leq \mathbb{E} \left[\frac{1 + \sum_i 1\{W_i \leq -T_q\}}{1 \vee \sum_i 1\{W_i \geq T_q\}} \frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 + \sum_{i \in S_0} 1\{W_i \leq -T_q\}} \right], \\ &\leq q \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 + \sum_{i \in S_0} 1\{W_i \leq -T_q\}} \right] = q \mathbb{E}[\mathcal{M}_{T_q}(W)]. \end{aligned}$$

Now to get FDR bounds, we only need to figure out an upper bound for $\mathbb{E}[\mathcal{M}_{T_q}(W)]$. However, due to the failure of exchangeability, $\mathcal{M}_{T_q}(W)$ is no longer a supermartingale with stopping time T_q . To deal with this challenge, we give a new statistics W^s defined in Equation (14), where $\mathcal{M}_{T_q}(W^s)$ provides an upper bound for $\mathcal{M}_{T_q}(W)$ and W^s leads to an almost supermartingale structure.

To see the upper bound for $\mathcal{M}_{T_q}(W)$, from definition of W (9) and the definition of W^s (14), we have for $W_i > 0$, $|W_i| = Z_i = |W^s|$, for $W_i < 0$, $|W_i| = \tilde{Z}_i > Z_i = |W^s|$, while W_i shares the same sign as W_i^s . Therefore

$$\begin{aligned} \mathcal{M}_{T_q}(W) &= \frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 + \sum_{i \in S_0} 1\{W_i \leq -T_q\}} = \frac{\sum_{i \in S_0} 1\{|W_i| \geq T_q, W_i > 0\}}{1 + \sum_{i \in S_0} 1\{|W_i| \geq T_q, W_i < 0\}}, \\ &= \frac{\sum_{i \in S_0} 1\{Z_i \geq T_q, W_i > 0\}}{1 + \sum_{i \in S_0} 1\{\tilde{Z}_i \geq T_q, W_i < 0\}}, \\ &\leq \frac{\sum_{i \in S_0} 1\{Z_i \geq T_q, W_i > 0\}}{1 + \sum_{i \in S_0} 1\{Z_i \geq T_q, W_i < 0\}}, \\ &= \frac{\sum_{i \in S_0} 1\{W_i^s \geq T_q\}}{1 + \sum_{i \in S_0} 1\{W_i^s \leq -T_q\}} =: \mathcal{M}_{T_q}(W^s), \end{aligned}$$

which gives details of reaching (15).

For the second point, we can show that $\mathcal{M}_{T_q}(W^s)$ is a supermartingale on the dominant part $\Lambda_{\nu, \kappa}$ defined in Equation (16), while the probability for (ξ, ζ) to lie on the Gaussian tail $\Lambda_{\nu, \kappa}^c$ is small. Details of these facts will be introduced in the following sections.

B.2. Almost Supermartingale Bound of Dominant Part. In this step, we exploit the fact that $\mathcal{M}_{T_q}(W^s)$ is a supermartingale on the dominant event $\Lambda_{\nu,\kappa}$ in (16), that establishes an upper bound for FDR using the Lemmas in Section 3 conditional on $(\xi, \zeta) \in \Lambda_{\nu,\kappa}$.

From the definition of x^s and \hat{k}_q^s in Lemma 3.2, there holds

$$x_1^s = \mathcal{M}_0(W^s), \quad x_{\hat{k}_q^s}^s = \mathcal{M}_{T_q}(W^s).$$

In other words, x_k^s is the discrete version of $\mathcal{M}_{T_q}(W^s)$ as an almost supermartingale and \hat{k}_q^s , as a discrete version of T_q , is a stopping time with respect to filtration F^s .

By Optional Stopping Lemma D.4 for discrete almost supermartingales, there holds

$$\begin{aligned} \mathbb{E}[\mathcal{M}_{T_q}(W^s)] &= \mathbb{E}[x_{\hat{k}_q^s}^s] \leq (1 + g(\kappa, \nu))^{|S_0|-1} \mathbb{E}[x_1^s], \\ &= (1 + g(\kappa, \nu))^{|S_0|-1} \mathcal{M}_0(W^s). \end{aligned}$$

By Lemma 3.3, there further holds

$$\begin{aligned} \mathbb{E}[\mathcal{M}_{T_q}(W^s)] &\leq (1 + g(\kappa, \nu))^{|S_0|-1} \mathcal{M}_0(W^s), \\ (28) \quad &\leq (1 + g(\kappa, \nu))^{3|S_0|-1}, \end{aligned}$$

which leads to a FDR bound conditional on the dominant part $(\xi, \zeta) \in \Lambda_{\nu,\kappa}$.

B.3. Estimate of Gaussian Tail Bound. In this section, we provide an estimation on the probability of the Gaussian Tail event $(\xi, \zeta) \in \Lambda_{\nu,\kappa}^c$. From the definition of $\Lambda_{\nu,\kappa}$ (16), there holds

$$\begin{aligned} \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu,\kappa}^c) &\leq \mathbb{P}(\| -D[\Sigma_X]^{-1}(\xi - \Sigma_X \beta^*) \|_\infty \geq \kappa \sigma \frac{1}{\sqrt{n}}) + \dots \\ (29) \quad &\dots + \mathbb{P}(\|\zeta\|_\infty \geq \kappa \sqrt{s} \sigma \frac{1}{\sqrt{n}}). \end{aligned}$$

For the first part of Equation (29), take $u \sim \mathcal{N}(0, I_p)$, recall that $\mathbb{E}[\xi] = \Sigma_X \beta^*$ and $\text{var}[\xi] = \frac{\sigma^2 \Sigma_X}{n}$, there holds $u \sim \frac{\sqrt{n}}{\sigma} [\Sigma_X]^{-\frac{1}{2}} [\xi - \Sigma_X \beta^*]$, and consequently

$$\mathbb{P}(\| -D[\Sigma_X]^{-1}(\xi - \Sigma_X \beta^*) \|_\infty \geq \kappa \sigma \frac{1}{\sqrt{n}}) = \mathbb{P}(\|D[\Sigma_X]^{-\frac{1}{2}} u\|_\infty > \kappa).$$

Denote $\|D[\Sigma_X]^{-\frac{1}{2}}\|_\infty =: M_{X,D}$, there holds

$$\begin{aligned} \mathbb{P}(\|\Sigma_{X,D} u\|_\infty > \kappa) &\leq \mathbb{P}\left(\|u\|_\infty > \frac{\kappa}{M_{X,D}}\right), \\ &= 1 - \left[2\Phi\left(\frac{\kappa}{M_{X,D}}\right) - 1\right]^p, \\ &\leq p \left[2 - 2\Phi\left(\frac{\kappa}{M_{X,D}}\right)\right], \end{aligned}$$

where $\Phi(x)$ is the distribution function for standard Gaussian random variable and the last step uses the fact that $1 - (1 - \alpha)^p \leq p\alpha$ for any $\alpha > 0$.

For the second part of Equation (29), since $\mathbb{E}[\zeta] = 0$ and $\text{var}[\zeta] = \frac{\sigma^2(2s - \nu s^2)}{n} I_m$, ζ_i are i.i.d. Gaussian random variables with variance $\frac{\sigma^2(2s - \nu s^2)}{n} \leq \frac{\sigma^2 s}{n}$. Consequently, there holds

$$\mathbb{P}\left(\|\zeta\|_\infty \geq \kappa \sqrt{s} \sigma \frac{1}{\sqrt{n}}\right) \leq m(2 - 2\Phi(\kappa)).$$

Combining the two parts together, we obtain

$$(30) \quad \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}^c) \leq p \left[2 - 2\Phi\left(\frac{\kappa}{M_{X,D}}\right) \right] + m(2 - 2\Phi(\kappa)),$$

which gives an upper bound for the Gaussian tail event $(\xi, \zeta) \in \Lambda_{\nu, \kappa}^c$.

B.4. FDR Bounds for Split Knockoffs. In this section, we finish the proof for Theorem 3.4 by combining the almost supermartingale bound above conditional on the dominant part $\Lambda_{\nu, \kappa}$ together with the Gaussian tail $\Lambda_{\nu, \kappa}^c$ bound. Below we address Split Knockoff and Split Knockoff+ separately.

B.4.1. Split Knockoff. For Split Knockoff, the modified FDR bound can be decomposed into two parts in the following way:

$$\begin{aligned} & \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_{i \in S_0} 1\{W_i \geq T_q\} + q^{-1}} \right] \\ & \leq \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_{i \in S_0} 1\{W_i \geq T_q\} + q^{-1}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa} \right] \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}) + \dots \\ & \quad \dots + \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_{i \in S_0} 1\{W_i \geq T_q\} + q^{-1}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa}^c \right] \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}^c). \end{aligned}$$

For the first part, from Section B.1, B.2, there holds

$$\begin{aligned} & \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_{i \in S_0} 1\{W_i \geq T_q\} + q^{-1}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa} \right] \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}), \\ & \leq \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_{i \in S_0} 1\{W_i \geq T_q\} + q^{-1}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa} \right], \\ & \leq q \mathbb{E}[\mathcal{M}_{T_q}(W^s) \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa}] \leq q(1 + g(\kappa, \nu))^{3|S_0|-1}. \end{aligned}$$

For the second part, from Section B.3, there holds

$$\begin{aligned} & \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_{i \in S_0} 1\{W_i \geq T_q\} + q^{-1}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa}^c \right] \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}^c) \\ & \leq \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}^c) \leq p \left[2 - 2\Phi\left(\frac{\kappa}{M_{X,D}}\right) \right] + m(2 - 2\Phi(\kappa)). \end{aligned}$$

Combining these two parts together leads to

$$\begin{aligned} \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_{i \in S_0} 1\{W_i \geq T_q\} + q^{-1}} \right] & \leq q(1 + g(\kappa, \nu))^{3|S_0|-1} + \dots \\ & \quad \dots + p \left[2 - 2\Phi\left(\frac{\kappa}{M_{X,D}}\right) \right] + m(2 - 2\Phi(\kappa)). \end{aligned}$$

B.4.2. Split Knockoff+. For Split Knockoff+, the FDR bound can be achieved in the same way as Split Knockoff. First, we decompose the FDR bound into two parts:

$$\mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 \vee \sum_{i \in S_0} 1\{W_i \geq T_q\}} \right]$$

$$\begin{aligned} &\leq \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 \vee \sum_{i \in S_0} 1\{W_i \geq T_q\}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa} \right] \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}) + \dots \\ &\dots + \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 \vee \sum_{i \in S_0} 1\{W_i \geq T_q\}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa}^c \right] \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}^c). \end{aligned}$$

For the first part, from Section B.1, B.2, there holds

$$\begin{aligned} &\mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 \vee \sum_{i \in S_0} 1\{W_i \geq T_q\}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa} \right] \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}), \\ &\leq \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 \vee \sum_{i \in S_0} 1\{W_i \geq T_q\}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa} \right], \\ &\leq q \mathbb{E}[\mathcal{M}_{T_q}(W^s) \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa}] \leq q(1 + g(\kappa, \nu))^{3|S_0|-1}. \end{aligned}$$

For the second part, from Section B.3, there holds

$$\begin{aligned} &\mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 \vee \sum_{i \in S_0} 1\{W_i \geq T_q\}} \mid (\xi, \zeta) \in \Lambda_{\nu, \kappa}^c \right] \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}^c) \\ &\leq \mathbb{P}((\xi, \zeta) \in \Lambda_{\nu, \kappa}^c) \leq p \left[2 - 2\Phi\left(\frac{\kappa}{M_{X,D}}\right) \right] + m(2 - 2\Phi(\kappa)). \end{aligned}$$

Combining these two parts together gives

$$\begin{aligned} \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{1 \vee \sum_{i \in S_0} 1\{W_i \geq T_q\}} \right] &\leq q(1 + g(\kappa, \nu))^{3|S_0|-1} + \dots \\ &\dots + p \left[2 - 2\Phi\left(\frac{\kappa}{M_{X,D}}\right) \right] + m(2 - 2\Phi(\kappa)). \end{aligned}$$

This ends the proof. \square

REMARK. As shown in the Remark of Section D.3, when $\kappa \sim \ln \nu$, there holds $g(\kappa, \nu) \lesssim \frac{\ln \nu}{\sqrt{\nu}}$. Therefore from the upper bound for (modified) FDR with Split Knockoffs, there holds

$$\begin{aligned} \mathbb{E} \left[\frac{\sum_{i \in S_0} 1\{W_i \geq T_q\}}{\sum_{i \in S_0} 1\{W_i \leq -T_q\} + q^{-1}} \right] &\lesssim q + |S_0|g(\kappa, \nu) + p\Phi(-\ln \nu) + m\Phi(-\ln \nu), \\ &\approx q + |S_0|g(\kappa, \nu) \lesssim q + |S_0| \frac{\ln \nu}{\sqrt{\nu}}. \end{aligned}$$

Hence, it will be sufficient to take $\nu \gtrsim |S_0|^2 \ln |S_0|$ to make ν satisfy

$$q(1 + g(\kappa, \nu))^{3|S_0|-1} + p \left[2 - 2\Phi\left(\frac{\kappa}{M_{X,D}}\right) \right] + m(2 - 2\Phi(\kappa)) - 1 \leq \alpha,$$

for any constant $\alpha > 0$.

APPENDIX C: PROOF FOR THEOREM 4.1

In this section, we approach the model selection consistency problem by constructing Primal-Dual Witness (PDW) of Split LASSO regularization paths, following the same treatment in the traditional LASSO problem (Wainwright, 2009) and Split Linearized Bregman Iterations (Huang et al., 2016, 2020). We first introduce the successful Primal-Dual Witness which has a unique solution of Split LASSO; then we introduce the incoherence condition

for Split LASSO and establish the no-false-positive and sign consistency of Split LASSO regularization path, i.e. Theorem 4.1.

The set of witness $(\hat{\beta}^\lambda, \hat{\gamma}^\lambda, \hat{\rho}^\lambda) \in \mathbb{R}^p \times \mathbb{R}^m \times \mathbb{R}^m$ is constructed in the following way:

1. First, we set $\hat{\gamma}_{S_0}^\lambda = 0$, and obtain $(\hat{\beta}^\lambda, \hat{\gamma}_{S_1}^\lambda) \in \mathbb{R}^p \times \mathbb{R}^{|S_1|}$ by solving

$$(31) \quad (\hat{\beta}^\lambda, \hat{\gamma}_{S_1}^\lambda) = \underset{(\beta, \gamma_{S_1})}{\operatorname{argmin}} \left\{ \frac{1}{2n} \|y - X\beta\|_2^2 + \frac{1}{2\nu} \|D\beta - \gamma\|_2^2 + \lambda \|\gamma_{S_1}\|_1 \right\}.$$

2. Second, we choose $\hat{\rho}_{S_1}^\lambda = \partial \|\hat{\gamma}_{S_1}^\lambda\|_1$ as the subgradient of $\|\hat{\gamma}_{S_1}^\lambda\|_1$.
3. Third, for no-false-positive, we solve for $\hat{\rho}_{S_0}^\lambda \in \mathbb{R}^{S_0}$ satisfying the KKT condition (32), and check whether or not the dual feasibility condition $|\hat{\rho}_j^\lambda| < 1$ for all $j \in S_0$ is satisfied.
4. Fourth, for model selection (sign) consistency, we check whether $\hat{\rho}_{S_1}^\lambda = \operatorname{sign}(\beta_{S_1}^*)$ is satisfied.

We start from the KKT conditions that an optimal solution of the Split LASSO problem (4) satisfies, as they will be commonly used throughout this section. The KKT conditions are

$$(32a) \quad 0 = -(\Sigma_X + L_D)\beta(\lambda) + \frac{D^T}{\nu}\gamma(\lambda) + \left\{ \Sigma_X\beta^* + \frac{X^T}{n}\varepsilon \right\},$$

$$(32b) \quad \lambda\rho(\lambda) = \frac{D\beta(\lambda)}{\nu} - \frac{\gamma(\lambda)}{\nu},$$

where $\rho(\lambda) \in \partial \|\gamma(\lambda)\|_1$.

C.1. Primal-Dual Witness Property. In this section, we introduce the following lemma that gives the uniqueness property on the success of Primal-Dual Witness for Split LASSO problem.

LEMMA C.1. *When the PDW succeed, if the subproblem (31) is strictly convex, the solution $(\hat{\beta}, \hat{\gamma})$ is the unique optimal solution for split LASSO.*

PROOF. When PDW succeed, we have $\|\hat{\rho}_{S_0}\|_\infty < 1$, and therefore $(\hat{\beta}, \hat{\gamma})$ is a set of optimal solution, while $\hat{\rho}$ is in the subgradient of $\|\hat{\gamma}\|_1$. Let $(\tilde{\beta}, \tilde{\gamma})$ be any other optimal solution for Split LASSO. Denote

$$F(\beta, \gamma) = \frac{1}{2n} \|y - X\beta\|_2^2 + \frac{1}{2\nu} \|D\beta - \gamma\|_2^2.$$

Then there holds

$$F(\hat{\beta}, \hat{\gamma}) + \lambda \langle \hat{\rho}, \hat{\gamma} \rangle = F(\tilde{\beta}, \tilde{\gamma}) + \lambda \|\tilde{\gamma}\|_1,$$

which is

$$F(\hat{\beta}, \hat{\gamma}) - \lambda \langle \hat{\rho}, \tilde{\gamma} - \hat{\gamma} \rangle - F(\tilde{\beta}, \tilde{\gamma}) = \lambda (\|\tilde{\gamma}\|_1 - \langle \hat{\rho}, \tilde{\gamma} \rangle).$$

Also, by Equation (32), there holds $\frac{\partial F(\hat{\beta}, \hat{\gamma})}{\partial \hat{\beta}} = 0$, and $\frac{\partial F(\hat{\beta}, \hat{\gamma})}{\partial \hat{\gamma}} = -\lambda \hat{\rho}$. Therefore

$$(33) \quad F(\hat{\beta}, \hat{\gamma}) + \left\langle \frac{\partial F(\hat{\beta}, \hat{\gamma})}{\partial \hat{\gamma}}, \tilde{\gamma} - \hat{\gamma} \right\rangle + \left\langle \frac{\partial F(\hat{\beta}, \hat{\gamma})}{\partial \hat{\beta}}, \tilde{\beta} - \hat{\beta} \right\rangle - F(\tilde{\beta}, \tilde{\gamma}) = \lambda (\|\tilde{\gamma}\|_1 - \langle \hat{\rho}, \tilde{\gamma} \rangle).$$

Since F is convex, left hand side of Equation (33) is non-positive, then there holds

$$\|\tilde{\gamma}\|_1 \leq \langle \hat{\rho}, \tilde{\gamma} \rangle.$$

Since $|\hat{\rho}_{S_0}| < 1$, there holds $\tilde{\gamma}_{S_0} = 0$. Therefore $(\tilde{\beta}, \tilde{\gamma})$ is also an optimal solution for the subproblem (31). If the subproblem (31) is strictly convex, then $(\hat{\beta}, \hat{\gamma})$ is the only solution for split LASSO. \square

C.2. Incoherence Condition and Path Consistency. In this section, We first show on how we can get the incoherence condition and then we give the proof for Theorem 4.1.

From $D[\Sigma_X + L_D]^{-1} \times$ Equation (32a) $+ \nu \times$ Equation (32b), and the fact that $\gamma^* = D\beta^*$, there holds

$$\begin{aligned} \lambda\nu\hat{\rho} &= -\hat{\gamma} + \frac{D[\Sigma_X + L_D]^{-1}D^T\hat{\gamma}}{\nu} + D[\Sigma_X + L_D]^{-1}(\Sigma_X + L_D - L_D)\beta^* + \dots \\ &\quad \dots + D[\Sigma_X + L_D]^{-1}\frac{X^T}{n}\varepsilon, \\ &= -H_\nu(\hat{\gamma} - \gamma^*) + \omega, \end{aligned}$$

where $H_\nu = I_m - \frac{D[\Sigma_X + L_D]^{-1}D^T}{\nu}$, and $\omega = D[\Sigma_X + L_D]^{-1}\frac{X^T}{n}\varepsilon$. Define H_ν^{11} to be the covariance matrix for S_1 , H_ν^{00} to be the covariance matrix for S_0 , and H_ν^{10} , H_ν^{01} to be the covariance matrix between S_1 and S_0 , there holds

$$\lambda\nu \begin{bmatrix} \hat{\rho}_{S_1} \\ \hat{\rho}_{S_0} \end{bmatrix} = - \begin{bmatrix} H_\nu^{11} & H_\nu^{10} \\ H_\nu^{01} & H_\nu^{00} \end{bmatrix} \begin{bmatrix} \hat{\gamma}_{S_1} - \gamma_{S_1}^* \\ 0_{S_0} \end{bmatrix} + \begin{bmatrix} \omega_{S_1} \\ \omega_{S_0} \end{bmatrix},$$

which means

$$(34a) \quad \lambda\nu\hat{\rho}_{S_1} = -H_\nu^{11}(\hat{\gamma}_{S_1} - \gamma_{S_1}^*) + \omega_{S_1},$$

$$(34b) \quad \lambda\nu\hat{\rho}_{S_0} = -H_\nu^{01}(\hat{\gamma}_{S_1} - \gamma_{S_1}^*) + \omega_{S_0}.$$

Assume that H_ν^{11} is reversible and solve $\hat{\gamma}_{S_1} - \gamma_{S_1}^*$ from Equation (34a), there holds

$$(35) \quad \hat{\gamma}_{S_1} - \gamma_{S_1}^* = -\lambda\nu[H_\nu^{11}]^{-1}\hat{\rho}_{S_1} + [H_\nu^{11}]^{-1}\omega_{S_1}.$$

Then, plugging Equation (35) into Equation (34b), there holds

$$(36) \quad \hat{\rho}_{S_0} = H_\nu^{01}[H_\nu^{11}]^{-1}\hat{\rho}_{S_1} + \frac{1}{\lambda\nu}\{\omega_{S_0} - H_\nu^{01}[H_\nu^{11}]^{-1}\omega_{S_1}\}.$$

Then we can give the Incoherence Condition (22) from Equation (36). Below, we are going to give the proof for Theorem 4.1.

PROOF OF THEOREM 4.1.

1) From Equation (36) and Incoherence Condition (22), there holds

$$\begin{aligned} \|\hat{\rho}_{S_0}\|_\infty &\leq (1 - \chi) + \frac{1}{\lambda_n\nu}[\|\omega_{S_0}\|_\infty + (1 - \chi)\|\omega_{S_1}\|_\infty], \\ &\leq (1 - \chi) + \frac{1}{\lambda_n} \left\| \frac{\omega}{\nu} \right\|_\infty. \end{aligned}$$

Recall that $\omega = D[\Sigma_X + L_D]^{-1}\frac{X^T}{n}\varepsilon$, therefore $\frac{\omega_i}{\nu} = \frac{1}{\nu}D_i[\Sigma_X + L_D]^{-1}\frac{X^T}{n}\varepsilon$ is a Gaussian random variable with variance

$$\begin{aligned} &\frac{1}{\nu} \frac{\sigma^2}{n} D_{i,\cdot} [\Sigma_X + L_D]^{-1} \Sigma_X [\Sigma_X + L_D]^{-1} D_{i,\cdot}^T, \\ &\leq \frac{1}{\nu} \frac{\sigma^2}{n} D_{i,\cdot} [\Sigma_X + L_D]^{-1} D_{i,\cdot}^T \leq \frac{\sigma^2}{n}. \end{aligned}$$

Therefore

$$\mathbb{P} \left(\left\| \frac{\omega}{\lambda_n\nu} \right\|_\infty \geq \frac{\chi}{2} \right) \leq 2m \exp \left(-\frac{\lambda_n^2 n \chi^2}{8\sigma^2} \right).$$

Moreover, by $\lambda_n > \frac{1}{\chi} \sqrt{\frac{\sigma^2 \log p}{n}}$, there holds

$$\mathbb{P}\left(\|\hat{\rho}_{S_0}\|_\infty > 1 - \frac{\chi}{2}\right) \leq 2e^{-2c_1 n \lambda_n^2},$$

for some constant c_1 .

2) From Equation (35), there holds

$$\|\hat{\gamma}_{S_1} - \gamma_{S_1}^*\|_\infty \leq \nu \lambda_n \|[H_\nu^{11}]^{-1}\|_\infty + \|[H_\nu^{11}]^{-1}\omega_{S_1}\|_\infty.$$

Note that the first term here is a deterministic term, therefore we only need to estimate the second term. Recall that $\|\frac{\sigma^2}{n} D[\Sigma_X + L_D]^{-1} \Sigma_X [\Sigma_X + L_D]^{-1} D^T\|_2 \leq \nu \frac{\sigma^2}{n}$, there holds

$$\mathbb{P}(\|[H_\nu^{11}]^{-1}\omega_{S_1}\|_\infty > \nu t) \leq 2 \exp\left(-\frac{t^2 C_{\min} n}{\sigma^2} + \log |S_1|\right),$$

which holds for any subgaussian noise of scale σ^2 . Take $t = 4\sigma \lambda_n / \sqrt{C_{\min}}$, and note that $8n\lambda_n^2 > \log m > \log S_1$, there holds

$$\mathbb{P}(\|[H_\nu^{11}]^{-1}\omega_{S_1}\|_\infty > \nu \frac{4\sigma \lambda_n}{\sqrt{C_{\min}}}) \leq 2 \exp(-c_2 \lambda_n^2 n).$$

After all, there holds

$$\|\hat{\gamma}_{S_1} - \gamma_{S_1}^*\|_\infty \leq \lambda_n \nu \left[\frac{4\sigma}{\sqrt{C_{\min}}} + \|[H_\nu^{11}]^{-1}\|_\infty \right],$$

with probability greater than $1 - 2 \exp(-c_2 \lambda_n^2 n)$. Therefore for $c = \max\{c_1, c_2\}$, if $\min_{i \in S_1} \gamma_i^* > \lambda_n \nu \left[\frac{4\sigma}{\sqrt{C_{\min}}} + \|[H_\nu^{11}]^{-1}\|_\infty \right]$, with probability greater than

$$1 - 4 \exp(-c \lambda_n^2 n),$$

$\hat{\gamma}$ recovers the support set of γ^* . □

APPENDIX D: PROOF OF LEMMAS

In this section, we will give the proof for Lemmas mentioned in Section 3. We will first introduce some basic lemmas on the symmetric properties of $\zeta|\xi$, then we will provide proof for the Lemmas.

D.1. Some Basic Lemmas. In this section, we will first introduce some basic lemmas that illustrate the point that $\zeta|\xi$ shall be gradually independently symmetrically distributed around zero with the growth of ν .

LEMMA D.1. *Denote $R := D(\Sigma_X)^{-1} D^T$, there holds:*

$$\begin{aligned} \mathbb{E}(\zeta|\xi) &= -[\text{diag}(s)D][\Sigma_X]^{-1}(\xi - \Sigma_X \beta^*), \\ &\sim N(0, \sigma^2 s^2 \frac{R}{n}); \\ \text{var}(\zeta|\xi) &= \frac{\sigma^2}{n} (2sI_m - s^2 \nu I_m - s^2 R), \\ (37) \quad &\succeq \frac{\sigma^2}{n} \eta s I_m. \end{aligned}$$

REMARK. Here, $\mathbb{E}(\zeta|\xi) = O(s)$, and $\text{var}(\zeta|\xi) = O(s)$. As we have $s \leq \frac{1}{\nu}$, $\zeta|\xi$ will become symmetrically distributed around zero as ν increases.

PROOF. Since $\tilde{A}_{\gamma,1}^T \tilde{A}_{\gamma,1} = \text{diag}(\mathbf{s})(2I - \text{diag}(\mathbf{s})\nu)$, $\tilde{A}_{\gamma,1}^T \tilde{A}_{\gamma,1}$ is a diagonal matrix. The conditional variance of $\zeta|\xi$ will be

$$\begin{aligned} & \sigma^2 \frac{1}{n} \left[\tilde{A}_{\gamma,1}^T \tilde{A}_{\gamma,1} \right] - \sigma^2 \left[\frac{\tilde{A}_{\gamma,1}^T X}{n\sqrt{n}} \right] \left(\frac{\Sigma_X}{n} \right)^{-1} \left[X^T \frac{\tilde{A}_{\gamma,1}}{n\sqrt{n}} \right] \\ &= \frac{1}{n} \sigma^2 s(2 - s\nu)I_m - \sigma^2 \left[-\frac{\text{diag}(\mathbf{s})D}{n} \right] \left(\frac{\Sigma_X}{n} \right)^{-1} \left[-\frac{\text{diag}(\mathbf{s})D}{n} \right]^T, \\ &= \frac{\sigma^2}{n} (2sI_m - s^2\nu I_m - s^2R), \\ &= \frac{s\sigma^2}{n} (2I_m - s\nu I_m - sR). \end{aligned}$$

Take $s_0 = 2\lambda_{\min}(C_v)$. Note that there exists a split knockoff copy that takes $\text{diag}(s_0)$ as the separation between the feature matrix and the split knockoff copy. Therefore

$$\frac{\sigma^2}{n} (2s_0I_m - s_0^2\nu I_m - s_0^2R) \succeq 0,$$

which means

$$2I_m - s_0\nu I_m - s_0R \succeq 0.$$

Multiple $\frac{s}{s_0}$ on both side of the equation, there holds

$$2\frac{s}{s_0}I_m - s\nu I_m - sR \succeq 0.$$

Note that $s \leq \frac{2-\eta}{2}s_0$, and as a consequence,

$$\begin{aligned} 2I_m - s\nu I_m - sR &= \eta I_m + (2 - \eta)I_m - s\nu I_m - sR, \\ &\succeq \eta I_m + 2\frac{s}{s_0}I_m - s\nu I_m - sR, \\ &\succeq \eta I_m. \end{aligned}$$

Finally, there holds

$$\text{var}(\zeta|\xi) \succeq \frac{\sigma^2}{n} s\eta I_m.$$

The conditional mean of $\zeta|\xi$ will be

$$\begin{aligned} & 0 + \left[\frac{\tilde{A}_{\gamma,1}^T X}{n\sqrt{n}} \right] \left(\frac{\Sigma_X}{n} \right)^{-1} (\xi - \Sigma_X \beta^*) \\ &= -\frac{\text{diag}(\mathbf{s})D}{n} \left(\frac{\Sigma_X}{n} \right)^{-1} (\xi - \Sigma_X \beta^*), \\ &= -[\text{diag}(\mathbf{s})D][\Sigma_X]^{-1} (\xi - \Sigma_X \beta^*). \end{aligned}$$

Note that $(\xi - \Sigma_X \beta^*) \sim N(0, \sigma^2 \frac{\Sigma_X}{n})$, thus there holds

$$-[\text{diag}(\mathbf{s})D][\Sigma_X]^{-1} (\xi - \Sigma_X \beta^*) \sim N\left(0, \sigma^2 \frac{1}{n} [\text{diag}(\mathbf{s})D][\Sigma_X]^{-1} [\text{diag}(\mathbf{s})D]^T\right).$$

Therefore

$$\mathbb{E}(\zeta|\xi) \sim N\left(0, \sigma^2 s^2 \frac{R}{n}\right),$$

which ends the proof. \square

Then we can proceed further to the symmetry of $\text{sign}(\zeta_i r_i)|K_i$, and give the following lemma.

LEMMA D.2. *Conditional on $\Lambda_{\nu, \kappa}$, there holds*

$$(38) \quad \frac{1}{C(\kappa, \nu)} \mathbb{P}(\zeta_i r_i > 0 | K_i) \leq \mathbb{P}(\zeta_i r_i < 0 | K_i) \leq C(\kappa, \nu) \mathbb{P}(\zeta_i r_i > 0 | K_i),$$

where

$$(39) \quad C(\kappa, \nu) = \frac{\Phi\left(\frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}}\right)}{1 - \Phi\left(\frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}}\right) - 2\Phi(-\kappa + C(R)\kappa\sqrt{s})},$$

$C(R) := 1 + (\nu^{-1} + \nu^{-\frac{1}{2}})\eta^{-1} \max_i \|R_{i, -i}\|$, and $K_i = \{\zeta_{-i}, \xi\}$.

REMARK. Since $\Phi(x) \leq x + \frac{1}{2}$, there holds

$$(40) \quad \begin{aligned} C(\kappa, \nu) &\leq \frac{\frac{1}{2} + \frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}}}{\frac{1}{2} - \frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}} - 2\Phi(-\kappa + C(R)\kappa\sqrt{s})}, \\ &\leq \frac{\frac{1}{2} + \frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta} + 1} + 2\Phi(-\kappa + C(R)\kappa\sqrt{s})}{\frac{1}{2} - \frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}} - 2\Phi(-\kappa + C(R)\kappa\sqrt{s})}. \end{aligned}$$

PROOF. Denote $\mu_i = \mathbb{E}(\zeta_i | K_i)$, $\sigma_i^2 = \text{var}(\zeta_i | K_i)$. First, we are going to prove that $\eta \frac{\sigma_i^2}{n} s \leq \sigma_i < \frac{\sigma_i^2}{n} 2s$, where the right hand side is trivial. For the left hand side, by Inequality (37), consider the Schur complement for (i, i) -th element of

$$\frac{\sigma^2}{n} (2sI_m - s^2\nu I_m - s^2R) - \frac{\sigma^2}{n} \eta s I_m \succeq 0,$$

there holds

$$\begin{aligned} 0 &\preceq \left[\frac{\sigma^2}{n} (2s - s^2\nu - s^2R_{i,i}) - \frac{\sigma^2}{n} s\eta \right] - \dots \\ &\quad \dots - s^4 \frac{\sigma^2}{n} R_{i,-i} [(2sI_{m-1} - s^2\nu I_{m-1} - s^2R_{-i,-i}) - s\eta I_{m-1}]^{-1} R_{i,-i}^T, \\ &\preceq \left[\frac{\sigma^2}{n} (2s - s^2\nu - s^2R_{i,i}) - \frac{\sigma^2}{n} s\eta \right] - s^4 \frac{\sigma^2}{n} R_{i,-i} [2sI_{m-1} - s^2\nu I_{m-1} - s^2R_{-i,-i}]^{-1} R_{i,-i}^T, \end{aligned}$$

which means

$$\frac{\sigma^2}{n} (2s - s^2\nu - s^2R_{i,i}) - s^4 \frac{\sigma^2}{n} R_{i,-i} [2sI_{m-1} - s^2\nu I_{m-1} - s^2R_{-i,-i}]^{-1} R_{i,-i}^T \succeq \frac{\sigma^2}{n} s\eta.$$

From Lemma D.1, there holds

$$\begin{aligned} \sigma_i^2 &= \frac{\sigma^2}{n} (2s - s^2\nu - s^2R_{i,i}) - s^4 \frac{\sigma^2}{n} R_{i,-i} [(2sI_{m-1} - s^2\nu I_{m-1} - s^2R_{-i,-i})]^{-1} R_{i,-i}^T, \\ &\geq \eta \frac{\sigma^2}{n} s. \end{aligned}$$

Then we are going to find an upper bound for $|\nu_i|$. From Lemma D.1, for $I \in \Lambda_{\nu, \kappa}$, there holds

$$\begin{aligned} \|\mathbb{E}(\zeta|\xi)\|_\infty &= \left\| -[\text{diag}(\mathbf{s})D][\Sigma_X]^{-1}(\xi - \Sigma_X\beta^*) \right\|_\infty, \\ &< \kappa s \sigma \frac{1}{\sqrt{n}}. \end{aligned}$$

For $\|\zeta\|_\infty < \kappa\sqrt{s}\sigma\frac{1}{\sqrt{n}}$, by Inequality (37),

$$\begin{aligned} |\mu_i| &= |\mathbb{E}(\zeta_i|K_i)| = |\mathbb{E}(\zeta_i|\xi) + s^2 R_{i,-i} [2sI_{m-1} - s^2\nu I_{m-1} - s^2 R_{-i,-i}]^{-1} [\zeta_{-i} - \mathbb{E}(\zeta_{-i}|\xi)]|, \\ &< \kappa s \sigma \frac{1}{\sqrt{n}} + s \max_i \|R_{i,-i}\| \eta^{-1} (\kappa s \sigma \frac{1}{\sqrt{n}} + \kappa\sqrt{s}\sigma \frac{1}{\sqrt{n}}), \\ &< C(R) \kappa s \sigma \frac{1}{\sqrt{n}}, \end{aligned}$$

where $C(R) := 1 + (\nu^{-1} + \nu^{-\frac{1}{2}})\eta^{-1} \max_i \|R_{i,-i}\|$ and the last step is by the fact that $s \leq \frac{1}{\nu}$.

According to Lemma D.1, for $\|\zeta\|_\infty < \kappa\sqrt{s}\sigma\frac{1}{\sqrt{n}}$, there holds

$$\begin{aligned} &\mathbb{P}(\zeta_i r_i > 0 | K_i) \\ &= \mathbb{P}(\zeta_i > 0 | K_i, r_i > 0) \mathbb{P}(r_i > 0) + \dots \\ &\quad \dots + \mathbb{P}(\zeta_i < 0 | K_i, r_i < 0) \mathbb{P}(r_i < 0), \\ &= \mathbb{P}\left(\frac{\zeta_i - \mu_i}{\sigma_i} \geq -\frac{\mu_i}{\sigma_i} | K_i, r_i > 0\right) \mathbb{P}(r_i > 0) + \dots \\ &\quad \dots + \mathbb{P}\left(\frac{\zeta_i - \mu_i}{\sigma_i} \leq -\frac{\mu_i}{\sigma_i} | K_i, r_i < 0\right) \mathbb{P}(r_i < 0), \\ &\geq \mathbb{P}\left(\frac{\zeta_i - \mu_i}{\sigma_i} \geq \frac{|\mu_i|}{\sigma_i} | K_i, r_i > 0\right) \mathbb{P}(r_i > 0) + \dots \\ &\quad \dots + \mathbb{P}\left(\frac{\zeta_i - \mu_i}{\sigma_i} \leq -\frac{|\mu_i|}{\sigma_i} | K_i, r_i < 0\right) \mathbb{P}(r_i < 0), \\ (41) \quad &\geq 1 - \Phi\left(\frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}}\right), \end{aligned}$$

where the last step is due to the fact that $\frac{\zeta_i - \mu_i}{\sigma_i} \sim \mathcal{N}(0, 1)$ and $|\mu_i| \leq C(R) \frac{\kappa s \sigma}{\sqrt{n}}$, $\sigma_i^2 \geq \frac{\eta s \sigma^2}{n}$.

Thus as a consequence,

$$\begin{aligned} \mathbb{P}(\zeta_i r_i < 0 | K_i) &= 1 - \mathbb{P}(\zeta_i r_i > 0 | K_i), \\ (42) \quad &\leq \Phi\left(\frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}}\right). \end{aligned}$$

Similarly, there holds

$$(43) \quad \mathbb{P}\left(|\zeta_i r_i| > \kappa\sqrt{s}\sigma\frac{1}{\sqrt{n}} | K_i\right) \leq 2\Phi(-\kappa + C(R)\kappa\sqrt{s}).$$

Combining Eq. (41), (42) and (43), there holds

$$\frac{\mathbb{P}\left(-\kappa\sqrt{s}\sigma\frac{1}{\sqrt{n}} < \zeta_i r_i < 0 | K_i\right)}{\mathbb{P}\left(\kappa\sqrt{s}\sigma\frac{1}{\sqrt{n}} > \zeta_i r_i > 0 | K_i\right)} \leq \frac{\Phi\left(\frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}}\right)}{1 - \Phi\left(\frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}}\right) - 2\Phi(-\kappa + C(R)\kappa\sqrt{s})} =: C(\nu, \kappa).$$

Then we finished one part of our target, and the other half can be done similarly due to symmetry. We note that $C(\kappa, \nu) > 1$ since $\Phi\left(\frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}}\right) > 1/2$ while $1 - \Phi\left(\frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}}\right) < 1/2$. \square

After getting these basic lemmas on the symmetry of $\zeta|\xi$, we now proceed to prove the Lemmas.

D.2. Proof for Lemma 3.1 (a). In this section, we will give a proof for Lemma 3.1 (a) by analyzing the KKT conditions of the feature significance stage and knockoff significance stage.

The KKT condition that the solution $\gamma(\lambda)$ should satisfy is

$$\lambda\rho(\lambda) = \frac{D\beta(\lambda)}{\nu} - \frac{\gamma(\lambda)}{\nu},$$

where $\rho(\lambda) \in \partial\|\gamma(\lambda)\|_1$. The KKT condition that the solution $\tilde{\gamma}(\lambda)$ should satisfy is

$$\lambda\tilde{\rho}(\lambda) = \frac{D\beta(\lambda)}{\nu} - \frac{\tilde{\gamma}(\lambda)}{\nu} + \left\{ -s\gamma^* + \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}}\varepsilon \right\},$$

where $\tilde{\rho}(\lambda) \in \partial\|\tilde{\gamma}(\lambda)\|_1$. Hence we mainly focus on the following equations:

$$(44a) \quad \lambda\rho(\lambda) = \frac{D\beta(\lambda)}{\nu} - \frac{\gamma(\lambda)}{\nu},$$

$$(44b) \quad \lambda\tilde{\rho}(\lambda) = \frac{D\beta(\lambda)}{\nu} - \frac{\tilde{\gamma}(\lambda)}{\nu} + \left\{ -s\gamma^* + \frac{\tilde{A}_{\gamma,1}^T}{\sqrt{n}}\varepsilon \right\}.$$

From Equation (44a) - (44b), for $i \in S_0$, there holds

$$(45) \quad \lambda\rho_i(\lambda) - \lambda\tilde{\rho}_i(\lambda) = \frac{\tilde{\gamma}_i(\lambda)}{\nu} - \frac{\gamma_i(\lambda)}{\nu} - \zeta_i.$$

Below we take $i \in S_0$. For simplicity, we only consider the case of $r_i = 1$, since the symmetric case when $r_i = -1$ can be proved similarly. Now we are going to show $\{W_i < 0\} = \{\zeta_i > 0\} = \{r_i\zeta_i > 0\}$ ($r_i = 1$) in two directions.

(a) $\{W_i < 0\} \subseteq \{r_i\zeta_i > 0\}$. If $W_i < 0$, there holds $r'_i = r_i = 1$ and $Z'_i > Z_i$. Take $\lambda = Z'_i -$, there holds $\lambda\tilde{\rho}_i(\lambda) = \lambda \geq \lambda\rho_i(\lambda)$, $\tilde{\gamma}_i(\lambda) > 0$ and $\gamma_i(\lambda) = 0$. Therefore, from Equation (45), there holds

$$0 \geq \lambda\rho_i(\lambda) - \lambda\tilde{\rho}_i(\lambda) = \frac{\tilde{\gamma}_i(\lambda)}{\nu} - \frac{\gamma_i(\lambda)}{\nu} - \zeta_i > -\zeta_i,$$

which means $\zeta_i > 0$.

(b) $\{r_i\zeta_i > 0\} \subseteq \{W_i < 0\}$. For the case $r_i\zeta_i > 0$, there holds $\zeta_i > 0$. Take $\lambda = Z_i -$, then there holds $\lambda\rho_i(\lambda) = \lambda \geq \lambda\tilde{\rho}_i(\lambda)$ and $\gamma_i(\lambda) > 0$. Therefore, from Equation (45), there holds

$$\begin{aligned} 0 \leq \lambda\rho_i(\lambda) - \lambda\tilde{\rho}_i(\lambda) &= \frac{\tilde{\gamma}_i(\lambda)}{\nu} - \frac{\gamma_i(\lambda)}{\nu} - \zeta_i, \\ &< \frac{\tilde{\gamma}_i(\lambda)}{\nu} - \zeta_i. \end{aligned}$$

Therefore by the *continuity* of $\beta(\lambda)$, this inequality means $\tilde{\gamma}_i(Z_i) \geq \zeta_i > 0$, and therefore $Z'_i > Z_i$. Moreover, for $\lambda > Z_i$, there holds $\gamma_i(\lambda) = 0$. From Equation (45), there holds

$$-\lambda < \lambda\rho_i(\lambda) + \zeta = \lambda\tilde{\rho}_i(\lambda) + \frac{\tilde{\gamma}_i(\lambda)}{\nu},$$

which means $\tilde{\gamma}_i(\lambda) \geq 0$. As there holds $Z'_i > Z_i$, this further implies $r'_i = r_i = 1$. \square

D.3. Proof for Lemma 3.1 (b). In this section, we give a proof for Lemma 3.1 (b) based on the basic Lemma D.2.

PROOF. From Lemma D.2, there holds

$$\mathbb{P}(\zeta_i r_i < 0 | K_i) \leq C(\kappa, \nu) \mathbb{P}(\zeta_i r_i > 0 | K_i),$$

where $K_i = \{\zeta_{-i}, \xi\}$. Then there holds

$$1 = \mathbb{P}(\zeta_i r_i < 0 | K_i) + \mathbb{P}(\zeta_i r_i > 0 | K_i) \leq (C(\kappa, \nu) + 1) \mathbb{P}(\zeta_i r_i > 0 | K_i).$$

Therefore

$$\mathbb{P}(\zeta_i r_i > 0 | K_i) \geq \frac{1}{C(\kappa, \nu) + 1}.$$

Similarly, there holds

$$\mathbb{P}(\zeta_i r_i < 0 | K_i) \leq \frac{C(\kappa, \nu)}{C(\kappa, \nu) + 1},$$

then consequently,

$$\frac{1 - C(\kappa, \nu)}{2(C(\kappa, \nu) + 1)} \leq \mathbb{P}(\zeta_i r_i < 0 | K_i) - \frac{1}{2} \leq \frac{C(\kappa, \nu) - 1}{2(C(\kappa, \nu) + 1)}.$$

Then we can define

$$(46) \quad g(\kappa, \nu) := \frac{C(\kappa, \nu) - 1}{2(C(\kappa, \nu) + 1)},$$

where $C(\kappa, \nu)$ is defined in Equation (39). □

REMARK. From Inequality (40), there holds

$$\begin{aligned} g(\kappa, \nu) &= \frac{C(\kappa, \nu) - 1}{2(C(\kappa, \nu) + 1)}, \\ &\leq \frac{C(R)\kappa\sqrt{s}}{\sqrt{\eta}} + 2\Phi(-\kappa + C(R)\kappa\sqrt{s}). \end{aligned}$$

Take $\kappa \sim \ln \nu$. Since $s \leq \frac{1}{\nu}$, there holds

$$g(\kappa, \nu) \lesssim \frac{\ln \nu}{\sqrt{\nu}} + \Phi(-\ln \nu) \approx \frac{\ln \nu}{\sqrt{\nu}}.$$

D.4. Proof for Lemma 3.2. In this section, we first apply Lemma 3.1 and the basic lemmas to achieve the result that $\text{sign}(W)$ will be approximately independent Bernoulli random variables, then we give a proof for Lemma 3.2.

LEMMA D.3. For any $A \subset S_0$, take A^+, A^- to be an arbitrary division of A . Conditional on $\Lambda_{\nu, \kappa}$, there holds

$$\left[\frac{1}{2} - g(\kappa, \nu) \right]^{|A|} \leq \mathbb{P} \left([\cap_{i \in A^+} \{W_i > 0\}] \cap [\cap_{i \in A^-} \{W_i < 0\}] \mid \cap_{i \in A^c} \{W_i\} \right) \leq \left[\frac{1}{2} + g(\kappa, \nu) \right]^{|A|}.$$

Here, $A^c = \{1, 2, \dots, m\} - A$.

PROOF. First, conditional on $\Lambda_{\nu, \kappa}$, there holds

$$\left| \mathbb{P}(\zeta_i r_i < 0 | K_i) - \frac{1}{2} \right| \leq g(\kappa, \nu),$$

where $g(\kappa, \nu) = \frac{C(\kappa, \nu) - 1}{2(C(\kappa, \nu) + 1)}$. Note that from Lemma 3.1, $\{W_i > 0\} = \{\zeta_i r_i < 0\}$. Therefore

$$\left| \mathbb{P}(W_i > 0 | K_i) - \frac{1}{2} \right| \leq g(\kappa, \nu).$$

Therefore

$$(47) \quad \left| \frac{f(W_i > 0, K_i)}{f(K_i)} - \frac{1}{2} \right| \leq g(\kappa, \nu),$$

where $f(\cdot)$ here is the marginal density.

We will prove by doing mathematical induction on $|A|$. Take $i \notin A$, as K_i can determine W_{-i} , there holds

$$\begin{aligned} & \mathbb{P} \left(W_i > 0 \mid [\cap_{j \in A^+} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \cap [\cap_{i \in A^c} \{W_i\}] \right) \\ &= \frac{\mathbb{P} \left(\{W_i > 0\} \cap [\cap_{j \in A^+} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \cap [\cap_{i \in A^c} \{W_i\}] \right)}{\mathbb{P} \left([\cap_{j \in A^+} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \cap [\cap_{i \in A^c} \{W_i\}] \right)}, \\ &= \frac{\int_{[\cap_{j \in A^+} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \cap [\cap_{i \in A^c} \{W_i\}]} f(W_i > 0, K_i) dK_i}{\int_{[\cap_{j \in A^+} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \cap [\cap_{i \in A^c} \{W_i\}]} f(K_i) dK_i}. \end{aligned}$$

Combined with inequality (47), there holds

$$\left| \mathbb{P} \left(W_i > 0 \mid [\cap_{j \in A^+} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \cap [\cap_{i \in A^c} \{W_i\}] \right) - \frac{1}{2} \right| \leq g(\kappa, \nu).$$

Since

$$\begin{aligned} & \mathbb{P} \left([\cap_{j \in A^+ \cup \{i\}} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \mid \cap_{i \in A^c} \{W_i\} \right) \\ &= \mathbb{P} \left(W_i > 0 \mid [\cap_{j \in A^+} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \cap [\cap_{i \in A^c} \{W_i\}] \right) \cdots \\ & \quad \cdots \cdot \mathbb{P} \left([\cap_{j \in A^+} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \mid \cap_{i \in A^c} \{W_i\} \right), \end{aligned}$$

there holds

$$\left[\frac{1}{2} - g(\kappa, \nu) \right]^{|A|+1} \leq \mathbb{P} \left([\cap_{j \in A^+ \cup \{i\}} \{W_j > 0\}] \cap [\cap_{j \in A^-} \{W_j < 0\}] \mid \cap_{i \in A^c} \{W_i\} \right) \leq \left[\frac{1}{2} + g(\kappa, \nu) \right]^{|A|+1}.$$

Similarly, there holds

$$\left[\frac{1}{2} - g(\kappa, \nu) \right]^{|A|+1} \leq \mathbb{P} \left([\cap_{j \in A^+} \{W_j > 0\}] \cap [\cap_{j \in A^- \cup \{i\}} \{W_j < 0\}] \mid \cap_{i \in A^c} \{W_i\} \right) \leq \left[\frac{1}{2} + g(\kappa, \nu) \right]^{|A|+1}.$$

Finally, our desired result follows from mathematical induction. \square

We can now give a proof for Lemma 3.2 based on Lemma D.3.

PROOF FOR LEMMA 3.2.

Denote $\epsilon = |g(\kappa, \nu)|$ for short. If $V_s^+(k) = v$, $V_s^-(k) = k - v$, then $x_k^s = \frac{v}{k-v+1}$. Define

$V_s(k)^c$ as $\{W_i : |W_i^s| < T_k^s\} \cup \{W_i : i \in S_1\}$. Note that $|W_i^s|$ is completely determined by ξ , from Lemma D.3, for $1 \leq k \leq |S_0|$, there holds

$$(48) \quad \mathbb{P}(V_s^+(k) = v | V_s(k)^c) \leq \left(\frac{1}{2} + \epsilon\right)^k C_k^v,$$

and similarly

$$(49) \quad \mathbb{P}(V_s^+(k) = v, V_s^+(k-1) = v-1 | V_s(k)^c) \geq \left(\frac{1}{2} - \epsilon\right)^k C_{k-1}^{v-1}.$$

By (49) / (48), there holds

$$\mathbb{P}(V_s^+(k-1) = v-1 | V_s^+(k) = v, V_s(k)^c) \geq \left(\frac{\frac{1}{2} - \epsilon}{\frac{1}{2} + \epsilon}\right)^k \frac{v}{k}.$$

Denote $p = \mathbb{P}(V_s^+(k-1) = v-1 | V_s^+(k) = v, V_s(k)^c)$, for $v < k$, there holds

$$\begin{aligned} \mathbb{E}[x_{k+1}^0 | F_k^s] &= \frac{v-1}{k-v+1} p + \frac{v}{k-v} (1-p), \\ &= \left(\frac{v-1}{k-v+1} - \frac{v}{k-v}\right) p + \frac{v}{k-v}, \\ &= -\frac{k \cdot p}{(k-v+1)(k-v)} + \frac{v}{k-v}, \\ &\leq -\frac{v}{(k-v+1)(k-v)} \left(\frac{\frac{1}{2} - \epsilon}{\frac{1}{2} + \epsilon}\right)^k + \frac{v}{k-v} - \frac{v}{k-v+1} + \frac{v}{k-v+1}, \\ &= \frac{v}{k-v+1} + \frac{v}{(k-v+1)(k-v)} \left(1 - \left(\frac{\frac{1}{2} - \epsilon}{\frac{1}{2} + \epsilon}\right)^k\right), \\ &\leq x_k^s \left(2 - \left(\frac{\frac{1}{2} - \epsilon}{\frac{1}{2} + \epsilon}\right)^{|S_0|}\right), \\ &\leq x_k^s (1 + 4m\epsilon), \end{aligned}$$

where the second last step is by $k-v \geq 1$, and the last step is by $1 - (1-x)^m < xm$. For $v = k$, there holds $\mathbb{E}[x_{k+1}^s | F_k^s] = k-1 \leq k = x_k^s \leq x_k^s (1 + 4m\epsilon)$. \square

REMARK. We show in this remark that $\hat{k}_q^s := |S_0| + 1 - \operatorname{argmax}_i \{T_i^s \geq T_q\}$ is a stopping time with respect to the filtration F^s , where T_i^s is defined as the i -th largest element in $\{|W_j^s| : j \in S_0\}$.

By definition of stopping time, we need to show that $\{\hat{k}_q^s = |S_0| + 1 - k\} \in F_{|S_0|+1-k}^s$, which is equivalent to $\{\operatorname{argmax}_i \{T_i^s \geq T_q\} = k\} \in F_{|S_0|+1-k}^s$. To see this, we note that from the definitions of the filtration F^s and T_q :

- $F_{|S_0|+1-k}^s$ includes $\{W_i : i \in S_1\}$, $\{W_i : i \in S_0, |W_i^s| < T_k^s\}$, $V_s^+(k) := \#\{W_i > 0, i \in S_0, |W_i^s| \geq T_k^s\}$ and $V_s^-(k) := \#\{W_i < 0, i \in S_0, |W_i^s| \geq T_k^s\}$, therefore $F_{|S_0|+1-l}^s \subset F_{|S_0|+1-k}^s$ for all $l \geq k$ since $V_s^+(l)$ ($V_s^-(l)$) is decided by $V_s^+(k)$ ($V_s^-(k)$) and $\{W_i : i \in S_0, T_l^s \leq |W_i^s| < T_k^s\}$, respectively;

- the event $\Omega_k := \{\operatorname{argmax}_i \{T_i^s \geq T_q\} = k\}$ is defined by, for all $l > k$,

$$\frac{|\{i : W_i \leq -T_l^s\}|}{1 \vee |\{i : W_i \geq T_l^s\}|} > q, \text{ and } \frac{|\{i : W_i \leq -T_k^s\}|}{1 \vee |\{i : W_i \geq T_k^s\}|} \leq q,$$

i.e. decided by $\#\{i : W_i \leq -T_l^s\}$ and $\#\{i : W_i \geq T_l^s\}$ for all $l \geq k$.

Hence it suffices to show that $F_{|S_0|+1-k}^s$ includes

$$\#\{i : W_i \leq -T_k^s\} \text{ and } \#\{i : W_i \geq T_k^s\},$$

which by the inclusive property of filtration ($F_{|S_0|+1-l}^s \subset F_{|S_0|+1-k}^s$) includes $\#\{i : W_i \leq -T_l^s\}$ and $\#\{i : W_i \geq T_l^s\}$ for all $l \geq k$, as desired.

To see this, the first set is decomposed by

$$\begin{aligned} & \#\{W_i \leq -T_k^s\} \\ &= \#\{W_i \leq -T_k^s, i \in S_0\} + \#\{W_i \leq -T_k^s, i \in S_1\} \\ &= \#\{W_i \leq -T_k^s, i \in S_0, |W_i^s| \geq T_k^s\} + \#\{W_i \leq -T_k^s, i \in S_0, |W_i^s| < T_k^s\} + \dots \\ & \quad \dots + \#\{W_i \leq -T_k^s, i \in S_1\}, \\ &= \#\{W_i^s \leq -T_k^s, i \in S_0\} + \#\{W_i \leq -T_k^s, i \in S_0, |W_i^s| < T_k^s\} + \dots \\ & \quad \dots + \#\{W_i \leq -T_k^s, i \in S_1\}. \end{aligned}$$

Here the first part is equal to $V_s^-(k) = \sum_{i \in S_0} 1\{W_i^s \leq -T_k^s\}$, the second part is determined by $\{W_i, i \in S_0, |W_i^s| < T_k^s\}$, the third part is determined by $\{W_i, i \in S_1\}$, all of which are in the σ -field of $F_{|S_0|+1-k}^s$. This shows that $F_{|S_0|+1-k}^s$ includes $\#\{i : W_i \leq -T_k^s\}$.

Similarly, the second set is decomposed by

$$\#\{i : W_i \geq T_k^s\} = \#\{i : W_i \geq T_k^s, i \in S_0\} + \#\{i : W_i \geq T_k^s, i \in S_1\},$$

where the first part is equal to $V_s^+(k) = \sum_{i \in S_0} 1\{W_i^s \geq T_k^s\}$ and the second part is determined by $\{W_i, i \in S_1\}$, both of which are in the σ -field of $F_{|S_0|+1-k}^s$. Therefore $F_{|S_0|+1-k}^s$ includes $\#\{i : W_i \geq T_k^s\}$.

Combining these two sets together, we achieve our desired result. \square

D.5. Optional Stopping Lemma. In this section, we introduce a simple generalization on the optional stopping theorem for the almost supermartingale case.

LEMMA D.4 (Optional Stopping). *Given positive integers $m < n$, and n positive bounded random variables x_1, x_2, \dots, x_n . Suppose τ is a stopping time on $\{x_k\}_{k=1}^n$, with respect to filtration $\{F_k\}_{k=1}^n$. Suppose further for some $C > 0$, $k \geq m$, there holds $\mathbb{E}[x_{k+1}|F_k] \leq (1+C)x_k$. Then there holds*

$$\mathbb{E}[x_\tau 1\{\tau > m\}] \leq (1+C)^{n-m} \mathbb{E}[x_m 1\{\tau > m\}].$$

REMARK. Note that for the case $m = 1$, there holds

$$\begin{aligned} \mathbb{E}[x_\tau] &= \mathbb{E}[x_1 1\{\tau = 1\}] + \mathbb{E}[x_1 1\{\tau > 1\}], \\ &\leq \mathbb{E}[x_1 1\{\tau = 1\}] + (1+C)^{n-1} \mathbb{E}[x_1 1\{\tau > 1\}], \\ &\leq (1+C)^{n-1} \mathbb{E}[x_1]. \end{aligned}$$

PROOF. Define $y_k = x_k(1+C)^{n-k}$ for $k \geq m$, and $y_k = x_k(1+C)^{n-m}$ for $k < m$. Then for $1 \leq k \leq n$, there holds $x_k \leq y_k \leq x_k(1+C)^{n-m}$. And there holds

$$\begin{aligned} \mathbb{E}[x_\tau 1\{\tau > m\}] &= \sum_{k=m+1}^n \mathbb{E}[x_k 1\{\tau = k\}], \\ &\leq \sum_{k=m+1}^n \mathbb{E}[y_k 1\{\tau = k\}], \\ &= \mathbb{E}[y_\tau 1\{\tau > m\}]. \end{aligned}$$

Similarly,

$$\mathbb{E}[y_m 1\{\tau > m\}] \leq (1+C)^{n-m} \mathbb{E}[x_m 1\{\tau > m\}].$$

Therefore, we only need to prove that $\mathbb{E}[y_\tau 1\{\tau > m\}] \leq \mathbb{E}[y_m 1\{\tau > m\}]$. Note that $\mathbb{E}[y_{k+1}|F_k] \leq y_k$, which means for $k \geq m$, there holds $\mathbb{E}[y_{k+1} - y_k|F_k] \leq 0$. Then there holds

$$\begin{aligned} \mathbb{E}[y_\tau 1\{\tau > m\}] &= \sum_{k=m+1}^n \mathbb{E}[y_k 1\{\tau = k\}], \\ &= \sum_{k=m+1}^n \mathbb{E}[y_k (1\{\tau > k-1\} - 1\{\tau > k\})], \\ &= \mathbb{E}[y_{m+1} 1\{\tau > m\}] + \sum_{k=m+1}^{n-1} \mathbb{E}[(y_{k+1} - y_k) 1\{\tau > k\}], \\ &= \mathbb{E}[y_{m+1} 1\{\tau > m\}] + \sum_{k=m+1}^{n-1} \mathbb{E}[\mathbb{E}[(y_{k+1} - y_k)|F_k] 1\{\tau > k\}], \\ &\leq \mathbb{E}[y_{m+1} 1\{\tau > m\}]. \end{aligned}$$

Note that

$$\begin{aligned} \mathbb{E}[y_{m+1} 1\{\tau > m\}] &= \mathbb{E}[y_m 1\{\tau > m\}] + \mathbb{E}[(y_{m+1} - y_m) 1\{\tau > m\}], \\ &= \mathbb{E}[y_m 1\{\tau > m\}] + \mathbb{E}[\mathbb{E}[(y_{m+1} - y_m)|F_m] 1\{\tau > m\}], \\ &\leq \mathbb{E}[y_m 1\{\tau > m\}], \end{aligned}$$

which ends the proof. \square

D.6. Proof for Lemma 3.3. In this section, we will give the proof for Lemma 3.3 based on basic Lemma D.2 and Lemma D.3.

PROOF. First, from Lemma D.2, conditional on $I \in \Lambda_{\nu, \kappa}$, there holds

$$\left| \mathbb{P}(\zeta_i r_i < 0 | K_i) - \frac{1}{2} \right| \leq g(\kappa, \nu).$$

Moreover, from Lemma D.3, for any $A \subset \{1, 2, \dots, |S_0|\} := [|S_0|]$, there holds

$$\mathbb{P}([\cap_{i \in A} \{W_i > 0\}] \cap [\cap_{i \in [|S_0|] - A} \{W_i < 0\}]) \leq \left[\frac{1}{2} + g(\kappa, \nu) \right]^{|S_0|}.$$

Therefore for any $0 \leq k \leq |S_0|$, there holds

$$\mathbb{P}\left(\sum_{i \in S_0} 1\{W_i > 0\} = k\right) \leq C_{|S_0|}^k \left[\frac{1}{2} + g(\kappa, \nu)\right]^{|S_0|}.$$

Then consequently,

$$\begin{aligned} \mathbb{E}\left[\frac{\sum_{i \in S_0} 1\{W_i > 0\}}{1 + \sum_{i \in S_0} 1\{W_i < 0\}}\right] &\leq \left[\frac{1}{2} + g(\kappa, \nu)\right]^{|S_0|} \sum_{i=1}^{|S_0|} \frac{k}{|S_0| - k + 1} C_{|S_0|}^k, \\ &= \left[\frac{1}{2} + g(\kappa, \nu)\right]^{|S_0|} \sum_{i=1}^{|S_0|} C_{|S_0|}^{k-1}, \\ &\leq [1 + 2g(\kappa, \nu)]^{|S_0|}, \\ &\leq [1 + g(\kappa, \nu)]^{2|S_0|}. \end{aligned}$$

This ends the proof. □

APPENDIX E: MATLAB PACKAGE

Reproducible codes for experiments can be downloaded at

https://github.com/yao-lab/split_knockoffs.