

Skew cyclic codes over $\mathbb{Z}_4 + v\mathbb{Z}_4$ with derivation

Djoko Suprijanto ^{*} and Hopein Christofen Tang [†]

Abstract

In this work, we study a class of skew cyclic codes over the ring $R := \mathbb{Z}_4 + v\mathbb{Z}_4$, where $v^2 = v$, with an automorphism θ and a derivation Δ_θ , namely codes as modules over a skew polynomial ring $R[x; \theta, \Delta_\theta]$, whose multiplication is defined using an automorphism θ and a derivation Δ_θ . We investigate the structures of a skew polynomial ring $R[x; \theta, \Delta_\theta]$. We define Δ_θ -cyclic codes as a generalization of the notion of cyclic codes. The properties of Δ_θ -cyclic codes as well as dual Δ_θ -cyclic codes are derived. Some new codes over \mathbb{Z}_4 with good parameters are obtained via a Gray map as well as residue and torsion codes of these codes.

1 Introduction

Cyclic codes are an important class of codes from both theoretical and practical viewpoint. Theoretically, cyclic codes have a rich mathematical theory, in particular they have additional algebraic structures to make, practically, the process of encoding and decoding more efficient.

Cyclic codes over finite fields were first studied by Prange [22] in 1957. Since then, many coding theories have made a significant progress in the study of cyclic codes for both the so called random-error correction and burst-error correction (See, for example, [15] for the detailed description of random-error and burst-error correction).

In 2007, Boucher, Geiselmann, and Ulmer [6] (see also [7],[8]) extended the notion of cyclic codes over finite fields by using generator polynomials in non-commutative skew polynomial rings. The

^{*}Combinatorial Mathematics Research Group, Faculty of Mathematics and Natural Sciences, Institut Teknologi Bandung, Jl. Ganesha 10, Bandung, 40132, INDONESIA, djoko.suprijanto@itb.ac.id

[†]Combinatorial Mathematics Research Group, Faculty of Mathematics and Natural Sciences, Institut Teknologi Bandung, Jl. Ganesha 10, Bandung, 40132, INDONESIA, hopeinct@students.itb.ac.id

new notion of codes is called skew cyclic codes over finite fields. Since there are much more skew cyclic codes (over finite fields), this new class of codes allows to systematically search for codes with good properties. Boucher, Geiselmann, and Ulmer [6] also give many examples of codes which improve the previously best known linear codes over the fields.

Later, the notion of skew cyclic codes over finite fields was generalized to the skew cyclic codes over several kind of finite rings. Abualrub, Aydin, and Seneviratne [1] considered skew cyclic codes over $\mathbb{F}_2 + u\mathbb{F}_2$. They [1] also constructed optimal self-dual codes over the ring. Gursoy, Siap, and Yildiz [13] investigated structural properties of skew cyclic codes over $\mathbb{F}_q + v\mathbb{F}_q$. They [13] showed that that skew cyclic codes over this ring are principally generated. Later, the first author together with his coauthors considered structural aspects of skew cyclic codes over the ring A_k [16] and B_k [17] (c.f. [18]), respectively. Very recently, Benbelkacem, Ezerman, Abualrub, Aydin, and Batoul [4] considered the skew cyclic codes over the mixed alphabet which are also a finite ring, denoted by \mathbb{F}_4R . They [4] showed a natural connection between the skew cyclic codes over this ring to DNA codes.

In the next development, Boucher and Ulmer [9] generalized the notion of skew cyclic codes over finite fields to the skew cyclic codes over finite fields with derivation. They [9] also constructed MDS as well as MRD codes from certain families of the skew cyclic codes. Sharma and Bhaintwal [23] extended the study of these skew cyclic codes over a finite ring, namely over the ring $\mathbb{Z}_4 + u\mathbb{Z}_4$, with $u^2 = 1$. Via residue codes, Plotkin sum, or the Gray map they [23] defined, several linear codes over \mathbb{Z}_4 with good parameters were obtained. Continuing the study of [23], in this paper, we investigate a class of skew cyclic codes with derivation over the ring $\mathbb{Z}_4 + v\mathbb{Z}_4$, with $v^2 = v$.

The organization of the paper is as follows. In Section 2, we provide some definitions and basic facts related to the ring $\mathbb{Z}_4 + v\mathbb{Z}_4$ and also the linear codes over the ring $\mathbb{Z}_4 + v\mathbb{Z}_4$. We also define a Gray map from $\mathbb{Z}_4 + v\mathbb{Z}_4$ to \mathbb{Z}_4^2 , which can be extended naturally to define the Gray map from $(\mathbb{Z}_4 + v\mathbb{Z}_4)^n$ to \mathbb{Z}_4^{2n} . Several properties of the skew-polynomial ring $(\mathbb{Z}_4 + v\mathbb{Z}_4)[x; \theta, \Delta_\theta]$ are derived. The notion of Δ_θ -cyclic codes as well as dual of Δ_θ -cyclic codes as a generalization of cyclic codes together with their properties are investigated in Section 3 and Section 4, respectively. Several examples of linear codes over \mathbb{Z}_4 with good parameters obtained by using the Plotkin sum construction, a Gray map, or residue and torsion codes of these class of codes are provided in Section 5. The paper is ended by concluding remarks. We follow [15] for undefined terms in coding theory.

2 Preliminaries

In this section, we present some definitions together with some basic facts regarding the ring $\mathbb{Z}_4 + v\mathbb{Z}_4$, linear codes over the ring, and the skew-polynomial ring $(\mathbb{Z}_4 + v\mathbb{Z}_4)[x; \theta, \Delta_\theta]$ that are needed in the next sections.

2.1 The ring $\mathbb{Z}_4 + v\mathbb{Z}_4$

Let $R := \mathbb{Z}_4 + v\mathbb{Z}_4 = \{a + bv : a, b \in \mathbb{Z}_4\}$, with $v^2 = v$. This ring is isomorphic to the polynomial ring, namely $R \cong \frac{\mathbb{Z}_4[v]}{\langle v^2 - v \rangle}$. An element $a + bv \in R$ is a unit if and only if a and $a + b$ both are units in \mathbb{Z}_4 . Since the units of \mathbb{Z}_4 are 1 and 3, then the units of R are 1, 3, $1 + 2v$, and $3 + 2v$. Hence, the non-units of R are

$$\{0, 2, v, 2v, 3v, 1 + v, 1 + 3v, 2 + v, 2 + 2v, 2 + 3v, 3 + v, 3 + 3v\}.$$

R is a principal ideal ring and has 7 non-trivial ideals of R , namely

$$\langle 2v \rangle = \{0, 2v\},$$

$$\langle 2 + 2v \rangle = \{0, 2 + 2v\},$$

$$\langle 2 \rangle = \{0, 2, 2v, 2 + 2v\},$$

$$\langle v \rangle = \{0, v, 2v, 3v\} = \langle 3v \rangle,$$

$$\langle 3 + v \rangle = \{0, 1 + 3v, 2 + 2v, 3 + v\} = \langle 1 + 3v \rangle,$$

$$\langle 1 + v \rangle = \{0, 2, 2v, 1 + v, 1 + 3v, 2 + 2v, 3 + v, 3 + 3v\} = \langle 3 + 3v \rangle,$$

$$\langle 2 + v \rangle = \{0, 2, v, 2v, 3v, 2 + v, 2 + 2v, 2 + 3v\} = \langle 2 + 3v \rangle,$$

with $\langle 1 + v \rangle$ and $\langle 2 + v \rangle$ as maximal ideals. Hence, R is a semi-local ring.

For more information on the structures of the ring $R = \mathbb{Z}_4 + v\mathbb{Z}_4$, the reader can refer [3], [12], [19].

2.2 Linear codes over R

An important weight on \mathbb{Z}_4 is called a Lee weight. For $x \in \mathbb{Z}_4$, the Lee weight of x , denoted by $w_L(x)$, is defined as $w_L(0) = 0$, $w_L(1) = 1 = w_L(3)$, $w_L(2) = 2$. The Lee weight for any vector

$(r_0, r_1, \dots, r_{n-1}) \in \mathbb{Z}_4^n$ is defined as a rational sum of the Lee weights of its coordinates, namely $w_L(r_0, r_1, \dots, r_{n-1}) = w_L(r_0) + w_L(r_1) + \dots + w_L(r_{n-1})$.

Define a Gray map $\phi : R \longrightarrow \mathbb{Z}_4^2$ as

$$\phi(a + bv) = (a, a + b).$$

The Gray weight $w_G(a + bv)$ for any $a + bv \in R$ is defined as $w_G(a + bv) = w_L(\phi(a + bv))$. The Gray weights of the elements of R are given as follows.

x	0	1	2	3	v	$2v$	$3v$	$1 + v$
$w_G(x)$	0	2	4	2	1	2	1	3
x	$1 + 2v$	$1 + 3v$	$2 + v$	$2 + 2v$	$2 + 3v$	$3 + v$	$3 + 2v$	$3 + 3v$
$w_G(x)$	2	1	3	2	3	1	2	3

The Gray map ϕ is extended naturally to $\Phi : R^n \longrightarrow \mathbb{Z}_4^{2n}$ as

$$\Phi(a_0 + b_0v, a_1 + b_1v, \dots, a_{n-1} + b_{n-1}v) = (a_0, a_0 + b_0, a_1, a_1 + b_1, \dots, a_{n-1}, a_{n-1} + b_{n-1}),$$

and the Gray weight of any vector $\mathbf{x} \in R^n$ is defined as the rational sum of Gray weights of its coordinates.

A code C of length n over R is a non-empty subset of R^n . A code C is called linear over R if it is an R -submodule of R^n . A linear code over R is called free if it is free as an R -submodule. The Gray distance of any vectors $\mathbf{x}, \mathbf{y} \in R^n$ is defined as $d_G(\mathbf{x}, \mathbf{y}) = w_G(\mathbf{x} - \mathbf{y})$ and the Lee distance of any vectors $\mathbf{x}, \mathbf{y} \in \mathbb{Z}_4^n$ is defined as $d_L(\mathbf{x}, \mathbf{y}) = w_L(\mathbf{x} - \mathbf{y})$. The minimum Gray distance $d_G(C)$ and the minimum Lee distance $d_L(C)$ of C is defined as $d_G(C) := \min\{d_G(\mathbf{x}, \mathbf{y}) : \mathbf{x}, \mathbf{y} \in C, \mathbf{x} \neq \mathbf{y}\}$ and $d_L(C) := \min\{d_L(\mathbf{x}, \mathbf{y}) : \mathbf{x}, \mathbf{y} \in C, \mathbf{x} \neq \mathbf{y}\}$, respectively. It is easy to verify that the Gray map Φ is a distance-preserving map (isometry) from (R^n, d_G) to (\mathbb{Z}_4^{2n}, d_L) .

A (linear) code over the ring \mathbb{Z}_4 is defined similarly. We write the parameters of a linear code C over \mathbb{Z}_4 as $[n, 4^{k_1}2^{k_2}, d_L]$, where n is a length of C , $|C| = 4^{k_1}2^{k_2}$, and $d_L = d_L(C)$. Moreover, following Hammons, Kumar, Calderbank, Sloane, and Solé [14] (c.f. [25]), we say that the code C is of type $4^{k_1}2^{k_2}$.

For a linear code $C \subseteq R^n$ over R , we define a residue code $Res(C)$ and a torsion code $Tor(C)$ of C , respectively, as follows

$$Res(C) := \{\mathbf{a} : \mathbf{a} + \mathbf{b}v \in C, \text{ for some } \mathbf{b} \in \mathbb{Z}_4^n\},$$

and

$$\text{Tor}(C) := \{\mathbf{b} : \mathbf{b}v \in C\}.$$

We note that $\text{Res}(C)$ and $\text{Tor}(C)$ are linear codes of length n over \mathbb{Z}_4 .

Regarding the Residue and Torsion codes, we have the following property.

Lemma 2.1. *Let C be a free linear code of length n over R and $\{\mathbf{c}_1, \mathbf{c}_2, \dots, \mathbf{c}_k\}$, with $\mathbf{c}_i = \mathbf{a}_i + \mathbf{b}_i v$, be a basis of C . Then the followings hold:*

(1) $\text{Res}(C)$ is a free linear code over \mathbb{Z}_4 with $\{\mathbf{a}_1, \mathbf{a}_2, \dots, \mathbf{a}_k\}$ as a basis.

(2) $\text{Tor}(C)$ is a free linear code over \mathbb{Z}_4 with $\{\mathbf{a}_1 + \mathbf{b}_1, \mathbf{a}_2 + \mathbf{b}_2, \dots, \mathbf{a}_k + \mathbf{b}_k\}$ as a basis.

Proof. (1) Let $\mathbf{a} \in \text{Res}(C)$. Then there exists $\mathbf{b} \in \mathbb{Z}_4^n$ such that $\mathbf{a} + \mathbf{b}v \in C$. Since $\{\mathbf{c}_1, \mathbf{c}_2, \dots, \mathbf{c}_k\}$ is a basis of C , then there exist $r_1, r_2, \dots, r_k \in R$, with $r_i = s_i + t_i v$, for $i \in [1, k]_{\mathbb{Z}}$, such that

$$\begin{aligned} \mathbf{a} + \mathbf{b}v &= \sum_{i=1}^k r_i \mathbf{c}_i \\ &= \sum_{i=1}^k (s_i + t_i v)(\mathbf{a}_i + \mathbf{b}_i v) \\ &= \sum_{i=1}^k s_i \mathbf{a}_i + \left(\sum_{i=1}^k (s_i \mathbf{b}_i + t_i \mathbf{a}_i + t_i \mathbf{b}_i) \right) v. \end{aligned}$$

Hence, $\mathbf{a} = \sum_{i=1}^k s_i \mathbf{a}_i$, and we conclude that $\{\mathbf{a}_1, \mathbf{a}_2, \dots, \mathbf{a}_k\}$ generates $\text{Res}(C)$. Now, suppose on the contrary that $\{\mathbf{a}_1, \mathbf{a}_2, \dots, \mathbf{a}_k\}$ is linearly dependent. Then there exist $m_1, m_2, \dots, m_k \in \mathbb{Z}_4$, not all zero, such that

$$\mathbf{0} = \sum_{i=1}^k m_i \mathbf{a}_i.$$

But,

$$\begin{aligned} \sum_{i=1}^k (m_i + 3m_i v) \mathbf{c}_i &= \sum_{i=1}^k (m_i + 3m_i v)(\mathbf{a}_i + \mathbf{b}_i v) \\ &= \sum_{i=1}^k m_i \mathbf{a}_i + (m_i \mathbf{b}_i + 3m_i \mathbf{a}_i + 3m_i \mathbf{b}_i) v \\ &= \sum_{i=1}^k m_i \mathbf{a}_i + 3 \left(\sum_{i=1}^k m_i \mathbf{a}_i \right) v \\ &= \mathbf{0}. \end{aligned}$$

Since m_1, m_2, \dots, m_k not all are zeros, then $m_1 + 3m_1v, m_2 + 3m_2v, \dots, m_k + 3m_kv$ not all are zeros, contradict to the fact that $\{\mathbf{c}_1, \mathbf{c}_2, \dots, \mathbf{c}_k\}$ is a basis for C . We conclude that $\{\mathbf{a}_1, \mathbf{a}_2, \dots, \mathbf{a}_k\}$ is a basis of $\text{Res}(C)$.

(2) Similar to (1).

□

Now, let C be a free linear code of length n over R , with a basis $\{\mathbf{c}_1, \mathbf{c}_2, \dots, \mathbf{c}_k\}$. For $\mathbf{c}' \in \Phi(C)$, there exists $\mathbf{c} \in C$ such that $\mathbf{c}' = \Phi(\mathbf{c})$. Let $\mathbf{c} = \sum_{i=1}^k r_i \mathbf{c}_i \in C$, with some $r_i = s_i + t_i v$, for $i \in [1, k]_{\mathbb{Z}}$. We have

$$\begin{aligned} \Phi(\mathbf{c}) &= \Phi\left(\sum_{i=1}^k r_i \mathbf{c}_i\right) \\ &= \sum_{i=1}^k \Phi((s_i + t_i v) \mathbf{c}_i) \\ &= \sum_{i=1}^k s_i \Phi(\mathbf{c}_i) + t_i \Phi(\mathbf{c}_i v). \end{aligned}$$

It means that $\{\Phi(\mathbf{c}_1), \Phi(\mathbf{c}_1 v), \Phi(\mathbf{c}_2), \Phi(\mathbf{c}_2 v), \dots, \Phi(\mathbf{c}_k), \Phi(\mathbf{c}_k v)\}$ generates $\Phi(C)$. Next, suppose that $\{\Phi(\mathbf{c}_1), \Phi(\mathbf{c}_1 v), \Phi(\mathbf{c}_2), \Phi(\mathbf{c}_2 v), \dots, \Phi(\mathbf{c}_k), \Phi(\mathbf{c}_k v)\}$ is linearly dependent. Then, there exist $m_1, m_2, \dots, m_k, \ell_1, \ell_2, \dots, \ell_k \in \mathbb{Z}_4$, not all are zeros, such that

$$\begin{aligned} 0 &= \sum_{i=1}^k m_i \Phi(\mathbf{c}_i) + \ell_i \Phi(\mathbf{c}_i v) \\ &= \sum_{i=1}^k \Phi((m_i + \ell_i v) \mathbf{c}_i) \\ &= \Phi\left(\sum_{i=1}^k (m_i + \ell_i v) \mathbf{c}_i\right). \end{aligned}$$

The last condition implies that $\sum_{i=1}^k (m_i + \ell_i v) \mathbf{c}_i = 0$. Since not all $m_1, m_2, \dots, m_k, \ell_1, \ell_2, \dots, \ell_k$ are zeros, then $\{\mathbf{c}_1, \mathbf{c}_2, \dots, \mathbf{c}_k\}$ becomes linearly dependent, a contradiction. We conclude that $\{\Phi(\mathbf{c}_1), \Phi(\mathbf{c}_1 v), \Phi(\mathbf{c}_2), \Phi(\mathbf{c}_2 v), \dots, \Phi(\mathbf{c}_k), \Phi(\mathbf{c}_k v)\}$ is a basis of $\Phi(C)$. Hence, we have proven the following theorem.

Theorem 2.2. *If C be a free linear code of length n over R having a basis $\{\mathbf{c}_1, \mathbf{c}_2, \dots, \mathbf{c}_k\}$, then $\{\Phi(\mathbf{c}_1), \Phi(\mathbf{c}_1 v), \Phi(\mathbf{c}_2), \Phi(\mathbf{c}_2 v), \dots, \Phi(\mathbf{c}_k), \Phi(\mathbf{c}_k v)\}$ is a basis of a free linear code $\Phi(C)$.*

2.3 Skew-polynomial ring $R[x; \theta, \Delta_\theta]$

We first recall the definition of a derivation on the ring \mathbf{R} following [9].

Definition 1. Let \mathbf{R} be a finite ring and $\Theta : \mathbf{R} \longrightarrow \mathbf{R}$ be an automorphism of \mathbf{R} . Then a map $\Delta_{\Theta} : \mathbf{R} \longrightarrow \mathbf{R}$ is called a derivation on \mathbf{R} if the following two conditions are satisfied:

- (i) $\Delta_{\Theta}(x + y) = \Delta_{\Theta}(x) + \Delta_{\Theta}(y)$, and
- (ii) $\Delta_{\Theta}(xy) = \Delta_{\Theta}(x)y + \Theta(x)\Delta_{\Theta}(y)$.

Let \mathbf{R} be a ring with automorphism Θ and derivation Δ_{Θ} . The skew-polynomial ring $\mathbf{R}[x; \Theta, \Delta_{\Theta}]$ is the set of all polynomials over \mathbf{R} with ordinary addition of polynomials and multiplication defined by

$$xa := \Theta(a)x + \Delta_{\Theta}(a),$$

for any $a \in \mathbf{R}$. This multiplication is extended to all polynomials in $\mathbf{R}[x; \Theta, \Delta_{\Theta}]$ in the usual manner. This kind of ring was introduced by Ore [21] in 1933, where \mathbf{R} is equal to the finite field \mathbb{F}_q . See also McDonald [20].

Consider a map $\theta : R \longrightarrow R$ defined by $\theta(a + bv) = a + b - bv$. It is easy to see that θ define an automorphism of R . Moreover, since for all $a + bv \in R$ we have $\theta^2(a + bv) = a + bv$, we conclude that the order of θ is 2.

The following lemma shows a derivation on the ring R .

Lemma 2.3. For all $x \in R$, a map $\Delta_{\theta} : R \longrightarrow R$ such that

$$\Delta_{\theta}(x) = (1 + 2v)(\theta(x) - x)$$

defines a derivation on R .

Proof. Let $a + bv, c + dv \in R$. We have

$$\begin{aligned} \Delta_{\theta}((a + bv) + (c + dv)) &= \Delta_{\theta}((a + c) + (b + d)v) \\ &= (1 + 2v)((a + c) + (b + d) - (b + d)v - ((a + c) + (b + d)v)) \\ &= b + d \\ &= (1 + 2v)(b - 2bv) + (1 + 2v)(d - 2dv) \\ &= \Delta_{\theta}(a + bv) + \Delta_{\theta}(c + dv), \end{aligned}$$

and

$$\begin{aligned}
\Delta_\theta((a + bv)(c + dv)) &= \Delta_\theta(ac + (bc + ad + bd)v) \\
&= (1 + 2v)((bc + ad + bd) - 2(bc + ad + bd)v) \\
&= (bc + ad + bd) \\
&= b(c + dv) + (a + b - bv)d \\
&= (1 + 2v)(b - 2bv)(c + dv) \\
&\quad + (a + b - bv)(1 + 2v)(d - 2dv) \\
&= \Delta_\theta(a + bv)(c + dv) + \theta(a + bv)\Delta_\theta(c + dv),
\end{aligned}$$

and hence, by definition, Δ_θ is a derivation on R . □

We prove several properties related to the derivation Δ_θ on R . We begin with the following.

Lemma 2.4. *Let $\Delta_\theta(x) = (1 + 2v)(\theta(x) - x)$ be a derivation on R . Then the following holds:*

- (1) $\Delta_\theta\theta + \theta\Delta_\theta \equiv 0$.
- (2) $\Delta_\theta\Delta_\theta \equiv 0$.
- (3) for all $x \in R$, $\Delta_\theta(x) = 0 \iff \theta(x) = x$.

Proof. Let $\Delta_\theta(x) = (1 + 2v)(\theta(x) - x)$ be a derivation on R .

- (1) For $a + bv \in R$,

$$\begin{aligned}
\Delta_\theta(\theta(a + bv)) + \theta(\Delta_\theta(a + bv)) &= \Delta_\theta(a + b - bv) - \theta((1 + 2v)(a + b - bv - (a + bv))) \\
&= (1 + 2v)(-b + 2bv) + \theta((1 + 2v)(b - 2bv)) \\
&= 0.
\end{aligned}$$

- (2) For $a + bv \in R$,

$$\begin{aligned}
\Delta_\theta(\Delta_\theta(a + bv)) &= \Delta_\theta((1 + 2v)(a + b - bv - (a + bv))) \\
&= \Delta_\theta((1 + 2v)(b - 2bv)) \\
&= 0.
\end{aligned}$$

- (3) Clear from the definition of derivation. □

Lemma 2.5. For all $a \in R$, we have $x^2a = ax^2$.

Proof. Since $xa = \theta(a)x + \Delta_\theta(a)$, then

$$\begin{aligned} x^2a &= x\theta(a)x + x\Delta_\theta(a) \\ &= (\theta^2(a)x + \Delta_\theta(\theta(a)))x + \theta(\Delta_\theta(a))x + \Delta_\theta^2(a) \\ &= \theta^2(a)x^2 + ((\Delta_\theta\theta + \theta\Delta_\theta)(a))x + \Delta_\theta^2(a) \\ &= ax^2 \text{ (by Lemma 2.4).} \end{aligned}$$

□

We can generalize the Lemma 2.5 by a mathematical induction.

Corollary 2.6. For all $a \in R$, $n \in \mathbb{Z}^+$, we have

$$x^n a = \begin{cases} (\theta(a)x + \Delta_\theta(a))x^{n-1}, & n \text{ is odd,} \\ ax^n, & n \text{ is even.} \end{cases}$$

Proof. We have known that $xa = \theta(a)x + \Delta_\theta(a)$ and $x^2a = ax^2$. Suppose the above statement holds for all $n \leq k$, with $k \geq 2$. Consider two cases. If $k + 1$ is even, then $k - 1$ is also even. From the hypothesis of induction,

$$x^{k+1}a = x^2(x^{k-1}a) = x^2ax^{k-1} = (ax^2)x^{k-1} = ax^{k+1}.$$

If $k + 1$ is odd, then k is even. Again, from the hypothesis of induction,

$$x^{k+1}a = x(x^k a) = xax^k = (xa)x^k = (\theta(a)x + \Delta_\theta(a))x^k.$$

Then the result follows. □

Let us consider the following example.

Example 2.7. Let $\Delta_\theta(x) = (1 + 2v)(\theta(x) - x)$ be a derivation on R . Let $f(x) = f_0 + f_1x + x^2$ and $g(x) = g_0 + g_1x$ be two polynomials in $R[x; \theta, \Delta_\theta]$. Then

$$f(x) + g(x) = (f_0 + g_0) + (f_1 + g_1)x + x^2 = g(x) + f(x).$$

Also, by applying Corollary 2.6,

$$\begin{aligned}
f(x)g(x) &= (f_0 + f_1x + x^2)(g_0 + g_1x) \\
&= f_0(g_0 + g_1x) + f_1x(g_0 + g_1x) + x^2(g_0 + g_1x) \\
&= f_0g_0 + f_0g_1x + f_1(\theta(g_0)x + \Delta_\theta(g_0)) + f_1(\theta(g_1)x + \Delta_\theta(g_1))x + g_0x^2 + g_1x^3 \\
&= (f_0g_0 + f_1\Delta_\theta(g_0)) + (f_0g_1 + f_1\theta(g_0) + f_1\Delta_\theta(g_1))x + (f_1\theta(g_1) + g_0)x^2 + g_1x^3,
\end{aligned}$$

while

$$\begin{aligned}
g(x)f(x) &= (g_0 + g_1x)(f_0 + f_1x + x^2) \\
&= g_0(f_0 + f_1x + x^2) + g_1x(f_0 + f_1x + x^2) \\
&= g_0f_0 + g_0f_1x + g_0x^2 + g_1(\theta(f_0)x + \Delta_\theta(f_0)) + g_1(\theta(f_1)x + \Delta_\theta(f_1))x + g_1x^3 \\
&= (g_0f_0 + g_1\Delta_\theta(f_0)) + (g_0f_1 + g_1\theta(f_0) + g_1\Delta_\theta(f_1))x + (g_0 + g_1\theta(f_1))x^2 + g_1x^3.
\end{aligned}$$

Therefore, $f(x)g(x) \neq g(x)f(x)$, and hence $R[x; \theta, \Delta_\theta]$ is non-commutative. \diamond

Let R^θ be a subset of R , fixed element-wise by θ , namely $R^\theta := \{a \in R : \theta(a) = a\}$. It is easy to verify that R^θ is a subring of R . In our case, $R^\theta = \{0, 1, 2, 3\} = \mathbb{Z}_4$. Also, for all $a \in R^\theta$, we have $\Delta_\theta(a) = 0$. It implies, by Corollary 2.6, that for all $a \in R^\theta$ and $n \in \mathbb{Z}^+$, we have $x^n a = ax^n$.

Definition 2. A polynomial $f(x) \in R[x; \theta, \Delta_\theta]$ is called a central element if it satisfies

$$f(x)a(x) = a(x)f(x),$$

for all $a(x) \in R[x; \theta, \Delta_\theta]$. The center of $R[x; \theta, \Delta_\theta]$, denoted by $Z(R[x; \theta, \Delta_\theta])$, is defined as

$$Z(R[x; \theta, \Delta_\theta]) := \{f(x) \in R[x; \theta, \Delta_\theta] : f(x)a(x) = a(x)f(x), \text{ for all } a(x) \in R[x; \theta, \Delta_\theta]\}.$$

The central element satisfies the following property.

Theorem 2.8. $f(x) \in Z(R[x; \theta, \Delta_\theta])$ if and only if $f(x) \in R^\theta[x]$ and for all odd integers i , the coefficient of x^i is equal to 0.

Proof. (\implies) Let $f(x) = f_0 + f_1x + f_2x^2 + \cdots + f_kx^k$. Observe that

$$xf(x) = \sum_{i=0}^k (xf_i)x^i = \sum_{i=0}^k (\theta(f_i)x + \Delta_\theta(f_i))x^i = \Delta_\theta(f_0) + \sum_{i=1}^k (\theta(f_{i-1}) + \Delta_\theta(f_i))x^i + \theta(f_k)x^{k+1}$$

and

$$f(x)x = f_0x + f_1x^2 + \cdots + f_kx^{k+1}.$$

Since $f(x)$ is a central element, then $xf(x) = f(x)x$, which implies

$$\Delta_\theta(f_0) = 0, \quad (1)$$

$$\theta(f_{i-1}) + \Delta_\theta(f_i) = f_{i-1}, \text{ for } 1 \leq i \leq k, \quad (2)$$

$$\theta(f_k) = f_k. \quad (3)$$

The Equation (3) implies $f_k \in R^\theta$. By Lemma 2.4 we have $\Delta_\theta(f_k) = 0$. By substituting the Equation (2) repeatedly we obtain $f_1, f_2, \dots, f_{k-1} \in R^\theta$. Moreover, by Equation (1) and Lemma 2.4 obtain $f_0 \in R^\theta$. Thus, $f(x) \in R^\theta[x]$.

Now, take $a = v \in R$. Observe that

$$af(x) = af_0 + af_1x + \dots + af_kx^k$$

and

$$f(x)a = f_0a + \sum_{i=1}^k f_i(x^i a).$$

In this case, for $0 \leq 2j < k$, the coefficient of x^{2j} in $af(x)$ and $f(x)a$ is equal to af_{2j} and $f_{2j}a + f_{2j+1}\Delta_\theta(a)$, respectively. Since $f(x)$ is a central element and $\Delta_\theta(a) = 1$, we conclude that $f_{2j+1} = 0$.

(\Leftarrow) Let $f(x) = f_0 + f_2x^2 + f_4x^4 + \dots + f_{2m}x^{2m} \in R^\theta[x]$. Let $a(x) = a_0 + a_1x + a_2x^2 + \dots + a_kx^k \in R[x; \theta, \Delta_\theta]$. Observe that

$$(f_{2i}x^{2i})(a_jx^j) = f_{2i}(x^{2i}a_j)x^j = f_{2i}a_jx^{2i+j},$$

and

$$\begin{aligned} (a_jx^j)(f_{2i}x^{2i}) &= a_j(x^j f_{2i})x^{2i} \\ &= \begin{cases} a_j\theta(f_{2i})x^{2i+j} + a_j\Delta_\theta(f_{2i})x^{2i+j-1}, & j \text{ is odd,} \\ a_jf_{2i}x^{2i+j}, & j \text{ is even,} \end{cases} \\ &= a_jf_{2i}x^{2i+j} \text{ (by Lemma 2.4).} \end{aligned}$$

Then, $f_{2i}x^{2i}(a_jx^j) = (a_jx^j)(f_{2i}x^{2i})$, for all i, j . Hence, $f(x)a = af(x)$. \square

Lemma 2.9 (Right-Division Algorithm). *Let $f(x), g(x) \in R[x; \theta, \Delta_\theta]$ such that the leading coefficient of $g(x)$ is a unit. Then there exist $q(x), r(x) \in R[x; \theta, \Delta_\theta]$ such that*

$$f(x) = q(x)g(x) + r(x),$$

with $r(x) = 0$ or $\deg r(x) < \deg g(x)$.

Proof. Let $f(x) = f_0 + f_1x + f_2x^2 + \cdots + f_r x^r$ and $g(x) = g_0 + g_1x + g_2x^2 + \cdots + g_s x^s$, where g_s is unit, be two polynomials in $R[x; \theta, \Delta_\theta]$. If $r < s$, we can choose $q(x) = 0$ and $r(x) = f(x)$ to get the desired result. If $r \geq s$, define a polynomial $h(x) := f(x) - A(x)g(x)$, where

$$A(x) = \begin{cases} f_r \theta(g_s^{-1}) x^{r-s}, & r-s \text{ is odd,} \\ f_r g_s^{-1} x^{r-s}, & r-s \text{ is even.} \end{cases}$$

If $r - s$ is odd, then the coefficient of x^r in $A(x)g(x)$ is equal to the coefficient of x^r in $f_r \theta(g_s^{-1}) x^{r-s} g_s x^s$, namely

$$f_r \theta(g_s^{-1}) \theta(g_s) = f_r \theta(g_s^{-1} g_s) = f_r.$$

If $r - s$ is even, then the coefficient of x^r in $A(x)g(x)$ is equal to the coefficient of x^r in $f_r g_s^{-1} x^{r-s} g_s x^s$, namely

$$f_r g_s^{-1} g_s = f_r.$$

Thus, the coefficient of x^r in $f(x) - A(x)g(x)$ is equal to 0, and hence the degree of $h(x)$ is less than r . We prove the result by induction on r . The case when $r = 0$ is obvious. Suppose that the result holds for every polynomial having degree less than $r > 0$. By the induction hypothesis, we obtain

$$h(x) = q_1(x)g(x) + r_1(x),$$

with $r_1(x) = 0$ or $\deg(r_1(x)) < \deg(g(x))$. Therefore,

$$f(x) = h(x) + A(x)g(x) = (q_1(x) + A(x))g(x) + r_1(x) = q(x)g(x) + r(x),$$

with $q(x) = q_1(x) + A(x)$ and $r(x) = r_1(x)$. Hence, the result follows. \square

3 Δ_θ -cyclic codes over R

For $f(x)$ a polynomial of degree n in $R[x; \theta, \Delta_\theta]$, let

$$\langle f(x) \rangle = \{a(x)f(x) : a(x) \in R[x; \theta, \Delta_\theta]\}.$$

It is easy to see that $R[x; \theta, \Delta_\theta] / \langle f(x) \rangle$ is a left module over $R[x; \theta, \Delta_\theta]$, where the scalar multiplication is defined by

$$r(x) (a(x) + \langle f(x) \rangle) := r(x)a(x) + \langle f(x) \rangle.$$

Definition 3. A code $C \subseteq R^n$ is called a Δ_θ -linear code of length n over R if C is a left $R[x; \theta, \Delta_\theta]$ -submodule of $R[x; \theta, \Delta_\theta]/\langle f(x) \rangle$ for a polynomial $f(x) \in R[x; \theta, \Delta_\theta]$ of degree n . If $f(x)$ is a central element then C is called a central Δ_θ -linear code.

Definition 4. A code $C \subseteq R^n$ is called a Δ_θ -cyclic code of length n over R if C is a Δ_θ -linear code and for all $\mathbf{c} = (c_0, c_1, \dots, c_{n-1}) \in C$ we have

$$T_{\Delta_\theta}(\mathbf{c}) := (\theta(c_{n-1}) + \Delta_\theta(c_0), \theta(c_0) + \Delta_\theta(c_1), \dots, \theta(c_{n-2}) + \Delta_\theta(c_{n-1})) \in C.$$

Here, T_{Δ_θ} is called a shifting operator of Δ_θ -cyclic.

For our purpose, to convert the algebraic structures of Δ_θ -cyclic codes into combinatorial structures and vice versa, we consider the following correspondence:

$$\begin{aligned} R[x; \theta, \Delta_\theta]/\langle f(x) \rangle &\longrightarrow R^n, \\ c_0 + c_1x + c_2x^2 + \dots + c_{n-1}x^{n-1} &\longmapsto (c_0, c_1, \dots, c_{n-1}). \end{aligned}$$

From now on, let $R_{n, \Delta_\theta} := R[x; \theta, \Delta_\theta]/\langle x^n - 1 \rangle$.

Lemma 3.1. *If $c(x) = c_0 + c_1x + c_2x^2 + \dots + c_{n-1}x^{n-1} \in R_{n, \Delta_\theta}$ is identified by a codeword $\mathbf{c} = (c_0, c_1, \dots, c_{n-1}) \in R^n$, then $xc(x)$ is identified by $T_{\Delta_\theta}(\mathbf{c}) \in R^n$.*

Proof.

$$\begin{aligned} xc(x) &= x \left(\sum_{i=0}^{n-1} c_i x^i \right) \\ &= \sum_{i=0}^{n-1} (xc_i) x^i \\ &= \sum_{i=0}^{n-1} (\theta(c_i)x + \Delta_\theta(c_i)) x^i \\ &= \sum_{i=0}^{n-1} \theta(c_i) x^{i+1} + \sum_{i=0}^{n-1} \Delta_\theta(c_i) x^i \\ &= \left(\sum_{i=1}^{n-1} \theta(c_{i-1}) + \Delta_\theta(c_i) x^i \right) + (\theta(c_{n-1}) + \Delta_\theta(c_0)) \quad (\text{denoting that } c_{-1} = c_{n-1}) \\ &= \sum_{i=0}^{n-1} (\theta(c_{i-1}) + \Delta_\theta(c_i)) x^i. \end{aligned}$$

It means that $xc(x)$ is identified by $T_{\Delta_\theta}(\mathbf{c}) \in R^n$. □

Lemma 3.2. *A code $C \subseteq R^n$ is Δ_θ -cyclic code if and only if C is a $R[x; \theta, \Delta_\theta]$ -submodule of R_{n, Δ_θ} .*

Proof. (\implies) Since C is a Δ_θ -linear code, then $(C, +)$ is a subgroup of $(R_{n,\Delta_\theta}, +)$, and for any $\mathbf{c} \in C$, identified by $c(x) \in R_{n,\Delta_\theta}$, we have $T_{\Delta_\theta}(\mathbf{c}) \in C$. By Lemma 3.1, $T_{\Delta_\theta}(\mathbf{c}) \in C$ can be identified by $xc(x) \in R_{n,\Delta_\theta}$. Inductively, we obtain $x^i c(x) \in C$, for all $i \in \mathbb{Z}^+$. By the linearity of a scalar multiplication, we have $a(x)c(x) \in C$, for all $a(x) \in R[x; \theta, \Delta_\theta]$. Hence, C is submodule of R_{n,Δ_θ} .

(\impliedby) If C is a submodule of R_{n,Δ_θ} , then for all $\mathbf{c} \in C$, identified by $c(x) \in R_{n,\Delta_\theta}$, we have $xc(x) \in C$. By Lemma 3.1, $xc(x)$ can be identified by $T_{\Delta_\theta}(\mathbf{c}) \in R^n$. Hence, $T_{\Delta_\theta}(\mathbf{c}) \in C$, which implies that C is a Δ_θ -cyclic code. \square

Corollary 3.3. *If $C \subseteq R^n$ is a Δ_θ -cyclic code of even length n , then C is an ideal of R_{n,Δ_θ} .*

Proof. Since n is even then, by Theorem 2.8, $x^n - 1$ is a central element. Then for all $a(x) \in R[x; \theta, \Delta_\theta]$, we have $a(x)(x^n - 1) = (x^n - 1)a(x)$. Then, $\langle x^n - 1 \rangle$ is a two-sided ideal of $R[x; \theta, \Delta_\theta]$. Since C is a submodule of $R[x; \theta, \Delta_\theta]$, then C is an ideal of R_{n,Δ_θ} . \square

Lemma 3.4. *Let $C \subseteq R^n$ be a Δ_θ -cyclic code. Then the following two statements hold.*

- (1) C is a cyclic code of length n over R if n is odd;
- (2) C is a quasi-cyclic code of length n and index 2 over R if n is even.

Proof. (1) If n is odd, then there exists $b \in \mathbb{Z}$ such that $2b = n + 1$. Let $\mathbf{c} = (c_0, c_1, \dots, c_{n-1}) \in C$ be a codeword identified by $c(x) = c_0 + c_1x + c_2x^2 + \dots + c_{n-1}x^{n-1} \in R_{n,\Delta_\theta}$. It is clear that $x^{2b}c(x) \in C$. Observe that

$$x^{2b}c(x) = x^{2b} \sum_{i=0}^{n-1} c_i x^i = \sum_{i=0}^{n-1} (x^{2b} c_i) x^i = \sum_{i=0}^{n-1} c_i x^{n+1+i} = \sum_{i=0}^{n-1} c_{i-1} x^i \quad (\text{denoting that } c_{-1} = c_{n-1}).$$

Note that $x^{2b}c_i = c_i x^{2b}$ is derived from Corollary 2.6. The equation above says that the codeword $x^{2b}c(x) \in C$ can be identified by the vector $(c_{n-1}, c_0, c_1, \dots, c_{n-2}) \in C$. Thus, C is a cyclic code.

- (2) Observe that for every vector $\mathbf{c} = (c_0, c_1, \dots, c_{n-1}) \in C$ identified by the polynomial $c(x) = c_0 + c_1x + c_2x^2 + \dots + c_{n-1}x^{n-1} \in R_{n,\Delta_\theta}$ we have $x^2c(x) \in C$. By the similar way as in part (1), we can show that $x^2c(x)$ can be identified by $(c_{n-2}, c_{n-1}, c_0, \dots, c_{n-3}) \in C$. Then, C is a quasi-cyclic code of index 2.

\square

Lemma 3.5. *If $C \subseteq R^n$ is a Δ_θ -cyclic code and $g(x)$ is a nonzero polynomial in C of smallest degree with leading coefficient is a unit, then the following three statements hold.*

- (1) $C = \langle g(x) \rangle$.
- (2) $g(x)$ is a right divisor of $x^n - 1$.
- (3) $\{g(x), xg(x), \dots, x^{n-k-1}g(x)\}$ is a basis of C , with $k = \deg(g(x))$.

Proof. (1) It is clear that $\langle g(x) \rangle \subseteq C$. Let $c(x) \in C$. By the right-division algorithm, there exist $q(x), r(x) \in R[x; \theta, \Delta_\theta]$ such that

$$c(x) = q(x)g(x) + r(x),$$

with $r(x) = 0$ or $\deg(r(x)) < \deg(g(x))$. Since C is a submodule of R_{n, Δ_θ} over $R[x; \theta, \Delta_\theta]$, then $r(x) = c(x) - q(x)g(x) \in C$. Moreover, since $g(x)$ is a nonzero polynomial of smallest degree, then $r(x) = 0$. Thus $c(x) = q(x)g(x) \in \langle g(x) \rangle$, and hence $C \subseteq \langle g(x) \rangle$.

(2) Again, by right-division algorithm, there exist $q(x), r(x) \in R[x; \theta, \Delta_\theta]$ such that

$$x^n - 1 = q(x)g(x) + r(x),$$

with $r(x) = 0$ or $\deg(r(x)) < \deg(g(x))$. By the same argument with above, we have $x^n - 1 = q(x)g(x)$. It means that $g(x)$ is a right divisor of $x^n - 1$.

(3) From the above result, consider $x^n - 1 = h(x)g(x)$, for some $h(x) \in R[x; \theta, \Delta_\theta]$. Let $c(x) \in C = \langle g(x) \rangle$. Denote $c(x) = \ell(x)g(x)$, for some $\ell(x) \in R[x; \theta, \Delta_\theta]$. If $\deg(\ell(x)) \leq n - k - 1$, then $c(x) \in \langle g(x), xg(x), \dots, x^{n-k-1}g(x) \rangle$. If $\deg(\ell(x)) > n - k - 1$, by using the right-division algorithm we come up with the conclusion that $c(x) = \ell(x)g(x) = r(x)g(x)$ (in R_{n, Δ_θ}) for some polynomial $r(x) \in R[x; \theta, \Delta_\theta]$ with $r(x) = 0$ or $\deg(r(x)) < \deg(h(x)) = n - k$, so $\{g(x), xg(x), \dots, x^{n-k-1}g(x)\}$ generates C . Moreover, it is easy to see that the set is also linearly independent. Hence, we conclude that $\{g(x), xg(x), \dots, x^{n-k-1}g(x)\}$ is a basis for C .

□

Since $\langle g(x) \rangle$ is a submodule of R_{n, Δ_θ} over $R[x; \theta, \Delta_\theta]$, then by Lemma 3.2, C is a Δ_θ -cyclic code. The Lemma 3.5 above says that if $C = \langle g(x) \rangle$ is a Δ_θ -cyclic code, where $g(x)$ is a nonzero polynomial in C of smallest degree with a unit leading coefficient and $g(x)$ is also a right divisor of $x^n - 1$, then C is free. Hence, we obtained a construction method for Δ_θ -cyclic codes as described by the following.

Corollary 3.6. *If $g(x)$ is a right divisor of $x^n - 1$, with leading coefficient a unit, then $C = \langle g(x) \rangle$ is a free Δ_θ -cyclic code.*

If C is a free Δ_θ -cyclic code, then the existence of a generating polynomial of C is guaranteed.

Lemma 3.7. *If $C \subseteq R^n$ is a free Δ_θ -cyclic code, then there exists a nonzero polynomial of smallest degree $g(x) \in C$ such that $C = \langle g(x) \rangle$ where $g(x)$ is a right divisor of $x^n - 1$.*

Proof. Let $g(x) \in C$ is a nonzero polynomial of smallest degree. Suppose the leading coefficient of $g(x)$ is not a unit, then it should be a zero divisor (since R is a finite ring). Let a be a leading coefficient of $g(x)$. Since a is a zero divisor, then there exists $r \in R$, $r \neq 0$, such that $ra = 0$. Since C is a linear code, then $rg(x) \in C$. It is clear that $rg(x)$ is either a nonzero polynomial of degree less than the degree of $g(x)$ or $rg(x) = 0$. But the last equation is impossible since it implies $\{g(x)\}$ is linearly dependent. Hence, the leading coefficient of $g(x)$ should be a unit. Thus, by Lemma 3.5, we have $C = \langle g(x) \rangle$, with $g(x)$ is a right divisor of $x^n - 1$. \square

Now, we are able to present a generator matrix G of a free Δ_θ -cyclic code of length n over R . Let $C = \langle g(x) \rangle$ be a free Δ_θ -cyclic code of length n generated by a right divisor $g(x)$ of $x^n - 1$, whose leading coefficient is unit. Then the generator matrix G of C of dimension $(n - k) \times n$ is given by

$$G = \begin{pmatrix} g(x) \\ xg(x) \\ x^2g(x) \\ \vdots \\ x^{n-k-1}g(x) \end{pmatrix},$$

where $g(x) = g_0 + g_1x + g_2x^2 + \cdots + g_kx^k$. To be more precise, if $n - k$ is odd, then

$$G = \begin{pmatrix} g_0 & g_1 & g_2 & \cdots & g_k & 0 & \cdots & 0 \\ \Delta_\theta(g_0) & \theta(g_0) + \Delta_\theta(g_1) & \theta(g_1) + \Delta_\theta(g_2) & \cdots & \theta(g_{k-1}) + \Delta_\theta(g_k) & \theta(g_k) & \cdots & 0 \\ 0 & 0 & g_0 & \cdots & g_{k-3} & g_{k-2} & \cdots & 0 \\ \vdots & \vdots & \vdots & \cdots & \vdots & \vdots & \vdots & \vdots \\ 0 & 0 & \cdots & g_0 & g_{k-2} & \cdots & g_{k-1} & g_k \end{pmatrix},$$

and if $n - k$ is even, then

$$G = \begin{pmatrix} g_0 & g_1 & g_2 & \cdots & g_k & 0 & \cdots & 0 & 0 \\ \Delta_\theta(g_0) & \theta(g_0) + \Delta_\theta(g_1) & \theta(g_1) + \Delta_\theta(g_2) & \cdots & \theta(g_{k-1}) + \Delta_\theta(g_k) & \theta(g_k) & \cdots & 0 & 0 \\ 0 & 0 & g_0 & \cdots & g_{k-3} & g_{k-2} & \cdots & 0 & 0 \\ \vdots & \vdots & \vdots & \cdots & \vdots & \vdots & \vdots & \vdots & \vdots \\ 0 & 0 & \cdots & \Delta_\theta(g_0) & \theta(g_0) + \Delta_\theta(g_1) & \theta(g_1) + \Delta_\theta(g_2) & \cdots & \theta(g_{k-1}) + \Delta_\theta(g_k) & \theta(g_k) \end{pmatrix}.$$

4 Dual of Δ_θ -cyclic codes over R

In this section, we investigate the structure of the dual of a free Δ_θ -cyclic code over R with even length.

Definition 5. Let $C \subseteq R^n$ is a Δ_θ -cyclic code. Dual of C , denoted by C^\perp , is defined by

$$C^\perp = \{\mathbf{x} \in R^n : \mathbf{x} \cdot \mathbf{y} = 0, \text{ for all } \mathbf{y} \in C\}.$$

Here, $\mathbf{x} \cdot \mathbf{y} = x_0y_0 + x_1y_1 + \cdots + x_{n-1}y_{n-1}$ denotes the usual inner product in R^n .

It is easy to check that C^\perp is a linear code over R . Moreover, for any even n , if C is a free Δ_θ -cyclic code, then C^\perp is free, as we show below.

Lemma 4.1. *Let n be an even integer. Let $g(x), h(x) \in R[x; \theta, \Delta_\theta]$, where a leading coefficient of $g(x)$ is a unit, and $h(x)g(x) = x^n - 1$. Then we have*

$$h(x)g(x) = g(x)h(x).$$

Proof. If n is even, then $x^n - 1 = h(x)g(x)$ is a central element (by Theorem 2.8). Then we have

$$h(x)h(x)g(x) = h(x)g(x)h(x).$$

Since $h(x)$ is not a zero divisor, then $x^n - 1 = h(x)g(x) = g(x)h(x)$. □

Lemma 4.2. *Let C be a Δ_θ -cyclic code, where $C = \langle g(x) \rangle$, for some right divisor $g(x)$ of $x^n - 1$, whose leading coefficient is unit and n is even. Let $x^n - 1 = h(x)g(x)$. Then $c(x) \in R_{n, \Delta_\theta}$ is contained in C if and only if $c(x)h(x) = 0$ (in R_{n, Δ_θ}).*

Proof. (\implies) Since $c(x) \in C$, then there exists $a(x) \in R[x; \theta, \Delta_\theta]$ such that $c(x) = a(x)g(x)$. Hence,

$$c(x)h(x) = a(x)g(x)h(x) = a(x)h(x)g(x) = a(x)(x^n - 1) = 0$$

(in R_{n, Δ_θ}).

(\impliedby) Since $c(x)h(x) = 0$ (in R_{n, Δ_θ}), for some $c(x) \in R_{n, \Delta_\theta}$, then $c(x)h(x) = q(x)(x^n - 1)$, for some $q(x) \in R[x; \theta, \Delta_\theta]$. In this case

$$c(x)h(x) = q(x)(x^n - 1) = q(x)h(x)g(x) = q(x)g(x)h(x).$$

Since $h(x)$ is not a zero divisor, then we have $c(x) = q(x)g(x) \in \langle g(x) \rangle = C$.

□

We also have known that all unit in R are $\{1, 3, 1 + 2v, 3 + 2v\}$. It is easy to check that for all a unit in R , we have $\theta(a)$ is also unit in R . Hence, we have the following.

Lemma 4.3. *If $a \in R$ is a unit then $\theta(a) \in R$ is also a unit.*

Now, consider a Δ_θ -cyclic code C of even length n . Let $C = \langle g(x) \rangle$, where $g(x)$ is a right divisor of $x^n - 1$ and its leading coefficient is a unit. Then there exists $h(x) = h_0 + h_1x + \cdots + h_kx^k \in R_{n, \Delta_\theta}$ such that $x^n - 1 = h(x)g(x)$. For $c(x) = c_0 + c_1x + \cdots + c_{n-1}x^{n-1} \in C$, by Lemma 4.2, we have $c(x)h(x) = 0$ (in R_{n, Δ_θ}). By considering the coefficients of $x^k, x^{k+1}, \dots, x^{n-1}$ in the last equation, we obtain two systems of equations each consisting of $n - k$ linear equations in c_0, c_1, \dots, c_{n-1} . To be more precise, we have the following two systems of equations, for k is odd and even, respectively.

$$\begin{cases} c_i h_k + c_{i+1}(\theta(h_{k-1}) + \Delta_\theta(h_k)) + c_{i+2}h_{k-2} + \cdots + c_{k+i}(\theta(h_0) + \Delta_\theta(h_1)) = 0, & i \text{ is even,} \\ c_i \theta(h_k) + c_{i+1}h_{k-1} + c_{i+2}(\theta(h_{k-2}) + \Delta_\theta(h_{k-1})) + \cdots + c_{k+i}h_0 + c_{k+i+1}\Delta_\theta(h_0) = 0, & i \text{ is odd.} \end{cases}$$

$$\begin{cases} c_i h_k + c_{i+1}(\theta(h_{k-1}) + \Delta_\theta(h_k)) + c_{i+2}h_{k-2} + \cdots + c_{k+i}h_0 + c_{k+i+1}\Delta_\theta(h_0) = 0, & i \text{ is even,} \\ c_i \theta(h_k) + c_{i+1}h_{k-1} + c_{i+2}(\theta(h_{k-2}) + \Delta_\theta(h_{k-1})) + \cdots + c_{k+i}(\theta(h_0) + \Delta_\theta(h_1)) = 0, & i \text{ is odd,} \end{cases}$$

If we write the system of equations in a matrix form, we obtain $Hc^T = 0$, for the matrix H of dimension $(n - k) \times n$. It implies that $GH^T = 0$, for a generator matrix G of C . Moreover, it is easy to check that H is of the row echelon form with diagonal elements h_k or $\theta(h_k)$, and having a submatrix of dimension $(n - k) \times (n - k)$. Since h_k is a unit, then by Lemma 4.3, we have $\theta(h_k)$ is also a unit. Then, the rows of H are linearly independent. Hence,

$$|\text{Row space of } H| = |R|^{n-k} = |C^\perp|.$$

Thus, H is a parity check matrix of C and we have proven the following theorem.

Theorem 4.4. *Let $C = \langle g(x) \rangle$ be a Δ_θ -cyclic code of even length n and $x^n - 1 = h(x)g(x)$, for some $h(x) = h_0 + h_1x + h_2x^2 + \cdots + h_kx^k \in R_{n, \Delta_\theta}$. Then the $(n - k) \times n$ parity-check matrix H for C is given by*

$$\begin{pmatrix} h_k & \theta(h_{k-1}) + \Delta_\theta(h_k) & h_{k-2} & \cdots & \cdots & \cdots & \theta(h_0) + \Delta_\theta(h_1) & 0 & \cdots & \cdots & \cdots & \cdots & 0 & 0 \\ 0 & \theta(h_k) & h_{k-1} & \theta(h_{k-2}) & \cdots & \cdots & h_0 & \Delta_\theta(h_0) & 0 & \cdots & \cdots & \cdots & 0 & 0 \\ 0 & 0 & h_k & \theta(h_{k-1}) + \Delta_\theta(h_k) & h_{k-2} & \cdots & \cdots & \cdots & \theta(h_0) + \Delta_\theta(h_1) & 0 & \cdots & \cdots & 0 & 0 \\ \vdots & \vdots & \vdots & \vdots & \vdots & \ddots & \ddots & \ddots & \ddots & \ddots & \ddots & \ddots & \vdots & \vdots \\ 0 & 0 & \cdots & \cdots & 0 & h_k & \theta(h_{k-1}) + \Delta_\theta(h_k) & h_{k-2} & \cdots & \cdots & \cdots & \cdots & h_1 & \theta(h_0) + \Delta_\theta(h_1) \end{pmatrix}$$

for an odd k , and

$$\begin{pmatrix} h_k & \theta(h_{k-1}) + \Delta_\theta(h_k) & h_{k-2} & \cdots & \cdots & \cdots & h_0 & \Delta_\theta(h_0) & 0 & \cdots & \cdots & \cdots & \cdots & 0 & 0 \\ 0 & \theta(h_k) & h_{k-1} & \theta(h_{k-2}) & \cdots & \cdots & h_1 & \theta(h_0) + \Delta_\theta(h_1) & 0 & \cdots & \cdots & \cdots & \cdots & 0 & 0 \\ 0 & 0 & h_k & \theta(h_{k-1}) + \Delta_\theta(h_k) & h_{k-2} & \cdots & \cdots & \cdots & h_0 & \theta(h_1) + \Delta_\theta(h_2) & 0 & \cdots & \cdots & 0 & 0 \\ \vdots & \vdots & \vdots & \vdots & \vdots & \ddots & \ddots & \ddots & \ddots & \ddots & \ddots & \ddots & \ddots & \vdots & \vdots \\ 0 & 0 & \cdots & \cdots & 0 & \theta(h_k) & h_{k-1} & h_{k-2} & \cdots & \cdots & \cdots & \cdots & \cdots & h_1 & \theta(h_0) + \Delta_\theta(h_1) \end{pmatrix}$$

for an even k .

5 Application

As an application, we obtained many linear codes over \mathbb{Z}_4 with new parameters, by using Gray map, and also residue and torsion codes of these skew codes over the skew polynomial ring $R[x; \theta, \Delta_\theta]$.

First, as a consequence of Theorem 2.2, we have the property below.

Corollary 5.1. *Let C be a free Δ_θ -cyclic code of length n over R with $|C| = 16^k$. Then the free linear codes $Res(C)$ and $Tor(C)$ have parameter $4^k 2^0$, and the free linear code $\Phi(C)$ has parameter $4^{2k} 2^0$.*

Remark 1. The first part of Corollary 5.1, related the parameters of $Res(C)$ and $Tor(C)$, does not hold for the code over $\mathbb{Z}_4 + u\mathbb{Z}_4$, with $u^2 = 1$ that considered by Sharma and Bhaintwal [23].

The linear codes over \mathbb{Z}_4 , many of them are with new parameters, are listed in the table below.

C or the generators of C	$\Phi(C)$	$Res(C)$	$Tor(C)$	C^{PS}
	$[n, 4^{k_1} 2^{k_2}, d_L]$	$[n, 4^{k_1} 2^{k_2}, d_L]$	$[n, 4^{k_1} 2^{k_2}, d_L]$	$[n, 4^{k_1} 2^{k_2}, d_L]$
$\langle 3 + x \rangle$	$[8, 4^6, 2]^*$	$[4, 4^3, 2]**$	$[4, 4^3, 2]**$	$[8, 4^6, 2]^*$
$\langle (3 + 2v) + (3 + 2v)x + 2x^2 + (1 + 2v)x^3 + (3 + 2v)x^4 \rangle$			$[6, 4^2, 6]**$	
$\langle 3v + (3 + v)x + (3 + v)x^2 + (1 + 2v)x^3 + (2 + 2v)x^4 + 2x^5 + vx^6 + (1 + 3v)x^7 + (1 + v)x^8 + x^9 \rangle$		$[12, 4^3, 10]^*$		
$\langle (1 + 3v) + 3x + x^2 + (3 + 2v)x^4 + 2x^5 + 2vx^6 + 2x^7 + (1 + 3v)x^8 + 3x^9 + 3x^{10} + x^{12} \rangle$		$[16, 4^4, 12]**$		
$\{g_1(x), xg_1(x)\}$		$[4, 4^1 2^1, 4]^*$		$[8, 4^2 2^2, 4]^*$
$\{g_2(x), xg_2(x), x^2 g_2(x)\}$		$[4, 4^1 2^2, 2]^*$		$[8, 4^2 2^4, 2]^*$
$\{g_3(x), xg_3(x), x^2 g_3(x)\}$		$[5, 4^2 2^1, 4]***$		
$\{g_4(x), xg_4(x), x^2 g_4(x)\}$		$[6, 4^2 2^1, 4]^*$		
$\{g_5(x), xg_5(x), x^2 g_5(x), x^3 g_5(x), x^4 g_5(x)\}$		$[6, 4^2 2^3, 4]^*$		$[12, 4^4 2^6, 4]^*$
$\{g_6(x), xg_6(x), x^2 g_6(x), x^3 g_6(x)\}$		$[6, 4^3 2^1, 4]^*$		$[12, 4^6 2^2, 4]^*$
$\{g_7(x), xg_7(x), x^2 g_7(x), x^3 g_7(x), x^4 g_7(x), x^5 g_7(x), x^6 g_7(x)\}$		$[8, 4^4 2^3, 4]***$		$[16, 4^8 2^6, 4]^*$

$\{g_8(x), xg_8(x), x^2g_8(x), x^3g_8(x), x^4g_8(x), x^5g_8(x)\}$			$[8, 4^5 2^1, 4]^{***}$	$[16, 4^{10} 2^2, 4]^*$
$\{g_9(x), xg_9(x), x^2g_9(x)\}$		$[9, 4^3 2^0, 7]^{**}$		
$\{g_{10}(x), xg_{10}(x), x^2g_{10}(x)\}$		$[10, 4^3 2^0, 8]^{**}$		
$\{g_{11}(x), xg_{11}(x)\}$		$[15, 4^2 2^0, 15]^{**}$		
$\{g_{12}(x), xg_{12}(x), x^2g_{12}(x)\}$		$[18, 4^3 2^0, 14]^{**}$		

Table 1: Linear codes over \mathbb{Z}_4

Notes on the Table 1:

- * means the codes we obtained have new k_1 and k_2 , but there is/are other codes in the database [2] with the same minimum Lee distances but with greater or equal cardinalities.
- ** means the codes we obtained have minimum Lee distances better than the existing ones in the database [2], with the same values of k_1 and k_2 .
- *** means the codes we obtained have new k_1 and k_2 , with greater cardinalities compared with the existing one in the database [2], with the same value of minimum Lee distances.
- *) means the codes we obtained have the same parameters as some existing good linear codes in the database [2].
- C^{PS} is a code obtained by Plotkin-sum construction, namely $C^{PS} := \{(\mathbf{x} \mid \mathbf{x} + \mathbf{y}) : \mathbf{x}, \mathbf{y} \in \text{Res}(C)\}$ or $C^{PS} := \{(\mathbf{x} \mid \mathbf{x} + \mathbf{y}) : \mathbf{x}, \mathbf{y} \in \text{Tor}(C)\}$.
- $g_1(x) = (1 + 3v) + 2x + (3 + 3v)x^2$.
- $g_2(x) = (1 + v) + (2 + 2v)x + (1 + 3v)x^2$.
- $g_3(x) = (1 + 3v) + 2vx + (2 + 2v)x^2 + 2vx^3 + (1 + 3v)x^4$.
- $g_4(x) = 3 + (1 + 3v)x + (3 + v)x^2 + (2 + 3v)x^3$.
- $g_5(x) = (3 + 3v) + (1 + 3v)x + (3 + 3v)x^3 + (3 + v)x^4 + 2x^5$.

- $g_6(x) = (1 + v) + x + (2 + v)x^2 + vx^3 + 3vx^5.$
- $g_7(x) = (1 + v) + 3x^1 + (2 + 3v)x^2 + (3 + v)x^3 + (2 + 2v)x^4 + 2x^6 + x^7.$
- $g_8(x) = 2v + (2 + 3v)x^1 + (1 + 3v)x^2 + (1 + 2v)x^3 + 2vx^4 + (1 + v)x^5 + x^6 + 3vx^7.$
- $g_9(x) = (1 + v) + (1 + 3v)x^1 + (3 + 2v)x^2 + 3x^3 + (3 + 3v)x^4 + (2 + 2v)x^5 + (2 + 3v)x^6 + (3 + 3v)x^7 + (1 + 3v)x^8.$
- $g_{10}(x) = (1 + 3v) + (2 + 2v)x^1 + 3x^2 + vx^4 + 3x^5 + (3 + 3v)x^6 + x^7 + x^8.$
- $g_{11}(x) = (1 + v) + (2 + v)x^2 + (3 + 2v)x^3 + (3 + v)x^5 + (1 + 2v)x^6 + 2x^7 + (3 + v)x^8 + 3x^9 + 2vx^{10} + (3 + 2v)x^{11} + (1 + 2v)x^{12} + (2 + v)x^{13} + (1 + 3v)x^{14}.$
- $g_{12}(x) = 1 + 2vx^1 + (3 + 2v)x^2 + (2 + 2v)x^3 + (1 + 2v)x^4 + x^5 + vx^6 + x^7 + (1 + 2v)x^8 + (3 + 2v)x^9 + (1 + 3v)x^{10} + (3 + 3v)x^{11} + (2 + v)x^{12} + (3 + 3v)x^{13} + x^{14} + (2 + v)x^{15} + (2 + 2v)x^{16}.$

5.1 Notes on computation

We notice that for any $g(x) \in R_{n,\Delta_\theta}$, the set $\{g(x), xg(x), x^2g(x), \dots, x^{n-1}g(x)\}$ is a generating set, which is not necessary minimal, of the Δ_θ -cyclic code $C = \langle g(x) \rangle$ over R . So far, the method we use to construct the codes over \mathbb{Z}_4 is by consider first the subcode $C_k = \langle g(x), xg(x), x^2g(x), \dots, x^{k-1}g(x) \rangle$ of C . Then construct the $Res(C_k)$, $Tor(C_k)$, and $\Phi(C_k)$. But for the case of Δ_θ -cyclic codes over R , we can simplify our computation as follows.

Let C be a Δ_θ -cyclic code over R of length n generated by $\{g(x), xg(x), x^2g(x), \dots, x^{n-1}g(x)\}$, where $g(x) = c_0 + c_1x + c_2x^2 + \dots + c_{n-1}x^{n-1} \in R_{n,\Delta_\theta}$ and $c_i = a_i + b_iv$, for $0 \leq i \leq n-1$. To be more precise, for an even and an odd n , the generator of $C \subseteq R^n$ consists of the following vectors, respectively:

$$g_1 = (a_0 + b_0v, a_1 + b_1v, \dots, a_{n-2} + b_{n-2}v, a_{n-1} + b_{n-1}v),$$

$$g_2 = (a_{n-1} + b_{n-1} + b_0 - b_{n-1}v, a_0 + b_0 + b_1 - b_0v, \dots, a_{n-3} + b_{n-3} + b_{n-2} - b_{n-3}v, \\ a_{n-2} + b_{n-2} + b_{n-1} - b_{n-2}v),$$

$$g_3 = (a_{n-2} + b_{n-2}v, a_{n-1} + b_{n-1}v, \dots, a_{n-4} + b_{n-4}v, a_{n-3} + b_{n-3}v),$$

⋮

$$g_n = (a_1 + b_1 + b_2 - b_1v, a_2 + b_2 + b_3 - b_2v, \dots, a_{n-1} + b_{n-1} + b_0 - b_{n-1}v, a_0 + b_0 + b_1 - b_0v),$$

and

$$\begin{aligned}
g_1 &= (a_0 + b_0v, a_1 + b_1v, \dots, a_{n-2} + b_{n-2}v, a_{n-1} + b_{n-1}v), \\
g_2 &= (a_{n-1} + b_{n-1} + b_0 - b_{n-1}v, a_0 + b_0 + b_1 - b_0v, \dots, a_{n-3} + b_{n-3} + b_{n-2} - b_{n-3}v, \\
&\quad a_{n-2} + b_{n-2} + b_{n-1} - b_{n-2}v), \\
g_3 &= (a_{n-2} + b_{n-2}v, a_{n-1} + b_{n-1}v, \dots, a_{n-4} + b_{n-4}v, a_{n-3} + b_{n-3}v), \\
&\quad \vdots \\
g_n &= (a_1 + b_1v, a_2 + b_2v, \dots, a_{n-1} + b_{n-1}v, a_0 + b_0v).
\end{aligned}$$

By applying the Lemma 2.1, we obtain the generator of the $Res(C)$ for an even and an odd n consists of the following vectors, respectively:

$$\begin{aligned}
Res(g_1) &= (a_0, a_1, a_2, \dots, a_{n-2}, a_{n-1}), \\
Res(g_2) &= (a_{n-1} + b_{n-1} + b_0, a_0 + b_0 + b_1, \dots, a_{n-3} + b_{n-3} + b_{n-2}, a_{n-2} + b_{n-2} + b_{n-1}), \\
Res(g_3) &= (a_{n-2}, a_{n-1}, \dots, a_{n-4}, a_{n-3}), \\
&\quad \vdots \\
Res(g_n) &= (a_1 + b_1 + b_2, a_2 + b_2 + b_3, \dots, a_{n-1} + b_{n-1} + b_0, a_0 + b_0 + b_1),
\end{aligned}$$

and

$$\begin{aligned}
Res(g_1) &= (a_0, a_1, a_2, \dots, a_{n-2}, a_{n-1}), \\
Res(g_2) &= (a_{n-1} + b_{n-1} + b_0, a_0 + b_0 + b_1, \dots, a_{n-3} + b_{n-3} + b_{n-2}, a_{n-2} + b_{n-2} + b_{n-1}), \\
Res(g_3) &= (a_{n-2}, a_{n-1}, \dots, a_{n-4}, a_{n-3}), \\
&\quad \vdots \\
Res(g_n) &= (a_1, a_2, \dots, a_{n-1}, a_0).
\end{aligned}$$

Moreover, the generator of the $Tor(C)$ for an even and an odd n consists of the following vectors, respectively:

$$\begin{aligned}
Tor(g_1) &= (a_0 + b_0, a_1 + b_1, a_2 + b_2, \dots, a_{n-2} + b_{n-2}, a_{n-1} + b_{n-1}), \\
Tor(g_2) &= (a_{n-1} + b_0, a_0 + b_1, \dots, a_{n-3} + b_{n-2}, a_{n-2} + b_{n-1}), \\
Tor(g_3) &= (a_{n-2} + b_{n-2}, a_{n-1} + b_{n-1}, \dots, a_{n-4} + b_{n-4}, a_{n-3} + b_{n-3}), \\
&\quad \vdots \\
Tor(g_n) &= (a_1 + b_2, a_2 + b_3, \dots, a_{n-1} + b_0, a_0 + b_1),
\end{aligned}$$

and

$$\begin{aligned}
Tor(g_1) &= (a_0 + b_0, a_1 + b_1, a_2 + b_2, \dots, a_{n-2} + b_{n-2}, a_{n-1} + b_{n-1}), \\
Tor(g_2) &= (a_{n-1} + b_0, a_0 + b_1, \dots, a_{n-3} + b_{n-2}, a_{n-2} + b_{n-1}), \\
Tor(g_3) &= (a_{n-2} + b_{n-2}, a_{n-1} + b_{n-1}, \dots, a_{n-4} + b_{n-4}, a_{n-3} + b_{n-3}), \\
&\vdots \\
Tor(g_n) &= (a_1 + b_1, a_2 + b_2, \dots, a_{n-1} + b_{n-1}, a_0 + b_0).
\end{aligned}$$

Then, for any $k \leq n$, if C_k is generated by the set $\{g_1, g_2, \dots, g_k\}$, then the $Res(C_k)$ and $Tor(C_k)$ is generated by $\{Res(g_1), Res(g_2), \dots, Res(g_k)\}$ and $\{Tor(g_1), Tor(g_2), \dots, Tor(g_k)\}$, respectively. Our method can reduce the computational time significantly.

Exactly the same method can also be used to the code $\Phi(C_k)$. This observation brings us to the conclusion that the codes $Res(C_k)$, $Tor(C_k)$, and $\Phi(C_k)$ has at most 4^k , 4^k , and 4^{2k} codewords, respectively. Moreover, the similar observation can also be applied to the code over $\mathbb{Z}_4 + u\mathbb{Z}_4$, with $u^2 = 1$, investigated by Sharma and Bhaintwal [23] and it is easy to verify that in this case, the codes $Res(C_k)$, $Tor(C_k)$, and $\Phi(C_k)$ has at most 4^{2k} codewords.

6 Concluding remarks

We have investigated the algebraic structures of skew-cyclic codes, also known as θ -cyclic codes, with a derivation Δ_θ over the ring $R = \mathbb{Z}_4 + v\mathbb{Z}_4$, with $v^2 = v$, generalizing the observation of Boucher and Ulmer [9], where they defined and considered the skew-cyclic codes with derivation over a finite field. To our best knowledge, this is the second attempt after the first paper by Sharma and Bhaintwal [23]. Our work can also be viewed as a partial answer of the question of Dougherty [10], page 99:

Question 6.5 Determine the structure of all θ -cyclic codes in $R[x; \theta] / \langle x^n - \lambda \rangle$ where R is a finite commutative Frobenius ring.

As an application, we derive several new codes over \mathbb{Z}_4 unknown to exist before due to the database [2], with good parameters. All computations to find the codes were done by using Python and Magma computational algebra system [5].

While investigating the new good codes over \mathbb{Z}_4 , we were aware that for the case of linear codes

over \mathbb{Z}_4 , we have the following upper bound for the minimum Lee distance

$$d_L \leq \frac{|C|}{|C|-1}n. \quad (4)$$

The bound above has been found in 1968 by Wyner and Graham [26], but we are able to reprove the bound in an elementary way. In many cases, the bound is much better than the known Lee distance bound derived by Dougherty and Shiromoto [11] as given by Theorem 6.1 below.

Theorem 6.1 (Lee distance bound). *If C is a linear code of length n over \mathbb{Z}_4 with parameters $[n, 4^{k_1}2^{k_2}, d_L]$, then $d_L \leq 2n - 2k_1 - k_2 + 1$.*

As an application, we can also construct, by hand, many new linear codes over \mathbb{Z}_4 , with the highest known minimum Lee distance, previously unknown to exist in the database [2]. This result, which is now in preparation will be published elsewhere in a separate paper [24].

Regarding the derivation, it is easy to show that the map $\Delta_\theta(x) = (3 + 2v)(\theta(x) - x)$ also defines a derivation on R . All the properties in this paper which hold for the derivation $\Delta_\theta(x) = (1 + 2v)(\theta(x) - x)$ above also hold for the derivation $\Delta_\theta(x) = (3 + 2v)(\theta(x) - x)$.

The method explained in Section 5 can be modified for the case of derivation $\Delta_\theta(x) = (3 + 2v)(\theta(x) - x)$. There is some hope to obtain many more examples of the linear codes over \mathbb{Z}_4 with better parameters. As an example, the torsion code $Tor(C)$ of the code $C := \langle g(x), xg(x), x^2g(x) \rangle$, with $g(x) = 3v + (2 + v)x + 3vx^2 + vx^3$, has parameters $[4, 4^{12^2}, 4]$, which is better than the one in Table 1.

Acknowledgments

This research is supported by the Institut Teknologi Bandung (ITB) and the Ministry of Education, Culture, Research and Technology (*Kementerian Pendidikan, Kebudayaan, Riset dan Teknologi (Kemdikbudristek)*), Republic of Indonesia.

References

- [1] T. Abualrub, N. Aydin, and P. Seneviratne, "On θ -cyclic codes over $\mathbb{F}_2 + u\mathbb{F}_2$," *Australas. J. Combin.* **54**(2) (2012), 115-126.
- [2] N. Aydin and T. Asamov, "The database of \mathbb{Z}_4 codes," available at <http://www.z4codes.info> (accessed at September 2021).
- [3] R.K. Bandi and M. Bhaintwal, "Codes over $\mathbb{Z}_4 + v\mathbb{Z}_4$," in *Proc. Commun. Inform. ICACCI*, Sep. 2004, 422-427.
- [4] N. Benbelkacem, M.F. Ezerman, T. Abualrub, N. Aydin, and A. Batoul, "Skew cyclic codes over \mathbb{F}_4R ," *J. Algebra Appl.* (2021) (to appear).
- [5] W. Bosma, J.J. Cannon, C. Fieker, and A. Steel, *Handbook of magma functions*, Sydney 2011.
- [6] D. Boucher, W. Geiselmann, and F. Ulmer, "Skew cyclic codes," *Appl. Algebra Engrg. Comm. Comput.* **18**(4) (2007), 379-389.
- [7] D. Boucher and F. Ulmer, "Coding with skew polynomial rings," *J. Symb. Comput.* **44**(3-4) (2009), 1644-1656.
- [8] D. Boucher and F. Ulmer, "Coding as modules over skew polynomial rings," in Proceedings of the 12th IMA Conference on Cryptography and Coding, *Lecture Notes in Comput. Sci.* **5921** (2009), 38-55.
- [9] D. Boucher and F. Ulmer, "Linear codes using skew polynomials with automorphisms and derivations," *Des. Codes Cryptogr.* **70**(3) (2014), 405-431.
- [10] S.T. Dougherty, *Algebraic coding theory over finite commutative rings*, SpringerBriefs in Mathematics, Springer, 2017.
- [11] S.T. Dougherty and K. Shiromoto, "Maximum distance codes over rings of order 4," *IEEE Trans. Inform. Theory* **47**(1) (2001), 400-404.
- [12] J. Gao, F. W. Fu, and Y. Gao, "Some classes of linear codes over $\mathbb{Z}_4 + v\mathbb{Z}_4$ and their applications to construct good and new \mathbb{Z}_4 -linear codes," *Appl. Algebra Engrg. Comm. Comput.* **28**(2) (2017), 131-153.

- [13] F. Gursoy, I. Siap, and B. Yildiz, "Construction of skew cyclic codes over $\mathbb{F}_q + v\mathbb{F}_q$," *Adv. Math. Commun.* **8**(3) (2014), 313-322.
- [14] A.R. Hammons, P.V. Kumar, A.R. Calderbank, N.J.A. Sloane, and P. Solé, "The \mathbb{Z}_4 -linearity of Kerdock, Preparata, Goethals and Related Codes," *IEEE Trans. Inform. Theory* **40**(2) (1994), 301-319.
- [15] W.C. Huffman and V. Pless, *Fundamentals of Error Correcting Codes*, Cambridge University Press, 2003.
- [16] Irwansyah, A. Barra, S.T. Dougherty, A. Muchlis, I. Muchtadi-Alamsyah, P. Sole, D. Suprijanto, and O. Yemen, " Θ_S -cyclic codes over A_k ," *Int. J. Comput. Math. Comput. Syst. Theory* **1**(1) (2016), 14-31.
- [17] Irwansyah, A. Barra, A. Muchlis, I. Muchtadi-Alamsyah, and D. Suprijanto, "skew cyclic codes over B_k ," *J. Appl. Math. Comput.* **57**(1-2) (2018), 69-84.
- [18] Irwansyah and D. Suprijanto, "Structure of linear codes over the ring B_k ," *J. Appl. Math. Comput.* **58**(1-2) (2018), 755-775.
- [19] J. Liu and H. Liu, "Construction of cyclic DNA codes over the ring $\mathbb{Z}_4 + v\mathbb{Z}_4$," *IEEE Access* **8** (2020), 111200-111207.
- [20] B.R. McDonald, *Finite Rings with Identity*. Marcel Dekker Inc., New York, 1974.
- [21] O. Ore, "Theory of non-commutative polynomials," *Annals. Math.* **34** (1933), 480-508.
- [22] E. Prange, "Cyclic error-correcting codes in two symbols," *Airforce Cambridge Research Center, Cambridge, MA, Tech. Rep. AFCRC-TN* (1957), 57-103.
- [23] A. Sharma and M. Bhaintwal, "A class of skew cyclic codes over $\mathbb{Z}_4 + v\mathbb{Z}_4$ with derivation," *Adv. Math. Commun.* **12**(4) (2018), 723-739.
- [24] H.C. Tang and D. Suprijanto, "New optimal linear codes over \mathbb{Z}_4 ," (preprint, 2022).
- [25] Zhe-Xian Wan, *Quaternary codes*, World Scientific, 1997.
- [26] A.D. Wyner and R.L. Graham, "An upper bound on minimum distance for a k -ary code," *Inform. Control* **13**(1) (1968), 46-52.