

ESTIMATION OF BINARY TIME-FREQUENCY MASKS FROM AMBIENT NOISE

JOSÉ LUIS ROMERO AND MICHAEL SPECKBACHER

ABSTRACT. We investigate the retrieval of a binary time-frequency mask from a few observations of filtered white ambient noise. Confirming household wisdom in acoustic modeling, we show that this is possible by inspecting the average spectrogram of ambient noise. Specifically, we show that the lower quantile of the average of $\mathcal{O}(\log(|\Omega|/\varepsilon))$ masked spectrograms is enough to identify a rather general mask Ω with confidence at least ε , up to shape details concentrated near the boundary of Ω . As an application, the expected measure of the estimation error is dominated by the perimeter of the time-frequency mask. The estimator requires no knowledge of the noise variance, and only a very qualitative profile of the filtering window, but no exact knowledge of it.

1. INTRODUCTION

Time-frequency masking is the process of altering a signal $f : \mathbb{R}^d \rightarrow \mathbb{C}$ by weighting its time-frequency profile with a *mask*. A standard model for such operation is based on the *short-time Fourier transform* of f . First a profile of f is built out of its time-frequency correlations with an auxiliary smooth and fast-decaying *window function* $g : \mathbb{R}^d \rightarrow \mathbb{C}$:

$$(1.1) \quad V_g f(x, \xi) = \int_{\mathbb{R}^d} f(t) \overline{g(t-x)} e^{-2\pi i \xi \cdot t} dt, \quad (x, \xi) \in \mathbb{R}^{2d}.$$

Second, a mask $m : \mathbb{R}^d \times \mathbb{R}^d \rightarrow \mathbb{C}$ is applied to the time-frequency profile of f by solving the optimization problem

$$(1.2) \quad H_m f = \operatorname{argmin}_{\tilde{f}} \int_{\mathbb{R}^d \times \mathbb{R}^d} \left| m(x, \xi) \cdot V_g f(x, \xi) - V_g \tilde{f}(x, \xi) \right|^2 dx d\xi,$$

whose solution is, more explicitly,

$$(1.3) \quad H_m f(t) = \int_{\mathbb{R}^d \times \mathbb{R}^d} m(x, \xi) V_g f(x, \xi) g(t-x) e^{2\pi i \xi \cdot t} dx d\xi, \quad t \in \mathbb{R}^d.$$

While the filter (1.3) depends on the auxiliary window function g , different choices of smooth and fast-decaying g yield qualitatively similar results.

The subclass of *binary masks*, $m(x, \xi) \in \{0, 1\}$, plays a distinguished role in acoustic modeling — see, e.g., [30, 31]. In this case m is the indicator function of a domain $\Omega \subseteq \mathbb{R}^d \times \mathbb{R}^d$ and (1.3) models a *hard filter* that rejects certain time-frequency components, for example, following a perceptual criterion. The *direct estimation problem* consists in producing a binary mask optimally tailored to a certain task such as the separation of speech from noise in a particular auditory setup. In contrast, the *inverse estimation problem* consists in learning

2020 *Mathematics Subject Classification.* 42C40, 46E10, 60H40, 47B35, 46E22.

Key words and phrases. spectrograms, localization operators, binary masks, white noise, operator identification, level sets.

J. L. R. and M. S. gratefully acknowledge support from the Austrian Science Fund (FWF): Y 1199.

the mask of a filter from (known or unknown) test inputs, for example, so as to retrieve the current calibration of a device that simulates or enhances human hearing [21].

While the problem of retrieving a mask m from observations of filtered signals $H_m f$ is challenging — as it is one example of operator identification, see [23, 25, 28] and the references therein — learning a binary mask is expected to be substantially easier. In fact, it is household wisdom of acoustic modeling that a binary mask is revealed by simply inspecting the filtered output of *ambient noise*. The purpose of this article is to provide a formal analysis of this fact in the idealized setting of *white ambient noise* — that is, noise whose stochastics are independent at disjoint spatial locations. Crucially, *we do not assume the variance of the noise to be known*, and, similarly, we do not assume exact knowledge of the window function g .

2. RESULTS

2.1. Mask estimation with unknown noise level.

Setup. Let $g : \mathbb{R}^d \rightarrow \mathbb{C}$ be a Schwartz function normalized by $\|g\|_2 = 1$, let $\Omega \subseteq \mathbb{R}^{2d}$ be a compact domain, and denote H_Ω the filter (1.3) with binary mask

$$m(z) = \begin{cases} 1 & \text{if } z \in \Omega \\ 0 & \text{if } z \notin \Omega \end{cases}.$$

Ambient noise model. We consider zero-mean Gaussian *complex white noise* \mathcal{N} with variance $\sigma^2 > 0$, that is, a generalized complex-valued Gaussian stochastic process on \mathbb{R}^d satisfying

$$\begin{aligned} \mathbb{E}\{\mathcal{N}(z) \cdot \overline{\mathcal{N}(w)}\} &= \sigma^2 \cdot \delta(z - w), \\ \mathbb{E}\{\mathcal{N}(z) \cdot \mathcal{N}(w)\} &= 0. \end{aligned}$$

Measure-theoretic aspects are presented in more detail in Section 3.4. The key assumption is *whiteness*: If $E_1, E_2 \subset \mathbb{R}^d$ are disjoint Borel sets, then $\mathcal{N}|_{E_1}$ and $\mathcal{N}|_{E_2}$ are statistically independent. The assumption that \mathcal{N} is complex-valued is made for mathematical convenience, as it is compatible with the use of complex exponentials in the Fourier transform. (Indeed, the modulation operation $\mathcal{N} \rightarrow e^{2\pi i \xi} \cdot \mathcal{N}$, $\xi \in \mathbb{R}^d$, preserves the stochastics of \mathcal{N}). The minor modifications necessary to treat real-valued white noise are sketched in Section 2.2.

Data. Suppose that we observe $H_\Omega(\mathcal{N}_1), \dots, H_\Omega(\mathcal{N}_K)$, where $\mathcal{N}_1, \dots, \mathcal{N}_K$ are K independent realizations of complex white noise with *unknown variance* $\sigma^2 > 0$. Even though a typical realization of white noise \mathcal{N} is not a function on \mathbb{R}^d but merely a tempered distribution, the fact that $g \in \mathcal{S}(\mathbb{R}^d)$ allows us to interpret $H_\Omega(\mathcal{N})$ distributionally — see Section 3.4 for details.

Goal. We wish to estimate Ω based on the available data.

Proposed estimator. We first fix a function $\varphi \in \mathcal{S}(\mathbb{R}^d)$, which we call *reconstruction window*, normalized by $\|\varphi\|_2 = 1$. A typical choice is a Gaussian $\varphi(t) = 2^{d/4} e^{-\pi t^2}$. We then let

$$(2.1) \quad \rho(z) := \frac{1}{K} \sum_{k=1}^K |V_\varphi(H_\Omega \mathcal{N}_k)(z)|^2, \quad z = (x, \xi) \in \mathbb{R}^d \times \mathbb{R}^d$$

be the *average observed spectrogram*. As an estimate of Ω , we propose the following lower quantile of ρ :

$$(2.2) \quad \widehat{\Omega} := \left\{ z \in \mathbb{R}^d \times \mathbb{R}^d : \rho(z) \geq \frac{1}{4} \max_{w \in \mathbb{R}^{2d}} \rho(w) \right\}.$$

Assumptions. We assume that Ω is reasonably large in the sense that its measure dominates its perimeter:

$$(2.3) \quad |\Omega| \geq \max \left\{ 2, 8 \int_{\mathbb{R}^{2d}} |V_g g(z)|^2 |z| \, dz \cdot |\partial\Omega| \right\}.$$

Here, $|\partial\Omega|$ denotes the *perimeter* of Ω , that is the $2d - 1$ dimensional measure of its boundary (see Section 3.2).

Performance guarantees. The *estimation error* is the symmetric difference set

$$(2.4) \quad \Omega \Delta \widehat{\Omega} = (\Omega \setminus \widehat{\Omega}) \cup (\widehat{\Omega} \setminus \Omega).$$

Our main result shows that with overwhelming probability the estimation error is concentrated around the *boundary* of Ω ; see Figure 1 for an illustration. More precisely, denoting the r -neighborhood of a set $E \subseteq \mathbb{R}^{2d}$ by

$$E^r := \{ z \in \mathbb{R}^{2d} : d(z, E) < r \},$$

the main result reads as follows.

Theorem 2.1 (Recovery up to boundary details). *Let $g, \varphi \in \mathcal{S}(\mathbb{R}^d)$ with $\|g\|_2 = \|\varphi\|_2 = 2$ be model and reconstruction windows. Let $\Omega \subset \mathbb{R}^{2d}$ be compact and satisfying the largeness condition (2.3). Let $K \geq 4$, assume that K independent realizations of $H_\Omega(\mathcal{N})$ are observed, and consider the estimator $\widehat{\Omega}$ defined in (2.2).*

Then there exist positive constants $c, C, r > 0$, that depend on g and φ but not on Ω , such that with probability at least $1 - c \cdot |\Omega^r| \cdot e^{-CK}$, the estimation error satisfies

$$(2.5) \quad \Omega \Delta \widehat{\Omega} \subseteq [\partial\Omega]^r.$$

Let us remark on some aspects of Theorem 2.1:

- The estimation method *does not require knowledge of the noise level* $\sigma > 0$. Similarly, the performance guarantees are independent of σ .
- Recovery up to a neighborhood of the boundary of Ω is intuitively the best possible result, as the task is to approximate a domain from smooth data $H_\Omega(\mathcal{N}_K)$. The largeness assumption (2.3) means that the estimation objective is large compared to the expected unavoidable error. We are however unaware of a formal no-go result showing that boundary details are not recoverable.
- Given a confidence level $\varepsilon > 0$, Theorem 2.1 shows that the putatively optimal recovery (2.5) is achieved with only $\mathcal{O}(\log(|\Omega^r|/\varepsilon))$ measurements of ambient noise.
- While the estimation method does not require precise knowledge of the model window g , its time-frequency concentration does impact the performance guarantees through the largeness condition (2.3). Similarly, the correlation between the model and reconstruction windows

affects the overall estimation performance. In fact, as we shall see, the size of the constants c, C, r depends mainly on the following mutual correlation measure:

$$\int_{\mathbb{R}^{2d}} |V_\varphi g(z)|^2 |z| \, dz.$$

Thus, in practice, the choice of the reconstruction window φ amounts to a rough guess of the time-frequency profile of the model window g . See Figure 1 for an illustration with $\varphi \neq g$.

As an application of Theorem 2.1 we see that the measure of the estimation error is dominated by the perimeter of the masking domain $|\partial\Omega|$.

Theorem 2.2. *Under the conditions of Theorem 2.1, with the stated probability, the estimation error satisfies*

$$|\Omega \Delta \widehat{\Omega}| \leq C_1 \cdot |\partial\Omega|,$$

where the constant C_1 depends on φ and g but not on Ω .

Finally, we also derive a bound for the expected reconstruction error.

Theorem 2.3. *Under the conditions of Theorem 2.1, there exist constants $C_1, C_2, r > 0$ that depend on g and φ but not on Ω such that if*

$$K \geq C_1 \log(|\Omega^r|),$$

then

$$\mathbb{E} \left\{ |\Omega \Delta \widehat{\Omega}| \right\} \leq C_2 \cdot |\partial\Omega|.$$

Our proofs below provide more precise versions of the main results, with additional qualitative information on the various constants.

2.2. Real-valued noise. We now briefly discuss how to adapt the main result to *real* white noise. Consider the estimation problem in Section 2.1, but this time under the assumption that the ambient noise is real-valued and white. Specifically, suppose that we observe $H_\Omega(\mathcal{N}_1), \dots, H_\Omega(\mathcal{N}_K)$, where $\mathcal{N}_1, \dots, \mathcal{N}_K$ are independent copies of real-valued white noise on \mathbb{R}^d with variance $\sigma^2 > 0$.

Setting $K' := \lfloor K/2 \rfloor$, the new stochastic processes

$$(2.6) \quad \mathcal{N}'_k := \mathcal{N}_k + i \cdot \mathcal{N}_{k+K'}, \quad k = 1, \dots, K',$$

are independent copies of complex white noise with variance $2\sigma^2$. As the averaged spectrogram (2.1) associated with the observations $H_\Omega(\mathcal{N}'_1), \dots, H_\Omega(\mathcal{N}'_{K'})$ can be computed from the available data,

$$(2.7) \quad \rho(z) := \frac{1}{K'} \sum_{k=1}^{K'} |V_\varphi(H_\Omega \mathcal{N}'_k)(z)|^2 = \frac{1}{K'} \sum_{k=1}^{K'} |V_\varphi(H_\Omega \mathcal{N}_k)(z) + i \cdot V_\varphi(H_\Omega \mathcal{N}_{k+K'})(z)|^2,$$

and $K' \leq K \leq 3K'$ as soon as $K \geq 4$, the performance guarantees from Theorems 2.1, 2.2, and 2.3 still hold, with possibly larger constants.

Finally, note that if $\mathcal{N}_1, \dots, \mathcal{N}_K$ are independent copies of complex-valued white noise, then so are $\mathcal{N}'_1, \dots, \mathcal{N}'_{K'}$ as given by (2.6). Hence, the *complexified estimator* (2.7) satisfies the performance guarantees of Theorem 2.1 regardless of whether the ambient noise is real or complex-valued.




FIGURE 1. The symmetric difference $\Omega \Delta \widehat{\Omega}$ is depicted in grey and $\partial\Omega$ in black. Parameters: $|\Omega| = 100$; $K = 20$; $\varphi(t) = 2^{1/4}e^{-\pi t^2}$; left column: $g = \varphi$; right column: $g(t) = \varphi(t)t^2$.

2.3. Related literature and technical overview. The spectrogram of a function is the squared absolute value of its short-time Fourier transform (1.1) and provides a useful proxy for the elusive notion of a *time-varying spectrum* [8]. As with other quadratic time-frequency representations in the so-called *Cohen class*, its use represents a compromise between many desirable but only approximately achievable properties [10]. A specific merit of the spectrogram is being non-negative and efficiently computable, which makes it a popular tool in signal processing [27]. On the other hand, the choice of the analyzing window g introduces a trade-off between spatial and temporal resolution. In the acoustic filter model (1.3), g is an *partially unknown degree of freedom*. An important consequence of our work is that the estimation of a binary mask succeeds based only on a rough educated guess for g (namely, the reconstruction window φ).

The estimator that we propose and analyze is a level set of the average observed spectrogram (2.1) taken with an *observation dependent threshold* (lower quantile). Level sets of spectrograms are standard tools in signal processing. For example, a common method to extract a signal embedded into noise consists in computing a spectrogram level set with a carefully chosen threshold related to the expected signal to noise ratio. See [17] for performance guarantees for signal estimation under white noise contamination based on spectrogram level sets with Gaussian windows, and [4] for a systematic study of analytic time-frequency representations of white noise.

At the technical level, we make the central assumption that the ambient noise is *Gaussian*, which translates into suitable concentration properties for various statistical quantities. Indeed, we make essential use of concentration of measure for quadratic forms [3, 29]. In order to apply these in an analog setting, we consider adequate low-rank approximations of the filter (1.3).

It is a general principle that the low-rank core of a matrix can be revealed by sketching it with independent random vectors. One usually takes a number of random input vectors slightly exceeding the matrix numerical rank and then computes a reduced singular value decomposition [20]. Remarkably, as we show in Theorem 2.1, a time-frequency filter with a *binary* mask can be learned from far fewer noise measurements, and without costly linear algebra computations. (Indeed, the numerical rank of H_Ω is $\approx |\Omega|$ [24, Chapter 1] while the number of required measurements is $\approx \log(|\Omega|)$.) The proof of Theorem 2.1 exploits a priori knowledge of the *asymptotic profile of the spectrum and eigenvectors* of the filter H_Ω , which reduces the size of the learning task. At the technical level, we build and significantly elaborate on the spectral analysis of [1, 2, 5].

Finally, we point out some limitations of our work. First, while noise can be multifaceted [9], ours is white and Gaussian. Second, we work with signals directly in the continuous domain, while in practice measurements are finite, and effective duration and bandwidth needs to be taken into account [24, 27]. These are modeling simplifications and we expect that our work can be suitably generalized.

2.4. Organization. Section 3 establishes the notation and preliminary results. Basic background on time-frequency analysis, noise and spectral theory is provided in Section 4. The main results are then proved in Section 5.

3. PRELIMINARIES

3.1. Notation. We denote balls in \mathbb{R}^d by $B_R(z)$ and define the distance between a point z and a set Ω by $\text{dist}(z, \Omega) = \inf\{|z - w| : w \in \Omega\}$. Moreover, we write $A \lesssim B$ if there exists a universal constant $C > 0$ such that $A \leq CB$. We use $\|\cdot\|_s$ and $\|\cdot\|_F$ for the spectral and Frobenius norms of a matrix in $\mathbb{C}^{m \times m}$ respectively. The convolution of two functions f, g on \mathbb{R}^d is $f * g(z) = \int_{\mathbb{R}^d} f(w)g(z - w) dw$.

3.2. Sets with finite perimeter. For a compact set $\Omega \subset \mathbb{R}^{2d}$ we let $|\partial\Omega|$ denote the $2d - 1$ Hausdorff measure of the topological boundary of Ω . Whenever this measure is finite, the set Ω has *finite perimeter* in the sense that its characteristic function χ_Ω has bounded variation. Moreover, in this case, $\text{Var}(\chi_\Omega) \leq |\partial\Omega|$, as $\text{Var}(\chi_\Omega)$ is the $2d - 1$ Hausdorff measure of the measure-theoretic boundary of Ω , which is a subset of the topological boundary of Ω . In our main results, the assumption that Ω is compact, together with (2.3), implies that $|\partial\Omega| < \infty$. See [15, Chapter 5] for comprehensive background on sets of finite perimeter.

We will use the following estimate on regularization with an integrable convolution kernel $\psi : \mathbb{R}^{2d} \rightarrow \mathbb{R}$:

$$(3.1) \quad \|\chi_\Omega * \psi - (f\psi)\chi_\Omega\|_1 \leq \int_{\mathbb{R}^{2d}} |\psi(z)||z| dz \cdot |\partial\Omega|,$$

for a proof, see, e.g., [1, Lemma 3.2].

3.3. Complex Gaussian vectors. A complex Gaussian vector is a random vector X on \mathbb{C}^n such that $(\operatorname{Re}(X), \operatorname{Im}(X))$ is normally distributed, has zero mean, and vanishing pseudo-covariance $\mathbb{E}\{XX^t\} = 0$. The stochastics of such X are thus encoded in its covariance matrix

$$\Sigma = \mathbb{E}\{XX^*\},$$

and we write $X \sim \mathcal{CN}(0, \Sigma)$.

3.4. Complex white noise. Let $\mathcal{S}_{\mathbb{R}}(\mathbb{R}^d)$ and $\mathcal{S}(\mathbb{R}^d)$ be the spaces of real and complex valued Schwarz functions and $\mathcal{S}'_{\mathbb{R}}(\mathbb{R}^d)$, $\mathcal{S}'(\mathbb{R}^d)$ their respective duals (the spaces of tempered distributions). By the Bochner-Minlos theorem, there exists a unique probability measure on $\mathcal{B}_{\mathbb{R}}$, the family of Borel subsets of $\mathcal{S}'_{\mathbb{R}}(\mathbb{R}^d)$, such that

$$\int_{\mathcal{S}'_{\mathbb{R}}(\mathbb{R}^d)} e^{i\langle f, \varphi \rangle} d\mu_{\mathbb{R}}(\varphi) = e^{-\frac{\sigma^2}{4}\|f\|^2},$$

for all $f \in \mathcal{S}_{\mathbb{R}}(\mathbb{R}^d)$. If $f, g \in \mathcal{S}_{\mathbb{R}}(\mathbb{R}^d)$, then $\langle f, \varphi \rangle \sim \mathcal{N}(0, \frac{\sigma^2}{2}\|f\|^2)$ and $\mathbb{E}\{\langle f, \varphi \rangle \overline{\langle g, \varphi \rangle}\} = \frac{\sigma^2}{2}\langle f, g \rangle$. In particular, $\langle f, \varphi \rangle$ and $\langle g, \varphi \rangle$ are independent if and only if f, g are orthogonal.

With the identification $\mathcal{S}(\mathbb{R}^d) = \mathcal{S}_{\mathbb{R}}(\mathbb{R}^d) + i\mathcal{S}_{\mathbb{R}}(\mathbb{R}^d)$, we introduce the product measure $\mu_{\mathbb{C}} = \mu_{\mathbb{R}} \times i\mu_{\mathbb{R}}$. Let $\mathcal{B}_{\mathbb{C}}$ denote the product σ -algebra on $\mathcal{S}'(\mathbb{R}^d)$. Then we may define the measure space $(\mathcal{S}'(\mathbb{R}^d), \mathcal{B}_{\mathbb{C}}, \mu_{\mathbb{C}})$ which we call *complex white noise*. If $f, g \in \mathcal{S}(\mathbb{R}^d)$ and \mathcal{N} is an instance of complex white noise, then $\langle f, \mathcal{N} \rangle \sim \mathcal{CN}(0, \sigma^2\|f\|^2)$ and $\mathbb{E}\{\langle f, \mathcal{N} \rangle \overline{\langle g, \mathcal{N} \rangle}\} = \sigma^2\langle f, g \rangle$. For more on complex white noise, see for example [22, Section 6].

3.5. Concentration of measure for quadratic forms. We will need the following complex version of the Hanson-Wright inequality [3, 29], which we prove for completeness.

Theorem 3.1. *Let X be an m -dimensional complex Gaussian random variable with $X \sim \mathcal{CN}(0, \Sigma)$ and $A \in \mathbb{C}^{m \times m}$ Hermitian. Then for every $t > 0$,*

$$\mathbb{P}(|\langle AX, X \rangle - \mathbb{E}\{\langle AX, X \rangle\}| \geq t) \leq 2 \exp\left(-C_{\text{hw}} \min\left(\frac{t^2}{\|\Sigma\|_s^2 \|A\|_F^2}, \frac{t}{\|\Sigma\|_s \|A\|_s}\right)\right)$$

for some universal constant $C_{\text{hw}} > 0$.

Proof. Define $Y := (\operatorname{Re}(X), \operatorname{Im}(X))^T \in \mathbb{R}^{2m}$ as well as

$$\mathbb{A} := \begin{pmatrix} \operatorname{Re}(A) & -\operatorname{Im}(A) \\ \operatorname{Im}(A) & \operatorname{Re}(A) \end{pmatrix} \in \mathbb{R}^{2m \times 2m}.$$

As A is hermitian, one has that \mathbb{A} is symmetric and $\langle AX, X \rangle = \langle \mathbb{A}Y, Y \rangle$ which implies that $\|A\|_s = \|\mathbb{A}\|_s$. On the other hand, it is clear from its definition that $\|\mathbb{A}\|_F^2 = 2\|A\|_F^2$. Moreover, if $X \sim \mathcal{CN}(0, \Sigma)$ then $Y \sim \mathcal{N}(0, \Sigma')$ with

$$\Sigma' = \begin{pmatrix} \mathbb{E}\{\operatorname{Re}(X)\operatorname{Re}(X)^T\} & \mathbb{E}\{\operatorname{Im}(X)\operatorname{Re}(X)^T\} \\ \mathbb{E}\{\operatorname{Re}(X)\operatorname{Im}(X)^T\} & \mathbb{E}\{\operatorname{Im}(X)\operatorname{Im}(X)^T\} \end{pmatrix}.$$

Again we have $\langle \Sigma X, X \rangle = \langle \Sigma' Y, Y \rangle$ showing that $\|\Sigma\|_s = \|\Sigma'\|_s$. The result then follows after an application of [3, Theorem 2.5]. \square

4. TIME-FREQUENCY FILTERS AND THE RANGE OF THE SHORT-TIME FOURIER TRANSFORM

4.1. Basic properties of the STFT. Let $z = (x, \xi) \in \mathbb{R}^d \times \mathbb{R}^d$. The *time-frequency shifts* of a function $f \in L^2(\mathbb{R}^d)$ are

$$\pi(z)f(t) = e^{2\pi i \xi \cdot t} f(t - x), \quad z = (x, \xi) \in \mathbb{R}^d \times \mathbb{R}^d.$$

The short-time Fourier transform (STFT) of a function $f \in L^2(\mathbb{R}^d)$ with respect to a window $g \in L^2(\mathbb{R}^d)$ is defined by (1.1) and satisfies the following *orthogonality relation*

$$(4.1) \quad \int_{\mathbb{R}^{2d}} V_{g_1} f_1(z) \overline{V_{g_2} f_2(z)} dz = \langle f_1, f_2 \rangle \langle g_2, g_1 \rangle, \quad f_1, f_2, g_1, g_2 \in L^2(\mathbb{R}^d).$$

The range of the STFT, $V_g(L^2(\mathbb{R}^d))$, is a reproducing kernel subspace of $L^2(\mathbb{R}^{2d})$ with *reproducing kernel* $K_g(z, w) = \langle \pi(w)g, \pi(z)g \rangle$. Concretely, this means that $V_g(L^2(\mathbb{R}^d))$ is closed in $L^2(\mathbb{R}^{2d})$ and the following reproducing formula holds:

$$(4.2) \quad V_g f(z) = \int_{\mathbb{R}^{2d}} V_g(w) K_g(z, w) dw, \quad f \in L^2(\mathbb{R}^d).$$

As soon as $g \in \mathcal{S}(\mathbb{R}^d)$, the definition of the short-time Fourier transform (1.1) extends to $f \in \mathcal{S}'(\mathbb{R}^d)$ in the usual way and yields a continuous function $V_g f : \mathbb{R}^{2d} \rightarrow \mathbb{C}$; see [18, Chapter 11], or [6].

4.2. Spectral properties of time-frequency filters. Let $g \in \mathcal{S}(\mathbb{R}^d)$ with $\|g\|_2 = 1$ and $\Omega \subset \mathbb{R}^{2d}$ be compact. The *time-frequency localization operator* $H_\Omega : L^2(\mathbb{R}^d) \rightarrow L^2(\mathbb{R}^d)$ is defined by the formula:

$$(4.3) \quad H_\Omega f = \int_{\Omega} V_g f(z) \pi(z) g dz,$$

where the integral is to be interpreted in the weak sense

$$\langle H_\Omega f, h \rangle = \int_{\Omega} V_g f(z) \langle \pi(z) g, h \rangle dz, \quad h \in L^2(\mathbb{R}^d).$$

Originally introduced in [13], H_Ω is a basic tool in signal processing as it models a non-stationary filter. As an operator, H_Ω is compact and self-adjoint. Let $1 \geq \lambda_1 \geq \lambda_2 \geq \dots > 0$ be its non-zero eigenvalues counted with multiplicities and $\{f_m\}_{m \in \mathbb{N}} \subset L^2(\mathbb{R}^d)$ the corresponding orthonormal set of eigenfunctions. This set may be incomplete if H_Ω has a non-trivial null-space — it could also be finite if H_Ω has finite rank, but we still write $m \in \mathbb{N}$ with a slight abuse of notation. In any case, H_Ω has infinite rank as soon as Ω has non-empty interior [14, Lemma 5.8]. The set of eigenfunctions are not only orthogonal on \mathbb{R}^d but they also satisfy the following *double orthogonality* property:

$$(4.4) \quad \int_{\Omega} V_g f_m(z) \overline{V_g f_n(z)} dz = \lambda_m \delta_{m,n}.$$

It is easy to see that H_Ω is trace-class and

$$(4.5) \quad \sum_{m \geq 1} \lambda_m = |\Omega|.$$

The investigation of the fine asymptotics of the spectrum of H_Ω is an active field of research. Roughly stated, H_Ω has $\approx |\Omega|$ eigenvalues λ_m that are close to 1, while λ_m decays fast as soon as k is moderately larger than $|\Omega|$ [13]. We will only need the following simple estimate, whose proof follows from a minor variation of [26, Lemma 4.3] and is omitted.

Lemma 4.1. *Let $g \in \mathcal{S}(\mathbb{R})$ satisfy $\|g\|_2 = 1$, and let $\Omega \subset \mathbb{R}^{2d}$ be a compact set satisfying (2.3). Then $\lambda_m \geq \frac{3}{4}$ for every $1 \leq m \leq |\Omega|/2$.*

The definition of H_Ω readily extends to distributional arguments: if $f \in \mathcal{S}'(\mathbb{R}^d)$, then $V_g f$ is a continuous function, and (4.3) is well-defined. It follows from basic pseudo-differential theory that

$$(4.6) \quad H_\Omega : \mathcal{S}'(\mathbb{R}^d) \rightarrow \mathcal{S}(\mathbb{R}^d),$$

and

$$(4.7) \quad \langle H_\Omega f, h \rangle = \langle f, H_\Omega h \rangle, \quad f, h \in \mathcal{S}'(\mathbb{R}^d).$$

(Indeed, the *Weyl symbol* of H_Ω is the Schwartz function $\chi_\Omega * W_g$, where W_g is the Wigner distribution of f — see [16, Chapter 2 and Theorem 2.21].) In particular, $f_m \in \mathcal{S}(\mathbb{R}^d)$, for all $k \geq 1$; see [5, 11, 12] for more refined regularity properties.

4.3. Filtering white noise. Almost every realization of white noise \mathcal{N} defines a tempered distribution, and, by (4.6), $H_\Omega \mathcal{N}$ is a well-defined random Schwartz function on \mathbb{R}^{2d} — see [4, Section 3], [19, Section 6.1] and [17, Section 3] for more on the random function $V_g \mathcal{N}$.

We now note that the eigenexpansion of H_Ω can be applied to white noise.

Lemma 4.2. *Let $g \in \mathcal{S}(\mathbb{R}^d)$ with $\|g\|_2 = 1$, $\Omega \subset \mathbb{R}^{2d}$ compact, and \mathcal{N} complex white noise with standard deviation σ . Then there exists a sequence $\alpha_m \sim \mathcal{CN}(0, \sigma^2)$ of independent complex normal variables such that, almost surely,*

$$(4.8) \quad H_\Omega(\mathcal{N}) = \sum_{m=1}^{\infty} \lambda_m \alpha_m f_m,$$

with (almost sure) absolute convergence in $L^2(\mathbb{R}^{2d})$.

Proof. Let $\alpha_m := \langle \mathcal{N}, f_m \rangle$. The orthogonality of $\{f_m : m \geq 1\}$ implies the independence of $\{\alpha_m : m \geq 1\}$. By (4.5), $\sum_m \lambda_m \mathbb{E}\{|\alpha_m|\} < \infty$. Hence, almost surely, $\sum_m \lambda_m |\alpha_m| < \infty$. Consider one such realization. Then $\sum_m \lambda_m \alpha_m f_m$ is absolutely convergent in $L^2(\mathbb{R}^d)$. In addition, for $m' \geq 1$,

$$\left\langle \sum_m \lambda_m \alpha_m f_m, f_{m'} \right\rangle = \lambda_{m'} \alpha_{m'},$$

by absolute convergence, while

$$\langle H_\Omega \mathcal{N}, f_{m'} \rangle = \langle \mathcal{N}, H_\Omega f_{m'} \rangle = \lambda_{m'} \alpha_{m'}.$$

On the other hand, $\langle \sum_m \lambda_m \alpha_m f_m, h \rangle = 0$ for $h \in \text{Ker}(H_\Omega) = \{f_m : m \geq 1\}^\perp$, while (4.7) gives

$$\langle H_\Omega \mathcal{N}, h \rangle = \langle \mathcal{N}, H_\Omega h \rangle = 0.$$

This proves (4.8). □

5. PROOF OF THE MAIN RESULTS

Throughout this section we let $g, \varphi \in \mathcal{S}(\mathbb{R}^d)$ be normalized by $\|g\|_2 = \|\varphi\|_2 = 1$. We also let $\Omega \subseteq \mathbb{R}^{2d}$ be compact with $|\partial\Omega| < \infty$ and satisfying (2.3). The corresponding time-frequency localization operator is diagonalized as in Section 4.2; we adopt the corresponding notation. We also let $\mathcal{N}_1, \dots, \mathcal{N}_K$ be K independent realizations of complex white noise with variance $\sigma^2 > 0$.

As a first step, we investigate the case $\sigma = 1$ and level sets

$$(5.1) \quad S_\delta = \{z \in \mathbb{R}^{2d} : \rho(z) \geq \delta\}$$

associated with a deterministic threshold $\delta \in (0, 1)$. Afterwards we investigate general σ and random thresholds.

We also introduce the auxiliary function $\vartheta : \mathbb{R}^{2d} \rightarrow \mathbb{R}_{\geq 0}$:

$$(5.2) \quad \vartheta(z) := \sum_{m \in \mathbb{N}} |\lambda_m V_\varphi f_m(z)|^2, \quad z \in \mathbb{R}^{2d}.$$

As $\{V_\varphi f_m\}_{m \in \mathbb{N}}$ is an orthonormal sequence in the reproducing kernel Hilbert space $V_\varphi(L^2(\mathbb{R}))$,

$$(5.3) \quad \vartheta(z) \leq \sum_{m=1}^{\infty} |V_\varphi f_m(z)|^2 \leq K_\varphi(z, z) = 1,$$

while (4.5) shows that ϑ is not identically zero.

5.1. Pointwise error estimate. We start by investigating the stochastic concentration of the functions ρ and ϑ .

Lemma 5.1. *Let $\sigma = 1$. There exists a universal constant $C_1 \in (0, 1]$ such that for every $z \in \mathbb{R}^{2d}$:*

$$(5.4) \quad \mathbb{P}(|\rho(z) - \vartheta(z)| \geq t) \leq 3 \exp\left(-C_1 K \min\left(\frac{t^2}{\vartheta(z)^2}, \frac{t}{\vartheta(z)}\right)\right).$$

Proof. Let $L \in \mathbb{N}$ and define the complex Gaussian random vector $X_m := \alpha_{\text{mod}(m-1, L)+1}^{\lceil m/L \rceil}$, for $m \in \{1, \dots, LK\}$. Clearly, $X \sim \mathcal{CN}(0, I_{KL})$. Let us also define the matrix-valued function $M : \mathbb{R}^{2d} \rightarrow \mathbb{R}^{L \times L}$,

$$M(z)_{\ell, m} := \lambda_\ell \lambda_m V_\varphi f_\ell(z) \overline{V_\varphi f_m(z)},$$

and the block-diagonal Hermitian matrix $\mathcal{M} : \mathbb{R}^{2d} \rightarrow \mathbb{R}^{KL \times KL}$,

$$\mathcal{M}(z) := \frac{1}{K} \begin{pmatrix} M(z) & & 0 \\ & \ddots & \\ 0 & & M(z) \end{pmatrix} \in \mathbb{C}^{KL \times KL}.$$

Let P_L denote the projection onto the space spanned by the first L eigenfunctions of H_Ω . It can then be verified that

$$\begin{aligned} \rho_L(z) &:= \frac{1}{K} \sum_{k=1}^K |V_\varphi(P_L H_\Omega \mathcal{N}_k)(z)|^2 = \frac{1}{K} \sum_{k=1}^K \sum_{\ell=1}^L \sum_{m=1}^L \alpha_\ell^k \overline{\alpha_m^k} \lambda_\ell \lambda_m V_\varphi f_\ell(z) \overline{V_\varphi f_m(z)} \\ &= \langle \mathcal{M}(z) X, X \rangle. \end{aligned}$$

In order to apply Theorem 3.1, we need to calculate the expectation of $\langle \mathcal{M}(z)X, X \rangle$ as well as the Frobenius and spectral norm of $\mathcal{M}(z)$.

The independence of the random variables α_m^k implies

$$\begin{aligned} \mathbb{E}\{\rho_L(z)\} &= \mathbb{E}\left\{\frac{1}{K}\sum_{k=1}^K|V_\varphi(P_L H_\Omega \mathcal{N}_k)(z)|^2\right\} \\ &= \frac{1}{K}\sum_{k=1}^K\sum_{\ell=1}^L\sum_{m=1}^L\lambda_\ell\lambda_m\mathbb{E}\left\{\alpha_\ell^k\overline{\alpha_m^k}\right\}V_\varphi f_\ell(z)\overline{V_\varphi f_m(z)} \\ &= \sum_{m=1}^L|\lambda_m V_\varphi f_m(z)|^2 =: \vartheta_L(z). \end{aligned}$$

The Frobenius norm of $\mathcal{M}(z)$ is

$$\begin{aligned} \|\mathcal{M}(z)\|_F^2 &= \frac{1}{K}\|M(z)\|_F^2 = \frac{1}{K}\sum_{\ell=1}^L\sum_{m=1}^L|\lambda_\ell\lambda_m V_\varphi f_\ell(z)V_\varphi f_m(z)|^2 \\ &= \frac{1}{K}\left(\sum_{m=1}^L|\lambda_m V_\varphi f_m(z)|^2\right)^2 \leq \frac{1}{K}\left(\sum_{m=1}^\infty|\lambda_m V_\varphi f_m(z)|^2\right)^2 = \frac{1}{K}\vartheta(z)^2. \end{aligned}$$

The spectral norm of $\mathcal{M}(z)$ is $\|\mathcal{M}(z)\|_s = \frac{1}{K}\|M(z)\|_s$. Thus, by Cauchy-Schwarz,

$$\begin{aligned} \|M(z)\|_s &= \sup_{\|X\|_2=1}\left(\sum_{m=1}^L\left|\sum_{\ell=1}^L(M(z))_{m,\ell}X_\ell\right|^2\right)^{\frac{1}{2}} \\ &\leq\left(\sum_{m=1}^L\sum_{\ell=1}^L|\lambda_\ell\lambda_m V_\varphi f_\ell(z)V_\varphi f_m(z)|^2\right)^{\frac{1}{2}} = \vartheta_L(z) \leq \vartheta(z). \end{aligned}$$

Therefore, by Theorem 3.1,

$$(5.5) \quad \mathbb{P}(|\rho_L(z) - \vartheta_L(z)| \geq t) \leq 2 \exp\left(-C_{hw}K \min\left(\frac{t^2}{\vartheta(z)^2}, \frac{t}{\vartheta(z)}\right)\right).$$

Let us use the following abbreviations

$$\begin{aligned} R_1(z) &:= \frac{1}{K}\sum_{k=1}^K\sum_{\ell=L+1}^\infty\sum_{m=1}^L\lambda_\ell\lambda_m\alpha_\ell^k\overline{\alpha_m^k}V_\varphi f_\ell(z)\overline{V_\varphi f_m(z)}, \\ R_2(z) &:= \frac{1}{K}\sum_{k=1}^K\sum_{\ell=1}^L\sum_{m=L+1}^\infty\lambda_\ell\lambda_m\alpha_\ell^k\overline{\alpha_m^k}V_\varphi f_\ell(z)\overline{V_\varphi f_m(z)}, \\ R_3(z) &:= \frac{1}{K}\sum_{k=1}^K\sum_{\ell=L+1}^\infty\sum_{m=L+1}^\infty\lambda_\ell\lambda_m\alpha_\ell^k\overline{\alpha_m^k}V_\varphi f_\ell(z)\overline{V_\varphi f_m(z)}. \end{aligned}$$

We now carry out certain estimates for $L \rightarrow \infty$, under the assumption that $\lambda_n \neq 0$ for all $n \geq 1$. We remark that the conclusions will also hold trivially if $\{\lambda_n\}_{n \in \mathbb{N}}$ is finitely supported,

as then $R_1 = R_2 = R_3 = 0$ for L large enough. We first estimate

$$\begin{aligned} \mathbb{P}(|\rho(z) - \vartheta(z)| \geq t) &\leq \mathbb{P}(|\rho_L(z) + R_1(z) + R_2(z) + R_3(z) - \vartheta(z)| \geq t) \\ &\leq \mathbb{P}(|\rho_L(z) - \vartheta(z)| + |R_1(z)| + |R_2(z)| + |R_3(z)| \geq t) \\ &\leq \mathbb{P}\left(|\rho_L(z) - \vartheta(z)| \geq \frac{t}{4}\right) + \sum_{s=1}^3 \mathbb{P}\left(|R_s(z)| \geq \frac{t}{4}\right), \end{aligned}$$

where we used that at least one of the four summands needs to be larger than one fourth of $t/4$ and subsequently the union bound.

Let us treat the summands separately. First, we choose L large enough such that ϑ_L is a good approximation of ϑ . In particular, we assume $|\vartheta_L(z) - \vartheta(z)| \leq t/8$. We note here that L may be chosen independently of z since $|V_\varphi f_m(z)| \leq 1$ for every $z \in \mathbb{R}^{2d}$. Then, using (5.5) we obtain

$$\begin{aligned} \mathbb{P}\left(|\rho_L(z) - \vartheta(z)| \geq \frac{t}{4}\right) &\leq \mathbb{P}\left(|\rho_L(z) - \vartheta_L(z)| \geq \frac{t}{8}\right) \\ &\leq 2 \cdot \exp\left(-\frac{C_{hw}}{64} K \min\left(\frac{t^2}{\vartheta(z)^2}, \frac{t}{\vartheta(z)}\right)\right). \end{aligned}$$

Let us now estimate the term R_1 . Then R_2 and R_3 can be treated with the same arguments. First note that, by (4.5),

$$\begin{aligned} |R_1(z)| &\leq \frac{1}{K} \sum_{k=1}^K \sum_{\ell=1}^{\infty} \sum_{m=L+1}^{\infty} \lambda_m \lambda_\ell |\alpha_m^k \alpha_\ell^k| \\ &\leq \frac{1}{K} \sum_{k=1}^K \left(\sum_{m=L+1}^{\infty} \lambda_m\right)^{\frac{1}{2}} \left(\sum_{m=L+1}^{\infty} \lambda_m |\alpha_m^k|^2\right)^{\frac{1}{2}} \left(\sum_{\ell=1}^{\infty} \lambda_\ell\right)^{\frac{1}{2}} \left(\sum_{\ell=1}^{\infty} \lambda_\ell |\alpha_\ell^k|^2\right)^{\frac{1}{2}} \\ &\leq \frac{1}{K} \left(|\Omega| \sum_{m=L+1}^{\infty} \lambda_m\right)^{\frac{1}{2}} \sum_{k=1}^K \sum_{\ell=1}^{\infty} \lambda_\ell |\alpha_\ell^k|^2. \end{aligned}$$

This estimate implies that

$$\begin{aligned} \mathbb{P}\left(|R_1(z)| \geq \frac{t}{4}\right) &\leq \mathbb{P}\left(\sum_{k=1}^K \sum_{\ell=1}^{\infty} \lambda_\ell |\alpha_\ell^k|^2 \geq \frac{Kt}{4} \left(|\Omega| \sum_{m=L+1}^{\infty} \lambda_m\right)^{-\frac{1}{2}}\right) \\ &\leq \sum_{k=1}^K \mathbb{P}\left(\sum_{\ell=1}^{\infty} \lambda_\ell |\alpha_\ell^k|^2 \geq \frac{t}{4} \left(|\Omega| \sum_{m=L+1}^{\infty} \lambda_m\right)^{-\frac{1}{2}}\right) \\ &= K \mathbb{P}\left(\sum_{\ell=1}^{\infty} \lambda_\ell |\alpha_\ell^1|^2 \geq \frac{t}{4} \left(|\Omega| \sum_{m=L+1}^{\infty} \lambda_m\right)^{-\frac{1}{2}}\right). \end{aligned}$$

The probability on the right hand side goes to zero as $L \rightarrow \infty$ (note that the left hand side of the tail bound is independent of L). In particular, we may choose L large enough such that

$$\mathbb{P}\left(|R_1(z)| \geq \frac{t}{4}\right) \leq \frac{1}{3} \cdot \exp\left(-\frac{C_{hw}}{64} K \min\left(\frac{t^2}{\vartheta(z)^2}, \frac{t}{\vartheta(z)}\right)\right).$$

Repeating the argument for R_2 and R_3 and choosing $C_1 = \min(C_{hw}/64, 1)$ concludes the proof. \square

We now turn our attention to the level set (5.1).

Theorem 5.2. *Let $\delta \in (0, \frac{2}{3})$ and $\sigma = 1$. If $z \in \mathbb{R}^{2d}$ is such that $|\vartheta(z) - \chi_\Omega(z)| \leq \frac{\delta}{4}$, then there exists a universal constant $C > 0$ such that*

$$(5.6) \quad \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_\delta}(z)) \leq 3 \cdot e^{-CK},$$

and

$$(5.7) \quad \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_\delta}(z)) \leq 3 \cdot \exp\left(-C \frac{K\delta}{\vartheta(z)}\right), \quad \text{if } z \in \Omega^c.$$

Proof. Let us first reinspect the event $A(z) := \{\chi_\Omega(z) \neq \chi_{S_\delta}(z)\}$. If $z \notin \Omega$, then the event $A(z)$ is equivalently described by $\delta \leq \rho(z)$, and, in this case,

$$\delta \leq \rho(z) = |\rho(z) - \chi_\Omega(z)| \leq |\rho(z) - \vartheta(z)| + |\chi_\Omega(z) - \vartheta(z)|.$$

Hence, by the assumption $|\chi_\Omega(z) - \vartheta(z)| \leq \delta/4$ it follows that

$$A(z) \subset \left\{ |\rho(z) - \vartheta(z)| \geq \frac{\delta}{4} \right\},$$

and consequently

$$\mathbb{P}(\chi_\Omega(z) \neq \chi_{S_\delta}(z)) \leq \mathbb{P}\left(|\rho(z) - \vartheta(z)| \geq \frac{\delta}{4}\right).$$

Therefore, (5.6) and (5.7) follow from Lemma 5.1 and the observation $\delta/\vartheta(z) \geq 4$.

If on the other hand $z \in \Omega$, then $A(z)$ is characterized by $\rho(z) < \delta$ and we have

$$1 - \delta < 1 - \rho(z) = |\rho(z) - \chi_\Omega(z)| \leq |\rho(z) - \vartheta(z)| + |\vartheta(z) - \chi_\Omega(z)|.$$

Again, by the assumption $|\chi_\Omega(z) - \vartheta(z)| \leq \delta/4$, and $\delta < \frac{2}{3}$ we obtain

$$A(z) \subset \left\{ |\rho(z) - \vartheta(z)| > 1 - \frac{5\delta}{4} \right\} \subset \left\{ |\rho(z) - \vartheta(z)| > \frac{1}{6} \right\},$$

and may then proceed as before, this time noting that $\vartheta(z) \leq 1$. \square

In Theorem 5.2 we required that $|\vartheta(z) - \chi_\Omega(z)| \leq \delta/4$. Let us now bound the measure of the set where this is not satisfied.

Proposition 5.3. *Set*

$$M(g, \varphi) := \int_{\mathbb{R}^{2d}} |V_\varphi g(z)|^2 |z| \, dz.$$

Then

- (i) $\|\chi_\Omega - \vartheta\|_1 \lesssim M(g, \varphi) \cdot |\partial\Omega|$,
- (ii) $|\{z \in \mathbb{R}^{2d} : |\vartheta(z) - \chi_\Omega(z)| \geq \delta\}| \lesssim M(g, \varphi) \cdot \frac{|\partial\Omega|}{\delta}$,
- (iii) $\|\vartheta\|_1 \leq |\Omega|$,
- (iv) $|\chi_\Omega(z) - \vartheta(z)| \lesssim M(g, \varphi) \cdot \text{dist}(z, \partial\Omega)^{-1}$.

Proof. On the one hand, by the eigen-expansion $H_\Omega = \sum_m \lambda_m \langle \cdot, f_m \rangle f_m$,

$$\langle H_\Omega \pi(z)\varphi, \pi(z)\varphi \rangle = \sum_{m \in \mathbb{N}} \lambda_m |\langle \pi(z)\varphi, f_m \rangle|^2 = \sum_{m \in \mathbb{N}} \lambda_m |V_\varphi f_m(z)|^2.$$

On the other hand, applying (4.3) directly gives

$$\begin{aligned} \langle H_\Omega \pi(z)\varphi, \pi(z)\varphi \rangle &= \int_{\mathbb{R}^{2d}} \chi_\Omega(w) |\langle \pi(z)\varphi, \pi(w)g \rangle|^2 dw \\ &= \int_{\mathbb{R}^{2d}} \chi_\Omega(w) |V_\varphi g(z-w)|^2 dw = \chi_\Omega * |V_\varphi g|^2(z), \end{aligned}$$

which shows

$$\sum_{m \in \mathbb{N}} \lambda_m |V_\varphi f_m(z)|^2 = \chi_\Omega * |V_\varphi g|^2(z), \quad z \in \mathbb{R}^{2d}.$$

We hence estimate

$$|\chi_\Omega(z) - \vartheta(z)| \leq |\chi_\Omega(z) - \chi_\Omega * |V_\varphi g|^2(z)| + \sum_{m \in \mathbb{N}} (\lambda_m - \lambda_m^2) |V_\varphi f_m(z)|^2.$$

If $z \in \Omega$, then

$$\sum_{m \in \mathbb{N}} (\lambda_m - \lambda_m^2) |V_\varphi f_m(z)|^2 \leq \sum_{m \in \mathbb{N}} (1 - \lambda_m) |V_\varphi f_m(z)|^2 = \chi_\Omega(z) - \chi_\Omega * |V_\varphi g|^2(z),$$

where we used that $\sum_m |V_\varphi f_m(z)|^2 = K_\varphi(z, z) = 1$. If on the other hand $z \in \Omega^c$, then

$$\sum_{m \in \mathbb{N}} (\lambda_m - \lambda_m^2) |V_\varphi f_m(z)|^2 \leq \sum_{m \in \mathbb{N}} \lambda_m |V_\varphi f_m(z)|^2 = \chi_\Omega * |V_\varphi g|^2(z) - \chi_\Omega(z),$$

and therefore

$$(5.8) \quad |\chi_\Omega(z) - \vartheta(z)| \leq 2 |\chi_\Omega(z) - \chi_\Omega * |V_\varphi g|^2(z)|.$$

Since $\|V_\varphi g\|_2 = 1$, by (3.1),

$$\|\chi_\Omega - \vartheta\|_1 \leq 2 |\partial\Omega| \int_{\mathbb{R}^{2d}} |V_\varphi g(z)|^2 |z| dz,$$

that is (i) holds. Property (ii) then follows by Chebyshev's inequality. The third property follows directly from (4.5): $\|\vartheta\|_1 = \sum_m \lambda_m^2 \leq \sum_m \lambda_m = |\Omega|$.

Finally, to prove (iv) we define $R = \text{dist}(z, \partial\Omega)$. Then $\chi_\Omega(z) = \chi_\Omega(w)$ for every $|z-w| < R$ which implies using (5.8)

$$\begin{aligned} |\chi_\Omega(z) - \vartheta(z)| &\leq 2 |\chi_\Omega(z) - \chi_\Omega * |V_\varphi g|^2(z)| \\ &\leq 2 |\chi_\Omega(z) - \chi_\Omega * (|V_\varphi g|^2 \chi_{B_R(0)})(z)| + 2 |\chi_\Omega * (|V_\varphi g|^2 (1 - \chi_{B_R(0)}))(z)| \\ &\leq 2 \chi(z) \left(1 - \int_{|z-w| < R} |V_\varphi g(z-w)|^2 dw \right) + 2 \int_{|w| \geq R} |V_\varphi g(w)|^2 dw. \end{aligned}$$

Hence,

$$|\chi_\Omega(z) - \vartheta(z)| \leq 4 \int_{|w| \geq R} |V_\varphi g(w)|^2 dy \leq \frac{4}{R} \int_{\mathbb{R}^{2d}} |V_\varphi g(z)|^2 |z| dz.$$

□

5.2. Estimates of symmetric difference with high probability. Our subsequent estimates depend on the local supremum

$$\mathcal{K}(z, w) := \sup_{y \in B_1(z)} |K_\varphi(y, w)|.$$

Let us first bound the probability of $\|(\rho - \vartheta)\mathcal{K}(z_0, \cdot)\|_1$ being large.

Lemma 5.4. *Let $z_0 \in \mathbb{R}^{2d}$, $\sigma = 1$, and $\gamma \in [\gamma_0, 1]$, $\gamma_0 > 0$. Then there exist constants $c, C > 0$ only depending on φ and γ_0 such that*

$$(5.9) \quad \mathbb{P} \left(\int_{\mathbb{R}^{2d}} |\rho(w) - \vartheta(w)| \mathcal{K}(z_0, w) dw \geq \gamma \right) \leq c \cdot e^{-CK} \cdot \int_{\mathbb{R}^{2d}} \vartheta(w) \mathcal{K}(z_0, w) dw.$$

Proof. Let us define

$$(5.10) \quad C_\varphi := \int_{\mathbb{R}^{2d}} \mathcal{K}(0, w) dw < \infty.$$

Let $p \geq 1$. By Chebyshev's and Hölder's inequalities,

$$\begin{aligned} & \mathbb{P} \left(\int_{\mathbb{R}^{2d}} |\rho(w) - \vartheta(w)| \mathcal{K}(z_0, w) dw \geq \gamma \right) \\ & \leq (\gamma)^{-p} \mathbb{E} \left\{ \left(\int_{\mathbb{R}^{2d}} |\rho(w) - \vartheta(w)| \mathcal{K}(z_0, w) dw \right)^p \right\} \\ & \leq (\gamma)^{-p} C_\varphi^{p-1} \int_{\mathbb{R}^{2d}} \mathbb{E} \{ |\rho(w) - \vartheta(w)|^p \} \mathcal{K}(z_0, w) dw \\ & \leq \left(\frac{C_\varphi}{\gamma} \right)^p \int_{\mathbb{R}^{2d}} \int_0^\infty pt^{p-1} \mathbb{P} (|\rho(w) - \vartheta(w)| \geq t) dt \mathcal{K}(z_0, w) dw, \end{aligned}$$

where we used that $C_\varphi \geq \int |K_\varphi(0, w)| dw \geq \int |V_\varphi \varphi(w)|^2 dw = 1$. Let us further estimate the integral with respect to t . We invoke Lemma 5.1 and use that the respective constant is $C_1 \leq 1$ to estimate

$$\begin{aligned} & \int_0^\infty pt^{p-1} \mathbb{P} (|\rho(w) - \vartheta(w)| \geq t) dt \\ & \lesssim \int_0^\infty pt^{p-1} \exp \left(-C_1 K \min \left(\frac{t^2}{\vartheta(w)^2}, \frac{t}{\vartheta(w)} \right) \right) dt \\ & = \int_0^{\vartheta(w)} pt^{p-1} \exp \left(-\frac{C_1 K t^2}{\vartheta(w)^2} \right) dt + \int_{\vartheta(w)}^\infty pt^{p-1} \exp \left(-\frac{C_1 K t}{\vartheta(w)} \right) dt \\ & = \frac{p}{2} \left(\frac{\vartheta(w)^2}{C_1 K} \right)^{\frac{p}{2}} \int_0^{C_1 K} t^{\frac{p-2}{2}} e^{-t} dt + p \left(\frac{\vartheta(w)}{C_1 K} \right)^p \int_{C_1 K}^\infty t^{p-1} e^{-t} dt \\ & \leq \vartheta(w) C_1^{-p} \left[\Gamma \left(\frac{p}{2} + 1 \right) K^{-\frac{p}{2}} + \Gamma(p+1) K^{-p} \right]. \end{aligned}$$

Hence we have thus far shown that for every $1 \leq p < \infty$,

$$\begin{aligned} & \mathbb{P} \left(\int_{\mathbb{R}^{2d}} |\rho(w) - \vartheta(w)| \mathcal{K}(z_0, w) dw \geq \gamma \right) \\ & \lesssim \left(\frac{C_\varphi}{C_1 \gamma} \right)^p \left[\frac{\Gamma \left(\frac{p}{2} + 1 \right)}{K^{\frac{p}{2}}} + \frac{\Gamma(p+1)}{K^p} \right] \int_{\mathbb{R}^{2d}} \vartheta(w) \mathcal{K}(z_0, w) dw. \end{aligned}$$

Let us write for short $s = C_\varphi/C_1\gamma > 1$. If $K/s^2 \geq 2$, then we choose $p = 2\lfloor K/2s^2 \rfloor \geq 1$ and

$$\begin{aligned} s^p \left[\frac{\Gamma\left(\frac{p}{2} + 1\right)}{K^{\frac{p}{2}}} + \frac{\Gamma(p+1)}{K^p} \right] &= \left(\frac{s^2}{K}\right)^{\lfloor \frac{K}{2s^2} \rfloor} \left\lfloor \frac{K}{2s^2} \right\rfloor! + \left(\frac{s}{K}\right)^{2\lfloor \frac{K}{2s^2} \rfloor} \left(2 \left\lfloor \frac{K}{2s^2} \right\rfloor\right)! \\ &\leq \left(\frac{1}{2}\right)^{\lfloor \frac{K}{2s^2} \rfloor} \left\lfloor \frac{K}{2s^2} \right\rfloor^{-\lfloor \frac{K}{2s^2} \rfloor} \left\lfloor \frac{K}{2s^2} \right\rfloor! + \left(2 \left\lfloor \frac{K}{2s^2} \right\rfloor\right)^{-2\lfloor \frac{K}{2s^2} \rfloor} \left(2 \left\lfloor \frac{K}{2s^2} \right\rfloor\right)! \\ &\leq 2 \left(\frac{1}{2}\right)^{\lfloor \frac{K}{2s^2} \rfloor}, \end{aligned}$$

where the final inequality follows from

$$(2n)^{-2n} (2n)! = (2n)^{-n} n! \cdot (2n)^{-n} (n+1) \cdot \dots \cdot 2n \leq \left(\frac{1}{2}\right)^n, \quad n \in \mathbb{N}.$$

Since $2 \left(\frac{1}{2}\right)^{\lfloor \frac{K}{2s^2} \rfloor} \lesssim e^{-c(C_1\gamma/2C_\varphi)^2 K} \leq e^{-c(C_1\gamma_0/2C_\varphi)^2 K}$ for a universal constant $c > 0$, we conclude that (5.9) holds.

Finally, if $K/s^2 < 2$, then $\gamma > \gamma_0$ implies that $K < 2C_\varphi^2/\gamma_0^2 C_1^2$. Hence, in that case, setting $p = 1$ yields

$$\mathbb{P} \left(\int_{\mathbb{R}^{2d}} |\rho(w) - \vartheta(w)| \mathcal{K}(z_0, w) dw \geq \gamma \right) \lesssim \frac{C_\varphi}{C_1\gamma_0} \int_{\mathbb{R}^{2d}} \vartheta(w) \mathcal{K}(z_0, w) dw,$$

and (5.9) also holds, possibly after taking a different constants c, C . \square

As an application, we obtain the following.

Lemma 5.5. *Let $\sigma = 1$, $\delta \in [\delta_0, 1]$, $\delta_0 > 0$, and $z_0 \in \mathcal{A}(\delta)$, where*

$$(5.11) \quad \mathcal{A}(\delta) := \left\{ z \in \mathbb{R}^{2d} : \int_{\mathbb{R}^{2d}} \vartheta(w) \mathcal{K}(z, w) dw \leq \frac{\delta}{2\|V_\varphi\varphi\|_1} \right\}.$$

There exist constants $c, C > 0$ only depending on φ and δ_0 such that

$$(5.12) \quad \mathbb{P} \left(\sup_{z \in B_1(z_0)} \rho(z) \geq \delta \right) \leq c \cdot e^{-CK} \cdot \int_{\mathbb{R}^{2d}} \vartheta(z) \mathcal{K}(z_0, z) dz.$$

Proof. From the reproducing formula (4.2), almost surely

$$\begin{aligned} \sup_{z \in B_1(z_0)} \rho(z) &= \sup_{z \in B_R(z_0)} \frac{1}{K} \sum_{k=1}^K \left| \int_{\mathbb{R}^{2d}} V_\varphi H_\Omega \mathcal{N}_k(w) K_\varphi(z, w) dw \right|^2 \\ &\leq \|V_\varphi\varphi\|_1 \sup_{z \in B_1(z_0)} \frac{1}{K} \sum_{k=1}^K \int_{\mathbb{R}^{2d}} |V_g H_\Omega \mathcal{N}_k(w)|^2 |K_\varphi(z, w)| dw \\ (5.13) \quad &\leq \|V_\varphi\varphi\|_1 \int_{\mathbb{R}^{2d}} \rho(w) \mathcal{K}(z_0, w) dw. \end{aligned}$$

Hence,

$$\begin{aligned} \mathbb{P} \left(\sup_{z \in B_R(z_0)} \rho(z) \geq \delta \right) &\leq \mathbb{P} \left(\int_{\mathbb{R}^{2d}} \rho(w) \mathcal{K}(z_0, w) dw \geq \frac{\delta}{\|V_\varphi \varphi\|_1} \right) \\ &= \mathbb{P} \left(\int_{\mathbb{R}^{2d}} (\rho(z) - \vartheta(z)) \mathcal{K}(z_0, z) dz \geq \left(\frac{\delta}{\|V_\varphi \varphi\|_1} - \int_{\mathbb{R}^{2d}} \vartheta(z) \mathcal{K}(z_0, z) dz \right) \right) \\ &\leq \mathbb{P} \left(\int_{\mathbb{R}^{2d}} |\rho(z) - \vartheta(z)| \mathcal{K}(z_0, z) dz \geq \frac{\delta}{2\|V_\varphi \varphi\|_1} \right). \end{aligned}$$

Now the estimate follows from Lemma 5.4. \square

Since we assume that $g, \varphi \in \mathcal{S}(\mathbb{R}^d)$, there exists $m_{g, \varphi} > 0$ such that

$$(5.14) \quad |\langle \varphi, \pi(z)g \rangle| \leq m_{g, \varphi} (1 + |z|)^{-2(d+1)}.$$

If $\varphi = g$, we write m_φ .

Theorem 5.6. *Let $\sigma = 1$, $\delta \in [\delta_0, 1]$, $\delta_0 > 0$, and $\mathcal{A}(\delta)$ as in Lemma 5.5. Then there exist constants $c, C > 0$ depending only on φ and δ_0 such that the probability of an estimation error occurring in $\Omega^c \cap \mathcal{A}(\delta)$ satisfies*

$$(5.15) \quad \mathbb{P} \left(\sup_{z \in \Omega^c \cap \mathcal{A}(\delta)} \rho(z) \geq \delta \right) \leq c \cdot |\Omega| \cdot e^{-CK}.$$

Proof. By the Besicovitch covering theorem [7], there exist points $\{z_k\}_k \subset \mathcal{A}(\delta)$ such that $\mathcal{A}(\delta) \subset \bigcup_k B_1(z_k)$, and

$$(5.16) \quad \sup_{z \in \mathbb{R}^{2d}} \#\{k : z \in B_1(z_k)\} \leq b_d < \infty,$$

where b_d is a universal constant depending only on the dimension d .

Next, we show that $\sup_{w \in \mathbb{R}^{2d}} \sum_k \mathcal{K}(z_k, w)$ is bounded by a constant only depending on φ . To see this, we first note that if $z \in B_1(z_k)$ and $|z_k - w| \geq n - 1$, then $|z - w| \geq n - 2$, and,

$$\bigcup_{n-1 \leq |z_k - w| < n} B_1(z_k) \subset B_{n+1}(w) \setminus B_{n-2}(w).$$

Hence, by (5.16), there are at most $b_d(|B_{n+1}(0)| - |B_{n-2}(0)|)/|B_1(0)|$ such points z_k . Consequently, (5.14) implies

$$\begin{aligned} \sum_k \mathcal{K}(z_k, w) &\leq m_\varphi \sum_{n \in \mathbb{N}} \sum_{n-1 \leq |z_k - w| < n} \sup_{z \in B_1(z_k)} (1 + |z - w|)^{-2(d+1)} \\ &\lesssim m_\varphi b_d \left(1 + \sum_{n \geq 2} (1 + (n - 2))^{-2(d+1)} (|B_{n+1}(0)| - |B_{n-2}(0)|) \right) \\ &\lesssim m_\varphi b_d \left(1 + \sum_{n \geq 2} n^{-2(d+1)} n^{2d} \right) \lesssim m_\varphi < \infty. \end{aligned}$$

Taking the union bound, and applying Lemma 5.5 then shows

$$\begin{aligned}
\mathbb{P}\left(\sup_{z \in \mathcal{A}(\delta) \cap \Omega^c} \rho(z) \geq \delta\right) &\leq \sum_k \mathbb{P}\left(\sup_{z \in B_1(z_k)} \rho(z) \geq \delta\right) \\
&\leq c \cdot e^{-CK} \sum_k \int_{\mathbb{R}^{2d}} \vartheta(z) \mathcal{K}(z_k, z) \, dz \\
&\leq c \cdot e^{-CK} \sup_{w \in \mathbb{R}^{2d}} \sum_k \mathcal{K}(z_k, w) \int_{\mathbb{R}^{2d}} \vartheta(z) \, dz \\
&\lesssim m_\varphi c \cdot e^{-CK} |\Omega|,
\end{aligned}$$

where we used $\|\vartheta\|_1 \leq |\Omega|$ (see Proposition 5.3 (iii)). □

Next we estimate the size of the region $\Omega^c \setminus \mathcal{A}(\delta)$.

Proposition 5.7. *Let $\delta > 0$. Then there exists a constant $c > 0$ only depending on φ such that*

$$(5.17) \quad |\Omega^c \setminus \mathcal{A}(\delta)| \leq c \cdot M(g, \varphi) \cdot \frac{|\partial\Omega|}{\delta},$$

and

$$\int_{\mathbb{R}^{2d}} \vartheta(w) \mathcal{K}(z, w) \, dw \leq c \cdot M(g, \varphi) \cdot \text{dist}(z, \partial\Omega)^{-1}, \quad z \in \Omega^c.$$

Proof. Observe that

$$\mathcal{K}(z, w) \leq m_\varphi \sup_{y \in B_1(z)} (1 + |y - w|)^{-2(d+1)} \lesssim m_\varphi (1 + |z - w|)^{-2(d+1)}.$$

Then we may estimate the following integral

$$\begin{aligned}
\int_{\Omega^c} \int_{\mathbb{R}^{2d}} \vartheta(w) \mathcal{K}(z, w) \, dw \, dz &= \int_{\Omega^c} \int_{\Omega} \vartheta(w) \mathcal{K}(z, w) \, dw \, dz + \int_{\Omega^c} \int_{\Omega^c} \vartheta(w) \mathcal{K}(z, w) \, dw \, dz \\
&\lesssim m_\varphi \int_{\Omega^c} \int_{\Omega} (1 + |z - w|)^{-2(d+1)} \, dw \, dz + \int_{\Omega^c} \vartheta(w) \int_{\Omega^c} \mathcal{K}(z, w) \, dz \, dw \\
&\lesssim m_\varphi \cdot |\partial\Omega| + m_\varphi \cdot M(g, \varphi) \cdot |\partial\Omega|,
\end{aligned}$$

where we applied (3.1) with $\psi(z) = (1 + |z|)^{-2(d+1)}$ and Proposition 5.3 (i) to derive the estimates on the first and second integral respectively. Then (5.17) follows from Chebyshev's inequality.

To show the second property, we set $R = \text{dist}(z, \partial\Omega)^{-1}$ and assume that $z \in \Omega^c$. By Proposition 5.3 (iv) it holds

$$\begin{aligned}
\int_{\mathbb{R}^{2d}} \vartheta(w) \mathcal{K}(z, w) \, dw &= \int_{\Omega + B_{R/2}(0)} \vartheta(w) \mathcal{K}(z, w) \, dw + \int_{(\Omega + B_{R/2}(0))^c} \vartheta(w) \mathcal{K}(z, w) \, dw \\
&\lesssim \int_{\Omega + B_{R/2}(0)} \mathcal{K}(z, w) \, dw + M(g, \varphi)(R/2)^{-1} \int_{(\Omega + B_{R/2}(0))^c} \mathcal{K}(z, w) \, dw \\
&\leq m_\varphi \int_{\Omega + B_{R/2}(0)} (1 + |z - w|)^{-2(d+1)} \, dw + \|\mathcal{K}(z, \cdot)\|_1 M(g, \varphi)(R/2)^{-1} \\
&\leq m_\varphi \int_{B_{R/2}(0)^c} (1 + |w|)^{-2(d+1)} \, dw + \|\mathcal{K}(0, \cdot)\|_1 M(g, \varphi)(R/2)^{-1} \\
&\lesssim (m_\varphi + \|\mathcal{K}(0, \cdot)\|_1 M(g, \varphi)) R^{-1}.
\end{aligned}$$

□

We will now consider estimates for the uniform error probability in Ω . We first bound the probability that an estimation error occurs in a set of the form $\Omega \cap \{|\vartheta - 1| \leq \delta\}$.

Theorem 5.8. *Let $\sigma = 1$ and $\delta \in (0, 1/2]$. There exist a universal constant $C > 0$ and a constant c only depending on φ such that*

$$(5.18) \quad \mathbb{P} \left(\inf_{z \in \Omega \cap \{|\vartheta - 1| \leq \delta/3\}} \rho(z) < \delta \right) \leq c \cdot |\Omega^1| \cdot e^{-CK}.$$

Proof. First, we observe that

$$\begin{aligned}
(5.19) \quad \inf_{z \in B_R(z_0)} \rho(z) &\geq \rho(z_0) - \sup_{z \in B_R(z_0)} |\rho(z_0) - \rho(z)| \\
&\geq \rho(z_0) - \sup_{z \in B_R(z_0)} \frac{1}{K} \sum_{k=1}^K \left| |V_\varphi H_\Omega \mathcal{N}_k(z_0)|^2 - |V_\varphi H_\Omega \mathcal{N}_k(z)|^2 \right|.
\end{aligned}$$

The reproducing formula (4.2) and Cauchy-Schwarz inequality then show that for any $f \in L^2(\mathbb{R})$, $0 < R \leq 1$, and $z \in B_R(z_0)$

$$\begin{aligned}
& \left| |V_\varphi f(z)|^2 - |V_\varphi f(z_0)|^2 \right| = (|V_\varphi f(z)| - |V_\varphi f(z_0)|)(|V_\varphi f(z)| + |V_\varphi f(z_0)|) \\
& = \left| |V_\varphi \pi(-z_0)f(z - z_0)| - |V_\varphi \pi(-z_0)f(0)| \right| (|V_\varphi f(z)| + |V_\varphi f(z_0)|) \\
& \leq \int_{\mathbb{R}^{2d}} |V_\varphi \pi(-z_0)f(w) \langle \pi(z - z_0)\varphi - \varphi, \pi(w)\varphi \rangle| dw \\
& \quad \cdot \int_{\mathbb{R}^{2d}} |V_\varphi f(w)| |K_\varphi(z, w) + K_\varphi(z_0, w)| dw \\
& \leq \int_{\mathbb{R}^{2d}} |V_\varphi \pi(-z_0)f(w) \langle \pi(z - z_0)\varphi - \varphi, \pi(w)\varphi \rangle| dw \cdot 2 \int_{\mathbb{R}^{2d}} |V_\varphi f(w)| \mathcal{K}(z_0, w) dw \\
& \leq 2C_\varphi^{1/2} \left(\int_{\mathbb{R}^{2d}} |V_\varphi \pi(-z_0)f(w)|^2 |\langle \pi(z - z_0)\varphi - \varphi, \pi(w)\varphi \rangle| dw \right)^{\frac{1}{2}} \\
& \quad \cdot \left(\int_{\mathbb{R}^{2d}} |\langle \pi(z - z_0)\varphi - \varphi, \pi(w)\varphi \rangle| dw \right)^{\frac{1}{2}} \cdot \left(\int_{\mathbb{R}^{2d}} |V_\varphi f(w)|^2 \mathcal{K}(z_0, w) dw \right)^{\frac{1}{2}} \\
& \leq 2^{3/2} C_\varphi^{1/2} \int_{\mathbb{R}^{2d}} |V_\varphi f(w)|^2 \mathcal{K}(z_0, w) dw \cdot \left(\int_{\mathbb{R}^{2d}} |\langle \pi(z - z_0)\varphi - \varphi, \pi(w)\varphi \rangle| dw \right)^{\frac{1}{2}} \\
& \leq T_\varphi(R) \int_{\mathbb{R}^{2d}} |V_\varphi f(w)|^2 \mathcal{K}(z_0, w) dw,
\end{aligned}$$

where

$$T_\varphi(R) := 2^{3/2} C_\varphi^{1/2} \sup_{z \in B_R(0)} \left(\int_{\mathbb{R}^{2d}} |\langle \pi(z)\varphi - \varphi, \pi(w)\varphi \rangle| dw \right)^{\frac{1}{2}} \rightarrow 0, \quad \text{as } R \rightarrow 0,$$

because φ is a Schwartz function. Therefore,

$$(5.20) \quad \sup_{z \in B_R(z_0)} |\rho(z_0) - \rho(z)| \leq T_\varphi(R) \int_{\mathbb{R}^{2d}} \rho(w) \mathcal{K}(z_0, w) dw.$$

Let now $z_0 \in \{z \in \mathbb{R}^{2d} : |\vartheta(z) - \chi_\Omega(z)| \leq \delta/3\} \cap \Omega$. Then, combining the assumption $\delta \in (0, 1/2]$ with (5.19) and (5.20) yields

$$\begin{aligned}
\mathbb{P} \left(\inf_{z \in B_R(z_0)} \rho(z) < \delta \right) & \leq \mathbb{P} \left(\rho(z_0) - \vartheta(z_0) < \delta - \vartheta(z_0) + T_\varphi(R) \int_{\mathbb{R}^{2d}} \rho(w) \mathcal{K}(z_0, w) dw \right) \\
& \leq \mathbb{P} \left(\rho(z_0) - \vartheta(z_0) < -\frac{1}{3} + T_\varphi(R) \int_{\mathbb{R}^{2d}} \rho(w) \mathcal{K}(z_0, w) dw \right).
\end{aligned}$$

In the following, we make use of $\mathbb{P}(A) = \mathbb{P}(A \cap B) + \mathbb{P}(A \cap B^c) \leq \mathbb{P}(A \cap B) + \mathbb{P}(B^c)$. Define the events

$$A_{z_0} := \left\{ \rho(z_0) - \vartheta(z_0) < -\frac{1}{3} + T_\varphi(R) \int_{\mathbb{R}^{2d}} \rho(w) \mathcal{K}(z_0, w) dw \right\},$$

and

$$(5.21) \quad B_{z_0} := \left\{ T_\varphi(R) \int_{\mathbb{R}^{2d}} \rho(w) \mathcal{K}(z_0, w) dw < \frac{1}{6} \right\}.$$

Then, we may estimate

$$\mathbb{P}(A_{z_0} \cap B_{z_0}) \leq \mathbb{P} \left(\rho(z_0) - \vartheta(z_0) < -\frac{1}{6} \right) \leq \mathbb{P} \left(|\rho(z_0) - \vartheta(z_0)| > \frac{1}{6} \right) \lesssim e^{-CK},$$

where we used Lemma 5.1 and $\vartheta(z_0) \leq 1$.

Second, choose $R_\varphi \leq 1$ so that

$$(5.22) \quad \frac{1}{6T_\varphi(R_\varphi)} \geq 2C_\varphi,$$

where C_φ is the constant defined in (5.10). Then we estimate $\mathbb{P}(B_{z_0}^c)$ as follows:

$$\begin{aligned} \mathbb{P}(B_{z_0}^c) &= \mathbb{P}\left(\int_{\mathbb{R}^{2d}} \rho(w)\mathcal{K}(z_0, w) dw \geq \frac{1}{6T_\varphi(R_\varphi)}\right) \\ &\leq \mathbb{P}\left(\int_{\mathbb{R}^{2d}} |\rho(w) - \vartheta(w)|\mathcal{K}(z_0, w) dw \geq \frac{1}{6T_\varphi(R_\varphi)} - \int_{\mathbb{R}^{2d}} \vartheta(w)\mathcal{K}(z_0, w) dw\right) \\ &\leq \mathbb{P}\left(\int_{\mathbb{R}^{2d}} |\rho(w) - \vartheta(w)|\mathcal{K}(z_0, w) dw \geq \frac{1}{6T_\varphi(R_\varphi)} - C_\varphi\right) \\ &\leq \mathbb{P}\left(\int_{\mathbb{R}^{2d}} |\rho(w) - \vartheta(w)|\mathcal{K}(z_0, w) dw \geq C_\varphi\right) \\ &\leq \mathbb{P}\left(\int_{\mathbb{R}^{2d}} |\rho(w) - \vartheta(w)|\mathcal{K}(z_0, w) dw \geq 1\right) \\ &\leq c \cdot e^{-CK} \int_{\mathbb{R}^{2d}} \vartheta(w)\mathcal{K}(z_0, w) dw \lesssim m_\varphi \cdot c \cdot e^{-CK}, \end{aligned}$$

where we used Lemma 5.4.

Let us consider a covering of $\Omega \cap \{z \in \mathbb{R}^{2d} : |\vartheta(z) - 1| \leq \delta/3\}$ by balls $B_{R_\varphi}(z_k)$, $z_k \in \Omega \cap \{|\vartheta - 1| \leq \delta/3\}$, with at most b_d overlaps. Then there are at most $|\Omega|^{R_\varphi} b_d / (\pi R_\varphi^2)$ points z_k defining such a covering. A union bound argument then yields

$$\begin{aligned} \mathbb{P}\left(\inf_{z \in \Omega \cap \{|\vartheta-1| < \delta/3\}} \rho(z) \leq \delta\right) &\leq \sum_k \mathbb{P}\left(\inf_{z \in B_{R_\varphi}(z_k)} \rho(z) < \delta\right) \\ &\leq \sum_k P(A_{z_k} \cap B_{z_k}) + P(B_{z_k}^c) \\ &\lesssim c \sum_k m_\varphi e^{-CK} \lesssim c \frac{m_\varphi}{R_\varphi^2} |\Omega|^{R_\varphi} e^{-CK} \leq c \frac{m_\varphi}{R_\varphi^2} |\Omega| e^{-CK}, \end{aligned}$$

as $R_\varphi \leq 1$. □

So far we have considered a generic deterministic cutoff parameter δ . The following result will allow us to replace δ by the random threshold $\|\rho\|_\infty/4$.

Proposition 5.9. *Let $\sigma = 1$, and assume (2.3). Then there exist constants $c, C > 0$ depending only on φ and a constant $r > 0$ depending on g and φ such that*

$$\mathbb{P}(\|\rho\|_\infty \leq 2) \geq 1 - c \cdot |\Omega|^r \cdot e^{-CK}.$$

In addition, if $\delta \in [0, (20\|V_\varphi g\|_1^2)^{-1}]$, and $K \geq 2$, then

$$\mathbb{P}(\|\rho\|_\infty \leq \delta) \leq (20\|V_\varphi g\|_1^2 \delta)^{K/2}.$$

Proof. For the event $\{\|\rho\|_\infty > 2\}$, we argue as in the proof of Theorem 5.8. With the notation of that proof,

$$\begin{aligned} \sup_{z \in B_R(z_0)} \rho(z) &\leq \rho(z_0) + \sup_{z \in B_R(z_0)} |\rho(z_0) - \rho(z)| \\ &\leq \rho(z_0) + T_\varphi(R) \int_{\mathbb{R}^{2d}} \rho(w) \mathcal{K}(z_0, w) dw. \end{aligned}$$

Therefore, since $2 \geq 1 + \vartheta(z_0)$

$$\begin{aligned} \mathbb{P} \left(\sup_{z \in B_R(z_0)} \rho(z) > 2 \right) &\leq \mathbb{P} \left(\rho(z_0) > 1 + \vartheta(z_0) - T_\varphi(R) \int_{\mathbb{R}^{2d}} \rho(w) \mathcal{K}(z_0, w) dw \right) \\ &\leq \mathbb{P}(B_{z_0}^c) + \mathbb{P}(|\rho(z_0) - \vartheta(z_0)| > 5/6), \end{aligned}$$

where B_{z_0} is the event given by (5.21). Proposition 5.7 guarantees the existence of a constant $r = r(g, \varphi) > 0$ such that $(\Omega^c \setminus \mathcal{A}(1)) \cup \Omega \subset \Omega^r$. Therefore,

$$\begin{aligned} \mathbb{P}(\|\rho\|_\infty > 2) &\leq \mathbb{P} \left(\sup_{z \in \Omega^c \cap \mathcal{A}(1)} \rho(z) > 1 \right) + \mathbb{P} \left(\sup_{z \in (\Omega^c \setminus \mathcal{A}(1)) \cup \Omega} \rho(z) > 2 \right) \\ &\leq c|\Omega|e^{-CK} + \mathbb{P} \left(\sup_{z \in \Omega^r} \rho(z) > 2 \right). \end{aligned}$$

by Theorem 5.6. For the second term, we cover Ω^r with balls of radius $R_\varphi \leq 1$ satisfying (5.22) and apply a union bound argument as in the proof of Theorem 5.8 to show

$$\mathbb{P} \left(\sup_{z \in \Omega^r} \rho(z) > 2 \right) \lesssim \sum_k \left(\mathbb{P}(B_{z_k}^c) + \mathbb{P}(|\rho(z_k) - \vartheta(z_k)| > 5/6) \right) \lesssim \frac{m_\varphi}{R_\varphi} |\Omega^{r+1}| e^{-CK}.$$

To show the second property we first observe that, by the reproducing formula (4.2), the averaged spectrogram formed with respect to the model window g is dominated by ρ (which involves the reconstruction window g)

$$\begin{aligned} \sup_{z \in \mathbb{R}^{2d}} \frac{1}{K} \sum_{k=1}^K |V_g H_\Omega \mathcal{N}_k(z)|^2 &= \sup_{z \in \mathbb{R}^{2d}} \frac{1}{K} \sum_{k=1}^K \left| \int_{\mathbb{R}^{2d}} V_\varphi H_\Omega \mathcal{N}_k(w) \langle \pi(w)\varphi, \pi(z)g \rangle dw \right|^2 \\ &\leq \sup_{z \in \mathbb{R}^{2d}} \int_{\mathbb{R}^{2d}} \frac{1}{K} \sum_{k=1}^K |V_\varphi H_\Omega \mathcal{N}_k(w)|^2 |\langle \pi(w)\varphi, \pi(z)g \rangle| dw \int_{\mathbb{R}^{2d}} |\langle \pi(w)\varphi, \pi(z)g \rangle| dw \\ &\leq \sup_{z \in \mathbb{R}^{2d}} \|\rho\|_\infty \left(\int_{\mathbb{R}^{2d}} |\langle \pi(w)\varphi, \pi(z)g \rangle| dw \right)^2 = \|V_\varphi g\|_1^2 \|\rho\|_\infty. \end{aligned}$$

Next, we use the double orthogonality property (4.4) of the eigenfunctions f_m to derive

$$\begin{aligned} \int_\Omega \sum_{k=1}^K |V_g H_\Omega \mathcal{N}_k(z)|^2 dz &= \sum_{k=1}^K \sum_{\ell, m \in \mathbb{N}} \alpha_\ell^k \overline{\alpha_m^k} \lambda_\ell \lambda_m \int_\Omega V_g f_\ell(z) \overline{V_g f_m(z)} dz \\ &= \sum_{k=1}^K \sum_{m \in \mathbb{N}} |\alpha_m^k|^2 \lambda_m^3. \end{aligned}$$

Therefore, there exist $z_0 \in \Omega$ such that

$$\frac{1}{K} \sum_{k=1}^K |V_g H_\Omega \mathcal{N}_k(z_0)|^2 \geq \frac{1}{K|\Omega|} \sum_{k=1}^K \sum_{m \in \mathbb{N}} |\alpha_m^k|^2 \lambda_m^3 \geq \frac{1}{K|\Omega|} \left(\frac{3}{4} \right)^3 \sum_{k=1}^K \sum_{m=1}^{\lfloor |\Omega|/2 \rfloor} |\alpha_m^k|^2,$$

where we used Lemma 4.1 to derive the last inequality. We define $Y = \sum_{k=1}^K \sum_{m=1}^{\lfloor |\Omega|/2 \rfloor} |\alpha_m^k|^2 = \sum_{k=1}^K \sum_{m=1}^{\lfloor |\Omega|/2 \rfloor} (\operatorname{Re}(\alpha_m^k)^2 + \operatorname{Im}(\alpha_m^k)^2)$. Then $2Y \sim \chi^2(2K \lfloor |\Omega|/2 \rfloor)$ and

$$\begin{aligned} \mathbb{P}(\|\rho\|_\infty \leq \delta) &\leq \mathbb{P}\left(\sup_{z \in \mathbb{R}^{2d}} \frac{1}{K} \sum_{k=1}^K |V_g H_\Omega \mathcal{N}_k(z)|^2 \leq \|V_\varphi g\|_1^2 \delta\right) \\ &\leq \mathbb{P}\left(2Y \leq 2 \left(\frac{4}{3}\right)^3 \|V_\varphi g\|_1^2 K \lfloor |\Omega| \rfloor \delta\right) \\ &= \Gamma(K \lfloor |\Omega|/2 \rfloor)^{-1} \gamma\left(K \lfloor |\Omega|/2 \rfloor, \left(\frac{4}{3}\right)^3 \|V_\varphi g\|_1^2 K \lfloor |\Omega| \rfloor \delta\right) \\ &\leq \Gamma(K \lfloor |\Omega|/2 \rfloor)^{-1} \gamma\left(K \lfloor |\Omega|/2 \rfloor, 10 \|V_\varphi g\|_1^2 K \lfloor |\Omega|/2 \rfloor \delta\right), \end{aligned}$$

where $\gamma(a, z)$ denotes the lower incomplete gamma function and we used $|\Omega| \leq 4 \lfloor |\Omega|/2 \rfloor$, by (2.3), as well as $4(4/3)^3 \leq 10$. Subsequently, we will show that

$$(5.23) \quad \gamma(a, ax) \leq (2x)^{a/2} \Gamma(a), \quad x \in [0, 1/2], \quad a \geq 2,$$

which concludes our proof by setting $x = 10 \|V_\varphi g\|_1^2 \delta$ and $a = K \lfloor |\Omega|/2 \rfloor \geq 2$.

To this end, we prove that $h_1(x) := x^{-a/2} \gamma(a, ax)$ is non-decreasing on $(0, 1/2]$; then (5.23) will follow by

$$x^{-a/2} \gamma(a, ax) = h_1(x) \leq h_1(1/2) = 2^{a/2} \gamma\left(a, \frac{a}{2}\right) \leq 2^{a/2} \Gamma(a).$$

The derivative of h_1 is given by

$$h_1'(x) = x^{-a/2-1} \left((ax)^a e^{-ax} - \frac{a}{2} \gamma(a, ax) \right) = x^{-a/2-1} h_2(x).$$

We note that $h_2(0) = 0$, and that

$$h_2'(x) = a(xa)^a e^{-ax} ((2x)^{-1} - 1) \geq 0, \quad x \in (0, 1/2].$$

This implies that $h_2(x) \geq 0$, and consequently $h_1'(x) \geq 0$ whenever $x \in (0, 1/2]$. \square

We can now prove our main results.

5.3. Proof of Theorem 2.1. Let $\sigma = 1$. We apply Theorem 5.8 and Proposition 5.9 to show

$$(5.24) \quad \mathbb{P}\left(\inf_{z \in \Omega \cap \{|\vartheta-1| \leq 1/6\}} \rho(z) < \|\rho\|_\infty / 4\right) \leq \mathbb{P}\left(\inf_{z \in \Omega \cap \{|\vartheta-1| \leq 1/6\}} \rho(z) < 1/2\right) + \mathbb{P}(\|\rho\|_\infty > 2) \\ \leq \frac{1}{2} c |\Omega^r| e^{-CK}.$$

The probability on left hand side of (5.24) is homogeneous with respect to σ . Hence, the same estimate holds for all $\sigma > 0$.

Similarly, for $\sigma = 1$, Theorem 5.6 and Proposition 5.9 yield

$$\begin{aligned} & \mathbb{P} \left(\sup_{z \in \Omega^c \cap \mathcal{A}(1/(100\|V_\varphi g\|_1^2))} \rho(z) \geq \|\rho\|_\infty / 4 \right) \\ & \leq \mathbb{P} \left(\sup_{z \in \Omega^c \cap \mathcal{A}(1/(100\|V_\varphi g\|_1^2))} \rho(z) \geq 1/(100\|V_\varphi g\|_1^2) \right) + \mathbb{P}(\|\rho\|_\infty \leq 1/(25\|V_\varphi g\|_1^2)) \\ & \leq \frac{1}{2} c |\Omega^r| e^{-CK}, \end{aligned}$$

where $r = r(g, \varphi)$. Again by homogeneity, the probability bound holds also for general $\sigma > 0$.

Hence, up to an event of probability at most $c|\Omega^r|e^{-CK}$, the estimation error $\Omega\Delta\widehat{\Omega}$ is contained in the union of the sets

$$(5.25) \quad \Omega \cap \{|\vartheta - 1| > 1/6\}, \\ \Omega^c \setminus \mathcal{A}((100\|V_\varphi g\|_1^2)^{-1}) = \left\{ z \in \Omega^c : \int_{\mathbb{R}^{2d}} \vartheta(w) \mathcal{K}(z, w) dw > \frac{1}{200\|V_\varphi \varphi\|_1 \|V_\varphi g\|_1^2} \right\}.$$

Propositions 5.3 and 5.7 shows that each of these sets is contained in $[\partial\Omega]^{r'}$, for an adequate constant, $r' = r'(g, \varphi)$. This completes the proof. \square

5.4. Proof of Theorem 2.2. With the notation of the proof of Theorem 2.1, with the same success probability, the estimation error $\Omega\Delta\widehat{\Omega}$ is contained in the union of the sets (5.25). In that event, we use Propositions 5.3 and 5.7 to estimate

$$|\Omega\Delta\widehat{\Omega}| \leq |\{\chi_\Omega - \vartheta > 1/6\}| + |\Omega^c \setminus \mathcal{A}(1/(80\|V_\varphi g\|_1^2))| \leq C_1 |\partial\Omega|,$$

with $C_1 = C_1(g, \varphi)$. \square

5.5. Proof of Theorem 2.3. The following is a more precise version of Theorem 2.3.

Theorem 5.10. *Let $g, \varphi \in \mathcal{S}(\mathbb{R}^d)$ with $\|g\|_2 = \|\varphi\|_2 = 1$, $K \geq 7$, and $\Omega \subset \mathbb{R}^{2d}$ compact and satisfying (2.3). Then there exist constants $c_1, c_2, C, r > 0$ depending only on g and φ such that*

$$(5.26) \quad \mathbb{E} \left\{ |\Omega\Delta\widehat{\Omega}| \right\} \leq c_1 \cdot |\partial\Omega| + c_2 \cdot |\Omega^r|^2 \cdot e^{-CK}.$$

Consequently, choosing $K \geq C' \log(|\Omega^r|)$ yields

$$\mathbb{E} \left\{ |\Omega\Delta\widehat{\Omega}| \right\} \leq c_3 \cdot |\partial\Omega|,$$

with c_3 depending only on g and φ .

Proof. Let us assume that $\sigma = 1$. The general case then follows again by homogeneity. We define the family of events $E_0 = \{4 \leq \|\rho\|_\infty < \infty\}$, and $E_n = \{a_n \leq \|\rho\|_\infty < b_n\}$, with $a_n = (20\|V_\varphi g\|_1^2 n)^{-1}$, $b_n = (20\|V_\varphi g\|_1^2 (n-1))^{-1}$ for $n \geq 2$, and $a_1 = 1/(20\|V_\varphi g\|_1^2)$, $b_1 = 4$.

Note that $\bigcup_{n \geq 0} E_n = \{\|\rho\|_\infty \in (0, \infty)\}$ and the complementary event has zero probability. Hence,

$$(5.27) \quad \begin{aligned} \mathbb{E}\{|\Omega \Delta \widehat{\Omega}|\} &= \mathbb{E}\left\{\|\chi_\Omega - \chi_{S_{\|\rho\|_\infty/4}}\|_1\right\} = \int_{\mathbb{R}^{2d}} \mathbb{E}\left\{|\chi_\Omega(z) - \chi_{S_{\|\rho\|_\infty/4}}(z)|\right\} dz \\ &= \sum_{n \in \mathbb{N}_0} \int_{\mathbb{R}^{2d}} \mathbb{P}\left(\{\chi_\Omega(z) \neq \chi_{S_{\|\rho\|_\infty/4}}(z)\} \cap E_n\right) dz. \end{aligned}$$

For $n \geq 1$, we first observe that

$$(5.28) \quad \mathbb{P}\left(\{\chi_\Omega(z) \neq \chi_{S_{\|\rho\|_\infty/4}}(z)\} \cap E_n\right) \leq \begin{cases} \mathbb{P}\left(\chi_\Omega(z) \neq \chi_{S_{b_{n/4}}}(z)\right), & \text{if } z \in \Omega \\ \mathbb{P}\left(\chi_\Omega(z) \neq \chi_{S_{a_{n/4}}}(z)\right), & \text{if } z \in \Omega^c \end{cases}.$$

Using Propositions 5.3 and 5.9 we can estimate for $n \geq 3$ and $K \geq 7$

$$(5.29) \quad \begin{aligned} &\int_{\mathbb{R}^{2d}} \mathbb{P}\left(\{\chi_\Omega(z) \neq \chi_{S_{\|\rho\|_\infty/4}}(z)\} \cap E_n\right) dz \\ &\leq \int_{\Omega \cup \{\vartheta - \chi_\Omega > a_n^2\}} \mathbb{P}(E_n) dz + \int_{\Omega^c \cap \{\vartheta - \chi_\Omega \leq a_n^2\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{a_{n/4}}}(z)) dz \\ &\lesssim (n-1)^{-K/2} (|\Omega| + n^2 \|V_\varphi g\|_1^4 M(g, \varphi) |\partial\Omega|) + \int_{\Omega^c \cap \{\vartheta \leq a_n^2\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{a_{n/4}}}(z)) dz \\ &\lesssim \left(\frac{1}{2}\right)^{K/4} n^{-7/4} |\Omega| + n^{-3/2} |\partial\Omega| + \int_{\Omega^c \cap \{\vartheta \leq a_n^2\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{a_{n/4}}}(z)) dz. \end{aligned}$$

If $\vartheta(z) \leq \delta^2$, then $\exp(-CK/\delta) \geq \exp(-CK/\sqrt{\vartheta(z)}) \geq \exp(-CK\delta/\vartheta(z))$. Therefore, Theorem 5.2 allows us to further estimate the integral above for a general parameter $\delta > 0$ as follows

$$\begin{aligned} \int_{\Omega^c \cap \{\vartheta \leq \delta^2\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{\delta/4}}(z)) dz &\lesssim \int_{\Omega^c \cap \{\vartheta \leq \delta^2\}} e^{-C\frac{K\delta}{\vartheta(z)}} dz \\ &= \int_0^\infty \left| \left\{ z \in \{\vartheta \leq \delta^2\} : \exp\left(-C\frac{K\delta}{\vartheta(z)}\right) \geq t \right\} \right| dt \\ &\leq \int_0^\infty \left| \left\{ z \in \{\vartheta \leq \delta^2\} : \exp\left(-C\frac{K}{\sqrt{\vartheta(z)}}\right) \geq t \right\} \right| dt \\ &\leq \int_0^{e^{-CK/\delta}} \left| \left\{ z \in \{\vartheta \leq \delta^2\} : \sqrt{\vartheta(z)} \geq \frac{CK}{\log(1/t)} \right\} \right| dt \\ &\lesssim \int_0^{e^{-CK/\delta}} \frac{\log(1/t)}{K} \int_{\mathbb{R}^{2d}} \sqrt{\vartheta(z)} dz dt \\ &= \frac{\|\sqrt{\vartheta}\|_1}{K} (-x \log x + x) \Big|_0^{e^{-CK/\delta}} \lesssim \|\sqrt{\vartheta}\|_1 e^{-CK/\delta}. \end{aligned}$$

In order to estimate $\|\sqrt{\vartheta}\|_1$ we first note that the integral kernel of H_Ω can be written in two ways if we either use its eigenexpansion or (4.3)

$$k_{H_\Omega}(s, t) = \sum_{m \in \mathbb{N}} \lambda_m \overline{f_m(t)} f_m(s) = \int_\Omega \overline{\pi(w)g(t)} \pi(w)g(s) dw.$$

Integrating against $\pi(z)\varphi(t)$ and $\overline{\pi(z)\varphi(s)}$ thus yields

$$\vartheta(z) \leq \sum_{m \in \mathbb{N}} \lambda_m |V_\varphi f_m(z)|^2 = \int_{\Omega} |\langle \pi(z)\varphi, \pi(w)g \rangle|^2 dw.$$

To estimate $\|\sqrt{\vartheta}\|_1$, let $Q_k = k + [-\frac{1}{2}, \frac{1}{2}]^{2d}$, $k \in \mathbb{Z}^{2d}$, and $I_\Omega = \{k \in \mathbb{Z}^{2d} : |Q_k \cap \Omega| > 0\}$. Using (5.14) shows

$$\begin{aligned} \|\sqrt{\vartheta}\|_1 &\leq \int_{\mathbb{R}^{2d}} \left(\int_{\Omega} |\langle \pi(z)\varphi, \pi(w)g \rangle|^2 dw \right)^{1/2} dz \\ &\leq \sum_{k \in \mathbb{Z}^{2d}} \int_{\mathbb{R}^{2d}} \left(\int_{\Omega \cap Q_k} |\langle \pi(z)\varphi, \pi(w)g \rangle|^2 dw \right)^{1/2} dz \\ &\leq \sum_{k \in I_\Omega} |\Omega \cap Q_k|^{1/2} \int_{\mathbb{R}^{2d}} \sup_{w \in Q_k} |\langle \pi(z-w)\varphi, g \rangle| dz \\ &\leq m_{g,\varphi} \sum_{k \in I_\Omega} \int_{\mathbb{R}^{2d}} \sup_{w \in Q_0} (1 + |z-w|^2)^{-(d+1)} dz \\ (5.30) \quad &\lesssim |I_\Omega| \leq |\Omega|^{d^{1/2}}, \end{aligned}$$

where we used that $Q_k \subset \Omega^{d^{1/2}}$ for every $k \in I_k$.

In the case $n = 0$, we use Propositions 5.3 (iii) and 5.9 and argue similarly as in the inequalities leading up to (5.29)

$$\begin{aligned} &\int_{\mathbb{R}^{2d}} \mathbb{P}(\{\chi_\Omega(z) \neq \chi_{S_{\|\rho\|_\infty/4}}(z)\} \cap E_0) dz \\ &\lesssim \int_{\Omega \cup \{|\vartheta - \chi_\Omega| > \frac{1}{4}\}} \mathbb{P}(E_0) dz + \int_{\Omega^c \cap \{|\vartheta - \chi_\Omega| \leq \frac{1}{4}\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{\|\rho\|_\infty/4}}(z)) dz \\ &\lesssim c'(|\Omega| + |\partial\Omega|) \cdot |\Omega^r| e^{-CK} + \int_{\Omega^c \cap \{|\vartheta - \chi_\Omega| \leq \frac{1}{4}\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_1}(z)) dz \\ (5.31) \quad &\leq c''|\Omega^r|^2 e^{-CK} + \int_{\Omega^c \cap \{|\vartheta - \chi_\Omega| \leq \frac{1}{4}\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_1}(z)) dz. \end{aligned}$$

For $n = 1, 2$, we finally get from Propositions 5.3 (iii), (5.28), and Theorem 5.2

$$\begin{aligned} &\int_{\mathbb{R}^{2d}} \mathbb{P}(\{\chi_\Omega(z) \neq \chi_{S_{\|\rho\|_\infty/4}}(z)\} \cap E_n) dz \\ &\leq \int_{(\Omega^c \cap \{\vartheta > \frac{a_n}{16}\}) \cup (\Omega \cap \{1 - \vartheta > \frac{b_n}{16}\})} 1 dz + \int_{\Omega \cap \{1 - \vartheta \leq \frac{b_n}{16}\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{\|\rho\|_\infty/4}}(z)) dz \\ &\quad + \int_{\Omega^c \cap \{\vartheta \leq \frac{a_n}{16}\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{\|\rho\|_\infty/4}}(z)) dz \\ &\lesssim |\partial\Omega| + \int_{\Omega \cap \{|\vartheta - 1| \leq \frac{b_n}{16}\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{b_n/4}}(z)) dz \\ &\quad + \int_{\Omega^c \cap \{\vartheta \leq \frac{a_n}{16}\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{a_n/4}}(z)) dz \\ (5.32) \quad &\lesssim |\partial\Omega| + |\Omega| e^{-CK} + \int_{\Omega^c \cap \{\vartheta \leq \frac{a_n}{16}\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_{a_n/4}}(z)) dz. \end{aligned}$$

In order to bound the integrals in (5.31) and (5.32) we argue as before and use Theorem 5.2, and Proposition 5.3 (iii) to show that

$$\begin{aligned} \int_{\Omega^c \cap \{|\vartheta - \chi_\Omega| \leq \delta/4\}} \mathbb{P}(\chi_\Omega(z) \neq \chi_{S_\delta}(z)) \, dz &\lesssim \int_{\{|\vartheta - \chi_\Omega| < \delta/4\}} e^{-C \frac{K\delta}{\vartheta(z)}} \, dz \\ &\leq \int_0^{e^{-CK\delta}} \left| \left\{ z \in \mathbb{R}^{2d} : \vartheta(z) \geq \frac{CK\delta}{\log(1/t)} \right\} \right| \, dt \\ &\lesssim \|\vartheta\|_1 \int_0^{e^{-CK\delta}} \frac{\log(1/t)}{K\delta} \, dt \lesssim |\Omega| \delta^{-1} e^{-CK\delta}, \end{aligned}$$

and choose $\delta \in \{1, a_1, a_2\}$. Combining this estimate with (5.27) and Proposition 5.9 finally yields

$$\begin{aligned} \mathbb{E} \left\{ \|\chi_\Omega - \chi_{S_{\|\rho\|_\infty/4}}\|_1 \right\} &\lesssim \sum_{n=3}^{\infty} \left(e^{-CK} n^{-7/4} |\Omega| + n^{-3/2} |\partial\Omega| + |\Omega^r| e^{-CKn} \right) \\ &\quad + |\partial\Omega| + |\Omega| e^{-CK} + |\Omega^r|^2 e^{-CK} \\ &\leq c_1 |\partial\Omega| + c_2 |\Omega^r|^2 e^{-C'K}. \end{aligned}$$

□

REFERENCES

- [1] L. D. Abreu, K. Gröchenig, and J. L. Romero. On accumulated spectrograms. *Trans. Amer. Math. Soc.*, 368:3629–3649, 2016.
- [2] L. D. Abreu, J. M. Pereira, and J. L. Romero. Sharp rates of convergence for accumulated spectrograms. *Inverse Problems*, 33(11):115008, 2017.
- [3] R. Adamczak. A note on the Hanson-Wright inequality for random vectors with dependencies. *Electron. Commun. Probab.*, 2015.
- [4] R. Bardenet and A. Hardy. Time-frequency transforms of white noises and Gaussian analytic functions. *Appl. Comput. Harmon. Anal.*, 50:73–104, 2021.
- [5] F. Bastianoni, E. Cordero, and F. Nicola. Decay and smoothness for eigenfunctions of localization operators. *J. Math. Anal. Appl.*, 492:124480, 2020.
- [6] Á. Bényi and K. A. Okoudjou. *Modulation Spaces: With Applications to Pseudodifferential Operators and Nonlinear Schrödinger Equations*. Applied and Numerical Harmonic Analysis. Birkhäuser Basel, 2020.
- [7] A. S. Besicovitch. A general form of the covering principle and relative differentiation of additive functions. *Proc. Cambridge Philos. Soc.*, 41:103–110, 1945.
- [8] L. Cohen. Time-frequency spatial-spatial frequency representations. In *Nonlinear signal and image analysis (Gainesville, FL, 1995)*, volume 808 of *Ann. New York Acad. Sci.*, pages 97–115. New York Acad. Sci., New York, 1997.
- [9] L. Cohen. The history of noise [on the 100th anniversary of its birth]. *IEEE Signal Processing Magazine*, 22(6):20–45, 2005.
- [10] L. Cohen. Time-frequency analysis: what we know and what we don't. In *Landscapes of time-frequency analysis—ATFA 2019*, *Appl. Numer. Harmon. Anal.*, pages 75–101. Birkhäuser/Springer, Cham, 2020.
- [11] E. Cordero and K. Gröchenig. Time-frequency analysis of localization operators. *J. Funct. Anal.*, 205(1):107–131, 2003.
- [12] E. Cordero and L. Rodino. *Time-frequency analysis of operators*, volume 75 of *De Gruyter Studies in Mathematics*. De Gruyter, Berlin, [2020] ©2020.
- [13] I. Daubechies. Time-frequency localization operators: a geometric phase space approach. *IEEE Trans. Inform. Theory*, 34(4):605–612, 1988.
- [14] M. Dörfler and J. L. Romero. Frames adapted to a phase-space cover. *Constr. Approx.*, 39(3):445–484, 2014.

- [15] L. C. Evans and R. F. Gariepy. *Measure Theory and Fine Properties of Functions*. Studies in Advanced Mathematics. CRC Press, Boca Raton, FL, 1992.
- [16] G. B. Folland. *Harmonic analysis in phase space*, volume 122 of *Annals of Mathematics Studies*. Princeton University Press, Princeton, NJ, 1989.
- [17] S. Ghosh, M. Lin, and D. Sun. Signal analysis via the stochastic geometry of spectrogram level sets. *IEEE Trans. Signal Proc.*, 70:1104–1117, 2022.
- [18] K. Gröchenig. *Foundations of Time-Frequency Analysis*. Appl. Numer. Harmon. Anal. Birkhäuser Boston, 2001.
- [19] A. Haimi, G. Koliander, and J. L. Romero. Zeros of Gaussian Weyl-Heisenberg Functions and Hyperuniformity of Charge. *J. Stat. Phys.*, 187(3):Paper No. 22, 2022.
- [20] N. Halko, P. G. Martinsson, and J. A. Tropp. Finding structure with randomness: probabilistic algorithms for constructing approximate matrix decompositions. *SIAM Rev.*, 53(2):217–288, 2011.
- [21] O. Hazrati, J. Lee, and P. C. Loizou. Blind binary masking for reverberation suppression in cochlear implants. *J. Acoust. Soc. Amer.*, 133(3):1607–1614, 2013.
- [22] T. Hida. *Brownian Motion*. Applications of Mathematics. Springer, 1st edition, 1980.
- [23] F. Hlawatsch and G. Matz. *Wireless Communications over Rapidly Time-Varying Channels*. Academic Press, 2011.
- [24] J. A. Hogan and J. D. Lakey. *Duration and bandwidth limiting*. Applied and Numerical Harmonic Analysis. Birkhäuser/Springer, New York, 2012. Prolate functions, sampling, and applications.
- [25] W. Kozek and G. E. Pfander. Identification of operators with bandlimited symbols. *SIAM J. Math. Anal.*, 37(3):867–888, 2005.
- [26] F. Marceca and J. L. Romero. Spectral deviation of concentration operators for the short-time Fourier transform. *arXiv:2104.06150*, 2021.
- [27] A. Papandreou-Suppappola. *Applications in time-frequency signal processing*. CRC press, 2018.
- [28] G. E. Pfander and D. F. Walnut. Sampling and reconstruction of operators. *IEEE Trans. Inform. Theory*, 62(1):435–458, 2016.
- [29] M. Rudelson and R. Vershynin. Hanson-Wright inequality and sub-Gaussian concentration. *Electron. Comm. Probab.*, 18(82):1–19, 2013.
- [30] D. Wang. On ideal binary mask as the computational goal of auditory scene analysis. In *Speech separation by humans and machines*, pages 181–197. Springer, 2005.
- [31] D. Wang and G. J. Brown. *Computational auditory scene analysis: Principles, algorithms, and applications*. Wiley-IEEE press, 2006.

FACULTY OF MATHEMATICS, UNIVERSITY OF VIENNA, OSKAR-MORGENSTERN-PLATZ 1, A-1090 VIENNA, AUSTRIA, AND ACOUSTICS RESEARCH INSTITUTE, AUSTRIAN ACADEMY OF SCIENCES, WOHLLEBENGASSE 12-14, VIENNA, 1040, AUSTRIA

Email address: jose.luis.romero@univie.ac.at

FACULTY OF MATHEMATICS, UNIVERSITY OF VIENNA, OSKAR-MORGENSTERN-PLATZ 1, A-1090 VIENNA, AUSTRIA

Email address: michael.speckbacher@univie.ac.at