

PARAMETER REGION FOR MULTISTATIONARITY IN n -SITE PHOSPHORYLATION NETWORKS


ELISENDA FELIU¹, NIDHI KAIHNSA², TIMO DE WOLFF³, OĞUZHAN YÜRÜK⁴

ABSTRACT. This work addresses the problem of understanding the parameter region where a family of networks relevant in cell signalling admits at least two steady states, a property termed multistationarity. The problem is phrased in the context of real algebraic geometry and reduced to studying whether a polynomial, defined as the determinant of a parametric matrix of size three, attains negative values over the positive orthant. The networks are indexed by a natural number n , and for all n , we give sufficient conditions for the polynomial to be positive and hence, preclude multistationarity. We also provide sufficient conditions for the polynomial to attain negative values and hence, enable multistationarity. These conditions are derived by exploiting the structure of the polynomial, its Newton polytope, and employing circuit polynomials. We also prove that the parameter regions that enable or preclude multistationarity are connected for all n .

1. Introduction

Given a dynamical system, the notion of *multistationarity* implies the existence of multiple steady states or equilibrium points. Often in biological processes, multistationarity has been associated with and found relevant for cellular decision making processes [24, 27, 36]. This has led to an extensive interest in developing methods to identify whether parametric models arising from reaction networks admit multistationarity, and to determine and understand the parameter region where this occurs, e.g. [1, 7, 8, 10, 11, 13–16, 26, 29, 35].

In this work, we focus on understanding the rate parameters that allow or restrict the multistationarity in a phosphorylation and dephosphorylation cycle for a substrate with n phosphorylation sites. This particular reaction network constitutes a crucial part of biological systems relevant for cell signalling. For two sites, that is, for $n = 2$, the dual phosphorylation cycle is



In this system, S , E , and F denote substrate, kinase, and phosphatase, respectively. Kinase and phosphatase catalyze the phosphorylation and dephosphorylation of the substrate. The subscripts 0, 1, and 2 of the phosphoforms S_0 , S_1 , and S_2 denote the number of phosphorylated sites of the substrate S .

Over the years, under the assumption of mass-action kinetics, the process of dual phosphorylation has been studied rigorously by means of polynomial ordinary differential equations (ODEs) [1, 6, 9, 16]. Besides its relevance in biology, this network has become testing grounds

¹Department of Mathematical Sciences, University of Copenhagen. efeliu@math.ku.dk

²Division of Applied Mathematics, Brown University. nidhi_kaihnsa@brown.edu

³Institute of Analysis and Algebra, TU Braunschweig. t.de-wolff@tu-braunschweig.de


⁴Chair of Discrete Mathematics/Geometry, Technische Universität Berlin. yuruk@math-tu.berlin.de

2010 *Mathematics Subject Classification.* 92Bxx, 14Pxx, 37N25, 52B20, 90C26.

Key words and phrases. Phosphorylation network, Multistationarity, Parameter Estimation, Chemical reaction network, Real algebraic geometry, Circuit polynomial, Connectedness.

for developing various mathematical methods focused towards understanding multistationarity and dynamics of reaction networks in general. In [16], the authors studied the region of reaction rate constants (the κ 's in (1)) that yield multistationarity, giving a description of the boundary between the region of parameters that enable multistationarity and the region of parameters that preclude multistationarity. Moreover, it was shown that both regions are path connected.

In this article we explore the general n -phosphorylation network, *i.e.*, the substrate has n sites available for phosphorylation, and the network takes the following form:



The main question we address is for which reaction rate constants κ_i , $i \in \{1, \dots, 6n\}$, the n -phosphorylation network can have multiple steady states, that is, there exist total amounts of kinase, phosphatase and substrate for which the system has at least two positive steady states. In [1] the authors answer a related question and provide sufficient conditions for multistationarity involving a subset of the reaction rate constants and the total amounts.

Addressing this question for a fixed n requires challenging computations, since the number of parameters and variables become very large as n increases. However, for any n , the differential equation system associated with the network admits exactly three linear first integrals and the set of steady states admits a nice parametrization. These key facts allow us to reduce the study of multistationarity to studying whether a polynomial in three variables attains negative values over the positive orthant (Proposition 3.3). This question can in turn be addressed by exploring the Newton polytope associated with the polynomial (Theorem 3.5), and in the end, the multistationarity problem can be reduced to studying the signs a bivariate polynomial attains (Corollary 3.9).

Imposing that at least one of the coefficients corresponding to vertices of the Newton polytope is negative, we obtain sufficient conditions for multistationarity (Theorem 4.1). However, these are not necessary as Theorem 4.3 shows: multistationarity can arise when the conditions in Theorem 4.1 are not satisfied and only points in the interior of the Newton polytope have negative coefficients.

To preclude multistationarity, we note that a polynomial can be nonnegative even if some points in the interior of its Newton polytope have negative coefficients. We use SONC (sums of nonnegative circuit) polynomials as a symbolic nonnegativity certificate in order to describe a non-empty region in the parameter space that ensures the monostationarity of the system (Theorem 5.3).

Besides generating various verifiable conditions on parameters for the n -phosphorylation network that enable or preclude multistationarity, we also present topological characteristics of the respective regions in Section 6. We show in Theorem 6.2 and Corollary 6.4 that both the mono- and multistationarity regions in the parameter space are path connected for all n .

The structure of the paper is as follows: In Section 2, we describe the basic setup and the dynamics of the system in detail, and give a brief introduction to circuit polynomials. In Section 3 we compute the polynomial whose sign determines if the system can have multiple steady states. Moreover, we write a general expression of this polynomial for all n and describe the corresponding Newton polytope. We provide sufficient conditions for multistationarity in Section 4 by studying this Newton polytope. Section 5 focuses on giving sufficient conditions

for monostationarity by employing SONC polynomials. Section 6 studies the topology of the mono- and multistationarity regions.

2. Preliminaries

2.1. The parametric system. We consider the reaction network (2) and describe the ODE system that governs evolution of the concentration of the species in time [1, 17, 34]. We then lay the groundwork to derive a polynomial for this system whose positivity will determine the monostationarity of network (2). The concentrations of the species in the network are denoted as follows:

$$\begin{aligned} e &= [E], & f &= [F], & s_i &= [S_i] & \text{for } i = 0, \dots, n, \\ u_i &= [FS_{i+1}], & y_i &= [ES_i] & \text{for } i = 0, \dots, n-1. \end{aligned}$$

Under the assumption of mass-action kinetics, the ODE system in $\mathbb{R}_{\geq 0}^{3n+3}$ is as follows:

$$(3) \quad \begin{aligned} \frac{de}{dt} &= - \sum_{i=0}^{n-1} \kappa_{6i+1} s_i e + \sum_{i=0}^{n-1} \kappa_{6i+1} (\kappa_{6i+2} + \kappa_{6i+3}) y_i, \\ \frac{df}{dt} &= - \sum_{i=0}^{n-1} \kappa_{6i+4} s_{i+1} f + \sum_{i=0}^{n-1} (\kappa_{6i+5} + \kappa_{6i+6}) u_i, \\ \frac{ds_i}{dt} &= \kappa_{6i-3} y_{i-1} - \kappa_{6i+1} s_i e + \kappa_{6i+2} y_i + \kappa_{6i+6} u_i - \kappa_{6i-2} s_i f + \kappa_{6i-1} u_{i-1}, & \text{for } i = 0, \dots, n, \\ \frac{dy_i}{dt} &= \kappa_{6i+1} s_i e - (\kappa_{6i+2} + \kappa_{6i+3}) y_i, & \text{for } i = 0, \dots, n-1, \\ \frac{du_i}{dt} &= \kappa_{6i+4} s_{i+1} f - (\kappa_{6i+5} + \kappa_{6i+6}) u_i, & \text{for } i = 0, \dots, n-1, \end{aligned}$$

with the convention that $\kappa_j = 0$ if $j > 6n$ or $j < 0$ (this becomes relevant only for $\frac{ds_0}{dt}$ and $\frac{ds_n}{dt}$). This system of ODEs admits three linear first integrals, such that the trajectories are confined in the following level sets for some $E_{\text{tot}}, F_{\text{tot}}, S_{\text{tot}} \geq 0$:

$$(4) \quad e + \sum_{i=0}^{n-1} y_i = E_{\text{tot}}, \quad f + \sum_{i=0}^{n-1} u_i = F_{\text{tot}}, \quad s_0 + \sum_{i=1}^n s_i + \sum_{i=0}^{n-1} y_i + \sum_{i=0}^{n-1} u_i = S_{\text{tot}}.$$

Each of these equations is called a *conservation law* and $E_{\text{tot}}, F_{\text{tot}}$ and S_{tot} are the *total amounts*, which are taken nonnegative. The intersection of a level set with the nonnegative orthant is called a *stoichiometric compatibility class*. In particular, the ODE system has $3n + 3$ variables and for a given initial condition, the trajectory lies in a $3n$ dimensional subspace determined by the three linear constraints in (4).

The steady states of the system are found by setting the left-hand side of (3) to zero. Using the notation in [1], we consider the inverses of Michaelis-Menten constants of the (de)phosphorylation events

$$(5) \quad K_i = \frac{\kappa_{6i+1}}{\kappa_{6i+2} + \kappa_{6i+3}}, \quad L_i = \frac{\kappa_{6i+4}}{\kappa_{6i+5} + \kappa_{6i+6}}, \quad i = 0, \dots, n-1,$$

and define

$$(6) \quad T_i = \prod_{j=0}^i \frac{\kappa_{6j+3} K_j}{\kappa_{6j+6} L_j} = T_{i-1} \frac{\kappa_{6i+3} K_i}{\kappa_{6i+6} L_i}, \quad i = 0, \dots, n-1, \quad T_{-1} = 1.$$

For later use, we define the following composition of surjective maps $\eta: \mathbb{R}_{>0}^{6n} \rightarrow \mathbb{R}_{>0}^{4n} \rightarrow \mathbb{R}_{>0}^{3n}$

$$(7) \quad \kappa \mapsto (\kappa_3, \kappa_6, \dots, \kappa_{6n}, K_0, \dots, K_{n-1}, L_0, \dots, L_{n-1}) \mapsto (T_0, \dots, T_{n-1}, K_0, \dots, K_{n-1}, L_0, \dots, L_{n-1}).$$

As a consequence of the three conservation laws, the equations corresponding to e, f , and s_0 are redundant as they are linearly dependent on the rest. The steady state equations for s_{i+1}, y_i, u_i with $i = 0, \dots, n-1$ are linear in these variables, and have a unique solution, which is positive provided e, f, s_0 are positive:

$$s_{i+1} = T_i e^{i+1} f^{-(i+1)} s_0 \quad y_i = K_i T_{i-1} e^{i+1} f^{-i} s_0 \quad u_i = L_i T_i e^{i+1} f^{-i} s_0.$$

This gives rise to a parametrization of the set of positive steady states in the variables e, f, s_0 ,

$$(8) \quad \varphi_\kappa: \mathbb{R}_{>0}^3 \rightarrow \mathbb{R}_{>0}^{3n+3},$$

that is, the image of φ_κ is precisely the set of positive steady states. For later use, we consider the polynomial function $\tilde{\psi}_\kappa$ given by the right-hand side of (3) in the same order and construct the polynomial function

$$(9) \quad \psi_\kappa: \mathbb{R}^{3n+3} \rightarrow \mathbb{R}^{3n+3}$$

by replacing the first three entries of $\tilde{\psi}_\kappa$ by the left-hand side of (4). Hence, the last $3n$ entries of ψ_κ correspond to the right-hand side of $\frac{ds_i}{dt}$, $\frac{dy_i}{dt}$, and $\frac{du_i}{dt}$ in (3).

In a fixed stoichiometric compatibility class with positive total amounts, this system has finitely many positive steady states for any choice of reaction rate constants κ , specifically between 1 and $2n - 1$ [34]. It is conjectured that there exist parameter values for which the system has $2n - 1$ positive steady states, but this has only been established for $n \leq 4$ [19]. For general n , it has been proven that there exist parameter values for which the system admits $n + 1$ (n even) or n (n odd) positive steady states with half plus one of them asymptotically stable [17, 34].

For a given vector of reaction rate constants κ , if there exist positive E_{tot}, F_{tot} , and S_{tot} such that some stoichiometric compatibility class has at least two positive steady states, then we say that κ enables multistationarity. If this is not the case, then κ is said to preclude multistationarity. For $n = 2$, the set of reaction rate constants that enable multistationarity was explored in detail in [16], building on preliminary results by Conradi and Mincheva [9]. In this work we go beyond the case $n = 2$ and determine subsets of reaction rate constants that enable or preclude multistationarity for general n , that is, for the network (2).

2.2. Nonnegative Circuit Polynomials. Let f be a polynomial function on \mathbb{R}^m . Determining if $f(x)$ is nonnegative over \mathbb{R}^m is a classical problem in real algebraic geometry. It has been studied since the 19th century and is the subject of Hilbert's 17th problem [21]. In this article, to certify nonnegativity of a polynomial we use sums of nonnegative circuit polynomials introduced by Ilman and de Wolff in [22]. For a multivariate polynomial $f(x) = \sum_\alpha c_\alpha x_1^{\alpha_1} \cdots x_m^{\alpha_m}$ with $\alpha = (\alpha_1, \dots, \alpha_m) \in \mathbb{Z}^m$, the *Newton polytope*, denoted by $N(f)$, is the convex hull of the exponent vectors of the monomials with non-zero coefficients, i.e. $N(f) := \text{conv}(\{\alpha \in \mathbb{Z}^m : c_\alpha \neq 0\})$. Often we will also use $\text{coeff}(f, \alpha)$ to denote the *coefficient of x^α in the polynomial $f(x)$* . We next define circuit polynomials.

Definition 2.1. A polynomial $f \in \mathbb{R}[x_1, \dots, x_m]$ is called a *circuit polynomial* if

$$f(x) = c_\beta x^\beta + \sum_{j=0}^r c_{\alpha(j)} x^{\alpha(j)},$$

where $\beta, \alpha(j) \in \mathbb{N}^m$, $c_{\alpha(j)} \in \mathbb{R}_{>0}$ for $j = 0, \dots, r$, $c_\beta \in \mathbb{R}$, and $N(f)$ is a simplex with vertices $\alpha(0), \dots, \alpha(r)$ such that the exponent β is in the strict interior of $N(f)$. That is, $\beta = \sum_{j=0}^r \lambda_j \alpha(j)$ with $\lambda_j > 0$ and $\sum_{j=0}^r \lambda_j = 1$. We define the *circuit number* as

$$\Theta_f := \prod_{j=0}^r \left(\frac{c_{\alpha(j)}}{\lambda_j} \right)^{\lambda_j}.$$

Note that the circuit number Θ_f can be computed by solving a system of linear equations. In this article, we will consider circuit polynomials restricted to the nonnegative orthant, as the variables will be concentrations and reaction rate constants. We are interested in polynomials that take nonnegative (resp. positive) values over the positive orthant, which we call respectively *nonnegative* (resp. *positive*) polynomials. Thus, as opposed to the original definition of circuit polynomials given in [22] where the focus was on nonnegativity over the whole real space, we do not restrict $\alpha(j)$ in Definition 2.1 to have even entries. We can do this because in the positive orthant, we can redefine the polynomial by replacing every variable with its square. Interested readers are referred to [22, Section 3] for a detailed discussion. For further details about SONCs in general see e.g., [12, 20, 22, 23].

In [22, Theorem 3.8], the authors gave conditions using circuit number for nonnegativity of circuit polynomials on \mathbb{R}^m . Let f be a circuit polynomial as defined in Definition 2.1. Then, the theorem below is a direct specialization of Theorem 3.8 in [22].

Theorem 2.2 ([22], Theorem 3.8). *With the notation in Definition 2.1, a circuit polynomial f is nonnegative on $\mathbb{R}_{\geq 0}^m$ if and only if $c_\beta \geq -\Theta_f$.*

The *Motzkin polynomial*, $x^4y^2 + x^2y^4 - 3x^2y^2 + 1$, is a classical example of a nonnegative polynomial which is not a sum of squares [25]. This is a circuit polynomial with $\beta = (2, 2)$, and $\lambda_j = 1/3$ for all j (see e.g., [22]). The circuit number is 3 and hence, the polynomial is nonnegative by Theorem 2.2.

Remark 2.3. Let f be a polynomial whose support contains only a single exponent that is not a vertex of $N(f)$, and let the coefficients of f at the vertices of $N(f)$ be positive. Then f is nonnegative if and only if it is SONC, see [33, Theorem 3.10], also [3, Theorem 11]. Such polynomials are examples of *AGE (Arithmetic-Geometric Exponential) functions* as defined in [4], and they yield an equivalent description of SONC polynomials.

3. A polynomial for multistationarity and the Newton polytope

We follow the approach in [16] and study the space of reaction rate constants that enable multistationarity after first reducing the problem to understanding the positivity of a multivariate polynomial for given reaction rates. This section is devoted to computing the general expression of the polynomial and exploring the structure of the associated Newton polytope to determine whether it is positive on the positive orthant. To this end, we apply Theorem 1 in [6], and obtain the following proposition. Here J_{ψ_κ} denotes the Jacobian matrix of the polynomial function defined in (9) in $3n + 3$ variables.

Proposition 3.1. *Let $\kappa \in \mathbb{R}_{> 0}^{6n}$, ψ_κ be the polynomial function in (9) and φ_κ the parametrization of the set of positive steady states from (8). Define the following rational function*

$$q_\kappa(e, f, s_0) := (-1)^{3n} \det J_{\psi_\kappa}(\varphi_\kappa(e, f, s_0)).$$

The following holds:

- (i) *If $q_\kappa(e, f, s_0) > 0$ for all $(e, f, s_0) \in \mathbb{R}_{> 0}^3$, then κ precludes multistationarity.*
- (ii) *If $q_\kappa(e^*, f^*, s_0^*) < 0$ for some $(e^*, f^*, s_0^*) \in \mathbb{R}_{> 0}^3$, then κ enables multistationarity. In this case the stoichiometric compatibility class containing $\varphi_\kappa(e^*, f^*, s_0^*)$ contains at least two positive steady states.*

Proof. The statement is exactly the conclusion of Theorem 1 in [6], as the dimension of the stoichiometric compatibility classes is $3n$. So we need to check that the two hypotheses to apply Theorem 1 in [6] hold. First, the reaction network (1) is dissipative, as it is conservative (each concentration appears in at least one conservation law that has all coefficients nonnegative). Second, we have to verify that there are no boundary steady states (steady states with some entry equal to zero) when total amounts are positive. This follows from Theorem 25 in [28], as (1) is a MESSI system that satisfies the hypotheses of the theorem. \square

Based on Proposition 3.1, a strategy to determine the set of reaction rate constants that enable multistationarity consists of studying the signs q_κ attains on the positive orthant. To compute q_κ , for all n , the first step is to reduce the computation of the determinant of a matrix of size $3n + 3$, to that of the determinant of a 3×3 matrix. Let Φ be the linear map given by the left-hand side of (4). Then the composition $\Phi \circ \varphi_\kappa$ is a function from $\mathbb{R}_{> 0}^3$ to $\mathbb{R}_{> 0}^3$.

Proposition 3.2. *For any $\kappa \in \mathbb{R}_{> 0}^{6n}$ and $(e, f, s_0) \in \mathbb{R}_{> 0}^3$, the sign of $q_\kappa(e, f, s_0)$ agrees with the sign of*

$$\det J_{\Phi \circ \varphi_\kappa}(e, f, s_0).$$

Proof. By the chain rule, it holds

$$(10) \quad J_{\psi_\kappa \circ \varphi_\kappa}(e, f, s_0) = J_{\psi_\kappa}(\varphi_\kappa(e, f, s_0)) \cdot J_{\varphi_\kappa}(e, f, s_0).$$

We write $J_{\psi_\kappa}(\varphi_\kappa(e, f, s_0))$ in block form as

$$J_{\psi_\kappa}(\varphi_\kappa(e, f, s_0)) = \begin{pmatrix} A' & A'' \\ B' & B'' \end{pmatrix}, \quad A' \in \mathbb{R}^{3 \times 3}, \quad B'' \in \mathbb{R}^{3n \times 3n}.$$

The first three components of $\psi_\kappa \circ \varphi_\kappa$ agree with $\Phi \circ \varphi_\kappa$ by construction, and the last $3n$ components are identically zero, as φ_κ is precisely found by solving the system given after setting the last $3n$ entries of ψ_κ to zero. Since φ_κ is the identity in the first three entries, for some $D \in \mathbb{R}^{3n \times 3}$ we write (10) in block form and obtain the consequent relations:


$$\begin{pmatrix} J_{\Phi \circ \varphi_\kappa}(e, f, s_0) \\ 0 \end{pmatrix} = \begin{pmatrix} A' & A'' \\ B' & B'' \end{pmatrix} \begin{pmatrix} Id_{3 \times 3} \\ D \end{pmatrix}$$

$$J_{\Phi \circ \varphi_\kappa}(e, f, s_0) = A' + A''D, \quad B' + B''D = 0.$$

By adding to the first three columns of $J_{\psi_\kappa}(\varphi_\kappa(e, f, s_0))$ linear combinations of the remaining $3n$ columns with coefficients given by the three columns of D respectively, we obtain

$$\begin{aligned} \det J_{\psi_\kappa}(\varphi_\kappa(e, f, s_0)) &= \det \begin{pmatrix} A' & A'' \\ B' & B'' \end{pmatrix} = \det \begin{pmatrix} A' + A''D & A'' \\ B' + B''D & B'' \end{pmatrix} = \det \begin{pmatrix} J_{\Phi \circ \varphi_\kappa}(e, f, s_0) & A'' \\ 0 & B'' \end{pmatrix} \\ &= \det J_{\Phi \circ \varphi_\kappa}(e, f, s_0) \cdot \det B''. \end{aligned}$$

All that remains is to show that the sign of $\det B''$ is $(-1)^{3n}$. The matrix B'' is the Jacobian of the last $3n$ rows of ψ_κ in the variables s_i, y_i, u_i . Note that it is precisely the coefficient matrix of the linear system that is solved to find φ_κ . To find the determinant, we use the theory developed in [18, 31], see also [32], where this determinant is found using the Matrix-Tree theorem on a suitable digraph. Consider the following digraph:



Consider the directed spanning trees rooted at the vertex $*$ (that is, such that $*$ is the only vertex without outgoing edges), and for each such tree, define its label as the product of the labels of its edges. By [31, Proposition 1], the determinant of B'' is $(-1)^{3n}$ times the sum of the labels of all spanning trees rooted at $*$. As there is at least one such tree, and all labels are positive, this gives that the sign of $\det B''$ is $(-1)^{3n}$. This concludes the proof. \square

In view of Proposition 3.1 and 3.2, multistationarity is established by considering the sign of the determinant of the Jacobian of $\Phi \circ \varphi_\kappa$. The entries of $\Phi \circ \varphi_\kappa$ are

$$\begin{aligned} e + \sum_{i=0}^{n-1} K_i T_{i-1} e^{i+1} f^{-i} s_0, \\ f + \sum_{i=0}^{n-1} L_i T_i e^{i+1} f^{-i} s_0, \\ s_0 + \sum_{i=1}^n T_{i-1} e^i f^{-i} s_0 + \sum_{i=0}^{n-1} (K_i T_{i-1} + L_i T_i) e^{i+1} f^{-i} s_0. \end{aligned}$$

Hence, $\Phi \circ \varphi_\kappa$ depends on κ through the assembled parameters K_i, L_i, T_i . As we are only interested in the determinant of the Jacobian of $\Phi \circ \varphi_\kappa$, we subtract the first and second equations from the third, and

in this way the last equation is replaced by

$$-e - f + s_0 + \sum_{i=0}^{n-1} T_i e^{i+1} f^{-(i+1)} s_0.$$

For convenience, the parameters and variables are relabeled in the following way:

$$(11) \quad \begin{aligned} a_i &= K_i T_{i-1}, & b_i &= L_i T_i, & c_i &= T_i, & \text{for } i = 0, \dots, n-1, \\ x_1 &= e, & x_2 &= \frac{e}{f}, & x_3 &= s_0. \end{aligned}$$

With this notation, an easy computation now gives that the determinant of the Jacobian of $\Phi \circ \varphi_\kappa$ is the determinant of the following matrix:

$$(12) \quad J := \begin{bmatrix} 1 + \sum_{i=0}^{n-1} (i+1) a_i x_2^i x_3 & -\sum_{i=0}^{n-1} i a_i x_2^{i+1} x_3 & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) b_i x_2^i x_3 & 1 - \sum_{i=0}^{n-1} i b_i x_2^{i+1} x_3 & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ -1 + \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+1} x_3 & -1 - \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+2} x_3 & 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix}.$$

The determinant of (12) is a polynomial in x_1, x_2, x_3 with coefficients depending on a_i, b_i, c_i , which in turn depend on $T_i, K_i, L_i, i = 0, \dots, n-1$. We, therefore, view $\det J$ as a polynomial in x_1, x_2, x_3 with coefficients depending on a parameter vector in $\mathbb{R}_{>0}^{3n}$, and define:

$$(13) \quad p_\eta(x_1, x_2, x_3) := \det J, \quad \eta = (T_0, \dots, T_{n-1}, K_0, \dots, K_{n-1}, L_0, \dots, L_{n-1}) \in \mathbb{R}_{>0}^{3n}.$$

The discussion above together with Propositions 3.1 and 3.2, shows that whether or not κ enables multistationarity depends only on the entries of the vector $\eta(\kappa)$ and yield the following proposition.

Proposition 3.3. *Let $\kappa \in \mathbb{R}_{>0}^{6n}$, consider $\eta(\kappa) \in \mathbb{R}_{>0}^{3n}$ using (7), and the polynomial $p_{\eta(\kappa)}(x_1, x_2, x_3)$ in (13). It holds:*

- (i) *If $p_{\eta(\kappa)}(x_1, x_2, x_3) > 0$ for all $(x_1, x_2, x_3) \in \mathbb{R}_{>0}^3$, then κ precludes multistationarity.*
- (ii) *If $p_{\eta(\kappa)}(x_1^*, x_2^*, x_3^*) < 0$ for some $(x_1^*, x_2^*, x_3^*) \in \mathbb{R}_{>0}^3$, then κ enables multistationarity. In this case the stoichiometric compatibility class containing $\varphi_\kappa(x_1^*, \frac{x_1^*}{x_2^*}, x_3^*)$ contains at least two positive steady states.*

In Appendix A we explicitly compute p_η as the determinant of the matrix J in (12). We now explore the structure of the polynomial $p_\eta(x_1, x_2, x_3)$ using techniques from real algebraic geometry, in particular, via studying its Newton polytope. The polynomial is quadratic in x_3 and can be written as:

$$(14) \quad p_\eta(x_1, x_2, x_3) = A_2(x_2)x_3^2 + (A_{10}(x_2) + A_{11}(x_2)x_1)x_3 + (A_{00}(x_2) + A_{01}(x_2)x_1),$$

with

$$\begin{aligned} A_2(x_2) &= \left(1 + \sum_{i=0}^{n-1} c_i x_2^{i+1}\right) \left(\sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i b_j x_2^{\ell+1}\right), \\ A_{11}(x_2) &= (1 + x_2) \left(\sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i b_j x_2^\ell\right), \\ A_{10}(x_2) &= \sum_{\ell=0}^{n-1} (\ell+1) a_\ell x_2^\ell - \sum_{\ell=0}^{n-1} \ell b_\ell x_2^{\ell+1} + \sum_{\ell=0}^{2n-2} \sum_{i+j=\ell} (j+1-i) b_i c_j x_2^{\ell+2} + \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i c_j x_2^{\ell+1}, \\ A_{01}(x_2) &= \sum_{i=0}^{n-1} (a_i + b_i) x_2^i, \quad \text{and} \quad A_{00}(x_2) = 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1}. \end{aligned}$$

Lemma 3.4. *For the polynomial p_η written as in (14), the polynomials $A_{01}(x_2)$ and $A_{00}(x_2)$ have only positive coefficients, while $A_2(x_2), A_{10}(x_2)$, and $A_{11}(x_2)$ have both positive and negative coefficients.*

Moreover, $A_2(x_2)$ is nonnegative if and only if $A_{11}(x_2)$ is nonnegative.

Proof. The first part follows easily from inspection of the coefficients of the polynomials. The second statement is immediate as both A_2 and A_{11} are positive multiples of $\sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (j-i) a_j b_i x_2^\ell$. \square

Note that

$$(15) \quad \sum_{i+j=\ell} (i-j) a_i b_j x_2^{\ell+1} = \sum_{\substack{i>j \\ i+j=\ell}} (i-j)(a_i b_j - a_j b_i) x_2^{\ell+1}.$$

Furthermore, recalling the definition of a_i, b_i , and c_i in (11), and of T_i in (6), we obtain that

$$(16) \quad \begin{aligned} a_i b_j - a_j b_i &= K_i T_{i-1} L_j T_j - K_j T_{j-1} L_i T_i = T_{i-1} T_{j-1} \left(K_i L_j \frac{\kappa_{6j+3} K_i}{\kappa_{6j+6} L_j} - K_j L_i \frac{\kappa_{6i+3} K_j}{\kappa_{6i+6} L_i} \right) \\ &= T_{i-1} T_{j-1} K_i K_j \left(\frac{\kappa_{6j+3}}{\kappa_{6j+6}} - \frac{\kappa_{6i+3}}{\kappa_{6i+6}} \right). \end{aligned}$$

Therefore, the signs of $a_i b_j - a_j b_i$ depend on the minors of the following matrix:

$$(17) \quad M_\kappa = \begin{bmatrix} \kappa_3 & \kappa_9 & \dots & \kappa_{6n-3} \\ \kappa_6 & \kappa_{12} & \dots & \kappa_{6n} \end{bmatrix}.$$

Newton Polytope of $p_\eta(x_1, x_2, x_3)$. To analyze the possible signs that $p_\eta(x_1, x_2, x_3)$ attains over the positive orthant, we begin by exploring the properties of its Newton polytope. The rest of this section focuses on the shape and structure of $N(p_\eta)$. We start by noting that p_η is linear in x_1 , and hence can be expressed as

$$p_\eta(x_1, x_2, x_3) = P_0(x_2, x_3) + x_1 P_1(x_2, x_3)$$

with

$$(18) \quad P_0(x_2, x_3) = A_2(x_2)x_3^2 + A_{10}(x_2)x_3 + A_{00}(x_2) \quad \text{and} \quad P_1(x_2, x_3) = A_{11}(x_2)x_3 + A_{01}(x_2).$$

Therefore, the two hyperplanes $H_0 := \{x \in \mathbb{R}^3 : x_1 = 0\}$ and $H_1 := \{x \in \mathbb{R}^3 : x_1 = 1\}$ contain all exponent vectors, and further

$$(19) \quad N(p_\eta) \cap H_0 = \{0\} \times N(P_0), \quad N(p_\eta) \cap H_1 = \{1\} \times N(P_1).$$

Theorem 3.5. *Let $n \geq 1$, and $\eta \in \mathbb{R}_{>0}^{3n}$ such that $a_1 b_0 - a_0 b_1 \neq 0$ and $a_{n-1} b_{n-2} - a_{n-2} b_{n-1} \neq 0$. Then the set of vertices of the Newton polytope $N(p_\eta)$ of p_η in (14) consists of the following 10 points:*

$$\left\{ (0, 0, 0), (0, n, 0), (0, 0, 1), (0, 2n, 1), (0, 2, 2), (0, 3n-2, 2), (1, 0, 0), (1, n-1, 0), (1, 1, 1), (1, 2n-2, 1) \right\}.$$

Furthermore, $N(P_0) = N(p_\eta) \cap H_0$ is a hexagon with set of vertices

$$\{(0, 0), (n, 0), (0, 1), (2n, 1), (2, 2), (3n-2, 2)\}.$$

Proof. The hypothesis implies that the polynomials $A_2, A_{11}, A_{10}, A_{01}, A_{00}$ in x_2 have degree $3n-2, 2n-2, 2n, n-1, n$ respectively, and lowest exponent $1, 1, 0, 0, 0$ respectively.

Considering that the vertices of $N(p_\eta)$ are contained in the union of hyperplanes $H_0 \cup H_1$, the set of vertices of $N(p_\eta)$ is the union of the set of vertices of $N(p_\eta) \cap H_0$ and of $N(p_\eta) \cap H_1$. By (19), it is enough to find the vertices of $N(P_0)$ and $N(P_1)$, which are planar polytopes.

As P_0 is quadratic in x_3 , see (18), the vertices of $N(P_0)$ are on the lines $L_i := \{(x_2, x_3) \in \mathbb{R}^2 : x_3 = i\}$, for $i = 0, 1, 2$. The polytopes $N(P_0) \cap L_i$ for $i = 0, 1, 2$ correspond to the Newton polytopes of the univariate polynomials A_{00}, A_{10} , and A_2 respectively. Their vertices are simply the highest and lowest exponents of these polynomials. Therefore, the set of vertices of $N(P_0)$ is contained in $S_1 = \{(0, 0), (n, 0), (0, 1), (2n, 1), (2, 2), (3n-2, 2)\}$. To show that this is exactly the set of vertices of $N(P_0)$, it is enough to verify that $(0, 1), (2n, 1)$ do not lie in the convex hull of the 4 remaining points. This is easily checked by considering the relative position of $(0, 1)$ with respect to the line joining $(0, 0)$ and $(2, 2)$, and similarly, that of $(2n, 1)$ with respect to the line joining $(n, 0)$ and $(3n-2, 2)$. The Newton polytope $N(P_0)$ is therefore the hexagon with vertex set S_1 .

For $N(P_1)$, we note that P_1 in (18) is linear in x_3 . Hence, as above, we consider first the vertices of $N(P_1) \cap \{(x_2, x_3) \in \mathbb{R}^2 : x_3 = i\}$ for $i = 0, 1$, which are $0, n-1$ and $1, 2n-2$ respectively. It follows that the set of vertices of $N(P_1)$ is $S_2 = \{(0, 0), (n-1, 0), (1, 1), (2n-2, 1)\}$. By (19), we conclude that the set of vertices of $N(p_\eta)$ is as given in the statement. \square

Remark 3.6. In the original parameter vector $\kappa \in \mathbb{R}_{>0}^{6n}$, the condition in Theorem 3.5 corresponds by (16) to $\kappa_3 \kappa_{12} - \kappa_6 \kappa_9 \neq 0$ and $\kappa_{6n-9} \kappa_{6n} - \kappa_{6n-3} \kappa_{6n-6} \neq 0$.

Given a polynomial $P \in \mathbb{R}[x_1, \dots, x_m]$, and a proper face F of $N(P)$, we let P_F denote the *restriction* of P to F , that is, P_F is the sum of the terms $c_\alpha x_1^{\alpha_1} \cdots x_m^{\alpha_m}$ of P satisfying $(\alpha_1, \dots, \alpha_m) \in F$. In what follows we will use the following well-known result that gives a connection between the signs P attains over $\mathbb{R}_{>0}^m$, and the signs P_F attains.

Proposition 3.7. *Let F be a proper face of the Newton polytope $N(P)$ of a polynomial $P \in \mathbb{R}[x_1, \dots, x_m]$ and let P_F be the restriction of P to F . Then for any $x \in \mathbb{R}_{>0}^m$ such that $P_F(x) \neq 0$, there exists $y \in \mathbb{R}_{>0}^m$ such that*

$$\text{sign}(P(y)) = \text{sign}(P_F(x)).$$

In particular, for $t > 0$ large enough and $\omega \in \mathbb{R}^m$ in the open outer normal cone of F , $y = (x_1 t^{\omega_1}, \dots, x_m t^{\omega_m})$ generates the desired point.

A proof of this proposition can be found in [16]. Recall that the open outer normal cone of F consists of the vectors ω such that $\omega \cdot x^T > \omega \cdot y^T$ for every $x \in F$ and $y \in N(P) \setminus F$ where x^T, y^T denotes the transpose. We can easily deduce that if the coefficient of the monomial supported at one of the vertices is negative, then there exists some $x \in \mathbb{R}_{>0}^m$ such that the polynomial is negative.

Theorem 3.8. *Fix $\eta \in \mathbb{R}_{>0}^{3n}$.*

- (i) *The polynomial p_η attains a negative value over $\mathbb{R}_{>0}^3$ if and only if P_0 attains negative values over $\mathbb{R}_{>0}^2$.*
- (ii) *Moreover, p_η is either positive over the positive orthant or p_η attains negative values over $\mathbb{R}_{>0}^3$. In other words, p_η has a zero in $\mathbb{R}_{>0}^3$ if and only if it takes negative values.*

Proof. The two statements in the theorem follow from these two implications:

$$\begin{aligned} p_\eta(x_1, x_2, x_3) \leq 0 \text{ for some } (x_1, x_2, x_3) \in \mathbb{R}_{>0}^3 &\implies P_0(x_2, x_3) < 0 \text{ for some } (x_2, x_3) \in \mathbb{R}_{>0}^2 \\ &\implies p_\eta(x_1, x_2, x_3) < 0 \text{ for some } (x_1, x_2, x_3) \in \mathbb{R}_{>0}^3. \end{aligned}$$

To show the second implication, note that $N(p_\eta) \cap H_0$ and $N(p_\eta) \cap H_1$ are two facets of $N(p_\eta)$, and p_η restricted to these facets is respectively P_0 and $x_1 P_1$. Therefore, if $P_0(x_2, x_3) < 0$ for some $(x_2, x_3) \in \mathbb{R}_{>0}^2$, then Proposition 3.7 readily gives that p_η also attains negative values.

For the first implication, $p_\eta(x_1, x_2, x_3) \leq 0$ implies that $P_0(x_2, x_3)$ or $P_1(x_2, x_3)$ are negative. If $P_1(x_2, x_3) < 0$, then by Lemma 3.4 necessarily $A_{11}(x_2) < 0$ and hence, by the same lemma, we also have $A_2(x_2) < 0$. As $A_2(x_2)$ is the leading coefficient of P_0 , there exists $x_3^* > 0$ such that $P_0(x_2, x_3^*) < 0$. This concludes the proof of the theorem. \square

As the signs p_η attain are completely determined by the signs of P_0 over $\mathbb{R}_{>0}^2$ by Theorem 3.8, we rewrite P_0 as P_η , to indicate dependence on the parameter vector $\eta \in \mathbb{R}_{>0}^{3n}$:

$$(20) \quad P_\eta(x_2, x_3) = A_2(x_2)x_3^2 + A_{10}(x_2)x_3 + A_{00}(x_2).$$

Theorem 3.8 tells us that the silent scenario in Proposition 3.3, namely when p_η is nonnegative over $\mathbb{R}_{>0}^3$, cannot occur. This gives the following characterization of multistationarity of the n -phosphorylation cycle.

Corollary 3.9. *Let $\kappa \in \mathbb{R}_{>0}^{6n}$, consider $\eta(\kappa) \in \mathbb{R}_{>0}^{3n}$ from (7), and $P_{\eta(\kappa)}(x_2, x_3)$ as in (20). Then κ enables multistationarity if and only if $P_{\eta(\kappa)}(x_2^*, x_3^*) < 0$ for some $(x_2^*, x_3^*) \in \mathbb{R}_{>0}^2$.*

4. Sufficient conditions for multistationarity

In this section we start by providing conditions on the parameters to ensure multistationarity using Corollary 3.9. Then, we describe subsets of the parameter space that preclude multistationarity. First, we make the observation that if the polynomial $A_2(x_2)$ in (14) is negative, then P_η in (20) attains negative values. This follows immediately from P_η being quadratic in x_3 with $A_2(x_2)$ as the leading coefficient. Recall that the sign of the coefficients of $A_2(x_2)$ are determined by (15).

Theorem 4.1. *If $\kappa \in \mathbb{R}_{>0}^{6n}$ is such that*

$$\kappa_3 \kappa_{12} - \kappa_6 \kappa_9 < 0 \quad \text{or} \quad \kappa_{6n-9} \kappa_{6n} - \kappa_{6n-3} \kappa_{6n-6} < 0,$$

then $P_{\eta(\kappa)}$ attains negative values, and hence κ enables multistationarity.

Proof. By Theorem 3.5, the set of vertices of $N(P_{\eta(\kappa)})$ is $\{(0, 0), (n, 0), (0, 1), (2n, 1), (2, 2), (3n - 2, 2)\}$, see Remark 3.6. The coefficient of the lowest degree term of $A_2(x_2)$ (i.e. $x_2^2 x_3^2$) is a positive multiple of $a_1 b_0 - b_0 a_1$ by (15), and of $\kappa_3 \kappa_{12} - \kappa_6 \kappa_9$ by (16). Similarly, the coefficient of the highest degree term of $A_2(x_2)$ (i.e. $x_2^{3n-2} x_3^2$) is a positive multiple of $\kappa_{6n-9} \kappa_{6n} - \kappa_{6n-3} \kappa_{6n-6}$. If one of these coefficients is negative, then $P_{\eta(\kappa)}$ attains negative values by Proposition 3.7, and therefore, by Corollary 3.9, κ enables multistationarity. Note that the other coefficients of $P_{\eta(\kappa)}$ corresponding to vertices of $N(P_{\eta(\kappa)})$ are strictly positive. \square

The expressions in Theorem 4.1 correspond to the first and last maximal minors of the matrix M_κ in (17).

Proposition 4.2. *Let $\kappa \in \mathbb{R}_{>0}^{6n}$ be such that the matrix M_κ in (17) has rank one. Then κ precludes multistationarity if and only if the polynomial $A_{10}(x_2)$ is positive or $A_{10}(y^2)$ is a sum of squares.*

Proof. By hypothesis, all maximal minors of M_κ vanish, and therefore, A_2 is identically zero by (15) and (16). It follows that $P_{\eta(\kappa)}(x_2, x_3) = A_{10}(x_2)x_3 + A_{00}(x_2)$. As A_{00} has only positive coefficients, $P_{\eta(\kappa)}(x_2, x_3)$ attains negative values if and only if $A_{10}(x_2)$ does. The statement now follows from the fact that $P_{\eta(\kappa)}(x_2, x_3)$ cannot be nonnegative. Finally, if a univariate polynomial is positive, then it is a sum of squares. \square

In the next result we show that network (2) can be multistationary even if all the minors of the matrix M_κ are positive.

Theorem 4.3. *Let $\kappa \in \mathbb{R}_{>0}^{6n}$ be such that all the minors of M_κ are positive. Then, by choosing $K_0 = \frac{\kappa_1}{\kappa_2 + \kappa_3}$ small enough by varying κ_1 and/or κ_2 and leaving the rest of the entries of κ fixed, we obtain a parameter vector that enables multistationarity.*

Proof. Fix the value of the assembled parameters $K_1, \dots, K_{n-1}, L_0, \dots, L_{n-1}$ corresponding to κ , and construct $T_0(K_0), \dots, T_{n-1}(K_0)$ as in (6) but with K_0 treated as a parameter. For the one parameter family of vectors $\xi(K_0) = (T_0(K_0), \dots, T_{n-1}(K_0), K_0, \dots, K_{n-1}, L_0, \dots, L_{n-1}) \in \mathbb{R}_{>0}^{3n}$, the polynomial $P_{\xi(K_0)}(x_2, x_3)$ becomes a polynomial in K_0, x_2 , and x_3 , which we denote as $Q(K_0, x_2, x_3)$. We prove the theorem by studying the Newton polytope of $Q(K_0, x_2, x_3)$.

Note that K_0 is a factor with exponent 1 in each of a_i, b_i , and c_i . Consider the exponents of K_0 and x_2 in the polynomials A_{00}, A_{10} , and A_2 in (14). Close inspection of each of these show that $N(Q)$ is contained in the convex hull of the following set of points:

$$S := \{(0, 0, 0), (1, 1, 0), \dots, (1, n, 0), (1, 0, 1), \dots, (1, n, 1), (2, 2, 1), \dots, (2, 2n, 1), \\ (2, 2, 2), \dots, (2, 2n - 2, 2), (3, 3, 2), \dots, (3, 3n - 2, 2)\}.$$

Note that some points could appear with zero coefficient for certain parameter values.

Consider the point $(1, n, 1) \in S$. The term of Q with monomial $K_0 x_2^n x_3$ is $-(n-1) b_{n-1} x_2^n x_3$. Hence, the coefficient is negative and $(1, n, 1) \in N(Q)$. With $\omega = (-2(n+1), 2, 4) \in \mathbb{R}^3$ and $\gamma = -1$, it holds

$$\omega \cdot (1, n, 1)^T + \gamma > 0, \quad \omega \cdot q^T + \gamma < 0 \text{ for all } q \in S \setminus \{(1, n, 1)\}.$$

Therefore, the hyperplane $\omega \cdot x^T + \gamma = 0$ separates $(1, n, 1)$ and $\text{conv}(S \setminus \{(1, n, 1)\})$. It follows that $(1, n, 1) \notin \text{conv}(S \setminus \{(1, n, 1)\})$, showing that $(1, n, 1)$ is a vertex of $N(Q)$.

By Proposition 3.7, Q attains negative values after appropriately choosing $K_0, x_2, x_3 > 0$. As ω belongs to the outer normal cone of $(1, n, 1)$ by construction, the point $(t^{-2(n+1)}, t^2, t^4)$ makes Q negative for t large enough. This amounts to letting K_0 be small enough, and as κ_3 was fixed in the definition of $T_i(K_0)$, this must be achieved by varying κ_1 and/or κ_2 . This concludes the proof. \square

Remark 4.4. Theorem 4.3 implies that the conditions in Theorem 4.1 are not necessary for multistationarity. It gives, additionally, a way to construct parameters that enable multistationarity, while satisfying the condition that the negative coefficients of $N(P_{\eta(\kappa)})$ correspond to points in the interior of $N(P_{\eta(\kappa)})$.

Although we have shown the existence of values of K_0 for multistationarity when the rest of the parameters are fixed, the theorem remains true when all parameters but L_{n-1} are fixed. This is shown by considering $P_{\eta(\kappa)}$ as a polynomial in the variables L_{n-1}, x_2 and x_3 . Then, the point $(0, n, 1)$ is a vertex of the corresponding polytope and the proof follows similar arguments as the proof of Theorem 4.3.

5. Sufficient Conditions for Monostationarity

In this section we present a systematic way to construct a sufficient condition for monostationarity for all n . To this end, we describe a region R in the parameter space such that for any $\kappa \in \mathbb{R}_{>0}^{6n}$ the polynomial $P_{\eta(\kappa)}$ in (20) is positive. The approach is a generalization of the methods that are used in [16] for $n = 2$, and in [37] for $n = 3$.

For the particular method we use in this section, it is crucial that the coefficients of the terms that correspond to the vertices of $N(P_{\eta(\kappa)})$ have positive sign. If this is not the case, then Theorem 4.1 implies that multistationarity is enabled. Therefore, throughout this section we only consider parameters $\kappa \in \mathbb{R}_{>0}^{6n}$ where

$$(21) \quad \kappa_3\kappa_{12} - \kappa_6\kappa_9 > 0 \quad \text{and} \quad \kappa_{6n-9}\kappa_{6n} - \kappa_{6n-3}\kappa_{6n-6} > 0.$$

For the cases $n = 2$ and $n = 3$, the conditions in (21) are sufficient for all minors of the matrix M_κ in (17) to be positive.

Remark 5.1. For $n = 2$, assuming that the minors of the matrix M_κ are all positive, then $P_{\eta(\kappa)}$ has only one term that can have negative coefficient. The exponent that corresponds to this particular term is contained in the interior of $N(P_{\eta(\kappa)})$. Therefore, as discussed in Remark 2.3, $P_{\eta(\kappa)}$ is nonnegative if and only if it is a SONC polynomial.

We note that if all minors of the matrix M_κ are positive, then the polynomial $A_2(x_2)$ is positive over $\mathbb{R}_{>0}$ and only $A_{10}(x_2)$ contributes to negative terms to $P_{\eta(\kappa)}$. For $n > 3$, the conditions in (21) are not enough to guarantee that all minors of M_κ are positive. In Proposition 5.2, we give a sufficient condition that ensures that all minors of M_κ are positive.

Proposition 5.2. *Assume that for a given $\kappa \in \mathbb{R}_{>0}^{6n}$, it holds that $a_{i+1}b_i - a_i b_{i+1} > 0$ (resp. ≥ 0) for all $i \in \{0, \dots, n-1\}$. Then, all 2 by 2 minors of M_κ are positive (resp. nonnegative).*

Proof. We need to show that $\kappa_{6i+3}\kappa_{6j+6} - \kappa_{6i+6}\kappa_{6j+3} > 0$, equivalently $\frac{\kappa_{6i+3}}{\kappa_{6i+6}} - \frac{\kappa_{6j+3}}{\kappa_{6j+6}} > 0$ for all $j > i$. Note that

$$\frac{\kappa_{6i+3}}{\kappa_{6i+6}} - \frac{\kappa_{6j+3}}{\kappa_{6j+6}} = \sum_{k=1}^{j-i} \frac{\kappa_{6(i+k-1)+3}}{\kappa_{6(i+k-1)+6}} - \frac{\kappa_{6(i+k)+3}}{\kappa_{6(i+k)+6}}.$$

By hypothesis and (16), all terms in the sum are positive and hence, so is their sum. The argument for nonnegativity is analogous. This concludes the proof. \square

In the rest of this section, we only consider parameter vectors $\kappa \in \mathbb{R}_{>0}^{6n}$ for which all 2 by 2 minors of M_κ are nonnegative and (21) holds. These yield to parameter vectors $\eta \in \mathbb{R}_{>0}^{3n}$ such that the set of exponents of the monomials of P_η that may have negative coefficient is

$$A_- := \{(2, 1), (3, 1), \dots, (2n-2, 1)\},$$

and we define

$$\iota_i := (i+1, 1), \quad \text{for } i \in \{1, \dots, 2n-3\}.$$

Furthermore, we know from Theorem 3.5 that $N(P_\eta)$ is a hexagon for $n \geq 2$, and let us label its vertices as follows:

$$\alpha_1 := (0, 0), \quad \alpha_2 := (2, 2), \quad \alpha_3 := (2n, 1), \quad \alpha_4 := (0, 1), \quad \alpha_5 := (n, 0), \quad \alpha_6 := (3n-2, 2).$$

For each $\iota_i \in A_-$, with $x = (x_2, x_3)$, we consider two polynomials:

$$(22) \quad C_{1,i}(x) = \sum_{j=1}^3 \frac{\text{coeff}(P_\eta, \alpha_j)}{2n-3} x^{\alpha_j} + \delta_{1,i} x^{\iota_i} \quad \text{and} \quad C_{2,i}(x) = \sum_{j=4}^6 \frac{\text{coeff}(P_\eta, \alpha_j)}{2n-3} x^{\alpha_j} + \delta_{2,i} x^{\iota_i},$$

where $\delta_{1,i}, \delta_{2,i} \in \mathbb{R}$ are chosen such that $\delta_{1,i} + \delta_{2,i} = \text{coeff}(P_\eta, \iota_i)$.

Note that for all $i \in \{1, \dots, 2n-3\}$, ι_i is in the relative interior of the triangles $\text{conv}(\{\alpha_1, \alpha_2, \alpha_3\})$ and $\text{conv}(\{\alpha_4, \alpha_5, \alpha_6\})$. Therefore, for $i = 1, 2$, $N(C_{1,i})$ and $N(C_{2,i})$ are respectively

$$(23) \quad \Delta_1 := \text{conv}(\{\alpha_1, \alpha_2, \alpha_3\}) \quad \text{and} \quad \Delta_2 := \text{conv}(\{\alpha_4, \alpha_5, \alpha_6\}).$$

It follows that $C_{1,i}$ and $C_{2,i}$ are circuit polynomials. We denote the circuit numbers associated with $C_{1,i}$ and $C_{2,i}$ with $\Theta_{1,i}$ and $\Theta_{2,i}$, respectively. Then, for $i \in \{1, \dots, 2n-3\}$, it holds

$$(24) \quad \begin{aligned} \Theta_{1,i} &= \left(\frac{\text{coeff}(C_{1,i}, \alpha_1)}{\frac{2n-1-i}{4n-2}} \right)^{\frac{2n-1-i}{4n-2}} \left(\frac{\text{coeff}(C_{1,i}, \alpha_2)}{\frac{2n-1-i}{4n-2}} \right)^{\frac{2n-1-i}{4n-2}} \left(\frac{\text{coeff}(C_{1,i}, \alpha_3)}{\frac{2i}{4n-2}} \right)^{\frac{2i}{4n-2}} \\ &= \left(\frac{\text{coeff}(P_\eta, \alpha_1)}{(2n-1-i)} \right)^{\frac{2n-1-i}{4n-2}} \left(\frac{\text{coeff}(P_\eta, \alpha_2)}{(2n-1-i)} \right)^{\frac{2n-1-i}{4n-2}} \left(\frac{\text{coeff}(P_\eta, \alpha_3)}{2i} \right)^{\frac{2i}{4n-2}} \left(\frac{4n-2}{2n-3} \right), \end{aligned}$$

and similarly,

$$(25) \quad \Theta_{2,i} = \left(\frac{\text{coeff}(P_\eta, \alpha_4)}{(4n-2i-4)} \right)^{\frac{4n-2i-4}{4n-2}} \left(\frac{\text{coeff}(P_\eta, \alpha_5)}{(i+1)} \right)^{\frac{i+1}{4n-2}} \left(\frac{\text{coeff}(P_\eta, \alpha_6)}{i+1} \right)^{\frac{i+1}{4n-2}} \left(\frac{4n-2}{2n-3} \right).$$

For each $i \in \{1, \dots, 2n-3\}$ we define the region $R_i \subseteq \mathbb{R}_{>0}^{6n}$ as follows:

$$R_i := \{ \kappa \in \mathbb{R}_{>0}^{6n} : \text{coeff}(P_{\eta(\kappa)}, \iota_i) \geq -\Theta_{1,i} - \Theta_{2,i}, \kappa_3 \kappa_{12} - \kappa_6 \kappa_9 > 0, \kappa_{6n-9} \kappa_{6n} - \kappa_{6n-3} \kappa_{6n-6} > 0, \text{ and} \\ \kappa_{6\ell+3} \kappa_{6j+6} - \kappa_{6\ell+6} \kappa_{6j+3} \geq 0 \text{ for all } \ell < j, \ell = 2, \dots, n-2 \},$$

where $\Theta_{1,i}, \Theta_{2,i}$ are defined using $\eta(\kappa)$. We denote the intersection of these $2n-3$ regions by

$$(26) \quad R := \bigcap_{i=1}^{2n-3} R_i.$$

Theorem 5.3. *With $R \subseteq \mathbb{R}_{>0}^{6n}$ as in (26), it holds:*

- (i) *There exists $\kappa \in R$ such that $P_{\eta(\kappa)}$ has some negative coefficient. In particular, $R \neq \emptyset$.*
- (ii) *$P_{\eta(\kappa)}(x_2, x_3) > 0$ for any $\kappa \in R$ and $(x_2, x_3) \in \mathbb{R}_{>0}^2$, and hence κ precludes multistationarity.*

Proof. We start by proving (ii). Let $\kappa \in R$, and $\eta := \eta(\kappa)$. Let $A(P_\eta)$ be the set of exponents of P_η , and define $A_+ = A(P_\eta) \setminus (A_- \cup \Delta_1 \cup \Delta_2)$ (with Δ_1, Δ_2 as in (23)). We rewrite P_η using the circuit polynomials defined in (22) as follows:

$$(27) \quad P_\eta(x) = \sum_{j=1}^2 \sum_{i=1}^{2n-3} C_{j,i}(x) + \sum_{\alpha \in A_+} \text{coeff}(P_\eta, \alpha) x^\alpha.$$

For any $\alpha \in A_+$, it holds that $\text{coeff}(P_\eta, \alpha) \geq 0$. Recall that the coefficient of x^{ι_i} in $C_{j,i}$ equals $\delta_{j,i}$, and these could be chosen arbitrarily as long as $\delta_{1,i} + \delta_{2,i} = \text{coeff}(P_\eta, \iota_i)$. This equality holds if we pick

$$\delta_{j,i} = -\Theta_{j,i} + \frac{\text{coeff}(P_\eta, \iota_i) + \Theta_{1,i} + \Theta_{2,i}}{2}, \quad j = 1, 2.$$

Furthermore, as in R it holds $\text{coeff}(P_\eta, \iota_i) \geq -\Theta_{1,i} - \Theta_{2,i}$, we find that $\delta_{j,i} \geq -\Theta_{j,i}$ for $j = 1, 2$ and hence $C_{1,i}$ and $C_{2,i}$ are nonnegative circuit polynomials by Theorem 2.2. By the decomposition (27), P_η is nonnegative as well, and combined with Corollary 3.9, we have shown (ii).

To prove (i) we construct explicitly a point satisfying the conditions. We consider the one parameter family of reaction rate constants $\kappa(k) \in \mathbb{R}_{>0}^{6n}$ with $k > 0$ defined as

$$(28) \quad \kappa_j = \begin{cases} n-i & \text{if } j = 6i+3 \text{ and } i < n, \\ 2 & \text{if } j = 6i+4 \text{ and } i < n, \\ k & \text{if } j = 6n-5 = 6(n-1)+1, \\ 1 & \text{otherwise,} \end{cases}$$

and let $\eta(k) := \eta(\kappa(k)) \in \mathbb{R}_{>0}^{3n}$. We show that there exists an interval $I \subset \mathbb{R}_{>0}$ such that for any $k \in I$, $\kappa(k) \in R$ and $P_{\eta(k)}$ contains a negative term. For any such $\kappa(k)$, we have $L_i = 1$ for any $i \in \{0, \dots, n-1\}$, and hence, $b_i = c_i = T_i$ for all $i \in \{0, \dots, n-1\}$. Similarly, we have

$$(29) \quad K_i = \begin{cases} \frac{1}{n-i+1} & \text{if } i \in \{0, \dots, n-2\}, \\ \frac{k}{2} & \text{if } i = n-1, \end{cases} \quad \text{and} \quad T_i = \begin{cases} \frac{n-i}{n+1} & \text{if } i \in \{-1, 0, \dots, n-2\}, \\ \frac{k}{n+1} & \text{if } i = n-1. \end{cases}$$

We start by noting that for each $\kappa(k)$ and for any $i \in \{0, \dots, n-1\}$, it holds

$$\left(\frac{\kappa_{6i+3}}{\kappa_{6i+6}} - \frac{\kappa_{6(i+1)+3}}{\kappa_{6(i+1)+6}} \right) = (n-i) - (n-i-1) = 1 > 0.$$

Hence, all minors of $M_{\kappa(k)}$ are positive by Proposition 5.2, and so are the coefficients of $P_{\eta(k)}$ corresponding to the exponents $\alpha_1, \dots, \alpha_6$. It follows from (24) and (25) that $\Theta_{1,i}(k) + \Theta_{2,i}(k) > 0$ for all $i \in \{1, \dots, 2n-3\}$, where $\Theta_{1,i}(k)$, $\Theta_{2,i}(k)$ are the circuit numbers obtained for $\kappa(k)$.

Let $\mathcal{C}_\ell(k) := \text{coeff}(P_{\eta(k)}, \iota_{\ell-1})$, which is the coefficient of x_2^ℓ in the polynomial $A_{10}(x_2)$. We show in Lemma B.1 in the Appendix, that for any $k > 0$, $\mathcal{C}_\ell(k) > 0$ when $\ell \in \{2, \dots, 2n-2\}$ and $\ell \neq n$. Thus, $\kappa(k) \in R_\ell$ for any $\ell \neq n$.

We consider the coefficient of x_2^n in $A_{10}(x_2)$, see (14). As for $\kappa(k)$ we have $b_i c_j = T_i T_j$ and $\sum_{i+j=n-2} (j+1-i) T_i T_j = \sum_{i+j=n-2} T_i T_j$, we have

$$\mathcal{C}_n(k) = -(n-1)b_{n-1} + \sum_{i+j=n-2} T_i T_j + \sum_{\substack{i+j=n-1 \\ i>j}} (i-j)(a_i c_j - a_j c_i).$$

Using the identities (11), (29), and (30) we find $a_{n-1}c_0 - a_0c_{n-1} = \frac{k(n-1)}{(n+1)^2}$ and $b_{n-1} = \frac{k}{n+1}$. This gives:

$$\mathcal{C}_n(k) = k \left(\frac{n-1}{n+1} \right) \left(\frac{n-1}{n+1} - 1 \right) + \sum_{i+j=n-2} T_i T_j + \sum_{\substack{i+j=n-1 \\ i>j, i \neq n-1}} (i-j)(a_i c_j - a_j c_i).$$

The variable k does not appear in the last two summands of $\mathcal{C}_n(k)$ and hence, $\mathcal{C}_n(k)$ is a linear function of k with a negative leading term and a positive constant term.

Let $k_0 > 0$ be the zero of $\mathcal{C}_n(k)$, and consider the function $g(k) = \mathcal{C}_n(k) + \Theta_{1,n-1}(k) + \Theta_{2,n-1}(k)$. Note that $g(k_0) > 0$ as $\mathcal{C}_n(k_0) = 0$. As g is continuous in k , there exists $\epsilon_0 > 0$ such that for all $k \in (k_0, k_0 + \epsilon_0)$, $g(k) > 0$. Hence $\kappa(k) \in R_{n-1}$. By definition of R , it then follows that $\kappa(k) \in R$ and by construction $\mathcal{C}_n(k) < 0$ for any such k , showing (i). \square

In the next example, we give the conditions to be in R explicitly when $n = 3$ and $\kappa(k)$ is the parameter vector constructed in (28) in the proof of Theorem 5.3(i).

Example 5.4. Let $n = 3$, $\kappa(k) = (1, 1, 3, 2, 1, 1, 1, 1, 2, 2, 1, 1, k, 1, 1, 2, 1, 1)$ be as in (28). The Newton polytope $N(P_{\eta(k)})$ is shown in the right panel of Figure 1. The circuit numbers from (24) and (25) are

$$\begin{aligned} \Theta_{1,1} &= 2^{-\frac{32}{10}} 3^{-1} 5 k^{\frac{4}{10}}, & \Theta_{2,1} &= 2^{-\frac{28}{10}} 3^{-\frac{16}{10}} 5 k^{\frac{6}{10}}, \\ \Theta_{1,2} &= 2^{-\frac{26}{10}} 3^{-\frac{16}{10}} 5 k^{\frac{8}{10}}, & \Theta_{2,2} &= 2^{-3} 3^{-\frac{16}{10}} 5 k^{\frac{9}{10}}, \\ \Theta_{1,3} &= 2^{-\frac{32}{10}} 3^{-\frac{16}{10}} 5 k^{\frac{12}{10}}, & \Theta_{2,3} &= 2^{-\frac{44}{10}} 3^{-1} 5 k^{\frac{12}{10}}. \end{aligned}$$

The vectors $\kappa(k) \in \mathbb{R}_{>0}^{18}$ are in the regions R_1, R_2 and R_3 in the parameter space if they satisfy the following inequalities respectively

$$\begin{aligned} \frac{6k+1}{8} &\geq -2^{-\frac{32}{10}} 3^{-1} 5 k^{\frac{4}{10}} - 2^{-\frac{28}{10}} 3^{-\frac{16}{10}} 5 k^{\frac{6}{10}}, \\ \frac{3-k}{4} &\geq -2^{-\frac{26}{10}} 3^{-\frac{16}{10}} 5 k^{\frac{8}{10}} - 2^{-3} 3^{-\frac{16}{10}} 5 k^{\frac{9}{10}}, \\ \frac{7k+4}{16} &\geq -2^{-\frac{32}{10}} 3^{-\frac{16}{10}} 5 k^{\frac{12}{10}} - 2^{-\frac{44}{10}} 3^{-1} 5 k^{\frac{12}{10}}, \end{aligned}$$

respectively. As shown in the proof of Theorem 5.3, the first and the third inequalities hold for all $k > 0$. The second inequality holds if $k < 10.03$, and the coefficient corresponding to the term ι_{n-1} in $P_{\eta(k)}$ is negative if $k > 3$. Therefore, for $10.03 > k > 3$, $P_{\eta(k)}$ contains a negative term, but $P_{\eta(k)}$ is positive. Hence multistationarity is precluded for $\kappa(k)$.

We end this section with two remarks.




FIGURE 1. The support of P_η for $n = 2, 3$, black circles and red squares correspond to the exponents with positive and negative coefficients, respectively. On the left, blue triangles and green line segments denote the Newton polytopes of the circuit polynomials used in [16, Theorem 3.5]. On the right, blue and green triangles correspond to the simplices Δ_1 and Δ_2 from (23), respectively.

Remark 5.5. *labelRemark:CoverComparison* If the premise of Proposition 5.2 holds, then every term of $P_{\eta(\kappa)}$ with exponent in $A_+ = A(P_\eta) \setminus (A_- \cup \Delta_1 \cup \Delta_2)$ has a positive coefficient. This means that we can construct further circuit polynomials using the exponents in A_+ as vertices and in A_- as inner terms. For example, a similar approach was taken for the case $n = 2$ in [16, Theorem 3.5], where we considered two additional 1-dimensional circuits given by $\{(1, 0), (2, 1), (3, 2)\}$ and $\{(1, 1), (2, 1), (3, 1)\}$ (green line segments in the left pane in Figure 1). These were used to formulate a sufficient condition for monostationarity stronger than that of Theorem 5.3. In Theorem 5.3, we omit these extra polynomials in order to keep the notation tidy.

Remark 5.6. We note that if the values of the reaction rate constant κ is known, then we can find a lower bound for $P_{\eta(\kappa)}(x_2, x_3)$ by using various convex and polynomial optimization methods such as solving a relative entropy program induced by the SONC/SAGE decomposition or using semidefinite programming [2, 5]. However, for the results presented here, the parameters are a priori symbolic. Hence, we instead use the method of choosing circuit covers to obtain inequalities on the parameters, which yields symbolic necessary conditions for multistationarity.

6. Connectivity

We now shift gears and focus our attention to the question of connectivity: Are the subset of parameters enabling multistationarity and that of those precluding multistationarity path connected in the space of parameters? The results in this section show that the answer to both questions is yes.

Let $X \subseteq \mathbb{R}_{>0}^{6n}$ be the set of parameter vectors κ that enable multistationarity. We prove that X is path connected in two steps: First we show in Lemma 6.1 that a subset Y of X is path connected, and then we construct a path in X from any η that enables multistationarity to the subset Y in Theorem 6.2.

Lemma 6.1. *Let $Y \subseteq \mathbb{R}_{>0}^{6n}$ consist of the parameters $\kappa \in \mathbb{R}_{>0}^{6n}$ such that $\kappa_{6n-9}\kappa_{6n} - \kappa_{6n-6}\kappa_{6n-3} < 0$. Then, $Y \subseteq X$ is path connected.*

Proof. From Theorem 4.1, we know that $Y \subseteq X$. The proof that Y is path connected is a straightforward adaptation of Lemma 5.1 and Remark 5.3 in [16]. \square

Theorem 6.2. *For all $n \geq 2$, the set $X \subseteq \mathbb{R}_{>0}^{6n}$ consisting on the parameters η that enable multistationarity is path connected.*

Proof. Let $\kappa \in X$. Then by Corollary 3.9, there exists $x_2, x_3 > 0$ such that $P_{\eta(\kappa)}(x_2, x_3) < 0$. We proceed similarly to the proof of Theorem 4.3 by treating some parameters as variables.

Fix the value of the assembled parameters $K_0, \dots, K_{n-2}, L_0, \dots, L_{n-1}, T_0, \dots, T_{n-2}$ corresponding to κ , and construct $T_{n-1}(\kappa_{6n-3}, K_{n-1})$ as in (6) with κ_{6n-3}, K_{n-1} treated as parameters. We fix as well $x_2, x_3 > 0$, and consider the two parameter family of vectors

$$\xi(\kappa_{6n-3}, K_{n-1}) = (T_0, \dots, T_{n-2}, T_{n-1}(\kappa_{6n-3}, K_{n-1}), K_0, \dots, K_{n-1}, L_0, \dots, L_{n-1}) \in \mathbb{R}_{>0}^{3n}.$$

The polynomial $P_{\xi(\kappa_{6n-3}, K_{n-1})}(x_2, x_3)$ becomes a polynomial in κ_{6n-3}, K_{n-1} , denoted by $\bar{P}(\kappa_{6n-3}, K_{n-1})$.

Note that the parameters κ_{6n-3}, K_{n-1} are only present in the terms involving a_{n-1}, b_{n-1} and c_{n-1} , see (6) and (11). In particular, a_{n-1} depends only on K_{n-1} , while b_{n-1} and c_{n-1} depend on the product $\kappa_{6n-3}K_{n-1}$. Using (14), we express A_2, A_{10} and A_{00} in terms of κ_{6n-3} and K_{n-1} in the following way, with all $r_*^{(*)} \in \mathbb{R}$ independent of κ_{6n-3} and K_{n-1} :

$$\begin{aligned} \bar{A}_2 &= \left(1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \right) \left(\sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i b_j x_2^{\ell+1} \right) \\ &= (r_0^{(2)} + r_1^{(2)} \kappa_{6n-3} K_{n-1}) (r_2^{(2)} + r_3^{(2)} K_{n-1} + r_4^{(2)} \kappa_{6n-3} K_{n-1}) \quad \text{with } r_0^{(2)}, r_1^{(2)}, r_3^{(2)} > 0, \\ \bar{A}_{10} &= \sum_{\ell=0}^{n-1} (\ell+1) a_\ell x_2^\ell - \sum_{\ell=0}^{n-1} \ell b_\ell x_2^{\ell+1} + \sum_{\ell=0}^{2n-2} \sum_{i+j=\ell} (j+1-i) b_i c_j x_2^{\ell+2} + \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i c_j x_2^{\ell+1} \\ &= (r_0^{(10)} + r_1^{(10)} K_{n-1}) - (r_2^{(10)} + r_3^{(10)} \kappa_{6n-3} K_{n-1}) + (r_4^{(10)} + r_5^{(10)} \kappa_{6n-3} K_{n-1} + r_6^{(10)} \kappa_{6n-3}^2 K_{n-1}^2) \\ &\quad + (r_7^{(10)} + r_8^{(10)} K_{n-1} + r_9^{(10)} \kappa_{6n-3} K_{n-1}) \quad \text{with } r_1^{(10)}, r_8^{(10)} > 0, \\ \bar{A}_{00} &= 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} = (r_0^{(2)} + r_1^{(2)} \kappa_{6n-3} K_{n-1}). \end{aligned}$$

Collecting all the terms together we write \bar{P} as

$$\bar{P}(\kappa_{6n-3}, K_{n-1}) = p_0 + p_1 K_{n-1} + p_2 \kappa_{6n-3} K_{n-1} + p_3 \kappa_{6n-3} K_{n-1}^2 + p_4 \kappa_{6n-3}^2 K_{n-1}^2,$$

with $p_1 = r_0^{(2)} r_3^{(2)} x_3^2 + (r_1^{(10)} + r_8^{(10)}) x_3 > 0$ and $p_3 = r_1^{(2)} r_3^{(2)} x_3^2 > 0$. The Newton polytope of \bar{P} has vertices $(0, 0), (0, 1), (1, 2), (2, 2)$. The terms of \bar{P} that can be negative are all supported on the edge F joining the vertices $(0, 0)$ and $(2, 2)$. The outer normal cone of this edge is generated by $v = (v_1, v_2) = (1, -1)$.

By the choice of κ, x_2, x_3 , we know that \bar{P} attains negative values, namely by choosing $\kappa_{6n-5}, \kappa_{6n-4}, \kappa_{6n-3}$ to be the entries of the given κ . To avoid confusion, we denote them by $\kappa_{6n-5}^*, \kappa_{6n-4}^*, \kappa_{6n-3}^*$ and the corresponding assembled parameter as K_{n-1}^* . It follows that $\bar{P}_F(\kappa_{6n-3}^*, K_{n-1}^*) < 0$. We evaluate \bar{P} at $q_s = (\kappa_{6n-3}^* s^{v_1}, K_{n-1}^* s^{v_2}) = (\kappa_{6n-3}^* s, K_{n-1}^* s^{-1})$ and obtain

$$Q(s) := s \bar{P}(q_s) = p_1 K_{n-1}^* + p_3 \kappa_{6n-3}^* (K_{n-1}^*)^2 + s \bar{P}_F(\kappa_{6n-3}^*, K_{n-1}^*).$$

As for $s = 1$, $Q(s)$ is a linear function with negative coefficient and $Q(1) < 0$, we have that $Q(s) < 0$ for all $s \geq 1$. Hence, consider the parameter vector κ_s obtained from κ by replacing $\kappa_{6n-4}^*, \kappa_{6n-3}^*$ by $\kappa_{6n-4} s, \kappa_{6n-3} s$ such that the new K_{n-1} is $K_{n-1} s^{-1}$. Then κ_s enables multistationarity for all $s \geq 1$. As s increases, so does $\kappa_{6n-3} s$, and eventually κ_s belongs to Y . The parameter vectors κ_s thus give a path connecting the point κ in X with a point in Y . This concludes the proof. \square

The rest of the section focuses on showing that the region of parameters precluding multistationarity is also path connected. We first show that the region of monostationarity is connected in the $3n$ dimensional parameter space given by T_i, K_i, L_i for $i = 0, \dots, n-1$. Written in terms of T_i, K_i, L_i instead of a_i, b_i, c_i , the terms of the polynomial P_η in (20) are

$$\begin{aligned} A_2(x_2) &= \left(1 + \sum_{i=0}^{n-1} T_i x_2^{i+1} \right) \left(\sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) K_i L_j T_{i-1} T_j x_2^{\ell+1} \right), \\ A_{10}(x_2) &= \sum_{\ell=0}^{n-1} (\ell+1) K_\ell T_{\ell-1} x_2^\ell - \sum_{\ell=0}^{n-1} \ell L_\ell T_\ell x_2^{\ell+1} + \sum_{\ell=0}^{2n-2} \sum_{i+j=\ell} (j+1-i) L_i T_i T_j x_2^{\ell+2} \\ &\quad + \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) K_i T_{i-1} T_j x_2^{\ell+1}, \\ A_{00}(x_2) &= 1 + \sum_{i=0}^{n-1} T_i x_2^{i+1}. \end{aligned}$$

In Theorem 6.3 we show that the region $Z \subseteq \mathbb{R}_{>0}^{3n}$ of parameters for which P_η is positive is path connected. We prove this by showing that any point in Z is path connected to a point $\eta \in Z$ such that all the coefficients of P_η are positive. We then show that any two such points are also path connected in Z .

Theorem 6.3. *For all $n \geq 1$, the set*

$$Z := \{\eta \in \mathbb{R}_{>0}^{3n} : P_\eta(x_2, x_3) > 0 \text{ for all } (x_2, x_3) \in \mathbb{R}_{>0}^2\}$$

is path connected.

Proof. Let $\eta \in Z$. Hence, for all $x_2, x_3 > 0$, $P_\eta(x_2, x_3) > 0$. Fix $(x_2, x_3) \in \mathbb{R}_{>0}^2$ and all parameters in η but K_{n-1}, L_0 , and view $P_\eta(x_2, x_3)$ as a polynomial in K_{n-1} and L_0 with real coefficients. Let P' denote this polynomial. It is straightforward to see using (16) that P' takes the form

$$P'(K_{n-1}, L_0) := r_3 K_{n-1} L_0 + r_2 K_{n-1} + r_1 L_0 + r_0, \quad \text{with } r_1, r_2, r_3 > 0.$$

As in the proof of Theorem 6.2, we denote by K_{n-1}^*, L_0^* the corresponding parameter entries in η , such that $P'(K_{n-1}^*, L_0^*) > 0$.

We evaluate P' at $q_s = (K_{n-1}^* s, L_0^* s)$:

$$Q(s) := P'(q_s) = r_3 K_{n-1} L_0 s^2 + (r_2 K_{n-1} + r_1 L_0) s + r_0.$$

The polynomial Q is quadratic in s with positive leading term and $Q(1) > 0$. By Descartes' rule of signs, Q has at most one positive root and hence $Q(s) > 0$ for all $s \geq 1$.

As this holds for any fixed $(x_2, x_3) \in \mathbb{R}_{>0}^2$, it follows that

$$\eta_s := (T_0, \dots, T_{n-1}, K_0, \dots, K_{n-2}, K_{n-1}^* s, L_0^* s, L_1, \dots, L_{n-1}) \in Z, \quad \text{for all } s \geq 1.$$

We now show that for s large enough, all coefficients of P_{η_s} in x_2, x_3 are positive. The factor of $A_2(x_2)$ that can be negative is $\left(\sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) K_i L_j T_{i-1} T_j x_2^{\ell+1}\right)$. For the coefficient of x_2^k , seen as a polynomial in all parameters, the coefficients of all the monomials involving K_{n-1} and L_0 are positive, and there is at least one such monomial for every $2 \leq k \leq 2n-2$. Hence, by letting K_{n-1} and L_0 be sufficiently large, all coefficients become positive. An analogous argument holds for $A_{10}(x_2)$ and therefore we conclude that, for s large enough, all coefficients of P_{η_s} in x_2, x_3 are positive.

All that is left is to show that any two parameter points η_1, η_2 such that all coefficients of P_{η_i} are positive, are connected by a path in Z . First note that increasing the coordinates of K_{n-1} and L_0 in any of them leads to a parameter point also in Z with all coefficients of P_{η_i} positive. Second, consider the projection π outside the entries K_{n-1} and L_0 , and form the line segment $\eta'(s) := s\pi(\eta_1) + (1-s)\pi(\eta_2)$ for $s \in [0, 1]$. Extend $\eta'(s)$ to a parameter vector $\eta(s, K_{n-1}, L_0)$ with K_{n-1} and L_0 seen as variables. The coefficients of $P_{\eta(s, K_{n-1}, L_0)}$ are polynomials in K_{n-1}, L_0 with coefficients in s , such that the coefficients of the monomials involving K_{n-1}, L_0 are positive continuous functions of s . As $[0, 1]$ is compact, there exist K_{n-1}^* and L_0^* such that for any $K_{n-1} \geq K_{n-1}^*$ and $L_0 \geq L_0^*$, all the coefficients of $P_{\eta(s, K_{n-1}, L_0)}$ are positive for all $s \in [0, 1]$. By picking K_{n-1}^* and L_0^* to be larger than the entries of η_1 and η_2 , the desired path is the composition of the line segments in Z joining the points $\eta_1, \eta(0, K_{n-1}^*, L_0^*), \eta(1, K_{n-1}^*, L_0^*)$ and η_2 in this order. This concludes the proof. \square

In Theorem 6.3 above we have shown that the region of monostationarity is path connected in the parameter space given by the parameters K_i, L_i , and T_i for all $i = 0, \dots, n-1$. Next, we extend this result to the $6n$ dimensional parameter space given by $\kappa \in \mathbb{R}_{>0}^{6n}$.

Corollary 6.4. *The set of parameters $\kappa \in \mathbb{R}_{>0}^{6n}$ precluding multistationarity is path connected for all n .*

Proof. Let $\kappa, \kappa' \in \mathbb{R}_{>0}^{6n}$ preclude multistationarity. We have that $\eta(\kappa), \eta(\kappa') \in Z$, with Z as in Theorem 6.3 and hence, there is a continuous path

$$\xi(s) = (T_0(s), \dots, T_{n-1}(s), K_0(s), \dots, K_{n-1}(s), L_0(s), \dots, L_{n-1}(s)), \quad s \in [0, 1]$$

connecting them in Z . Define the points $\kappa(s) \in \mathbb{R}_{>0}^{6n}$ for $i = 0, \dots, n-1$, as

$$\begin{aligned} \kappa_{6i+2}(s) &:= \kappa_{6i+2}, & \kappa_{6i+3}(s) &:= \kappa_{6i+6} \frac{T_i(s)}{T_{i-1}(s)} \frac{L_i(s)}{K_i(s)}, & \kappa_{6i+1}(s) &:= K_i(s)(\kappa_{6i+2} + \kappa_{6i+3}(s)), \\ \kappa_{6i+5}(s) &:= \kappa_{6i+5}, & \kappa_{6i+6}(s) &:= \kappa_{6i+6}, & \kappa_{6i+4}(s) &:= L_i(s)(\kappa_{6i+5} + \kappa_{6i+6}). \end{aligned}$$

Using (6), $\frac{T_i(0)}{T_{i-1}(0)} \frac{L_i(0)}{K_i(0)} = \frac{\kappa_{6i+3}}{\kappa_{6i+6}}$ and hence $\kappa(0) = \kappa$. Furthermore, for all $s \in [0, 1]$, $\eta(\kappa(s)) = \xi(s)$. Therefore, $\kappa(s)$ precludes multistationarity for all $s \in [0, 1]$ and gives a path from κ to $\kappa(1)$. All that is left is to connect κ' with $\kappa(1)$. Note that for $i = 0, \dots, n-1$,

$$\begin{aligned} (\kappa_{6i+1}(1), \kappa_{6i+2}(1), \kappa_{6i+3}(1), \kappa_{6i+4}(1), \kappa_{6i+5}(1), \kappa_{6i+6}(1)) = \\ \left(\frac{\kappa'_{6i+1}}{\kappa'_{6i+2} + \kappa'_{6i+3}} (\kappa_{6i+2} + \kappa_{6i+6} \frac{\kappa'_{6i+3}}{\kappa_{6i+6}}), \kappa_{6i+2}, \kappa_{6i+6} \frac{\kappa'_{6i+3}}{\kappa_{6i+6}}, \frac{\kappa'_{6i+4}}{\kappa'_{6i+5} + \kappa'_{6i+6}}, \kappa_{6i+5}, \kappa_{6i+6} \right) \end{aligned}$$

To this end, define a path $\alpha(s)$ with, for $i = 0, \dots, n-1$,

$$\begin{aligned} \alpha_{6i+2}(s) &:= \kappa_{6i+2} \left(\frac{\kappa'_{6i+2}}{\kappa_{6i+2}} \right)^s, & \alpha_{6i+3}(s) &:= \kappa'_{6i+3} \left(\frac{\kappa_{6i+6}}{\kappa'_{6i+6}} \right)^{1-s}, & \alpha_{6i+1}(s) &:= \frac{\kappa'_{6i+1}}{\kappa_{6i+2} + \kappa'_{6i+3}} (\alpha_{6i+2}(s) + \alpha_{6i+3}(s)) \\ \alpha_{6i+5}(s) &:= \kappa_{6i+5} \left(\frac{\kappa'_{6i+5}}{\kappa_{6i+5}} \right)^s, & \alpha_{6i+6}(s) &:= \kappa'_{6i+6} \left(\frac{\kappa_{6i+6}}{\kappa'_{6i+6}} \right)^{1-s}, & \alpha_{6i+4}(s) &:= \frac{\kappa'_{6i+4}}{\kappa_{6i+5} + \kappa'_{6i+6}} (\alpha_{6i+5}(s) + \alpha_{6i+6}(s)). \end{aligned}$$

We have $\alpha(0) = \xi(1)$ and $\alpha(1) = \kappa'$. Furthermore, $\eta(\alpha(s)) = \eta(\kappa')$ for all $s \in [0, 1]$ and hence, $\alpha(s)$ precludes multistationarity. Thus, α gives the desired path and concludes the proof. \square

APPENDIX A.

In this appendix we compute the determinant of the matrix J in (12), which we rewrite here for convenience:

$$J := \begin{bmatrix} 1 + \sum_{i=0}^{n-1} (i+1) a_i x_2^i x_3 & - \sum_{i=0}^{n-1} i a_i x_2^{i+1} x_3 & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) b_i x_2^i x_3 & 1 - \sum_{i=0}^{n-1} i b_i x_2^{i+1} x_3 & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ -1 + \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+1} x_3 & -1 - \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+2} x_3 & 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix}.$$

Note that x_3 appears with degree one in each of the entries of columns 1 and 2 but the third column does not depend on x_3 . Therefore, the determinant of J can be written as a quadratic polynomial in x_3 :

$$P := \det J = A_2 x_3^2 + A_1 x_3 + A_0.$$

Specifically, after noticing that the first two columns can be written as a sum of two vectors, one independent of x_3 and the other a multiple of x_3 , we write the determinant of J as

$$P = \det J_1 + (\det J_2 + \det J_3) x_3 + (\det J_4) x_3^2,$$

where

$$\begin{aligned} J_1 &= \begin{bmatrix} 1 & 0 & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ 0 & 1 & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ -1 & -1 & 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix}, \\ J_2 &= \begin{bmatrix} 1 & - \sum_{i=0}^{n-1} i a_i x_2^{i+1} & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ 0 & - \sum_{i=0}^{n-1} i b_i x_2^{i+1} & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ -1 & - \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+2} & 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix}, \\ J_3 &= \begin{bmatrix} \sum_{i=0}^{n-1} (i+1) a_i x_2^i & 0 & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) b_i x_2^i & 1 & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+1} & -1 & 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix}, \\ J_4 &= \begin{bmatrix} \sum_{i=0}^{n-1} (i+1) a_i x_2^i & - \sum_{i=0}^{n-1} i a_i x_2^{i+1} & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) b_i x_2^i & - \sum_{i=0}^{n-1} i b_i x_2^{i+1} & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+1} & - \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+2} & 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix}. \end{aligned}$$

We proceed to compute each coefficient A_0, A_1, A_2 using the matrices J_i , $i = 1, 2, 3, 4$.

Computing A_0 . The determinant of J_1 is simply

$$A_0 = 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} + \sum_{i=0}^{n-1} b_i x_1 x_2^i + \sum_{i=0}^{n-1} a_i x_1 x_2^i.$$

Computing A_2 . We compute now the determinant of J_4 . After adding the first column multiplied by x_2 to the second column, $\det J_4$ agrees with the determinant of

$$J'_4 = \begin{bmatrix} \sum_{i=0}^{n-1} (i+1) a_i x_2^i & \sum_{i=0}^{n-1} a_i x_2^{i+1} & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) b_i x_2^i & \sum_{i=0}^{n-1} b_i x_2^{i+1} & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+1} & 0 & 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix}.$$

Subtraction of the second column of J'_4 multiplied by x_1/x_2 from the third column gives that $\det J_4 = \det J'_4 = \det J''_4$ with

$$J''_4 = \begin{bmatrix} \sum_{i=0}^{n-1} (i+1) a_i x_2^i & \sum_{i=0}^{n-1} a_i x_2^{i+1} & 0 \\ \sum_{i=0}^{n-1} (i+1) b_i x_2^i & \sum_{i=0}^{n-1} b_i x_2^{i+1} & 0 \\ \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+1} & 0 & 1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix}.$$

Hence, we compute the determinant of J''_4 . We start by finding the principal minor obtained by removing the last row and column of J''_4 :

$$\begin{aligned} M &= \left(\sum_{i=0}^{n-1} (i+1) a_i x_2^i \right) \left(\sum_{i=0}^{n-1} b_i x_2^{i+1} \right) - \left(\sum_{i=0}^{n-1} a_i x_2^{i+1} \right) \left(\sum_{i=0}^{n-1} (i+1) b_i x_2^i \right) \\ &= \left(\sum_{i=0}^{n-1} \sum_{j=0}^{n-1} (i+1) a_i b_j x_2^{i+j+1} \right) - \left(\sum_{i=0}^{n-1} \sum_{j=0}^{n-1} a_i (j+1) b_j x_2^{i+j+1} \right) \\ &= \sum_{i=0}^{n-1} \sum_{j=0}^{n-1} (i-j) a_i b_j x_2^{i+j+1} = \sum_{\ell=1}^{2n-2} \sum_{i+j=\ell} (i-j) a_i b_j x_2^{\ell+1} = \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i b_j x_2^{\ell+1}, \end{aligned}$$

where in the last equality we note that the term vanished for $\ell = 2n - 2$. From this, we obtain

$$A_2 = \det J_4 = \left(1 + \sum_{i=0}^{n-1} c_i x_2^{i+1} \right) \left(\sum_{\ell=1}^{2n-2} \sum_{i+j=\ell} (i-j) a_i b_j x_2^{\ell+1} \right).$$

Computing A_1 . We start by finding $\det J_2$.

$$\det J_2 = \det \begin{bmatrix} 1 & -\sum_{i=0}^{n-1} i a_i x_2^{i+1} & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ 0 & -\sum_{i=0}^{n-1} i b_i x_2^{i+1} & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ -1 & -\sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+2} & \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix} + \det \begin{bmatrix} 1 & -\sum_{i=0}^{n-1} i a_i x_2^{i+1} & 0 \\ 0 & -\sum_{i=0}^{n-1} i b_i x_2^{i+1} & 0 \\ -1 & -\sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+2} & 1 \end{bmatrix}.$$

The second determinant is simply

$$D_2 := - \sum_{i=0}^{n-1} i b_i x_2^{i+1}.$$

For the first determinant D_1 , adding the first row to the last gives

$$D_1 = \det \begin{bmatrix} 1 & -\sum_{i=0}^{n-1} i a_i x_2^{i+1} & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ 0 & -\sum_{i=0}^{n-1} i b_i x_2^{i+1} & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ 0 & -\sum_{i=0}^{n-1} (i a_i x_2^{i+1} + (i+1) c_i x_1^{-1} x_2^{i+2}) & \sum_{i=0}^{n-1} (a_i x_1 x_2^i + c_i x_2^{i+1}) \end{bmatrix},$$

and hence

$$\begin{aligned} D_1 &= - \left(\sum_{i=0}^{n-1} i b_i x_2^{i+1} \right) \left(\sum_{i=0}^{n-1} (a_i x_1 x_2^i + c_i x_2^{i+1}) \right) + \left(\sum_{i=0}^{n-1} b_i x_1 x_2^i \right) \left(\sum_{i=0}^{n-1} (i a_i x_2^{i+1} + (i+1) c_i x_1^{-1} x_2^{i+2}) \right) \\ &= \sum_{i=0}^{n-1} \sum_{j=0}^{n-1} (j-i) a_j b_i x_1 x_2^{i+j+1} + \sum_{i=0}^{n-1} \sum_{j=0}^{n-1} (j+1-i) b_i c_j x_2^{i+j+2} \end{aligned}$$

$$= \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (j-i) a_j b_i x_1 x_2^{\ell+1} + \sum_{\ell=0}^{2n-2} \sum_{i+j=\ell} (j+1-i) b_i c_j x_2^{\ell+2}.$$

This gives $\det J_2 = D_1 + D_2$.

We proceed similarly to the computation of $\det J_3$:

$$\det J_3 = \det \begin{bmatrix} \sum_{i=0}^{n-1} (i+1) a_i x_2^i & 0 & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) b_i x_2^i & 1 & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+1} & -1 & \sum_{i=0}^{n-1} c_i x_2^{i+1} \end{bmatrix} \\ + \det \begin{bmatrix} \sum_{i=0}^{n-1} (i+1) a_i x_2^i & 0 & 0 \\ \sum_{i=0}^{n-1} (i+1) b_i x_2^i & 1 & 0 \\ \sum_{i=0}^{n-1} (i+1) c_i x_1^{-1} x_2^{i+1} & -1 & 1 \end{bmatrix}.$$

The second determinant C_2 is

$$C_2 = \sum_{i=0}^{n-1} (i+1) a_i x_2^i.$$

For the first determinant C_1 , we have

$$C_1 = \det \begin{bmatrix} \sum_{i=0}^{n-1} (i+1) a_i x_2^i & 0 & \sum_{i=0}^{n-1} a_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) b_i x_2^i & 1 & \sum_{i=0}^{n-1} b_i x_1 x_2^i \\ \sum_{i=0}^{n-1} (i+1) (b_i x_2^i + c_i x_1^{-1} x_2^{i+1}) & 0 & \sum_{i=0}^{n-1} (b_i x_1 x_2^i + c_i x_2^{i+1}) \end{bmatrix},$$

and hence

$$C_1 = \left(\sum_{i=0}^{n-1} (i+1) a_i x_2^i \right) \left(\sum_{i=0}^{n-1} (b_i x_1 x_2^i + c_i x_2^{i+1}) \right) - \left(\sum_{i=0}^{n-1} a_i x_1 x_2^i \right) \left(\sum_{i=0}^{n-1} (i+1) (b_i x_2^i + c_i x_1^{-1} x_2^{i+1}) \right) \\ = \sum_{i=0}^{n-1} \sum_{j=0}^{n-1} (i-j) a_i b_j x_1 x_2^{i+j} + \sum_{i=0}^{n-1} \sum_{j=0}^{n-1} (i-j) a_i c_j x_2^{i+j+1} \\ = \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i b_j x_1 x_2^{\ell} + \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i c_j x_2^{\ell+1}.$$

Putting it all together, we get

$$A_1 = C_2 + D_2 + C_1 + D_1 \\ = \sum_{\ell=0}^{n-1} (\ell+1) a_{\ell} x_2^{\ell} - \sum_{\ell=0}^{n-1} \ell b_{\ell} x_2^{\ell+1} + \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (j-i) a_j b_i x_1 x_2^{\ell+1} \\ + \sum_{\ell=0}^{2n-2} \sum_{i+j=\ell} (j+1-i) b_i c_j x_2^{\ell+2} + \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i b_j x_1 x_2^{\ell} + \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i c_j x_2^{\ell+1} \\ = \sum_{\ell=0}^{n-1} (\ell+1) a_{\ell} x_2^{\ell} - \sum_{\ell=0}^{n-1} \ell b_{\ell} x_2^{\ell+1} + \sum_{\ell=0}^{2n-2} \sum_{i+j=\ell} (j+1-i) b_i c_j x_2^{\ell+2} + \sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (i-j) a_i c_j x_2^{\ell+1} \\ + x_1(1+x_2) \left(\sum_{\ell=1}^{2n-3} \sum_{i+j=\ell} (j-i) a_j b_i x_2^{\ell} \right).$$

APPENDIX B.

In this part of the appendix, we provide a supplementary lemma to prove Theorem 5.3.

Lemma B.1. *Let $\kappa(k)$ as given in (28). If $\ell \in \{2, \dots, 2n-2\}$, $\ell \neq n$, then the coefficient $C_{\ell}(k)$ of x_2^{ℓ} in A_{10} is positive for any $k \in \mathbb{R}_{>0}$.*

Proof. First, we consider the case $\ell \in \{n+1, \dots, 2n-2\}$, and note that in this case

$$\begin{aligned} \mathcal{C}_\ell(k) &= \sum_{i+j=\ell-2} (j+1-i) b_i c_j + \sum_{i+j=\ell-1} (i-j) a_i c_j \\ &= \sum_{i+j=\ell-2} T_i T_j + \sum_{\substack{i+j=\ell-1 \\ i>j}} (i-j) (a_i c_j - a_j c_i), \end{aligned}$$

as $b_i = c_i = T_i$ for any $i \in \{0, \dots, n-1\}$ for $\kappa(k)$, and $\sum_{i+j=\ell-2} (j+1-i) T_i T_j = \sum_{i+j=\ell-2} T_i T_j$.

The first summand is positive since each T_i is positive. Likewise, the last summand is also positive, because for any $i, j \in \{0, \dots, n-1\}$ such that $i > j$, we find using (29):

$$(30) \quad a_i c_j - a_j c_i = K_i T_{i-1} T_j - K_j T_{j-1} T_i = \begin{cases} \frac{i-j}{(n+1)^2} & \text{if } i \in \{1, \dots, n-2\}, \\ \frac{k}{(n+1)^2} (n-j-1) & \text{if } i = n-1. \end{cases}$$

Therefore $\mathcal{C}_\ell(k) > 0$ for $\ell \in \{n+1, \dots, 2n-2\}$.

The coefficient $\mathcal{C}_\ell(k)$ for $\ell \in \{2, \dots, n-1\}$ is given by

$$\begin{aligned} \mathcal{C}_\ell(k) &= (\ell+1) a_\ell - (\ell-1) b_{\ell-1} + \sum_{i+j=\ell-2} T_i T_j + \sum_{\substack{i+j=\ell-1 \\ i>j}} (i-j) (a_i c_j - a_j c_i) \\ &= \left(-(\ell-1) b_{\ell-1} + \sum_{i+j=\ell-2} T_i T_j \right) + (\ell+1) a_\ell + \sum_{\substack{i+j=\ell-1 \\ i>j}} (i-j) (a_i c_j - a_j c_i), \end{aligned}$$

where the second equality is simply a reordering of terms. The second and third terms are positive by (30). We will show that the first term is also positive.

We point out that T_{n-1} does not appear in any sum. For $\ell = 2$, the first term is $-(\ell-1) T_{\ell-1} + T_0^2 = T_0^2 > 0$ and hence, $\mathcal{C}_2(k) > 0$. For $\ell > 2$, (29) gives $T_i T_j = \frac{(n-i)(n-j)}{(n+1)^2}$, and we obtain

$$\begin{aligned} (n+1)^2 \sum_{i+j=\ell-2} T_i T_j &= \sum_{i+j=\ell-2} (n-i)(n-j) = \sum_{i=0}^{\ell-2} (n-i)(n-\ell+2+i) \\ &= \sum_{i=0}^{\ell-2} \left((n+1) - (i+1) \right) \left((n-\ell+1) + (i+1) \right) \\ &> (\ell-1)(n-\ell+1)(n+1) = (n+1)^2 (\ell-1) b_{\ell-1}. \end{aligned}$$

This gives $\mathcal{C}_\ell(k) > 0$ and concludes the proof. \square

Acknowledgements. EF acknowledges funding from the Independent Research Fund of Denmark. TdW is supported by the Deutsche Forschungsgemeinschaft (DFG, German Research Foundation) Emmy Noether Programme, grant WO 2206/1-1. OY is funded by the Deutsche Forschungsgemeinschaft (DFG, German Research Foundation) under Germany's Excellence Strategy – The Berlin Mathematics Research Center MATH+ (EXC-2046/1, project ID 390685689, sub-project AA1-9).

REFERENCES

- [1] F. Bihan, A. Dickenstein, and Giaroli M. Lower bounds for positive roots and regions of multistationarity in chemical reaction networks. *J. Algebra*, 542:367–411, 2020.
- [2] G. Blekherman, P.A. Parrilo, and R.R. Thomas. *Semidefinite Optimization and Convex Algebraic Geometry*, volume 13 of *MOS-SIAM Series on Optimization*. SIAM and the Mathematical Optimization Society, Philadelphia, 2013.
- [3] V. Chandrasekaran, R. Murray, and A. Wiermann. Newton polytopes and relative entropy optimization, 2018. To appear in *Foundations of Computational Mathematics*; published online: 05 March 2021.
- [4] V. Chandrasekaran and P. Shah. Relative Entropy Relaxations for Signomial Optimization. *SIAM J. Optim.*, 26(2):1147–1173, 2016.

- [5] V. Chandrasekaran and P. Shah. Relative entropy relaxations for signomial optimization. *SIAM Journal on Optimization*, 26(2):1147–1173, 2016.
- [6] C. Conradi, E. Feliu, M. Mincheva, and C. Wiuf. Identifying parameter regions for multistationarity. *PLoS Comput. Biol.*, 13(10):e1005751, 2017.
- [7] C. Conradi, D. Flockerzi, J. Raisch, and J. Stelling. Subnetwork analysis reveals dynamic features of complex (bio)chemical networks. *Proc. Nat. Acad. Sci.*, 104(49):19175–80, 2007.
- [8] C. Conradi, A. Iosif, and T. Kahle. Multistationarity in the space of total concentrations for systems that admit a monomial parametrization. *Bull. Math. Biol.*, 81(10):4174–4209, 2019.
- [9] C. Conradi and M. Mincheva. Catalytic constants enable the emergence of bistability in dual phosphorylation. *J. R. S. Interface*, 11(95), 2014.
- [10] G. Craciun, J. W. Helton, and R. J. Williams. Homotopy methods for counting reaction network equilibria. *Mathematical biosciences*, 216(2):140–149, 2008.
- [11] P. Donnell, M. Banaji, A. Marginean, and C. Pantea. Control: an open source framework for the analysis of chemical reaction networks. *Bioinformatics*, 30(11), 2014.
- [12] M. Dressler, S. Iliman, and T. de Wolff. A Positivstellensatz for Sums of Nonnegative Circuit Polynomials. *SIAM J. Appl. Algebra Geom.*, 1(1):536–555, 2017.
- [13] P. Ellison, M. Feinberg, H. Ji, and D. Knight. Chemical reaction network toolbox, version 2.2. Available online at <http://www.crnt.osu.edu/CRNTwin>, 2012.
- [14] M. Feinberg. The existence and uniqueness of steady states for a class of chemical reaction networks. *Arch. Rational Mech. Anal.*, 132(4):311–370, 1995.
- [15] E. Feliu. Injectivity, multiple zeros, and multistationarity in reaction networks. *Proceedings of the Royal Society A*, doi:10.1098/rspa.2014.0530, 2014.
- [16] E. Feliu, N. Kaihnsa, T. de Wolff, and O. Yürük. The Kinetic Space of Multistationarity in Dual Phosphorylation. *J. Dyn. Diff. Equat.*, 34:825–852, 2022.
- [17] E. Feliu, A. D. Rendall, and C. Wiuf. A proof of unlimited multistability for phosphorylation cycles. *Nonlinearity*, 33(11):5629–5658, 2020.
- [18] E. Feliu and C. Wiuf. Variable elimination in chemical reaction networks with mass-action kinetics. *SIAM J. Appl. Math.*, 72:959–981, 2012.
- [19] D. Flockerzi, K. Holstein, and C. Conradi. N-site Phosphorylation Systems with $2N-1$ Steady States. *Bull. Math. Biol.*, 76(8):1892–1916, 2014.
- [20] J. Forsgård and T. de Wolff. The Algebraic Boundary of the SONC Cone. To appear in *SIAM J. Appl. Algebra Geom.*; see also [arXiv:1905.04776](https://arxiv.org/abs/1905.04776).
- [21] D. Hilbert. Ueber die Darstellung definiter Formen als Summe von Formenquadraten. *Math. Ann.*, 32(3):342–350, 1888.
- [22] S. Iliman and T. de Wolff. Amoebas, Nonnegative Polynomials and Sums of Squares Supported on Circuits. *Res. Math. Sci.*, 3(9), 2016.
- [23] S. Iliman and T. de Wolff. Lower Bounds for Polynomials with Simplex Newton Polytopes based on Geometric Programming. *SIAM J. Optim.*, 26(2):1128–1146, 2016.
- [24] M. Laurent and N. Kellershohn. Multistability: a major means of differentiation and evolution in biological systems. *Trends Biochem. Sciences*, 24(11):418–422, 1999.
- [25] T.S. Motzkin. The arithmetic-geometric inequality. In *Inequalities: Proceedings, Volume 1*, chapter 10, pages 203–224. Academic Press, 1967.
- [26] K. M. Nam, B. M. Gyori, S. V. Amethyst, D. J. Bates, and J. Gunawardena. Robustness and parameter geography in post-translational modification systems. *PLoS Comput. Biol.*, 16(5):e1007573, 05 2020.
- [27] E. M. Ozbudak, M. Thattai, H. N. Lim, B. I. Shraiman, and A. Van Oudenaarden. Multistability in the lactose utilization network of escherichia coli. *Nature*, 427(6976):737–740, 2004.
- [28] M. Pérez Millán and A. Dickenstein. The structure of MESSI biological systems. *SIAM J. Appl. Dyn. Syst.*, 17:1650–1682, 2018.
- [29] M. Pérez Millán, A. Dickenstein, A. Shiu, and C. Conradi. Chemical reaction systems with toric steady states. *Bull. Math. Biol.*, 74:1027–1065, 2012.
- [30] B. Reznick. Some concrete aspects of Hilbert’s 17th Problem. In *Real algebraic geometry and ordered structures (Baton Rouge, LA, 1996)*, volume 253 of *Contemp. Math.*, pages 251–272. Amer. Math.

- Soc., Providence, RI, 2000.
- [31] M. Sáez, E. Feliu, and C. Wiuf. Graphical criteria for positive solutions to linear systems. *Linear Algebra and its Applications*, 552:166 – 193, 2018.
 - [32] M. Thomson and J. Gunawardena. The rational parameterization theorem for multisite post-translational modification systems. *J. Theor. Biol.*, 261:626–636, 2009.
 - [33] J. Wang. Nonnegative polynomials and circuit polynomials. *SIAM J. Appl. Algebra Geom.*, 6(2):111–133, 2022.
 - [34] L. Wang and E. D. Sontag. On the number of steady states in a multiple futile cycle. *J. Math. Biol.*, 57(1):29–52, 2008.
 - [35] C. Wiuf and E. Feliu. Power-law kinetics and determinant criteria for the preclusion of multistationarity in networks of interacting species. *SIAM J. Appl. Dyn. Syst.*, 12:1685–1721, 2013.
 - [36] W. Xiong and J. E. Ferrell Jr. A positive-feedback-based bistable 'memory module' that governs a cell fate decision. *Nature*, 426(6965):460–465, 2003.
 - [37] O. Yürük. *On the Maximal Mediated Set Structure and the Applications of Nonnegative Circuit Polynomials*. PhD thesis, TU Braunschweig, 2021.